

(19)



(11)

EP 2 624 243 B1

(12)

EUROPEAN PATENT SPECIFICATION

(45) Date of publication and mention
of the grant of the patent:
01.05.2019 Bulletin 2019/18

(51) Int Cl.:
G09G 3/20 (2006.01) G09G 3/32 (2016.01)

(21) Application number: **13153887.8**

(22) Date of filing: **04.02.2013**

(54) Driving system for active-matrix displays

Antriebssystem für Aktivmatrixanzeigen

Système de commande pour affichages à matrice active

(84) Designated Contracting States:
**AL AT BE BG CH CY CZ DE DK EE ES FI FR GB
GR HR HU IE IS IT LI LT LU LV MC MK MT NL NO
PL PT RO RS SE SI SK SM TR**

(30) Priority: **03.02.2012 US 201213365391**

(43) Date of publication of application:
07.08.2013 Bulletin 2013/32

(73) Proprietor: **Ignis Innovation Inc.
Waterloo, Ontario N2V 2C5 (CA)**

(72) Inventors:
• **Li, Kongning
Toronto, Ontario M3B 1L6 (CA)**

- **Gupta, Vasudha
Cupertino, CA 95014 (US)**
- **Chaji, Gholamreza
Waterloo, Ontario N2V 2S3 (CA)**
- **Nathan, Arokia
Cambridge CB4 3PL (GB)**

(74) Representative: **Grünecker Patent- und
Rechtsanwälte
PartG mbB
Leopoldstraße 4
80802 München (DE)**

(56) References cited:
**EP-A1- 2 299 427 US-A1- 2008 284 768
US-A1- 2009 002 281**

EP 2 624 243 B1

Note: Within nine months of the publication of the mention of the grant of the European patent in the European Patent Bulletin, any person may give notice to the European Patent Office of opposition to that patent, in accordance with the Implementing Regulations. Notice of opposition shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

Description**FIELD OF INVENTION**

5 **[0001]** The present invention relates to display technology, and particularly to driving systems for active-matrix displays such as AMOLED displays.

BACKGROUND OF THE INVENTION

10 **[0002]** A display device having a plurality of pixels (or sub-pixels) arranged in a matrix has been widely used in various applications. Such a display device includes a panel having the pixels and peripheral circuits for controlling the panels. Typically, the pixels are defined by the intersections of scan lines and data lines, and the peripheral circuits include a gate driver for scanning the scan lines and a source driver for supplying image data to the data lines. The source driver may include a gamma correction circuit for controlling the gray scale of each pixel. In order to display a frame, the source driver and the gate driver respectively provide a data signal and a scan signal to the corresponding data line and the corresponding scan line. As a result, each pixel will display a predetermined brightness and color.

15 **[0003]** In recent years, the matrix display using organic light emitting devices (OLED) has been widely employed in small electronic devices, such as handheld devices, cellular phones, personal digital assistants (PDAs), and cameras because of the generally lower power consumed by such devices. However, the quality of output in an OLED based pixel is affected by the properties of a drive transistor that is typically fabricated from amorphous or poly silicon as well as the OLED itself. In particular, threshold voltage and mobility of the transistor tend to change as the pixel ages. Moreover, the performance of the drive transistor may be effected by temperature. In order to maintain image quality, these parameters must be compensated for by adjusting the programming voltage to pixels. Compensation via changing the programming voltage is more effective when a higher level of programming voltage and therefore higher luminance is produced by the OLED based pixels. However, luminance levels are largely dictated by the level of brightness for the image data to a pixel, and the desired higher levels of luminance for more effective compensation may not be achievable while within the parameters of the image data.

20 **[0004]** Document EP 2 299 427 A1 describes a system for using raw grayscale image data, representing images to be displayed in successive frames. The system defines high and low ranges of raw grayscale image data, and determines whether the raw grayscale image data for each pixel falls within the high range or the low range. Raw grayscale image data that falls within the low range is converted to higher grayscale values, and the pixels are driven with currents corresponding to the higher grayscale values during time periods that are shorter than complete frame time periods. Raw grayscale image data that falls within the high range is converted to higher grayscale values, and the pixels are driven with currents corresponding to the higher grayscale values during time periods that are shorter than complete frame time periods and different from the time periods of the low range image data. When the raw grayscale image data is adjusted according to a preselected gamma curve before using that data to drive the pixels, the high and low ranges may be selected according to how well the gamma curve corrects the raw grayscale image data within the ranges.

30 **[0005]** Document US 2009/0002281 A1 relates to an active matrix organic electroluminescence display and its gradation control method. The active matrix organic electroluminescence (EL) display comprises plural selection and data lines mutually crossed, and a pixel circuit connected to the selection and data lines and having switching devices, a storage capacitor and an organic EL device. In a part of a period that the pixel circuit connected to the selection line is being selected, an applied first data signal is held as a voltage at the storage capacitor of the selected pixel circuit. After the selection signal applying, a first current according to the held voltage is supplied to the organic EL device, which emits light at luminance according to the first current. In another part of the period, a second current according to an applied second data signal is supplied to the organic EL device of the selected pixel circuit, and this emits light at luminance according to the second current.

40 **[0006]** Document US 2008/0284768 A1 relates to a method for driving liquid crystal display devices. A method in which one frame is divided into a plurality of subframes, and some of the plurality of subframes are used mainly for displaying images (bright images) and the others are used mainly for reducing afterimages of moving images (dark images) is described. In this example, graphs showing a relation between integrated luminance and a gray scale level in 1SF, a relation between integrated luminance and a gray scale level in 2SF, and a relation between integrated luminance and a gray scale level of the sum of 1SF and 2SF are employed.

SUMMARY

55 **[0007]** An object of the present invention is to provide a method and an apparatus of using raw grayscale values, representing images to be displayed in successive frames, that obviate or mitigate at least one of the disadvantages of existing systems. This object is solved by the present invention as claimed in the independent claims. Advantageous

embodiments of the present invention are defined by the dependent claims.

[0008] According to one implementation, illustrative example for understanding the present invention raw grayscale image data, representing images to be displayed in successive frames, is used to drive a display having pixels that include a drive transistor and an organic light emitting device by (1) dividing each frame into at least first and second-frames, and (2) supplying each pixel with a drive current that is (a) higher in the first sub-frame than in the second sub-frame for raw grayscale values in a first preselected range, and (b) higher in the second sub-frame than in the first sub-frame for raw grayscale values in a second preselected range. The display may be an active matrix display, and is preferably an AMOLED display.

[0009] In one implementation, the raw grayscale value for each frame is converted to first and second sub-frame grayscale values for the first and second sub-frames, and the drive current supplied to the pixel during the first and second sub-frames is based on the first and second sub-frame grayscale values. The first and second sub-frame grayscale values may be preselected to produce a pixel luminance during that frame that has a predetermined gamma relationship (e.g., a gamma 2.2 curve) to the raw grayscale value for that frame.

BRIEF DESCRIPTION OF THE DRAWINGS

[0010] The foregoing and other advantages of the invention will become apparent upon reading the following detailed description and upon reference to the drawings.

FIG. 1 is a block diagram of an AMOLED display system.

FIG. 2 is a block diagram of a pixel driver circuit for the AMOLED display in FIG. 1.

FIG. 3 is a block diagram similar to FIG. 1 but showing the source driver in more detail.

FIG. 4A-4B are timing diagrams illustrating the time period of one complete frame and two sub-frame time periods within the complete frame time period.

FIG. 5A-5D is a series of diagrammatic illustrations of the luminance produced by one pixel within the time periods of FIG. 4 in two different driving modes and when driven by two different grayscale values.

FIG. 6 is a graph illustrating two different gamma curves, for use in two different driving modes, for different grayscale values.

FIG. 7 is an illustration of exemplary values used to map grayscale data falling within a preselected low range to higher grayscale values.

FIG. 8 is a diagrammatic illustration of the data used to drive any given pixel in the two sub-frame time periods illustrated in FIG. 4, when the raw grayscale image data is in either of two different ranges.

FIG. 9 is a flow chart of a process executed by the source driver to convert raw grayscale image data that falls within a low range, to higher grayscale values.

FIG. 10 is a flow chart of a process executed by the source driver to supply drive data to the pixels in either of two different operating modes.

FIG. 11 is a flow chart of the same process illustrated in FIG. 10 with the addition of smoothing functions.

FIG. 12 is a diagram illustrating the use of multiple lookup tables in the processing circuit in the source driver.

FIG. 13 is a timing diagram of the programming signals sent to each row during a frame interval in the hybrid driving mode of the AMOLED display in FIG. 1.

FIG. 14A is a timing diagram for row and column drive signals showing programming and non-programming times for the hybrid drive mode using a single pulse.

FIG. 14B is a timing diagram is a timing diagram for row and column drive signals showing programming and non-programming times for the hybrid drive mode using a double pulse.

FIG. 15 is a diagram illustrating the use of multiple lookup tables and multiple gamma curves.

FIG. 16A is a luminance level graph of the AMOLED display in FIG. 1 for automatic brightness control without hysteresis.

FIG. 16B is a luminance level graph of the AMOLED display in FIG. 1 for automatic brightness control with hysteresis.

FIGs. 17A-17E are diagrammatic illustrations of an embodiment of the driving scheme of the present invention.

FIG. 18 is a plot of raw input grayscale values vs. converted grayscale values for two different sub-frames, in a further modified driving scheme.

DETAILED DESCRIPTION

[0011] While the invention is susceptible to various modifications and alternative forms, specific embodiments have been shown by way of example in the drawings and will be described in detail herein. It should be understood, however, that the invention is not intended to be limited to the particular forms disclosed. Rather, the invention is to cover all modifications, equivalents, and alternatives falling within the scope of an the appended claims.

[0012] FIG. 1 is an electronic display system 100 having an active matrix area or pixel array 102 in which an array of pixels 104 are arranged in a row and column configuration. For ease of illustration, only three rows and columns are shown. External to the active matrix area of the pixel array 102 is a peripheral area 106 where peripheral circuitry for driving and controlling the pixel array 102 are disposed. The peripheral circuitry includes a gate or address driver circuit 108, a source or data driver circuit 110, a controller 112, and a supply voltage (e.g., Vdd) driver 114. The controller 112 controls the gate, source, and supply voltage drivers 108, 110, 114. The gate driver 108, under control of the controller 112, operates on address or select lines SEL[i], SEL[i+1], and so forth, one for each row of pixels 104 in the pixel array 102. A video source 120 feeds processed video data into the controller 112 for display on the display system 100. The video source 120 represents any video output from devices using the display system 100 such as a computer, cell phone, PDA and the like. The controller 112 converts the processed video data to the appropriate voltage programming information to the pixels 104 on the display system 100.

[0013] In pixel sharing configurations described below, the gate or address driver circuit 108 can also optionally operate on global select lines GSEL[j] and optionally /GSEL[j], which operate on multiple rows of pixels 104 in the pixel array 102, such as every three rows of pixels 104. The source driver circuit 110, under control of the controller 112, operates on voltage data lines Vdata[k], Vdata[k+1], and so forth, one for each column of pixels 104 in the pixel array 102. The voltage data lines carry voltage programming information to each pixel 104 indicative of a brightness (gray level) of each light emitting device in the pixel 104. A storage element, such as a capacitor, in each pixel 104 stores the voltage programming information until an emission or driving cycle turns on the light emitting device. The supply voltage driver 114, under control of the controller 112, controls the level of voltage on a supply voltage (EL_Vdd) line, one for each row of pixels 104 in the pixel array 102. Alternatively, the voltage driver 114 may individually control the level of supply voltage for each row of pixels 104 in the pixel array 102 or each column of pixels 104 in the pixel array 102.

[0014] As is known, each pixel 104 in the display system 100 needs to be programmed with information indicating the brightness (gray level) of the organic light emitting device (OLED) in the pixel 104 for a particular frame. A frame defines the time period that includes a programming cycle or phase during which each and every pixel in the display system 100 is programmed with a programming voltage indicative of a brightness and a driving or emission cycle or phase during which each light emitting device in each pixel is turned on to emit light at a brightness commensurate with the programming voltage stored in a storage element. A frame is thus one of many still images that compose a complete moving picture displayed on the display system 100. There are at least two schemes for programming and driving the pixels: row-by-row, or frame-by-frame. In row-by-row programming, a row of pixels is programmed and then driven before the next row of pixels is programmed and driven. In frame-by-frame programming, all rows of pixels in the display system 100 are programmed first, and all of the pixels are driven row-by-row. Either scheme can employ a brief vertical blanking time at the beginning or end of each frame during which the pixels are neither programmed nor driven.

[0015] The components located outside of the pixel array 102 can be disposed in a peripheral area 106 around the pixel array 102 on the same physical substrate on which the pixel array 102 is disposed. These components include the gate driver 108, the source driver 110 and the supply voltage controller 114. Alternatively, some of the components in the peripheral area can be disposed on the same substrate as the pixel array 102 while other components are disposed on a different substrate, or all of the components in the peripheral area can be disposed on a substrate different from the substrate on which the pixel array 102 is disposed. Together, the gate driver 108, the source driver 110, and the supply voltage control 114 make up a display driver circuit. The display driver circuit in some configurations can include the gate driver 108 and the source driver 110 but not the supply voltage controller 114.

[0016] The controller 112 includes internal memory (not shown) for various look up tables and other data for functions such as compensation for effects such as temperature, change in threshold voltage, change in mobility, etc. Unlike a convention AMOLED, the display system 100 allows the use of higher luminance of the pixels 104 during one part of the frame period while emitting not light in the other part of the frame period. The higher luminance during a limited time of the frame period results in the required brightness from the pixel for a frame but higher levels of luminance facilitate the compensation for changing parameters of the drive transistor performed by the controller 112. The system 100 also includes a light sensor 130 that is coupled to the controller 112. The light sensor 130 may be a single sensor located in proximity to the array 102 as in this example. Alternatively, the light sensor 130 may be multiple sensors such as one in each corner of the pixel array 102. Also, the light sensor 130 or multiple sensors may be embedded in the same substrate as the array 102, or have its own substrate on the array 102. As will be explained, the light sensor 130 allows adjustment of the overall brightness of the display system 100 according to ambient light conditions.

[0017] FIG. 2 is a circuit diagram of a simple individual driver circuit 200 for a pixel such as the pixel 104 in FIG. 1. As explained above, each pixel 104 in the pixel array 102 in FIG. 1 is driven by the driver circuit 200 in FIG. 2. The driver circuit 200 includes a drive transistor 202 coupled to an organic light emitting device (OLED) 204. In this example, the organic light emitting device 204 is fabricated from a luminous organic material which is activated by current flow and whose brightness is a function of the magnitude of the current. A supply voltage input 206 is coupled to the drain of the drive transistor 202. The supply voltage input 206 in conjunction with the drive transistor 202 creates current in the light emitting device 204. The current level may be controlled via a programming voltage input 208 coupled to the gate of the

drive transistor 202. The programming voltage input 208 is therefore coupled to the source driver 110 in FIG. 1. In this example, the drive transistor 202 is a thin film transistor fabricated from hydrogenated amorphous silicon. Other circuit components (not shown) such as capacitors and transistors may be added to the simple driver circuit 200 to allow the pixel to operate with various enable, select and control signals such as those input by the gate driver 108 in FIG. 1. Such components are used for faster programming of the pixels, holding the programming of the pixel during different frames, and other functions.

[0018] Referring to FIG. 3, there is illustrated the source driver 110 that supplies a data line voltage to a data line DL to program the selected pixels coupled to the data line DL. The controller 112 provides raw grayscale image data, at least one operation timing signal and a mode signal (hybrid or normal driving mode) to the source driver 110. Each of the gate driver 108 and the source driver 110 or a combination may be built from a one-chip semiconductor integrated circuit (IC) chip.

[0019] The source driver 110 includes a timing interface (I/F) 342, a data interface (I/F) 324, a gamma correction circuit 340, a processing circuit 330, a memory 320 and a digital-to-analog converter (DAC) 322. The memory 320 is, for example, a graphic random access memory (GRAM) for storing grayscale image data. The DAC 322 includes a decoder for converting grayscale image data read from the GRAM 320 to a voltage corresponding to the luminance at which it is desired to have the pixels emit light. The DAC 322 may be a CMOS digital-to-analog converter.

[0020] The source driver 110 receives raw grayscale image data via the data I/F 324, and a selector switch 326 determines whether the data is supplied directly to the GRAM 320, referred to as the normal mode, or to the processing circuit 330, referred to as the hybrid mode. The data supplied to the processing circuit 330 is converted from the typical 8-bit raw data to 9-bit hybrid data, e.g., by use of a hybrid Look-Up-Table (LUT) 332 stored in permanent memory which may be part of the processing circuit 330 or in a separate memory device such as ROM, EPROM, EEPROM, flash memory, etc. The extra bit indicates whether each grayscale number is located in a predetermined low grayscale range LG or a predetermined high grayscale HG.

[0021] The GRAM 320 supplies the DAC 322 with the raw 8-bit data in the normal driving mode and with the converted 9-bit data in the hybrid driving mode. The gamma correction circuit 340 supplies the DAC 322 with signals that indicate the desired gamma corrections to be executed by the DAC 322 as it converts the digital signals from the GRAM 320 to analog signals for the data lines DL. DACs that execute gamma corrections are well known in the display industry.

[0022] The operation of the source driver 110 is controlled by one or more timing signals supplied to the gamma correction circuit 340 from the controller 112 through the timing I/F 342. For example, the source driver 110 may be controlled to produce the same luminance according to the grayscale image data during an entire frame time T in the normal driving mode, and to produce different luminance levels during sub-frame time periods T1 and T2 in the hybrid driving mode to produce the same net luminance as in the normal driving mode.

[0023] In the hybrid driving mode, the processing circuit 330 converts or "maps" the raw grayscale data that is within a predetermined low grayscale range LG to a higher grayscale value so that pixels driven by data originating in either range are appropriately compensated to produce a uniform display during the frame time T. This compensation increases the luminance of pixels driven by data originating from raw grayscale image data in the low range LG, but the drive time of those pixels is reduced so that the average luminance of such pixels over the entire frame time T is at the desired level. Specifically, when the raw grayscale value is in a preselected high grayscale range HG, the pixel is driven to emit light during a major portion of the complete frame time period T, such as the portion $\frac{3}{4}T$ depicted in FIG. 5(c). When the raw grayscale value is in the low range LG, the pixel is driven to emit light during a minor portion of the complete frame time period T, such as the portion $\frac{1}{4}T$ depicted in FIG. 5(d), to reduce the frame time during which the increased voltage is applied.

[0024] FIG. 6 illustrates an example in which raw grayscale values in a low range LG of 1-99 are mapped to corresponding values in a higher range of 102-245. In the hybrid driving mode, one frame is divided into two sub-frame time periods T1 and T2. The duration of one full frame is T, the duration of one sub-frame time period is $T1 = \alpha T$, and the duration of the other sub-frame time period is $T2 = (1-\alpha)T$, so $T = T1 + T2$. In the example in FIG. 5, $\alpha = 3/4$, and thus $T1 = (3/4)T$, and $T2 = (1/4)T$. The value of α is not limited to $3/4$ and may vary. As described below, raw grayscale data located in the low grayscale LG is transformed to high grayscale data for use in period T2. The operation timing of the sub-frame periods may be controlled by timing control signals supplied to the timing I/F 342. It is to be understood that more than two sub-frame time periods could be used by having different numbers of ranges of grayscales with different time periods assigned to each range.

[0025] In the example depicted in FIG. 5(a), L1 represents the average luminance produced during a frame period T for raw grayscale data located in the high grayscale range HG, when the normal drive mode is selected. In FIG. 5(b), L3 represents the average luminance produced during a frame period T for raw grayscale data located in the low grayscale range LG, in the normal drive mode. In FIG. 5(c), L2 represents the average luminance for raw grayscale data located in the high grayscale range HG, during the sub-frame period T1 when the hybrid drive mode is selected. In FIG. 5(d), L4 represents the average luminance for raw grayscale data located in the low grayscale range LG, during the sub-frame period T2 when the hybrid drive mode is selected. The average luminances produced over the entire frame period

T by the sub-frame luminances depicted in FIGs. 5(c) and 5(d) are the same as those depicted in FIGs. 5 (a) and 5(b), respectively, because $L2 = 4/3L1$ and $L4 = 4L3$.

[0026] If the raw grayscale image data is located in the low grayscale range LG, the source driver 110 supplies the data line DL with a data line voltage corresponding to the black level ("0") in the sub-frame period T2. If the raw grayscale data is located in the high grayscale range HD, the source driver 110 supplies the data line DL with a data line voltage corresponding to the black level ("0") in the sub-frame period T1.

[0027] FIG. 6 illustrates the gamma corrections executed by the DAC 322 in response to the control signals supplied to the DAC 322 by the gamma correction circuit 340. The source driver 110 uses a first gamma curve 4 for gamma correction in the hybrid driving mode, and a second gamma curve 6 for gamma correction in the normal driving mode. In the hybrid driving mode, values in the low range LG are converted to higher grayscale values, and then both those converted values and the raw grayscale values that fall within the high range HG are gamma-corrected according to the same gamma curve 4. The gamma-corrected values are output from the DAC 322 to the data lines DL and used as the drive signals for the pixels 104, with the gamma-corrected high-range values driving their pixels in the first sub-frame time period T1, and the converted and gamma-corrected low-range values driving their pixels in the second sub-frame time period T2.

[0028] In the normal driving mode, all the raw grayscale values are gamma-corrected according to a second gamma curve 6. It can be seen from FIG. 6 that the gamma curve 4 used in the hybrid driving mode yields higher gamma-corrected values than the curve 6 used in the normal driving mode. The higher values produced in the hybrid driving mode compensate for the shorter driving times during the sub-frame periods T1 and T2 used in that mode.

[0029] The display system 100 divides the grayscales into a low grayscale range LG and a high grayscale range HG. Specifically, if the raw grayscale value of a pixel is greater than or equal to a reference value D(ref), that data is considered as the high grayscale range HG. If the raw grayscale value is smaller than the reference value D(ref), that data is considered as the low grayscale range LG.

[0030] In the example illustrated in FIG. 6, the reference value D(ref) is set to 100. The grayscale transformation is implemented by using the hybrid LUT 132 of FIG. 1, as illustrated in FIGs. 6 and 7. One example of the hybrid LUT 132 is shown in FIG. 7 where the grayscale values 1-99 in the low grayscale range LG are mapped to the grayscale values 102-245 in the high grayscale range HG.

[0031] Assuming that raw grayscale data from the controller 112 is 8-bit data, 8-bit grayscale data is provided for each color (e.g., R, G, B etc) and is used to drive the sub-pixels having those colors. The GRAM 320 stores the data in 9-bit words for the 8-bit grayscale data plus the extra bit added to indicate whether the 8-bit value is in the low or high grayscale range.

[0032] In the flow chart of FIG. 9, data in the GRAM 320 is depicted as the nine bit word GRAM[8:0], with the bit GRAM[8] indicating whether the grayscale data is located in the high grayscale range HG or the low grayscale range LG. In the hybrid driving mode, all the input data from the data I/F 124 is divided into two kinds of 8-bit grayscale data, as follows:

1. If the raw input data is in the 8 bits of high grayscale range, local data D[8] is set to be "1" (D[8]=1), and the 8 bits of the local data D[7:0] is the raw grayscale data. The local data D[8:0] is saved as GRAM[8:0] in GRAM 320 where GRAM[8]=1.
2. If the raw input data is in the low grayscale LG, local data D[8] is set to be "0" (D[8]=0), and local data D[7:0] is obtained from the hybrid LUT 332. The local data D[8:0] is saved as GRAM[8:0] in GRAM 320

[0033] FIG. 9 is a flow chart of one example of an operation for storing 8-bit grayscale data into the GRAM 320 as a 9-bit GRAM data word. The operation is implemented in the processing circuit 330 in the source driver 110. Raw grayscale data is input from the data I/F 124 at step 520, providing 8-bit data at step 522. The processing circuit 330 determines the system mode, i.e., normal driving mode or hybrid driving mode, at step 524. If the system mode is the hybrid driving mode, the system uses the 256*9 bit LUT 132 at step 528 to provide 9-bit data D_R[8:0] at step 530, including the one-bit range indicator. This data is stored in the GRAM 320 at step 532. If the system mode is the normal driving mode, the system uses the raw 8-bit input data D_N[7:0] at step 534, and stores the data in the GRAM 320 at step 532.

[0034] FIG. 10 is a flow chart of one example of an operation for reading 9-bit GRAM data words and providing that data to the DAC 322. The system (e.g., the processing circuit 330) determines whether the current system mode is the normal driving mode or the hybrid driving mode at step 540. If the current mode is the hybrid driving mode, the system determines whether it is currently in a programming time at step 542. If the answer at step 542 is negative, step 544 determines whether GRAM [8] = 1, which indicates the raw grayscale value was in the low range LG. If the answer at step 544 is negative, indicating that the raw grayscale value is in the high range HG, GRAM [7:0] is provided as local data D[7:0] and the values of the appropriate LUT 132 are used at step 546 to provide the data D [7:0] to the DAC 322 at step 548. If the answer at step 544 is affirmative, Black (VSL) ("00") is provided to the DAC 322 at step 552, so that black level voltage is output from the DAC 122 (see FIG. 8).

[0035] In the programming period, step 550 determines whether $\text{GRAM}[8] = 1$. If the answer at step 550 is affirmative indicating the raw grayscale value is in the high range HG, the system advances to steps 546 and 548. If the answer at step 550 is negative indicating the raw grayscale value is in the low range LG, the system advances to step 552 to output a black-level voltage (see FIG. 8).

[0036] FIG. 11 is a flow chart of another example of an operation for reading 9-bit GRAM data and providing that data to the DAC 322. To avoid contorting effects during the transaction, the routine of FIG. 11 uses a smoothing function for a different part of a frame. The smoothing function can be, but is not limited to, offset, shift or partial inversion. In FIG. 11, the step 552 of FIG. 10 is replaced with steps 560 and 562. When the system is not in a programming period, if $\text{GRAM}[8] = 1$ (high range HG grayscale value), $\text{GRAM}[7:0]$ is processed by the smoothing function f and then provided to the DAC 322 at step 560. In the programming period, if $\text{GRAM}[8] \neq 1$ (low range LG grayscale value), $\text{GRAM}[7:0]$ is processed by the smoothing function f and then provided to the DAC 322 at step 562.

[0037] Although only one hybrid LUT 332 is illustrated in FIG. 3, more than one hybrid LUT may be used, as illustrated in FIG. 12. In FIG. 12, a plurality of hybrid LUTs 332 (1) ... 332 (m) receive data from, and have outputs coupled to, a multiplexer 350. Different ranges of grayscale values can be converted in different hybrid LUTs.

[0038] FIG. 13 is a timing diagram of the programming signals sent to each row during a frame interval in the hybrid driving mode of the AMOLED display in FIG. 1 and FIG. 3. Each frame is assigned a time interval such as the time intervals 600, 602, and 604, which is sufficient to program each row in the display. In this example, the display has 480 rows. Each of the 480 rows include pixels for corresponding image data that may be in the low grayscale value range or the high grayscale value range. In this example, each of the time intervals 600, 602, and 604 represents 60 frames per second or a frequency of 60 Hz. Of course other higher and lower frequencies and different numbers of rows may be used with the hybrid driving mode.

[0039] The timing diagram in FIG. 13 includes control signals necessary to avoid a tearing effect where programming data for the high and low grayscale values may overlap. The control signals include a tearing signal line 610, a data write signal line 612, a memory out low value (R) signal line 614 and a memory out high value (P) signal line 616. The hybrid driving mode is initiated for each frame by enabling the tearing signal line 610. The data write signal line 612 receives the row programming data 620 for each of the rows in the display system 100. The programming data 620 is processed using the LUTs as described above to convert the data to analog values reflecting higher luminance values for shortened intervals for each of the pixels in each row. During this time, a blanking interval 622 and a blanking interval 630 represent no output through the memory write lines 614 and 616 respectively.

[0040] Once the tearing signal line 610 is set low, a row programming data block 624 is output from the memory out low value line 614. The row programming data block 624 includes programming data for all pixels in each row in succession beginning with row 1. The row programming data block 624 includes only data for the pixels in the selected row that are to be driven at values in the low grayscale range. As explained above, all pixels that are to be driven at values in the high grayscale range in a selected row are set to zero voltage or adjusted for distortions. Thus, as each row is strobed, the DAC 322 converts the low gray scale range data (for pixels programmed in the low grayscale range) and sends the programming signals to the pixels (LUT modified data for the low grayscale range pixels and a zero voltage or distortion adjustment for the high grayscale range pixels) in that row.

[0041] While the row programming data block 624 is output, the memory output high value signal line 616 remains inactive for a delay period 632. After the delay period 632, a row programming data block 634 is output from the memory out high value line 616. The row programming data block 634 includes programming data for all pixels in each row in succession beginning with row 1. The row programming data block 634 includes only data for the pixels that are to be driven at values in the high grayscale range in the selected row. As explained above, all pixels that are to be driven at values in the low grayscale range in the selected row are set to zero voltage. The DAC 322 converts the high gray scale range data (for pixels programmed in the high grayscale range) and sends the programming signals to the pixels (LUT modified data for the high grayscale range pixels and a zero voltage for the low grayscale range pixels) in that row.

[0042] In this example, the delay period 632 is set to $1F + x/3$ where F is the time it takes to program all 480 rows and x is the time of the blanking intervals 622 and 630. The x variable may be defined by the manufacturer based on the speed of the components such as the processing circuit 330 necessary to eliminate tearing. Therefore, x may be lower for faster processing components. The delay period 632 between programming pixels emitting a level in the low grayscale range and those pixels emitting a level in the high grayscale range avoids the tearing effect.

[0043] FIG. 14A is a timing diagram for row and column drive signals showing programming and non-programming times for the hybrid drive mode using a single pulse for the AMOLED display in FIG. 1. The diagram in FIG. 14A includes a tearing signal 640, a set of programming voltage select signals 642, a gate clock signal 644, and row strobe signals 646a-646h. The tearing signal 640 is strobed low to initiate the hybrid drive mode for a particular video frame. The programming voltage select signals 642 allow the selection of all of the pixels in a particular row for receiving programming voltages from the DAC 322 in FIG. 3. In this example, there are 960 pixels in each row. The programming voltage select signals 642 initially are selected to send a set of low grayscale range programming voltages 650 to the pixels of the first row.

[0044] When the gate clock signal 644 is set high, the strobe signal 646a for the first row produces a pulse 652 to

select the row. The low gray scale pixels in that row are then driven by the programming voltages from the DAC 322 while the high grayscale pixels are driven to zero voltage. After a sub-frame time period, the programming voltage select signals 642 are selected to send a set of high grayscale range programming voltages 654 to the first row. When the gate clock signal 644 is set high, the strobe signal 646a for the first row produces a second pulse 656 to select the row. The high grayscale pixels in that row are then driven by the programming voltages from the DAC 322 while the low grayscale pixels are driven to zero voltage.

[0045] As is shown by FIG. 14A, this process is repeated for each of the rows via the row strobe signals 646b-646g. Each row is therefore strobed twice, once for programming the low grayscale pixels and once for programming the high grayscale values. When the first row is strobed the second time 656 for programming the high grayscale values, the first strobes for subsequent rows such as strobes 646c, 646d are initiated until the last row strobe (row 481) shown as strobe 646e. The subsequent rows then are strobed a second time in sequence as shown by the programming voltages 656 on the strobes 646f, 646g, 646h until the last row strobe (row 481) shown as strobe 646e.

[0046] FIG. 14B is a timing diagram for row and column drive signals showing programming and non-programming times for the hybrid drive mode using a double pulse. The double pulse to the drive circuit of the next row leaves the leakage path on for the drive transistor and helps improve compensation for the drive transistors. Similar to FIG. 14A, the diagram in FIG. 14B includes a tearing signal 680, a set of programming voltage select signals 682, a gate clock signal 684, and row strobe signals 686a-686h. The tearing signal 680 is strobed low to initiate the hybrid drive mode for a particular video frame. The programming voltage select signals 682 allow the selection of all of the pixels in a particular row for receiving programming voltages from the DAC 322 in FIG. 3. In this example, there are 960 pixels in each row. The programming voltage select signals 682 initially are selected to send a set of low grayscale range programming voltages 690 to the first row. When the gate clock signal 684 is set high, the strobe signal 686a for the first row produces a pulse 692 to select the row. The low gray scale pixels in that row are then driven by the programming voltages from the DAC 322 while the high grayscale pixels are driven to zero voltage. After a sub-frame time period, the programming voltage select signals 682 are selected to send a set of high grayscale range programming voltages 694 to the first row. When the gate clock signal 684 is set high, the strobe signal 686a for the first row produces a second pulse 696 to select the row. The high grayscale pixels in that row are then driven by the programming voltages from the DAC 322 while the low grayscale pixels are driven to zero voltage.

[0047] As is shown by FIG. 14B, this process is repeated for each of the rows via the row strobe signals 686b-686h. Each row is therefore strobed once for programming the low grayscale pixels and once for programming the high grayscale values. Each row is also strobed simultaneously with the previous row, such as the high strobe pulses 692 on the row strobe line 686a and 686b, in order to leave the leakage path on for the drive transistor. A dummy line that is strobed for the purpose of leaving the leakage path on for the drive transistor for the last active row (row 481) shown as strobe 646e in the display.

[0048] FIG. 15 illustrates a system implementation for accommodating multiple gamma curves for different applications and automatic brightness control, using the hybrid driving scheme. The automatic brightness control is a feature where the controller 112 adjusts the overall luminance level of the display system 100 according to the level of ambient light detected by the light sensor 130 in FIG. 1. In this example, the display system 100 may have four levels of brightness: bright, normal, dim and dimmest. Of course any number of levels of brightness may be used.

[0049] In FIG. 15, a different set of voltages from LUTs 700 (#1-#n) is provided to a plurality of DAC decoders 322a in the source driver 110. The set of voltages is used to change the display peak brightness using the different sets of voltages 700. Multiple gamma LUTs 702 (#1-#m) are provided so that the DACs 322a can also change the voltages from the hybrid LUTs 700 to obtain a more solid gamma curve despite changing the peak brightness.

[0050] In this example, there are 18 conditions with 18 corresponding gamma curve LUTs stored in a memory of the gamma correction circuit 340 in FIG. 3. There are six gamma conditions (gamma 2.2 bright, gamma 2.2 normal, gamma 2.2 dim, gamma 1.0, gamma 1.8 and gamma 2.5) for each color (red, green and blue). Three gamma conditions, gamma 2.2 bright, gamma 2.2 normal and gamma 2.2 dim, are used according to the brightness level. In this example, the dim and dimmest brightness levels both use the gamma 2.2 dim condition. The other gamma conditions are used for application specific requirements. Each of the six gamma conditions for each color has its own gamma curve LUT 702 in FIG. 13 which is accessed depending on the specific color pixel and the required gamma condition in accordance with the brightness control.

[0051] FIGs. 16A and 16B are graphs of two modes of the brightness control that may be implemented by the controller 112. FIG. 16A shows the brightness control without hysteresis. The y-axis of the graph 720 shows the four levels of overall luminance of the display system 100. The luminance levels include a bright level 722, a normal level 724, a dim level 726 and a dimmest level 728. The x-axis of the graph 720 represents the output of the light sensor 130. Thus, as the output of the light sensor 130 in FIG. 1 increases past certain threshold levels, indicating greater levels of ambient light, the luminance of the display system 100 is increased. The x-axis shows a low level 730, a middle level 732 and a high level 734. When the detected output from the light sensor crosses one of the levels 730, 732 or 734, the luminance level is adjusted downward or upward to the next level using the LUTs 700 in FIG. 15. For example, when the ambient

light detected exceeds the middle level 732, the luminance of the display is adjusted up to the normal level 724. If ambient light is reduced below the low level 730, the luminance of the display is adjusted down to the dimmest level 728.

[0052] FIG. 16B is a graph 750 showing the brightness control of the display system 100 in hysteresis mode. In order to allow smoother transitions to the eye, the brightness levels are sustained for a longer period when transitions are made between luminance levels. Similar to FIG. 16A, the y-axis of the graph 750 shows the four levels of overall luminance of the display system 100. The levels include a bright level 752, a normal level 754, a dim level 756 and a dimmest level 758. The x-axis of the graph 750 represents the output of the light sensor 130. Thus, as the output increases past certain threshold levels, indicating greater levels of ambient light, the luminance of the display system 100 is increased. The x-axis shows a low base level 760, a middle base level 762 and a high level 764. Each level 760, 762 and 764 includes a corresponding increase threshold level 770, 772 and 774 and a corresponding decrease threshold level 780, 782 and 784. Increases in luminance require greater ambient light than the base levels 760, 762 and 764. For example, when the detected ambient light exceeds an increase threshold level such as the threshold level 770, the luminance of the display is adjusted up to the dim level 756. Decreases in luminance require less ambient light than the base levels 760, 762 and 764. For example, if ambient light is reduced below the decrease threshold level 794, the luminance of the display is adjusted down to the normal level 754.

[0053] In an embodiment of the invention illustrated in FIGs. 17A-17E, the raw input grayscale values are converted to two different sub-frame grayscale values for two different sub-frames SF1 and SF2 of each frame F, so that the current levels are controlled to both enhance compensation and add relaxation intervals to extend the lifetime of the display. In the example in FIGs. 17A-17E, the duration of the first sub-frame SF1 is $\frac{1}{4}$ of the total frame time F, and the duration of the second sub-frame SF2 is the remaining $\frac{3}{4}$ of the total frame time F.

[0054] As depicted in FIG. 17A, as the value of the raw input grayscale values can range from zero to 255. As the input grayscale values increase from zero, those values are converted to increased values *sf1_gsv* for the first sub-frame SF1, and the grayscale value *sf2_gsv* for the second sub-frame SF2 is maintained at zero. This conversion may be effected using a look-up-table (LUT) that maps each grayscale input value to an increased sub-frame value *sf1_gsv* according to a gamma 2.2 curve. As the input grayscale values increase, the second sub-frame value remains at zero (at relaxation) until the first sub-frame value *sf1_gsv* reaches a preset threshold value *sf1_max*, e.g., 255, as depicted in FIG. 17B. Thus, up to this point no drive current is supplied to the pixel during the second sub-frame SF2 and so that the pixel remains black (at relaxation) during the second sub-frame SF2. The desired luminance represented by the input grayscale value is still achieved because the first sub-frame value *sf1_gsv* from the LUT is greater than the input value, which represents the desired luminance for an entire frame F. This improves compensation by providing a higher leakage current.

[0055] As depicted in FIG. 17C, after the threshold grayscale value *sf1_max* is reached, the first sub-frame grayscale value *sf1_gsv* remains at that maximum value as the input value continues to increase, while the second sub-frame grayscale value *sf2_gsv* begins to increase from zero. From this stage on, the LUT uses the following equation to govern the relationship between the first and second grayscale values:

$$sf1_gsv = \min [255 - sf2_gsv + 128, sf1_max]$$

(1)

Thus, as the second sub-frame value *sf2_gsv* increases, the first sub-frame value *sf1_gsv* remains at *sf1_max*, until the second sub-frame value *sf2_gsv* reaches a first threshold value *sf2_th*, e.g., 128. As depicted in FIG. 17D, when the input grayscale value increases to a value that causes the second sub-frame value *sf2_gsv* to increase above the threshold value *sf2_th*, the value of *sf2_gsv* continues to increase while the first sub-frame value *sf1_gsv* is decreased by the same amount. This relationship causes the total luminance (sum of luminance from both sub-frames) vs. the raw grayscale input values to follow a gamma curve of 2.2.

[0056] As shown in FIG. 17E, the concurrent increasing of *sf2_gsv* and decreasing of *sf1_gsv* continues until *sf2_gsv* reaches a maximum value *sf2_max*, e.g., 255, which corresponds to a *sf1_gsv* value of 128 according to Equation (1). At this point the input grayscale value is at its maximum, e.g., 255, where the pixel is at full brightness. The reduced first sub-frame value *sf1_gsv* provides a moderate relaxation to the pixel when running at full brightness, to extend the pixel lifetime.

[0057] A second implementation utilizes an LUT containing grayscale data depicted by the curves in FIG. 18, which has the raw grayscale input values on the x axis and the corresponding sub-frame values on the y axis. The values *sf1_gsv* for the first sub-frame are depicted by the solid-line curve SF1, and the values *sf2_gsv* for the second sub-frame are depicted by the broken-line curve SF2. These sub-frame values *sf1_gsv* and *sf2_gsv* are generated from a look-up table (LUT) which maps the input grayscale value to sub-frame values *sf1_gsv* and *sf2_gsv* that increase the luminance according to a gamma 2.2 curve as the input grayscale value increases.

[0058] As the input grayscale value increases from zero to 95, the value of *sf1_gsv* increases from zero to a threshold

value sf1_max (e.g., 255), and the value of sf2_gsv remains at zero. Thus, whenever the input grayscale value is in this range, the pixel will be black during the second sub-frame SF2, which provides a relaxation interval that helps reduce the rate of degradation and thereby extend the life of that pixel.

[0059] When the input grayscale value reaches 96, the LUT begins to increase the value of sf2_gsv and maintains the value of sf1_gsv at 255. When the input grayscale value reaches 145, the LUT progressively decreases the value of sf1_gsv from 255 while continuing to progressively increase the value of sf2_gsv.

[0060] While particular embodiments and applications of the present invention have been illustrated and described, it is to be understood that the invention is not limited to the precise construction and compositions disclosed herein and that various modifications, changes, and variations can be apparent from the foregoing descriptions without departing from the scope of the invention as defined in the appended claims.

Claims

1. A method of using raw grayscale values, representing images to be displayed in successive frames, to drive a display having pixels (104) that include a drive transistor (200) and an organic light emitting device (202), said method comprising:

dividing each frame into first and second sub-frames;

converting the raw grayscale values for each frame to first and second sub-frame grayscale values for the first and second sub-frames, respectively; and

supplying each pixel with a drive current during said first and second sub-frames that is based on said first and second sub-frame grayscale values, respectively, wherein said drive current is

higher in said first sub-frame than in said second sub-frame for raw grayscale values in a first preselected range of raw grayscale values starting from zero, and

higher in said second sub-frame than in said first sub-frame for raw grayscale values in a second preselected range of raw grayscale values;

wherein the raw grayscale values for each frame are converted to respective first and second sub-frame grayscale values for the first and second sub-frames, respectively, such that: as the raw grayscale values increase from zero within the first preselected range,

the first sub-frame grayscale values are increased grayscale values that increase with the increasing raw grayscale values until a first threshold grayscale value for the first sub-frame grayscale values is reached, while the second sub-frame grayscale values are maintained at zero, and

after said first threshold grayscale value is reached, for a continuous range of raw grayscale values the first sub-frame grayscale values remain at said first threshold grayscale value as the raw grayscale values continue to increase, while the second sub-frame grayscale values progressively increase from zero until reaching a second threshold grayscale value for the second sub-frame grayscale values; and

when the raw grayscale value increases to a value that causes the second sub-frame grayscale value to increase above said second threshold grayscale value, the second sub-frame grayscale value continues to increase while the first sub-frame grayscale value is decreased by the same amount; wherein

the first preselected range is a grayscale range lower than the second preselected range, and a duration of the first sub-frame is shorter than a duration of the second sub-frame.

2. The method of claim 1 in which the first and second sub-frame grayscale values are preselected to produce a pixel luminance during that frame that has a predetermined gamma relationship to said raw grayscale value for that frame.

3. The method of claim 1 or claim 2 in which said display is an active matrix display.

4. The method of claim 3 in which said pixels (104) in said active matrix display are OLED pixels.

5. An apparatus for using raw grayscale values, the raw grayscale values representing images to be displayed in successive frames, to drive a display having an array of pixels (102) that each include a drive transistor (200) and an organic light emitting device (202), multiple select lines coupled to said array (102) for delivering signals that select when each pixel (104) is to be driven, and multiple data lines for delivering drive signals to the selected pixels,

said apparatus comprising:

a source driver (110) coupled to said data lines and including a processing circuit (112) for receiving said raw grayscale values and adapted to

divide each frame into first and second sub-frames,
convert the raw grayscale values for each frame to first and second sub-frame grayscale values for the first and second sub-frames, respectively, and
supply each pixel with a drive current during said first and second sub-frames that is based on the first and second sub-frame grayscale values, respectively, wherein said drive current is

higher in said first sub-frame than in said second sub-frame for raw grayscale values in a first preselected range of raw grayscale values starting from zero, and
higher in said second sub-frame than in said first sub-frame for raw grayscale values in a second preselected range of raw grayscale values;

wherein the raw grayscale values for each frame are converted to respective first and second sub-frame grayscale values for the first and second sub-frames, respectively, such that: as the raw grayscale values increase from zero within the first preselected range,

the first sub-frame grayscale values are increased grayscale values that increase with the increasing raw grayscale values until a first threshold grayscale value for the first sub-frame grayscale values is reached, while the second sub-frame grayscale values are maintained at zero, and
after said first threshold grayscale value is reached, for a continuous range of raw grayscale values the first sub-frame grayscale values remain at said first threshold grayscale value as the raw grayscale values continue to increase, while the second sub-frame grayscale values progressively increase from zero until reaching a second threshold grayscale value for the second sub-frame grayscale values; and

when the raw grayscale value increases to a value that causes the second sub-frame grayscale value to increase above said second threshold grayscale value, the second sub-frame grayscale value continues to increase while the first sub-frame grayscale value is decreased by the same amount; wherein
the first preselected range is a grayscale range lower than the second preselected range, and
a duration of the first sub-frame is shorter than a duration of the second sub-frame.

6. The apparatus of claim 5 in which first and second sub-frame grayscale values are preselected to produce a pixel luminance during that frame that has a predetermined gamma relationship to said raw grayscale value for that frame.

7. The apparatus of claim 5 or claim 6 in which said display is an active matrix display.

8. The apparatus of claim 7 in which said pixels (104) in said active matrix display are OLED pixels.

Patentansprüche

1. Verfahren zum Verwenden von rohen Graustufenwerten, die in aufeinanderfolgenden Rahmen anzuzeigende Bilder wiedergeben, für das Betreiben eines Display mit Pixeln (104), die einen Treibertransistor (200) und eine organische Lichtemissionseinrichtung (202) enthalten, wobei das Verfahren umfasst:

Teilen jedes Rahmens in erste und zweite Subrahmen,
Wandeln der rohen Graustufenwerte für jeden Rahmen zu ersten und zweiten Subrahmen-Graustufenwerten für jeweils die ersten und zweiten Subrahmen, und
Versorgen jedes Pixels mit einem Treiberstrom während der ersten und zweiten Subrahmen, der jeweils auf den ersten und zweiten Subrahmen-Graustufenwerten basiert, wobei der Treiberstrom:

höher in dem ersten Subrahmen als in dem zweiten Subrahmen ist für rohe Graustufenwerte in einem ersten vorausgewählten Bereich von rohen Graustufenwerten, der bei null beginnt, und
höher in dem zweiten Subrahmen als in dem ersten Subrahmen ist für Graustufenwerte in einem zweiten vorausgewählten Bereich von rohen Graustufenwerten,

wobei die rohen Graustufenwerte für jeden Rahmen zu entsprechenden ersten und zweiten Subrahmen-Graustufenwerten für jeweils die ersten und zweiten Subrahmen gewandelt werden, sodass, wenn die rohen Graustufenwerte von null größer werden innerhalb des vorausgewählten Bereichs:

5 die ersten Subrahmen-Graustufenwerte erhöhte Graustufenwerte sind, die sich mit der Erhöhung der rohen Graustufenwerte erhöhen, bis ein erster Schwellwert-Graustufenwert für die ersten Subrahmen-Graustufenwerte erreicht wird, während die zweiten Subrahmen-Graustufenwerte bei null gehalten werden, und
10 nachdem der erste Schwellwert-Graustufenwert erreicht wurde, für einen kontinuierlichen Bereich von rohen Graustufenwerten die ersten Subrahmen-Graustufenwerte bei dem ersten Schwellwert-Graustufenwert bleiben, während sich die rohen Graustufenwerte weiterhin erhöhen und sich die zweiten Subrahmen-Graustufenwerte progressiv von null erhöhen, bis sie einen zweiten Schwellwert-Graustufenwert für die zweiten Subrahmen-Graustufenwerte erreichen, und

15 wenn sich der rohe Graustufenwert zu einem Wert erhöht, der veranlasst, dass sich der zweite Subrahmen-Graustufenwert über den zweiten Schwellwert-Graustufenwert erhöht, sich der zweite Subrahmen-Graustufenwert weiterhin erhöht, während der erste Subrahmen-Graustufenwert um die gleiche Größe vermindert wird, wobei:

20 der erste vorausgewählte Bereich ein Graustufenbereich ist, der niedriger als der zweite vorausgewählte Bereich ist, und
die Dauer des ersten Subrahmens kürzer ist als die Dauer des zweiten Subrahmens.

2. Verfahren nach Anspruch 1, in dem die ersten und zweiten Subrahmen-Graustufenwerte vorausgewählt werden, um eine Pixelhelligkeit während dieses Rahmens zu erzeugen, die eine vorbestimmte Gamma-Beziehung zu dem
25 rohen Graustufenwert für diesen Rahmen aufweist.

3. Verfahren nach Anspruch 1 oder 2, in dem das Display ein Aktivmatrixdisplay ist.

30 4. Verfahren nach Anspruch 3, in dem die Pixel (104) in dem Aktivmatrixdisplay OLED-Pixel sind.

5. Vorrichtung zum Verwenden von rohen Graustufenwerten, wobei die rohen Graustufenwerte Bilder für die Anzeige in aufeinanderfolgenden Rahmen wiedergeben, für das Betreiben eines Displays mit einer Anordnung von Pixeln (102), die jeweils einen Treibertransistor (200) und eine organische Lichtemissionseinrichtung (202) enthalten, mehreren Auswahlleitungen, die mit der Anordnung (102) gekoppelt sind, um Signale zuzuführen, die auswählen,
35 wann jedes Pixel (104) zu betreiben ist, und mehreren Datenleitungen für das Zuführen von Treibersignalen zu den ausgewählten Pixeln, wobei die Vorrichtung umfasst:

einen Source-Treiber (110), der mit den Datenleitungen gekoppelt ist, eine Verarbeitungsschaltung (112) zum Empfangen der rohen Graustufenwerte enthält und ausgebildet ist zum:

40 Teilen jedes Rahmens in erste und zweite Subrahmen,
Wandeln der rohen Graustufenwerte für jeden Rahmen zu ersten und zweiten Subrahmen-Graustufenwerten für jeweils die ersten und zweiten Subrahmen, und

45 Versorgen jedes Pixels mit einem Treiberstrom während der ersten und zweiten Subrahmen, der jeweils auf den ersten und zweiten Subrahmen-Graustufenwerten basiert, wobei der Treiberstrom:

höher in dem ersten Subrahmen als in dem zweiten Subrahmen ist für rohe Graustufenwerte in einem ersten vorausgewählten Bereich von rohen Graustufenwerten, der bei null beginnt, und
50 höher in dem zweiten Subrahmen als in dem ersten Subrahmen ist für Graustufenwerte in einem zweiten vorausgewählten Bereich von rohen Graustufenwerten,

wobei die rohen Graustufenwerte für jeden Rahmen zu entsprechenden ersten und zweiten Subrahmen-Graustufenwerten für jeweils die ersten und zweiten Subrahmen gewandelt werden, sodass, wenn die rohen Graustufenwerte von null größer werden innerhalb des vorausgewählten Bereichs:

55 die ersten Subrahmen-Graustufenwerte erhöhte Graustufenwerte sind, die sich mit der Erhöhung der rohen Graustufenwerte erhöhen, bis ein erster Schwellwert-Graustufenwert für die ersten Subrahmen-Graustufenwerte erreicht wird, während die zweiten Subrahmen-Graustufenwerte bei null gehalten werden, und
nachdem der erste Schwellwert-Graustufenwert erreicht wurde, für einen kontinuierlichen Bereich von rohen Graustufenwerten die ersten Subrahmen-Graustufenwerte bei dem ersten Schwellwert-Graustufenwert bleiben, während sich die rohen Graustufenwerte weiterhin erhöhen und sich die zweiten Subrahmen-Graustufenwerte progressiv von null erhöhen, bis sie einen zweiten Schwellwert-Graustufenwert für die zweiten Subrahmen-Graustufenwerte erreichen, und

fenwerte erreicht wird, während die zweiten Subrahmen-Graustufenwerte bei null gehalten werden, und nachdem der erste Schwellwert-Graustufenwert erreicht wurde, für einen kontinuierlichen Bereich von rohen Graustufenwerten die ersten Subrahmen-Graustufenwerte bei dem ersten Schwellwert-Graustufenwert bleiben, während sich die rohen Graustufenwerte weiterhin erhöhen und sich die zweiten Subrahmen-Graustufenwerte progressiv von null erhöhen, bis sie einen zweiten Schwellwert-Graustufenwert für die zweiten Subrahmen-Graustufenwerte erreichen, und

wenn sich der rohe Graustufenwert zu einem Wert erhöht, der veranlasst, dass sich der zweite Subrahmen-Graustufenwert über den zweiten Schwellwert-Graustufenwert erhöht, sich der zweite Subrahmen-Graustufenwert weiterhin erhöht, während der erste Subrahmen-Graustufenwert um die gleiche Größe vermindert wird, wobei:

der erste vorausgewählte Bereich ein Graustufenbereich ist, der niedriger als der zweite vorausgewählte Bereich ist, und
die Dauer des ersten Subrahmens kürzer ist als die Dauer des zweiten Subrahmens.

6. Vorrichtung nach Anspruch 5, in der die ersten und zweiten Subrahmen-Graustufenwerte vorausgewählt werden, um eine Pixelhelligkeit während dieses Rahmens zu erzeugen, die eine vorbestimmte Gamma-Beziehung zu dem rohen Graustufenwert für diesen Rahmen aufweist.

7. Vorrichtung nach Anspruch 5 oder 6, in der das Display ein Aktivmatrixdisplay ist.

8. Vorrichtung nach Anspruch 7, in der die Pixel (104) in dem Aktivmatrixdisplay OLED-Pixel sind.

Revendications

1. Procédé d'utilisation de valeurs d'échelle de gris brutes, représentant des images à afficher dans des trames successives, pour commander un affichage ayant des pixels (104) qui incluent un transistor d'attaque (200) et un dispositif électroluminescent organique (202), ledit procédé consistant à :

diviser chaque trame en une première et une seconde sous-trame ;
convertir les valeurs d'échelle de gris brutes pour chaque trame en valeurs d'échelle de gris de première et seconde sous-trames pour les première et seconde sous-trames, respectivement ; et
fournir un courant d'attaque à chaque pixel durant lesdites première et seconde sous-trames, qui est basé sur lesdites valeurs d'échelle de gris de première et seconde sous-trames, respectivement, dans lequel ledit courant d'attaque est
plus élevé dans ladite première sous-trame que dans ladite seconde sous-trame pour les valeurs d'échelle de gris brutes dans une première gamme présélectionnée de valeurs d'échelle de gris brutes partant de zéro, et plus élevé dans ladite seconde sous-trame que dans ladite première sous-trame pour les valeurs d'échelle de gris brutes dans une seconde gamme présélectionnée de valeurs d'échelle de gris brutes ;
dans lequel les valeurs d'échelle de gris brutes pour chaque trame sont converties en valeurs d'échelle de gris de première et seconde sous-trames respectives pour la première et la seconde sous-trame, respectivement, de sorte que : à mesure que les valeurs d'échelle de gris brutes augmentent à partir de zéro dans la première gamme présélectionnée,
les valeurs d'échelle de gris de première sous-trame sont des valeurs d'échelle de gris augmentées qui augmentent avec l'augmentation des valeurs d'échelle de gris brutes jusqu'à ce qu'une première valeur seuil d'échelle de gris pour les valeurs d'échelle de gris de première sous-trame soit atteinte, tandis que les valeurs d'échelle de gris de seconde sous-trame sont maintenues à zéro, et
après que ladite première valeur seuil d'échelle de gris est atteinte, pour une gamme continue de valeurs d'échelle de gris brutes, les valeurs d'échelle de gris de première sous-trame demeurent au niveau de ladite première valeur seuil d'échelle de gris alors que les valeurs d'échelle de gris brutes continuent d'augmenter, tandis que les valeurs d'échelle de gris de seconde sous-trame augmentent progressivement à partir de zéro jusqu'à ce qu'elles atteignent une seconde valeur seuil d'échelle de gris pour les valeurs d'échelle de gris de seconde sous-trame ; et
lorsque la valeur d'échelle de gris brute augmente jusqu'à une valeur telle que la valeur d'échelle de gris de seconde sous-trame passe au-dessus de ladite seconde valeur seuil d'échelle de gris, la valeur d'échelle de gris de seconde sous-trame continue d'augmenter tandis que la valeur d'échelle de gris de première sous-

trame diminue dans la même proportion ; dans lequel
la première gamme présélectionnée est une gamme d'échelle de gris inférieure à la seconde gamme présélectionnée, et
une durée de la première sous-trame est inférieure à une durée de la seconde sous-trame.

2. Procédé selon la revendication 1, dans lequel les valeurs d'échelle de gris de première et seconde sous-trames sont présélectionnées pour produire une luminance de pixel durant une trame qui a une relation gamma prédéterminée avec ladite valeur d'échelle de gris brute pour cette trame.

3. Procédé selon la revendication 1 ou la revendication 2, dans lequel ledit affichage est un affichage à matrice active.

4. Procédé selon la revendication 3, dans lequel lesdits pixels (104) dudit affichage à matrice active sont des pixels OLED.

5. Appareil destiné à utiliser des valeurs d'échelle de gris brutes, les valeurs d'échelle de gris brutes représentant des images à afficher dans des trames successives, pour commander un affichage ayant une matrice de pixels (102) dont chacun inclut un transistor d'attaque (200) et un dispositif électroluminescent organique (202), des lignes de sélection multiples couplées à ladite matrice (102) pour délivrer des signaux qui sélectionnent le moment où chaque pixel (104) doit être excité, et des lignes de données multiples pour délivrer des signaux d'attaque aux pixels sélectionnés, ledit appareil comprenant :

un pilote source (110) couplé auxdites lignes de données et incluant un circuit de traitement (112) pour recevoir lesdites valeurs d'échelle de gris brutes, et conçu pour
diviser chaque trame en une première et une seconde sous-trame,
convertir les valeurs d'échelle de gris brutes pour chaque trame en valeurs d'échelle de gris de première et seconde sous-trames pour les première et seconde sous-trames, respectivement, et
fournir un courant d'attaque à chaque pixel durant lesdites première et seconde sous-trames, qui est basé sur les valeurs d'échelle de gris de première et seconde sous-trames, respectivement, dans lequel ledit courant d'attaque est
plus élevé dans ladite première sous-trame que dans ladite seconde sous-trame pour les valeurs d'échelle de gris brutes dans une première gamme présélectionnée de valeurs d'échelle de gris brutes partant de zéro, et plus élevé dans ladite seconde sous-trame que dans ladite première sous-trame pour les valeurs d'échelle de gris brutes dans une seconde gamme présélectionnée de valeurs d'échelle de gris brutes ;
dans lequel les valeurs d'échelle de gris brutes pour chaque trame sont converties en valeurs d'échelle de gris de première et seconde sous-trames respectives pour la première et la seconde sous-trame, respectivement, de sorte que : à mesure que les valeurs d'échelle de gris brutes augmentent à partir de zéro dans la première gamme présélectionnée,
les valeurs d'échelle de gris de première sous-trame sont des valeurs d'échelle de gris augmentées qui augmentent avec l'augmentation des valeurs d'échelle de gris brutes jusqu'à ce qu'une première valeur seuil d'échelle de gris pour les valeurs d'échelle de gris de première sous-trame soit atteinte, tandis que les valeurs d'échelle de gris de seconde sous-trame sont maintenues à zéro, et
après que ladite première valeur seuil d'échelle de gris est atteinte, pour une gamme continue de valeurs d'échelle de gris brutes, les valeurs d'échelle de gris de première sous-trame demeurent au niveau de ladite première valeur seuil d'échelle de gris alors que les valeurs d'échelle de gris brutes continuent d'augmenter, tandis que les valeurs d'échelle de gris de seconde sous-trame augmentent progressivement à partir de zéro jusqu'à ce qu'elles atteignent une seconde valeur seuil d'échelle de gris pour les valeurs d'échelle de gris de seconde sous-trame ; et
lorsque la valeur d'échelle de gris brute augmente jusqu'à une valeur telle que la valeur d'échelle de gris de seconde sous-trame passe au-dessus de ladite seconde valeur seuil d'échelle de gris, la valeur d'échelle de gris de seconde sous-trame continue d'augmenter tandis que la valeur d'échelle de gris de première sous-trame diminue dans la même proportion ; dans lequel
la première gamme présélectionnée est une gamme d'échelle de gris inférieure à la seconde gamme présélectionnée, et
une durée de la première sous-trame est inférieure à une durée de la seconde sous-trame.

6. Appareil selon la revendication 5, dans lequel les valeurs d'échelle de gris de première et seconde sous-trames sont présélectionnées pour produire une luminance de pixel durant une trame qui a une relation gamma prédéterminée avec ladite valeur d'échelle de gris brute pour cette trame.

EP 2 624 243 B1

7. Appareil selon la revendication 5 ou la revendication 6, dans lequel ledit affichage est un affichage à matrice active.
8. Appareil selon la revendication 7, dans lequel lesdits pixels (104) dudit affichage à matrice active sont des pixels OLED.

5

10

15

20

25

30

35

40

45

50

55




FIG. 1




FIG. 2




FIG. 3




FIG. 4A




FIG. 4B




FIG. 5A




FIG. 5C




FIG. 5B




FIG. 5D




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 15




FIG. 13




FIG. 14A




FIG. 14B




FIG. 16A




FIG. 16B




FIG. 17A




FIG. 17B




FIG. 17C




FIG. 17D




FIG. 17E




FIG. 18

REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Patent documents cited in the description

- EP 2299427 A1 [0004]
- US 20090002281 A1 [0005]
- US 20080284768 A1 [0006]

专利名称(译)	有源矩阵显示器的驱动系统		
公开(公告)号	EP2624243B1	公开(公告)日	2019-05-01
申请号	EP2013153887	申请日	2013-02-04
[标]申请(专利权)人(译)	伊格尼斯创新公司		
申请(专利权)人(译)	IGNIS创新INC.		
当前申请(专利权)人(译)	IGNIS创新INC.		
[标]发明人	LI KONGNING GUPTA VASUDHA CHAJI GHOLAMREZA NATHAN AROKIA		
发明人	LI, KONGNING GUPTA, VASUDHA CHAJI, GHOLAMREZA NATHAN, AROKIA		
IPC分类号	G09G3/20 G09G3/32		
CPC分类号	G09G3/2022 G09G3/2081 G09G3/3225 G09G2320/0276 G09G2320/043 G09G2320/0626 G09G2320/0673 G09G2360/144 G09G2360/16 G09G3/3233		
优先权	13/365391 2012-02-03 US		
其他公开文献	EP2624243A1		
外部链接	Espacenet		

摘要(译)

表示要在连续帧中显示的图像的原始灰度图像数据用于通过将每个帧分成至少第一帧和第二帧来驱动具有包括驱动晶体管和有机发光器件的像素的显示器，并且提供每个像素对于第一预选范围内的原始灰度值，第一子帧中的驱动电流高于第二子帧中的驱动电流，并且第二子帧中的驱动电流高于第一子帧中的原始灰度值的驱动电流。第二个预选范围。显示器可以是有源矩阵显示器，例如AMOLED显示器。

$$sf1_gsv = \min [255 - sf2_gsv + 128, sf1_max]$$

(1)