



US008638278B2

(12) **United States Patent**
Yamazaki et al.

(10) **Patent No.:** **US 8,638,278 B2**
(45) **Date of Patent:** **Jan. 28, 2014**

(54) **DISPLAY DEVICE**

(71) Applicant: **Semiconductor Energy Laboratory Co., Ltd.**, Atsugi (JP)

(72) Inventors: **Shunpei Yamazaki**, Tokyo (JP); **Jun Koyama**, Kanagawa (JP); **Mitsuaki Osame**, Kanagawa (JP); **Mai Osada**, Kanagawa (JP)

(73) Assignee: **Semiconductor Energy Laboratory Co., Ltd.**, Atsugi-shi, Kanagawa-ken (JP)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

(21) Appl. No.: **13/792,302**

(22) Filed: **Mar. 11, 2013**

(65) **Prior Publication Data**
US 2013/0187142 A1 Jul. 25, 2013

Related U.S. Application Data

(63) Continuation of application No. 13/480,545, filed on May 25, 2012, now Pat. No. 8,400,379, which is a continuation of application No. 13/030,191, filed on Feb. 18, 2011, now Pat. No. 8,194,008, which is a continuation of application No. 12/609,820, filed on Oct. 30, 2009, now Pat. No. 7,990,348, which is a continuation of application No. 10/920,279, filed on Aug. 18, 2004, now Pat. No. 7,623,098, which is a continuation of application No. 09/833,673, filed on Apr. 13, 2001, now Pat. No. 7,221,338.

(30) **Foreign Application Priority Data**

Apr. 18, 2000 (JP) 2000-117045
Mar. 5, 2001 (JP) 2001-059511

(51) **Int. Cl.**
G09G 3/30 (2006.01)

(52) **U.S. Cl.**
USPC **345/76**; 315/169.3

(58) **Field of Classification Search**
USPC 345/76-84; 315/169.3
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,308,556 A 12/1981 Osaka
5,041,823 A 8/1991 Johnson et al.

(Continued)

FOREIGN PATENT DOCUMENTS

EP 0372364 A1 6/1990
EP 0391655 A2 10/1990

(Continued)

OTHER PUBLICATIONS

Office Action (U.S. Appl. No. 09/833,673), dated Dec. 1, 2004, 10 pages.

(Continued)


Primary Examiner — Ricardo L Osorio

(74) *Attorney, Agent, or Firm* — Fish & Richardson P.C.

(57) **ABSTRACT**

The present invention is intended to suppress power consumption of an EL display. In accordance with the brightness of an image to be displayed in a pixel portion, the contrast of the image is determined whether to be inverted or not, and the number of bits of the digital video signal to be input into the pixel portion is reduced, and the magnitude of a current to flow through the EL element is allowed to be maintained at a constant level even when a temperature of an EL layer changes by providing the EL display with another EL element to be used for monitoring a temperature.

15 Claims, 29 Drawing Sheets



(56)

References Cited

U.S. PATENT DOCUMENTS

5,247,190 A 9/1993 Friend et al.
 5,399,502 A 3/1995 Friend et al.
 5,414,443 A 5/1995 Kanatani et al.
 5,594,463 A 1/1997 Sakamoto
 5,597,223 A 1/1997 Watanabe et al.
 5,745,085 A 4/1998 Tomio et al.
 5,844,535 A 12/1998 Itoh et al.
 5,856,816 A 1/1999 Youn
 5,882,761 A 3/1999 Kawami et al.
 5,886,474 A 3/1999 Asai et al.
 5,893,730 A 4/1999 Yamazaki et al.
 5,990,629 A 11/1999 Yamada et al.
 6,005,350 A 12/1999 Hachiya et al.
 6,008,801 A 12/1999 Jeong
 6,049,321 A 4/2000 Sasaki
 6,054,976 A 4/2000 Kubota et al.
 6,069,676 A 5/2000 Yuyama
 6,072,448 A 6/2000 Kojima et al.
 6,097,302 A 8/2000 Zinzell
 6,127,993 A 10/2000 Ohba et al.
 6,147,451 A 11/2000 Shibata et al.
 6,219,113 B1 4/2001 Takahara
 6,320,325 B1 11/2001 Cok et al.
 6,335,713 B1 1/2002 Imai
 6,373,459 B1 4/2002 Jeong
 6,376,994 B1 4/2002 Ochi et al.
 6,380,558 B1 4/2002 Yamazaki et al.
 6,392,617 B1 5/2002 Gleason
 6,396,468 B2 5/2002 Matsushima et al.
 6,396,508 B1 5/2002 Noecker
 6,404,137 B1 6/2002 Shodo
 6,411,306 B1 6/2002 Miller et al.
 6,414,661 B1 7/2002 Shen et al.
 6,417,824 B1 7/2002 Tokunaga et al.
 6,424,326 B2 7/2002 Yamazaki et al.
 6,452,576 B1 9/2002 Van Velzen et al.
 6,469,439 B2 10/2002 Himeshima et al.
 6,486,862 B1 11/2002 Jacobsen et al.
 6,496,218 B2 12/2002 Takigawa et al.
 6,518,941 B1 2/2003 Kimura
 6,518,962 B2 2/2003 Kimura et al.
 6,525,704 B1 2/2003 Kondo et al.
 6,528,951 B2 3/2003 Yamazaki et al.
 6,534,925 B2 3/2003 Kawashima
 6,552,736 B2 4/2003 Honda et al.
 6,559,594 B2 5/2003 Fukunaga et al.
 6,693,616 B2 2/2004 Koyama et al.
 6,756,820 B1 6/2004 Heyne et al.
 6,784,864 B1 8/2004 Koyama et al.
 6,816,144 B2 11/2004 Tsuchi
 6,873,275 B2 3/2005 Komamura et al.
 7,623,098 B2 11/2009 Yamazaki et al.
 8,237,355 B2 8/2012 Yamazaki
 2001/0017618 A1 8/2001 Azami
 2001/0017683 A1 8/2001 Hiroki et al.
 2001/0026257 A1 10/2001 Kimura
 2002/0030649 A1 3/2002 Zavracky et al.
 2002/0053884 A1 5/2002 Kimura
 2002/0105493 A1 8/2002 Komiya

2002/0145602 A1 10/2002 Matsueda
 2002/0154151 A1 10/2002 Koyama
 2002/0180672 A1 12/2002 Yamazaki et al.
 2002/0180721 A1 12/2002 Kimura et al.
 2003/0063081 A1 4/2003 Kimura et al.
 2003/0132716 A1 7/2003 Yamazaki et al.
 2004/0201583 A1 10/2004 Burroughes et al.
 2004/0239668 A1 12/2004 Morosawa et al.
 2005/0017933 A1 1/2005 Koyama
 2005/0017963 A1 1/2005 Yamazaki et al.
 2005/0017964 A1 1/2005 Yamazaki et al.
 2005/0162371 A1 7/2005 Morita

FOREIGN PATENT DOCUMENTS

EP 0707301 A1 4/1996
 EP 0923067 A1 6/1999
 JP 56-119179 A 9/1981
 JP 61-083593 A 4/1986
 JP 62-192792 A 8/1987
 JP 05-094151 A 4/1993
 JP 07-036410 A 2/1995
 JP 08-171370 A 7/1996
 JP 09-148066 A 6/1997
 JP 10-092576 A 4/1998
 JP 10-214060 A 8/1998
 JP 10-232649 A 9/1998
 JP 10-268842 A 10/1998
 JP 10-312173 A 11/1998
 JP 11-054268 A 2/1999
 JP 11-272223 A 10/1999
 JP 11-273856 A 10/1999
 JP 2000-013209 A 1/2000
 JP 2000-089736 A 3/2000
 JP 2000-098330 A 4/2000
 JP 2001-109433 A 4/2001
 JP 2002-511608 A 4/2002
 TW 250560 A 7/1995
 WO WO 90/07768 A1 7/1990
 WO WO 90/13148 A1 11/1990
 WO WO 98/40871 A1 9/1998
 WO WO 99/53472 A1 10/1999
 WO WO 01/27910 A1 4/2001

OTHER PUBLICATIONS

Office Action (U.S. Appl. No. 09/833,673), dated Aug. 19, 2005, 6 pages.
 Office Action (U.S. Appl. No. 09/833,673), dated Feb. 24, 2006, 6 pages.
 Office action (U.S. Appl. No. 200510003809.0) mailed Feb. 6, 2009 with English translation.
 R. Dawson et al., "Design of an Improved Pixel for a Polysilicon Active-Matrix Organic LED Display," SID '98 Digest, vol. XXIX, May 17-22, 1998, pp. 11-14.
 M. Mizukami et al., "6-Bit Digital VGA OLED," SID '00 Digest, vol. XXXI, May 16-18, 2000, pp. 912-915.
 Schenk et al., "Polymers for Light Emitting Diodes," EuroDisplay '99: Proceedings of the 19th International Display Research Conference, Sep. 1999, pp. 33-37.
 Search Report (European Application No. 01109581.7) dated May 11, 2009.

Fig. 1




Fig. 2




Fig. 3




Fig. 4




Fig. 5




Fig. 6




Fig. 7




Fig. 8




Fig. 9




Fig. 10




Fig. 11




Fig. 12




Fig. 13




Fig. 14




Fig. 15A




Fig. 15B




Fig. 16




Fig. 17




Fig. 18A




Fig. 18B




Fig. 19




Fig. 20




Fig. 21




Fig. 22




Fig. 23A




Fig. 23B




Fig. 23C








Fig. 23D










Fig. 26A




Fig. 26B




Fig. 27A





Fig. 27B






Fig. 28A




Fig. 28B




Fig. 28C




Fig. 28D




Fig. 28E




Fig. 28F

Fig. 29A





Fig. 29B



1

DISPLAY DEVICE

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a continuation of U.S. application Ser. No. 13/480,545, filed May 25, 2012, now allowed, which is a continuation of U.S. application Ser. No. 13/030,191, filed Feb. 18, 2011, now U.S. Pat. No. 8,194,008, which is a continuation of U.S. application Ser. No. 12/609,820, filed Oct. 30, 2009, now U.S. Pat. No. 7,990,348, which is a continuation of U.S. application Ser. No. 10/920,279, filed Aug. 18, 2004, now U.S. Pat. No. 7,623,098, which is a continuation of U.S. application Ser. No. 09/833,673, filed Apr. 13, 2001, now U.S. Pat. No. 7,221,338, which claims the benefit of foreign priority applications filed in Japan as Serial No. 2000-117045 on Apr. 18, 2000, and Serial No. 2001-059511 on Mar. 5, 2001, all of which are incorporated by reference.

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a display panel in which a light emitting element formed on a substrate is sealed between the substrate and a cover member. In addition, the present invention also relates to a display module in which an IC chip is mounted on the above-mentioned display panel. It should be noted that in the present specification, the display panel and the display module are collectively referred to as the light emitting device. The present invention further relates to an electronic apparatus that employs the above-mentioned light emitting device.

2. Description of the Related Art

Recently, techniques for forming a TFT on a substrate has been greatly advanced, and much developments have been made to apply those techniques to an active-matrix type display device. In particular, a TFT employing a poly-crystalline silicon film can operate at a higher speed since a field effect mobility (simply referred to as the mobility) thereof is larger than that of a TFT employing the conventional amorphous silicon film. Thus, it becomes possible to control pixels by means of a driver circuit formed on the same substrate as the pixels. Such the pixels was conventionally controlled by means of a driver circuit provided at the outside of the substrate.

The active-matrix type display device as mentioned above can exhibit various advantages such as a reduced fabricating cost, miniaturization of the display device, an increased fabricating yield, a reduced throughput or the like, by providing various circuits and elements on the identical substrate.

Furthermore, developments of an active-matrix type light emitting device having light emitting elements as a self-emission type element have been actively conducted. Such a light emitting device is also referred to as an Organic EL Display (OLED) or an Organic Light Emitting Diode (OLED).

Unlike a liquid crystal display, the light emitting device is of the self-emission type. The light emitting element has a structure in which a layer containing an organic compound (hereinafter referred to as the organic compound layer) that allows luminescence to be generated by applying an electrical field thereto is interposed between a pair of electrodes (an anode and a cathode). The organic compound layer usually has a layered structure. Typical examples therefor include a layered structure of "a hole transportation layer, a light emitting layer/an electron transportation layer" proposed by Tang et al. of Eastman Kodak Co. This structure has a high luminous efficiency, and most of light emitting devices about

2

which research and development activities are currently being progressed employ this structure.

Although a luminescence in an organic compound includes a singlet excitation (fluorescence) and a triplet excitation (phosphorescence), the light emitting device of the present invention can use one or both of the above luminescence.

Alternatively, a layered structure in which a hole injection layer/a hole transportation layer/a light emitting layer/an electron transportation layer, or a hole injection layer/a hole transportation layer/a light emitting layer/an electron transportation layer/an electron injection layer are formed on an anode in these orders may be used. Furthermore, fluorescent dyes or the like may be doped into the light emitting layer.

In the present specification, all of the layers to be disposed between the cathode and the anode are collectively referred to as the organic compound layer. Accordingly, all of the above-mentioned layers such as the hole injection layer, the hole transportation layer, the light emitting layer, the electron transportation layer, the electron injection layer or the like are included in the organic compound layer.

A predetermined voltage is applied to the organic compound layer made of the above-mentioned structure via the pair of electrodes, and thus recombination of carriers occurs in the light emitting layer, thereby resulting in light emission. In the present specification, when the light emitting element emits light, the light emitting element is expressed as being driven. In addition, in the present specification, the light emitting element composed of an anode, an organic compound layer, and a cathode is referred to as the light emitting element.

Since the light emitting device is not required to employ a back light, a thickness and a weight of the display itself can be suppressed, as compared to a liquid crystal display. For that reason, the light emitting device has come to be used as a display section of a portable information terminal (a mobile computer, a portable telephone, a portable game apparatus, an electronic book or the like), instead of the liquid crystal display.

In order to suppress power consumption of the portable information terminal, it has been desired to suppress power consumption of the light emitting device to be employed as the display section.

Moreover, digitalization of a receiver or a VTR to be used in home as well as various equipment to be used in a TV or radio broadcast station has now proceeded. As the next step following digitalization of a broadcast system is digitalization of broadcast electric waves, i.e., realization of digital broadcasting. Vigorous research and development activities have been performed toward such a goal.

One scheme to be used for realizing a digital driving of the light emitting device is a temporal gradation display. More specifically, the temporal gradation display refers to a driving method in which the gradation display is performed by controlling a time period during which the light emitting element is to emit light in one frame period.

In the case where the light emitting device is digitally driven to perform the temporal gradation display, the required number of rewriting a digital video signal containing image information to be input to pixels is increased, as the number of gradation of an image to be displayed is increased. Consequently, power consumption of a group of driver circuits to be used for inputting the digital video signal into the pixels is increased, thereby resulting in increased power consumption of the light emitting device.

In addition, since the light emitting element is of the self-emission type, a time period during which the light emitting element is to emit light in one frame period varies depending

on an image to be displayed. Accordingly, power consumption of the light emitting device in turn varies depending on an image to be displayed.

Furthermore, the magnitude of a current to flow through the light emitting element varies also depending on temperature. Even with a voltage of the same magnitude being applied across the electrodes of the light emitting element, the magnitude of a current to flow through the light emitting element varies due to temperature characteristics of the light emitting element. For example, as the temperature of the organic compound layer increases, a larger current tends to flow. Accordingly, as an environmental temperature under which the light emitting element is to be used increases, power consumption of the light emitting device increases, which in turn increases the brightness of the light emitting element.

In view of the above-described situations, the present invention is intended to suppress power consumption of a light emitting device and an electronic apparatus employing the light emitting device as its display section.

SUMMARY OF THE INVENTION

A first structure according to the present invention is characterized in which in the case where a monochrome display is performed in a light emitting device, the contrast of an image is determined whether to be inverted or not in accordance with what kind of an image to be displayed by pixels in a pixel portion.

In accordance with the above-mentioned structure, the magnitude of a current to flow through the light emitting element can be suppressed to some degree, thereby resulting in a reduced power consumption of the light emitting device.

Furthermore, a second structure in accordance with the present invention is characterized in that in a light emitting device that performs a digitally-driven time-divisional gradation display, a digital video signal input to a source signal line driver circuit included in the light emitting device is input into a pixel portion after its number of bits is reduced. More specifically, a bit of the digital video signal is sequentially cut off from the least significant bit to reduce the number of bits of the digital video signal to be input into the pixel portion.

In accordance with the above-mentioned structure, since the number of bits of the digital video signal to be input into the pixels is reduced, the required number of writing the digital video signal by the source signal line driver circuit and a gate signal line driver circuit can be reduced. Thus, power consumption of the source signal line driver circuit and the gate signal line driver circuit can be reduced, thereby resulting in a reduced power consumption of the light emitting device.

Moreover, in accordance with a third structure of the present invention, a light emitting device is provided with a light emitting element for monitoring a temperature. One of electrodes of the temperature-monitoring light emitting element is connected to a constant current source. Thus, by means of temperature characteristics of the temperature-monitoring light emitting element, the magnitude of a current to flow through a light emitting element of a pixel is maintained at a constant level.

In accordance with the above-described structure, the magnitude of a current to flow through the light emitting element of a pixel is maintained at a constant level, even when a temperature of the organic compound layer changes. Thus, power consumption of the light emitting device can be prevented from increasing even when an environmental temperature of the light emitting device increases, which in turn can maintain the brightness at a constant level.

In accordance with the first, second, and third structures of the present invention as described in the above, it is possible to suppress the power consumption of a light emitting device and an electronic apparatus which employs the light emitting device. It should be noted that only either one of the first through third structures is required to be included in the present invention, although two or all of the first through third structures may be included.

Structures in accordance with the present invention will be further described below.

The present invention provides a display device having a plurality of pixels, wherein a polarity of a digital video signal to be input into the plurality of pixels is inverted, thereby resulting in brightness of the plurality of pixels being changed.

The present invention provides a display device having a pixel portion including a plurality of pixels, and a source signal line driver circuit, wherein the source signal line driver circuit includes a switching circuit for switching a polarity of an output, and a polarity of a digital video signal input to the switching circuit is inverted by means of a shift signal to be input into the switching circuit and the resultant signal is then input into the plurality of pixels.

The present invention provides a display device having a pixel portion including a plurality of pixels, and a source signal line driver circuit, wherein each of the plurality of pixels has a light emitting element, and the source signal line driver circuit includes a shift register, one or more latches and a switching circuit, and a polarity of a digital video signal input from the one or more latches into the switching circuit is inverted by means of a shift signal to be input into the switching circuit and the resultant signal is then input into the plurality of pixels.

The present invention provides a display device having a pixel portion including a plurality of pixels, and a source signal line driver circuit, wherein each of the plurality of pixels has a light emitting element, and the source signal line driver circuit includes a shift register, one or more latches and a switching circuit, and a polarity of a digital video signal input from the one or more latches into the switching circuit is inverted by means of a shift signal to be input into the switching circuit and the resultant signal is then input into the plurality of pixels, and an average of a time period during which all of the light emitting elements emit light in one frame period is equal to or less than a half of the maximum value of the time period during which all of the light emitting elements emit light in one frame period.

The above structures may be characterized in which the switching circuit includes an inverter, a first analog switch, and a second analog switch, wherein the digital video signal input into the switching circuit is input into an input terminal of the first analog switch via the inverter, the digital video signal output from the one or more latches is input into an input terminal of the second analog switch, the shift signal is input from a first control input terminal of the first analog switch and a second control input terminal of the second analog switch, a signal obtained by inverting the polarity of the shift signal is input from a second control input terminal of the first analog switch and a second control input terminal of the second analog switch, and signals output from output terminals of the first analog switch and the second analog switch are output from the switching circuit.

The above structures may be characterized in which the switching circuit includes an inverter, a first NAND, a second NAND, and a NOR, wherein the first NAND is supplied with the digital video signal via the inverter and the shift signal, the second NAND is supplied with the digital video signal and a

signal obtained by inverting a polarity of the shift signal, a signal output from the first NAND and a signal output from the second NAND are input into the NOR, and a signal output from the NOR is output from the switching circuit.

The present invention provides a display device having a plurality of pixels and a source signal line driver circuit, wherein among a digital video signal to be input into the source signal line driver circuit, only more significant bits are input into the plurality of pixels.

The present invention provides a display device having a pixel portion including a plurality of pixels, and a source signal line driver circuit, wherein the source signal line driver circuit includes a shift register, a first latch, a second latch, and a clock signal control circuit, a clock signal is input into the shift register via the clock signal control circuit to thereby output a timing signal from the shift register, a digital video signal is input into and held at the first latch by the timing signal, the digital video signal held at the first latch is input into and held at the second latch by a latch signal, the digital video signal input into and held at the second latch is input into the plurality of pixels, and the clock signal control circuit reduces the number of bits of the digital video signal to be input into and held at the first latch by supplying a constant fixed electrical potential instead of the clock signal to the shift register for a constant period of time.

The above structure may be characterized in which the clock signal control circuit includes a NAND and an inverter, wherein a clock signal and a selection signal are input into the NAND, and a signal output from the NAND is output from the clock signal control circuit via the inverter.

The above structure may be characterized in which the clock signal control circuit includes a first analog switch, a second analog switch, and an inverter, wherein a selection signal is input via the inverter into a second control input terminal of the first analog switch and a first control input terminal of the second analog switch, the selection signal is input into a first control input terminal of the first analog switch and a second control input terminal of the second analog switch, a clock signal is input into an input terminal of the first analog switch, a fixed electrical potential is supplied to an input terminal of the second analog switch, and signals output from output terminals of the first analog switch and the second analog switch are output from the clock signal control circuit.

The present invention provides a display device having a pixel portion including a plurality of pixels, and a source signal line driver circuit, wherein the source signal line driver circuit includes a shift register, a first latch, a second latch, and a timing signal control circuit, a timing signal output from the shift register is input into the first latch via the timing signal control circuit, a digital video signal is input into and held at the first latch by the timing signal input into the first latch, the digital video signal held at the first latch is input into and held at the second latch by a latch signal, the digital video signal input into and held at the second latch is input into the plurality of pixels, and the timing signal control circuit reduces the number of bits of the digital video signal to be input into and held at the first latch by supplying to the first latch a constant fixed electrical potential instead of the timing signal output from the shift register for a constant period of time.

The above structure may be characterized in which the timing signal control circuit includes a NAND and an inverter, wherein a timing signal and a selection signal are input into the NAND, and a signal output from the NAND is output from the timing signal control circuit via the inverter.

The above structure may be characterized in which the timing signal control circuit includes a first analog switch, a

second analog switch, and an inverter, wherein a selection signal is input via the inverter into a second control input terminal of the first analog switch and a first control input terminal of the second analog switch, the selection signal is input into a first control input terminal of the first analog switch and a second control input terminal of the second analog switch, the timing signal is input into an input terminal of the first analog switch, a fixed electrical potential is supplied to an input terminal of the second analog switch, a current is supplied to flow through the plurality of light emitting elements is maintained by means of temperature characteristics of the monitoring light emitting element.

The present invention provides a display device including a pixel portion including a plurality of pixels, a power source line, a buffer amplifier, a monitoring light emitting element, and a constant current source, wherein each of the plurality of pixels includes a thin film transistor and a light emitting element, each of the monitoring light emitting element and the light emitting element includes a first electrode, a second electrode, and an organic compound layer disposed between the first electrode and the second electrode, the first electrode of the monitoring light emitting element is connected to the constant current source, the first electrode of the monitoring light emitting element is also connected to a non-inverted input terminal of the buffer amplifier, and an output terminal of the buffer amplifier is connected to the power source line, and an electrical potential of the power source line is applied to the first electrode of the light emitting element via the thin film transistor.

The present invention provides a display device including a pixel portion having a plurality of pixels, a power source line, a buffer amplifier, a monitoring light emitting element, a constant current source, and an adding circuit, wherein each of the plurality of pixels includes a thin film transistor and a light emitting element, each of the monitoring light emitting element and the light emitting element includes a first electrode, a second electrode, and an organic compound layer disposed between the first electrode and the second electrode, the first electrode of the monitoring light emitting element is connected to the constant current source, the first electrode of the monitoring light emitting element is also connected to a non-inverted input terminal of the buffer amplifier, an output terminal of the buffer amplifier is connected to an input terminal of the adding circuit, an output terminal of the adding circuit is connected to the power source line, a constant potential difference is always maintained between the input terminal and the output terminal of the adding circuit, and an electrical potential of the power source line is applied to the first electrode of the light emitting element via the thin film transistor.

The present invention may be embodied in the form of a video camera, an image analog switch, and signals output from output terminals of the first analog switch and the second analog switch are output from the timing signal control circuit.

The present invention provides a display device having a pixel portion including a plurality of pixels and a source signal line driver circuit, wherein the source signal line driver circuit includes a shift register, a first latch, a second latch, and a start pulse signal control circuit, a start pulse signal is input into the shift register via the start pulse signal control circuit to thereby output a timing signal from the shift register, a digital video signal is input into and held at the first latch by the timing signal, the digital video signal held at the first latch is input into and held at the second latch by a latch signal, the digital video signal input into and held at the second latch is input into the plurality of pixels, and the start pulse signal

control circuit reduces the number of bits of the digital video signal to be input into and held at the first latch by supplying to the shift register a constant fixed electrical potential instead of the start pulse for a constant period of time.

The above structure may be characterized in which the start pulse signal control circuit includes a NAND and an inverter, wherein a start pulse signal and a selection signal are input into the NAND, and a signal output from the NAND is output from the start pulse signal control circuit via the inverter.

The above structure may be characterized in which the start pulse signal control circuit includes a first analog switch, a second analog switch, and an inverter, wherein a selection signal is input via the inverter into a second control input terminal of the first analog switch and a first control input terminal of the second analog switch, the selection signal is input into a first control input terminal of the first analog switch and a second control input terminal of the second analog switch, a start pulse signal is input into an input terminal of the first analog switch, a fixed electrical potential is supplied to an input terminal of the second analog switch, and signals output from output terminals of the first analog switch and the second analog switch are output from the start pulse signal control circuit.

The present invention provides a display device including a plurality of pixels having a plurality of light emitting elements, and a monitoring light emitting element, wherein the reproduction apparatus, a head mount display, a portable telephone, or a portable information terminal employing the above-mentioned display device.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of a light emitting device in accordance with the present invention.

FIG. 2 is a block diagram of a light emitting device in accordance with the present invention.

FIG. 3 is a block diagram of a light emitting device in accordance with the present invention.

FIG. 4 is a block diagram of a light emitting device in accordance with the present invention.

FIG. 5 is a diagram for illustrating connection of a monitoring light emitting element of a light emitting device in accordance with the present invention.

FIG. 6 is a diagram for illustrating a pixel portion of a light emitting device in accordance with the present invention.

FIG. 7 is an expanded diagram of a pixel of a light emitting device in accordance with the present invention.

FIG. 8 is a diagram for illustrating a driving method of a light emitting device in accordance with the present invention.

FIG. 9 is a block diagram of a light emitting device in accordance with the present invention.

FIG. 10 is a diagram for illustrating a pixel portion of a light emitting device in accordance with the present invention.

FIG. 11 is an expanded diagram of a pixel of a light emitting device in accordance with the present invention.

FIG. 12 is a diagram for illustrating a driving method of a light emitting device in accordance with the present invention.

FIG. 13 is a circuit diagram of a source signal line driver circuit of a light emitting device in accordance with the present invention.

FIG. 14 is a partial plan view of a latch (A).

FIGS. 15A and 15B are circuit diagrams of a switching circuit.

FIG. 16 is an equivalent circuit diagram of an analog switch.

FIG. 17 is a circuit diagram of a source signal line driver circuit of a light emitting device in accordance with the present invention.

FIGS. 18A and 18B are circuit diagrams of a clock signal control circuit, a timing signal control circuit, and a start pulse signal control circuit.

FIG. 19 is a circuit diagram of a source signal line driver circuit of a light emitting device in accordance with the present invention.

FIG. 20 is a circuit diagram of a source signal line driver circuit of a light emitting device in accordance with the present invention.

FIG. 21 is a diagram for illustrating connection of a monitoring light emitting element of a light emitting device in accordance with the present invention.

FIG. 22 is a circuit diagram of an adding circuit.

FIGS. 23A through 23D are cross-sectional views for illustrating various steps of a fabricating method of a light emitting device.

FIGS. 24A through 24C are cross-sectional views for illustrating various steps of a fabricating method of a light emitting device.

FIGS. 25A through 25C are cross-sectional views for illustrating various steps of a fabricating method of a light emitting device.

FIGS. 26A and 26B are cross-sectional views for illustrating various steps of a fabricating method of a light emitting device.

FIGS. 27A and 27B are diagram for illustrating electronic apparatuses each employing a light emitting device in accordance with the present invention.

FIGS. 28A through 28F are diagram for illustrating electronic apparatuses each employing a light emitting device in accordance with the present invention.

FIGS. 29A and 29B show a connection of a light emitting element for a monitor of the light emitting device of the present invention, and a characteristic in measurement values of brightness due to temperatures of the light emitting element, respectively.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[Embodiment Mode 1]

A first structure in accordance with the present invention will be now described. FIG. 1 shows a block diagram of a light emitting device having the first structure in accordance with the present invention.

Reference numeral 101 denotes a pixel portion in which a plurality of pixels are provided in matrix. Reference numerals 102 and 103 denote a source signal line driver circuit and a gate signal line driver circuit, respectively.

The source signal line driver circuit 102 includes a shift register 102-1, a latch (A) 102-2, a latch (B) 102-3, and a switching circuit 102-4. It should be noted that the source signal line driver circuit of the present invention may further include a level shift, a buffer or the like, in addition to the components mentioned above.

Although not illustrated, the gate signal line driver circuit 103 includes a shift register and a buffer. In some cases, the gate signal line driver circuit 103 may further include a level shift in addition to the shift register and the buffer. Gate electrodes of pixel TFTs in one row are connected to one gate signal line, and therefore, all of the pixels TFTs in one row have to be simultaneously turned on. Accordingly, a buffer capable of allowing a large current to flow therethrough is used.

In the source signal line driver circuit **102**, a clock signal (CLK) and a start pulse (SP) are input into the shift register **102-1**. The shift register **102-1** sequentially generates a timing signal based on these clock signal (CLK) and start pulse (SP) and supplies the generated timing signal sequentially to a circuit in the succeeding stage.

The timing signal to be output from the shift register **102-1** may be sequentially supplied to the circuit in the succeeding stage through a buffer or the like (not illustrated). The timing signal from the shift register **102-1** is buffered and amplified by the buffer or the like. Since a number of circuits or elements are connected to a wiring to which the timing signal is to be supplied, a large load capacitance (parasitic capacitance) exists. In order to prevent a rising edge or a trailing edge of the timing signal from being rounded due to such a large load capacitance, the above-mentioned buffer is provided.

The timing signal output from the shift register **102-1** is supplied to the latch (A) **102-2**. The latch (A) **102-2** includes latches in multiple stages for processing an n-bit digital video signal. When the timing signal is input to the latch (A) **102-2**, it sequentially takes in the n-bit digital video signal to be externally supplied to the source signal line driver circuit **102** and held them therein.

When the digital video signal is taken in into the latch (A) **102-2**, the digital video signal may be sequentially input into the latches in the multiple stages included in the latch (A) **102-2**. However, the present invention is not limited to such a structure. A so-called division driving may be performed in which the latches in the multiple stages included in the latch (A) **102-2** are divided into several groups and the digital video signal is input every group in parallel and simultaneously. In such a case, the number of the groups is referred to as the division number. For example, in the case where the latches are divided into four groups, it can be said that the device is driven through the quarter-division scheme.

A time period required for completing all of the writing of the digital video signal into the latches in all of the stages of the latch (A) **102-2** is referred to as a line period. More specifically, the line period refers to a time period measured from a timing when the writing of the digital video signal into the latch in the leftmost stage in the latch (A) **102-2** starts until a timing when the writing of the digital video signal into the latch in the rightmost stage ends. In practice, the line period may include a horizontal blanking period in addition to the above-described line period.

After the one line period ends, latch signals are supplied to the latch (B) **102-3**. At this moment, the digital video signal that has been written into and held at the latch (A) **102-2** is simultaneously sent out to the latch (B) **102-3** to be written into latches in all of the stages of the latch (B) **102-3** and held therein.

Further digital video signal to be externally supplied to the source signal line driver circuit **102** is again sequentially written, based on the timing signal from the shift register **102-1**, into the latch (A) **102-2** from which the previous digital video signal was sent out to the latch (B) **102-3**.

During the second turn of the one line period, the digital video signal that has been written into and held at the latch (B) **102-3** is simultaneously sent out to the switching circuit **102-4**. The switching circuit **102-4** causes the polarity of the digital video signal input from the latch (B) **102-3** to be inverted, or alternatively allows the polarity of those digital video signal not to be inverted, in accordance with shift signals, and outputs the resultant signals.

The digital video signal includes information of either "0" or "1". The digital video signal corresponding to "0" is a

signal having a Hi potential, while the digital video signal corresponding to "1" is a signal having a Lo potential, or vice versa. The inversion of the polarity of the digital video signal means that the digital video signal having information of "0" is converted into that having information of "1", while the digital video signal having information of "1" is converted into that having information of "0".

The shift signal is a signal to be used for selecting whether the polarity of the digital video signal input from the latch (B) **102-3** is to be inverted or not. The polarity of the digital video signal is inverted by the shift signal when an average of a time period during which all of the light emitting elements emit light in one frame period becomes longer than a half of a time period during which the light emitting elements emit light in one frame period in the case where the totally white is to be displayed in the pixel portion **101**, thereby resulting in power consumption being reduced. On the other hand, when an average of the time period during which all of the light emitting elements emit light in one frame period becomes shorter than a half of the time period during which the light emitting elements emit light in one frame period in the case where the totally white is to be displayed in the pixel portion **101**, the polarity of the digital video signal is not allowed to be inverted in accordance with the shift signal, for the purpose of suppressing the power consumption.

Whether the polarity of the digital video signal should be inverted or not in accordance with the shift signal may be chosen by a user, or alternatively, may be automatically chosen based on an image to be displayed.

The digital video signal output from the switching circuit **102-4** is input into the source signal lines.

On the other hand, in the gate signal line driver circuit **103**, a gate signal from a shift register (not illustrated) is input into a buffer (not illustrated), and further input into a corresponding gate signal line (also referred to as a scanning line).

In accordance with the gate signal input into the gate signal line, the digital video signal input into the source signal lines is input into the pixels.

In the above description, the source signal line driver circuit **102** and the gate signal line driver circuit **103** may be provided on the same substrate as the pixel portion **101**. Alternatively, those driver circuits **102** and **103** may be provided on an IC chip and connected to the pixel portion **101** via some techniques such as FPC or TAB.

In accordance with the above-mentioned structure of the present embodiment of the invention, in the case where the light emitting device for performing a digitally-driven time-divisional gradation display displays a monochrome image, the contrast of an image can be inverted based on natures of the image to be displayed in the pixel portion. More specifically, the contrast of the image to be displayed in the pixel portion is inverted when an average of a time period during which all of the light emitting elements emit light in one frame period becomes longer than a half of a time period during which the light emitting elements emit light in one frame period in the case where the totally white is to be displayed in the pixel portion **101**. On the other hand, when an average of the time period during which all of the light emitting elements emit light in one frame period becomes shorter than a half of the time period during which the light emitting elements emit light in one frame period in the case where the totally white is to be displayed in the pixel portion **101**, it is desirable that the contrast of the image to be displayed in the pixel portion is not allowed to be inverted.

In the above description of the present embodiment, the switching circuit is included in the source signal line driver

circuit. Alternatively, it is acceptable that the switching circuit is not included in the source signal line driver circuit.

In the present embodiment mode, only the situation where the digital video signal is employed has been described. Alternatively, the present invention may be applied to the case where an analog video signal is used instead of the digital video signal.

Accordingly, the magnitude of a current to flow through the light emitting element can be suppressed to some extent in accordance with the first structure of the present invention, thereby resulting in the power consumption of the resultant light emitting device being suppressed.

[Embodiment Mode 2]

A second structure in accordance with the present invention will be now described. FIG. 2 shows a block diagram of a light emitting device having the second structure in accordance with the present invention. In FIG. 2, the same components as shown in FIG. 1 are designated with the same reference numerals.

The light emitting device in the present embodiment mode employs a clock signal control circuit 106 which allows a constant electrical potential instead of the clock signal (CLK) to be applied to the shift register 102-1.

More specifically, the light emitting device is configured to input a constant electrical potential (fixed electrical potential) into the shift register 102-1, instead of the clock signal, for a constant time period by means of the clock signal control circuit 106. The above structure prevents the timing signal that is to be used for inputting the digital video signal at less significant bits in the range from the first bit to the m-th bit (m is any integer in the range from 1 to n) into the latch (A) 102-2 from being input into the latch (A) 102-2. Accordingly, only the digital video signal at more significant bits in the range from the (m+1)-th bit to the n-th bit can be written into the latch (A) 102-2.

The light emitting device in the present embodiment mode is different from that shown in FIG. 1 in that the source signal line driver circuit 102 does not include the switching circuit 102-4. Accordingly, the digital video signal that has been written into and held at the latch (B) 102-3 is input into the source signal lines by means of the latch signal to be input into the latch (B) 102-3.

In accordance with the present embodiment mode, in the light emitting device that performs a digitally-driven time-divisional gradation display, the digital video signal input into the source signal line driver circuit contained in the light emitting device is input into the pixel portion after the number of bits thereof is reduced. More specifically, the number of bits of the digital video signal to be input into the pixel portion is reduced by sequentially cutting off a bit of the digital video signal from the least significant bit.

In accordance with the above-described structure, the number of bits of the digital video signal to be input into the pixel portion is reduced, and therefore, the required number of writing the digital video signal into the pixels by means of the source signal line driver circuit and the gate signal line driver circuit can be reduced. Thus, the power consumption of the source signal line driver circuit and the gate signal line driver circuit can be suppressed, thereby resulting in the power consumption of the light emitting device being suppressed.

It should be noted that in the present embodiment mode, the clock signal control circuit 106 may be provided on the same substrate as the pixel portion 101, or alternatively, may be formed in an IC chip.

[Embodiment Mode 3]

Another example of the second structure in accordance with the present invention, which is different from the one described in Embodiment Mode 2, will be now described.

FIG. 3 shows a block diagram of a light emitting device having the second structure in accordance with the present invention. In FIG. 3, the same components as shown in FIG. 1 are designated with the same reference numerals.

The light emitting device in the present embodiment mode employs a timing signal control circuit 107 which allows a constant electrical potential, instead of the timing signal output from the shift register 102-1, to be applied to the latch (A) 102-2.

More specifically, the light emitting device is configured to input a constant electrical potential (fixed electrical potential) into the latch (A) 102-2, instead of the timing signal output from the shift register 102-1, for a constant time period by means of the timing signal control circuit 107. The above structure prevents the timing signal that is to be used for inputting the digital video signal at less significant bits in the range from the first bit to the m-th bit (m is any integer in the range from 1 to n) into the latch (A) 102-2 from being input into the latch (A) 102-2. Accordingly, only the digital video signal at more significant bits in the range from the (m+1)-th bit to the n-th bit can be written into the latch (A) 102-2.

It should be noted that in the present embodiment mode, the fixed electrical potential is required to be at such a level that prevents the digital video signal from being written into the latch (A) 102-2.

In accordance with the present embodiment mode, in the light emitting device that performs a digitally-driven time-divisional gradation display, the digital video signal input into the source signal line driver circuit contained in the light emitting device is input into the pixel portion after the number of bits thereof is reduced. More specifically, the number of bits of the digital video signal to be input into the pixel portion is reduced by sequentially cutting off the bit of the digital video signal from the least significant bit.

In accordance with the above-described structure, the number of bits of the digital video signal to be input into the pixel portion is reduced, and therefore, the required number of writing the digital video signal into the pixels by means of the source signal line driver circuit and the gate signal line driver circuit can be reduced. Thus, the power consumption of the source signal line driver circuit and the gate signal line driver circuit can be suppressed, thereby resulting in the power consumption of the light emitting device being suppressed.

It should be noted that in the present embodiment mode, the timing signal control circuit 107 may be provided on the same substrate as the pixel portion 101, or alternatively, may be formed in an IC chip.

[Embodiment Mode 4]

Still another example of the second structure in accordance with the present invention, which is different from the ones described in Embodiment Modes 2 and 3, will be now described. FIG. 4 shows a block diagram of a light emitting device having the second structure in accordance with the present invention. In FIG. 4, the same components as shown in FIG. 1 are designated with the same reference numerals.

The light emitting device in the present embodiment mode employs a start pulse signal control circuit 108 which allows a constant electrical potential, instead of the start pulse signal (SP), to be applied to the shift register 102-1.

More specifically, the light emitting device is configured to input a constant electrical potential (fixed electrical potential) into the shift register 102-1, instead of the start pulse signal, for a constant time period by means of the start pulse signal control circuit 108, so that the timing signal that is to be used for inputting the digital video signal at less significant bits in the range from the first bit to the m-th bit (m is any integer in

the range from 1 to n) into the latch (A) 102-2 is prevented from being input into the latch (A) 102-2. Accordingly, only the digital video signal at more significant bits in the range from the (m+1)-th bit to the n-th bit can be written into the latch (A) 102-2.

It should be noted that in the present embodiment mode, the fixed electrical potential is required to be at such a level that prevents the timing signal from being output from the shift register 102-1.

In accordance with the present embodiment mode, in the light emitting device that performs a digitally-driven time-divisional gradation display, the digital video signal input into the source signal line driver circuit contained in the light emitting device is input into the pixel portion after the number of bits thereof is reduced. More specifically, the number of bits of the digital video signal to be input into the pixel portion is reduced by sequentially cutting off the bit of the digital video signal from the least significant bit.

In accordance with the above-described structure, the number of bits of the digital video signal to be input into the pixel portion is reduced, and therefore, the required number of writing the digital video signal into the pixels by means of the source signal line driver circuit and the gate signal line driver circuit can be reduced. Thus, the power consumption of the source signal line driver circuit and the gate signal line driver circuit can be suppressed, thereby resulting in the power consumption of the light emitting device being suppressed.

It should be noted that in the present embodiment mode, the start pulse signal control circuit 108 may be provided on the same substrate as the pixel portion 101, or alternatively, may be formed in an IC chip. [Embodiment Mode 5]

A third structure in accordance with the present invention will be now described with reference to FIG. 5.

In FIG. 5, reference numeral 501 denotes a power source line. In the present specification, the power source line refers to a wiring to be used for applying a predetermined electrical potential to a pixel electrode contained in a light emitting element in a pixel section by means of the digital video signal to be input into a source signal line. In the present specification, the electrical potential of the power source line is referred to as the power source potential.

Reference numeral 502 denotes a buffer amplifier, reference numeral 503 denotes a monitoring light emitting element, and reference numeral 504 denotes a constant current source. One of electrodes of the monitoring light emitting element 503 is connected to the constant current source 504, so that a constant current always flows through the monitoring light emitting element 503. When a temperature of an organic compound layer contained in the light emitting element changes, the magnitude of the current to flow through the monitoring light emitting element 503 does not change, but rather, an electrical potential of the electrode of the monitoring light emitting element 503 connected to the constant current source 504 changes.

On the other hand, the buffer amplifier 502 includes two input terminals and one output terminal. One of the two input terminals is a non-inverted input terminal (+), while the other is an inverted input terminal (-). An electrical potential at one of electrodes of the monitoring light emitting element 503 is supplied to the buffer amplifier 502.

The buffer amplifier 502 is a circuit for preventing an electrical potential at a pixel electrode of the monitoring light emitting element 503 connected to the constant current source 504 changes in accordance with a load such as a wiring capacitance of the power source line 501 or the like. Accordingly, the electrical potential provided to the non-inverted

input terminal of the buffer amplifier 502 is output from an output terminal to be supplied to the power source line as the power source potential, without being changed in accordance with a load such as a wiring capacitance of the power source line 501 or the like.

Accordingly, even when a temperature of the monitoring light emitting element 503 or the organic compound layer of the light emitting element in the pixel portion changes due to a change in an environmental temperature, the power source potential is changed so as to allow a constant current to flow through the light emitting element. Thus, even when the environmental temperature of the light emitting device increases, power consumption of the light emitting device can be prevented from increasing.

In the present embodiment mode, the buffer amplifier 502, the monitoring light emitting element 503, and the constant current source 504 may be provided on the same substrate as the pixel portion, or alternatively, may be formed in an IC chip. Moreover, the monitoring light emitting element 503 may be included in the pixel portion, or alternatively, may be provided independently of the pixel portion.

The present invention can suppress power consumption of a light emitting device and an electronic apparatus employing the light emitting device in accordance with the above-described first through third structures. It should be noted that only either one of the first through third structures is required to be included in the present invention, although two or all of the first through third structures may be included.

The present invention can allow power consumption of the light emitting device to be suppressed by means of the above-described three structures.

Embodiments

Several embodiments will be described below.

[Embodiment 1]

In the present embodiment, the structure of a pixel portion of a light emitting device and its driving method in accordance with the present invention will be described.

FIG. 6 shows an expanded view of the pixel portion 301 of the light emitting device in accordance with the present embodiment of the invention. Source signal lines (S1 to Sx), power source lines (V1 to Vx), and gate signal lines (G1 to Gy) are provided in the pixel portion 301.

In the present embodiment, a pixel 304 refers to a region in which one of the source signal lines (S1 to Sx), one of the power source lines (V1 to Vx), and one of the gate signal lines (G1 to Gy) are provided. In the pixel portion 301, a plurality of the pixels 304 are arranged in matrix.

An expanded view of the pixel 304 is shown in FIG. 7. In FIG. 7, reference numeral 305 denotes a switching TFT. A gate electrode of the switching TFT 305 is connected to the gate signal line G (G1 to Gx). One of a source region and a drain region of the switching TFT 305 is connected to the source signal line S (S1 to Sx), while the other thereof is connected to a gate electrode 306 of a current-controlling TFT 306 as well as to a capacitor 308 of each pixels.

The capacitor 308 is provided for holding a gate potential of the current-controlling TFT 306 (an electrical potential difference between the gate electrode and the source region) when the switching TFT 305 is in the non-selected condition (off condition). Although the capacitor 308 is provided in the present embodiment, the present invention is not limited to such a structure. The capacitor 308 may be omitted.

One of the source region and the drain region of the current-controlling TFT 306 is connected to the power source line V (V1 to Vx), while the other is connected to the light emitting element 307. The power source line V is connected to the capacitor 308.

The light emitting element 307 is composed of an anode, a cathode, and an organic compound layer provided between the anode and the cathode. In the case where the anode is connected to the source region or the drain region of the current-controlling TFT 306, the anode functions as the pixel electrode and the cathode functions as a counter electrode. On the other hand, in the case where the cathode is connected to the source region or the drain region of the current-controlling TFT 306, the cathode functions as the pixel electrode and the anode functions as the counter electrode.

A counter potential is supplied to the counter electrode of the light emitting element 307. In addition, the power source potential is supplied to the power source line V. The power source potential and the counter potential are supplied to the light emitting device of the present invention by means of a power source provided by an externally-attached IC chip or the like.

The switching TFT 305 and the current-controlling TFT 306 may be either of the n-channel type TFT or the p-channel type TFT. It should be noted, however, that in the case where the source region or the drain region of the current-controlling TFT 306 is connected to the anode of the light emitting element 307, it is preferable that the current-controlling TFT 306 is the p-channel type TFT. On the other hand, in the case where the source region or the drain region of the current-controlling TFT 306 is connected to the cathode of the light emitting element 307, it is preferable that the current-controlling TFT 306 is the n-channel type TFT.

The switching TFT 305 and the current-controlling TFT 306 may have a multi-gate structure such as a double gate structure, a triple gate structure or the like, rather than a single gate structure.

Then, a driving method of the light emitting device of the present invention that includes the above-mentioned structure will be described with reference to FIG. 8.

First, the power source potential of the power source line becomes to be equal to an electrical potential of the counter electrode of the light emitting element. Then, a gate signal is input from the gate signal line driver circuit to the gate signal line G1. As a result, the switching TFTs 305 of all of the pixels connected to the gate signal line G1 (i.e., the pixels in the first row) are placed in the ON state.

Simultaneously, the digital video signal at the first bit is input from the source signal line driver circuit into the source signal lines (S1 to Sx). The digital video signal is input to the gate electrode of the current-controlling TFT 306 via the switching TFT 305.

Then, at the same time when the input of the gate signal into the G1 is completed, the similar gate signal is input into the next gate signal line G2. Thus, the switching TFTs 305 of all of the pixels connected to the gate signal line G2 (i.e., the pixels in the second row) are placed in the ON state, thereby the digital video signal at the first bit is input from the source signal lines (S1 to Sx) into the pixels in the second row.

Thereafter, the gate signal is sequentially input to all of the gate signal lines (G1 to Gx). A time period required for selecting all of the gate signal lines (G1 to Gx) and inputting the digital video signal at the first bit into the pixels in all of the rows is a writing period Ta1.

When the writing period Ta1 is completed, a light emitting period Tr1 then starts. During the light emitting period Tr1, the power source potential of the power source line comes to be at such a potential level that provides a potential difference with respect to the counter electrode, so that the light emitting element can emit light when the power source potential is supplied to the pixel electrode of the light emitting element.

In the present embodiment, in the case where the digital video signal has information of "0", the current-controlling TFT 306 is in the OFF state. Accordingly, the power source potential is not supplied to the pixel electrode of the light emitting element 307. As a result, the light emitting element 307 included in the pixel to which the digital video signal having information of "0" is supplied does not emit light.

On the other hand, in the case where the digital video signal has information of "1", the current-controlling TFT 306 is in the ON state. Accordingly, the power source potential is supplied to the pixel electrode of the light emitting element 307. As a result, the light emitting element 307 included in the pixel to which the digital video signal having information of "1" is supplied emits light.

Thus, during the display period Tr1, the light emitting element 307 is placed either in the emission state or the non-emission state, so that all of the pixels perform a display operation. A time period during which the pixel performs the display operation is referred to as a display period Tr. More specifically, the display period that starts when the digital video signal at the first bit is input into the pixel is referred to as Tr1. In FIG. 8, only the display period of the pixels in the first row is illustrated for the purpose of simplification of the description. Timings at which the respective display periods for all of the rows start are the same.

When the display period Tr1 is completed, a next writing period Ta2 starts, and the power source potential of the power source line comes to be equal to the electrical potential of the counter electrode of the light emitting element. Similarly in the case of the writing period Ta1, all of the gate signal lines are sequentially selected, and the digital video signal at the second bit is input into all of the pixels. A time period required for completing the input of the digital video signal at the second bit into the pixels in all of the rows is referred to as a writing period Ta2.

When the writing period Ta2 is completed, a display period Tr2 then starts, and the power source potential of the power source line comes to be at such a potential level that provides a potential difference with respect to the counter electrode, so that the light emitting element can emit light when the power source potential is supplied to the pixel electrode of the light emitting element. Thus, all of the pixels perform the display operation.

The above-described operations are repeated until the digital video signal at the n-th bit is input into the pixels, so that the writing period Ta and the display period Tr appear alternately. After all of the display periods (Tr1 to Trn) are completed, one image can be displayed. In the driving method in accordance with the present invention, a time period required for displaying one image is referred to as one frame period (F). After a certain one frame period (F) is completed, the next one frame period is started. The writing period Ta1 again appears, and the above-described operations are repeated.

In a normal light emitting device, it is preferable to provide 60 or more frame periods per one second. If the number of images to be displayed in one second is smaller than 60, flickering of the image may become visually significant.

In the present embodiment, it is necessary that the sum of all of the writing periods is shorter than one frame period and ratios among the respective display periods are set to satisfy the relationship of $Tr1:Tr2:Tr3: \dots :Tr(n-1):Trn=2^0:2^1:2^2: \dots :2^{(n-2)}:2^{(n-1)}$. Through the combination of the display periods, a desired gradation display among the total of 2^n gradations can be realized.

The gradation to be displayed by a particular pixel in a certain one frame period is determined by obtaining the sum of the display periods during which the light emitting element

emits light in that frame period. For example, assuming that $n=8$ and the brightness obtained when the pixel emits light in all of the display periods is expressed as 100%, the brightness of 1% can be realized in the case where the pixel emits light in Tr1 and Tr2, while the brightness of 60% can be realized

when Tr3, Tr5, and Tr8 are selected. The display periods Tr1 through Trn may appear on any order. For example, during, one frame period, the display periods may be controlled to appear in such an order that Tr1 is followed by Tr3, Tr5, Tr2,

Although the level of the power source potential at the power source line is changed by means of the writing period and the display period in the above description of the present embodiment, the present invention is not limited thereto. A potential difference which allows the light emitting element to emit light when the power source potential is supplied to the pixel electrode of the light emitting element may be controlled to always exist between the power source potential and the electrical potential at the counter electrode. In such a case, the light emitting element can emit light even in the writing period. Accordingly, the gradation to be displayed by a particular pixel in a certain frame period is determined by the sum of the writing periods and the display periods during which the light emitting element emits light in that frame period. In this case, it is necessary that the sum of the writing periods and the display periods corresponding to the digital video signal at the respective bits is set to satisfy the relationship of $(Ta1+Tr1):(Ta2+Tr2):(Ta3+Tr3): \dots : (Ta(n-1)+Tr(n-1)):(Tan+Trn)=2^0:2^1:2^2: \dots : 2^{(n-2)}:2^{(n-1)}$. [Embodiment 2]

In the present embodiment, another example of the structure of a pixel portion of a light emitting device and its driving method in accordance with the present invention, different from those in the Embodiment 1, will be described.

FIG. 9 shows an exemplary block diagram of a light emitting device in the present embodiment. The light emitting device in FIG. 9 includes a pixel portion 901 by TFT formed on the substrate and includes a source signal side driver circuit 902, a writing gate signal side driver circuit (first gate signal line driver circuit) 903a, and an erasure gate signal line driver circuit (second gate signal line driver circuit) 903b, each provided in the periphery of the pixel portion. Although the light emitting device with one source signal side driver circuit is described in the present embodiment, two of the source signal side driver circuits may be provided.

The source signal side driver circuit 902 has at least one of the first through third structures of the present invention described previously.

In the present embodiment, the source signal line driver circuit 902 and the writing gate signal side driver circuit 903a and the erasure gate signal line driver circuit 903b may be provided on the same substrate as the pixel portion 901, or alternatively, may be formed on an IC chip and connected to the pixel portion 901 via a certain connector such as FPC, TAB or the like.

An expanded view of the pixel portion 901 is shown in FIG. 10. In FIG. 10, source signal lines (S1 to Sx), power source lines (V1 to Vx), and writing gate signal lines (first gate signal lines) (Ga1 to Gay), and erasure gate signal lines (second gate signal lines) (Ge1 to Gey) are provided in the pixel portion 901.

The pixel 904 refers to a region in which one of the source signal lines (S1 to Sx), one of the power source lines (V1 to Vx), one of the writing gate signal lines (Ga1 to Gay), and one of the erasure gate signal lines (Ge1 to Gey) are provided. In the pixel portion 901, a plurality of the pixels 904 are arranged in matrix.

An expanded view of the pixel 904 is shown in FIG. 11. In FIG. 11, reference numeral 907 denotes the switching TFT. A gate electrode of the switching TFT 907 is connected to the gate signal line Ga (Ga1 to Gay). One of a source region and a drain region of the switching TFT 907 is connected to the source signal line S (S1 to Sx), while the other thereof is connected to a gate electrode of a current-controlling TFT 908 as well as to a capacitor 912 and source and drain regions of an erasure TFT 909 included in each pixels.

The capacitor 912 is provided for holding a gate potential of the current-controlling TFT 908 when the switching IF 907 is in the non-selected condition (off condition). Although the capacitor 912 is provided in the present embodiment, the present invention is not limited to such a structure. The capacitor 912 may be omitted.

One of the source region and the drain region of the current-controlling TFT 908 is connected to the power source line V (V1 to Vx), while the other thereof is connected to the light emitting element 910. The power source line V is connected to the capacitor 912.

One of the source region and the drain region of the erasure TFT 909 that is not connected to the source or drain region of the switching TFT 907 is connected to the power source line V. A gate electrode of the erasure TFT 909 is connected to the erasure gate signal line Ge.

The light emitting element 910 is composed of an anode, a cathode, and an organic compound layer provided between the anode and the cathode. In the case where the anode is connected to the source region or the drain region of the current-controlling TFT 908, the anode functions as the pixel electrode and the cathode functions as a counter electrode. On the other hand, in the case where the cathode is connected to the source region or the drain region of the current-controlling TFT 908, the cathode functions as the pixel electrode and the anode functions as the counter electrode.

A counter potential is supplied to the counter electrode 911 of the light emitting element 910. In addition, the power source potential is supplied to the power source line V. A potential difference between the counter potential and the power source potential is always maintained at such a level that causes the light emitting element to emit light when the power source potential is applied to the pixel electrode. The power source potential and the counter potential are supplied to the light emitting device of the present invention by means of a power source provided by an externally-attached IC chip or the like.

In the typical light emitting device to date, when the amount of light emission per unit light emission area of a pixel is 200 cd/m², a current of several mA/cm² per unit area of a pixel portion is required to flow. Thus, especially with a larger display area, it becomes difficult to control the magnitude of the electrical potential to be supplied from the power source provided in the IC chip by means of a switch. In the present embodiment, the power source potential and the counter potential are always maintained to be constant, and therefore, the magnitude of the electrical potential to be supplied from the power source provided in the IC chip is not required to be controlled by means of a switch. Accordingly, the present embodiment is useful for realizing a panel having a larger display size.

The switching TFT 907, the current-controlling TFT 908, and the erasure TFT 909 may be either of the n-channel type TFT or the p-channel type TFT. It should be noted, however, that in the case where the source region or the drain region of the current-controlling TFT 908 is connected to the anode of the light emitting element 910, it is preferable that the current-controlling TFT 908 is the p-channel type TFT. On the other

hand, in the case where the source region or the drain region of the current-controlling TFT 908 is connected to the cathode of the light emitting element 910, it is preferable that the current-controlling TFT 908 is the n-channel type TFT.

The switching TFT 907, the current-controlling TFT 908, and the erasure TFT 909 may have a multi-gate structure such as a double gate structure, a triple gate structure or the like, rather than a single gate structure.

Then, a driving method of the light emitting device of the present invention that includes the above-mentioned structure will be described with reference to FIG. 12.

First, a writing gate signal is input from the writing gate signal line driver circuit 903a to the writing gate signal line Ga1, and thus, the switching TFTs 907 of all of the pixels connected to the writing gate signal line Ga1 (i.e., the pixels in the first row) are placed in the ON state. In the present specification, when all of the TFTs having a gate electrode connected to a certain signal line, the signal line is referred to as being selected. Thus, in the above-described case, the writing gate signal line Ga1 is being selected.

Simultaneously, the digital video signal at the first bit is input from the source signal line driver circuit 902 into the source signal lines (S1 to Sx). More specifically, the digital video signal is input to the gate electrode of the current-controlling TFT 908 via the switching TFT 907.

In the present embodiment, in the case where the digital video signal has information of "0", the current-controlling TFT 908 is in the OFF state. Accordingly, the power source potential is not supplied to the pixel electrode of the light emitting element 910. As a result, the light emitting element 910 included in the pixel to which the digital video signal having information of "0" is supplied does not emit light.

On the other hand, in the case where the digital video signal has information of "1", the current-controlling TFT 908 is in the ON state. Accordingly, the power source potential is supplied to the pixel electrode of the light emitting element 910. As a result, the light emitting element 910 included in the pixel to which the digital video signal having information of "1" is supplied emits light.

Thus, at the same time when the digital video signal is input into the pixels in the first row, the light emitting element is placed either in the emission state or the non-emission state, so that all of the pixels in the first row perform a display operation. A time period during which the pixel performs the display operation is referred to as a display period Tr. More specifically, the display period that starts when the digital video signal at the first bit is input into the pixel is referred to as Tr1. In FIG. 12, only the display period of the pixels in the first row is illustrated for the purpose of simplification of the description. Timings at which the display periods for the respective rows start are offset from each other by a certain time difference.

Then, at the same time when the selection of the Ga1 is completed, the next writing gate signal line Ga2 is selected by the writing gate signal. Thus, the switching TFTs 907 of all of the pixels connected to the writing gate signal line Ga2 are placed in the ON state, thereby the digital video signal at the first bit is input from the source signal lines (S1 to Sx) into the pixels in the second row.

Thereafter, all of the writing gate signal lines (Ga1 to Gax) are sequentially selected. A time period required for selecting all of the writing gate signal lines (Ga1 to Gax) and inputting the digital video signal at the first bit into the pixels in all of the rows is a writing period Ta1.

On the other hand, before the digital video signal at the first bit is input into the pixels in all of the rows, in other words, before the writing period Ta1 is completed, the erasure gate

signal line Ge1 is selected by an erasure gate signal to be input from the erasure gate signal line driver circuit 903b, in parallel to the input of the digital video signal of the first bit into the pixels.

When the erasure gate signal line Ge1 is selected, the erasure TFTs 909 in all of the pixels connected to the erasure gate signal line Ge1 (the pixels in the first row) are placed in the ON state. Thus, the power source potential of the power source line (V1 to Vx) is supplied to the gate electrodes of the current-controlling TFTs 908 in the pixels in the first row.

When the power source potential is supplied to the gate electrodes of the current-controlling TFTs 908, the current-controlling TFTs 908 are placed in the OFF state. Thus, the power source potential is not supplied to the pixel electrodes of the light emitting elements 910, so that all of the light emitting elements included in the pixels in the first row are placed in the non-emission state. Thus, the pixels in the first row do not perform a display operation. In other words, the digital video signal that has been held at the gate electrode of the current-controlling TFT since the selection of the writing gate signal line Ga1 is erased when the power source potential is supplied to the gate electrode of the current-controlling TFT. Thus, the pixels in the first row do not perform a display operation.

A time period during which the pixel does not perform a display operation is referred to as a non-display period Td. The display period Tr1 for the pixels in the first row is completed simultaneously when the erasure gate signal is input into the erasure gate signal line Ge1, and the non-display period Td1 starts.

In FIG. 12, only the non-display period for the pixels in the first row is particularly illustrated for the purpose of simplification of the description. Timings at which the non-display periods for the respective rows start are offset from each other by a certain time difference.

Then, at the same time when the selection of the Ge1 is completed, the next erasure gate signal line Ge2 is selected by the erasure gate signal. Thus, the erasure TFTs 909 of all of the pixels connected to the erasure gate signal line Ge2 (the pixels in the second row) are placed in the ON state. The power source potential of the power source lines (V1 to Vx) is supplied to the gate electrode of the current-controlling TFT 908 via the erasure TFT 909. When the power source potential is supplied to the gate electrode of the current-controlling TFT 908, the current-controlling TFT 908 is placed in the OFF state. Thus, the power source potential is not supplied to the pixel electrode of the light emitting element 910, so that all of the light emitting elements included in the pixels in the second row are placed in the non-emission state. Thus, the pixels in the second row do not perform a display operation and are placed in the non-display state.

Then, all of the erasure gate signal lines are sequentially selected by the erasure gate signal. A time period required for selecting all of the erasure gate signal lines (Ga1 to Gax) and erasing the digital video signal at the first bit held in the pixels in all of the rows is referred to as the erasure period Te1.

On the other hand, before the digital video signal at the first bit held in the pixels in all of the rows is erased, in other words, before the erasure period Te1 is completed, the writing gate signal line Ga1 is again selected, in parallel to the erasure of the digital video signal at the first bit in the pixels. Thus, the pixels in the first row again perform the display operation. The non-display period Td1 is thus completed, and a display period Tr2 starts.

Thereafter, all of the writing gate signal lines are sequentially selected in the similar manner as described before, and the digital video signal at the second bit is input into all of the

pixels. A time period required for inputting the digital video signal at the second bit into the pixels in all of the rows is referred to as a writing period Ta2.

On the other hand, before the digital video signal at the second bit is input into the pixels in all of the rows, in other words, before the writing period Ta2 is completed, the erasure gate signal line Ge2 is selected in parallel to the input of the digital video signal at the second bit into the pixels. Thus, all of the light emitting elements included in the pixels in the first row are placed in the non-emission state. Thus, the pixels in the first row do not perform a display operation. The display period Tr2 for the pixels in the first row is then completed, and the non-display period Td2 starts.

Thereafter, all of the erasure gate signal lines are sequentially selected. A time period required for selecting all of the erasure gate signal lines (Ga1 to Gax) and erasing the digital video signal at the second bit held at the pixels in all of the rows is an erasure period Te2.

The above-described operations are repeated until the digital video signal at the m-th bit is input into the pixels, so that the display period Tr and the non-display period Td appear alternately. The display period Tr1 is a period from the start of the writing period Ta1 until the erasure period Te1 starts. The non-display period Td1 is a period from the start of the erasure period Te1 until the display period Tr2 starts. Similarly as the display period Tr1 and the non-display period Td1, lengths of the display periods Tr2, Tr3, . . . , Tr(m-1) and the non-display periods Td2, Td3, Td(m-1) are defined by means of the writing periods Ta1, Ta2, . . . , Tam and the erasure periods Te1, Te2, . . . , Te(m-1).

After the digital video signal at the m-th bit has been input into the pixels in the first row, the erasure gate signal line Ge1 is not selected. For the purpose of simplification of the description, the case with $m=n-2$ is described as an example in the present embodiment. However, the present invention is not limited to such a case. In the present invention, as the value of m, any number in the range from 2 to n can be arbitrarily selected.

When the digital video signal at the (n-2)-th bit is input into the pixels in the first row, the pixels in the first row are placed in the display period Tr(n-2) to perform a display operation. Until the next digital video signal at the next bit is input, the digital video signal at the (n-2)-th bit is held at the pixels.

When the digital video signal at the (n-1)-th bit is input into the pixels in the first row, the digital video signal at the (n-2)-th bit held at the pixels are rewritten into the digital video signal at the (n-1)-th. The pixels in the first row are then placed in the display period Tr(n-1) to perform a display operation. Until the next digital video signal at the next bit is input, the digital video signal at the (n-2)-th bit is held at the pixels.

The above-described operations are repeated until the digital video signal at the n-th bit is input into the pixels. The display period Tr(n-2) is a period from the start of the writing period Ta(n-2) until the writing period Ta(n-1) starts. Similarly as the display period Tr(n-2), lengths of the display periods Tr(n-1) and Trn are defined by means of the writing period Ta.

In the present embodiment, it is necessary that the sum of all of the writing periods is shorter than one frame period and ratios among the respective display periods are set to satisfy the relationship of $Tr1:Tr2:Tr3: \dots :Tr(n-1):Trn=2^0:2^1:2^2: \dots :2^{(n-2)}:2^{(n-1)}$. Through the combination of the display periods, a desired gradation display among the total of 2^n gradations can be realized.

After all of the display periods (Tr1 through Trn) are completed, one image can be displayed. In the driving method in accordance with the present invention, a time period required for displaying one image is referred to as one frame period (F).

After a certain one frame period (F) is completed, the digital video signal at the first bit is again input into the pixels, so that the pixels in the first row are again placed in the display period Tr1. The above-mentioned operations are again repeated.

In a normal light emitting device, it is preferable to provide 60 or more frame periods per one second. If the number of images to be displayed in one second is smaller than 60, flickering of the image may become visually significant.

The gradation to be displayed by a particular pixel in a certain one frame period is determined by obtaining the sum of the display periods during which the light emitting element emits light in that frame period. For example, assuming that $n=8$ and the brightness obtained when the pixel emits light in all of the display periods is expressed as 100%, the brightness of 1% can be realized in the case where the pixel emits light in Tr1 and Tr2, while the brightness of 60% can be realized when Tr3, Tr5, and Tr8 are selected.

The writing period Tam during which the digital video signal at the m-th bit is input into the pixels is required to be shorter than the display period Trm. Accordingly, the number of bits in is required to be such a number from 1 to n that can allow the writing period Tam to be shorter than the display period Trm.

The display periods (Tr1 through Trn) may appear on any order. For example, during one frame period, the display periods may be controlled to appear in such an order that Tr1 is followed by Tr4, Tr3, Tr2, It should be noted, however, that the appearing order of the display periods is preferably set so as not to cause the erasure periods (Te1 through Ten) to be overlapped with each other.

In the present embodiment, the display period Tr and the writing period Ta are partially overlapped with each other. In other words, the pixels can perform a display operation even during the writing period. Accordingly, a ratio of the sum of the display periods within one frame period (duty ratio) is not determined only by the length of the writing period.

[Embodiment 3]

In the present embodiment, the structure of the source signal line driver circuit contained in the light emitting device as described in Embodiment 1 will be described in detail. FIG. 13 shows a circuit diagram of the source signal line driver circuit in the present embodiment. In FIG. 13, the same components as those shown in FIG. 1 are designated with the same reference numerals.

Reference numeral 102-1 denotes a shift register, to which a clock signal (CLK), a signal (CLKB) obtained by inverting the polarity of the clock signal, a start pulse signal (SP), a bi-direction shift signal (SL/R) are input through the illustrated wirings, respectively.

Reference numerals 102-2 and 102-3 denote a latch (A) and a latch (B), respectively. In the present embodiment, a combination of the latches (A) 102-2 and a combination of the latches (B) 102-3 corresponds to four source signal lines. However, the number of source signal lines to which a combination of the latches (A) 102-2 and a combination of the latches (B) 102-3 corresponds is not limited to the above number in the present embodiment. In addition, although a level shift for changing a width of a voltage amplitude of a signal is not provided in the present embodiment, such a level shift may be appropriately provided by a designer.

The digital video signal (DV) to be supplied externally to the source signal line driver circuit is input into the latch (A) **102-2** through the illustrated wirings. A latch signal S_LAT and a signal S_LATb obtained by inverting the polarity of the S_LAT are respectively input into the latch (B) **102-3** through the illustrated wirings.

The structure of the latch (A) **102-2** will be described in detail with reference to a portion **801** of the latch (A) **102-2**. The portion **801** of the latch (A) **102-2** includes two clocked inverters and two inverters.

A plan view of the portion **801** of the latch (A) **102-2** is shown in FIG. **14**. Reference numerals **831a** and **831b** respectively denote active layers of TFTs that constitute one of the inverters included in the portion **801** of the latch (A) **102-2**. Reference numeral **836** denotes a common gate electrode of the TFTs that constitute the particular one of the inverters. Reference numerals **832a** and **832b** respectively denote active layers of TFTs that constitute the other one of the inverters included in the portion **801** of the latch (A) **102-2**. Reference numerals **837a** and **837b** denote gate electrodes formed over the active layers **832a** and **832b**, respectively. The gate electrodes **837a** and **837b** are electrically connected to each other.

Reference numerals **833a** and **833b** respectively denote active layers of TFTs that constitute one of the clocked inverters included in the portion **801** of the latch (A) **102-2**. Gate electrodes **838a** and **838b** are provided over the active layer **833a** to form a double gate structure. Similarly, gate electrodes **838b** and **839** are provided over the active layer **833b** to form a double gate structure.

Reference numerals **834a** and **834b** respectively denote active layers of TFTs that constitute the other one of the clocked inverters included in the portion **801** of the latch (A) **102-2**. Gate electrodes **839** and **840** are provided over the active layer **834a** to form a double gate structure. Similarly, gate electrodes **840** and **841** are provided over the active layer **834b** to form a double gate structure.

Reference numeral **102-4** denotes the switching circuit. FIGS. **15A** and **15B** shows circuit diagrams of the switching circuit in accordance with the present embodiment.

The switching circuit **102-4** of the present embodiment as shown in FIG. **15A** includes an inverter **851**, a first analog switch **852**, and a second analog switch **853**. A shift signal SS and a signal SSB obtained by inverting the polarity of the shift signal SS are input through the illustrated wirings.

Equivalent circuit diagrams of the first analog switch **852** and the second analog switch **853** are shown in FIG. **16**. Each of the first analog switch **852** and the second analog switch **853** includes an n-channel type TFT and a p-channel type TFT. A signal to be input from an input terminal (IN) is sampled by means of a signal to be input from a first control input terminal (Vin) or a second control input terminal (Vinb), and the resultant signals is output from an output terminal (OUT).

The digital video signal from the latch (B) **102-3** is input via the inverter **851** into the first analog switch **852** through the input terminal (IN). Simultaneously, the digital video signal from the latch (B) **102-3** is input into the second analog switch **853** through the input terminal (IN).

The shift signal SS and the signal SSB obtained by inverting the polarity of the shift signal SS are input into the first analog switch **852** and the second analog switch **853**, to respectively, through the first control input terminal (Vin) or the second control input terminal (Vinb). The digital video signal is sampled by this shift signal SS, and the sampled digital video signal is output from output terminals (OUT) of the first analog switch **852** and the second analog switch **853**.

The digital video signal input into the switching circuit **102-4** is output therefrom after the polarity thereof is inverted, or alternatively, without having the polarity inverted. The shift signal SS determines whether the polarity of the digital video signal is to be inverted or not in the switching circuit **102-4**.

The switching circuit **102-4** as shown in FIG. **15B** includes an inverter **861**, a first NAND **862**, a second NAND **863**, and NOR **864**. A shift signal SS and a signal SSB obtained by inverting the polarity of the shift signal SS are input through the illustrated wirings.

The digital video signal from the latch (B) **102-3** is provided through the inverter **861**. Simultaneously, the signal SSB obtained by inverting the polarity of the shift signal SS is input into the first NAND **862**.

Simultaneously with the input of the digital video signal into the first NAND **862** through the inverter **861**, the digital video signal is also input into the second NAND **863**. Simultaneously, the shift signal SS is also input into the second NAND **863**.

Signals output from the first NAND **862** and the second NAND **863** are simultaneously input into the NOR **864**. A signal output from the NOR **864** is input into the source signal line.

The digital video signal input into the switching circuit **102-4** is output therefrom after the polarity thereof is inverted, or alternatively, without having the polarity inverted. The shift signal SS determines whether the polarity of the digital video signal is to be inverted or not in the switching circuit **102-4**.

The structure of the switching circuit is not limited to those shown in FIGS. **15A** and **15B**. The switching circuit may have any appropriate structure as long as it can allow the digital video signal input thereto to be output therefrom with either the inverted polarity or the non-inverted polarity.

The present embodiment can be freely combined with Embodiments 1 or 2. [Embodiment 4]

In the present embodiment, the structure of the source signal line driver circuit contained in the light emitting device as described in Embodiment 2 will be described in detail. FIG. **17** shows a circuit diagram of the source signal line driver circuit in the present embodiment. In FIG. **17**, the same components as those shown in FIG. **1** are designated with the same reference numerals.

Reference numeral **102-1** denotes a shift register, to which a clock signal (CLK), a signal (CLKB) obtained by inverting the polarity of the clock signal, a start pulse signal (SP), a bi-direction shift signal (SUR) are input through the illustrated wirings, respectively.

Reference numerals **102-2** and **102-3** denote a latch (A) and a latch (B), respectively. In the present embodiment, a combination of the latches (A) **102-2** and a combination of the latches (B) **102-3** correspond to four source signal lines. However, the number of source signal lines to which a combination of the latches (A) **102-2** and a combination of the latches (B) **102-3** correspond is not limited to the above number in the present embodiment. In addition, although a level shift for changing a width of a voltage amplitude of a signal is not provided in the present embodiment, such a level shift may be appropriately provided by a designer.

The digital video signal (DV) to be supplied externally to the source signal line driver circuit is input into the latch (A) **102-2** through the illustrated wirings. A latch signal S_LAT and a signal S_LATb obtained by inverting the polarity of the S_LAT are respectively input into the latch (B) **102-3** through the illustrated wirings.

25

The detailed structure of the latch (A) **102-2** is the same as that shown in FIG. **14**. Accordingly, the description thereof is omitted here.

Reference numeral **106** denotes the clock signal control circuit, that can supply a constant electrical potential (fixed electrical potential), instead of the clock signal (CLK), to the shift register **102-1** for a constant time period.

More specifically, the constant electrical potential (fixed electrical potential) instead of the clock signal is input into the shift register **102-1** for a constant time period by means of the clock signal control circuit **106**, so that the timing signal that is to be used for inputting the digital video signal at less significant bits in the range from the first bit to the m-th bit into the latch (A) **102-2** is prevented from being input into the latch (A) **102-2**. Accordingly, among the digital video signal n input from external source signal line driver circuit, only the digital video signal at more significant bits in the range from the (m+1)-th bit to the n-th bit can be written into the latch (A) **102-2**.

FIGS. **18A** and **18B** show detailed circuit diagrams of the clock signal control circuit **106** in accordance with the present embodiment.

The clock signal control circuit **106** of the present embodiment as shown in FIG. **18A** includes a NAND **1801** and an inverter **1802**. A selection signal is input through the illustrated wiring.

The clock signal to be input externally to the source signal line driver circuit is input into the NAND **1801** through an input terminal (IN). Simultaneously, the selection signal is also input into the NAND **1801**. A signal output from the NAND **1801** is provided at an output terminal (OUT) after the polarity thereof is inverted by the inverter **1802** to be input into the shift register **102-1**.

The selection signal determines whether the clock signal is to be input into the shift register **102-1**, or the constant electrical potential (fixed electrical potential) is to be instead supplied thereto.

The clock signal control circuit **106** of the present embodiment as shown in FIG. **18B** includes a first analog switch **1811**, a second analog switch **1812**, and an inverter **1813**. A selection signal is input through the illustrated wiring.

Equivalent circuit diagrams of the first analog switch **1811** and the second analog switch **1812** are the same as that shown in FIG. **16**. Each of the first analog switch **1811** and the second analog switch **1812** includes an n-channel type TFT and a p-channel type TFT. A signal to be input from an input terminal (IN) is sampled by means of a signal to be input from a first control input terminal (Vin) or a second control input terminal (Vnb), to be then output from an output terminal (OUT).

The selection signal is input into the first analog switch **1811** and the second analog switch **1812** through the first control input terminal (Vin). Simultaneously, the selection signal is also input into the first analog switch **1811** and the second analog switch **1812** through the second control input terminal (Vnb) after the polarity thereof is inverted. Further simultaneously, the clock signal to be supplied externally to the source signal line driver circuit is input into the first analog switch **1811** through the input terminal (IN). The second analog switch **1812** is supplied with the constant electrical potential (fixed electrical potential) through the input terminal (IN).

Signals respectively output from output terminals (OUT) of the first analog switch **1811** and the second analog switch **1812** are both output from an output terminal of the clock signal control circuit **106**.

26

The selection signal determines whether the clock signal is to be input into the shift register **102-1**, or the constant electrical potential (fixed electrical potential) is to be instead supplied thereto.

The structure of the clock signal control circuit is not limited to those shown in FIGS. **18A** and **18B**.

The present embodiment can be freely combined with Embodiments 1 through 3.

[Embodiment 5]

In the present embodiment, the structure of the source signal line driver circuit contained in the light emitting device as described in Embodiment 3 will be described in detail. FIG. **19** shows a circuit diagram of the source signal line driver circuit in the present embodiment. In FIG. **19**, the same components as those shown in FIG. **1** are designated with the same reference numerals.

Reference numeral **102-1** denotes a shift register, to which a clock signal (CLK), a signal (CLKB) obtained by inverting the polarity of the clock signal, a start pulse signal (SP), a bi-direction shift signal (SL/R) are input through the illustrated wirings, respectively.

Reference numerals **102-2** and **102-3** denote a latch (A) and a latch (B), respectively. In the present embodiment, a combination of the latches (A) **102-2** and a combination of the latches (B) **102-3** correspond to four source signal lines. However, the number of source signal lines to which a combination of the latches (A) **102-2** and a combination of the latches (B) **102-3** correspond is not limited to the above number in the present embodiment. In addition, although a level shift for changing a width of a voltage amplitude of a signal is not provided in the present embodiment, such a level shift may be appropriately provided by a designer.

The digital video signal (DV) to be supplied externally to the source signal line driver circuit is input into the latch (A) **102-2** through the illustrated wirings. A latch signal S_LAT and a signal S_LATb obtained by inverting the polarity of the S_LAT are respectively input into the latch (B) **102-3** through the illustrated wirings.

The detailed structure of the latch (A) **102-2** is the same as that shown in FIG. **14**. Accordingly, the description thereof is omitted here.

Reference numeral **107** denotes the timing signal control circuit, that can supply a constant electrical potential (fixed electrical potential), instead of the timing signal, to the latch (A) **102-2** for a constant time period.

More specifically, the constant electrical potential (fixed electrical potential) instead of the timing signal is input into the shift register **102-2** for a constant time period by means of the timing signal control circuit **107**, so that the timing signal that is to be used for inputting the digital video signal at less significant bits in the range from the first bit to the m-th bit into the latch (A) **102-2** is prevented from being input into the latch (A) **102-2**. Accordingly, only the digital video signal at more significant bits in the range from the (m+1)-th bit to the n-th bit can be written into the latch (A) **102-2**.

A structure of the timing signal control circuit **107** in the present embodiment is the same as those shown in FIGS. **18A** and **18B**. Accordingly, the detailed description about the structure of the timing signal control circuit **107** should be found in Embodiment 4. It should be noted, however, that in the present embodiment, the timing signal from the shift register **102-1** is input into the input terminal (IN) in the circuits as shown in FIGS. **18A** and **18B**. A signal output from an output terminal (OUT) in the circuits as shown in FIGS. **18A** and **18B** is input into the latch (A) **102-2**. The selection signal determines whether the timing signal is to be input into

the latch (A) **102-2**, or the constant electrical potential (fixed electrical potential) is to be instead supplied thereto.

The structure of the timing signal control circuit is not limited to those shown in FIGS. **18A** and **18B**.

The present embodiment can be freely combined with Embodiments 1 through 3. [Embodiment 6]

In the present embodiment, the structure of the source signal line driver circuit contained in the light emitting device as described in Embodiment 4 will be described in detail. FIG. **20** shows a circuit diagram of the source signal line driver circuit in the present embodiment. In FIG. **20**, the same components as those shown in FIG. **1** are designated with the same reference numerals.

Reference numeral **102-1** denotes a shift register, to which a clock signal (CLK), a signal (CLKB) obtained by inverting the polarity of the clock signal, a start pulse signal (SP), a bi-direction shift signal (SL/R) are input through the illustrated wirings, respectively.

Reference numerals **102-2** and **102-3** denote a latch (A) and a latch (B), respectively. In the present embodiment, a combination of the latches (A) **102-2** and a combination of the latches (B) **102-3** correspond to four source signal lines. However, the number of source signal lines to which a combination of the latches (A) **102-2** and a combination of the latches (B) **102-3** correspond is not limited to the above number in the present embodiment. In addition, although a level shift for changing a width of a voltage amplitude of a signal is not provided in the present embodiment, such a level shift may be appropriately provided by a designer.

The digital video signal (DV) to be supplied externally to the source signal line driver circuit is input into the latch (A) **102-2** through the illustrated wirings. A latch signal S_LAT and a signal S_LATb obtained by inverting the polarity of the S_LAT are respectively input into the latch (B) **102-3** through the illustrated wirings.

The detailed structure of the latch (A) **102-2** is the same as that shown in FIG. **14**. Accordingly, the description thereof is omitted here.

Reference numeral **108** denotes the start pulse signal control circuit, that can supply a constant electrical potential (fixed electrical potential), instead of the start pulse signal (SP), to the shift register **102-1** for a constant time period.

More specifically, the constant electrical potential (fixed electrical potential) instead of the start pulse signal is input into the shift register **102-2** for a constant time period by means of the start pulse signal control circuit **108**, so that the timing signal that is to be used for inputting the digital video signal at less significant bits in the range from the first bit to the m-th bit into the latch (A) **102-2** is prevented from being input into the shift register **102-1**. Accordingly, only the digital video signal at more significant bits in the range from the (m+1)-th bit to the n-th bit can be written into the latch (A) **102-2**.

A structure of the start pulse signal control circuit **108** in the present embodiment is the same as those shown in FIGS. **18A** and **18B**. Accordingly, the detailed description about the structure of the start pulse signal control circuit **108** should be found in Embodiment 4. It should be noted, however, that in the present embodiment, the start pulse signal is input into the input terminal (IN) in the circuits as shown in FIGS. **18A** and **18B**. A signal output from an output terminal (OUT) in the circuits as shown in FIGS. **18A** and **18B** is input into the shift register **102-1**. The selection signal determines whether the start pulse signal is to be input into the shift register **102-1**, or the constant electrical potential (fixed electrical potential) is to be instead supplied thereto.

The structure of the start pulse signal control circuit is not limited to those shown in FIGS. **18A** and **18B**.

The present embodiment can be freely combined with Embodiments 1 through 3. [Embodiment 7]

In the present embodiment, another example for the third structure in accordance with the present invention, which is different from that as described in Embodiment 5, will be described with reference to FIG. **21**. In FIG. **21**, the same component as shown in FIG. **5** are designated with the same reference numerals.

In FIG. **21**, reference numeral **501** denotes a power source line, reference numeral **502** denotes a buffer amplifier, reference numeral **503** denotes a monitoring light emitting device, reference numeral **504** denotes a constant current source, and reference numeral **505** denotes an adding circuit. One of electrodes of the monitoring light emitting element **503** is connected to the constant current source **504**, so that a constant current always flows through the monitoring light emitting element **503**. When a temperature of an organic compound layer contained in the light emitting element changes, the magnitude of the current to flow through the monitoring light emitting element **503** does not change, but rather, an electrical potential of the electrode of the monitoring light emitting element **503** connected to the constant current source **504** changes.

On the other hand, the buffer amplifier **502** includes two input terminals and one output terminal. One of the two input terminals is a non-inverted input terminal (+), while the other is an inverted input terminal (-). An electrical potential at one of electrodes of the monitoring light emitting device **503** is supplied to the non-inverted input terminal of the buffer amplifier **502**.

The buffer amplifier **502** is a circuit for preventing an electrical potential at a pixel electrode of the monitoring light emitting element **503** connected to the constant current source **504** from changing in accordance with a load such as a wiring capacitance of the power source line **501** or the like. Accordingly, the electrical potential provided to the non-inverted input terminal of the buffer amplifier **502** is output from an output terminal to be supplied to the power source line as the power source potential, without being changed in accordance with a load of a wiring capacitance of the power source line **501**, adding circuit **505** or the like, to the adding circuit **505**.

The electrical potential supplied to the adding circuit **505** from the output terminal of the buffer amplifier **502** is further supplied to the power source line **501** as the power source voltage, after a certain constant potential difference is added thereto or subtracted therefrom.

FIG. **22** shows the detailed circuit diagram of the adding circuit in the present embodiment. The adding circuit **505** includes a first resistor **521**, a second resistor **522**, a power source **525** for the adding circuit, and a non-inverting amplifier circuit **520**. The non-inverting amplifier circuit **520** includes a third resistor **523**, a fourth resistor **524**, a power source **526** for the non-inverting amplifier circuit, and an amplifier **527**.

One of the terminals of the first resistor **521** functions as an input terminal (IN) of the adding circuit. The other terminal of the first resistor **521** is connected to one of the terminals of the second resistor **522**. The other terminal of the second resistor **522** is connected to the power source **525** for the adding circuit. An output obtainable between the first resistor **521** and the second resistor **522** is input into the non-inverted input terminal (+) of the amplifier **527** of the non-inverting amplifier circuit **520**.

One of the terminals of the third resistor **523** is connected to an output terminal of the amplifier **527**, while the other terminal of the third resistor **523** is connected to the inverted input terminal of the amplifier **527**. An output obtainable between the third resistor **523** and the inverted input terminal of the amplifier **527** is input to one of the terminals of the fourth resistor **524**. The other terminal of the fourth resistor **524** is connected to the power source **526** for the non-inverting amplifier circuit. An output obtainable between the third resistor **523** and the output terminal of the amplifier **527** is output from an output terminal (OUT) of the adding circuit **505**.

In accordance with the above-described structure, even when a temperature of the monitoring light emitting element **503** or the organic compound layer of the light emitting element in the pixel portion changes due to a change in an environmental temperature, the power source potential is changed so as to allow a constant current to flow through the light emitting element. Thus, even when the environmental temperature of the light emitting device increases, power consumption of the light emitting device can be prevented from increasing, and furthermore, the brightness of the light emitting element can be maintained at a constant level. Moreover, by further providing the adding circuit **505**, the electrical potential of the power source line **501** is not required to be at the same level as the electrical potential of the electrode connected to the constant current source **504** of the monitoring light emitting element **503**. Thus, the magnitude of the current to flow through the buffer amplifier **502**, the monitoring light emitting element **503**, and the constant current source **504** can be suppressed, thereby resulting in the power consumption being suppressed.

The structure of the adding circuit **505** is not limited to that shown in FIG. 22.

The present embodiment can be freely combined with Embodiments 1 through 6. [Embodiment 8]

In Embodiment 8, a method of manufacturing a pixel portion and TFTs (n-channel TFTs and p-channel TFTs) of a driver circuit formed in the periphery of the pixel portion, on the same substrate simultaneously is explained in detail.

First, as shown in FIG. 23A, a base film **401** made from an insulating film such as a silicon oxide film, a silicon nitride film, or a silicon oxynitride film is formed on a substrate **400** made from glass such as barium borosilicate glass or aluminum borosilicate glass, typically Corning Corp. #7059 glass or #1737 glass, or made from a quartz substrate. For example, a silicon oxynitride film made from SiH_4 , NH_3 , and N_2O by plasma CVD is formed with a thickness of 10 to 200 nm (preferably from 50 to 100 nm), and a hydrogenated silicon oxynitride film with a thickness of 50 to 200 nm (preferably between 100 and 150 nm), made from SiH_4 and N_2O , is similarly formed and laminated. Note that the base film is shown as one layer in FIG. 23A. The base film **401** is shown as a two layer structure in Embodiment 8, but it may also be formed as a single layer of the above insulating films, and it may also be formed having a lamination structure in which two layers or more are laminated.

Semiconductor layers **402** to **405** are formed from a crystalline semiconductor film which is formed by a semiconductor film having an amorphous structure with a laser crystallization method or a known thermal crystallization method. The thickness of the semiconductor layers **402** to **405** is formed to a thickness of 25 to 80 nm (preferably between 30 and 60 nm). There are no limitations in the crystalline semiconductor film material, but it is preferable to form the film from silicon or silicon germanium (SiGe) alloy.

As for known crystallization methods, there is a thermal crystallization method using an electric furnace, a laser annealing crystallization method using laser light, a lamp annealing crystallization method using infrared light, and a crystallization method using a catalyst metal.

A laser such as a pulse emission type or continuous emission type excimer laser, a YAG laser, and a YVO₄ laser can be used in the laser crystallization method to manufacture a crystalline semiconductor film. A method of condensing laser light emitted from a laser emission device into a linear shape by an optical system and then irradiating the light to the semiconductor film may be used when these types of lasers are used. The crystallization conditions may be suitably selected by the operator, but when using the excimer laser, the pulse emission frequency is set to 300 Hz, and the laser energy density is set from 100 to 400 mJ/cm² (typically between 200 and 300 mJ/cm²). Further, the second harmonic is utilized when using the YAG laser, the pulse emission frequency is set from 30 to 300 kHz, and the laser energy density may be set from 300 to 600 mJ/cm² (typically between 350 and 500 mJ/cm²). The laser light collected into a linear shape with a width of 100 to 1000 μm , for example 400 μm , is then irradiated over the entire surface of the substrate. This is performed with an overlap ratio of 50 to 98% for the linear shape laser light.

Then, a gate insulating film **406** is formed covering the semiconductor layers **402** to **405**. A gate insulating film **406** is formed by an insulating film containing silicon with a thickness of 40 to 150 nm by plasma CVD or sputtering. A 120 nm thick silicon oxynitride film is formed in Embodiment 8. The gate insulating film **406** is not limited to this type of silicon oxynitride film, of course, and other insulating films containing silicon may also be used, in a single layer or in a lamination structure. For example, when using a silicon oxide film, it can be formed by plasma CVD with a mixture of TEOS (tetraethyl orthosilicate) and O_2 , at a reaction pressure of 40 Pa, with the substrate temperature set from 300 to 400° C. and by discharging at a high frequency (13.56 MHz) electric power density of 0.5 to 0.8 W/cm². Good characteristics as a gate insulating film can be obtained by subsequently performing thermal annealing, at between 400 and 500° C., of the silicon oxide film thus manufactured.

A first conducting film **407** and a second conducting film **408** are then formed on the gate insulating film **406** in order to form gate electrodes. The first conducting film **407** is formed from Ta (tantalum) with a thickness of 50 to 100 nm, and the second conducting film **408** is formed from W (tungsten) having a thickness of 100 to 300 nm, in Embodiment 8.

The Ta film is formed by sputtering, and sputtering of a Ta target is performed in Ar. If appropriate amounts of Xe and Kr are added to Ar at the time of sputtering, the internal stress of the Ta film is relaxed, and film peeling can be prevented. The resistivity of an α phase Ta film is on the order of 20 $\mu\Omega\text{cm}$, and it can be used in the gate electrode, but the resistivity of a β phase Ta film is on the order of 180 $\mu\Omega\text{cm}$ and it is unsuitable for the gate electrode. An α phase Ta film can easily be obtained if a tantalum nitride film, which possesses a crystal structure near that of α phase Ta, is formed with a thickness of 10 to 50 nm as a base for Ta in order to form α phase Ta.

The W film is formed by sputtering with a W target, which can also be formed by thermal CVD using tungsten hexafluoride (WF_6). Whichever is used, it is necessary to be able to make the film become low resistance in order to use it as the gate electrode, and it is preferable that the resistivity of the W film be made equal to or less than 20 $\mu\Omega\text{cm}$. The resistivity can be lowered by enlarging the crystal grains of the W film, but for cases in which there are many impurity elements such

as oxygen in the W film, crystallization is inhibited, and the film becomes high resistance. A W target having a purity of 99.9999% or 99.99% is thus used in sputtering. In addition, by forming the W film while taking sufficient care that no impurities from the gas phase are introduced at the time of film formation, the resistivity of 9 to 20 $\mu\Omega\text{cm}$ can be achieved.

Note that, although the first conducting film **407** is Ta and the second conducting film **408** is W in Embodiment 8, the conducting films are not limited to these, and both may also be formed from an element selected from the group consisting of Ta, W, Ti, Mo, Al, and Cu, or from an alloy material having one of these elements as its main constituent, or from a chemical compound of these elements. Further, a semiconductor film, typically a poly-crystalline silicon film into which an impurity element such as phosphorus is doped, may also be used. An example of preferable combinations other than that used in Embodiment 8 include: forming the first conducting film by tantalum nitride (TaN) and combining it with the second conducting film formed from W; forming the first conducting film by tantalum nitride (TaN) and combining it with the second conducting film formed from Al; and forming the first conducting film by tantalum nitride (TaN) and combining it with the second conducting film formed from Cu. (See FIG. 23B.)

Masks **409** to **412** are formed next from resist, and a first etching process is performed in order to form electrodes and wirings. An ICP (inductively coupled plasma) etching method is used in Embodiment 8. A gas mixture of CF_4 and Cl_2 is used as an etching gas, and a plasma is generated by applying a 500 W RF electric power (13.56 MHz) to a coil shape electrode at a pressure of 1 Pa. A 100 W RF electric power (13.56 MHz) is also applied to the substrate side (test piece stage), effectively applying a negative self-bias voltage. The W film and the Ta film are both etched on the same order when CF_4 and Cl_2 are combined.

Not shown in FIG. 23C, edge portions of the first conducting layer and the second conducting layer are made into a tapered shape in accordance with the effect of the bias voltage applied to the substrate side under the above etching conditions by using a suitable resist mask shape. The angle of the tapered portions is from 15 to 45°. The etching time may be increased by approximately 10 to 20% in order to perform etching without any residue remaining on the gate insulating film. The selectivity of a silicon oxynitride film with respect to a W film is from 2 to 4 (typically 3), and therefore approximately 20 to 50 nm of the exposed surface of the silicon oxynitride film is etched by this over-etching process. Further, not shown in FIG. 23C, regions of the gate insulating film **406** not covered by first shape conducting layers **414** to **417** are made thinner by 20 to 50 nm after etching.

The first shape conducting layers **414** to **417** (first conducting layers **414a** to **417a** and second conducting layers **414b** to **417b**) are thus formed from the first conducting layer and the second conducting layer in accordance with the first etching process.

A second etching process is performed next, as shown in FIG. 23D. The ICP etching method is similarly used, a mixture of CF_4 , Cl_2 , and O_2 is used as the etching gas, and a plasma is generated by supplying a 500 W RF electric power (13.56 MHz) to a coil shape electrode at a pressure of 1 Pa. A 50 W RF (13.56 MHz) electric power is applied to the substrate side (test stage), and a self-bias voltage which is lower in comparison to that of the first etching process is applied. The W film is etched anisotropically under these etching conditions, and Ta (the first conducting layers) is anisotropically etched at a slower etching speed, forming second shape

conducting layers **419** to **422** (first conducting layers **419a** to **422a** and second conducting layers **419b** to **422b**). Further, although not shown in FIG. 23D, the gate insulating film **406** is additionally etched on the order of 20 to 50 nm, becoming thinner, in regions not covered by the second shape conducting layers **419** to **422**.

The etching reaction of the W film and the Ta film in accordance with the mixed gas of CF_4 and Cl_2 can be estimated from the radicals generated, and from the ion types and vapor pressures of the reaction products. Comparing the vapor pressures of W and Ta fluorides and chlorides, the W fluoride compound WF_6 is extremely high, and the vapor pressures of WCl_5 , TaF_5 , and TaCl_5 are of similar order. Therefore the W film and the Ta film are both etched by the CF_4 and Cl_2 gas mixture. However, if a suitable quantity of O_2 is added to this gas mixture, CF_4 and O_2 react, forming CO and F, and a large amount of F radicals or F ions are generated. As a result, the etching speed of the W film having a high fluoride vapor pressure becomes fast. On the other hand, even if F increases, the etching speed of Ta does not relatively increase. Further, Ta is easily oxidized compared to W, and therefore the surface of Ta is oxidized by the addition of O_2 . The etching speed of the Ta film is further reduced because Ta oxides do not react with fluorine and chlorine. It therefore becomes possible to have a difference in etching speeds between the W film and the Ta film, and it becomes possible to make the etching speed of the W film larger than that of the Ta film.

Then, the masks **409a** to **412a** are removed, and a first doping process is performed as shown in FIG. 24A, adding an impurity element which imparts n-type conductivity. For example, doping may be performed at an acceleration voltage of 70 to 120 keV and with a dose amount of 1×10^{13} atoms/ cm^2 . The doping process is performed using the second shape conducting layers **419** to **422** as masks against the impurity element, and so as to also add the impurity element in regions below the second conducting layers **419a** to **422a**. First impurity regions **425** to **428**, which overlap with the second conducting layers **419a** to **422a**, and second impurity regions **429** to **432**, which have a higher impurity concentration than the first impurity regions, are thus formed. Note that the impurity element which imparts n-type conductivity is added after removing the masks **409a** to **412a** in Embodiment 8, but the present invention is not limited to this. The impurity element which imparts n-type conductivity may also be added in the step of FIG. 24A, and then the masks **409a** to **412a** may be removed.

A mask **433** is next formed on the semiconductor layer **404** so as to cover the second conducting layers **421a** and **421b**. The mask **433** partially overlaps with the second impurity region **431**, sandwiching the gate insulating film **406**. A second doping process is then performed, and an impurity element which imparts n-type conductivity is added. Doping of the impurity element which imparts n-type conductivity is performed at conditions in which the dose amount is raised higher than that of the first doping process, and at a low acceleration voltage. (See FIG. 24B.) The doping can be carried out by ion doping or ion implantation. Ion doping is performed under conditions of a dose amount from 1×10^{13} to 5×10^{14} atoms/ cm^2 and an acceleration voltage of 60 to 100 keV. A periodic table group 15 element, typically phosphorus (P) or arsenic (As) is used as the impurity element which imparts n-type conductivity, and phosphorus (P) is used here. The second shape conducting layers **419** to **422** become masks with respect to the impurity element which imparts n-type conductivity in this case, and source regions **434** to **437**, drain regions **438** to **441**, and Lov regions **442** to **445** are

formed in a self-aligning manner. Further, Loff region **446** is formed in accordance with the mask **433**. The impurity element which imparts n-type conductivity is added to the source regions **434** to **437**, and to the drain regions **438** to **441** with a concentration in the range of 1×10^{20} to 1×10^{21} atoms/cm³.

It is possible to freely set the length of the Loff region **446** by controlling the size of the mask **433** according to Embodiment 8.

Note that in the specification, the LDD region overlapping with a gate electrode through a gate insulating film is referred to as an Lov region, and the LDD region not overlapping with a gate electrode through a gate insulating film is referred to as an Loff region.

The impurity element which imparts n-type conductivity is added at a concentration of 1×10^{17} to 1×10^{19} atoms/cm³ in the Loff region, and at a concentration of 1×10^{16} to 1×10^{18} atoms/cm³ in the Lov region.

Note that, in FIG. 24B, either before or after doping of an impurity element which imparts n-type conductivity is performed under the above mentioned condition, doping of an impurity element which imparts an n-type conductivity may also be performed with an acceleration voltage of 70 to 120 keV in a state in which the mask **433** is formed on the semiconductor layer **404**. The concentration of the impurity element which imparts an n-type conductivity in a portion **446** which becomes an Loff region of the switching TFT can be suppressed in accordance with the above process, and the concentration of the impurity element which imparts n-type conductivity in portions **442** and **443**, which become Lov regions of the TFTs used in the driver circuit can be increased. It is possible to lower the off current of the switching TFT by suppressing the concentration of the impurity element which imparts an n-type conductivity in the portion **446** which becomes the Loff region of the switching TFT. Further, hot carriers generated in accordance with a high electric field in the vicinity of the drain and a cause of a degradation phenomenon due to the hot carrier effect can be prevented by increasing the concentration of the n-type conductivity imparting impurity element in the portion **443** which becomes the Lov region of the n-channel TFT used in the driver circuit.

After removing the mask **453**, source regions **447** and **448**, drain regions **449** and **450**, and Lov regions **451** and **452**, having a conductivity type which is the inverse of the above one conductivity type, are then formed in the semiconductor layers **402** and **405** for forming the p-channel TFT, as shown in FIG. 24C. The second shape conducting layers **419** and **422** are used as a mask with respect to the impurity element, and the impurity regions are formed in a self-aligning manner. The semiconductor layers **402** and **403**, which form n-channel TFTs, are covered over their entire surface areas by a resist masks **453** at this point. Phosphorus is added in differing concentration to the source regions **447** and **448**, the drain regions **449** and **450**, and the Lov regions **451** and **452**, and ion doping is performed here using diborane (B₂H₆), so that impurity is added to each of the regions with a concentration of 2×10^{20} to 2×10^{21} atoms/cm³.

Impurity regions (source regions, drain regions, Lov regions, and Loff regions) are formed in the respective semiconductor layers **402** to **405** by the above processes. The second conducting layers **419** to **422** overlapping the semiconductor layers function as gate electrodes.

A process of activating the impurity elements added to the respective semiconductor layers is then performed, with the aim of controlling the conductivity type. Thermal annealing using an annealing furnace is performed for this process. In addition, laser annealing and rapid thermal annealing (RTA) can also be applied. Thermal annealing is performed with an

oxygen concentration equal to or less than 1 ppm, preferably equal to or less than 0.1 ppm, in a nitrogen atmosphere at 400 to 700° C., typically between 500 and 600° C. Heat treatment is performed for 4 hours at 500° C. in Embodiment 8. However, for cases in which the wiring material used in the conducting layers **419** to **422** is weak with respect to heat, it is preferable to perform activation after forming an interlayer insulating film (having silicon as its main constituent) in order to protect the wirings and the like.

In addition, heat treatment is performed for 1 to 12 hours at 300 to 450° C. in an atmosphere containing between 3 and 100% hydrogen, performing hydrogenation of the semiconductor layers. This process is one of terminating dangling bonds in the semiconductor layers by hydrogen which is thermally excited. Plasma hydrogenation (using hydrogen excited by a plasma) may also be performed as another means of hydrogenation.

A first interlayer insulating film **455** is formed next from a silicon oxynitride film having a thickness of 100 to 200 nm. (FIG. 25A) A second interlayer insulating film **458** made from an organic insulating material is then formed on the first interlayer insulating film **455**.

Contact holes are then formed in the gate insulating film **406**, the first interlayer insulating film **455** and the second interlayer insulating film **458**, and source wirings **459** to **462** are formed to contact the source regions **447**, **435**, **436**, and **448** through the contact holes. In the same way, drain wirings **463** to **465** are further formed to contact the drain regions **449**, **439**, **440** and **450**. (FIG. 25B)

Note that it is preferable to form the contact holes by dry etching using CF₄ and O₂ when the gate insulating film **406**, the first interlayer insulating film **455**, and the second interlayer insulating film **458** are SiO₂ films or SiON films. Further, for cases in which the gate insulating film **406**, the first interlayer insulating film **455**, and the second interlayer insulating film **458** are organic resin films, it is preferable to form the contact holes by dry etching using CHF₃ or by BHF (buffered hydrogen fluoride, HF+NH₄F). In addition, if the gate insulating film **406**, the first interlayer insulating film **455** and the second interlayer insulating film **458** are formed by different materials, it is preferable to change the method of etching and the etchant or etching gas type for each film. The contact holes may also be formed by using the same etching method and the same etchant or etching gas.

A third interlayer insulating film **467** is formed next from an organic resin. Organic resins such as polyimide, polyamide, acrylic, and BCB (benzocyclobutene) can be used. In particular, it is preferable to use acrylic, which has superior levelness, because the third interlayer insulating film **467** is formed with a strong implication of leveling. An acrylic film is formed in Embodiment 8 at a film thickness at which steps formed by the TFTs can be sufficiently leveled. The film thickness is preferably from 1 to 5 μm (more preferably between 2 and 4 μm).

A contact hole for reaching the drain wiring **465** is formed next in the third interlayer insulating film **467**, and a pixel electrode **468** is formed. An indium tin oxide (ITO) film is formed with a thickness of 110 nm in Embodiment 8, and patterning is then performed, thereby forming the pixel electrode **468**. Further, a transparent conducting film in which between 2 and 20% zinc oxide (ZnO) is mixed with indium oxide may also be used. The pixel electrode **468** becomes an anode of a light emitting layer. (See FIG. 25C.)

A first bank **469** and a second bank **470** are formed next from a resin material. The first bank **469** and the second bank **470** are formed in order to separate an organic compound layers and cathodes, which are formed later, of adjacent pix-

els. It is therefore preferable that the second bank **470** stick out farther horizontally than the first bank **469**. Note that it is preferable that the combined thickness of the first bank **469** and the second bank **470** be made on the order of 1 to 2 μm , but there are no limitations on this thickness provided that the organic compound layers and the cathodes formed later of adjacent pixels can be separated. Further, it is necessary to form the first bank **469** and the second bank **470** by an insulating film, and it is therefore possible to use materials such as an oxide or a resin, for example. The first bank **469** and the second bank **470** may both be formed by the same material, and they may also be formed by different materials. The first bank **469** and the second bank **470** are formed in stripe shapes between pixels. The first bank **469** and the second bank **470** may be formed on and along the source wirings (source signal lines), and may be formed on and along the gate wirings (gate signal lines). Note that the first bank **469** and the second bank **470** may also be formed by a material in which a pigment is mixed into a resin. (See FIG. 26A.)

An organic compound layer **471** and a cathode (MgAg electrode) **472** are formed next in succession without exposure to the atmosphere using vacuum evaporation. Note that the film thickness of the organic compound layer **471** may be from 80 to 200 nm (typically between 100 and 120 nm), and that the film thickness of the cathode **472** may be from 180 to 300 nm (typically between 200 and 250 nm). Note also that, although only one pixel is shown in Embodiment 8, an organic compound layer which emits red color light, an organic compound layer which emits green color light, and an organic compound layer which emits blue color light are formed at the same time at this point. Note that materials to form an organic compound layer and a cathode is partially laminated on the bank **470**, however, in this specification, the materials are not included in the organic compound layer **471** and the cathode **472**.

The organic compound layer **471** and the cathode **472** are formed in order for a pixel corresponding to the red color, a pixel corresponding to the green color, and a pixel corresponding to the blue color. However, the organic compound layer **471** lacks resistance with respect to solutions, and therefore each color must be formed separately without using a photolithography technique. It is preferable to use a metal mask and cover the pixels other than the desired pixel, and selectively form the organic compound layer **471** and the cathode **472** in only the required portions.

Namely, first a mask is set so as to cover all of the pixels except for those corresponding to the red color, and red color light-emitting organic compound layers are selectively formed using the mask. Next, a mask is set so as to cover all of the pixels except for those corresponding to the green color, and green color light-emitting organic compound layers are selectively formed using the mask. Finally, a mask is set so as to cover all of the pixels except for those corresponding to the blue color, and blue color light-emitting organic compound layers selectively formed using the mask. Note that, although the use of all different masks is described here, the same mask may also be reused. Further, it is preferable to perform processing until an organic compound layer and a cathode are formed on all of pixels without releasing the vacuum.

Note that the organic compound layer **471** has a single layer structure composed of only a light-emitting layer is shown in Embodiment 8, but a structure having layers such as a hole transporting layer, a hole injecting layer, an electron transporting layer, and an electron injecting layer in addition to the light-emitting layer may also be used for the organic compound layer. Various examples of these types of combi-

nations have already been reported, and all such structures may be used. A known material can be used as the organic compound layer **471**. Considering the driver voltage of a light emitting element, it is preferable to use an organic material as the known material.

The cathode **472** is formed next. An example of using an MgAg electrode as the cathode of an light emitting element is shown in Embodiment 8, but it is also possible to use other known materials.

The active matrix substrate having the structure shown in FIG. 26B is thus completed. Note that, after forming the first bank **469** and the second bank **470**, it is effective to perform processing in succession without exposure to the atmosphere up through to the formation of the cathode **472** by using a multi-chamber method (or an in-line method) thin film formation apparatus.

In Embodiment 8, a source region **504**, a drain region **505**, an Loff region **506**, an Lov region **507**, and a channel forming region **508** are contained in a semiconductor layer of a switching TFT **501**. The Loff region **506** is formed so as not to overlap with the gate electrode **421** through the gate insulating film **406**. Further, the Lov region **507** is formed so as to overlap with the gate electrode **421** through the gate insulating film **406**. This type of structure is extremely effective in reducing the off current.

Further, a single gate structure is used as the switching TFT **501** in Embodiment 8, but the present invention may also have a double gate structure or another type of multi-gate structure for the switching TFT. Two TFTs are substantially connected in series by using the double gate structure, giving the advantage of additionally reducing the off current.

Further, the switching TFT **501** is an n-channel TFT in Embodiment 8, but a p-channel TFT may also be used.

A semiconductor layer of a current controlling TFT **502** contains a source region **510**, a drain region **511**, an Lov region **512**, and a channel forming region **513**. The Lov region **512** is formed so as to overlap with the gate electrode **422** through the gate insulating film **406**. Note that the current controlling TFT **502** does not have the Loff region in Embodiment 8, but a structure having the Loff region may also be used.

Further, the current controlling TFT **502** is a p-channel TFT in Embodiment 8, but it may also be an n-channel TFT.

Note that the active matrix substrate of Embodiment 8 shows an extremely high reliability, and its operational characteristics are also increased, by arranging optimally structured TFT in not only the pixel portion, but also in the driver circuit portion.

First, a TFT having a structure in which hot carrier injection is reduced so as not to have a very large drop in operational speed is used as an n-channel TFT **503** of a CMOS circuit forming the driver circuit portion. Note that circuits such as a shift register, a buffer, a level shifter, and a sampling circuit (sample and hold circuits) are included as the driver circuits here. Signal conversion circuits such as a D/A converter can also be included in the case of performing digital drive.

A semiconductor layer of the n-channel TFT **503** of the CMOS circuit in Embodiment 8 contains a source region **521**, a drain region **522**, an Lov region **523**, and a channel forming region **524**.

Further, a semiconductor layer of a p-channel TFT **504** of the CMOS circuit contains a source region **531**, a drain region **532**, an Lov region **533**, and a channel forming region **534**.

Note that, in practice, it is preferable to perform packaging (sealing) by a protecting film having high airtight characteristics and little outgassing (such as a laminate film or an

ultraviolet hardened resin film) or by a transparent sealing material after completing up through to the processes of FIG. 26B so as to have no exposure to the atmosphere. Further, if an inert gas is placed in the inside of the sealing material, and a drying agent (barium oxide, for example) is arranged inside of the sealing material, then the reliability of the light emitting element is increased.

Further, a connector (flexible printed circuit, FPC) is attached in order to connect the elements formed on the substrate, with terminals extended from the circuits, to external signal terminals after increasing the airtight characteristics in accordance with the packaging process or the like. A manufactured product is thus completed. This type of deliverable state is referred to as a light emitting device throughout this specification.

The widths of the gate electrodes in the direction of the channel length (referred to hereinafter as a width of the gate electrode) differ as stated above in accordance with manufacturing processes of the present invention. Therefore, it is possible to make the ion implantation within the semiconductor layers arranged under the first gate electrode less than the ion concentration within the semiconductor layers not arranged under the first gate electrode by utilizing the difference in ion penetration depth, due to the difference of gate electrode thickness, when performing ion injection using the gate electrodes as masks.

Further, in order to form the Loff regions using a mask, only the width of Lov region needs to be controlled by etching. It becomes easy to control positions of the Lov regions and the Loff regions.

Note that although an example in which light emitted from the organic compound layer is directed toward the substrate side is explained in Embodiment 8, the present invention is not limited to this, and a structure in which light emitted from the organic compound layer is directed above the substrate may also be used. In this case, the cathode of the light emitting element becomes the pixel electrode, and it is preferable that the current controlling TFT be an n-channel TFT.

Note that although the case in which a pixel has a switching TFT and a current controlling TFT is explained in Embodiment 8, the present invention is not limited to this. Even when a pixel has three TFTs or more, it is possible to apply the present embodiment.

The method of manufacturing a light emitting device according to the present invention is not limited to the manufacturing method described in Embodiment 8 and other manufacturing methods can be utilized.

Note that it is possible to freely combine Embodiment 8 with any of Embodiments 1 to 7. [Embodiment 9]

A light emitting device manufactured by the present invention has superior visibility in bright locations in comparison to a liquid crystal display device because it is a self-emission type device, and moreover viewing angle is wide. Accordingly, it can be used as a display portion for various electronic apparatuses. For example, it is appropriate to use the light emitting display device of the present invention as a display portion of a display device incorporating the light emitting device in its casing having a diagonal equal to 30 inches or greater (typically equal to 40 inches or greater) for appreciation of TV broadcasts by large screen. The light emitting device of the present invention can be used as a display portion for various electronic apparatuses.

The following can be given as examples of such electronic apparatuses: a video camera; a digital camera; a goggle type display (head mounted display); a car navigation system; an audio reproducing device (such as a car audio system, an

audio compo system); a notebook personal computer; a game equipment; a portable information terminal (such as a mobile computer, a mobile telephone, a mobile game equipment or an electronic book); and an image playback device provided with a recording medium (specifically, a device which performs playback of a recording medium and is provided with a display which can display those images, such as a digital video disk (DVD)). In particular, because portable information terminals are often viewed from a diagonal direction, the wideness of the field of vision is regarded as very important. Thus, it is preferable that the light emitting device is employed. Examples of those electronic apparatuses are shown in FIGS. 27 and 28.

FIG. 27A illustrates a portable information terminal which includes a display panel 2701 and an operation panel 2702. The display panel 2701 is connected with the operation panel 2702 at a connection portion 2703. In the connection portion 2703, an angle between a surface provided with the display portion 2704 of the display panel 2701 and a surface provided with an operation key 2706 of the operation panel 2702 can be arbitrarily varied.

The display panel 2701 includes the display portion 2704. Further, the portable information terminal shown in FIG. 27A has a function as a telephone, and the display panel 2701 includes an audio output portion 2705, so that voice is outputted from the audio output portion 2705. The light emitting device of the present invention can be utilized for the display portion 2704.

The operation panel 2702 includes an operation key 2706, a power switch 2707, an audio input portion 2708, and a CCD receiving portion 2709. Note that although the operation key 2706 and the power switch 2707 are provided separately in FIG. 27A, the power switch 2707 may be included in the operation key 2706.

In the audio input portion 2707, voice is inputted. The image inputted at the CCD receiving portion 2709 is received in the portable information terminal as an electronic data.

Note that although the display panel 2701 includes the audio output portion 2705 and the operation panel includes the audio input portion 2708 in FIG. 27A, the present embodiment is not limited to this. Namely, the display panel 2701 includes the audio input portion 2708, and the operation panel includes the audio output portion 2705. Further, the audio output portion 2705 and the audio input portion 2708 may be provided in the display panel 2701, and the audio output portion 2705 and the audio input portion 2708 may be provided in the operation panel 2702.

Note that although the portable information terminal includes no antenna in FIG. 27A, an antenna may be provided, if necessary.

FIG. 27B illustrates a portable telephone, which includes a main body 2601, an audio output portion 2602, an audio input portion 2603, a display portion 2604, operation switches 2605, and an antenna 2606. The light emitting device in accordance with the present invention can be used as the display portion 2604. The display portion 2604 can reduce power consumption of the portable telephone by displaying white-colored characters on a black-colored background.

The light emitting device of the present invention is very effective for the portable type electronic apparatus since power consumption can be reduced.

FIG. 28A illustrates a display device having a light emitting device which includes a frame 2001, a support table 2002, a display portion 2003, or the like. The light emitting device of the present invention is applicable to the display portion 2003. The light emitting device is of the self-emission

type and therefore requires no back light. Thus, the display portion thereof can have a thickness thinner than that of the liquid crystal display device.

FIG. 28B illustrates a video camera which includes a main body **2101**, a display portion **2102**, an audio input portion **2103**, operation switches **2104**, a battery **2105**, an image receiving portion **2106**, or the like. The light emitting device in accordance with the present invention can be used as the display portion **2102**.

FIG. 28C illustrates one portion (the right-half piece) of a head-mounted type electronic apparatus which includes a main body **2201**, signal cables **2202**, a head mount band **2203**, a screen portion **2204**, an optical system **2205**, a display portion **2206**, or the like. The light emitting device of the present invention is applicable to the display portion **2206**.

FIG. 28D illustrates an image reproduction apparatus provided with a recording medium (more specifically, a DVD reproduction apparatus), which includes a main body **2301**, a recording medium (a DVD or the like) **2302**, operation switches **2303**, a display portion (a) **2304**, another display portion (b) **2305**, or the like. The display portion **2304** (a) is used mainly for displaying image information, while the display portion **2305** (b) is used mainly for displaying character information. The light emitting device in accordance with the present invention can be used as these display portions **2304** (a) and **2305** (b). The image reproduction apparatus provided with a recording medium further includes a domestic game equipment or the like.

FIG. 28E illustrates a goggle type display (head-mounted display) which includes a main body **2401**, a display portion **2402**, and an arm portion **2403**. The light emitting device in accordance with the present invention can be used to the display portion **2402**.

FIG. 28F illustrates a personal computer which includes a main body **2501**, a frame **2502**, a display portion **2503**, a key board **2504**, or the like. The light emitting device in accordance with the present invention can be used as the display portion **2503**. Note that if emission luminance of an organic material becomes higher in the future, light including outputted image information is enlarged to be projected by means of lenses or the like, thereby applying to a front-type or a rear-type projector.

The aforementioned electronic apparatuses are more likely to be used for display information distributed through a telecommunication path such as Internet, a CATV (cable television system), and in particular likely to display moving picture information. The light emitting device is suitable for displaying moving pictures since the organic material can exhibit high response speed.

Since a light emitting portion of the light emitting device consumes power, it is desirable to display information in such a manner that the light emitting portion therein becomes as small as possible. Accordingly, when the light emitting device is applied to a display portion which mainly displays character information, e.g. a display portion of a portable information terminal, and more particular, a portable telephone or a car audio reproducing equipment, it is desirable to drive the light emitting display device so that the character information is formed by a light-emitting portion while a non-emission portion corresponds to the background.

As set forth above, the present invention can be applied variously to a wide range of electronic apparatuses in all fields. Note that it is possible to freely combine Embodiment 9 with any of Embodiments 1 to 8.

[Embodiment 10]

In this embodiment, a further specific structure of a third structure of the present invention and a change in brightness due to a temperature will be explained with measured values.

FIG. 29A shows a connection state of a light emitting element for a monitor, which is included in a light emitting device of this embodiment. Reference numerals **701**, **702**, **703**, **704** and **705** represent a power source line, a buffer amplifier, a monitoring light emitting element, a constant current source, and one of light emitting elements in a pixel portion, respectively.

FIG. 29A shows a case when a current controlling TFT (not shown) is "ON" state, and the current controlling TFT directly connects a pixel electrode of the light emitting element **705** in the pixel portion and the power source line **701**.

Also, in FIG. 29A, although an anode of the light emitting element **705** in the pixel portion is used as a pixel electrode, this embodiment is not limited to such a structure. A cathode may be used as a pixel electrode.

The constant current source **704** of this embodiment has an amplifier, a variable resistor and a bipolar transistor. References **V1** and **V2** represent a predetermined voltage to be applied, a relationship (a voltage applied to an anode < **V2** < **V1**) is satisfied. By the way, the relationship among the voltage applied to the anode, **V2**, and **V1** is changed depending on whether an anode is used as a pixel electrode or a cathode is used as pixel electrode. In order to flow a forward bias current into a light emitting element, the relationship among the voltage applied to the anode, **V2**, and **V1** is appropriately set. Also, the constant current source **704** is not limited to the structure as shown in FIG. 29A, a well-known constant current source can be used.

An output terminal of the constant current source **704** is connected with a pixel electrode of the monitoring light emitting element **703**. By the way, when an anode of the light emitting element **705** in the pixel portion is used as a pixel electrode, an anode of the monitoring light emitting element **703** is also used as a pixel electrode. To the contrary, when a cathode of the light emitting element **705** in the pixel portion is used as a pixel electrode, a cathode of the monitoring light emitting element **703** is also used as a pixel electrode. In FIG. 29A, the anode of the monitoring light emitting element **703** is used as a pixel electrode.

When the output terminal of the constant current source **704** is connected with the pixel electrode of the monitoring light emitting element **703** and thus a current flows into the monitoring light emitting element **703**, its value is always kept constant. And then, when a temperature of a organic compound layer included in the light emitting element is changed, although an amount of a current flowing into the monitoring light emitting element **703** is not changed, a potential of the pixel electrode of the monitoring light emitting element **703**, which is connected with the constant current source **704**, is changed.

On the other hand, the buffer amplifier **702** has two input terminals and one output terminal, one of the two input terminals is a non-inverted input terminal (+), and the other is an inverted input terminal (-). A potential of the pixel electrode of the monitoring light emitting element **703** is provided with the non-inverted input terminal of the buffer amplifier **702**.

The buffer amplifier **702** is a circuit for suppressing a change in the potential of the pixel electrode of the monitoring light emitting element **703**, which is connected with the constant current source **704**, due to a load such as a wiring capacitance of the power source line **701** or the like. Thus, the potential provided with the non-inverted input terminal of the buffer amplifier **702** is output from the output terminal with-

out the change due to a load such as a wiring capacitance of the power source line 701 or the like, and provided with the pixel electrode of the light emitting element 705 in the pixel portion. As a result, a current flowing into the monitoring light emitting element 703 is equal to a current flowing into the light emitting element 705 in the pixel portion.

Then, even when a temperature of an organic compound layer of, the monitoring light emitting element 703 or the light emitting element 705 in the pixel portion is changed depending on a change in an ambient temperature, a constant current flows into each light emitting element. Thus, even when the ambient temperature of the light emitting device rises, an increase in power consumption of the light emitting device can be suppressed.

FIG. 29B shows a change in measurement values of brightness due to a temperature, of the light emitting element 705 in the pixel portion of the light emitting device having the structure as shown in FIG. 29A. By the way, a graph (corrected) relates to the measurement values in the light emitting device of the present invention, and a graph (not corrected) relates to the measurement values in the light emitting device without the third structure of the present invention.

As can be cleared from FIG. 29A, in the graph (not corrected), the brightness is increased depending on the rise of the temperature. However, in the graph (corrected), even when the temperature rises, the brightness is almost kept constant. Since a current and a brightness are in a proportional relation, in the light emitting device of the present invention, even when the temperature rises, a current can be kept constant, and the increase in the power consumption can be suppressed.

Also, in a light emitting element, a decrease in brightness is caused by deterioration of an organic light emitting layer. Here, even if the deterioration is caused in the same level, a decrease amount in brightness in the case where a current flowing between a cathode and an anode is kept constant is smaller than that in the case where a voltage applied between the cathode and the anode is kept constant. Thus, since a current flowing into the light emitting element can be kept constant in the light emitting device of the present invention, a decrease in brightness, due to deterioration can be suppressed.

This embodiment can be arbitrarily combined with the structures of Embodiments 1 to 9 with respect to the operation.

As described in the above, in accordance with the first structure of the present invention, the magnitude of a current to flow through the light emitting element can be suppressed to some degree, thereby resulting in a reduced power consumption of the light emitting device. In accordance with the second structure of the present invention, the number of bits of the digital video signal to be input into the pixels is reduced, and therefore, the required number of writing the digital video signal by the source signal line driver circuit and a gate signal line driver circuit can be reduced. Thus, power consumption of the source signal line driver circuit and the gate signal line driver circuit can be reduced, thereby resulting in a reduced power consumption of the light emitting device. In accordance with the third structure of the present invention, the magnitude of a current to flow through a light emitting element of a pixel is maintained at a constant level, even when a temperature of the organic compound layer changes. Thus, power consumption of the light emitting device can be prevented from increasing even when an environmental temperature of the light emitting device increases, which in turn can maintain the brightness at a constant level.

In accordance with the first, second, and third structures of the present invention as described in the above, it is possible to suppress the power consumption of a light emitting device and an electronic apparatus which employs the light emitting device. It should be noted that only either one of the first through third structures is required to be included in the present invention, although two or all of the first through third structures may be included.

What is claimed is:

1. A display device comprising:

a transistor including a semiconductor region, a gate insulating film, and a gate electrode;

a first interlayer insulating film over the transistor;

a second interlayer insulating film over the first interlayer insulating film;

a pixel electrode over the second interlayer insulating film, wherein the pixel electrode is electrically connected with the semiconductor region;

a first resin partly in contact with a top surface of the pixel electrode;

a second resin over the first resin; and

a light emitting layer including an organic compound over the pixel electrode and the second resin.

2. The display device according to claim 1, wherein each of the first resin and the second resin is a bank.

3. The display device according to claim 1, wherein the first resin and the second resin is formed of a same material.

4. The display device according to claim 1, wherein the first resin and the second resin is formed of different materials.

5. The display device according to claim 1, wherein the second resin is wider than the first resin.

6. The display device according to claim 1, wherein the light emitting layer over the second resin is spaced apart from the light emitting layer over the pixel electrode.

7. The display device according to claim 1, wherein the display device is incorporated in one selected from the group consisting of a telephone, a video camera, a digital camera, a goggle type display, an image reproduction apparatus, and a personal computer.

8. A display device comprising:

a transistor including a semiconductor region, a gate insulating film, and a gate electrode;

a first interlayer insulating film including silicon oxide over the transistor;

a second interlayer insulating film including an organic resin over the first interlayer insulating film;

a pixel electrode over the second interlayer insulating film, wherein the pixel electrode is electrically connected with the semiconductor region;

a first resin partly in contact with a top surface of the pixel electrode;

a second resin over the first resin; and

a light emitting layer including an organic compound over the pixel electrode and the second resin.

9. The display device according to claim 8, wherein the first interlayer insulating film further includes silicon oxynitride under the silicon oxide.

10. The display device according to claim 8, wherein each of the first resin and the second resin is a bank.

11. The display device according to claim 8, wherein the first resin and the second resin is formed of a same material.

12. The display device according to claim 8, wherein the first resin and the second resin is formed of different materials.

13. The display device according to claim 8, wherein the second resin is wider than the first resin.

14. The display device according to claim 8, wherein the light emitting layer over the second resin is spaced apart from the light emitting layer over the pixel electrode.

15. The display device according to claim 8, wherein the display device is incorporated in one selected from the group consisting of a telephone, a video camera, a digital camera, a goggle type display, an image reproduction apparatus, and a personal computer.

* * * * *

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : 8,638,278 B2
APPLICATION NO. : 13/792302
DATED : January 28, 2014
INVENTOR(S) : Shunpei Yamazaki et al.

Page 1 of 1

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

In the Specifications

Column 15, line 29, before “306” insert --TFT--;

Column 18, line 11, replace “IF” with --TFT--;

Column 19, line 44, after “period” delete “to”;

Column 22, line 28, replace “in” with --m--;

Column 23, line 62, after “853,” delete “to”;

Column 24, line 49, replace “(SUR)” with --(SL/R)--;

Column 26, line 52, replace “hit” with --bit--;

Column 39, line 27, replace “2305(6)” with --2305(b)--.

Signed and Sealed this
Sixth Day of May, 2014



Michelle K. Lee
Deputy Director of the United States Patent and Trademark Office

专利名称(译)	显示设备		
公开(公告)号	US8638278	公开(公告)日	2014-01-28
申请号	US13/792302	申请日	2013-03-11
[标]申请(专利权)人(译)	株式会社半导体能源研究所		
申请(专利权)人(译)	半导体能源研究所CO. , LTD. ,		
当前申请(专利权)人(译)	半导体能源研究所有限公司.		
[标]发明人	YAMAZAKI SHUNPEI KOYAMA JUN OSAME MITSUAKI OSADA MAI		
发明人	YAMAZAKI, SHUNPEI KOYAMA, JUN OSAME, MITSUAKI OSADA, MAI		
IPC分类号	G09G3/30 G09F3/00 H04B1/00 G09G3/20 G09F9/30 H04M1/00 H05B33/00 H05B33/14 G09G5/00 G03B19/02 H04N5/225 G09G3/32 G09G3/10		
CPC分类号	G09G2320/029 G09G2310/0251 G09G2320/043 G09G2300/0866 G09G2310/0281 G09G3/2022 G09G2310/0262 G09G2320/041 H01L27/32 G09G2310/027 H01L27/3244 G09G2330/028 G09G3/3258 G09G3/3291 G09G2300/0842 G09G3/3266 G09G2330/021		
代理机构(译)	FISH & RICHARDSON P.C.		
优先权	2000117045 2000-04-18 JP 2001059511 2001-03-05 JP 13/030191 2012-06-05 US 12/609820 2011-08-02 US 10/920279 2009-11-24 US 09/833673 2007-05-22 US		
其他公开文献	US20130187142A1		
外部链接	Espacenet USPTO		

摘要(译)

本发明旨在抑制EL显示器的功耗。根据要在像素部分中显示的图像的亮度，确定图像的对比度是否被反转，并且减少要输入到像素部分的数字视频信号的比特数，即使当EL层的温度通过为EL显示器提供另一个用于监测温度的EL元件而改变EL层的温度时，也允许流过EL元件的电流的大小保持在恒定的水平。

