

(19)



(11)

**EP 2 078 270 B1**

(12)

**EUROPEAN PATENT SPECIFICATION**

(45) Date of publication and mention of the grant of the patent:  
**29.11.2017 Bulletin 2017/48**

(51) Int Cl.:  
**G06F 19/00<sup>(2011.01)</sup> A61B 5/00<sup>(2006.01)</sup>**

(21) Application number: **07844765.3**

(86) International application number:  
**PCT/US2007/083155**

(22) Date of filing: **31.10.2007**

(87) International publication number:  
**WO 2008/057883 (15.05.2008 Gazette 2008/20)**

**(54) SYSTEM AND METHOD FOR MONITORING CARDIORESPIRATORY PARAMETERS**

SYSTEM UND VERFAHREN ZUR ÜBERWACHUNG VON HERZ-LUNGEN-PARAMETERN

SYSTÈME ET MÉTHODE DE SUIVI DE PARAMÈTRES RESPIRATOIRES

(84) Designated Contracting States:  
**AT BE BG CH CY CZ DE DK EE ES FI FR GB GR HU IE IS IT LI LT LU LV MC MT NL PL PT RO SE SI SK TR**

(56) References cited:  
**WO-A-2004/013611 WO-A-2004/089208  
WO-A-2006/115704 WO-A1-96/11630  
WO-A2-2007/143535 US-A- 4 085 740  
US-A- 4 513 748 US-A- 4 513 748  
US-A- 4 926 868 US-A- 4 958 638  
US-A1- 2003 201 894 US-A1- 2004 127 804  
US-A1- 2004 249 296 US-A1- 2005 073 424  
US-A1- 2005 240 087 US-A1- 2006 189 924  
US-A1- 2006 241 510**

(30) Priority: **01.11.2006 US 863862 P**

(43) Date of publication of application:  
**15.07.2009 Bulletin 2009/29**

• **AMY DIANE DROITCOUR: "NON-CONTACT MEASUREMENT OF HEART AND RESPIRATION RATES WITH A SINGLE-CHIP MICROWAVE DOPPLER RADAR", A DISSERTATION SUBMITTED TO THE DEPARTMENT OF ELECTRICAL ENGINEERING AND THE COMMITTEE ON GRADUATE STUDIES OF STANFORD UNIVERSITY IN PARTIAL FULFILLMENT OF THE REQUIREMENTS FOR THE DEGREE OF DOCTOR OF , 1 June 2006 (2006-06-01), pages 1-470, XP002688022, Retrieved from the Internet: URL:http://72.52.208.92/~gbpprorg/mil/inte r/Droitcour\_Thesis.pdf [retrieved on 2012-11-26]**

(60) Divisional application:  
**11195916.9 / 2 469 436**

(73) Proprietor: **ResMed Sensor Technologies Limited Dublin 4 (IE)**

(72) Inventors:  
• **DE CHAZAL, Philip Co. Dublin (IE)**  
• **HANLEY, Conor Dun Laoghaire (IE)**  
• **HENEGHAN, Conor Campbell, CA 95008 (US)**

(74) Representative: **Vossius & Partner Patentanwälte Rechtsanwälte mbB Siebertstrasse 3 81675 München (DE)**

**EP 2 078 270 B1**

Note: Within nine months of the publication of the mention of the grant of the European patent in the European Patent Bulletin, any person may give notice to the European Patent Office of opposition to that patent, in accordance with the Implementing Regulations. Notice of opposition shall not be deemed to have been filed until the opposition fee has been paid. (Art. 99(1) European Patent Convention).

**Description****BACKGROUND**

5 [0001] This application claims priority to U.S. Provisional Application serial no. 60/863,862 filed on November 1, 2006.

[0002] This disclosure relates to the monitoring of motion, breathing, and heart rate of living beings, *e.g.*, humans, in a convenient and low-cost fashion that is useful, for example, in the assessment of cardiorespiratory markers of fitness and activity, and more particularly to an apparatus, system, and method for acquiring, processing and displaying the corresponding information in a easily understandable format. In this application, reference is made to a system which can measure motion, breathing and heart rate as a cardiorespiratory monitoring device or system.

10 [0003] Monitoring of heart rate and respiration is of interest in assessing the performance of cardiorespiratory systems. For example, measurements of heart rate are useful when assessing fitness levels of humans, as there are well-established guidelines for physiologically normal ranges of heart rate in response to differing levels of activity. Measurements of heart rate are widely used in fitness training schedules. For example, an exercise which maintains heart rate in a range between 100 and 120 beats per minute (bpm) may be useful for fat-burning and endurance building, whereas a competitive athlete may wish to undertake activity which raises the heart rate level to 160-180 bpm. Moreover, levels have been determined which reliably adjust for age and gender, so that individuals interested in a structured cardiovascular fitness program can monitor their progress quantitatively. Accordingly, it is desirable to be able to measure heart rate in a variety of settings. However, reliable measurement of heart rate in exercise conditions poses certain technical challenges. While running or cycling, motion artifact can corrupt heart rate measurements. While swimming, electrical measurement of heart rate can be difficult due to the conducting nature of water.

15 [0004] In addition to heart rate, breathing rate, depth and patterns are useful indicators of the overall status of the cardiorespiratory system. It is well observed that breathing rate increases in response to exercise, but the rate of increase (or decrease during an exercise recovery period) is a marker of overall cardiorespiratory health. For persons with compromised cardiorespiratory status, who might experience dyspnoea, for example, the elevated respiratory rate is a useful marker of status.

20 [0005] Individual measurements of heart rate and respiration are of value, but in addition useful measurements can be derived from combinations of these measurements which provide overall markers. For example, it is known that breathing directly modulates heart rate through a physiological mechanism called respiratory sinus arrhythmia (RSA), in which the heart speeds up during inspiration, and decreases during expiration. RSA is particularly pronounced in young people, and tends to decline with age. However, in general, a high degree of RSA is associated with health, and will change in response to exercise and changes in diet (see for example, "Respiratory sinus arrhythmia alteration following training in endurance athletes," by Ronald E. De Meersman, published in European Journal of Applied Physiology, vol. 64, no. 5, September 1992, pages 434-436). However, in order to quantify RSA, simultaneous measurements of heart rate and respiration are desirable.

25 [0006] Other useful parameters of cardiorespiratory fitness are the anaerobic threshold (AT) and ventilatory threshold (VT). The anaerobic threshold is the point at which the cardiorespiratory system is not providing sufficient oxygen to the muscles for the muscles' energy needs to be fully met by aerobic metabolic processes. Accordingly, the body uses its glycogen stores in an anaerobic metabolic process to maintain muscle output. At this point, the person has reached their maximum oxygen uptake, and will shortly become too fatigued to maintain their activity level (the maximum oxygen uptake is referred to as  $VO_{2,max}$ ). To measure AT accurately requires specialized laboratory equipment and blood sampling, so while this is used as a "gold standard", it is not practical for widespread use by individuals interested in fitness. The ventilatory threshold is related physiologically to the anaerobic threshold. It is a point at which the response of minute ventilation (liters/min of air breathed) to exercise intensity becomes nonlinear, and is marked by a substantial increase in breathing rate. From an aerobic fitness point of view, it has been shown that the anaerobic threshold and the ventilatory threshold are strongly correlated. Since the goal of many fitness programs is to increase AT, it is useful to be able to use VT as a reliable surrogate marker. The cardiorespiratory monitor can be used to estimate VT by using combinations of respiration rate and heart rate. This will provide utility to the user of the monitor, as they can track the trends in their VT over long time periods (*e.g.*, over the course of a fitness training program).

30 [0007] In the clinical setting, it is also useful to have reliable markers of cardiovascular fitness. For example, people suffering from heart failure have high exercise intolerance. Some subjects with heart failure are candidates for heart transplant, but given the scarcity of available hearts, doctors must prioritize patients in order of the severity of their disease. Again, for such cases, measurements of VT can be useful in assessing the overall health of the patient. A discussion of the challenges of assessing cardiorespiratory markers for assessing heart transplantation candidates is given in D. Ramos-Barbón, D. Fitchett, W. J. Gibbons, D. A. Latter, and R. D. Levy, "Maximal Exercise Testing for the Selection of Heart Transplantation Candidates - Limitation of Peak Oxygen Consumption," *Chest*. 1999;115:410-417.

35 [0008] A large variety of techniques exist for measurement of heart rate for the purposes of assessing cardiorespiratory fitness. Surface lead electrocardiograms (ECGs) are a highly accurate way of capturing cardiac electrical activity, and

hence heart rate. However, they require that the subject attach gelled electrodes to the chest region, and also carry or wear the associated electronic processing and/or recording device. So generally, full ECG measurement is restricted to clinical applications.

5 [0009] More convenient techniques for electrocardiogram measurement have been introduced which trade off signal quality for convenience, and are now widely used in commercially available heart rate fitness monitors. These techniques use electrodes which are embedded in conductive textiles which are placed in proximity to the skin. Typically, the textiles form part of a chest band worn around the thorax at the level of the chest. Since the conductivity of the textile material is dependent on moisture content, these sensors work best when the person is exercising vigorously and the skin is moistened with sweat (alternatively users can apply some conducting gel to ensure good electrical measurement). The  
10 disadvantage of this system is the requirement for the person to wear the chest band, and the reduced signal quality when the person's skin is not moist.

[0010] Another technique for assessing heart rate during exercise is to use pulse oximetry, which measures the changes in reflected/transmitted light through blood vessels. A characteristic photoplethysmogram can be generated in which each cardiac contraction is visible as a distinct pulse. However, pulse oximetry methods for measuring heart rate are limited by motion artifacts and poor perfusion characteristics. The power requirements of the light emitting diodes used in oximeters can also be a limiting factor in the battery life of such a device.

15 [0011] Respiratory effort and breathing rate can be also measured in multiple ways. A common method for measuring respiratory effort uses inductance plethysmography, in which a person wears a tightly fitting elastic band around their thorax, whose inductance changes as the person breathes in and out. A limitation of the method from a convenience point of view is that the person has to wear a band, and remains connected to the associated electronic recording device via wires. An alternative system for measuring respiratory effort is to use impedance pneumography, in which the impedance change of the thorax is measured. The limitation of this technology is that it requires electrodes to be attached to the body, and has an active electrical component which needs to be carried by the subject.

20 [0012] For cardiorespiratory fitness assessment, it is also useful to measure gross bodily motion, as that is an overall indicator of daily activity and exercise intensity. The most common technique for measuring free-living activity is to use accelerometers, which can measure acceleration. When carried by a person, such devices can provide a useful indicator of the overall duration and intensity of the person's movement. such devices are often sold commercially as pedometers (step-counters). A limitation of this technology is the requirement for the person to carry the device, and the limitations of the algorithms for converting measured acceleration into activity patterns.

25 [0013] What is needed then, is a method, system and apparatus for measuring heart rate, respiratory rate and effort, and motion, and which overcomes various limitations of conventional approaches.

30 [0014] WO 2004/013611 A relates to an apparatus and methods for performing remote detection of physiological activity. One aspect involves obtaining information concerning respiration and heart function. In one embodiment, a source containing an oscillator is configured to illuminate the subject with electromagnetic signal beam and a receiver is configured to observe changes in the amplitude of the electromagnetic signal reflected by the subject.

35 [0015] WO 96/11630 A1 relates to a method and a device for determining threshold values for a person's energy metabolism. A testee is subjected to a gradually increasing stress in order to obtain the threshold values for his energy metabolism. The pulse rate of the testee is measured during the performance, the pulse shape of an ECG signal caused by the pulse is analyzed in order to determine the timing point of the ECG signal corresponding to each pulsation and  
40 in order to determine the intervals between the timing points of successive ECG signals. The respiratory frequency of the testee is calculated on the basis of the variations in the intervals between the timing points of the ECG signals. The respiratory frequency of the testee is calculated as a function of the pulse rate during the performance, or the respiratory volume is estimated on the basis of the degree of the variation in the timing points of the ECG signals.

## 45 SUMMARY

[0016] The invention is defined by the features of the independent claims 1 and 12. Further preferred embodiments of the invention are defined in the dependent claims. This disclosure provides various embodiments and aspects of an apparatus, system, and method for monitoring heart rate, breathing and motion. In one embodiment, a sensor unit can  
50 be either worn (for ambulatory use), or placed in a fixed position (e.g., as part of an exercise cycling machine). The sensor communicates with a processor and display and, in one aspect, the sensor, processor, and display may be physically implemented in the same unit. The processor may be used to extract information about heart rate, breathing and motion, and higher order information (e.g., the current heart rate relative to previous epochs). The display is configured to provide feedback to the user, such as displaying current heart rate or breathing rate. Feedback may also be provided  
55 using sound (e.g., a beep for every heart beat detected). In one aspect, a complete system may include one or more of a motion sensor (for detection of general bodily movement, respiration, and heart rate); a processing capability (to derive signals directly related to cardiac activity, breathing and motion, and hence to derive parameters such as breathing rate, heart rate, and movement); a display capability (to provide visual feedback); an auditory capability (to provide acoustic

feedback, e.g., a tone whose frequency varies with breathing, or a beep with every detected heart beat); and/or a communications capability (wired or wireless) to transmit acquired data to a separate unit. This separate unit may be configured to carry out the processing, display and auditory functions mentioned above.

[0017] In one or more embodiments, a system for measuring, analyzing, and displaying respiration, cardiac activity, and non-cardiorespiratory bodily movement includes one or more sensors configured to receive a reflected radio-frequency (RF) signal off a living subject, wherein the RF signal comprises a pulsed RF signal. A processor is configured to analyze the reflected signal to determine a measurement of physiological activity of the living subject. An output is arranged to provide selected information relating to the physiological activity to a user of the system. In another aspect, a system for measuring, analyzing, and displaying respiration, cardiac activity, and non-cardiorespiratory bodily movement includes one or more sensors configured to receive a reflected radio-frequency (RF) signal off a living subject, wherein the RF signal comprises a single RF frequency. In another aspect, a system for measuring, analyzing, and displaying respiration, cardiac activity, and non-cardiorespiratory bodily movement includes one or more sensors configured to receive a reflected radio-frequency (RF) signal off a living subject and a processor configured to analyze the reflected signal to determine a measurement of physiological activity of the living subject. The measured physiological activity may include two or more physiological signals. In one or more aspects of the embodiments, the physiological activity includes at least two of a respiratory movement, cardiac activity, and non-cardiorespiratory bodily movement. The system may further comprise a transmitter that generates the radio frequency signals that are reflected off the living subject, and the power levels emitted by the system are safe for continuous use with humans. The monitored physiological activity corresponds to movements which can include breathing, cardiac activity, and large movements of the body

(such as an arm swinging)

[0018] In another embodiment, a method for measuring, analyzing, and displaying respiration, cardiac activity, and bodily movement includes receiving radio-frequency signals reflected from a human subject; analyzing the reflected signals to produce measurements relating to respiration, cardiac activity, and bodily movement of the human subject; and providing selected information to a user of the system.

#### BRIEF DESCRIPTION OF THE DRAWINGS

[0019] Embodiments of the disclosure will now be described with reference to the accompanying drawings in which:

FIG. 1 is a diagram illustrating a schematic of how a system of an embodiment might be used in assessment of exercise and activity; FIG. 1(a) shows an embodiment of the system as an upper arm cuff band; FIG. 1(b) shows the system as a clip-on device which can be attached to a shirt-pocket; FIG. 1(c) shows an example of the device worn as a pendant around the neck; FIG. 1(d) illustrates the cardiorespiratory monitor in a treadmill fitness system; FIG. 1(e) gives an example of the cardiorespiratory monitor embedded in an exercise cycle machine; and FIG. 1(f) shows the device as a wristwatch-like device while swimming.

FIG. 2 provides a schematic representation of a sensor element of one embodiment.

FIG. 3 provides a representative raw sensor signal obtained when the sensor is close to the surface of the body (e.g., within 5 cm).

The upper curve of FIG. 4 shows the time course of a photoplethysmographic signal obtained from an adult subject, where each heart beat is associated with a distinctive pattern and the lower curve of FIG. 4 illustrates the signal obtained simultaneously from the same subject at a distance of several meters, showing that there are separate respiration and cardiac signals.

FIG. 5 illustrates the result of applying a technique for accessing and visualizing the breathing and cardiac information using a time-frequency representation such as the short-time Fourier transform and a peak-finding algorithm.

FIG. 6 provides a schematic of the system when multiple radio frequency (RF) blocks similar to those depicted in FIG. 2 are used for transmission and reception of the radio waves.

FIG. 7 illustrates a schematic of the display for the system.

FIG. 8 shows a schematic of how the system can calculate a parameter related to a ventilatory threshold.

## DETAILED DESCRIPTION

**[0020]** FIG. 1 is a diagram illustrating a schematic of various environments in which the system might be used in assessment of exercise and activity. First, the device can be used in ambulatory applications (where the person can move freely since they are wearing the cardiorespiratory monitor). FIG. 1(a) shows an embodiment of the system as an upper arm cuff band. FIG. 1(b) shows the system as a clip-on device which can be attached to a shirt-pocket. FIG. 1(c) shows an example of the device worn as a pendant around the neck, FIG. 1(d) illustrates the cardiorespiratory monitor in a treadmill fitness system, FIG. 1(e) gives an example of the cardiorespiratory monitor embedded in an exercise cycle machine and FIG. 1(f) shows the device as a wristwatch-like device while swimming. The device can also be configured for use with other known exercise equipment.

**[0021]** FIG. 2 provides a schematic representation of an exemplary sensor element. The sensor element uses radio-frequency sensing and processing to extract bodily motion associated with breathing and heart rate. The body motion associated with respiration is readily observable as breathing induces motion of the thorax and abdomen. The motion associated with cardiac activity is less obvious, but physiologists use the term "ballistocardiogram" to refer to the pressure wave apparent at the surface of the skin due to the cardiac contraction. This small motion can be detected by a sensitive motion sensor.

**[0022]** The system transmits a radio-frequency signal towards a person. The reflected signal is then received, amplified and mixed with a portion of the original signal, and the output of this mixer is then low pass filtered. The output of this mixer can therefore be considered as a processed time-domain signal derived from the reflected radio-frequency signal. This resulting signal contains information about the movement, respiration and cardiac activity of the person, and is referred to as the raw sensor signal. In FIG. 2, the radio frequency sensor components of the system are illustrated with a pulsed continuous wave signal for illustration. In an alternative embodiment, the system may also use quadrature transmission in which two carrier signals 90 degrees out of phase are used. In the limits that the pulse becomes very short in time, such a system can be recharacterized as an ultrawideband (UWB) radio-frequency sensor. Improved signal-to-noise ratio can also be obtained by using a continuous wave system, in which the RF signal is continuously transmitted.

**[0023]** FIG. 3 gives a representative raw sensor signal obtained when the sensor is close to the surface of the body (e.g., within 5 cm). The dominant components in the received raw sensor signal will be the ballistocardiogram, and the relative motion of the sensor and person. To reduce the relative motion, the sensor unit may be mechanically fixed to the skin using an elastic restraining mechanism, or similar. FIG. 3 is an example of the raw sensor signal with a dominant ballistocardiogram component (in this case, measured at the inside of the elbow on the upper arm). This represents 5 seconds of data collected using a 26 GHz pulsed continuous wave prototype of the system. In such cases, heart beats will be determined by a threshold passing technique (a pulse is associated with the point where the signal is greater or less than the threshold). In more complex (but typical cases), the ballistocardiogram will present a more complicated but repeatable pulse shape. Therefore a pulse shape template, implemented, for example, by a matched filter, can be correlated with the acquired cardiac signal, and places where the correlation is high will be used as the heart beat locations. Accordingly the system recognizes cardiac beats of the living subject by identifying peaks in the processed time-domain signal, or by carrying out a time-domain correlation of the received signal with a prototypical cardiac signal, or by other means. This processing results in a series of time markers identifying the occurrence time of each heart beat. These time markers can be used by a processor to audibly signal each heart beat of the living subject, or to light up an intermittent icon on a display.

**[0024]** Given a time marker of when each event occurred, calculating heart rate is possible. For the signal shown in FIG. 3, we will label the point at which the signal crosses a threshold as a cardiac event time  $B_n$  (where  $n$  is the beat number). From that we can calculate the instantaneous heart rate as  $1/BB_n$  where  $BB_n = B_n - B_{n-1}$  (the interbeat interval). In practice, it may be more useful to define the average heart rate over a time epoch (e.g., 10 seconds). This can be achieved by counting the number of beats which occurred within a 10-second window, and then dividing by 10 to obtain the average number of beats per second. For the example shown in FIG. 3, 5.9 beats occurred within a five second window, so that the reported heart rate is  $(5.9/5) \times 60 = 71$  beats per minute.

**[0025]** When the device is further away from the body (e.g., 1 meter or greater) the received raw sensor signal will be a combination of gross bodily movement, respiration, and cardiac activity. The upper curve of FIG. 4 shows the time course of a photoplethysmographic signal obtained from an adult subject, where each heart beat is associated with a distinctive pattern. The lower curve of FIG. 4 illustrates the signal obtained simultaneously from the same subject at a distance of several meters, and shows that there are separate respiration and cardiac signals. Specifically, the circles highlight the skin movement associated with each cardiac beat. The skin motion is typically aligned with the dichrotic peak in the pulse waveform.

**[0026]** In cases of usage further away from the body, as described above the received raw signal contains information about breathing and heart rate, as well as gross bodily motion. A technique for accessing and visualizing the breathing and cardiac information is to use a time-frequency representation such as the short-time Fourier transform and a peak-

finding algorithm. The processor can also be configured to recognize the physiological activity of the living subject using frequency domain processing of the received signals. The detailed description of this is provided below, but broadly it consists of taking the spectrum of an epoch centered at time  $t_1$ , and finding spectral peaks which correspond best to the expected breathing and cardiac frequencies. For that epoch, the two peaks can be noted, and considered as the cardiac and respiratory frequency at time  $t_1$ . A new epoch can then be formed which overlaps with the previous epoch, but which is now centered at  $t_2$ , and two new frequencies can be calculated which form the cardiac and respiratory frequency at time  $t_2$ . FIG. 5 illustrates the result of applying this technique to 50 seconds of data, with a window length of 20 seconds, and an overlap of 19 seconds. The breathing component at about 20 breaths per minute, and the cardiac component at approximately 70 beats per minute can be tracked over time..

**[0027]** FIG. 6 provides a schematic of the system when multiple radio frequency (RF) blocks are used for transmission and reception of the radio waves. In this schematic, there are three independent RF blocks, each capable of receiving and transmitting the radio waves. The individual RF blocks are similar to that shown earlier in FIG. 2. They will generate independent copies of the overall signal from the person being sensed, so that independent motion components can be extracted using signal processing (e.g., breathing, cardiac signal, and upper body motion). Note that the antennas can also transmit at separate frequencies if required. Physical separation of the antennas (e.g., by greater than a quarter wavelength) will also make the transmission paths statistically independent.

**[0028]** FIG. 7 illustrates a schematic of the display for the system. The system will typically display parameters such as current heart rate, current breathing rate, and the degree of respiratory sinus arrhythmia. Since the system may be easily integrated with a device capable of measuring position (e.g., using the Global Positioning System - GPS), position may also be displayed on the system output. The system will also have the capability to display useful trends for the user, such as the heart rate over the past hour, the values of RSA over the last week, etc. A further advantage of incorporating position information is that it allows the system to be used in standard tests of fitness. For example, a good marker of general cardiovascular health is the "one mile fitness test". In this, the person walks a mile briskly, and records their pulse at the end of the one-mile. A positioning system will automatically inform the person when they have walked a mile, and record the heart rate at that time. Similarly, in clinical applications, the six-minute walk test is routinely used. In this, a person is asked to walk for six minutes at their own pace, and the distance covered is a marker of their general cardiovascular health. An integrated positioning system will automatically keep a track of the distance covered, and the heart and respiration rate during that period. So the utility of the system can be augmented by including a positioning system configured to monitor a location of the living subject, and to simultaneously track their physiological activity.

**[0029]** FIG. 8 shows a schematic of how the system can calculate a parameter related to ventilatory threshold. The device can record the heart rate and breathing rate over a period of exercise. At the end of the exercise, the device can plot heart rate versus the average breathing rate seen at that heart rate. A schematic representation of such a curve is shown in FIG. 8. If the exercise intensity is close to the person's maximum, then the curve can be used to identify a "kink" at which breathing rate increases more rapidly with respect to heart rate. The breathing rate at which this occurs can act as a surrogate of ventilatory threshold (VT). The value of this parameter can be tracked over the course of weeks or months, as the person undergoes a fitness program.

**[0030]** In one embodiment, the system includes a sensor unit, and a monitoring and display unit where results can be analysed, visualized and communicated to the user. The sensor unit and the display/monitoring unit can be incorporated into a single stand-alone device, if required. The device may include one or more of a motion sensor (for detection of general bodily movement, respiration, and heart rate); a processing capability (to derive signals directly related to cardiac activity, breathing and motion, and hence to derive parameters such as breathing rate, heart rate, and movement); a display capability (to provide visual feedback); an auditory capability (to provide acoustic feedback, e.g., a tone whose frequency varies with breathing, or a beep with every detected heart beat); a communications capability (wired or wireless) to transmit acquired data to a separate unit. This separate unit can carry out the processing, display and auditory capability mentioned above.

**[0031]** More specifically, the typical sensor will include one or more radio-frequency Doppler sensors, which transmit radio-frequency energy (typically in the range of 100 MHz to 100 GHz), and which use the reflected received signal to construct a motion signal. For ease of explanation, we will first restrict our discussion to the case where only one sensor unit is used. The principle by which this works is that a radio-frequency wave

$$s(t) = u(t) \cos(2\pi f_c t + \theta) \quad (1)$$

is transmitted from the unit. In this example, the carrier frequency is  $f_c$ ,  $t$  is time, and  $\theta$  is an arbitrary phase angle.  $u(t)$  is a pulse shape. In a continuous wave system, the value is always one, and can be omitted from Eq. (1). More generally, the pulse will be defined as

$$u(t) = \begin{cases} 1, & t \in [kT, kT + T_p], k \in Z \\ 0 & \end{cases} \quad (2)$$

where  $T$  is the period width, and  $T_p$  is the pulse width. Where  $T_p \ll T$ , this becomes a pulsed continuous wave system. In the extreme case, as  $T_p$  becomes very short in time, the spectrum of the emitted signal becomes very wide, and the system is referred to as an ultrawideband (UWB) radar or impulse radar. Alternatively, the carrier frequency of the RF transmitted signal can be varied (chirped) to produce a so-called frequency modulated continuous wave (FMCW) system.

**[0032]** This radio frequency signal is generated in the sensor system using a local oscillator coupled with circuitry for applying the pulse gating. In the FMCW case, a voltage controlled oscillator is used together with a voltage-frequency converter to produce the RF signal for transmission. The coupling of the RF signal to the air is accomplished using an antenna. The antenna can be omnidirectional (transmitting power more-or-less equally in all directions) or directional (transmitting power preferentially in certain directions). It can be advantageous to use a directional antenna in this system so that transmitted and reflected energy is primarily coming from one direction. The system is compatible with various types of antenna such as simple dipole antennas, patch antennas, and helical antennas, and the choice of antenna can be influenced by factors such as the required directionality, size, shape, or cost. It should be noted that the system can be operated in a manner which has been shown to be safe for human use. The system has been demonstrated with a total system emitted average power of <1 mW (0 dBm) and lower. The recommended safety level for RF exposure is 1 mW/cm<sup>2</sup>. At a distance of 1 meter from a system transmitting at 0dBm, the equivalent power density will be at least 100 times less than this recommended limit.

**[0033]** In all cases, the emitted signal will be reflected off objects that reflect radio waves (such as the air-body interface), and some of the reflected signal will be received back at the transmitter. The received signal and the transmitted signal can be multiplied together in a standard electronic device called a mixer (either in an analog or digital fashion). For example, in the CW case, the mixed signal will equal

$$m(t) = \gamma \cos(2\pi f_c t) \cos(2\pi f_c t + \phi(t)) \quad (3)$$

where  $\phi(t)$  is the path difference of the transmitted and received signals (in the case where the reflection is dominated by a single reflective object), and  $\gamma$  is the attenuation experienced by the reflected signal. If the reflecting object is fixed, then  $\phi(t)$  is fixed, and so is  $m(t)$ . In the case of interest to us, the reflecting object (e.g., chest) is moving, and  $m(t)$  will be time-varying. As a simple example, if the chest is undergoing a sinusoidal motion due to respiration:

$$resp(t) = \cos(2\pi f_m t) \quad (4)$$

then the mixed signal will contain a component at  $f_m$  (as well as a component centred at  $2f_c$  which can be simply removed by filtering). The signal at the output of the low pass filter after mixing is referred to as the raw sensor signal, and contains information about motion, breathing and cardiac activity.

**[0034]** The amplitude of the raw sensor signal is affected by the mean path distance of the reflected signal, leading to detection nulls and peaks in the sensor (areas where the sensor is less or more sensitive). This effect can be minimised by using quadrature techniques in which the transmitter simultaneously transmits a signal 90 degrees out of phase (the two signals will be referred to as the I and Q components). This will lead to two reflected signals, which can be mixed, leading eventually to two raw sensor signals. The information from these two signals can be combined by taking their modulus (or other techniques) to provide a single output raw sensor signal.

**[0035]** In the UWB case, an alternative method of acquiring a raw sensor signal may be preferred. In the UWB case, the path distance to the most significant air-body interface can be determined by measuring the delay between the transmitted pulse and peak reflected signal. For example, if the pulse width is 1 ns, and the distance from the sensor to the body is 0.05m, then the total time  $m(\tau)$  elapsed before a peak reflection of the pulse will be  $0.1/(3 \times 10^8) \text{ s} = 0.33 \text{ ns}$ . By transmitting large numbers of pulses (e.g., a 1 ns pulse every 1  $\mu\text{s}$ ) and assuming that the path distance is changing slowly, we can derive a raw sensor signal as the average of the time delays over that period of time.

**[0036]** In this way, the radio-frequency sensor can acquire the motion of the part of the body at which the system is aimed. Directional selectivity can be achieved using directional antennas, or multiple RF transmitters. The combined motion of the thorax (which is a combination primarily of a respiration and cardiac signal) acquired in this way using a pulsed continuous wave system is shown in the lower curve of FIG 4. We stress however that a continuous wave, an FMCW, or a UWB radar can also obtain similar signals.

**[0037]** Moreover, since the bulk of the reflected energy is received from the surface layer of the skin, this motion sensor can also obtain the ballistocardiogram, which is the manifestation of the beating of the heart at the surface of the skin due to changes in blood pressure with each beat. An example of a surface ballistocardiogram obtained with an RF motion sensor has already been shown in FIG 3. In that case, the ballistocardiogram is emphasized by the sensor being

close to the skin (upper arm) and no respiratory component is visible.

**[0038]** In order to improve the qualities of the measured sensor signals, the physical volume from which reflected energy is collected by the sensor can be restricted using various methods. For example, the transmission antenna can be made "directional" (that is, it transmits more energy in certain directions), as can the receiver antenna. A technique called "time-domain gating" can be used to only measure reflected signals which arise from signals at a certain physical distance from the sensor. A practical way to implement this is to ensure that received signal is mixed with a transmitted signal over a predefined period of time. For example, imagine that a 12 ns pulse is emitted at time  $t=0$ ns. If the reflecting object is 150 cm away, the reflected pulse will be first received after 10 ns (since it takes light 10 ns to cover 300 cm). Assume a second object 300 cm away whose detection is not desired. The reflected pulse from this second object will not first arrive till time  $t=20$  ns. Therefore if mixing between the transmitted and received pulses is only allowed in the time period from  $t=10$  ns to  $t=15$  ns, all the information received will relate only to the first reflecting object. Frequency domain gating can be used to restrict motions of the reflected object above a certain frequency.

**[0039]** In a simple embodiment of the system, a single antenna will be used, with a single carrier frequency. This antenna will act as both the transmit and receive antenna. However, in principle, multiple receive and transmit antennas can be used, as can multiple carrier frequencies. In the case of measurements at multiple frequencies (e.g., at 500 MHz and 5 GHz) the lower frequency can be used to determine large motions accurately without phase ambiguity, which can then be subtracted from the higher-frequency sensor signals (which are more suited to measuring small motion, such as the cardiac signature).

**[0040]** All of these sensor inputs are fed into the unit for processing and display purposes, and for possible transmission to a separate unit (the monitoring unit).

**[0041]** The system then uses its processing capability to combine the sensor inputs to provide a number of useful outputs, and to display these outputs in a meaningful manner. These steps are carried out in the following manner.

**[0042]** The cardiorespiratory monitor is primarily designed to provide information about heart rate and respiration. When the person is moving, the sensor signal will often be dominated by motion, in which case processing is required to reduce motion artefact problems. A preferred technique for calculating respiration and heart beat activity in the presence of noise is as follows.

**[0043]** A raw signal is acquired for an epoch of desired length (e.g., 20 seconds). The spectrum of this period of the signal is estimated using a technique such as the smoothed averaged periodogram. In general, since respiration occurs typically at a frequency from 10 to 25 breaths per minute (about 0.15-0.45 Hz), and cardiac activity occurs in the range 60-120 beats per minute (1 to 2 Hz), the spectrum of the signal will have two peaks in the ranges 0.15-0.4Hz, and 1 to 2 Hz. The frequency at which these peaks occur can be referred to as the breathing frequency and the heart rate respectively, for that epoch. The results of the spectral analysis for each epoch can be arranged in time to form a time-frequency respiration plot, which is a useful means of visualizing the overall respiratory and cardiac activity. Note that the epochs can overlap, so that a breathing frequency and cardiac frequency can be calculated at arbitrary times (e.g., FIG. 5 shows the case where the analyzed epochs are one second apart).

**[0044]** The presence of large motion artefacts may confound the processing described above, so in some cases it may be necessary to preprocess the signal to reduce the effect of motion artefact. Since large movements lead to large-magnitude signals in the processed time domain, a processor can be configured to measure the energy content of a filtered signal, so that periods of bodily motion of the living subject are recognized by comparing the energy content to a predetermined energy value. A method for doing this is to prefilter the epoch with a linear high pass filter (to remove all frequencies below 0.05 Hz, for example). An alternative would be to median filter the data with a window length of 10 seconds, and remove the median filtered signal from the original signal. Alternatively, we can recognise periods of motion by their high energy content. These periods of motion may lead to artifacts in the processed signal, so suitable spectral analysis that removes periods of measurement can be used. Specifically, when calculating the spectrum of the epoch, the data from these high motion sections is not included in the estimation (using a technique called Lomb's periodogram which provides spectral estimates from data with missing segments).

**[0045]** An alternative processing technique for improving the accuracy of the heart beat and respiration detection is to acquire multiple signals from multiple sensors. This is particularly beneficial in the case of high motion artefact, such as the case when the system is used in a treadmill setting with person jogging in the field of the sensors. In such a case, a preferred solution is to have multiple sensors (e.g.  $m$ , where  $m$  might typically be in the range four to sixteen, but can vary from one to any number). In practice (for cost reasons), it is probably efficient to have a single transmit antenna, and multiple receive antennas only, rather than having each antenna be both transmitting and receiving. Likewise it may be beneficial to have the antenna or antennas generate RF signals at multiple frequencies. However, an embodiment of the method is where one transmitter is used, and  $m$  signals are received in the sensor (each path will experience a

different phase delay and amplitude change). A further useful embodiment of the system is one in which there are multiple sensors operating at different frequencies, wherein a relatively low frequency is used to estimate a large bodily movement of the living subject, and a relatively high frequency is used to estimate a smaller movement of the living subject. For example, a sensor operating at 1 GHz would be useful for detecting movement in the centimeter range, while a sensor operating in the same system at 100 GHz could help detect movement of millimetres.

**[0046]** A useful model is to collect the  $m$  received signal into a vector of signals  $\mathbf{x}$ :

$$\mathbf{x} = \begin{bmatrix} x_1 \\ x_2 \\ \vdots \\ x_m \end{bmatrix}$$

It can be reasonable assumed that each signal represents a mixture of reflections from multiple sources (e.g., one from breathing, one from cardiac activity, one from left arm movement, etc.). Therefore, the received signals represent a linear mixture of sources  $\mathbf{w}$ , so that

$$\mathbf{w} = \mathbf{A}\mathbf{x}$$

where

$$\mathbf{A} = \begin{bmatrix} \mathbf{a}_{11} & \mathbf{a}_{12} & \dots \\ \mathbf{a}_{21} & & \ddots \\ & \dots & \mathbf{a}_{mm} \end{bmatrix}$$

**[0047]** In practice, we are interested in obtaining the signals  $\mathbf{w}$ , since they will cleanly separate the different components of interest. A critical factor which aids us in this analysis is that the source signals are independent (i.e., the cardiac signal is independent of breathing, which is independent of arm motion, for example). There are many algorithms which map the received  $\mathbf{x}$  back to  $\mathbf{w}$ , under this assumption, and these are referred to as Independent Component Analysis (ICA) techniques. In particular, we can further optimise our solution by imposing certain constraints on the source signals (e.g., it should have a dominant frequency in the range 0.15 to 0.25 Hz). Such algorithms are called constrained ICA algorithms. A useful survey of techniques in ICA analysis can be found in "Independent component analysis for biomedical signals," C.J. James and C.W. Hesse, *Physiological Measurement* vol. 26 (1), R15-R39, Feb 2005.

**[0048]** As well as determining respiration rate and amplitude, cardiac rate, and motion, the system provides for means to combine signals for calculation of further useful outputs. For example, a useful marker of overall cardiorespiratory health is respiratory sinus arrhythmia (RSA). This measures the influence of breathing on heart rate, and the stronger the coupling, the better the overall cardiorespiratory health. In general, there is utility in configuring a processor to calculate a parameter of respiratory sinus arrhythmia using the measured heart rate and breathing rate information. One approach may be to calculate a parameter of respiratory sinus arrhythmia using cross-spectral analysis of measured heart rate and breathing rate signals.

**[0049]** However, a variety of techniques exists for calculating RSA. One embodiment for this system is as follows.

**[0050]** An epoch of measurement (e.g., 60 seconds) is taken, over which the person's activity is fairly constant. The coherence between the cardiac signal and the respiratory signal is obtained (coherence is typically defined as the ratio of the cross spectral density of two signals divided by the square root of the power spectral densities of the signals taken separately.) The highest value of the coherence in a defined band (e.g., 0.15-0.25 Hz) is taken as a measure of the coupling between heart rate and respiration. This coherence value can be tracked across different exercise sessions, or compared against a population mean.

**[0051]** A further useful measure of cardiorespiratory performance obtained by the system is the estimation of ventilatory threshold from heart rate measurements only, or combinations of heart rate and breathing rate. The system can be configured to calculate useful parameters of cardiorespiratory performance (such as ventilatory threshold) by relating a measured heart rate to a measured breathing rate over a defined period of measurement. A preferred embodiment for capturing ventilatory threshold from combined heart rate and breathing rate is to examine a curve of cardiac beats per

breathing cycle versus breathing rate. In such a curve, there is a characteristic kink, which occurs at the frequency corresponding to the ventilatory threshold.

[0052] Finally, the system provides means for communicating useful information to its user. The display means may be in a format such as a wristwatch, with parameters such as current heart rate, current breathing rate, and position. The user may also have the ability to view trend screens, which show charts of previous heart rates over different time scales, previous breathing rates, as well as derived parameters such as estimated RSA coherence. In some use cases, it is beneficial to design an enclosure which can contain one or more sensors, the processor, and the display. This enclosure could be suitable for being held in a hand of the user for convenience of use. The enclosure could also incorporate other functionality such as telecommunications or positioning systems (e.g., a cellular phone handset would be a specific embodiment of such an enclosure).

## STATEMENT OF INDUSTRIAL APPLICABILITY

[0053] This disclosure has application in the medical, safety, and sports fitness fields, for example, by monitoring motion, breathing, and heart rate of living beings, e.g., humans, in a convenient and low-cost fashion. Such monitoring is useful, for example, in the assessment of cardiorespiratory markers of fitness and activity of humans.

## Claims

1. A system for measuring and analyzing respiration, cardiac activity and non-cardiorespiratory bodily motion and providing a parameter of cardiorespiratory performance of a living subject, the system comprising:
  - one or more sensors configured to receive a reflected radio-frequency (RF) signal off the living subject;
  - a mixer configured to mix the reflected RF signal over a predefined period with an RF signal transmitted toward the living subject to obtain a raw motion signal;
  - a processor configured to:
    - determine an energy content of the raw motion signal;
    - compare the energy content to a predetermined energy value to recognize periods of large bodily motion of the living subject;
    - derive the spectrum of the raw motion signal while discarding data from large bodily motion sections;
    - analyze the spectrum of the raw motion signal to determine a breathing rate and heart rate of the living subject; and
    - calculate a ventilatory threshold as a parameter of cardiorespiratory performance by relating the determined breathing rate and heart rate over a defined period of measurement; and
  - an output arranged to provide selected information relating to the respiration and cardiac activity including the calculated ventilatory threshold.
2. The system of claim 1, wherein the selected information is selected from the group consisting of a respiratory movement, a respiratory depth, a respiratory sinus arrhythmia (RSA), cardiac activity, and non-cardiorespiratory bodily movement.
3. The system of claim 1, wherein the processor is configured to recognize respiration or cardiac activity of the living subject using a processed time-domain signal derived from the reflected radio-frequency signal.
4. The system of claim 3 wherein the cardiac activity comprises cardiac beats of the living subject recognized by identifying peaks in the processed time-domain signal.
5. The system of claim 1, wherein the processor is configured to recognize the respiration or cardiac activity of the living subject using frequency domain processing of the received signal.
6. The system of claim 1, further comprising: a filter, wherein the processor is configured to measure the energy content of a filtered signal.
7. The system of claim 1, further comprising multiple sensors configured to receive the reflected RF signal.

8. The system of claim 1, wherein the processor is configured to calculate a parameter of respiratory sinus arrhythmia using measured heart rate and breathing rate information.

5 9. The system of claim 1, further comprising multiple sensors operating at different frequencies, wherein a relatively low frequency is used to estimate the large bodily motion of the living subject, and a relatively high frequency is used to estimate a smaller motion of the living subject.

10 10. The system of claim 1, further comprising an enclosure configured to enclose the one or more sensors, the processor, and the output.

11. The system of claim 1, wherein the RF signal comprises a single frequency RF signal.

15 12. A method for measuring and analyzing respiration, cardiac activity and non-cardiorespiratory bodily motion and providing a parameter of cardiorespiratory performance of a living subject, the method comprising:

- transmitted a radio-frequency (RF) signal to the living subject;
- receiving a radio-frequency (RF) signal reflected from the living subject;
- mixing the reflected radio-frequency (RF) signal with the transmitted radio-frequency (RF) signal over a pre-determined period to obtain a raw motion signal;
- 20 - determining an energy content of the raw motion signal;
- comparing the energy content to a predetermined energy value to recognize periods of large bodily motion of the living subject;
- deriving the spectrum of the raw motion signal while discarding data from large bodily motion sections;
- analyzing the spectrum of the raw motion signal to determine a breathing rate and a heart rate of the living subject,;
- 25 - calculating a ventilatory threshold as parameter of cardiorespiratory performance by relating the determined breathing rate and the heart rate over a defined period of measurement; and
- outputting one or more selected information relating to the respiration and cardiac activity including the calculated ventilator threshold.

30 13. The method of claim 12, wherein said outputting comprises displaying one or more measurements relating to the respiration of the living subject.

35 14. The method of claim 12, further comprising: measuring energy content of a filtered signal.

### Patentansprüche

40 1. System zum Messen und Analysieren von Respiration, Herzaktivität und nichtkardiorespiratorischer Körperbewegung sowie Bereitstellen eines Parameters der kardiorespiratorischen Leistung eines lebenden Subjekts, wobei das System aufweist:

einen oder mehrere Sensoren, die so konfiguriert sind, dass sie ein reflektiertes Hochfrequenz- (HF) Signal vom lebenden Subjekt empfangen;

45 einen Mischer, der so konfiguriert ist, dass er das reflektierte HF-Signal über eine vordefinierte Periode mit einem zum lebenden Subjekt gesendeten HF-Signal mischt, um ein Rohbewegungssignal zu erhalten;

einen Prozessor, der so konfiguriert ist, dass er

einen Energiegehalt des Rohbewegungssignals bestimmt;

50 den Energiegehalt mit einem vorbestimmten Energiewert vergleicht, um Perioden großer Körperbewegung des lebenden Subjekts zu erkennen;

das Spektrum des Rohbewegungssignals ableitet, während er Daten aus großen Körperbewegungsteilstücken verwirft;

das Spektrum des Rohbewegungssignals analysiert, um eine Atemfrequenz und eine Herzfrequenz des lebenden Subjekts zu bestimmen; und

55 einen ventilatorischen Schwellwert als Parameter der kardiorespiratorischen Leistung berechnet, indem er die bestimmte Atemfrequenz und Herzfrequenz über eine definierte Messperiode in Beziehung setzt; und

## EP 2 078 270 B1

einen Ausgang, der so angeordnet ist, dass er ausgewählte Informationen in Beziehung zur Respiration und Herzaktivität, darunter den berechneten ventilatorischen Schwellwert, bereitstellt.

- 5 2. System nach Anspruch 1, wobei die ausgewählten Informationen aus der Gruppe ausgewählt sind, die aus einer respiratorischen Bewegung, einer respiratorischen Tiefe, einer respiratorischen Sinusarrhythmie (RSA), Herzaktivität und nichtkardiorespiratorischer Körperbewegung besteht.
- 10 3. System nach Anspruch 1, wobei der Prozessor so konfiguriert ist, dass er Respiration oder Herzaktivität des lebenden Subjekts mit Hilfe eines verarbeiteten Zeitbereichssignals erkennt, dass aus dem reflektierten Hochfrequenzsignal abgeleitet ist.
- 15 4. System nach Anspruch 3, wobei die Herzaktivität Herzschläge des lebenden Subjekts aufweist, die durch Identifizieren von Peaks im verarbeiteten Zeitbereichssignal erkannt werden.
- 20 5. System nach Anspruch 1, wobei der Prozessor so konfiguriert ist, dass er die Respiration oder Herzaktivität des lebenden Subjekts mit Hilfe von Frequenzbereichsverarbeitung des empfangenen Signals erkennt.
- 25 6. System nach Anspruch 1, das ferner aufweist: ein Filter, wobei der Prozessor so konfiguriert ist, dass er den Energiegehalt eines gefilterten Signals misst.
- 30 7. System nach Anspruch 1, das ferner mehrere Sensoren aufweist, die so konfiguriert sind, dass sie das reflektierte HF-Signal empfangen.
- 35 8. System nach Anspruch 1, wobei der Prozessor so konfiguriert ist, dass er einen Parameter von respiratorischer Sinusarrhythmie mit Hilfe von gemessenen Herzfrequenz- und Atemfrequenzinformationen berechnet.
- 40 9. System nach Anspruch 1, das ferner mehrere Sensoren aufweist, die mit unterschiedlichen Frequenzen arbeiten, wobei eine relativ niedrige Frequenz verwendet wird, die große Körperbewegung des lebenden Subjekts zu schätzen, und eine relativ hohe Frequenz verwendet wird, eine kleinere Bewegung des lebenden Subjekts zu schätzen.
- 45 10. System nach Anspruch 1, das ferner ein Gehäuse aufweist, das so konfiguriert ist, dass es den einen oder die mehreren Sensoren, den Prozessor und den Ausgang umschließt.
- 50 11. System nach Anspruch 1, wobei das HF-Signal ein einfrequentes HF-Signal aufweist.
- 55 12. Verfahren zum Messen und Analysieren von Respiration, Herzaktivität und nichtkardiorespiratorischer Körperbewegung sowie Bereitstellen eines Parameters der kardiorespiratorischen Leistung eines lebenden Subjekts, wobei das Verfahren aufweist:
  - Senden eines Hochfrequenz- (HF) Signals zum lebenden Subjekt;
  - Empfangen eines Hochfrequenz- (HF) Signals, das vom lebenden Subjekt reflektiert wird;
  - Mischen des reflektierten Hochfrequenz- (HF) Signals mit dem gesendeten Hochfrequenz- (HF) Signal über eine vorbestimmte Periode, um ein Rohbewegungssignal zu erhalten;
  - Bestimmen eines Energiegehalts des Rohbewegungssignals;
  - Vergleichen des Energiegehalts mit einem vorbestimmten Energiewert, um Perioden großer Körperbewegung des lebenden Subjekts zu erkennen;
  - Ableiten des Spektrums des Rohbewegungssignals, während Daten aus großen Körperbewegungsteilstücken verworfen werden;
  - Analysieren des Spektrums des Rohbewegungssignals, um eine Atemfrequenz und eine Herzfrequenz des lebenden Subjekts zu bestimmen;
  - Berechnen eines ventilatorischen Schwellwerts als Parameter der kardiorespiratorischen Leistung, indem die bestimmte Atemfrequenz und die Herzfrequenz über eine definierte Messperiode in Beziehung gesetzt werden; und
  - Ausgeben einer oder mehrerer ausgewählter Informationen in Beziehung zur Respiration und Herzaktivität, darunter des berechneten ventilatorischen Schwellwerts.
13. Verfahren nach Anspruch 12, wobei das Ausgeben aufweist: Anzeigen einer oder mehrerer Messungen in Beziehung zur Respiration des lebenden Subjekts.

14. Verfahren nach Anspruch 12, das ferner aufweist: Messen des Energiegehalts eines gefilterten Signals.

### Revendications

5

1. Système pour mesurer et analyser la respiration, l'activité cardiaque et le mouvement corporel non cardiorespiratoire et fournir un paramètre de performance cardiorespiratoire d'un sujet vivant, le système comprenant :

10

- un ou plusieurs capteurs configurés pour recevoir un signal radiofréquence (RF) réfléchi par le sujet vivant ;
- un mélangeur configuré pour mélanger le signal RF réfléchi sur une période prédéfinie avec un signal RF transmis vers le sujet vivant pour obtenir un signal de mouvement brut ;
- un processeur configuré pour :

15

- . déterminer un contenu énergétique du signal de mouvement brut ;
- . comparer le contenu énergétique à une valeur énergétique prédéterminée pour reconnaître les périodes de grand mouvement corporel du sujet vivant ;
- . déduire le spectre du signal de mouvement brut tout en rejetant des données des sections de grand mouvement corporel ;
- . analyser le spectre du signal de mouvement brut pour déterminer un rythme respiratoire et un rythme cardiaque du sujet vivant ; et
- . calculer un seuil ventilatoire en tant que paramètre de performance cardiorespiratoire en liant le rythme respiratoire et le rythme cardiaque déterminés sur une période définie de mesure ; et

20

25

- une sortie agencée pour fournir des informations sélectionnées concernant la respiration et l'activité cardiaque comprenant le seuil ventilatoire calculé.

30

2. Système selon la revendication 1, dans lequel les informations sélectionnées sont sélectionnées dans le groupe consistant en un mouvement respiratoire, un volume respiratoire, une arythmie sinusale respiratoire (RSA), une activité cardiaque et un mouvement corporel non cardiorespiratoire.

35

3. Système selon la revendication 1, dans lequel le processeur est configuré pour reconnaître la respiration ou l'activité cardiaque du sujet vivant en utilisant un signal dans le domaine temporel traité déduit du signal radiofréquence réfléchi.

40

4. Système selon la revendication 3, dans lequel l'activité cardiaque comprend les battements cardiaques du sujet vivant reconnus en identifiant des pics dans le signal dans le domaine temporel traité.

5. Système selon la revendication 1, dans lequel le processeur est configuré pour reconnaître la respiration ou l'activité cardiaque du sujet vivant en utilisant un traitement dans le domaine fréquentiel du signal reçu.

45

6. Système selon la revendication 1, comprenant en outre : un filtre, dans lequel le processeur est configuré pour mesurer le contenu énergétique d'un signal filtré.

7. Système selon la revendication 1, comprenant en outre de multiples capteurs configurés pour recevoir le signal RF réfléchi.

8. Système selon la revendication 1, dans lequel le processeur est configuré pour calculer un paramètre d'arythmie sinusale respiratoire en utilisant les informations de rythme cardiaque et de rythme respiratoire mesurées.

50

9. Système selon la revendication 1, comprenant en outre de multiples capteurs fonctionnant à différentes fréquences, dans lequel une fréquence relativement faible est utilisée pour estimer le grand mouvement corporel du sujet vivant, et une fréquence relativement élevée est utilisée pour estimer un mouvement plus petit du sujet vivant.

55

10. Système selon la revendication 1, comprenant en outre une enceinte configurée pour enfermer lesdits un ou plusieurs capteurs, le processeur et la sortie.

11. Système selon la revendication 1, dans lequel le signal RF comprend un signal RF monofréquence.

## EP 2 078 270 B1

12. Procédé pour mesurer et analyser la respiration, l'activité cardiaque et le mouvement corporel non cardiorespiratoire et fournir un paramètre de la performance cardiorespiratoire d'un sujet vivant, le procédé comprenant :

- la transmission d'un signal radiofréquence (RF) au sujet vivant ;
- la réception d'un signal radiofréquence (RF) réfléchi par le sujet vivant ;
- le mélange du signal radiofréquence (RF) réfléchi avec le signal radiofréquence (RF) transmis sur une période prédéterminée pour obtenir un signal de mouvement brut ;
- la détermination d'un contenu énergétique du signal de mouvement brut ;
- la comparaison du contenu énergétique avec une valeur énergétique prédéterminée pour reconnaître des périodes de grand mouvement corporel du sujet vivant ;
- la déduction du spectre du signal de mouvement brut tout en rejetant des données des sections de grand mouvement corporel ;
- l'analyse du spectre du signal de mouvement brut pour déterminer un rythme respiratoire et un rythme cardiaque du sujet vivant ;
- le calcul d'un seuil ventilatoire en tant que paramètre de performance cardiorespiratoire en liant le rythme respiratoire et le rythme cardiaque déterminés sur une période définie de mesure ; et
- la sortie d'une ou de plusieurs informations sélectionnées concernant la respiration et l'activité cardiaque comprenant le seuil ventilatoire calculé.

13. Procédé selon la revendication 12, dans lequel ladite sortie comprend l'affichage d'une ou de plusieurs mesures concernant la respiration du sujet vivant.

14. Procédé selon la revendication 12, comprenant en outre : la mesure d'un contenu énergétique d'un signal filtré.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8

**REFERENCES CITED IN THE DESCRIPTION**

*This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.*

**Patent documents cited in the description**

- US 86386206 P [0001]
- WO 2004013611 A [0014]
- WO 9611630 A1 [0015]

**Non-patent literature cited in the description**

- **RONALD E. DE MEERSMAN.** Respiratory sinus arrhythmia alteration following training in endurance athletes. *European Journal of Applied Physiology*, September 1992, vol. 64 (5), 434-436 [0005]
- **D. RAMOS-BARBÓN ; D. FITCHETT ; W. J. GIBBONS ; D. A. LATTER ; R. D. LEVY.** Maximal Exercise Testing for the Selection of Heart Transplantation Candidates - Limitation of Peak Oxygen Consumption. *Chest.*, 1999, vol. 115, 410-417 [0007]
- **C.J. JAMES ; C.W. HESSE.** Independent component analysis for biomedical signals. *Physiological Measurement*, February 2005, vol. 26 (1), R15-R39 [0047]

专利名称(译)	用于监测心肺功能参数的系统和方法		
公开(公告)号	<a href="#">EP2078270B1</a>	公开(公告)日	2017-11-29
申请号	EP2007844765	申请日	2007-10-31
[标]申请(专利权)人(译)	必安康医疗有限公司		
申请(专利权)人(译)	BIANCAMED有限公司		
当前申请(专利权)人(译)	瑞思迈SENSOR TECHNOLOGIES LIMITED		
[标]发明人	DE CHAZAL PHILIP HANLEY CONOR HENEGHAN CONOR		
发明人	DE CHAZAL, PHILIP HANLEY, CONOR HENEGHAN, CONOR		
IPC分类号	G06F19/00 A61B5/00		
优先权	60/863862 2006-11-01 US		
其他公开文献	EP2078270A4 EP2078270A2		
外部链接	<a href="#">Espacenet</a>		

摘要(译)

公开了一种装置，系统和方法，用于以方便和低成本的方式监测人的运动，呼吸，心率，以及用于从测量的信号导出和显示心肺功能的有用测量值。通过应用于以非接触方式获得的原始信号的处理，通常使用射频传感器，获得运动，呼吸和心率信号。描述了处理成单独的心脏和呼吸成分。可以通过使用频谱或时域处理来确定心率。可以使用光谱分析来计算呼吸率。描述了使用该系统导出心率，呼吸性窦性心律失常或通气阈值参数的处理。传感器，处理和显示器可以结合在单个装置中，该装置可以在锻炼时佩戴或靠近身体（例如，在手表或移动电话配置中），或者可替换地放置在一些固定的锻炼设备中。距离形成身体（例如，在跑步机仪表板中），并且还可以与其他传感器（例如位置定位器）集成。

