(19)

(12)





(11) **EP 1 818 010 A2**

EUROPEAN PATENT APPLICATION

- (43) Date of publication: 15.08.2007 Bulletin 2007/33
- (21) Application number: 06021295.8
- (22) Date of filing: 06.03.2001
- (84) Designated Contracting States: AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU MC NL PT SE TR Designated Extension States: LT LV RO SI
- (62) Document number(s) of the earlier application(s) in accordance with Art. 76 EPC:
 01914075.5 / 1 299 029
- (71) Applicant: Solianis Holding AG 6304 Zug (CH)
- (72) Inventors:
 Schrepfer, Thomas W.
 CH-5225 Oberbözberg (CH)
 - Caduff, Andreas 8005 Zürich (CH)

- (51) Int Cl.: *A61B 5/00*^(2006.01) *G01N 22/00*^(2006.01)
- A61B 5/05^(2006.01) G01N 33/487^(2006.01)
- Hirt, Etienne CH-6330 Cham (CH)
 Süsstrunk, Heinz CH-8135 Langnau am Albis (CH)
- (74) Representative: Blum, Rudolf Emil E. BLUM & CO. AG Patent- und Markenanwälte VSP Vorderberg 11 8044 Zürich (CH)

Remarks:

This application was filed on 11 - 10 - 2006 as a divisional application to the application mentioned under INID code 62.
Claims 13-39 are deemed to be abandoned due to non-payment of the claims fee (Rule 31 (2) EPC).

(54) Device for determining the concentration of a substance in body liquid

(57) For measuring the concentration of a substance in body fluid, such as the glucose level in blood or tissue, a strip electrode (18) and a ring electrode (19) are arranged at the specimen. The ring electrode (19) is in direct electrical contact with the specimen while the strip electrode (18) is electrically insulated therefrom. The strip electrode (18) is arranged parallel to an arm or a leg for obtaining a large interaction length. The electrodes (18, 19) form a capacitor in a resonant circuit. A modulated voltage in the MHz range close to or at the resonance frequency is applied to the electrodes and the response of the body fluid is measured. This design allows a measurement of high accuracy.



Description

Technical Field

[0001] The invention relates to a method and a device for determining the concentration of a substance in an in-vitro or in-vivo specimen containing body liquid according to the preamble of the independent claims.

Background Art

[0002] Radio wave spectroscopy has been known to provide promising potential in the in-vitro and in-vivo determination of the concentration of glucose and other substances in body fluids. In particular, this technology is of substantial interest for the determination of glucose concentration in blood and/or inter- or intracellular liquid. A device for measuring blood level glucose is disclosed in US 5 792 668, where two electrodes are brought into direct contact with the human body and the impedance is measured between them.

[0003] Despite its potential, the technology has not yet been used in commercial devices, which is attributed to the limited accuracy of the presently known solutions.

Disclosure of the Invention

[0004] Hence, it is the goal of the invention to provide a method and device that allow to increase the reliability of this type of measurement.

[0005] This goal is reached by the independent claims. **[0006]** In a first aspect of the invention, the first electrode is electrically insulated from the specimen. Hence, the measured parameter does not depend on the surface conditions of the specimen. Rather, the signal is capacitively coupled to the specimen and the measured parameter depends therefore primarily on the conditions within the specimen. The parameter measured in this way can then be converted to the desired concentration, e.g. by using calibration data.

[0007] Preferably, at least two electrodes are provided, wherein the modulated voltage is applied between them. By using two electrodes, a defined field can be established within the specimen. For best signals, it has been found advantageous to place the second electrode in electric contact with the specimen.

[0008] The measured parameter preferably depends on the electrical impedance at the electrode(s). It has been found that the concentration of various substances, in particular glucose, affects the real or imaginary part of this impedance because it changes the loss and/or dielectric constant of body fluid.

[0009] Preferably, the electrode forms part of a resonant circuit, which is operated at or close to its resonance frequency. Under such conditions, a change of the dielectric or loss properties of the specimen leads to substantial shifts in the parameters of the resonant circuit and can therefore be measured with high sensitivity.

[0010] A further aspect of the invention is directed to a device particularly suited for in-vivo measurements of the human body. This device comprises an elongate electrode having a width much smaller than its length. A

⁵ holder is provided to mount the electrode to an arm or a leg with the longitudinal axis of the electrode extending parallel thereto. In this way, a large interaction space is established, which allows to measure the desired concentration with a higher level of accuracy.

¹⁰ **[0011]** The method and device of the present invention has been found to be especially suited for measuring the glucose concentration in body fluid.

Brief Description of the Drawings

[0012] The invention will be better understood and objects other than those set forth above will become apparent when consideration is given to the following detailed description thereof. Such description makes reference to the annexed drawings, wherein:

Fig. 1 is a block circuit diagram of a preferred device for carrying out the invention,

Fig. 2 is a view onto a possible embodiment of the device,

Fig. 3 is a section along line III-III of Fig. 2,

Fig. 4 is the device of Fig. 3 with a wristband,

Fig. 5 shows the behavior of the relative amplitude A as a function of frequency,

Fig. 6 is a second embodiment of the circuit,
Fig. 7 is an alternative electrode geometry,
Fig. 8 shows measurements at varying glucose concentrations (mmol/liter) in physiologic solution and
Fig. 9 a third embodiment of the circuit.

Modes for Carrying Out the Invention

[0013] Fig. 1 shows a block circuit diagram of a preferred device for carrying out the invention. It comprises a voltage controlled oscillator (VCO) 1 as a signal source for generating a sine wave signal. This signal is fed to two amplifiers 2, 3. The output of first amplifier 2 is connected via a resistor R1 to a first signal path 4. A resonant circuit 5 comprising an inductance L and a capacitor C in series is connected between first signal path 4 and ground. The output of second amplifier 3 is connected via a resistor R2 to a second signal path 6. Second signal path 6 is substantially identical to first signal path 4 but comprises a resistor R3 as a reference load instead of resonant circuit 5.

[0014] Both signal paths 4, 6 are fed to a measuring circuit 7, which determines the relative amplitude A of both signals as well as, optionally, their mutual phase shift phi. Relative amplitude A can e.g. be the amplitude of first signal path 4 in units of the amplitude of second signal path 6 (wherein the amplitudes are the peak values of the sine waves).

[0015] The output signal of measuring circuit 7 is fed

30

35

40

45

50

55

15

20

25

10

to a microprocessor 8, which also controls the operation of VCO 1.

[0016] As can be seen from Fig. 1, the device in the present embodiment further comprises a temperature sensor 10, a display 11 and an input device 12 with user operatable controls, all of which are controlled by micro-processor 8.

[0017] Inductance L of the device of Fig. 1 can be generated by a coil and/or by the leads and electrodes of capacitor C. Its value is generally known with reasonable accuracy.

[0018] Capacitor C of the device of Fig. 1 is used as an antenna for probing a specimen. For this purpose, it is formed by electrodes that are arranged near the specimen. The geometry of the electrodes is selected such that the electric field generated by them extends into the specimen and the body liquid to be measured. Suitable geometries are discussed below. As mentioned above, at least one of the electrodes of the capacitor is electrically isolated such that capacitor C is primarily a capacitive load, the capacitance and loss of which depends on the electrical properties (i.e. the response) of the specimen at the frequency of VCO 1.

[0019] To measure the concentration of a substance in the body fluid of the specimen, microprocessor 8 can e.g. initiate a measurement cycle consisting of a frequency sweep of VCO 1. The sweep should start at a frequency fmin below the expected resonance frequency f0 of the resonant circuit 5 and extend to a frequency fmax above resonance frequency f. During this sweep, the electrical properties of signal path 4 will change substantially, while those of signal path 6 will vary only slightly. The amplitude determined by measuring circuit A will therefore fall to a minimum A0 at f0, as shown in Fig. 5. At the same time, phase shift phi crosses zero.

[0020] As can be shown, the dependence of A0 on the dielectric constant $\epsilon(f)$ and, in particular, on the loss or conductance p(f) of the fluid in the specimen is stronger than at off-resonance frequencies, which allows a sensitive measurement of the liquid's response to the electric field.

[0021] This is shown in Fig. 8, which represents measurements of the type shown in Fig. 5 at glucose concentrations between 0 and 17.5 mmol/l. The vertical axis represents the ratio in dB of the signals from first signal path 4 and second signal path 6. The resonance frequency is around 35.5 MHz.

[0022] It is presently believed that the specific impedance of the body fluid, i.e. the specific conductivity p(f)and the dielectric constant $\varepsilon(f)$ in a frequency range between 10 MHz and 2000 MHz, and in particular between 20 MHz and 70 MHz, are a function of the properties and concentration of the salty (ionic) components of the human body. These salty components primarily include solvated sodium, potassium, calcium and other minor ions and their counter ions, the primary counter ion being chloride. Other non-ionic solvated substances, in particular substances having a similar range of size as the ion complexes, can have an impact on the impedance pattern of the salty body fluid components, provided these substances occur in sufficient concentration. In particular, glucose has a similar range of size and is present in concentrations giving rise to a well detectable variation of

the amplitude A0 at resonance frequency. [0023] In a simple embodiment, only amplitude A0 is measured as a parameter for the determination of the concentration. Suitable calibration data stored in micro-

processor 8 is used to convert amplitude A0 into the desired concentration level.

[0024] The effects exploited for the measurement are temperature dependent. In order to obtain high accuracy over a wide temperature range, temperature sensor 10

¹⁵ is brought into thermal contact with the specimen to be measured. The signals from temperature sensor 10 are used to correct the obtained result, again using calibration data obtain from calibration measurements.

[0025] A proper design of the electrodes of capacitor ²⁰ C allows to optimize the accuracy and sensitivity of the present device in a given application. A preferred geometry of the device for in-vivo measurements in a living body is shown in Figs. 2 and 3.

[0026] The device comprises a housing 13 closed on one side by an electrode plate 14. The display 11 is arranged opposite electrode plate 14. The electronic circuits 16 are arranged between electrode plate 14 and display 11.

[0027] Electrode plate 14 comprises an electrically insulating substrate 17 with a strip electrode 18 and a top or ring electrode 19 arranged on an outer side 20 thereof. An inner side 21 of insulating substrate 17 is covered by a bottom electrode 22. A plurality of though-contacts 23 are provided to connect ring electrode 19 to bottom elec-

trode 22. A further through-contact 24 connects one end of strip electrode 18 to a small bond pad 25 arranged in an opening 26 of bottom electrode 22 on inner side 21.
[0028] Temperature sensor 10 is mounted to bottom electrode 22. The large number of through-contacts 23
ensure that bottom electrode 22 follows the temperature of the sensor and the momentum of the sensor of the s

of ring electrode 18 and therefore the temperature of the specimen closely. [0029] A typical size of electrode plate 14 is 32 mm x

21 mm. Bottom electrode 22 covers all of inner side 21

⁴⁵ except for the small opening 26 and is therefore much larger than strip electrode 18.

[0030] Leads 28 are provided to connect bottom electrode 22, contact pad 26 and temperature sensor 10 to the electronic circuits 16.

50 [0031] While bottom electrode 22 and ring electrode 19 are connected to ground, strip electrode 18 is connected to inductance L of resonant circuit 5. Therefore, the capacitor C is formed between strip electrode 18 as a first electrode and ring electrode 19 and bottom elec-

⁵⁵ trode 22 as a second electrode. In other words, the second electrode consists of two electrode layers: a top electrode layer formed by ring electrode 19 and a bottom electrode layer formed by bottom electrode 22.

[0032] An electrically insulating cover layer 29 covers all of strip electrode 18 but not ring electrode 19. In other words, strip electrode 18 is arranged between substrate 17 and cover layer 29. Cover layer 29 is preferably of a hard, moisture- and salt-impervious material such as glass, ceramics, a polycarbonate or diamondlike carbon (DLC) of a thickness preferably between 50 and 100 μ m. [0033] As can be seen in Fig. 4, a holder or wristband 31 is attached to housing 13 for fixing the device to an arm or a leg of a human body with cover layer 29 facing the body and a longitudinal axis of strip electrode 18 parallel to the arm or leg. In this way, ring electrode 19 comes into contact with the user's skin and sets the same to ground reference potential. The electric field generated by strip electrode 18 extends into the body tissue. Since strip electrode 18 is elongate and has a width much smaller than its length and extends along the arm or leg, a comparatively large region of the body is reached by the field. This allows to obtain more sensitive and accurate measurements.

[0034] As described above, a pure sine voltage has been found to be sufficient for obtaining accurate measurements. However, other types for modulated voltages, such as square-wave voltages or pulses can be used as well. In this case, measuring circuit 7 is preferably provided with suitable filters for selectively sampling one or more frequency components. At least one measured frequency component is preferably close to the resonance frequency of resonant circuit 5 for exploiting the circuit's high sensitivity to the specimen's properties at that frequency.

[0035] The electrode geometry can be varied for adapting it to a given application. While the design of Fig. 2 is optimized for a measurement on an arm or leg, a circular design can be used for measurement on a flatter body part or an in-vitro sample.

[0036] Ring electrode 19 does not necessarily have to form a closed ring as long as it provides sufficient grounding of the body part to be measured. It can e.g. also have U-shape or consist of two stripes parallel to and laterally enclosing strip electrode 18. Ring electrode 19 can also be omitted completely or be covered by cover layer 29, in particular for in-vitro measurements where noise is low.

[0037] Part of a further embodiment of the circuit is shown in Fig. 6. Here, no direct connection between resonant circuit 5 and measuring circuit 7 is used. Rather, an antenna electrode 33 is located in proximity to the electrodes of capacitor C, and measuring circuit 7 measures the signal returned by antenna electrode 33.

[0038] A possible arrangement of the electrodes is shown in Fig. 7. As can be seen, antenna electrode 33 is strip shaped and arranged in parallel to strip electrode 18. Both, antenna electrode 33 and strip electrode 18 are covered by cover layer 29 and therefore electrically insulated from the specimen.

[0039] The device of Figs. 6 and 7 is again sweeping VCO 1 between a frequency fmin below the resonance frequency f0 of resonant circuit 5 and a frequency fmax above it. In contrast to Fig. 5, measuring circuit 7 now detects a maximum amplitude A0 at f0, wherein the value of A0 depends on the response, i.e. the electrical properties of the specimen at the resonance frequency f0. The parameter A0 can now again be processed using

calibration data as described above. [0040] A comparison of the device of Figs. 1 and 2 with the device of Figs. 6 and 7 shows that the first embodi-

ment measures the response of the specimen from the 10 signal reflected to strip electrode 18. The second embodiment measures the response of the specimen from the signal transmitted from strip electrode 18 to antenna electrode 33.

[0041] It is found that the transmission and reflection 15 show different dependencies on the concentrations of various compounds of the body fluid. Hence, a combined measurement of reflection and transmission allows a further refinement of the measurement by elimination of the influence of compounds not of interest for the quantity to 20 be measured.

[0042] A third embodiment of a circuit is shown in Fig. 9. Here, the capacitor C formed by the electrodes is part of the resonant tank circuit of an active, self-oscillating oscillator 40. The amplitude A and frequency f0 of the 25 output signal of oscillator 40 depend on the capacitance and losses in capacitor C. The corresponding signal is fed to measuring circuit 7, which evaluates the parameters A and f0. Measuring the corresponding parameters A and f0 again allows a sensitive measurement of the 30 desired concentration using calibration data.

[0043] In the examples shown so far, the invention was used in a device for qualitatively or quantitatively displaying the concentration a substance (such as glucose) in body liquid. The invention can, however, e.g. also be used in devices that automatically administer medication to a body, such as an insulin pump, where the amount and/or time for administering the medication depends on the measured concentration. It can also be used in any other type of device that requires the measurement of 40 the concentration of a substance in body fluid.

[0044] While there are shown and described presently preferred embodiments of the invention, it is to be distinctly understood that the invention is not limited thereto but may be otherwise variously embodied and practiced within the scope of the following claims.

Claims

35

45

50

55

1. A device for determining the concentration of a substance in body liquid of a human body comprising an elongate first electrode (18) having a width much smaller than a length,

a holder (31) for fixing the first electrode (18) to an arm or leg of a body with a longitudinal axis of the first electrode being substantially parallel to the arm or lea

a signal source connected to the first electrode ap-

10

15

20

25

30

35

45

50

55

plying a modulated electrical voltage to the first electrode (18) for generating a modulated field in the specimen,

a measuring circuit (7) for measuring at least one parameter (A, phi, f0) depending on a response of the specimen to the field, and

a data processor determining the concentration from the parameter.

- The device of claim 1 further comprising a ring electrode (19) extending around all of said first electrode (18).
- The device of claim 2 wherein said ring electrode (19) is connected to ground.
- 4. The device of one of the claims 2 or 3 wherein said ring electrode surrounds a single strip electrode with said strip electrode forming said first electrode (19).
- The device of one of one of the preceding claims further comprising an electrically insulating substrate (17), wherein the first electrode (18) is arranged on a first side (20) of the substrate (17) between the substrate (17) and the cover layer (29).
- **6.** The device of claim 5 further comprising a second electrode (19, 22) arranged on the substrate, wherein the signal source (2) is connected to apply the modulated electrical voltage between the first (18) and the second (19, 22) electrode.
- 7. The device of one of the preceding claims wherein the first electrode (18) is part of a capacitor (C) of a resonant circuit (5) comprising the capacitor (C) and an inductance (L) connected to the signal source (1).
- **8.** The device of claim 7 wherein the capacitor (C) and the inductance (L) are arranged in series.
- **9.** The device of one of the claims 7 or 8 wherein the measuring circuit (7) is adapted to measure a voltage over the resonant circuit (5).
- **10.** The device of one of the claims 7 to 9 further comprising an antenna electrode (33) arranged in proximity to the first electrode (18), wherein the measuring circuit (7) is adapted to measure a signal transmitted from the first electrode (18) to the antenna electrode (33).
- **11.** The device of any of the preceding claims wherein said first electrode (18) is a straight strip electrode.
- **12.** The device of any of the preceding claims having two parallel strip electrodes (18, 23).
- 13. A method for determining the concentration of a sub-

stance in a in-vitro or in-vivo specimen containing body liquid comprising the steps of

arranging a first electrode (18) at said specimen, wherein said first electrode is electrically insulated from the specimen,

applying a modulated electrical voltage to the first electrode for generating a modulated field in the specimen and

- measuring at least one parameter (A, phi) depending on a response of the specimen to the field and determining the concentration therefrom.
- **14.** The method of claim 13 comprising the step of arranging a second electrode (19, 22) at said specimen, wherein the modulated electrical voltage is applied between the first and the second electrode (19, 22).
- **15.** The method of claim 14 wherein the second electrode (19, 22) is in electric contact with the body liquid in the specimen.
- **16.** The method of one of the claims 13 to 15 further comprising the step of measuring a temperature (T) of the specimen and using the temperature in the determination of the concentration.
 - **17.** The method of one of the claims 13 to 16 wherein the modulated electrical voltage is a sine voltage.
 - **18.** The method of one of the claims 13 to 17 wherein the modulated electrical voltage has a frequency between 10 MHz and 2 GHz, in particular between 20 MHz and 70 MHz.
- **19.** The method of one of the claims 13 to 18 wherein the parameter (A, phi, f0) depends on the electrical impedance at the first electrode.
- 40 20. The method of one of the claims 13 to 19 wherein the response of the specimen is measured by measuring a signal reflected from the first electrode.
 - **21.** The method of one of the claims 13 to 20 wherein an antenna electrode (33) is arranged at the specimen in proximity to the first electrode (18) and wherein the response of the specimen is measured by measuring a signal transmitted from the first electrode (18) to the antenna electrode (33).
 - **22.** The method of one of the claims 13 to 21 wherein the substance is glucose.
 - **23.** The method of one of the claims 13 to 22 wherein the specimen is a living body.
 - **24.** The method of one of the claims 13 to 23 comprising the step of using calibration data to convert the pa-

30

35

45

rameter (A, phi, f0) to the concentration.

- **25.** The method of one of the claims 13 to 24 wherein the first electrode forms part of a resonant circuit (5) having a resonance frequency (f0) and wherein the resonant circuit (5) is operated substantially at the resonance frequency.
- **26.** The method of claim 25 wherein the resonant circuit is at least part of a tank circuit of an active oscillator (40) and wherein the parameter is an amplitude (A) and/or a frequency (f0) of a signal generated by said oscillator (40).
- **27.** The method of claim 25 wherein the modulated voltage is frequency sweeped from a frequency (fmin) below the resonance frequency (f0) to a frequency (fmax) above the resonance frequency, and in particular wherein the parameter is a signal reflected to the first electrode (18) or transmitted to an antenna electrode (33) at the resonance frequency (f0).
- **28.** A device for determining the concentration of a substance in a in-vitro or in-vivo specimen containing body liquid, in particular for carrying out the method of one of the preceding claims, comprising a first electrode (18) covered by a cover layer (29)

of insulating material, a signal source (1) connected to the first electrode (18) applying a modulated electrical voltage to the first electrode (18) for generating an electric field in

the specimen, a measuring circuit (7) for measuring at least one parameter depending on a response of the specimen to the field, and

a data processor (8) determining the concentration from the parameter.

- **29.** The device of claim 28 comprising a holder (31) for fixing the first electrode (18) to a part of a body with ⁴⁰ the cover layer (29) facing the body.
- **30.** The device of one of the claims 28 or 29 further comprising an electrically insulating substrate (17), wherein the first electrode (18) is arranged on a first side (20) of the substrate (17) between the substrate (17) and the cover layer (29).
- **31.** The device of claim 30 further comprising a second electrode (19, 22) arranged on the substrate, wherein the signal source (2) is connected to apply the modulated electrical voltage between the first (18) and the second (19, 22) electrode.
- **32.** The device of claim 31, wherein the second electrode ⁵⁵ (19, 22) comprises a bottom electrode layer (22) arranged on a second side (21) of the substrate (17), said bottom electrode layer (22) having a larger ex-

tension than said top electrode layer (18).

- **33.** The device of one of the claims 31 or 32, wherein the second electrode (19, 22) comprises a top electrode layer (19) arranged on the first side (20) of the substrate (17), said top electrode layer (19) being arranged around at least part, in particular substantially all, of the first electrode (18).
- 10 34. The device of one of the claims 28 to 33, wherein the first electrode (18) is elongate having a width much smaller than a length.
- 35. The device of one of the claims 28 to 34 comprising a first (4) and a second (6) signal path between the signal source (1) and the measuring circuit (7), wherein the first electrode (18) in arranged in the first signal path (4) and a reference load (R3) is arranged in the second signal path (6), and wherein the measuring circuit (7) is adapted to measure a relative amplitude (A) and/or phase (phi) of signals from the first and second paths.
- 36. The device of one of the claims 28 to 35 wherein the first electrode (18) is part of a capacitor (C) of a resonant circuit (5) comprising the capacitor (C) and an inductance (L) connected to the signal source (1).
 - **37.** The device of claim 36 wherein the capacitor (C) and the inductance (L) are arranged in series.
 - **38.** The device of one of the claims 36 or 37 wherein the measuring circuit (7) is adapted to measure a voltage over the resonant circuit (5).
 - **39.** The device of one of the claims 36 to 38 further comprising an antenna electrode (33) arranged in proximity to the first electrode (18), wherein the measuring circuit (7) is adapted to measure a signal transmitted from the first electrode (18) to the antenna electrode (33).



Fig. 1









Fig. 7



Fig. 8



REFERENCES CITED IN THE DESCRIPTION

This list of references cited by the applicant is for the reader's convenience only. It does not form part of the European patent document. Even though great care has been taken in compiling the references, errors or omissions cannot be excluded and the EPO disclaims all liability in this regard.

Patent documents cited in the description

• US 5792668 A [0002]

patsnap

专利名称(译)	用于确定体液中物质浓度的装置		
公开(公告)号	EP1818010A2	公开(公告)日	2007-08-15
申请号	EP2006021295	申请日	2001-03-06
申请(专利权)人(译)	SOLIANIS HOLDING AG		
当前申请(专利权)人(译)	BIOVOTION AG		
[标]发明人	SCHREPFER THOMAS W CADUFF ANDREAS HIRT ETIENNE SUSSTRUNK HEINZ		
发明人	SCHREPFER, THOMAS W. CADUFF, ANDREAS HIRT, ETIENNE SÜSSTRUNK, HEINZ		
IPC分类号	A61B5/00 A61B5/05 G01N22/00 G01N33/487 A61B5/053 G01N27/02 A61B5/0408 A61B5/0478 A61B5 /0492 A61B5/145 A61B5/1477 G01N27/22		
CPC分类号	A61B5/05 A61B5/053 A61B5/14532		
优先权	PCT/IB2001/000334 2001-03-06 WO		
其他公开文献	EP1818010A3 EP1818010B1		
外部链接	Espacenet		

摘要(译)

为了测量体液中物质的浓度,例如血液或组织中的葡萄糖水平,在样本 处设置条形电极(18)和环形电极(19)。环形电极(19)与样品直接 电接触,而条形电极(18)与样品电绝缘。条形电极(18)平行于臂或 腿布置,以获得大的相互作用长度。电极(18,19)在谐振电路中形成电 容器。将接近或处于共振频率的MHz范围内的调制电压施加到电极,并 测量体液的响应。该设计允许高精度的测量。

