



US009801552B2

(12) **United States Patent**  
**Romesburg**

(10) **Patent No.:** **US 9,801,552 B2**  
(45) **Date of Patent:** **Oct. 31, 2017**

(54) **SYSTEMS AND METHODS FOR VARIABLE FILTER ADJUSTMENT BY HEART RATE METRIC FEEDBACK**

(75) Inventor: **Eric Douglas Romesburg**, Chapel Hill, NC (US)

(73) Assignee: **Valencell, Inc.**, Raleigh, NC (US)

(\*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 63 days.

(21) Appl. No.: **14/124,465**

(22) PCT Filed: **Jul. 25, 2012**

(86) PCT No.: **PCT/US2012/048079**

§ 371 (c)(1),  
(2), (4) Date: **Dec. 6, 2013**

(87) PCT Pub. No.: **WO2013/019494**

PCT Pub. Date: **Feb. 7, 2013**

(65) **Prior Publication Data**

US 2014/0114147 A1 Apr. 24, 2014

**Related U.S. Application Data**

(60) Provisional application No. 61/514,099, filed on Aug. 2, 2011.

(51) **Int. Cl.**  
**A61B 5/00** (2006.01)  
**A61B 5/024** (2006.01)  
(Continued)

(52) **U.S. Cl.**  
CPC ..... **A61B 5/0095** (2013.01); **A61B 5/0059** (2013.01); **A61B 5/0245** (2013.01);  
(Continued)

(58) **Field of Classification Search**  
None  
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,595,219 A 7/1971 Friedlander et al.  
4,240,882 A 12/1980 Ang et al.  
(Continued)

FOREIGN PATENT DOCUMENTS

CN 101212927 A 7/2008  
CN 201438747 U 4/2010  
(Continued)

OTHER PUBLICATIONS

Edmison et al., "E-Textile Based Automatic Activity Diary for Medical Annotation and Analysis," Proc. BSN 2006 Int. Workshop Wearable Implantable Body Sensor Netw. (2006), pp. 131-145, Apr. 3-5, 2006.

(Continued)


*Primary Examiner* — Carl H Layno  
*Assistant Examiner* — Jennifer Ghand

(74) *Attorney, Agent, or Firm* — Myers Bigel, P.A.

(57) **ABSTRACT**

A physiological signal processing system for a physiological waveform that includes a cardiovascular signal component provides a variable high pass filter that is responsive to the physiological waveform, and that is configured to high pass filter the physiological waveform in response to a corner frequency that is applied. A heart rate metric extractor is responsive to the variable high pass filter and is configured to extract a heart rate metric from the physiological waveform that is high pass filtered. A corner frequency adjuster is responsive to the heart rate metric extractor and is configured to determine the corner frequency that is applied to the variable high pass filter, based on the heart rate metric that was extracted. Analogous methods may also be provided.

**21 Claims, 12 Drawing Sheets**



- (51) **Int. Cl.**
- A61B 5/0245* (2006.01) 6,198,951 B1 3/2001 Kosuda et al.  
*A61B 5/0402* (2006.01) 6,205,354 B1 3/2001 Gellermann et al.  
*A61B 5/0476* (2006.01) 6,231,519 B1 5/2001 Blants et al.  
*A61B 5/04* (2006.01) 6,283,915 B1 9/2001 Nolan et al.  
*A61B 5/08* (2006.01) 6,285,816 B1 9/2001 Anderson et al.  
*A61B 5/0205* (2006.01) 6,289,230 B1 9/2001 Chaiken et al.  
6,298,314 B1 10/2001 Blackadar et al.  
6,332,868 B1 12/2001 Sato et al.  
6,358,216 B1 3/2002 Kraus et al.  
6,361,660 B1 3/2002 Goldstein  
6,371,925 B1 4/2002 Imai et al.  
6,374,129 B1 4/2002 Chin et al.  
6,415,167 B1 7/2002 Blank et al.  
6,443,890 B1 9/2002 Schulze et al.  
6,444,474 B1 9/2002 Thomas et al.  
6,454,718 B1 9/2002 Clift  
6,458,080 B1 10/2002 Brown et al.  
6,470,893 B1 10/2002 Boesen  
6,513,532 B2 2/2003 Mault et al.  
6,514,278 B1 2/2003 Hibst et al.  
6,527,711 B1 3/2003 Stivoric et al.  
6,527,712 B1 3/2003 Brown et al.  
6,529,754 B2 3/2003 Kondo  
6,534,012 B1 3/2003 Hazen et al.  
6,556,852 B1 4/2003 Schulze et al.  
6,569,094 B2 5/2003 Suzuki et al.  
6,571,117 B1 5/2003 Marbach  
6,605,038 B1 8/2003 Teller et al.  
6,616,613 B1 9/2003 Goodman  
6,631,196 B1 10/2003 Taenzer et al.  
6,647,378 B2 11/2003 Kindo  
6,656,116 B2 12/2003 Kim et al.  
6,694,180 B1 2/2004 Boesen  
6,745,061 B1 6/2004 Hicks et al.  
6,748,254 B2 6/2004 O'Neil et al.  
6,760,610 B2 7/2004 Tschupp et al.  
6,783,501 B2 8/2004 Takahashi et al.  
6,808,473 B2 10/2004 Hisano et al.  
6,859,658 B1 2/2005 Krug  
6,893,396 B2 5/2005 Schulze et al.  
6,941,239 B2 9/2005 Unuma et al.  
6,953,435 B2 10/2005 Kondo et al.  
6,996,427 B2 2/2006 Ali et al.  
6,997,879 B1 2/2006 Turcott  
7,018,338 B2 3/2006 Vetter et al.  
7,024,369 B1 4/2006 Brown et al.  
7,030,359 B2 4/2006 Römheld  
7,034,694 B2 4/2006 Yamaguchi et al.  
7,041,062 B2 5/2006 Friedrichs et al.  
7,043,287 B1 5/2006 Khalil et al.  
7,054,674 B2 5/2006 Cane et al.  
7,088,234 B2 8/2006 Naito et al.  
7,107,088 B2 9/2006 Aceti  
7,113,815 B2 9/2006 O'Neil et al.  
7,117,032 B2 10/2006 Childre et al.  
7,144,375 B2 12/2006 Kosuda  
7,163,512 B1 1/2007 Childre et al.  
7,175,601 B2 2/2007 Verjus et al.  
7,209,775 B2 4/2007 Bae et al.  
7,217,224 B2 5/2007 Thomas  
7,252,639 B2 8/2007 Kimura et al.  
7,263,396 B2 8/2007 Chen et al.  
7,289,837 B2 10/2007 Mannheimer et al.  
7,336,982 B2 2/2008 Yoo et al.  
7,341,559 B2 3/2008 Schultz et al.  
7,376,451 B2 5/2008 Mahony et al.  
7,470,234 B1 12/2008 Elhag et al.  
7,483,730 B2 1/2009 Diab et al.  
7,486,988 B2 2/2009 Goodall et al.  
7,507,207 B2 3/2009 Sakai et al.  
7,519,327 B2 4/2009 White  
7,526,327 B2 4/2009 Blondeau et al.  
7,583,994 B2 9/2009 Scholz  
7,625,285 B2 12/2009 Breving  
7,652,569 B2 1/2010 Kiff et al.  
7,689,437 B1 3/2010 Teller et al.  
7,695,440 B2 4/2010 Kondo et al.  
7,725,147 B2 5/2010 Li et al.  
7,756,559 B2 7/2010 Abreu
- (52) **U.S. Cl.**
- CPC ..... *A61B 5/02416* (2013.01); *A61B 5/0402* (2013.01); *A61B 5/04017* (2013.01); *A61B 5/0476* (2013.01); *A61B 5/725* (2013.01); *A61B 5/7225* (2013.01); *A61B 5/7278* (2013.01); *A61B 5/0205* (2013.01); *A61B 5/0816* (2013.01)
- (56) **References Cited**
- U.S. PATENT DOCUMENTS
- 4,331,154 A 5/1982 Broadwater et al.  
4,438,772 A 3/1984 Slavin  
4,491,760 A 1/1985 Linvill  
4,521,499 A 6/1985 Switzer  
4,541,905 A 9/1985 Kuwana et al.  
4,592,807 A 6/1986 Switzer  
4,655,225 A 4/1987 Dahne et al.  
4,830,014 A 5/1989 Goodman et al.  
4,882,492 A 11/1989 Schlager  
4,896,676 A 1/1990 Sasaki  
4,928,704 A 5/1990 Hardt  
4,957,109 A 9/1990 Groeger et al.  
5,002,060 A 3/1991 Nedivi  
5,022,970 A 6/1991 Cook et al.  
5,025,791 A 6/1991 Niwa  
5,079,421 A 1/1992 Knudson et al.  
5,080,098 A 1/1992 Willett et al.  
5,086,229 A 2/1992 Rosenthal et al.  
5,143,078 A 9/1992 Mather et al.  
5,226,417 A 7/1993 Swedlow et al.  
5,237,994 A 8/1993 Goldberger  
5,348,002 A 9/1994 Caro  
5,377,100 A 12/1994 Pope et al.  
5,482,036 A 1/1996 Diab et al.  
5,492,129 A 2/1996 Greenberger  
5,499,301 A 3/1996 Sudo et al.  
5,581,648 A 12/1996 Sahagen  
5,596,987 A 1/1997 Chance  
5,662,117 A 9/1997 Bittman  
5,673,692 A 10/1997 Schulze et al.  
5,697,374 A 12/1997 Odagiri et al.  
5,711,308 A 1/1998 Singer  
5,725,480 A 3/1998 Oosta et al.  
5,743,260 A 4/1998 Chung et al.  
5,779,631 A 7/1998 Chance  
5,797,841 A 8/1998 Delonzor et al.  
5,807,114 A 9/1998 Hodges et al.  
5,807,267 A 9/1998 Bryars et al.  
5,853,005 A 12/1998 Scanlon  
5,904,654 A 5/1999 Wohltmann et al.  
5,938,593 A 8/1999 Quелlette  
5,964,701 A 10/1999 Asada et al.  
5,971,931 A 10/1999 Raff  
5,974,338 A 10/1999 Asano et al.  
5,995,858 A 11/1999 Kinast  
6,004,274 A 12/1999 Aceti et al.  
6,013,007 A 1/2000 Root et al.  
6,023,541 A 2/2000 Merchant et al.  
6,030,342 A 2/2000 Amano et al.  
6,045,511 A 4/2000 Ott et al.  
6,067,006 A 5/2000 O'Brien  
6,070,093 A 5/2000 Oosta et al.  
6,078,829 A 6/2000 Uchida et al.  
6,080,110 A 6/2000 Thorgersen  
6,081,742 A 6/2000 Amano et al.  
6,186,145 B1 2/2001 Brown  
6,198,394 B1 3/2001 Jacobsen et al.

(56)

## References Cited

U.S. PATENT DOCUMENTS							
7,843,325	B2	11/2010	Otto	2005/0038349	A1	2/2005	Choi et al.
7,894,869	B2	2/2011	Hoarau	2005/0043600	A1	2/2005	Diab et al.
7,914,468	B2	3/2011	Shalon et al.	2005/0043630	A1	2/2005	Honeyager et al.
7,991,448	B2	8/2011	Edgar et al.	2005/0058456	A1	3/2005	Yoo
7,998,079	B2	8/2011	Nagai et al.	2005/0059870	A1	3/2005	Aceti
8,050,728	B2	11/2011	Al-Ali et al.	2005/0084666	A1	4/2005	Pong et al.
8,055,319	B2	11/2011	Oh et al.	2005/0101845	A1	5/2005	Nihtila
8,055,330	B2	11/2011	Egozi	2005/0101872	A1	5/2005	Sattler et al.
8,059,924	B1	11/2011	Letant et al.	2005/0113167	A1	5/2005	Buchner et al.
8,130,105	B2	3/2012	Al-Ali et al.	2005/0113656	A1	5/2005	Chance
8,137,270	B2	3/2012	Keenan et al.	2005/0113703	A1	5/2005	Farrington et al.
8,172,459	B2	5/2012	Abreu	2005/0116820	A1	6/2005	Goldreich
8,175,670	B2	5/2012	Baker, Jr. et al.	2005/0119833	A1	6/2005	Nanikashvili
8,204,730	B2	6/2012	Liu et al.	2005/0148883	A1	7/2005	Boesen
8,233,955	B2	7/2012	Al-Ali et al.	2005/0154264	A1	7/2005	Lecompte et al.
8,251,903	B2	8/2012	LeBoeuf et al.	2005/0177034	A1	8/2005	Beaumont
8,255,027	B2	8/2012	Al-Ali et al.	2005/0187448	A1	8/2005	Petersen et al.
8,255,029	B2	8/2012	Addison et al.	2005/0187453	A1	8/2005	Petersen et al.
8,303,512	B2	11/2012	Kosuda et al.	2005/0192515	A1	9/2005	Givens et al.
8,328,420	B2	12/2012	Abreu	2005/0196009	A1	9/2005	Boesen
8,416,959	B2	4/2013	Lott et al.	2005/0203349	A1	9/2005	Nanikashvili
8,491,492	B2	7/2013	Shinar et al.	2005/0203357	A1	9/2005	Debreczeny et al.
8,504,679	B2	8/2013	Spire et al.	2005/0209516	A1	9/2005	Fraden
8,506,524	B2	8/2013	Graskov et al.	2005/0222487	A1	10/2005	Miller et al.
8,512,242	B2	8/2013	LeBoeuf et al.	2005/0222903	A1	10/2005	Buchheit et al.
8,679,008	B2	3/2014	Hughes et al.	2005/0228244	A1	10/2005	Banet
8,730,048	B2	5/2014	Shen et al.	2005/0228299	A1	10/2005	Banet
9,005,129	B2	4/2015	Venkatraman et al.	2005/0240087	A1	10/2005	Keenan et al.
2001/0049471	A1	12/2001	Suzuki et al.	2005/0258816	A1	11/2005	Zen et al.
2002/0035340	A1	3/2002	Fraden et al.	2005/0259811	A1	11/2005	Kimm et al.
2002/0143242	A1	10/2002	Nemirovski	2006/0009685	A1	1/2006	Finarov et al.
2002/0156386	A1	10/2002	Dardik et al.	2006/0012567	A1	1/2006	Sicklinger
2002/0156654	A1	10/2002	Roe et al.	2006/0063993	A1	3/2006	Yu et al.
2002/0186137	A1	12/2002	Skardon	2006/0064037	A1	3/2006	Shalon et al.
2002/0188210	A1	12/2002	Aizawa	2006/0084878	A1	4/2006	Banet et al.
2002/0194002	A1	12/2002	Petrushin	2006/0084879	A1	4/2006	Nazarian et al.
2003/0002705	A1	1/2003	Boesen	2006/0122520	A1	6/2006	Banet et al.
2003/0007631	A1	1/2003	Bolognesi et al.	2006/0123885	A1	6/2006	Yates et al.
2003/0045785	A1	3/2003	Diab et al.	2006/0140425	A1	6/2006	Berg et al.
2003/0050563	A1	3/2003	Suribhotla et al.	2006/0142665	A1	6/2006	Garay et al.
2003/0064712	A1	4/2003	Gaston et al.	2006/0202816	A1	9/2006	Crump et al.
2003/0065257	A1	4/2003	Mault et al.	2006/0205083	A1	9/2006	Zhao
2003/0083583	A1	5/2003	Kovtun et al.	2006/0210058	A1	9/2006	Kock et al.
2003/0109030	A1	6/2003	Uchida et al.	2006/0211922	A1	9/2006	Al-Ali et al.
2003/0181795	A1	9/2003	Suzuki et al.	2006/0211924	A1	9/2006	Dalke et al.
2003/0212336	A1	11/2003	Lee et al.	2006/0217598	A1	9/2006	Miyajima et al.
2003/0220584	A1	11/2003	Honeyager et al.	2006/0224059	A1	10/2006	Swedlow et al.
2003/0222268	A1	12/2003	Yocum et al.	2006/0240558	A1	10/2006	Zhao
2004/0004547	A1	1/2004	Appelt et al.	2006/0246342	A1	11/2006	MacPhee
2004/0022700	A1	2/2004	Kim et al.	2006/0251277	A1	11/2006	Cho
2004/0030581	A1	2/2004	Leven	2006/0251334	A1	11/2006	Oba et al.
2004/0034289	A1	2/2004	Teller et al.	2006/0252999	A1	11/2006	Devaul et al.
2004/0034293	A1	2/2004	Kimball	2006/0264730	A1	11/2006	Stivoric et al.
2004/0054291	A1	3/2004	Schulz et al.	2006/0292533	A1	12/2006	Selod
2004/0075677	A1	4/2004	Loyall et al.	2006/0293921	A1	12/2006	McCarthy et al.
2004/0077934	A1	4/2004	Massad	2007/0004449	A1	1/2007	Sham
2004/0082842	A1	4/2004	Lumba et al.	2007/0004969	A1	1/2007	Kong et al.
2004/0103146	A1	5/2004	Park	2007/0015992	A1	1/2007	Filkins et al.
2004/0117204	A1	6/2004	Mazar et al.	2007/0021206	A1	1/2007	Sunnen
2004/0120844	A1	6/2004	Tribelsky et al.	2007/0027367	A1	2/2007	Oliver et al.
2004/0122294	A1	6/2004	Hatlestad et al.	2007/0027399	A1	2/2007	Chou
2004/0122702	A1	6/2004	Sabol et al.	2007/0036383	A1	2/2007	Romero
2004/0133123	A1	7/2004	Leonhardt et al.	2007/0050215	A1	3/2007	Kil et al.
2004/0135571	A1	7/2004	Uutela et al.	2007/0060800	A1	3/2007	Drinan et al.
2004/0138578	A1	7/2004	Pineda et al.	2007/0063850	A1	3/2007	Devaul et al.
2004/0186390	A1	9/2004	Ross et al.	2007/0082789	A1	4/2007	Nissila et al.
2004/0219056	A1	11/2004	Tribelsky et al.	2007/0083092	A1	4/2007	Rippo et al.
2004/0220488	A1	11/2004	Vyshedskiy et al.	2007/0083095	A1	4/2007	Rippo et al.
2004/0225207	A1	11/2004	Bae et al.	2007/0088221	A1	4/2007	Stahmann
2004/0228494	A1	11/2004	Smith	2007/0093702	A1	4/2007	Yu et al.
2004/0242976	A1	12/2004	Abreu	2007/0106167	A1	5/2007	Kinast
2005/0004458	A1	1/2005	Kanayama et al.	2007/0112273	A1	5/2007	Rogers
2005/0027216	A1	2/2005	Guillemaud et al.	2007/0112598	A1	5/2007	Heckerman et al.
2005/0030540	A1	2/2005	Thornton	2007/0116314	A1	5/2007	Grilliot et al.
2005/0033200	A1	2/2005	Soehren et al.	2007/0118054	A1	5/2007	Oliver et al.
				2007/0165872	A1	7/2007	Bridger et al.
				2007/0167850	A1	7/2007	Russell et al.
				2007/0191718	A1	8/2007	Nakamura
				2007/0197878	A1	8/2007	Shklarski

(56)

## References Cited

## U.S. PATENT DOCUMENTS

2007/0197881 A1 8/2007 Wolf et al.  
 2007/0213020 A1 9/2007 Novac  
 2007/0230714 A1 10/2007 Armstrong  
 2007/0233403 A1 10/2007 Alwan et al.  
 2007/0265097 A1 11/2007 Havukainen  
 2007/0270667 A1 11/2007 Coppi et al.  
 2007/0270671 A1 11/2007 Gal  
 2007/0293781 A1 12/2007 Sims et al.  
 2007/0299330 A1 12/2007 Couronne et al.  
 2008/0004536 A1 1/2008 Baxi et al.  
 2008/0015424 A1 1/2008 Bernreuter  
 2008/0039731 A1 2/2008 McCombie et al.  
 2008/0076972 A1 3/2008 Dorogusker et al.  
 2008/0081963 A1 4/2008 Naghavi et al.  
 2008/0086533 A1 4/2008 Neuhauser et al.  
 2008/0096726 A1 4/2008 Riley et al.  
 2008/0114220 A1 5/2008 Banet et al.  
 2008/0132798 A1 6/2008 Hong et al.  
 2008/0141301 A1 6/2008 Azzaro et al.  
 2008/0146890 A1 6/2008 LeBoeuf et al.  
 2008/0146892 A1 6/2008 LeBoeuf et al.  
 2008/0154098 A1 6/2008 Morris et al.  
 2008/0154105 A1 6/2008 Lemay  
 2008/0165017 A1 7/2008 Schwartz  
 2008/0170600 A1 7/2008 Sattler et al.  
 2008/0171945 A1 7/2008 Dotter  
 2008/0177162 A1 7/2008 Bae et al.  
 2008/0200774 A1 8/2008 Luo  
 2008/0203144 A1 8/2008 Kim  
 2008/0221461 A1 9/2008 Zhou et al.  
 2008/0249594 A1 10/2008 Dietrich  
 2008/0287752 A1 11/2008 Stroetz et al.  
 2009/0005662 A1 1/2009 Petersen et al.  
 2009/0006457 A1 1/2009 Stivoric et al.  
 2009/0010461 A1 1/2009 Klinghult et al.  
 2009/0030350 A1 1/2009 Yang et al.  
 2009/0054751 A1 2/2009 Babashan et al.  
 2009/0054752 A1 2/2009 Jonnalagadda et al.  
 2009/0069645 A1 3/2009 Nielsen et al.  
 2009/0082994 A1 3/2009 Schuler et al.  
 2009/0088611 A1 4/2009 Buschmann  
 2009/0093687 A1 4/2009 Telfort et al.  
 2009/0105548 A1 4/2009 Bart  
 2009/0105556 A1 4/2009 Fricke et al.  
 2009/0112071 A1 4/2009 LeBoeuf et al.  
 2009/0131761 A1 5/2009 Moroney, III et al.  
 2009/0131764 A1 5/2009 Lee et al.  
 2009/0175456 A1 7/2009 Johnson  
 2009/0177097 A1 7/2009 Ma et al.  
 2009/0214060 A1 8/2009 Chuang et al.  
 2009/0221888 A1 9/2009 Wijesiriwardana  
 2009/0227853 A1 9/2009 Wijesiriwardana  
 2009/0240125 A1 9/2009 Such et al.  
 2009/0253992 A1 10/2009 Van Der Loo  
 2009/0253996 A1 10/2009 Lee et al.  
 2009/0264711 A1 10/2009 Schuler et al.  
 2009/0270698 A1 10/2009 Shioi et al.  
 2009/0287067 A1 11/2009 Dorogusker et al.  
 2009/0299215 A1 12/2009 Zhang  
 2010/0004517 A1 1/2010 Bryenton et al.  
 2010/0022861 A1 1/2010 Cinbis et al.  
 2010/0045663 A1 2/2010 Chen et al.  
 2010/0100013 A1 4/2010 Hu et al.  
 2010/0113948 A1 5/2010 Yang et al.  
 2010/0168531 A1 7/2010 Shaltis et al.  
 2010/0172522 A1 7/2010 Mooring et al.  
 2010/0179389 A1 7/2010 Moroney et al.  
 2010/0185105 A1 7/2010 Baldinger  
 2010/0217102 A1 8/2010 LeBoeuf et al.  
 2010/0217103 A1 8/2010 Abdul-Hafiz et al.  
 2010/0222655 A1 9/2010 Starr et al.  
 2010/0228315 A1 9/2010 Nielsen  
 2010/0234714 A1 9/2010 Mercier et al.  
 2010/0268056 A1 10/2010 Picard et al.  
 2010/0274100 A1 10/2010 Behar et al.

2010/0274109 A1 10/2010 Hu et al.  
 2010/0292589 A1 11/2010 Goodman  
 2010/0298653 A1 11/2010 McCombie et al.  
 2011/0028810 A1 2/2011 Van Slyke et al.  
 2011/0028813 A1 2/2011 Watson et al.  
 2011/0081037 A1 4/2011 Oh et al.  
 2011/0105869 A1 5/2011 Wilson et al.  
 2011/0112382 A1 5/2011 Li et al.  
 2011/0130638 A1 6/2011 Raridan, Jr.  
 2011/0142371 A1 6/2011 King et al.  
 2011/0178564 A1 7/2011 Keefe  
 2011/0288379 A1 11/2011 Wu  
 2012/0030547 A1 2/2012 Raptis et al.  
 2012/0095303 A1 4/2012 He  
 2012/0156933 A1 6/2012 Kreger et al.  
 2012/0179011 A1 7/2012 Moon et al.  
 2012/0190948 A1 7/2012 Vetter et al.  
 2012/0197093 A1 8/2012 LeBoeuf et al.  
 2012/0277548 A1 11/2012 Burton  
 2013/0053661 A1 2/2013 Alberth et al.  
 2013/0072765 A1 3/2013 Kahn et al.  
 2013/0131519 A1 5/2013 LeBoeuf et al.  
 2013/0197377 A1 8/2013 Kishi et al.  
 2013/0245387 A1 9/2013 Patel  
 2013/0336495 A1 12/2013 Burgett et al.  
 2014/0051940 A1 2/2014 Messerschmidt  
 2014/0052567 A1 2/2014 Bhardwaj et al.  
 2014/0073486 A1 3/2014 Ahmed et al.  
 2014/0100432 A1 4/2014 Golda et al.  
 2014/0114147 A1 4/2014 Romesburg  
 2014/0127996 A1 5/2014 Park et al.  
 2014/0135596 A1 5/2014 LeBoeuf et al.  
 2014/0171755 A1 6/2014 LeBoeuf et al.  
 2014/0219467 A1 8/2014 Kurtz  
 2014/0236531 A1 8/2014 Carter  
 2014/0249381 A1 9/2014 LeBoeuf et al.  
 2014/0275852 A1 9/2014 Hong et al.  
 2014/0323880 A1 10/2014 Ahmed et al.  
 2014/0378844 A1 12/2014 Fei  
 2015/0011898 A1 1/2015 Romesburg  
 2015/0196256 A1 7/2015 Venkatraman et al.  
 2015/0282768 A1 10/2015 Luna et al.  
 2016/0038045 A1 2/2016 Shapiro

## FOREIGN PATENT DOCUMENTS

DE 3910749 A1 10/1990  
 EP 1 297 784 A1 4/2003  
 EP 1 480 278 A2 11/2004  
 EP 2 077 091 A2 7/2009  
 EP 2 182 839 B1 10/2011  
 GB 2 408 209 A 5/2005  
 GB 2 411 719 A 9/2005  
 JP 7-241279 9/1995  
 JP 9-253062 9/1997  
 JP 9-299342 11/1997  
 JP 2000-116611 4/2000  
 JP 2001-025462 1/2001  
 JP 20030159221 6/2003  
 JP 2004-513750 A 5/2004  
 JP 2004-283523 10/2004  
 JP 2007-044203 2/2007  
 JP 2007-185348 7/2007  
 JP 2008-136556 A 6/2008  
 JP 2008-279061 A 11/2008  
 JP 2009-153664 A 7/2009  
 JP 2010-526646 8/2010  
 JP 2014-068733 A 4/2014  
 KR 20-0204510 Y1 11/2000  
 WO WO 00/24064 4/2000  
 WO WO 2000/047108 A1 8/2000  
 WO WO 01/08552 A1 2/2001  
 WO WO 02/17782 A2 3/2002  
 WO WO 2002/017782 A2 3/2002  
 WO WO 2005/010568 A2 2/2005  
 WO WO 2005/020121 A1 3/2005  
 WO WO 2005/110238 A1 11/2005  
 WO WO 2006/009830 A2 1/2006  
 WO WO 2006/067690 A2 6/2006

(56) **References Cited**

## FOREIGN PATENT DOCUMENTS

WO WO 2007/012931 A2 2/2007  
 WO WO 2007/053146 A1 5/2007  
 WO WO 2008/141306 A2 11/2008  
 WO WO 2013/019494 A2 2/2013  
 WO WO 2013/038296 A1 3/2013  
 WO WO 2013/109390 A1 7/2013  
 WO WO 2014/092932 A1 6/2014  
 WO WO 2015/068066 A1 5/2015  
 WO WO 2015/131065 A1 9/2015

## OTHER PUBLICATIONS

European Search Report, EP Application No. 13863449.8, dated Oct. 19, 2015, 3 pages.

European Search Report, EP Application No. 14743615.8, dated Oct. 12, 2015, 3 pages.

European Search Report, EP Application No. 14743839.4, dated Oct. 12, 2015, 3 pages.

Gibbs et al., "Reducing Motion Artifact in Wearable Bio-Sensors Using MEMS Accelerometers for Active Noise Cancellation," 2005 American Control Conference, Jun. 8-10, 2005, Portland, OR, USA, pp. 1581-1586.

International Preliminary Report on Patentability, PCT/US2014/012940, dated Jun. 17, 2015, 23 pages.

International Search Report and Written Opinion of the International Searching Authority, corresponding to International Patent Application No. PCT/US2014/012940, dated Oct. 16, 2014, 13 pages.

International Search Report corresponding to International Patent Application No. PCT/US2014/012909, dated May 13, 2014, 3 pages.

Notification Concerning Transmittal of International Preliminary Report on Patentability, PCT/US2014/012909, dated Jul. 28, 2015.

Notification of Transmittal of the International Search Report and the Written Opinion of the International Searching Authority, or the Declaration, PCT/US2015/014562, dated Oct. 28, 2015.

Notification of Transmittal of the International Search Report and the Written Opinion of the International Searching Authority, or the Declaration, PCT/US2015/042636, dated Oct. 29, 2015.

Notification of Transmittal of the International Search Report and the Written Opinion of the International Searching Authority, or the Declaration, PCT/US2015/042015, dated Oct. 29, 2015.

Notification of Transmittal of the International Search Report and the Written Opinion of the International Searching Authority, or the Declaration, PCT/US2015/042035, dated Oct. 29, 2015.

Wood et al., "Active Motion Artifact Reduction for Wearable Sensors Using Laguerre Expansion and Signal Separation," Proceedings of the 2005 IEEE Engineering in Medicine and Biology, 27<sup>th</sup> Annual Conference, Shanghai, China, Sep. 1-4, 2005, pp. 3571-3574.

"U.S. Army Fitness Training Handbook" by the Department of the Army, 2003, The Lyons Press. p. 17.

"Warfighter Physiological and Environmental Monitoring: A Study for the U.S. Army Research Institute in Environmental Medicine and the Soldier Systems Center", Massachusetts Institute of Technology Lincoln Laboratory, Final Report, Nov. 1, 2004, prepared for the U.S. Army under Air Force Contract F19628-00-C-0002; approved for public release.

Anpo et al. "Photocatalytic Reduction of CO<sub>2</sub> With H<sub>2</sub>O on Titanium Oxides Anchored within Micropores of Zeolites: Effects of the Structure of the Active Sites and the Addition of Pt" *J. Phys. Chem. B*, 101:2632-2636 1997.

Bársan et al. "Understanding the fundamental principles of metal oxide based gas sensors; the example of CO sensing with SnO<sub>2</sub> sensors in the presence of humidity" *Journal of Physics: Condensed Matter* 15:R813-R839 (2003).

Bott "Electrochemistry of Semiconductors" *Current Separations* 17(3):87-91 (1998).

Colligan, M. J. et al. In "The psychological effects of indoor air pollution", Bulletin of the New York Academy of Medicine, vol. 57, No. 10, Dec. 1981, p. 1014-1026.

de Paula Santos, U. et al, In "Effects of air pollution on blood pressure and heart rate variability: a panel study of vehicular traffic controllers in the city of Sao Paulo, Brazil", *European Heart Journal* (2005) 26, 193-200.

Ebert, T et al., "Influence of Hydration Status on Thermoregulation and Cycling Hill Climbing," *Med. Sci. Sport Exerc.* vol. 39, No. 2, pp. 323-329, 2007.

European Search Report corresponding to European Application No. 07862660.3 dated Apr. 25, 2012; 7 pages.

Falkner et al, "Cardiovascular response to mental stress in normal adolescents with hypertensive parents. Hemodynamics and mental stress in adolescents," *Hypertension* 1979, 1:23-30.

FiTrainer "The Only Trainer You Need"; <http://itami.com>; Downloaded Feb. 26, 2010; © 2008 FiTrainer™; 2 pages.

Geladas et al., "Effect of cold air inhalation on core temperature in exercising subjects under stress," *The American Physiological Society*, pp. 2381-2387, 1988.

Gold, D.R. et al. In "Ambient Pollution and Heart Rate Variability", *Circulation* 2000, 101:1267-1273.

International Search Report corresponding to International Patent Application No. PCT/US2012/046446, dated Jan. 14, 2013, 3 pages.

International Search Report and Written Opinion of the International Searching Authority, corresponding to PCT/US2007/025114, dated May 13, 2008.

International Search Report Corresponding to International Application No. PCT/US2012/022634, dated Aug. 22, 2012, 9 pages.

Maomao et al., "Mobile Context-Aware Game for the Next Generation," 2<sup>nd</sup> International Conference on Application and Development of Computer Games ADCOG 2003, p. 78-81.

Martins et al. "Zinc oxide as an ozone sensor" *Journal of Applied Physics* 96(3):1398-1408 (2004).

Maughan, R.J., "Impact of mild dehydration on wellness and on exercise performance," *European Journal of Clinical Nutrition*, 57, Suppl. 2, pp. S19-S23, 2003.

Maughan et al., "Exercise, Heat, Hydration and the Brain," *Journal of the American College of Nutrition*, vol. 26, No. 5, pp. 604S-612S, 2007.

Mostardi, R., et al., "The effect of increased body temperature due to exercise on the heart rate and the maximal aerobic power," *Europ. J. Appl. Physiol*, 33, pp. 237-245, 1974.

Notification of Transmittal of the International Search Report and Written Opinion of the International Search Authority dated Jul. 30, 2010 by the Korean Intellectual Property Office for corresponding International Application No. PCT/US2010/021936.

Notification of Transmittal of the International Search Report and Written Opinion of the International Search Authority dated Aug. 26, 2010 by the Korean Intellectual Property Office for corresponding International Application No. PCT/US2010/021629.

Notification of Transmittal of the International Search Report and the Written Opinion of the International Search Authority dated Sep. 16, 2010 by the Korean Intellectual Property Office for corresponding International Application No. PCT/US2010/024922.

Notification of Transmittal of the International Search Report and the Written Opinion of the International Search Authority dated Sep. 27, 2010 by the Korean Intellectual Property Office for corresponding International Application No. PCT/US2010/025216.

Notification of Transmittal of the International Search Report and the Written Opinion of the International Searching Authority, or the Declaration corresponding to International Application No. PCT/US2013/070271; dated Feb. 26, 2014; 13 pages.

Saladin et al. "Photosynthesis of CH<sub>4</sub> at a TiO<sub>2</sub> Surface from Gaseous H<sub>2</sub>O and CO<sub>2</sub>" *J. Chem. Soc., Chem. Commun.* 533-534 (1995).

Shorten et al., "Acute effect of environmental temperature during exercise on subsequent energy intake in active men," *Am. J. Clin. Nutr.* 90, pp. 1215-1221, 2009.

Skubal et al. "Detection and identification of gaseous organics using a TiO<sub>2</sub> sensor" *Journal of Photochemistry and Photobiology A: Chemistry* 148:103-108 (2002).

(56)

## References Cited

## OTHER PUBLICATIONS

- Skubal et al. "Monitoring the Electrical Response of Photoinduced Organic Oxidation on TiO<sub>2</sub> Surfaces" Manuscript submitted Oct. 2000 to SPIE Intl. Symposium on Environment & Industrial Sensing, Boston, MA, Nov. 5-8, 2000, sponsored by SPIE, 10 pp.
- Thompson, M.W., "Cardiovascular drift and critical core temperature: factors limiting endurance performance in the heat?" *J. Exerc. Sci. Fit*, vol. 4, No. 1, pp. 15-24, 2006.
- Zhang et al. "Development of Chemical Oxygen Demand On-Line Monitoring System Based on a Photoelectrochemical Degradation Principle" *Environ. Sci. Technol.*, 40(7):2363-2368 (2006).
- Communication with Supplementary European Search Report, EP Application No. 12820308.0, dated Apr. 30, 2015.
- International Search Report and Written Opinion of the International Searching Authority, PCT Application No. PCT/US2012/048079, dated Oct. 9, 2012.
- Fleming et al., "A Comparison of Signal Processing Techniques for the Extraction of Breathing Rate from the Photoplethysmogram", *World Academy of Science, Engineering and Technology*, vol. 30, Oct. 2007, pp. 276-280.
- Nakajima et al., "Monitoring of heart and respiratory rates by photoplethysmography using a digital filtering technique", *Med. Eng. Phys.*, vol. 18, No. 5, Jul. 1996 pp. 365-372.
- Communication pursuant to Article 94(3) EPC, European Patent Application No. 12820308.0, dated Feb. 3, 2016, 5 pages.
- Notification of Transmittal of the International Search Report and Written Opinion of the International Searching Authority dated May 26, 2016 by the Korean Intellectual Property Office for corresponding International Application No. PCT/US2016/019126.
- Notification of Transmittal of the International Search Report and Written Opinion of the International Searching Authority dated May 26, 2016 by the Korean Intellectual Property Office for corresponding International Application No. PCT/US2016/019132.
- Notification of Transmittal of the International Search Report and the Written Opinion of the International Searching Authority, or the Declaration, PCT/US2015/046079, dated Dec. 29, 2015.
- Communication pursuant to Article 94(3) EPC, European Patent Application No. 13863449.8, dated Nov. 5, 2015, 7 pages.
- Communication pursuant to Article 94(3) EPC, European Patent Application No. 14743615.8, dated Dec. 23, 2015, 7 pages.
- Communication pursuant to Article 94(3) EPC, European Patent Application No. 14743839.4, dated Dec. 23, 2015, 6 pages.
- Extended European Search Report, EP Application No. 16164775.5 dated Sep. 13, 2016, 7 pages.
- Notification of Transmittal of the International Search Report and the Written Opinion of the International Searching Authority, or the Declaration, PCT/US2016/041842, dated Oct. 21, 2016, 5 pages.
- Notification of Transmittal of International Preliminary Report on Patentability, PCT/US2015/041562, dated Oct. 20, 2016, 14 pages.
- Notification of Transmittal of International Preliminary Report on Patentability, PCT/US2015/042636, dated Oct. 20, 2016, 7 pages.
- Notification of Transmittal of International Preliminary Report on Patentability, PCT/US2015/042015, dated Oct. 20, 2016, 10 pages.
- Notification of Transmittal of International Preliminary Report on Patentability, PCT/US2015/042035, dated Oct. 20, 2016, 8 pages.
- Notification of Transmittal of International Preliminary Report on Patentability, PCT/US2015/046079, dated Oct. 20, 2016, 10 pages.
- Asada, et al., "Mobile Monitoring with Wearable Photoplethysmographic Biosensors," *IEEE Engineering in Medicine and Biology Magazine*, May/June 2003, pp. 28-40.
- Bifulco et al., "Bluetooth Portable Device for Continuous ECG and Patient Motion Monitoring During Daily Life," *Medicon 2007, IFMBE Proceedings 16*, 2007, pp. 369-372.
- Brodersen et al., "In-Ear Acquisition of Vital Signs Discloses New Chances for Preventive Continuous Cardiovascular Monitoring," 4th International Workshop on Wearable and Implantable Body Sensor Networks (BSN 2007), vol. 13 of the series IFMBE Proceedings, pp. 189-194.
- Celka et al., "Motion Resistant Earphone Located Infrared based Heart Rate Measurement Device," *Proceedings of the Second IASTED International Conference on Biomedical Engineering*, Feb. 16-18, 2004, Innsbruck, Austria, pp. 582-585.
- Communication Pursuant to Article 94(3) EPC, EP 12 739 502.8, dated Jul. 19, 2016, 7 pages.
- Communication Pursuant to Article 94(3) EPC, EP 14 743 615.8, dated Jul. 19, 2016, 7 pages.
- Communication Pursuant to Article 94(3) EPC, EP 14 743 839.4, dated Jul. 20, 2016, 5 pages.
- Comtois et al., "A Wearable Wireless Reflectance Pulse Oximeter for Remote Triage Applications," 2006 IEEE, pp. 53-54.
- Comtois, Gary, W., "Implementation of Accelerometer-Based Adaptive Noise Cancellation in a Wireless Wearable Pulse Oximeter Platform for Remote Physiological Monitoring and Triage," Thesis, Worcester Polytechnic Institute, Aug. 31, 2007, 149 pages.
- Duun et al., "A Novel Ring Shaped Photodiode for Reflectance Pulse Oximetry in Wireless Applications," *IEEE Sensors 2007 Conference*, pp. 596-599.
- Geun et al., "Measurement Site and Applied Pressure Consideration in Wrist Photoplethysmography," *The 23<sup>rd</sup> International Technical Conference on Circuits/Systems, Computers and Communications*, 2008, pp. 1129-1132.
- Gibbs et al., "Active motion artifact cancellation for wearable health monitoring sensors using collocated MEMS accelerometers," *Smart Structures and Materials, 2005: Sensors and Smart Structures Technologies for Civil, Mechanical, and Aerospace Systems*, Proc. of SPIE, vol. 5765, pp. 811-819.
- Haahr et al., "A Wearable "Electronic Patch" for Wireless Continuous Monitoring of Chronically Diseased Patients," *Proceedings of the 5<sup>th</sup> International Workshop on Wearable and Implantable Body Sensor Networks*, in conjunction with the 5<sup>th</sup> International Summer School and Symposium on Medical Devices and Biosensors, The Chinese University of Hong Kong, HKSAR, China, Jun. 1-3, 2008, pp. 66-70.
- Han et al., "Artifacts in wearable photoplethysmographs during daily life motions and their reduction with least mean square based active noise cancellation method," *Computers in Biology and Medicine*, 42, 2012, pp. 387-393.
- Jiang, Honghui, "Motion-Artifact Resistant Design of Photoplethysmograph Ring Sensor for Driver Monitoring," Thesis, Massachusetts Institute of Technology, Feb. 2004, 62 pages.
- Kuzmina et al., "Compact multi-functional skin spectrometry setup," *Advanced Optical Materials, Technologies, and Devices*, Proc. of SPIE, vol. 6596, 2007, pp. 65960T-1 to 65960T-6.
- Lee et al., "Respiratory Rate Detection Algorithms by Photoplethysmography Signal Processing," 30<sup>th</sup> Annual International IEEE EMBS Conference, Vancouver, British Columbia, Canada, Aug. 20-24, 2008, pp. 1140-1143.
- Lindberg et al., "Monitoring of respiratory and heart rates using a fibre-optic sensor," *Med Biol Eng Comput*, Sep. 1992, vol. 30, No. 5, pp. 533-537.
- Luprano, Jean, "Sensors and Parameter Extraction by Wearable Systems: Present Situation and Future," *pHealth 2008*, May 21, 2008, 29 pages.
- Lygouras et al., "Optical-Fiber Finger Photo-Plethysmograph Using Digital Techniques," *IEEE Sensors Journal*, vol. 2, No. 1, Feb. 2002, pp. 20-25.
- Maguire et al., "The Design and Clinical Use of a Reflective Brachial Photoplethysmograph," Technical Report NIUM/SS/-/2002/04, Submitted Apr. 2002, Signals and Systems Research Group, National University of Ireland, Maynooth, Co. Kildare, Ireland, 13 pages.
- Mendelson et al., "Measurement Site and Photodetector Size Considerations in Optimizing Power Consumption of a Wearable Reflectance Pulse Oximeter," *Proceedings of the 25<sup>th</sup> Annual International Conference of the IEEE EMBS*, Cancun, Mexico, Sep. 17-21, 2003, pp. 3016-3019.
- Mendelson et al., "Noninvasive Pulse Oximetry Utilizing Skin Reflectance Photoplethysmography," *IEEE Transactions on Biomedical Engineering*, vol. 35, No. 10, Oct. 1988, pp. 798-805.
- Poh et al., "Motion Tolerant Magnetic Earring Sensor and Wireless Earpiece for Wearable Photoplethysmography," *IEEE Transactions on Information Technology in Biomedicine*, vol. 14, No. 3, May 2010, pp. 786-794.

(56)

**References Cited**

## OTHER PUBLICATIONS

Renevey et al., "Wrist-Located Pulse Detection Using IR Signals, Activity and Nonlinear Artifact Cancellation," IEEE EMBS, 2001, 4 pages.

Rhee et al., "Artifact-Resistant Power-Efficient Design of Finger-Ring Plethysmographic Sensors," IEEE Transactions on Biomedical Engineering, vol. 48, No. 7, Jul. 2001, pp. 795-805.

Shaltis, Phillip Andrew, Analysis and Validation of an Artifact Resistant Design for Oxygen Saturation Measurement Using Photo Plethysmographic Ring Sensors, Thesis, Massachusetts Institute of Technology, Jun. 2004, 103 pages.

Shin et al., "A Novel Headset with a Transmissive PPG Sensor for Heart Rate Measurement," ICBME 2008, Proceedings 23, 2009, pp. 519-522.

Spigulis et al., "Wearable wireless photoplethysmography sensors," Proc. of SPIE, vol. 6991, 2008, pp. 69912O-1 to 69912O-7.

Takatani et al., "Optical Oximetry Sensors for Whole Blood and Tissue," IEEE Engineering in Medicine and Biology, Jun./Jul. 1994, pp. 347-357.

Vogel et al., "A System for Assessing Motion Artifacts in the Signal of a Micro-Optic In-Ear Vital Signs Sensor," 30<sup>th</sup> Annual International IEEE EMBS Conference, Vancouver, British Columbia, Canada, Aug. 20-24, 2008.

Vogel et al., "In-Ear Heart Rate Monitoring Using a Micro-Optic Reflective Sensor," Proceedings of the 29<sup>th</sup> Annual International Conference of the IEEE EMBS Cite Internationale, Lyon, France, Aug. 23-26, 2007, pp. 1375-1378.

Wang et al., "Multichannel Reflective PPG Earpiece Sensor With Passive Motion Cancellation," IEEE Transactions on Biomedical Circuits and Systems, vol. 1, No. 4, Dec. 2007, pp. 235-241.

Wang et al., "Reflective Photoplethysmograph Earpiece Sensor for Ubiquitous Heart Rate Monitoring," 4<sup>th</sup> International Workshop on Wearable and Implantable Body Sensor Networks, 2007, vol. 13 of the series IFMBE Proceedings, pp. 179-183.

Wei et al. "A New Wristband Wearable Sensor Using Adaptive Reduction Filter to Reduce Motion Artifact," Proceedings of the 5<sup>th</sup> International Conference on Information Technology and Application in Biomedicine, in conjunction with the 2<sup>nd</sup> International Symposium & Summer School on Biomedical and Health Engineering, Shenzhen, China, May 30-31, 2008, pp. 278-281.

Wood, Levi Benjamin, "Motion Artifact Reduction for Wearable Photoplethysmogram Sensors Using Micro Accelerometers and Laguerre Series Adaptive Filters," Thesis, Massachusetts Institute of Technology, Jun. 2008, 74 pages.

Wikipedia "Least mean squares filter" Retrieved on Mar. 17, 2016 at URL [https://en.wikipedia.org/wiki/Least\\_mean\\_squares\\_filter](https://en.wikipedia.org/wiki/Least_mean_squares_filter) (6 pages).




FIG. 1




FIG. 2




FIG. 3




FIG. 4





FIG. 5






FIG. 7




FIG. 8





FIG. 9



**FIG. 10**




FIG. 11




FIG. 12




FIG. 13





FIG. 14



**FIG. 15**

**SYSTEMS AND METHODS FOR VARIABLE  
FILTER ADJUSTMENT BY HEART RATE  
METRIC FEEDBACK**

CROSS REFERENCE TO RELATED  
APPLICATIONS

This application is a 35 U.S.C. §371 national stage application of PCT International Application No. PCT/US2012/048079, filed on 25 Jul. 2012, which itself claims the benefit of provisional Patent Application No. 61/514,099, filed Aug. 2, 2011, entitled Systems and Methods for Variable Filter Adjustment by Physiological Metric Feedback, assigned to the assignee of the present invention, the disclosures of both of which are hereby incorporated herein by reference in their entirety as if set forth fully herein.

BACKGROUND

Various embodiments described herein relate generally to signal processing systems and methods, and more particularly to physiological signal processing systems and methods.

There is a growing market demand for personal health and environmental monitors, for example, for gauging overall health, fitness, metabolism, and vital status during exercise, athletic training, work, public safety activities, dieting, daily life activities, sickness and physical therapy. These personal health and environmental monitors process physiological signals that may be obtained from one or more physiological sensors, and are configured to extract one or more physiological metrics from physiological waveforms. Unfortunately, inaccurate physiological metric extraction can reduce the accuracy of health, fitness and/or vital status monitoring.

SUMMARY

It should be appreciated that this Summary is provided to introduce a selection of concepts in a simplified form, the concepts being further described below in the Detailed Description. This Summary is not intended to identify key features or essential features of this disclosure, nor is it intended to limit the scope of the invention.

Various embodiments described herein can provide physiological signal processing systems for physiological waveforms that include cardiovascular signal components therein. These physiological signal processing systems may include a variable high pass filter that is responsive to the physiological waveform and that is configured to high pass filter the physiological waveform in response to a corner frequency that is applied thereto. A heart rate metric extractor is responsive to the variable high pass filter and is configured to extract a heart rate metric from the physiological waveform that is high pass filtered. A corner frequency adjuster is responsive to the heart rate metric extractor and is configured to determine the corner frequency that is applied to the variable high pass filter, based on the heart rate metric that was extracted. A physiological metric assessor may also be provided that is responsive to the heart rate metric extractor and that is configured to process the heart rate metric to generate at least one physiological assessment.

Physiological waveforms may be processed according to various embodiments described herein. For example, the physiological waveform may include an electroencephalogram (EEG), an electrocardiogram (ECG) and/or a radio frequency (RF) waveform, an electro-optical physiological waveform including a photoplethysmograph (PPG) wave-

form, an electro-photoacoustic waveform including a photoacoustic waveform, an electro-mechanical physiological waveform including an auscultation waveform, a piezo sensor waveform and/or an accelerometer waveform, and/or an electro-nuclear physiological waveform. Moreover, various physiological assessments may be provided including ventilator threshold, lactate threshold, cardiopulmonary status, neurological status, aerobic capacity ( $VO_2$  max) and/or overall health or fitness.

Various configurations of variable high pass filters may also be provided according to various embodiments described herein. For example, the variable high pass filter may comprise a single high pass filter having an adjustable corner frequency, wherein the corner frequency adjuster is configured to determine the adjustable corner frequency. Alternatively, the variable high pass filter may comprise a plurality of high pass filters, a respective one of which includes a different value of the corner frequency, wherein the corner frequency adjuster is configured to select one of the plurality of high pass filters that corresponds to the corner frequency that is determined.

Various other embodiments of variable high pass filters may also be provided. Analog variable high pass filters may be provided with adjustable component values thereof. Alternatively, the variable high pass filter may comprise a variable digital high pass filter having a plurality of delay taps, wherein the corner frequency corresponds to a number of the plurality of delay taps that are selected to filter the physiological waveform. In these embodiments, the corner frequency adjuster may comprise a mapping system that is configured to map the heart rate metric that is extracted from the physiological waveform that is filtered into the number of the delay taps that are selected to high pass filter the physiological waveform.

Various embodiments described herein can also configure the corner frequency adjuster to reduce or prevent locking on an erroneous heart rate metric. In some embodiments, the corner frequency adjuster is configured to initially set a predetermined corner frequency corresponding to a predetermined heart rate prior to determining the corner frequency that is applied to the variable high pass filter from the heart rate metric. The predetermined heart rate may be a resting heart rate, such as 72 beats per minute. The corner frequency adjuster may also be configured to initially set the predetermined corner frequency corresponding to the predetermined heart rate until the heart rate metric extractor locks on a heart rate of the physiological waveform. Moreover, the corner frequency adjuster may also be configured to reset or reapply the predetermined corner frequency corresponding to the predetermined heart rate in response to determining that the physiological sensor is no longer responsive to a source of the physiological waveform. The corner frequency adjuster may also be configured to determine the at least one corner frequency that is applied to the variable high pass filter from the heart rate metric by applying a margin to the heart rate metric. Moreover, the variable high pass filter may include a gradual filter transition band (i.e., it is not a brick wall filter).

Various embodiments described herein may also provide physiological signal processing systems that may be used with physiological sensors that are configured to generate a physiological waveform that includes cardiovascular and pulmonary signal components therein. A variable high pass filter and a variable low pass filter are provided that are responsive to the physiological waveform and that are configured to high pass and low pass filter, respectively, the physiological waveform in response to at least one corner

frequency that is applied thereto. A heart rate metric extractor is provided that is responsive to the variable high pass filter and that is configured to extract a heart rate metric from the physiological waveform that is filtered by the variable high pass filter. A respiration rate metric extractor is provided that is responsive to the variable low pass filter and that is configured to extract a respiration rate metric from the physiological waveform that is filtered by the variable low pass filter. A corner frequency adjuster is also provided that is responsive to the heart rate metric extractor and that is configured to determine the at least one corner frequency that is applied to the variable high pass filter and the variable low pass filter from the heart rate metric.

The variable high pass and the variable low pass filter may respectively comprise a single high pass and a single low pass filter having an adjustable corner frequency, and the corner frequency adjuster may be configured to determine the adjustable corner frequency for the single high pass filter and the single low pass filter. Alternatively, the variable high pass filter and the variable low pass filter may respectively comprise a plurality of high pass filters and a plurality of low pass filters, a respective one of which includes a different corner frequency, and the corner frequency adjuster may be configured to select one of the plurality of high pass filters and one of the plurality of low pass filters that corresponds to the at least one corner frequency that is determined by the corner frequency adjuster.

Moreover, in some embodiments, the variable high pass filter and the variable low pass filter comprise a variable digital high pass filter and a variable digital low pass filter having a plurality of high pass and low pass delay taps, respectively, and the corner frequency is determined by a number of the high pass and low pass delay taps that are selected to filter the physiological waveform.

The corner frequency adjuster may also comprise a mapping system that is configured to map the heart rate metric that is extracted from the physiological waveform that is filtered into the number of the delay taps that are selected to filter the physiological waveform. The mapping system may be configured to determine a corner frequency of the variable low pass filter and the variable high pass filter by determining a maximum of a minimum heart rate and the heart rate metric minus a margin, and may be further configured to determine the number of delay taps by rounding a product of the delay of the delay taps and the minimum heart rate divided by the corner frequency that was determined. Moreover, the mapping system may be configured to determine a corner frequency of the variable low pass filter and the variable high pass filter by applying a margin to the heart rate metric, and may be further configured to determine the number of delay taps from the corner frequency that was determined.

Various embodiments described herein can also configure the corner frequency adjuster to reduce or prevent locking on an erroneous heart rate metric. In some embodiments, the corner frequency adjuster is configured to initially set at least one predetermined corner frequency corresponding to a predetermined heart rate prior to determining the at least one corner frequency that is applied to the variable high pass filter and the variable low pass filter from the heart rate metric. The predetermined heart rate may be a resting heart rate, such as 72 beats per minute. The corner frequency adjuster may be configured to initially set the at least one predetermined corner frequency corresponding to the predetermined heart rate until the heart rate metric extractor locks on a heart rate in the physiological waveform. The corner frequency may also be configured to reset or reapply

the at least one predetermined corner frequency corresponding to the predetermined heart rate in response to determining that the physiological sensor is no longer responsive to a source of the physiological waveform. The corner frequency adjuster may be configured to determine the corner frequency that is applied to the variable high pass filter and the variable low pass filter from the heart rate metric by applying a margin to the heart rate metric. Moreover, the variable high pass filter may include a gradual filter transition band (i.e., it is not a brick wall filter).

In any of the embodiments described herein, the corner frequency adjuster may include hysteresis to reduce or prevent excessive filter adjustment. Moreover, in any of these embodiments, the at least one corner frequency may comprise a same corner frequency that is applied to the variable high pass and low pass filters. Finally, in any of these embodiments, the sensor may be a plethysmograph sensor and, more specifically, a photoplethysmograph sensor.

Various embodiments have been described above in connection with physiological signal processing systems. However, analogous physiological signal processing methods may also be provided according to various embodiments described herein. For example, some embodiments described herein can provide a physiological signal processing method comprising high pass filtering the physiological waveform in response to an adjustable high pass filter corner frequency, extracting a heart rate metric from the physiological waveform that is high pass filtered and determining the adjustable high pass filter corner frequency that is applied to the high pass filtering, from the heart rate that was extracted. Moreover, the determining may be provided by selecting one of a plurality of high pass filters that corresponds to the high pass filter corner frequency that is determined, or determining a number of a plurality of delay taps that are selected in the filtering. Other embodiments corresponding to the above described system embodiments also may be provided.

Yet other embodiments of physiological signal processing methods comprise obtaining a physiological waveform that includes cardiovascular and pulmonary signal components therein, variable high pass and low pass filtering the physiological waveform in response to at least one corner frequency, extracting a heart rate metric from the physiological waveform that is filtered by the variable high pass filtering, extracting a respiration rate metric from the physiological waveform that is filtered by the variable low pass filtering, and determining the at least one corner frequency that is applied to the variable high pass and low pass filtering from the heart rate metric that was extracted. Again, the determining may comprise adjusting the corner frequency for the variable high pass and low pass filtering, for example by selecting one of a plurality of high pass and low pass filters that corresponds to at least one corner frequency that is determined and/or determining a number of a plurality of high pass and low pass delay taps that are selected by the variable high pass and low pass filtering. Specifically, the heart rate metric may be mapped into the number of delay taps. This may be embodied, for example, by determining a corner frequency of the variable low pass and the variable high pass filtering by applying a margin to the heart rate metric and determining the number of delay taps from the corner frequency. Other embodiments corresponding to the above described system embodiments may also be provided.

#### BRIEF DESCRIPTION OF THE DRAWINGS

FIGS. 1-4 are functional block diagrams of physiological signal processing systems and methods according to various embodiments described herein.

FIG. 5 is a functional block diagram of a digital variable high pass filter according to various embodiments described herein.

FIG. 6 is a functional block diagram of a digital variable low pass filter according to various embodiments described herein.

FIG. 7 is a flowchart of operations that may be performed by a corner frequency adjuster according to various embodiments described herein.

FIG. 8 graphically illustrates adjusting a corner frequency of a variable high pass filter according to various embodiments described herein.

FIG. 9 graphically illustrates adjusting a corner frequency of a variable low pass filter according to various embodiments described herein.

FIGS. 10-15 illustrate measured waveforms according to various embodiments described herein.

#### DETAILED DESCRIPTION

The present invention will now be described more fully hereinafter with reference to the accompanying figures, in which various embodiments are shown. This invention may, however, be embodied in many different forms and should not be construed as limited to the embodiments set forth herein. Like numbers refer to like elements throughout. The sequence of operations (or steps) is not limited to the order presented in the figures and/or claims unless specifically indicated otherwise. Features described with respect to one figure or embodiment can be associated with another embodiment or figure although not specifically described or shown as such.

It will be understood that, when a feature or element is referred to as being “connected”, “attached”, “coupled” or “responsive” to another feature or element, it can be directly connected, attached, coupled or responsive to the other feature or element or intervening features or elements may be present. In contrast, when a feature or element is referred to as being “directly connected”, “directly attached”, “directly coupled” or “directly responsive” to another feature or element, there are no intervening features or elements present.

The terminology used herein is for the purpose of describing particular embodiments only and is not intended to be limiting of the invention. As used herein, the singular forms “a”, “an” and “the” are intended to include the plural forms as well, unless the context clearly indicates otherwise. It will be further understood that the terms “comprises” and/or “comprising,” when used in this specification, specify the presence of stated features, steps, operations, elements, and/or components, but do not preclude the presence or addition of one or more other features, steps, operations, elements, components, and/or groups thereof. As used herein, the term “and/or” includes any and all combinations of one or more of the associated listed items.

It will be understood that although the terms first and second are used herein to describe various features/elements, these features/elements should not be limited by these terms. These terms are only used to distinguish one feature/element from another feature/element. Thus, a first feature/element discussed below could be termed a second feature/element, and similarly, a second feature/element discussed below could be termed a first feature/element without departing from the teachings of the present invention.

Unless otherwise defined, all terms (including technical and scientific terms) used herein have the same meaning as

commonly understood by one of ordinary skill in the art to which this invention belongs. It will be further understood that terms, such as those defined in commonly used dictionaries, should be interpreted as having a meaning that is consistent with their meaning in the context of the specification and relevant art and should not be interpreted in an idealized or overly formal sense unless expressly so defined herein. Well-known functions or constructions may not be described in detail for brevity and/or clarity.

The term “headset” includes any type of device or earpiece that may be attached to or near the ear (or ears) of a user and may have various configurations, without limitation. Headsets as described herein may include mono headsets (one earbud) and stereo headsets (two earbuds), earbuds, hearing aids, ear jewelry, face masks, headbands, and the like.

The term “real-time” is used to describe a process of sensing, processing, or transmitting information in a time frame which is equal to or shorter than the minimum timescale at which the information is needed. For example, the real-time monitoring of pulse rate may result in a single average pulse-rate measurement every minute, averaged over 30 seconds, because an instantaneous pulse rate is often useless to the end user. Typically, averaged physiological and environmental information is more relevant than instantaneous changes. Thus, in the context of embodiments of the present invention, signals may sometimes be processed over several seconds, or even minutes, in order to generate a “real-time” response.

The term “monitoring” refers to the act of measuring, quantifying, qualifying, estimating, sensing, calculating, interpolating, extrapolating, inferring, deducing, or any combination of these actions. More generally, “monitoring” refers to a way of getting information via one or more sensing elements. For example, “blood health monitoring” includes monitoring blood gas levels, blood hydration, and metabolite/electrolyte levels.

The term “physiological” refers to matter or energy of or from the body of a creature (e.g., humans, animals, etc.). In embodiments of the present invention, the term “physiological” is intended to be used broadly, covering both physical and psychological matter and energy of or from the body of a creature. However, in some cases, the term “psychological” is called-out separately to emphasize aspects of physiology that are more closely tied to conscious or subconscious brain activity rather than the activity of other organs, tissues, or cells.

The term “body” refers to the body of a subject (human or animal) who may wear a headset incorporating embodiments of the present invention.

In the included figures, various embodiments will be illustrated and described. However, it is to be understood that embodiments of the present invention are not limited to those worn by humans.

The ear is an ideal location for wearable health and environmental monitors. The ear is a relatively immobile platform that does not obstruct a person’s movement or vision. Headsets located at an ear have, for example, access to the inner-ear canal and tympanic membrane (for measuring core body temperature), muscle tissue (for monitoring muscle tension), the pinna and earlobe (for monitoring blood gas levels), the region behind the ear (for measuring skin temperature and galvanic skin response), and the internal carotid artery (for measuring cardiopulmonary functioning), etc. The ear is also at or near the point of exposure to: environmental breathable toxicants of interest (volatile organic compounds, pollution, etc.); noise pollution experi-

enced by the ear; and lighting conditions for the eye. Furthermore, as the ear canal is naturally designed for transmitting acoustical energy, the ear provides a good location for monitoring internal sounds, such as heartbeat, breathing rate, and mouth motion.

Wireless, Bluetooth®-enabled, and/or other personal communication headsets may be configured to incorporate physiological and/or environmental sensors, according to some embodiments of the present invention. As a specific example, Bluetooth® headsets are typically lightweight, unobtrusive devices that have become widely accepted socially. Moreover, Bluetooth® headsets are cost effective, easy to use, and are often worn by users for most of their waking hours while attending or waiting for cell phone calls. Bluetooth® headsets configured according to embodiments of the present invention are advantageous because they provide a function for the user beyond health monitoring, such as personal communication and multimedia applications, thereby encouraging user compliance. Exemplary physiological and environmental sensors that may be incorporated into a Bluetooth® or other type of headsets include, but are not limited to accelerometers, auscultatory sensors, pressure sensors, humidity sensors, color sensors, light intensity sensors, pressure sensors, etc.

Optical coupling into the blood vessels of the ear may vary between individuals. As used herein, the term “coupling” refers to the interaction or communication between excitation light entering a region and the region itself. For example, one form of optical coupling may be the interaction between excitation light generated from within a light-guiding earbud and the blood vessels of the ear. Light guiding earbuds are described in co-pending U.S. Patent Application Publication No. 2010/0217102, which is incorporated herein by reference in its entirety. In one embodiment, this interaction may involve excitation light entering the ear region and scattering from a blood vessel in the ear such that the intensity of scattered light is proportional to blood flow within the blood vessel. Another form of optical coupling may be the interaction between excitation light generated by an optical emitter within an earbud and the light-guiding region of the earbud.

Various embodiments described herein are not limited to headsets that communicate wirelessly. In some embodiments of the present invention, headsets configured to monitor an individual’s physiology and/or environment may be wired to a device that stores and/or processes data. In some embodiments, this information may be stored on the headset itself. Furthermore, various embodiments described herein are not limited to earbuds. Some embodiments may be employed around another part of the body, such as a digit, finger, toe, limb, wrist, around the nose or earlobe, or the like. Other embodiments may be integrated into a patch, such as a bandage that sticks on a person’s body.

Various embodiments described herein may arise from recognition that a physiological signal component in a physiological waveform may change dramatically over time, for example due to the user’s activity level and/or other factors. In order to effectively extract a physiological metric from the physiological waveform, the physiological metric itself may be used to directly or indirectly adjust a parameter of a variable filter, such as a filter’s low pass or high pass corner frequency. Accordingly, accurate filtering may be provided and accurate parameter extraction may be obtained, notwithstanding the large changes that may take place in the value of the physiological metric.

It also may be exceedingly difficult to extract metrics from physiological sensors that generate physiological wave-

forms that include multiple physiological signal components therein. For example, a physiological sensor, such as a plethysmograph or a photoplethysmograph, may include cardiovascular and pulmonary signal components therein. Unfortunately, these physiological metrics have overlapping frequency ranges. For example, the cardiovascular signal component (heart rate) may range from about 45 beats per minute to about 220 beats per minute, while the pulmonary signal component (respiration rate) may range from about 12 breaths per minute to about 70 breaths per minute. Due to the overlap, it may be exceedingly difficult to separate the two physiological components.

However, various embodiments described herein may arise from further recognition that, in general, although heart rate and respiration rate may overlap, their rise and fall may generally track due to, for example, changes in physical activity or the environment. Thus, they may both generally go up together and go down together. Accordingly, various embodiments described herein can provide a variable high pass and a variable low pass filter having at least one corner frequency that can be varied in response to a heart rate metric that is extracted from the high pass filtered physiological waveform. By providing variable filter adjustment using physiological metric feedback, the heart and/or respiration rate may be extracted accurately, notwithstanding the fact that they are contained in the same signal and overlap in their frequency ranges.

Various embodiments described herein may also arise from recognition that it did not appear to be heretofore possible to use an extracted heart rate to control a high pass filter that feeds a heart rate metric extractor. Specifically, due to the possibility for the extracted heart rate to be in error, the high pass filter may blind the metric extractor from the heart rate frequency in the physiological waveform signal. In other words, the heart rate metric extractor may get stuck at a high rate and, due to the high pass filtering that takes place, may never become responsive to the heart rate in the physiological waveform. Accordingly, the heart rate metric extractor may diverge or run away from the actual heart rate. Yet, despite these potential problems, various embodiments described herein can allow an extracted heart rate metric to be used to set a variable high pass filter corner frequency, and in some embodiments to also set a variable low pass filter corner frequency, while reducing or eliminating the heart rate extractor from being blinded to its own frequency.

Accordingly, various embodiments described herein can reduce or prevent locking on an erroneous heart rate metric. Thus, a heart rate metric can be used to set a corner frequency of a variable high pass filter for heart rate extraction. Moreover, the heart rate metric that is extracted may also be used to set a corner frequency for a variable low pass filter for respiration rate extraction, according to various embodiments described herein.

FIG. 1 is a functional block diagram of physiological signal processing systems and methods according to various embodiments described herein. Referring now to FIG. 1, these physiological signal processing systems/methods 100 may be used to process a physiological waveform 112 that is produced by a physiological sensor 110, and that includes a physiological signal component therein. The physiological waveform 112 may include an electrical physiological waveform including an electroencephalogram (EEG), an electrocardiogram (ECG) and/or a radio frequency (RF) waveform, an electro-optical physiological waveform including a photoplethysmograph (PPG) waveform, an electro-photoacoustic waveform including a photoacoustic waveform, an electro-mechanical physiological waveform including an

auscultation waveform, a piezo sensor waveform and/or an accelerometer waveform, and/or an electro-nuclear physiological waveform. The physiological signal component may include a neurological, cardiovascular and/or pulmonary signal component. For example, in some embodiments, the physiological sensor **110** may be a plethysmograph sensor, such as a photoplethysmograph (PPG) sensor, and the physiological waveform may include both cardiovascular and pulmonary signal components therein.

Still referring to FIG. 1, a heart rate metric extractor **130** extracts a heart rate metric **132** from the physiological waveform **112**. The heart rate metric extractor **130** may extract the heart rate metric using one or more conventional techniques. Moreover, a heart rate metric assessor **150** may be provided to assess the heart rate metric according to one or many known physiological metric assessment techniques. The physiological assessment may include ventilator threshold, lactate threshold, cardiopulmonary status, neurological status, aerobic capacity (VO<sub>2</sub> max) and/or overall health or fitness.

Still referring to FIG. 1, the heart rate metric extractor **130** is coupled to the physiological sensor **110** by a variable high pass filter **120**. The variable high pass filter **120** is responsive to the physiological sensor **110**, and is configured to high pass filter the physiological waveform **112** in response to a corner frequency **142** that is applied thereto. The high pass filter **120** may include a single analog or digital high pass filter having an adjustable corner frequency **142**. Alternatively, the variable high pass filter **120** may comprise a plurality of analog or digital high pass filters, a respective one of which includes a different value of the corner frequency **142**. Moreover, depending on the physiological waveform that is processed, the variable filter may be a variable high pass, low pass, bandpass, notch and/or other filter, and the filter parameter may be a low pass filter corner frequency, a high pass filter corner frequency, a bandpass filter corner frequency and/or bandwidth and/or a notch frequency. The variable digital filter may be embodied by a plurality of delay taps, the number of which is selected to provide the variable filtering.

Still continuing with the description of FIG. 1, a corner frequency adjuster **140** is provided that is responsive to the heart rate metric extractor **130** and is configured to determine the corner frequency **142** that is applied to the variable high pass filter **120** based on the heart rate metric **132** that was extracted. Accordingly, variable filter adjustment by physiological metric feedback is provided.

Many embodiments of corner frequency adjusters **140** will be described in detail below. In general, the corner frequency adjuster **140** may be configured to determine a corner frequency that is applied to the variable high pass filter **120** or to select from among a plurality of variable high pass filters, for example by selecting a number of delay taps in a variable digital high pass filter. For example, as will be described in more detail below, the corner frequency adjuster **140** may include a mapping system that is configured to map the heart rate metric **132** that is extracted from the physiological waveform **112** that is filtered by the variable high pass filter **120**, into a number of delay taps that is selected to filter the physiological waveform **112** by the variable high pass filter **120**.

FIG. 2 is a functional block diagram of physiological signal processing systems and methods according to various other embodiments described herein. These physiological signal processing systems and methods **200** are configured to extract cardiovascular and pulmonary physiological signal components that are included in a physiological wave-

form **112** as provided by the physiological sensor **110**. In some embodiments, the cardiovascular and pulmonary physiological signal components rise and fall in frequency roughly in tandem, and the cardiovascular signal component includes a highest frequency that is higher than the lowest frequency of the pulmonary signal component. It will be understood that more than two physiological signal components may be processed in other embodiments, but only two components are illustrated in FIG. 2 for ease of illustration.

In embodiments of FIG. 2, a variable high pass filter **220a** and a variable low pass filter **220b** may be provided. The variable high pass filter **220a** is responsive to the physiological waveform **112** and is configured to high pass filter the physiological waveform in response to a first corner frequency **242a** that is applied thereto. The variable low pass filter **220b** is responsive to the physiological waveform **112** and is configured to low pass filter the physiological waveform in response to a second corner frequency **242b** that is applied thereto. The first and second corner frequencies **242a**, **242b** may be identical in some embodiments, and may be different in other embodiments. Moreover, when the first physiological signal component is a cardiovascular signal component and the second physiological signal component is a pulmonary signal component, the first corner frequency **242a** is a high pass corner frequency and the second corner frequency **242b** is a low pass corner frequency.

Continuing with the description of FIG. 2, a heart rate metric extractor **230a** and a respiration rate metric extractor **230b** may be provided. The heart rate metric **232a** may be processed and analyzed by a heart rate metric assessor **250a**, and the respiration rate **232b** may be processed and analyzed by a respiration rate metric assessor **250b**. Many techniques for operating heart rate and respiration rate metric extractors and assessors are known, and need not be described further herein.

Still referring to FIG. 2, a corner frequency adjuster **240** is provided. The corner frequency adjuster **240** is responsive to the heart rate metric extractor **230a** to determine the first and second corner frequencies **242a** and **242b** that are applied to the variable high pass and low pass filters **220a** and **220b**, respectively. Various embodiments of the corner frequency adjuster **240** may be provided. Various detailed examples will be provided below.

FIG. 3 is a functional block diagram of an embodiment **300** of FIG. 1 that may be used to extract a heart rate metric **132** from the physiological waveform **112'** that is produced by a PPG sensor **110'**, wherein the physiological waveform **112'** includes both heart rate (HR) and respiration rate (RR) components. A variable high pass filter **120'** is embodied in FIG. 3 by a plurality of high pass filters **320**, each of which includes a different corner frequency. The heart rate metric extractor **130** is configured to extract a heart rate metric **132** using any known technique. The corner frequency adjuster **140** of FIG. 1 is embodied by a corner frequency adjuster **140'**, represented as a switch that is configured to select one of the plurality of high pass filters **320** that corresponds to the corner frequency that is determined. For example, in some embodiments, the corner frequency adjuster **140'** uses a mapping function to select one of the plurality of high pass filters **320** that has a corner frequency that is within a margin of the heart rate metric **132'**. In some embodiments, the margin may correspond to a margin of between about 18 and about 30 beats per minute below the heart rate metric **132'**. By selecting the appropriate high pass filter **320**, the corner frequency adjuster **140'** can reduce or prevent the respiration rate component from interfering with the extraction of the heart rate component.

It will be understood that the margin may be selected as a function of the heart rate metric 132. For example, a table lookup may be used to map a heart rate metric 132 that is extracted into a desired high pass filter corner frequency, and then the filter 320 may be selected that has a corner frequency that is closest to the mapped corner frequency. It will also be understood that hysteresis may be used to reduce or prevent switching of the high pass filters 320 too rapidly, because the rapid switching may adversely affect the extraction of the heart rate metric by the heart rate metric extractor 130.

In other embodiments of FIG. 3, it may also be desirable to extract a respiration rate metric from the waveform 112', so that low pass filters may be used in addition to high pass filters 320. The corner frequency adjuster 140' may be configured to adjust low pass filter corner frequency by applying a given margin below the heart rate metric.

FIG. 4 is a more detailed functional block diagram of embodiments 400 of FIG. 2, and may be used to extract a heart rate metric 232a and a respiration rate metric 232b from a PPG sensor 110' that provides a PPG sensor waveform 112' that includes both heart rate and respiration rate components. A variable high pass filter 220a and a variable low pass filter 220b is provided. Each of these filters may be embodied by a single filter with an adjustable corner frequency or by multiple filters having different corner frequencies, one of which may be selected. Heart rate extractor 230a and respiration rate extractor 230b are responsive to the variable high pass filter 220a and the variable low pass filter 220b, respectively, so as to obtain a heart rate metric 232a and a respiration rate metric. 232b. The corner frequency adjuster previously described may be embodied by a mapping function 340. As shown in embodiments of FIG. 4, the mapping function 340 is responsive to the heart rate metric 232a and is responsible for determining both the high pass filter corner frequency 242a and the low pass filter corner frequency 242b. In some embodiments, the same corner frequency may be used for both the variable high pass filter 220a and the variable low pass filter 220b. In other embodiments, the mapping function 340 may determine different corner frequencies 242a and 242b.

In embodiments of FIG. 4, only the heart rate metric 232a is used by the mapping function to determine the corner frequency for both the variable high pass filter 220a and the variable low pass filter 220b. It has been found, according to various embodiments described herein, that the heart rate metric 232a may provide a more accurate basis for determining both corner frequencies, because the heart rate metric may be subject to less conscious control by the user compared to the respiration rate metric. A specific mapping function will be described below.

As was described above, the variable high pass filter 220a and/or the variable low pass filter 220b of FIG. 4 may comprise a variable digital high pass filter and/or a variable digital low pass filter. FIG. 5 illustrates an embodiment of a variable digital high pass filter, and FIG. 6 illustrates an embodiment of a variable digital low pass filter.

Referring to FIG. 5, these embodiments of a variable high pass filter 220a' include a plurality of high pass delay taps 510 that are generated by a plurality of digital delay elements 520. The digital delay elements 520 are responsive to an input signal, which may be the physiological waveform 112' of a PPG sensor, and the variable high pass filter 220a' provides an output signal, which may be provided to a metric extractor, such as an HR extractor 230a of FIG. 4. A "width" parameter determines the number of delay taps that are selected by a mean block 530 and a summing node 540,

to determine the output signal. As shown in FIG. 6, the variable low pass filter 220b' can include a similar architecture. However, a summer 540 may not be needed in the variable low pass filter 220b' because the "DELAY" tap already feeds the mean block 530 with the same sign as the other taps 510.

Accordingly, FIGS. 5 and 6 illustrate various embodiments wherein the variable high pass filter (FIG. 5) and/or the variable low pass filter (FIG. 6) comprises a variable digital high pass filter 220a' and/or a variable digital low pass filter 220b' having a plurality of high pass and/or low pass delay taps 510, respectively, wherein the corner frequency is determined by a number of high pass and/or low pass delay taps 510 that are selected to filter the physiological waveform.

A specific embodiment of a mapping function 340 will now be described. In these embodiments, the mapping function 340 is configured to determine a corner frequency 242a of the variable high pass filter 220a' and the corner frequency 242b of the variable low pass filter 220b' by applying a margin to the heart rate metric 232a, and is further configured to determine the number of delay taps 510 from the corner frequency that was determined.

A mathematical description of this mapping function 340 may be provided by Equations (1) and (2):

$$\text{CornerFreq}=\max(\text{MINIMUM\_HR\_BPM},\text{HeartRate}-\text{MARGIN\_BPM}) \quad (1)$$

$$\text{Width}=\text{round}(\text{DELAY}*\text{MINIMUM\_HR\_BPM}/\text{CornerFreq}) \quad (2)$$

In Equations (1) and (2), variables in CAPITAL LETTERS are predetermined constants, while variables in CamelCase may change every frame. In this mapping function, CornerFreq is the corner frequency 242a and 242b. MINIMUM\_HR\_BPM is the minimum heart rate to be measured in beats per minute. HeartRate is the heart rate metric 232a that is measured. MARGIN\_BPM is a desired margin between the reported heart rate and the corner frequency of the variable filter, which may be empirically determined. The margin allows for some error in the reported heart rate without causing significant attenuation by the variable high pass filter. Accordingly, in Equation (1) the corner frequency is determined by the maximum of either the minimum heart rate or the measured heart rate minus the margin that is set. Moreover, in Equation (2), Width is the parameter in FIGS. 5 and 6 that determines the number of delay taps 510. Specifically, in FIGS. 5 and 6, two times the width determines the number of delay taps that are input into the mean block 530. As shown in Equation (2), the width may be determined by rounding up or down the value of the delay of each of the delay elements 520 multiplied by the minimum heart rate divided by the corner frequency that was determined in Equation (1).

Accordingly, Equations (1) and (2) illustrate an embodiment wherein the mapping function 340 is configured to determine a corner frequency of the variable low pass filter 220b and the variable high pass filter 220a by determining a maximum of a minimum heart rate, and the heart rate metric 232a minus the margin, and is further configured to determine the number of delay taps 510 by rounding a product of the delay 520 of the delay taps 510 and the minimum heart rate divided by the corner frequency 242a/242b that was determined. It will be understood, however, that many other mapping functions may be provided according to other embodiments described herein.

Embodiments that were described above in connection with FIGS. 1-4 use a heart rate metric that was extracted to

provide corner frequency adjustment of a variable high pass filter for a heart rate metric extractor, and may also use the heart rate metric that was extracted to adjust a corner frequency of a variable low pass filter of a respiration rate metric extractor. Heretofore, it does not appear that feedback of an extracted heart rate was used to control a high pass filter feeding a heart rate metric extractor. Specifically, because of the possibility for the extracted heart rate to be in error, the variable high pass filter may blind the heart rate metric extractor from the heart rate frequency in the physiological waveform. Stated differently, the heart rate metric extractor could lock on, i.e., get stuck at, a high rate, and remain unresponsive to the actual heart rate in the physiological waveform. Specifically, if the heart rate metric extractor locks on a high rate, the variable high pass filter may filter out the actual (lower) heart rate frequency in the physiological waveform. Accordingly, the heart rate metric extractor may diverge or run away from the actual heart rate. Thus, heretofore, feedback of the extracted heart rate to control the high pass filter feeding the heart rate metric extractor does not appear to have been used. In sharp contrast, various embodiments described herein can reduce or prevent locking on an erroneous heart rate metric. Thus, various embodiments described herein can use feedback of the heart rate metric that was extracted to control the high pass filter feeding the heart rate metric extractor, as was illustrated in FIGS. 1-4. The heart rate metric that was extracted may also be used to feed the low pass filter for the respiration rate metric extractor, as was shown in FIGS. 2 and 4.

FIG. 7 is a flowchart of operations that may be performed by a corner frequency adjuster 700, such as the corner frequency adjuster 140 of FIG. 1, the corner frequency adjuster 240 of FIG. 2, the corner frequency adjuster 140' of FIG. 3, or the mapping function 340 of FIG. 4, to reduce or prevent an erroneous extracted heart rate from blinding the heart rate metric extractor to the heart rate frequency in the physiological waveform. Referring now to FIG. 7, the corner frequency adjuster 700 may be configured to initially set at least one predetermined corner frequency corresponding to a predetermined heart rate prior to determining the at least one corner frequency that is applied to the variable high pass filter, and in some embodiments to the variable low pass filter, from the heart rate metric, as illustrated at Block 710. Thus, at startup, the extracted heart rate 132 may be initialized to a predetermined, relatively low heart rate, such as a resting heart rate of, for example, 72 beats per minute. By initially setting the extracted heart 132 at a low value, subsequent blinding of the metric extractor by the high pass filter that is set for a high heart rate, may be reduced or prevented. Thus, the corner frequency adjuster 700 is configured to reduce or prevent locking on an erroneous heart rate in the physiological waveform.

Then, at Block 720, once a heart rate metric is locked, the heart rate metric that was extracted may be used to determine the corner frequency at Block 730. Thus, Blocks 710-730 illustrate the use of a "hunting mode" at startup, where the corner frequency of the high pass filter, and in some embodiments of the low pass filter, is set at a predetermined frequency (Block 710) until the heart rate metric extractor locks on the heart rate PPG signal at Block 720. Then, the heart rate metric that was extracted may be used at Block 730.

One way to determine that the heart rate metric extractor has locked on the heart rate in the physiological waveform at Block 720 is to determine when the physiological waveform spectral peak is within a window around the extracted

heart rate. The window may be a predetermined window that remains constant, or may be a variable window. If the spectral peak is within the window around the extracted heart rate, the heart rate may be deemed to be believed, whereas if it is outside the window, it could be noise, and therefore be erroneous.

Finally, at Block 740, a determination may be made that the physiological waveform signal is lost, for example, because the physiological sensor 110 goes off the body. A determination that the physiological sensor goes off the body may be obtained using a proximity sensor and/or other techniques. If the signal is lost at Block 740, operations may return to Block 710 to reset (i.e., reapply) the predetermined heart rate and then return into hunting mode at Blocks 720 and 730. On the other hand, as long as the signal is not lost at Block 740, the heart rate metric that was extracted may continue to be used to determine the at least one corner frequency at Block 730. Thus, the corner frequency adjuster is configured to reduce or prevent locking on an erroneous heart rate metric.

Other techniques may also be used to reduce or prevent the high pass filter from blinding the metric extractor to the heart rate frequency in the physiological waveform. For example, the high pass filters 120, 220a, 120' or 220a' may all use a gradual filter transition band. Stated differently, brick wall high pass filters are not used in these embodiments. Thus, the gradual transition high pass filter may have a greater ability to include the heart rate frequency in the high pass filtered signal. Another technique may use a margin between the extracted heart rate and the corner frequency of the high pass filter. For example, 18 beats per minute margin may be used, as was already described. The above described techniques may be used individually, or in various combinations and subcombinations, to reduce or prevent the high pass filter from blinding the metric extractor from the heart rate frequency in the physiological waveform, and thereby reduce or prevent locking on an erroneous heart rate metric.

FIG. 8 illustrates how the corner frequency of a variable high pass filter, such as the variable high pass filter 220a' of FIG. 5, may be varied using the mapping function 340 described by Equations (1) and (2) above, according to various embodiments described herein. FIG. 8 assumes a value of DELAY of 15 samples and plots the frequency response of the variable high pass filter 220a' with various width values from 10 to 15 at a sample rate of 25 Hz. As shown, the corner frequency of the variable high pass filter 220a', which may be measured at, for example, the -2 dB, -3 dB or -6 dB magnitude, can be varied by varying the width parameter. The high pass filter of FIG. 8 may be used to extract the heart rate metric 232a.

FIG. 9 illustrates analogous operations for a variable digital low pass filter 220b', such as illustrated in FIG. 6. Again, in FIG. 9, a DELAY value of 15 samples is plotted as a function of widths from 10 to 15. The cutoff frequency may be measured, for example, by the -12 dB, -10 dB or -8 dB points in the magnitude. Accordingly, variable cutoff frequency low pass filters may be used to extract the respiration rate metric 232b.

FIGS. 10-15 illustrate other measured results. Specifically, FIG. 10 graphically illustrates a typical noise-reduced PPG spectrum.

FIG. 11 illustrates a signal-to-noise-and-distortion measurement for the same signal in FIG. 10.

FIG. 12 illustrates raw samples of the physiological waveform 112' that may be obtained by a PPG sensor 110'.

FIG. 13 illustrates heart rate HR (232a of FIG. 4) and step rate SR (in steps per minute) that may be extracted by a system and/or method of FIG. 4 over time.

FIG. 14 illustrates a respiration rate metric that may be provided by a respiration rate extractor 230b of FIG. 4 as a function of time. Finally, FIG. 15 illustrates a peak normalized spectrum for the respiration rate.

Various embodiments have been described herein primarily with respect to physiological signal processing systems. However, FIGS. 1-7 also describe analogous physical signal processing methods according to various embodiments described herein. For example, various analogous method embodiments described herein can select among multiple filters for extracting a physiological signal component, where the selection is controlled by an extracted physiological metric. The physiological metric can be the same or different than the physiological component. For example, an extracted heart rate metric can control the filtering of both heart rate and respiration rate. Variable filter adjustment by physiological waveform metric feedback may thereby be provided.

Various embodiments have been described herein with reference to block diagrams and a flowchart of methods, apparatus (systems and/or devices) and/or computer program products. It is understood that a block of the block diagrams and/or flowchart, and combinations of blocks in the block diagrams and/or flowchart, can be implemented by computer program instructions that are performed by one or more computer circuits. These computer program instructions may be provided to a processor circuit of a general purpose computer circuit, special purpose computer circuit, and/or other programmable data processing circuit to produce a machine, such that the instructions, which execute via the processor of the computer and/or other programmable data processing apparatus, transform and control transistors, values stored in memory locations, and other hardware components within such circuitry to implement the functions/acts specified in the block diagrams and/or flowchart, and thereby create means (functionality), structure and/or methods for implementing the functions/acts specified in the block diagrams and/or flowchart.

These computer program instructions may also be stored in a computer-readable medium that can direct a computer or other programmable data processing apparatus to function in a particular manner, such that the instructions stored in the computer-readable medium produce an article of manufacture including instructions which implement the functions/acts specified in the block diagrams and/or flowchart block or blocks.

A tangible, non-transitory computer-readable medium may include an electronic, magnetic, optical, electromagnetic, or semiconductor data storage system, apparatus, or device. More specific examples of the computer-readable medium would include the following: a portable computer diskette, a random access memory (RAM) circuit, a read-only memory (ROM) circuit, an erasable programmable read-only memory (EPROM or Flash memory) circuit, a portable compact disc read-only memory (CD-ROM), and a portable digital video disc read-only memory (DVD/Blu-ray™).

The computer program instructions may also be loaded onto a computer and/or other programmable data processing apparatus to cause a series of operational steps to be performed on the computer and/or other programmable apparatus to produce a computer-implemented process or method such that the instructions which execute on the computer or

other programmable apparatus provide steps for implementing the functions/acts specified in the block diagrams and/or flowchart.

Accordingly, the invention may be embodied in hardware and/or in software (including firmware, resident software, micro-code, etc.) that runs on a processor such as a digital signal processor, which may collectively be referred to as "circuitry," "a module" or variants thereof.

It should also be noted that in some alternate implementations, the functions/acts noted in the blocks may occur out of the order noted in the blocks. For example, two blocks shown in succession may in fact be executed substantially concurrently or the blocks may sometimes be executed in the reverse order, depending upon the functionality/acts involved. Moreover, the functionality of a given block of the block diagrams and/or flowchart may be separated into multiple blocks and/or the functionality of two or more blocks of the block diagrams and/or flowchart may be at least partially integrated. Finally, other blocks may be added/inserted between the blocks that are illustrated.

Many different embodiments have been disclosed herein, in connection with the above description and the drawings. It will be understood that it would be unduly repetitious and obfuscating to literally describe and illustrate every combination and subcombination of these embodiments. Accordingly, the present specification, including the drawings, shall be construed to constitute a complete written description of all combinations and subcombinations of the embodiments described herein, and of the manner and process of making and using them, and shall support claims to any such combination or subcombination.

In the drawings and specification, there have been disclosed embodiments of the invention and, although specific terms are employed, they are used in a generic and descriptive sense only and not for purposes of limitation, the scope of the invention being set forth in the following claims.

What is claimed is:

1. A physiological signal processing system comprising:
  - a physiological sensor that is configured to generate a physiological waveform that includes cardiovascular and pulmonary signal components therein;
  - a variable high pass filter and a variable low pass filter that are responsive to the physiological waveform and that are configured to high pass and low pass filter, respectively, the physiological waveform in response to at least one corner frequency that is applied thereto;
  - a heart rate metric extractor that is coupled to an output of the variable high pass filter and is responsive to the variable high pass filter and that is configured to extract a heart rate metric from the cardiovascular signal component of the physiological waveform that is output from the variable high pass filter responsive to high pass filtering the physiological waveform;
  - a respiration rate metric extractor that is coupled to an output of and is responsive to the variable low pass filter and that is configured to extract a respiration rate metric from the pulmonary signal component of the physiological waveform that is output from the variable low pass filter responsive to low pass filtering the physiological waveform; and
  - a corner frequency adjuster that is responsive to the heart rate metric extractor and that is configured to determine the at least one corner frequency that is applied to the variable high pass filter and the variable low pass filter from the heart rate metric that was extracted based on the output from the variable high pass filter.

2. A physiological signal processing system for a physiological waveform that includes a cardiovascular signal component therein, the physiological signal processing system comprising:

a variable high pass filter that is responsive to the physiological waveform and that is configured to high pass filter the physiological waveform in response to a corner frequency that is applied thereto;

a heart rate metric extractor that is coupled to an output of the variable high pass filter and is responsive to the variable high pass filter and that is configured to extract a heart rate metric from the cardiovascular signal component of the physiological waveform that is output from the variable high pass filter responsive to high pass filtering the physiological waveform; and

a corner frequency adjustor that is responsive to the heart rate metric extractor and that is configured to determine the corner frequency that is applied to the variable high pass filter from the heart rate metric that was extracted based on the output from the variable high pass filter.

3. A physiological signal processing system according to claim 2 wherein the physiological waveform comprises an electrical physiological waveform including an electroencephalogram (EEG), an electrocardiogram (ECG) and/or a radio frequency (RF) waveform, an electro-optical physiological waveform including a photoplethysmograph (PPG) waveform, an electro-photoacoustic waveform including a photoacoustic waveform, an electro-mechanical physiological waveform including an auscultation waveform, a piezo sensor waveform and/or an accelerometer waveform, and/or an electro-nuclear physiological waveform.

4. A physiological signal processing system according to claim 2 wherein the variable high pass filter comprises a single high pass filter having an adjustable corner frequency.

5. A physiological signal processing system according to claim 2 wherein the variable high pass filter comprises a plurality of high pass filters, a respective one of which includes a different value of the corner frequency, and wherein the corner frequency adjustor is configured to select one of the plurality of high pass filters that corresponds to the corner frequency that is determined.

6. A physiological signal processing system according to claim 2 wherein the variable high pass filter comprises a variable digital high pass filter having a plurality of delay taps and wherein the corner frequency corresponds to a number of the plurality of delay taps that are selected to filter the physiological waveform.

7. A physiological signal processing system according to claim 6 wherein the corner frequency adjustor comprises a mapping system that is configured to map the heart rate metric that is extracted from the physiological waveform that is filtered into the number of the delay taps that are selected to high pass filter the physiological waveform.

8. A physiological signal processing system according to claim 2 wherein the corner frequency adjustor is configured to reduce locking on an erroneous heart rate metric.

9. A physiological signal processing system according to claim 2 wherein the corner frequency adjustor is configured to initially set a predetermined corner frequency corresponding to a predetermined heart rate prior to determining the corner frequency that is applied to the variable high pass filter from the heart rate metric.

10. A physiological signal processing system according to claim 9 wherein the predetermined heart rate is a resting heart rate.

11. A physiological signal processing system according to claim 9 wherein the corner frequency adjustor is configured

to initially set the predetermined corner frequency corresponding to the predetermined heart rate until the heart rate metric extractor locks on a heart rate in the physiological waveform.

12. A physiological signal processing system according to claim 9 wherein the corner frequency adjustor is configured to reset the predetermined corner frequency corresponding to the predetermined heart rate in response to determining that the physiological sensor is no longer responsive to a source of the physiological waveform.

13. A physiological signal processing system according to claim 2 wherein the corner frequency adjustor is configured to set a predetermined corner frequency corresponding to a predetermined heart rate in response to determining that the physiological sensor is not responsive to a source of the physiological waveform.

14. A physiological signal processing system according to claim 2 wherein the corner frequency adjustor is configured to determine the corner frequency that is applied to the variable high pass filter from the heart rate metric by applying a margin to the heart rate metric.

15. A physiological signal processing system according to claim 2 wherein the variable high pass filter includes a gradual filter transition band.

16. A physiological signal processing system according to claim 2 further comprising:

a physiological metric assessor that is responsive to the heart rate metric extractor and that is configured to process the heart rate metric to generate at least one physiological assessment.

17. A physiological signal processing system according to claim 2, wherein the corner frequency adjustor is configured to determine the at least one corner frequency that is applied to the variable high pass filter based on the heart rate metric independent of a respiration rate metric.

18. A physiological signal processing method for a physiological waveform that includes a cardiovascular signal component therein, the physiological signal processing method comprising:

high pass filtering the physiological waveform in response to an adjustable high pass filter corner frequency; extracting a heart rate metric from the cardiovascular signal component of the physiological waveform that is output from the high pass filtering; and

determining the adjustable high pass filter corner frequency that is applied to the high pass filtering, from the heart rate metric that was extracted based on the output from the high pass filtering.

19. A physiological signal processing method according to claim 18 further comprising:

initially setting a predetermined corner frequency corresponding to a predetermined heart rate prior to the determining the at least one corner frequency that is applied to the variable high pass filtering from the heart rate metric.

20. A physiological signal processing method according to claim 19 wherein the initially setting the predetermined corner frequency comprises initially setting the predetermined corner frequency corresponding to the predetermined heart rate until the extracting locks on a heart rate in the physiological waveform.

21. A physiological signal processing method according to claim 19 further comprising:

resetting the predetermined corner frequency corresponding to the predetermined heart rate in response to determining that the physiological waveform is no longer being obtained.

专利名称(译)	用于通过心率度量反馈调整可变滤波器的系统和方法		
公开(公告)号	<a href="#">US9801552</a>	公开(公告)日	2017-10-31
申请号	US14/124465	申请日	2012-07-25
[标]申请(专利权)人(译)	ROMESBURG ERIC DOUGLAS		
申请(专利权)人(译)	ROMESBURG , ERIC DOUGLAS		
当前申请(专利权)人(译)	VALENCELL INC.		
[标]发明人	ROMESBURG ERIC DOUGLAS		
发明人	ROMESBURG, ERIC DOUGLAS		
IPC分类号	A61B5/00 A61B5/0402 A61B5/04 A61B5/0476 A61B5/0245 A61B5/024 A61B5/0205 A61B5/08		
CPC分类号	A61B5/0095 A61B5/0059 A61B5/0245 A61B5/02416 A61B5/0402 A61B5/0476 A61B5/725 A61B5/7225 A61B5/7278 A61B5/04017 A61B5/0816 A61B5/0205		
优先权	61/514099 2011-08-02 US		
其他公开文献	US20140114147A1		
外部链接	<a href="#">Espacenet</a> <a href="#">USPTO</a>		

摘要(译)

用于包括心血管信号分量的生理波形的生理信号处理系统提供响应于生理波形的可变高通滤波器，并且被配置为响应于所施加的转角频率对生理波形进行高通滤波。心率度量提取器响应于可变高通滤波器并且被配置为从高通滤波的生理波形中提取心率度量。转角频率调节器响应于心率度量提取器，并且被配置为基于所提取的心率度量来确定应用于可变高通滤波器的转角频率。也可以提供类似的方法。

