



US007890154B2

(12) **United States Patent**  
**Baker, Jr.**

(10) **Patent No.:** **US 7,890,154 B2**  
(45) **Date of Patent:** **\*Feb. 15, 2011**

- (54) **SELECTION OF ENSEMBLE AVERAGING WEIGHTS FOR A PULSE OXIMETER BASED ON SIGNAL QUALITY METRICS** 4,095,117 A 6/1978 Nagy
- 4,266,554 A 5/1981 Hamaguri
- 4,407,290 A 10/1983 Wilber
- 4,537,200 A 8/1985 Widrow
- (75) Inventor: **Clark R. Baker, Jr.**, Newman, CA (US) 4,549,551 A 10/1985 Dyck et al.
- (73) Assignee: **Nellcor Puritan Bennett LLC**, Boulder, CO (US) 4,603,700 A 8/1986 Nichols et al.
- 4,621,643 A 11/1986 New, Jr. et al.
- 4,649,505 A 3/1987 Zinser, Jr. et al.
- (\*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days. 4,700,708 A 10/1987 New, Jr. et al.

This patent is subject to a terminal disclaimer.

(Continued)

FOREIGN PATENT DOCUMENTS

- (21) Appl. No.: **12/315,449**
- (22) Filed: **Dec. 3, 2008**
- (65) **Prior Publication Data**
- US 2009/0082651 A1 Mar. 26, 2009

(Continued)

OTHER PUBLICATIONS

- (63) **Related U.S. Application Data**
- Continuation of application No. 11/701,173, filed on Feb. 1, 2007, now Pat. No. 7,474,907, which is a continuation of application No. 10/796,559, filed on Mar. 8, 2004, now Pat. No. 7,194,293.

Aoyagi, T., et al.; "Analysis of Motion Artifacts in Pulse Oximetry," *Japanese Society ME*, vol. 42, p. 20 (1993) (Article in Japanese—contains English summary of article).

(Continued)

Primary Examiner—Eric F Winakur

- (51) **Int. Cl.**  
*A61B 5/1455* (2006.01)
  - (52) **U.S. Cl.** ..... 600/323; 600/336
  - (58) **Field of Classification Search** ..... 600/310,  
600/322, 323, 324, 336
- See application file for complete search history.


(57) **ABSTRACT**

A method and a system for ensemble averaging signals in a pulse oximeter, including receiving first and second electromagnetic radiation signals from a blood perfused tissue portion corresponding to two different wavelengths of light, obtaining an assessment of the signal quality of the electromagnetic signals, selecting weights for an ensemble averager using the assessment of signal quality, and ensemble averaging the electromagnetic signals using the ensemble averager.

(56) **References Cited**  
U.S. PATENT DOCUMENTS

- 3,638,640 A 2/1972 Shaw
- 3,647,299 A 3/1972 Lavallee
- 3,704,706 A 12/1972 Herczfeld et al.
- 4,063,551 A 12/1977 Sweeney
- 4,086,915 A 5/1978 Kofsky et al.

20 Claims, 2 Drawing Sheets



U.S. PATENT DOCUMENTS					
			5,413,099 A	5/1995	Schmidt et al.
			5,431,170 A	7/1995	Mathews
			5,458,128 A	10/1995	Polanyi et al.
4,705,049 A	11/1987	John	5,467,778 A	11/1995	Catt et al.
4,714,341 A	12/1987	Hamaguri et al.	5,469,845 A	11/1995	DeLonzor et al.
4,723,294 A	2/1988	Taguchi	RE35,122 E	12/1995	Corenman et al.
4,763,282 A	8/1988	Rosenberg	5,479,922 A	1/1996	Reichl
4,770,179 A	9/1988	New, Jr. et al.	5,482,036 A	1/1996	Diab et al.
4,773,422 A	9/1988	Isaacson et al.	5,483,646 A	1/1996	Uchikoga
4,799,493 A	1/1989	DuFault	5,485,847 A	1/1996	Baker, Jr.
4,800,495 A	1/1989	Smith	5,490,505 A	2/1996	Diab et al.
4,802,486 A	2/1989	Goodman et al.	5,494,032 A	2/1996	Robinson et al.
4,805,623 A	2/1989	Jöbsis	5,503,148 A	4/1996	Pologe et al.
4,807,631 A	2/1989	Hersh et al.	5,511,042 A	4/1996	O'Brien, Jr.
4,817,013 A	3/1989	Corenman et al.	5,524,617 A	6/1996	Mannheimer
4,819,752 A	4/1989	Zelin	5,524,631 A	6/1996	Zahorian et al.
4,824,242 A	4/1989	Frick et al.	5,553,614 A	9/1996	Chance
4,848,901 A	7/1989	Hood, Jr.	5,553,615 A	9/1996	Carim et al.
4,860,759 A	8/1989	Kahn et al.	5,564,417 A	10/1996	Chance
4,863,265 A	9/1989	Flower et al.	5,575,284 A	11/1996	Athan et al.
4,867,571 A	9/1989	Frick et al.	5,575,285 A	11/1996	Takanashi et al.
4,869,253 A	9/1989	Craig, Jr. et al.	5,588,439 A	12/1996	Hollub
4,869,254 A	9/1989	Stone et al.	5,605,151 A	2/1997	Lynn
4,883,353 A	11/1989	Hausman et al.	5,611,337 A	3/1997	Bukta
4,892,101 A	1/1990	Cheung et al.	5,630,413 A	5/1997	Thomas et al.
4,907,594 A	3/1990	Muz	5,632,272 A	5/1997	Diab et al.
4,911,167 A	3/1990	Corenman et al.	5,645,059 A	7/1997	Fein et al.
4,913,150 A	4/1990	Cheung et al.	5,645,060 A	7/1997	Yorkey
4,927,264 A	5/1990	Shiga et al.	5,676,141 A	10/1997	Hollub
4,928,692 A	5/1990	Goodman et al.	5,680,857 A	10/1997	Pelikan et al.
4,934,372 A	6/1990	Corenman et al.	5,685,299 A	11/1997	Diab et al.
4,936,679 A	6/1990	Mersch	5,692,503 A	12/1997	Keunstner
4,938,218 A	7/1990	Goodman et al.	5,730,124 A	3/1998	Yamauchi
4,948,248 A	8/1990	Lehman	5,743,263 A	4/1998	Baker, Jr.
4,949,710 A	8/1990	Dorsett et al.	5,746,206 A	5/1998	Mannheimer
4,955,379 A	9/1990	Hall	5,758,644 A	6/1998	Diab et al.
4,956,867 A	9/1990	Zurek et al.	5,769,785 A	6/1998	Diab et al.
4,958,638 A	9/1990	Sharpe et al.	5,779,631 A	7/1998	Chance
4,960,126 A	10/1990	Conlon et al.	5,782,757 A	7/1998	Diab et al.
4,971,062 A	11/1990	Hasebe et al.	5,786,592 A	7/1998	Hök
4,972,331 A	11/1990	Chance	5,820,550 A	10/1998	Polson et al.
4,972,842 A	11/1990	Korten et al.	5,830,136 A	11/1998	DeLonzor et al.
4,974,591 A	12/1990	Awazu et al.	5,830,139 A	11/1998	Abreu
5,025,791 A	6/1991	Niwa	5,831,598 A	11/1998	Kauffert et al.
5,028,787 A	7/1991	Rosenthal et al.	5,842,981 A	12/1998	Larsen et al.
5,054,495 A	10/1991	Uemura et al.	5,853,364 A	12/1998	Baker et al.
5,057,695 A	10/1991	Hirao et al.	5,871,442 A	2/1999	Madarasz et al.
5,058,588 A	10/1991	Kaestle	5,873,821 A	2/1999	Chance et al.
5,065,749 A	11/1991	Hasebe et al.	5,920,263 A	7/1999	Huttenhoff et al.
5,078,136 A	1/1992	Stone et al.	5,934,277 A	8/1999	Mortz
5,084,327 A	1/1992	Stengel	5,995,855 A	11/1999	Kiani et al.
5,119,815 A	6/1992	Chance	5,995,856 A	11/1999	Mannheimer et al.
5,122,974 A	6/1992	Chance	5,995,859 A	11/1999	Takahashi
5,167,230 A	12/1992	Chance	6,002,952 A	12/1999	Diab et al.
5,190,038 A	3/1993	Polson et al.	6,011,986 A	1/2000	Diab et al.
5,246,002 A	9/1993	Prosser	6,064,898 A	5/2000	Aldrich
5,246,003 A	9/1993	DeLonzor	6,081,735 A	6/2000	Diab et al.
5,247,931 A	9/1993	Norwood	6,081,742 A	6/2000	Amano et al.
5,263,244 A	11/1993	Centa et al.	6,083,157 A	7/2000	Noller
5,267,562 A	12/1993	Ukawa et al.	6,088,607 A	7/2000	Diab et al.
5,273,036 A	12/1993	Kronberg et al.	6,094,592 A	7/2000	Yorkey et al.
5,275,159 A	1/1994	Griebel	6,120,460 A	9/2000	Abreu
5,279,295 A	1/1994	Martens et al.	6,134,460 A	10/2000	Chance
5,285,782 A	2/1994	Prosser	6,150,951 A	11/2000	Olejniczak
5,297,548 A	3/1994	Pologe	6,151,518 A	11/2000	Hayashi
5,348,004 A	9/1994	Hollub	6,154,667 A	11/2000	Miura et al.
5,351,685 A	10/1994	Potratz	6,157,850 A	12/2000	Diab et al.
5,355,880 A	10/1994	Thomas et al.	6,163,715 A	12/2000	Larsen et al.
5,355,882 A	10/1994	Ukawa et al.	6,181,958 B1	1/2001	Steuer et al.
5,372,136 A	12/1994	Steuer et al.	6,181,959 B1	1/2001	Schöllermann et al.
5,385,143 A	1/1995	Aoyagi	6,230,035 B1	5/2001	Aoyagi et al.
5,390,670 A	2/1995	Centa et al.	6,236,872 B1	5/2001	Diab et al.
5,398,680 A	3/1995	Polson et al.	6,266,546 B1	7/2001	Steuer et al.
5,398,682 A	3/1995	Lynn			

6,285,895	B1	9/2001	Ristolainen et al.	7,024,235	B2	4/2006	Melker et al.
6,312,393	B1	11/2001	Abreu	7,027,849	B2	4/2006	Al-Ali
6,339,715	B1	1/2002	Bahr et al.	7,030,749	B2	4/2006	Al-Ali
6,353,750	B1	3/2002	Kimura et al.	7,035,697	B1	4/2006	Brown
6,360,114	B1	3/2002	Diab et al.	7,039,538	B2	5/2006	Baker, Jr.
6,385,471	B1	5/2002	Mortz	7,047,056	B2	5/2006	Hannula et al.
6,397,091	B2	5/2002	Diab et al.	7,127,278	B2	10/2006	Melker et al.
6,408,198	B1	6/2002	Hanna et al.	7,139,599	B2	11/2006	Terry
6,415,236	B2	7/2002	Kobayashi et al.	7,162,306	B2	1/2007	Caby et al.
6,419,671	B1	7/2002	Lemberg	7,209,774	B2	4/2007	Baker, Jr.
6,430,525	B1	8/2002	Weber et al.	7,209,775	B2	4/2007	Bae et al.
6,438,399	B1	8/2002	Kurth	7,236,811	B2	6/2007	Schmitt
6,461,305	B1	10/2002	Schnall	7,263,395	B2	8/2007	Chan et al.
6,466,809	B1	10/2002	Riley	7,272,426	B2	9/2007	Schmid
6,487,439	B1	11/2002	Skladnev et al.	7,373,193	B2	5/2008	Al-Ali et al.
6,501,974	B2	12/2002	Huiku	2001/0005773	A1	6/2001	Larsen et al.
6,501,975	B2	12/2002	Diab et al.	2001/0020122	A1	9/2001	Steuer et al.
6,505,060	B1	1/2003	Norris	2001/0039376	A1	11/2001	Steuer et al.
6,526,301	B2	2/2003	Larsen et al.	2001/0044700	A1	11/2001	Kobayashi et al.
6,544,193	B2	4/2003	Abreu	2002/0026106	A1	2/2002	Khalil et al.
6,546,267	B1	4/2003	Sugiura et al.	2002/0035318	A1	3/2002	Mannheimer et al.
6,549,795	B1	4/2003	Chance	2002/0038079	A1	3/2002	Steuer et al.
6,580,086	B1	6/2003	Schulz et al.	2002/0042558	A1	4/2002	Mendelson
6,591,122	B2	7/2003	Schmitt	2002/0049389	A1	4/2002	Abreu
6,594,513	B1	7/2003	Jobsis et al.	2002/0062071	A1	5/2002	Diab et al.
6,606,509	B2	8/2003	Schmitt	2002/0111748	A1	8/2002	Kobayashi et al.
6,606,511	B1	8/2003	Ali et al.	2002/0133068	A1	9/2002	Huiku
6,615,064	B1	9/2003	Aldrich	2002/0137994	A1	9/2002	Baker et al.
6,618,042	B1	9/2003	Powell	2002/0156354	A1	10/2002	Larson
6,622,095	B2	9/2003	Kobayashi et al.	2002/0161287	A1	10/2002	Schmitt
6,647,280	B2	11/2003	Bahr et al.	2002/0161290	A1	10/2002	Chance
6,650,918	B2	11/2003	Terry	2002/0165439	A1	11/2002	Schmitt
6,654,621	B2	11/2003	Palatnik et al.	2002/0198443	A1	12/2002	Ting
6,654,624	B2	11/2003	Diab et al.	2003/0009091	A1	1/2003	Edgar, Jr. et al.
6,658,276	B2	12/2003	Kianl et al.	2003/0023140	A1	1/2003	Chance
6,658,277	B2	12/2003	Wasserman	2003/0055324	A1	3/2003	Wasserman
6,662,030	B2	12/2003	Khalil et al.	2003/0060693	A1	3/2003	Monfre et al.
6,668,183	B2	12/2003	Hicks et al.	2003/0139687	A1	7/2003	Abreu
6,671,526	B1	12/2003	Aoyagi et al.	2003/0144584	A1	7/2003	Mendelson
6,671,528	B2	12/2003	Steuer et al.	2003/0220548	A1	11/2003	Schmitt
6,678,543	B2	1/2004	Diab et al.	2003/0220576	A1	11/2003	Diab
6,684,090	B2	1/2004	Ali et al.	2004/0010188	A1	1/2004	Wasserman
6,690,958	B1	2/2004	Walker et al.	2004/0039273	A1	2/2004	Terry
6,697,658	B2	2/2004	Al-Ali	2004/0054270	A1	3/2004	Pewzner et al.
6,708,048	B1	3/2004	Chance	2004/0087846	A1	5/2004	Wasserman
6,711,424	B1	3/2004	Fine et al.	2004/0107065	A1	6/2004	Al-Ali
6,711,425	B1	3/2004	Reuss	2004/0127779	A1	7/2004	Steuer et al.
6,714,245	B1	3/2004	Ono	2004/0158135	A1	8/2004	Baker et al.
6,721,584	B2	4/2004	Baker et al.	2004/0171920	A1	9/2004	Mannheimer et al.
6,731,274	B2	5/2004	Powell	2004/0171948	A1	9/2004	Terry
6,745,060	B2	6/2004	Diab et al.	2004/0176670	A1	9/2004	Takamura et al.
6,785,568	B2	8/2004	Chance	2004/0176671	A1	9/2004	Fine et al.
6,793,654	B2	9/2004	Lemberg	2004/0181134	A1	9/2004	Baker et al.
6,801,797	B2	10/2004	Mannheimer et al.	2004/0230106	A1	11/2004	Schmitt et al.
6,801,798	B2	10/2004	Geddes et al.	2005/0080323	A1	4/2005	Kato
6,801,799	B2	10/2004	Mendelson	2005/0101850	A1	5/2005	Parker
6,810,277	B2	10/2004	Edgar, Jr. et al.	2005/0113651	A1	5/2005	Wood et al.
6,829,496	B2	12/2004	Nagai et al.	2005/0113656	A1	5/2005	Chance
6,836,679	B2	12/2004	Baker, Jr. et al.	2005/0168722	A1	8/2005	Forstner et al.
6,839,582	B2	1/2005	Heckel	2005/0177034	A1	8/2005	Beaumont
6,850,053	B2	2/2005	Daalmans et al.	2005/0192488	A1	9/2005	Bryenton et al.
6,863,652	B2	3/2005	Huang et al.	2005/0197552	A1	9/2005	Baker, Jr.
6,873,865	B2	3/2005	Steuer et al.	2005/0197793	A1	9/2005	Baker, Jr.
6,889,153	B2	5/2005	Dietiker	2005/0203357	A1	9/2005	Debreczeny et al.
6,898,451	B2	5/2005	Wuori	2005/0228248	A1	10/2005	Dietiker
6,939,307	B1	9/2005	Dunlop	2005/0267346	A1	12/2005	Faber et al.
6,947,780	B2	9/2005	Scharf	2005/0283059	A1	12/2005	Iyer et al.
6,949,081	B1	9/2005	Chance	2006/0009688	A1	1/2006	Lamego et al.
6,961,598	B2	11/2005	Diab	2006/0015021	A1	1/2006	Cheng
6,983,178	B2	1/2006	Fine et al.	2006/0020181	A1	1/2006	Schmitt
6,987,994	B1	1/2006	Mortz	2006/0030763	A1	2/2006	Mannheimer et al.
6,993,371	B2	1/2006	Kiani et al.	2006/0052680	A1	3/2006	Diab
6,996,427	B2	2/2006	Ali et al.	2006/0058683	A1	3/2006	Chance

2006/0064024	A1	3/2006	Schnall
2006/0195028	A1	8/2006	Hannula et al.
2006/0195280	A1	8/2006	Baker, Jr.
2006/0224058	A1	10/2006	Mannheimer
2006/0247501	A1	11/2006	Ali
2006/0258921	A1	11/2006	Addison et al.

## FOREIGN PATENT DOCUMENTS

EP	0630203	9/1993
EP	1006863	10/2003
EP	1006864	10/2003
JP	3170866	7/1991
JP	3238813	10/1991
JP	4191642	7/1992
JP	4332536	11/1992
JP	5049624	3/1993
JP	6016774	3/1994
JP	7124138	5/1995
JP	10216115	8/1998
JP	10337282	12/1998
JP	2003194714	7/2003
JP	2003210438	7/2003
JP	2003275192	9/2003
JP	2003339678	12/2003
JP	2004008572	1/2004
JP	2004113353	4/2004
JP	2004135854	5/2004
JP	2004194908	7/2004
JP	2004202190	7/2004
JP	2004248819	9/2004
JP	2004290545	10/2004
JP	25095606	A2 4/2005
WO	WO9221281	12/1992
WO	WO9309711	5/1993
WO	WO9403102	2/1994
WO	WO9512349	5/1995
WO	WO9749330	12/1997
WO	WO98/42249	10/1998
WO	WO98/42251	10/1998
WO	WO9843071	10/1998
WO	WO9843071	A1 10/1998
WO	WO9932030	7/1999
WO	WO0021438	4/2000
WO	WO2005009221	2/2005

## OTHER PUBLICATIONS

Barreto, A.B., et al.; "Adaptive Cancellation of Motion artifact in Photoplethysmographic Blood Volume Pulse Measurements for Exercise Evaluation," *IEEE-EMBC and CMBC—Theme 4: Signal Processing*, pp. 983-984 (1995).

Vincente, L.M., et al.; "Adaptive Pre-Processing of Photoplethysmographic Blood Volume Pulse Measurements," pp. 114-117 (1996).

Plummer, John L., et al.; "Identification of Movement Artifact by the Nellcor N-200 and N-3000 Pulse Oximeters," *Journal of clinical Monitoring*, vol. 13, pp. 109-113 (1997).

Barnum, P.T., et al.; "Novel Pulse Oximetry Technology Capable of Reliable Bradycardia Monitoring in the Neonate," *Respiratory Care*, vol. 42, No. 1, p. 1072 (Nov. 1997).

Poets, C. F., et al.; "Detection of movement artifact in recorded pulse oximeter saturation," *Eur. J. Pediatr.*, vol. 156, pp. 808-811 (1997).

Masin, Donald I., et al.; "Fetal Transmission Pulse Oximetry," *Proceedings 19<sup>th</sup> International Conference IEEE/EMBS*, Oct. 30-Nov. 2, 1997; pp. 2326-2329.

Leahy, Martin J., et al.; "Sensor Validation in Biomedical Applications," IFAC Modelling and Control in Biomedical Systems, Warwick, UK; pp. 221-226 (1997).

Barreto, Armando B., et al.; "Adaptive LMS Delay Measurement in dual Blood Volume Pulse Signals for Non-Invasive Monitoring," *IEEE*, pp. 117-120 (1997).

East, Christine E., et al.; "Fetal Oxygen Saturation and Uterine Contractions During Labor," *American Journal of Perinatology*, vol. 15, No. 6, pp. 345-349 (Jun. 1998).

Edrich, Thomas, et al.; "Can the Blood Content of the Tissues be Determined Optically During Pulse Oximetry Without Knowledge of the Oxygen Saturation?—An In-Vitro Investigation," *Proceedings of the 20th Annual International conference of the IEEE Engie in Medicine and Biology Society*, vol. 20, No. 6, p. 3072-3075, 1998.

Such, Hans Olaf; "Optoelectronic Non-invasive Vascular Diagnostics Using multiple Wavelength and Imaging Approach," *Dissertation*, (1998).

Todd, Bryan, et al.; "The Identification of Peaks in Physiological Signals," *Computers and Biomedical Research*, vol. 32, pp. 322-335 (1999).

Goldman, Julian M.; "Masimo Signal Extraction Pulse Oximetry," *Journal of Clinical Monitoring and Computing*, vol. 16, pp. 475-483 (2000).

Coetzee, Frans M.; "Noise-Resistant Pulse Oximetry Using a Synthetic Reference Signal," *IEEE Transactions on Biomedical Engineering*, vol. 47, No. 8, Aug. 2000, pp. 1018-1026.

Kaestle, S.; "Determining Artefact Sensitivity of New Pulse Oximeters in Laboratory Using Signals Obtained from Patient," *Biomedizinische Technik*, vol. 45 (2000).

Cysewska-Sobusaik, Anna; "Metrological Problems With noninvasive Transillumination of Living Tissues," *Proceedings of SPIE*, vol. 4515, pp. 15-24 (2001).

Belal, Suliman Yousef, et al.; "A fuzzy system for detecting distorted plethysmogram pulses in neonates and paediatric patients," *Physiol. Meas.*, vol. 22, pp. 397-412 (2001).

Chan, K.W., et al.; "17.3: Adaptive Reduction of Motion Artifact from Photoplethysmographic Recordings using a Variable Step-Size LMS Filter," *IEEE*, pp. 1343-1346 (2002).

Cyrill, D., et al.; "Adaptive Comb Filter for Quasi-Periodic Physiologic Signals," *Proceedings of the 25th Annual International Conference of the IEEE EMBS, Cancun, Mexico, Sep. 17-21, 2003*; pp. 2439-2442.

Stetson, Paul F.; "Determining Heart Rate from Noisy Pulse Oximeter Signals Using Fuzzy Logic," *The IEEE International Conference on Fuzzy Systems*, St. Louis, Missouri, May 25-28, 2003; pp. 1053-1058.

Aoyagi, Takuo; "Pulse oximetry: its invention, theory, and future," *Journal of Anesthesia*, vol. 17, pp. 259-266 (2003).

Lee, C.M., et al.; "Reduction of motion artifacts from photoplethysmographic recordings using wavelet denoising approach," *IEEE EMBS Asian-Pacific Conference on Biomedical Engineering*, Oct. 20-22, 2003; pp. 194-195.

Johansson, A.; "Neural network for photoplethysmographic respiratory rate monitoring," *Medical & Biological Engineering & Computing*, vol. 41, pp. 242-248 (2003).

Addison, Paul S., et al.; "A novel time-frequency-based 3D Lissajous figure method and its application to the determination of oxygen saturation from the photoplethysmogram," *Institute of Physic Publishing, Meas. Sci. Technol.*, vol. 15, pp. L15-L18 (2004).

Yao, Jianchu, et al.; "A Novel Algorithm to Separate Motion Artifacts from Photoplethysmographic Signals Obtained With a Reflectance Pulse Oximeter," *Proceedings of the 26th Annual International conference of the IEEE EMBS, San Francisco, California, Sep. 2004*, pp. 2153-2156.

Matsuzawa, Y., et al.; "Pulse Oximeter," *Home Care Medicine*, pp. 42-45 (Jul. 2004); (Article in Japanese—contains English summary of article).

Yan, Yong-sheng, et al.; "Reduction of motion artifact in pulse oximetry by smoothed pseudo Wigner-Ville distribution," *Journal of NeuroEngineering and Rehabilitation*, vol. 2, No. 3 (9 pages) (Mar. 2005).

Huang, J., et al.; "Low Power Motion Tolerant Pulse Oximetry," *Abstracts*, A7, p. 5103 (undated).

Lang, P., et al.; "Signal Identification and Quality Indicator™ for Motion Resistant Pulse Oximetry," *Abstracts*, A10, p. 5105 (undated).

Hamilton, Patrick S., et al.; "Effect of Adaptive Motion-Artifact Reduction on QRS Detection," *Biomedical Instrumentation & Technology*, pp. 197-202 (undated).

Kim, J.M., et al.; "Signal Processing Using Fourier & Wavelet Transform," pp. II-310-II-311 (undated).

Odagiri, Y.; "Pulse Wave Measuring Device," *Micromechatronics*, vol. 42, No. 3, pp. 6-11 (undated) (Article in Japanese—contains English summary of article).

Yamazaki, Nakaji, et al.; "Motion Artifact Resistant Pulse Oximeter (Durapulse PA 2100)," *Journal of Oral Cavity Medicine*, vol. 69, No. 4, pp. 53 (date unknown) (Article in Japanese—contains English summary of article).

Malettras, Francois-Xavier, et al.; "Construction and calibration of a new design of Fiber Optic Respiratory Plethysmograph (FORP)," *Optomechanical Design and Engineering*, Proceedings of SPIE, vol. 4444, pp. 285-293 (2001).

Relente, A.R., et al.; "Characterization and Adaptive Filtering of Motion Artifacts in Pulse Oximetry using Accelerometers," *Proceedings of the Second joint EMBS/BMES Conference*, Houston, Texas, Oct. 23-26, 2002; pp. 1769-1770.

Neumann, R., et al.; "Fourier Artifact Suppression Technology Provides Reliable SpO<sub>2</sub>," *Abstracts*, A11, p. S105 (undated).




FIG. 1




FIG. 2

## SELECTION OF ENSEMBLE AVERAGING WEIGHTS FOR A PULSE OXIMETER BASED ON SIGNAL QUALITY METRICS

This application is a Continuation of U.S. patent application Ser. No. 11/701,173, filed on Feb. 1, 2007, which is a continuation of U.S. patent application Ser. No. 10/796,559, filed on Mar. 8, 2004, now U.S. Pat. No. 7,194,293 issued Mar. 20, 2007, the full disclosures of which are hereby incorporated by reference in their entirety.

### BACKGROUND OF THE INVENTION

The present invention relates in general to oximeters, and in particular to the selection of ensemble averaging weights used for ensemble averaging of signals that include detected waveforms from a pulse oximeter.

A pulse oximeter is typically used to measure various blood characteristics including the blood oxygen saturation of hemoglobin in arterial blood and the pulse rate of the patient. Measurement of these characteristics has been accomplished by use of a non-invasive sensor that passes light through a portion of a patient's blood perfused tissue and photo-electrically senses the absorption and scattering of light in such tissue. The amount of light absorbed and scattered is then used to estimate the amount of blood constituent in the tissue using various algorithms known in the art. The "pulse" in pulse oximetry comes from the time varying amount of arterial blood in the tissue during a cardiac cycle. The signal processed from the sensed optical measurement is the familiar plethysmographic waveform, which corresponds with the cyclic attenuation of optical energy through a portion of a patient's blood perfused tissue.

Ensemble averaging, which is a temporal averaging scheme, involves the use of weighting factors. In a pulse oximeter, ensemble averaging is used to calculate a weighted average of new samples and previous ensemble-averaged samples from one pulse-period earlier. Weights selected and/or used for ensemble averaging have a significant effect on the ensemble averaging process. Such weights may be uniformly selected, or they may be based on the characteristics of the signals that are being ensemble averaged. For example, the Conlon U.S. Pat. No. 4,690,126 discloses ensemble averaging where different weights are assigned to different pulses and a composite, averaged pulse waveform is used to are assigned to different pulses and a composite, averaged pulse waveform is used to calculate oxygen saturation. Conlon's signal metrics for adjusting ensemble-averaging weights are based on a measure of the degree of motion artifact, a measure of the degree of low perfusion (e.g., pulse amplitude below a threshold), and pulse rate.

However, it is desirable to provide a more flexible and more robust methodology for the selection of ensemble averaging weights used for ensemble averaging of signals that include detected waveforms from a pulse oximeter.

### BRIEF SUMMARY OF THE INVENTION

The present invention is directed to the selection of ensemble averaging weights used for ensemble averaging of signals that correspond with detected waveforms from a pulse oximeter. The selection of ensemble averaging weights are based on one or more or a combination of various signal quality metrics or indicators. In one embodiment, the present invention provides a method of ensemble averaging signals in a pulse oximeter. The method includes receiving first and second electromagnetic radiation signals from a blood per-

fused tissue portion corresponding to two different wavelengths of light; obtaining an assessment of the signal quality of the electromagnetic signals; selecting weights for an ensemble averager using the assessment of signal quality; and ensemble averaging the electromagnetic signals using the ensemble averager.

In one aspect, the selection of ensemble averaging weights involves an assessment and use of various signal quality indicators, where the selecting of weights includes forming a combination of one or more of the following signal quality parameters, namely: a measure of the degree of arrhythmia of the signals; a measure of the degree of similarity or correlation between the first and second electromagnetic radiation signals; a measure of the degree of motion artifact by obtaining a ratio of a current pulse amplitude to the long-term average pulse amplitude of the signals; a ratio of a current pulse amplitude to the previous pulse amplitude of the signal; and a ratio of a current pulse period to that of an average pulse period of the signals.

For a fuller understanding of the nature and advantages of the embodiments of the present invention, reference should be made to the following detailed description taken in conjunction with the accompanying drawings.

### BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of an exemplary oximeter.

FIG. 2 is a block diagram of the signal processing architecture of a pulse oximeter in accordance with one embodiment of the present invention.

### DETAILED DESCRIPTION OF THE INVENTION

The methods and systems in accordance with the embodiments of the present invention are directed towards the selection of ensemble averaging weights used for ensemble averaging of signals that correspond with detected waveforms from a pulse oximeter. The selection of ensemble averaging weights are based on one or more or a combination of various signal quality metrics or indicators. The embodiments of the present invention are particularly applicable to and will be explained by reference to measurements of oxygen saturation of hemoglobin in arterial blood and pulse or heart rate, as in pulse oximeter monitors and pulse oximetry sensors. However, it should be realized that the embodiments of the present invention are equally applicable to any generalized patient monitor and associated patient sensor, such as ECG, blood pressure, etc., and are thus also applicable to non oximetry or pulse oximetry devices.

A typical pulse oximeter measures two physiological parameters, percent oxygen saturation of arterial blood hemoglobin ( $SpO_2$  or sat) and pulse rate. Oxygen saturation can be estimated using various techniques. In one common technique, the photocurrent generated by the photo-detector is conditioned and processed to determine the ratio of modulation ratios (ratio of ratios) of the red to infrared (IR) signals. This modulation ratio has been observed to correlate well to arterial oxygen saturation. Pulse oximeters and sensors may be empirically calibrated by measuring the modulation ratio over a range of in vivo measured arterial oxygen saturations ( $SaO_2$ ) on a set of patients, healthy volunteers, or animals. The observed correlation is used in an inverse manner to estimate blood oxygen saturation ( $SpO_2$ ) based on the measured value of modulation ratios of a patient. The estimation of oxygen saturation using modulation ratios is described in U.S. Pat. No. 5,853,364, entitled "METHOD AND APPARATUS FOR ESTIMATING PHYSIOLOGICAL PARAM-

ETERS USING MODEL-BASED ADAPTIVE FILTERING;” issued Dec. 29, 1998, and U.S. Pat. No. 4,911,167, entitled “METHOD AND APPARATUS FOR DETECTING OPTICAL PULSES;” issued Mar. 27, 1990, which are both herein incorporated by reference in their entirety for all purposes. The relationship between oxygen saturation and modulation ratio is described, for example, in U.S. Pat. No. 5,645,059, entitled “MEDICAL SENSOR WITH MODULATED ENCODING SCHEME;” issued Jul. 8, 1997, which is herein incorporated by reference in its entirety for all purposes. Most pulse oximeters extract the plethysmographic signal having first determined saturation or pulse rate, both of which are susceptible to interference.

FIG. 1 is a block diagram of one embodiment of a pulse oximeter that may be configured to implement the embodiments of the present invention. The embodiments of the present invention may be implemented as a data processing algorithm that is executed by the microprocessor 122, described below. Light from light source 110 passes into a blood perfused tissue 112, and is scattered and detected by photodetector 114. A sensor 100 containing the light source and photodetector may also contain an encoder 116 which provides signals indicative of the wavelength of light source 110 to allow the oximeter to select appropriate calibration coefficients for calculating oxygen saturation. Encoder 116 may, for instance, be a resistor.

Sensor 100 is connected to a pulse oximeter 120. The oximeter includes a microprocessor 122 connected to an internal bus 124. Also connected to the bus is a RAM memory 126 and a display 128. A time processing unit (TPU) 130 provides timing control signals to light drive circuitry 132 which controls when light source 110 is illuminated, and if multiple light sources are used, the multiplexed timing for the different light sources. TPU 130 also controls the gating-in of signals from photodetector 114 through an amplifier 133 and a switching circuit 134. These signals are sampled at the proper time, depending upon which of multiple light sources is illuminated, if multiple light sources are used. The received signal is passed through an amplifier 136, a low pass filter 138, and an analog-to-digital converter 140. The digital data is then stored in a queued serial module (QSM) 142, for later downloading to RAM 126 as QSM 142 fills up. In one embodiment, there may be multiple parallel paths of separate amplifier, filter and A/D converters for multiple light wavelengths or spectra received.

Based on the value of the received signals corresponding to the light received by photodetector 114, microprocessor 122 will calculate the oxygen saturation using various algorithms. These algorithms require coefficients, which may be empirically determined, corresponding to, for example, the wavelengths of light used. These are stored in a ROM 146. In a two-wavelength system, the particular set of coefficients chosen for any pair of wavelength spectra is determined by the value indicated by encoder 116 corresponding to a particular light source in a particular sensor 100. In one embodiment, multiple resistor values may be assigned to select different sets of coefficients. In another embodiment, the same resistors are used to select from among the coefficients appropriate for an infrared source paired with either a near red source or far red source. The selection between whether the near red or far red set will be chosen can be selected with a control input from control inputs 154. Control inputs 154 may be, for instance, a switch on the pulse oximeter, a keyboard, or a port providing instructions from a remote host computer. Furthermore, any number of methods or algorithms may be used to determine a patient’s pulse rate, oxygen saturation or any other desired physiological parameter.

The brief description of an exemplary pulse oximeter set forth above, serves as a basis for describing the methods for adjusting ensemble averaging weights for an ensemble averager, which are described below, in conjunction with FIG. 2.

The embodiments of the present invention may be implemented as a part of a larger signal processing system used to process optical signals for the purposes of operating a pulse oximeter. Such a signal processing system is shown in FIG. 2, which is a block diagram 200 of a signal processing architecture of a pulse oximeter in accordance with one embodiment of the present invention. The signal processing architecture 200 in accordance with the embodiments of the present invention may be implemented as a software algorithm that is executed by a processor of a pulse oximeter. In addition to calculating oxygen saturation and pulse rate, the system 200 measures various signal metrics that are used to determine filter weighting coefficients. Signal metrics are things that indicate if a pulse is likely a plethysmograph or noise. Signal metrics may be related to, for example, frequency (is it in the range of a human heart rate), shape (is it shaped like a cardiac pulse), rise time, etc. The system shown in FIG. 2 calculates both the oxygen saturation, and the pulse rate. The system 200 is also used for detecting venous pulsation and sensor off and lost pulse conditions, which are described separately below.

#### I. Oxygen Saturation Calculation

Block 202 represents the operation of the Signal Conditioning block. The digitized red and IR signals or waveforms are received and are conditioned in this block by: (1) taking the 1<sup>st</sup> derivative to get rid of baseline shift, (2) low pass filtering with fixed coefficients, and (3) dividing by a DC value to preserve the ratio. The function of the Signal Conditioning subsystem is to emphasize the higher frequencies that occur in the human plethysmograph and to attenuate low frequencies in which motion artifact is usually concentrated. The Signal Conditioning subsystem selects its filter coefficients (wide or narrow band) based on hardware characteristics identified during initialization. Inputs to block 202 are digitized red and IR signals, and its outputs are pre-processed red and IR signals.

Block 204 represents the operation of the Pulse Identification and Qualification block. The low pass filtered digitized red and IR signals are provided to this block to identify pulses, and qualify them as likely arterial pulses. This is done using a pre-trained neural net, and is primarily done on the IR signal. The pulse is identified by examining its amplitude, shape and frequency. An input to this block is the average pulse period from block 208. This function changes the upfront qualification using the pulse rate. The output of block 204 indicates the degree of arrhythmia and individual pulse quality. Inputs to block 204 are: (1) pre-processed red and IR signals, (2) Average pulse period, and (3) lowpass waveforms from the low pass filter. Outputs from block 204 include: (1) degree of arrhythmia, (2) pulse amplitude variations, (3) individual pulse quality, (4) pulse beep notification, and (5) qualified pulse periods and age.

Block 206 is used to compute signal quality metrics. This block (block 206) determines the pulse shape (e.g., derivative skew), period variability, pulse amplitude and variability, Ratio of Ratios variability, and frequency content relative to pulse rate. Inputs to block 206 include: (1) raw digitized red and IR signals, (2) degree of arrhythmia, individual pulse quality, pulse amplitude variation, (3) pre-processed red and IR signals, and (4) average pulse period. Outputs from block 206 include: (1) lowpass and ensemble averaging filter weights, (2) metrics for sensor off detector, (3) normalized pre-processed waveforms, and (4) percent modulation.

Block **208** computes average pulse periods. This block (block **208**) calculates the average pulse period from the pulses received. Inputs to block **208** include: qualified pulse periods and age. An output from block **208** includes the average pulse period.

Block **210** represents the functioning of the lowpass filter and ensemble averaging subsystem. Block **210** low pass filters and ensemble averages normalized and preprocessed waveforms processed by block **206**. The weights for the low pass filter are determined by the Signal Metrics block **206**. The signal is also ensemble averaged (i.e., frequencies other than those of interest near the pulse rate and its harmonics are attenuated), with the ensemble averaging filter weights also determined by Signal Metrics block **206**. Less weight is assigned if the signal is flagged as degraded. More weight is assigned if the signal is flagged as arrhythmic because ensemble-averaging is not appropriate during arrhythmia. Red and IR waveforms are processed separately, but with the same filtering weights. The filtering is delayed (e.g., approximately one second) to allow the signal metrics to be calculated first.

The filters use continuously variable weights. If samples are not to be ensemble-averaged, then the weighting for the previous filtered samples is set to zero in the weighted average, and the new samples are still processed through the algorithm. This block tracks the age of the signal and/or the accumulated amount of filtering (e.g., sum of response times and delays in processing). Too old a result will be flagged, if good pulses haven't been detected for a while. The inputs to block **210** include: (1) normalized pre-processed red and IR signals, (2) average pulse period, (3) low pass filter weights and ensemble averaging filter weights, (4) ECG triggers, if available, and (5) IR fundamental, for zero-crossing triggers. Outputs from block **210** include: (1) filtered red and IR signals, and (2) age.

Block **212** represents operations that estimate the ratio-of-ratios variance for the filtered waveforms and calculate averaging weights. The variable weighting for the filter is controlled by the ratio-of-ratios variance. The effect of this variable-weight filtering is that the ratio-of-ratios changes slowly as artifact increases and changes quickly as artifact decreases. The subsystem has two response modes, including fast and normal modes. For example, filtering in the fast mode targets an age metric of 3 seconds, and the target age may be 5 seconds in the normal mode. In the fast mode, the minimum weighting of the current value is clipped at a higher level. In other words, a low weight is assigned to the newest ratio-of-ratios calculation if there is noise present, and a high weight if no noise is present. The inputs to block **212** include: (1) filtered red and IR signals and age, (2) calibration coefficients, and (3) response mode (e.g., user speed settings). Outputs from block **212** include an averaging weight for ratio-of-ratios calculation. The averaging weight is used as an input to block **214** along with filtered IR and Red waveforms to calculate averaged ratio of ratios and age.

Block **216** represents operations that calculate oxygen saturation. Saturation is calculated using an algorithm with the calibration coefficients and averaged ratio of ratios. Inputs to block **216** include: (1) Averaged Ratio-of-Ratios, and (2) calibration coefficients. An output from block **216** is the oxygen saturation value.

## II. Pulse Rate Calculation

Block **218** low pass filters and ensemble averages the signal(s) conditioned by block **202**, for the pulse rate identification. The weights for the low pass filter are determined by the Signal Metrics block **206**. The signal is also ensemble averaged (i.e., frequencies other than those of interest near the

pulse rate and its harmonics are attenuated), with the ensemble averaging filter weights also determined by Signal Metrics block **206**. Less weight is assigned if the signal is flagged as degraded. More weight is assigned if the signal is flagged as arrhythmic because ensemble-averaging is not appropriate during arrhythmia. Red and IR are processed separately. The filtering is delayed (e.g., approximately one second) to allow the signal metrics to be calculated first.

The filters use continuously variable weights. If samples are not to be ensemble-averaged, then the weighting for the previous filtered samples is set to zero in the weighted average, and the new samples are still processed through the algorithm. This block (block **218**) tracks the age of the signal and/or the accumulated amount of filtering (sum of response times and delays in processing). Too old a result will be flagged (if good pulses haven't been detected for awhile). Inputs to block **218** include: (1) pre-processed red and IR signals, (2) average pulse period, (3) lowpass filter weights and ensemble averaging filter weights, (4) ECG triggers, if available, and (5) IR fundamental, for zero-crossing triggers. Outputs from block **218** include: (1) filtered red and IR signals and (2) age.

Block **220**, or the Filtered Pulse Identification and Qualification block, calculates the pulse periods from the filtered waveforms, and its results are used only when a pulse is disqualified by block **204**. Inputs to block **220** include: (1) filtered red and IR signals and age, (2) average pulse period, (3) hardware ID or noise floor, (4) and the kind or type of sensor that is used to detect the IR and Red energies. Output from block **220** includes qualified pulse periods and age.

Block **222**, or the Average Pulse Periods and Calculate Pulse Rate block, calculates the pulse rate and average pulse period. This block (block **222**) receives qualified pulse periods and age as inputs and provides: (1) average pulse period and (2) pulse rate as outputs.

## III. Venous Pulsation

Block **224**, or the Detect Venous Pulsation block receives as inputs the pre-processed red and IR signals and age from Block **202**, and pulse rate and provides an indication of venous pulsation as an output. Block **224** also provides an IR fundamental waveform in the time domain using a single-tooth comb filter which is output to the Ensemble Averaging filters (e.g., block **210** and **218**). Inputs to block **224** include: (1) filtered red and IR signals and age and (2) pulse rate. Outputs from block **224** include: an indication of venous pulsation and IR fundamental. In one embodiment, block **224** measures the "openness" of an IR-Red Lissajous plot to determine the whether a flag (e.g., Venous\_Pulsation) should be set. The output flag (e.g., Venous\_Pulsation) is updated periodically (e.g., every second). In addition, the IR fundamental waveform is output to the Ensemble Averaging filters.

## IV. Sensor Off

Block **226**, or the Detect Sensor-Off and Loss of Pulse Amplitude block, uses a pre-trained neural net to determine whether the sensor is off the surface of the blood-perfused tissue, for example, of a patient. The inputs to the neural net are metrics that quantify several aspects of the behavior of the IR and Red values over the last several seconds. Samples are ignored by many of the system **200**'s subsystems while the signal state is either not indicative of a pulse being present, or indicative that a sensor is not on a monitoring site (e.g., Pulse Present, Disconnect, Pulse Lost, Sensor May be Off, and Sensor Off). Inputs to block **226** include: (1) signal quality metrics, and (2) the oximeter's LED brightness, amplifier gain, and (3) an ID indicating the oximeter's hardware configuration. Outputs from block **226** include a signal state including sensor-off indication.

In the architecture 200 described above, the function of block 226, Pulse lost and Pulse Search indications, may be derived using information from several parts of the signal processing architecture. In addition, the signal processing architecture will not use the received IR and red waveforms to compute oxygen saturation or pulse rate if a valid sensor is not connected, or if the Sensor-Off or Loss of Pulse Amplitude are detected by the signal processing architecture.

The brief description of an embodiment of a pulse oximeter signal processing architecture in accordance with the present invention, set forth above, serves as a basis for describing the methods and devices that are directed towards the selection of ensemble averaging weights used for ensemble averaging of signals that correspond with detected waveforms from a pulse oximeter, as is generally indicated by blocks 210 and 218 above.

#### Ensemble Averaging Weights

As set forth above, the selection of ensemble averaging weights are based on one or more or a combination of various signal quality metrics or indicators. In particular, in one embodiment, the metrics that are used to adjust ensemble-averaging weight, includes a measure of the degree of arrhythmia. This metric is used to reduce the degree of ensemble-averaging when the patient appears to be arrhythmic, as ensemble-averaging works less well for signals having highly variable frequency content. Another metric used to adjust ensemble-averaging weight includes a measure of the degree of variability of ratio-of-ratios (e.g., lack of similarity or correlation between IR and Red waveforms). This metric is sensitive to the presence of motion or other noise sources. This metric is different from that of other known techniques such as Conlon's, in that Conlon teaches a metric that compares the similarity between current and previous-pulse waveforms, presumably from the same wavelength, but not the similarity between two simultaneous waveforms at different wavelengths. Another metric used to adjust ensemble-averaging weight includes a ratio of a current pulse amplitude to the long-term average pulse amplitude. A long-term average pulse amplitude refers to an average that has a response time of perhaps a minute when all pulses are qualified, and several times longer if most pulses are being disqualified. This metric is designed to capture the degree of motion artifact, similar to Conlon's, however, this metric is an analog metric, whereas Conlon's metric has just a few discrete states (e.g., no artifact, low artifact, high artifact). Another metric used to adjust ensemble-averaging weight includes a ratio of a current pulse amplitude to the previous pulse amplitude. This metric is used to quickly change the ensemble-averaging weight when large motion artifact start or stop. Another metric used to adjust ensemble-averaging weight includes a measure of the overall signal quality metric for a single pulse, which metric is itself a combination of several other metrics, including the metrics described above. This metric is used to quickly reduce the ensemble filtering when motion artifact subsides and the input waveform is presumed to be of better quality than a heavily ensemble-averaged waveform. Another metric used to adjust ensemble-averaging weight includes a ratio of a current pulse period to the average pulse period. This metric is used to reduce the ensemble filtering in the event that the heart skips a beat, which can happen occasionally on many people.

When the subsystem (210 and/or 218) is notified that the Pulse Identification and Qualification subsystem (204) has just completed evaluation of a potential pulse, the subsystem updates ensemble-averaging weights, used by the instances of the Ensemble Averaging subsystem. Separate weights are

computed for the two Ensemble Averaging instances whose outputs are used in computing saturation and pulse rate. These weights are based in part on metrics provided by the instance of the Pulse Identification and Qualification subsystem whose input waveforms have not been ensemble averaged.

The equations for Sat\_Ensemble\_Averaging\_Filter\_Weight are as follows:

$$x = \max(\text{Short\_RoR\_Variance}, \text{Pulse\_Qual\_RoR\_Variance}/1.5) * \max(\text{Long\_Term\_Pulse\_Amp\_Ratio}, 1.0)$$

$$\text{RoR\_Variance\_Based\_Filt\_Wt} = 0.5 * 0.05 / \max(0.05, x)$$

$$\text{Arr\_Prob} = (\text{Period\_Var} - 0.1 * \text{Short\_RoR\_Variance} - 0.09) / (0.25 - 0.09);$$

$$\text{Arr\_Min\_Filt\_Wt\_For\_Sat} = 0.05 + 0.5 * \text{bound}(\text{Arr\_Prob}, 0, 1.0)$$

$$\text{Sat\_Ensemble\_Averaging\_Filter\_Weight} = \max(\text{RoR\_Variance\_Based\_Filt\_Wt}, \text{Arr\_Min\_Filt\_Wt\_For\_Sat}) * (1.0 + \text{Pulse\_Qual\_Score})$$

$$\text{Sat\_Ensemble\_Averaging\_Filter\_Weight} = \min(\text{Sat\_Ensemble\_Averaging\_Filter\_Weight}, 1.0),$$

where  $\text{bound}(a, b, c)$  denotes  $\min(\max(a, b), c)$

The above equations result in a default weight of 0.5 for low values of the Ratio-of-Ratios variances. Short\_RoR\_Variance and Pulse\_Qual\_RoR\_Variance are both computed over a time interval (e.g., a three-second interval). The interval for Pulse\_Qual\_RoR\_Variance ends with the qualification or rejection of the most recent pulse, which would usually include the most recent samples. The weight is reduced by high Ratio-of-Ratios variances, and by high values of Long\_Term\_Pulse\_Amp\_Ratio that would typically indicate motion artifact. Arr\_Min\_Filt\_Wt\_For\_Sat imposes a minimum value on the ensemble-averaging weight (range 0.05-0.55) based primarily on Period\_Var, which quantifies the degree of arrhythmia. This is done because ensemble-averaging is less effective for pulses having dissimilar periods. If the most recent pulse received a good Pulse\_Qual\_Score, this can increase the maximum value of Sat\_Ensemble\_Averaging\_Filter\_Weight from 0.5 to 1.0.

The equations for Rate\_Ensemble\_Averaging\_Filter\_Weight are as follows:

$$\text{Arr\_Prob} = (\text{Period\_Var} - 0.07) / (0.20 - 0.07)$$

$$\text{Arr\_Min\_Filt\_Wt\_For\_Rate} = 0.05 + 0.5 * \text{bound}(\text{Arr\_Prob}, 0, 1.0)$$

$$x = \max(\text{RoR\_Variance\_Based\_Filt\_Wt}, \text{Arr\_Min\_Filt\_Wt\_For\_Rate}) * (1.0 + \text{Pulse\_Qual\_Score})$$

$$\text{if } \text{Short\_Term\_Pulse\_Amp\_Ratio} * \text{Long\_Term\_Pulse\_Amp\_Ratio} < 1.0$$

$$x = x / \text{Short\_Term\_Pulse\_Amp\_Ratio}$$

$$\text{if } \text{Avg\_Period} > 0$$

$$x = x * \text{bound}(\text{Pulse\_Qual\_Score} * \text{Qualified\_Pulse\_Period} / \text{Avg\_Period}, 1.0, 3.0)$$

$$\text{Rate\_Ensemble\_Averaging\_Filter\_Weight} = \min(x, 1.0)$$

These equations differ from the ones for Sat\_Ensemble\_Averaging\_Filter\_Weight as follows:

- a) The thresholds used to compute Arr\_Prob are somewhat lower, because it is desirable that arrhythmic pulses not be obscured by ensemble averaging prior to pulse qualification.
- b) Small values of Short\_Term\_Pulse\_Amp\_Ratio typically indicate that motion artifact has just subsided, which means that the ensemble-averaging weight may be quickly increased. This has been found empirically to be beneficial for pulse qualification, but not for ratio-of-ratios filtering and saturation computation.
- c) If the heart skips a beat, with or without prior arrhythmia, the longer-than-average Qualified\_Pulse\_Period that results will increase the ensemble-averaging weight, so as not to obscure the skipped beat from subsequent pulse qualification.

In one aspect, the ensemble averaging weights that have been determined as described above, are used for two separate ensemble averagers for processing a detected waveform for use in calculating oxygen saturation and a pulse rate. The ensemble averager used for calculating oxygen saturation operates on a signal which has been normalized, while the ensemble averager for the pulse rate calculation operates on a signal which has not been normalized. A pulse oximeter with separate ensemble averaging for oxygen saturation and heart rate is described in a co-pending patent application assigned to the assignee herein, and titled: Pulse Oximeter with Separate Ensemble Averaging for Oxygen Saturation and Heart Rate, Ser. No. 10/796,578, is hereby incorporated herein by reference, in its entirety for all purposes. In that patent application, the metrics chosen for the two paths through the two ensemble averagers can be varied to optimize the ensemble averaging for oxygen saturation or pulse rate calculations. For example, a lower threshold is used for a metric to detect arrhythmic pulses when used to calculate pulse rate, as compared to calculating oxygen saturation. Also, a metric for a short term pulse amplitude ratio will be small when motion artifact has just subsided, and this is given more weight in the pulse rate calculation than in the oxygen saturation calculation.

## DEFINITIONS

### Data Inputs

Avg\_Period—Average pulse period reported by Pulse Rate Calculation subsystem.

Long\_Term\_Pulse\_Amp\_Ratio—Quantifies last pulse amplitude compared to historic pulse amplitude. Provided by the Pulse Identification and Qualification subsystem. Values substantially larger than 1.0 are typically indicative of motion artifact, and result in lower Ensemble\_Averaging\_Filter\_Weights.

Period\_Var—Period-variability metric from the Pulse Identification and Qualification subsystem. Used to gauge the extent of arrhythmia. For instance, a value of 0.10 would indicate that the average difference between consecutive pulse periods is 10% of Avg\_Period.

Pulse\_Qual\_RoR\_Variance—RoR\_Variance metric from the Pulse Identification and Qualification subsystem.

Pulse\_Qual\_Score—Score computed by the pulse qualification neural net in the Pulse Identification and Qualification subsystem. Zero is extremely poor and 1.0 is excellent.

Qualified\_Pulse\_Period—Most recent pulse period qualified by the Pulse Identification and Qualification subsystem.

Short\_Term\_Pulse\_Amp\_Ratio—Quantifies last pulse amplitude compared to previous pulse amplitude.

### Outputs

Frequency\_Ratio—Ratio of Mean\_IR\_Frequency\_Content to pulse rate.

LPF\_RoR\_Variance—Quantifies variability of ratio-of-ratios. Computed over a 9-second window from LPF\_Scaled\_Waveforms.

Rate\_LPF\_Weight—Lowpass filter weight to be used by the instance of the Ensemble Averaging subsystem that preprocesses waveforms used for pulse qualification and pulse rate calculation.

RoR\_Variance—Quantifies variability of ratio-of-ratios. Computed over a 9-second window from Scaled\_Waveforms. For example, a value of 0.10 would indicate that sample-to-sample ratio-of-ratios values differ from the mean ratio-of-ratios value by an average of 10% of the mean ratio-of-ratios value.

Sat\_Ensemble\_Averaging\_Filter\_Weight—Ensemble-averaging weight to be used by the instance of the Ensemble Averaging subsystem that preprocesses waveforms used for pulse qualification and pulse rate calculation.

Sat\_LPF\_Weight—Lowpass filter weight to be used by the instance of the Ensemble Averaging subsystem that preprocesses waveforms used for pulse qualification and pulse rate calculation.

Scaled\_Waveforms—Scaled versions of IR and Red Pre\_Processed\_Waveforms.

Short\_RoR\_Variance—Quantifies variability of ratio-of-ratios. Computed over a 3-second window from Scaled\_Waveforms.

### Internal Variables

Arr\_Prob—Likelihood of arrhythmia that would limit the amount of ensemble averaging. Based on Period\_Var, with threshold that are specific to each of the two Ensemble\_Averaging\_Filter\_Weights.

Arr\_Min\_Filt\_Wt\_For\_Rate, Arr\_Min\_Filt\_Wt\_For\_Sat—Minimum values for the two Ensemble\_Averaging\_Filter\_Weights, based on their respective Arr\_Prob values.

LPF\_Scaled\_Waveforms—Lowpass-filtered version of Scaled\_Waveforms, used to compute LPF\_RoR\_Variance.

Mean\_IR\_Frequency\_Content—Estimate of mean frequency content of the IR input waveform. Used to compute Frequency\_Ratio metric.

RoR\_Variance\_Based\_Filt\_Wt—Component for Ensemble\_Averaging\_Filter\_Weights based on RoR\_Variance metrics and Long\_Term\_Pulse\_Amp\_Ratio.

Accordingly, as will be understood by those of skill in the art, the present invention which is related to the selection of ensemble averaging weights, may be embodied in other specific forms without departing from the essential characteristics thereof. For example, while the present embodiments have been described in the time-domain, frequency-based methods are equally relevant to the embodiments of the present invention. Accordingly, the foregoing disclosure is intended to be illustrative, but not limiting, of the scope of the invention, which is set forth in the following claims.

What is claimed is:

1. A method of ensemble averaging signals in a pulse oximetry system, comprising:

receiving, via a sensor, first and second electromagnetic radiation signals from a blood perfused tissue portion corresponding to two different wavelengths of light; and using an oximeter,

obtaining an assessment of the signal quality of the electromagnetic signals;

calculating weights for an ensemble averager from a continuous weighting function based at least in part upon the assessment of signal quality; and

11

ensemble averaging the electromagnetic signals using the ensemble averager.

2. The method of claim 1, wherein the obtaining an assessment of the signal quality comprises obtaining a measure of a degree of arrhythmia of the signals.

3. The method of claim 2, wherein the obtaining an assessment of the signal quality further comprises obtaining a measure of a degree of similarity or correlation between the first and second signals.

4. The method of claim 1, wherein the obtaining an assessment of the signal quality comprises obtaining a measure of a degree of motion artifact present in the signals.

5. The method of claim 4, wherein the obtaining a measure of the degree of motion artifact comprises obtaining a ratio of a current pulse amplitude to a long-term average pulse amplitude of the signals.

6. The method of claim 1, wherein the obtaining an assessment of the signal quality comprises obtaining a ratio of a current pulse amplitude to a previous pulse amplitude of the signals.

7. The method of claim 1, wherein the obtaining an assessment of the signal quality comprises obtaining a measure of a degree of the overall signal quality metric for a single pulse, which comprises a combination of other metrics.

8. The method of claim 1, wherein the obtaining an assessment of the signal quality comprises obtaining a ratio of a current pulse period to an average pulse period of the signals.

9. The method of claim 1, wherein the calculating weights comprises forming a combination of one or more parameters comprising a measure of a degree of arrhythmia of the signals, a measure of the degree of similarity or correlation between the first and second electromagnetic radiation signals, a measure of a degree of motion artifact by obtaining a ratio of a current pulse amplitude to a long-term average pulse amplitude of the signals, a ratio of a current pulse amplitude to a previous pulse amplitude of the signals, and/or a ratio of a current pulse period to an average pulse period of the signals.

10. A pulse oximetry system, comprising:

a sensor configured to receive first and second electromagnetic signals from a blood perfused tissue portion corresponding to two different wavelengths of light; and

a pulse oximeter configured to:

obtain an assessment of a signal quality of the first and second electromagnetic signals;

calculate a first weight associated with the first and second electromagnetic signals for an oxygen saturation ensemble averager and/or calculate a second weight associated with the first and second electromagnetic signals for a pulse rate ensemble averager using at least one continuously variable weighting function based at least in part upon the assessment of the signal quality; and

calculate an oxygen saturation value with an oxygen saturation averager based on the first weight and the

12

first and second electromagnetic signals and/or calculate a pulse rate value with the pulse rate ensemble averager based at least in part upon the second weight and the first and second electromagnetic signals.

11. The pulse oximetry system of claim 10, wherein the pulse oximeter is configured to obtain the assessment of the signal quality at least in part by determining a correlation between the first and second electromagnetic signals.

12. The pulse oximetry system of claim 10, wherein the pulse oximeter is configured to measure a degree of variability of a ratio-of-ratios of the first and second electromagnetic signals to obtain the assessment of the signal quality.

13. The pulse oximetry system of claim 10, wherein the first weight is based at least in part upon a variability of a ratio-of-ratios over time.

14. The pulse oximetry system of claim 10, wherein the first weight is based at least in part upon a pulse qualification score.

15. The pulse oximetry system of claim 10, wherein the pulse oximeter is configured to normalize the first and second electromagnetic signals.

16. The pulse oximetry system of claim 10, comprising a filter configured to low pass filter the first and second electromagnetic signals.

17. A pulse oximetry system, comprising:

a sensor configured to receive first and second electromagnetic signals from a blood perfused tissue portion corresponding to two different wavelengths of light; and

a pulse oximeter configured to:

obtain an assessment of a signal quality of the first and second electromagnetic signals, wherein the assessment comprises a determination of whether arrhythmia is present;

calculate a weight associated with the first and second electromagnetic signals for an ensemble averager using at least one continuously variable weighting function based at least in part upon the assessment of the signal quality; and

calculate an oxygen saturation value with the ensemble averager based at least in part upon the determination of whether arrhythmia is present, the weight, and the first and second electromagnetic signals.

18. The pulse oximetry system of claim 17, wherein the pulse oximetry system is configured to reduce a degree of ensemble-averaging when arrhythmia is present.

19. The pulse oximetry system of claim 17, wherein the ensemble averager comprises a pulse rate ensemble averager and/or an oxygen saturation ensemble averager.

20. The pulse oximetry system of claim 17, wherein the weight is based in part on a variability of a ratio-of-ratios over time.

\* \* \* \* \*

专利名称(译)	基于信号质量度量选择脉冲血氧计的整体平均权重		
公开(公告)号	<a href="#">US7890154</a>	公开(公告)日	2011-02-15
申请号	US12/315449	申请日	2008-12-03
[标]申请(专利权)人(译)	内尔科尔普里坦贝内特公司		
申请(专利权)人(译)	NELLCOR PURITAN BENNETT LLC NELLCOR PURITAN BENNETT INCORPORATED		
当前申请(专利权)人(译)	COVIDIEN LP		
[标]发明人	BAKER JR CLARK R		
发明人	BAKER, JR., CLARK R.		
IPC分类号	A61B5/1455 A61B5/00		
CPC分类号	A61B5/7203 A61B5/14552 A61B5/7221		
其他公开文献	US20090082651A1		
外部链接	<a href="#">Espacenet</a> <a href="#">USPTO</a>		

摘要(译)

一种用于对脉冲血氧计中的信号进行整体平均的方法和系统，包括从对应于两个不同波长的光的血液灌注组织部分接收第一和第二电磁辐射信号，获得对电磁信号的信号质量的评估，选择权重对于使用信号质量评估的整体平均器，并使用整体平均器对电磁信号进行整体平均。

