

FIG. 1





FIG. 2



$$Red = RedMod - \frac{Dark1 + Dark2}{2}$$

$$IR = IRMod - \frac{Dark2 + Dark3}{2}$$

FIG. 3




FIG. 4

OXIMETER AMBIENT LIGHT CANCELLATION

BACKGROUND OF THE INVENTION

[0001] The present invention relates to oximeters, and in particular to techniques for ambient light cancellation in pulse oximeters.

[0002] Pulse oximetry is typically used to measure various blood flow characteristics including, but not limited to, the blood-oxygen saturation of hemoglobin in arterial blood, the volume of individual blood pulsations supplying the tissue, and the rate of blood pulsations corresponding to each heart-beat of a patient. Measurement of these characteristics has been accomplished by use of a non-invasive sensor which scatters light through a portion of the patient's tissue where blood perfuses the tissue, and photoelectrically senses the absorption of light in such tissue. The amount of light absorbed is then used to calculate the amount of blood constituent being measured.

[0003] The light scattered through the tissue is selected to be of one or more wavelengths that are absorbed by the blood in an amount representative of the amount of the blood constituent present in the blood. The amount of transmitted light scattered through the tissue will vary in accordance with the changing amount of blood constituent in the tissue and the related light absorption. For measuring blood oxygen level, such sensors have typically been provided with a light source that is adapted to generate light of at least two different wavelengths, and with photodetectors sensitive to both of those wavelengths, in accordance with known techniques for measuring blood oxygen saturation.

[0004] Known non-invasive sensors include devices that are secured to a portion of the body, such as a finger, an ear or the scalp. In animals and humans, the tissue of these body portions is perfused with blood and the tissue surface is readily accessible to the sensor.

[0005] One problem with oximeter measurements is that in addition to receiving the light that was directed at the tissue, ambient light is also detected by the photodetector. Attempts can be made to block out ambient light, but some amount of ambient light will typically be detected. One particular concern is the light at the power line frequency of fluorescent or other lights, which is 60 Hz in the United States and 50 Hz in Europe and other countries.

[0006] Since a single photodetector is typically used, the light of different wavelengths, such as red and infrared, is time multiplexed. The detected signal must be demultiplexed. The demultiplexing frequency must be high enough so that it is much larger than the pulse rate. However, choosing a demultiplexing frequency is also impacted by the ambient light interference. One issue is the aliasing of harmonics of the AC power line frequency. U.S. Pat. No. 5,713,355 discusses a technique of altering the demultiplexing frequency depending upon the amount of ambient interference detected at each frequency.

[0007] U.S. Pat. No. 5,885,213 discusses subtracting a dark signal (detected ambient light) from the detected light signal. This is accomplished by leaving both the red and infrared light emitters off, in between turning them on, so that a "dark" signal supposedly composed of the ambient light present can be detected. This can then be subtracted from the desired signal. Other examples of patents dealing with the ambient light issue are U.S. Pat. No. 6,385,471, U.S. Pat. No. 5,846,190 and U.S. Pat. No. 4,781,195.

[0008] U.S. Pat. No. 6,449,501 discusses using a notch filter to filter out line frequency. However, the sampling rate is described as being set to twice the fundamental frequency of the power line interference, leaving higher harmonics of the power line interference as a problem, and it is unclear how the interference can be filtered without filtering the modulation frequency. Another example of a notch filter being used is set forth in U.S. Pat. No. 4,802,486, which uses a notch filter for the EKG signal.

BRIEF SUMMARY OF THE INVENTION

[0009] The present invention provides a pulse oximeter method and apparatus which provides (1) a notch filter at a distance between a demodulation frequency and a common multiple of commonly used power line frequencies (50, 60, 100, and 120) and also (2) a demodulation frequency greater than a highest pulse rate of a person and lower than any harmonic of 50, 60, 100, or 120 Hz. The invention thus allows the filtering of a significant source of ambient light interference, while choosing an optimum demodulation frequency that avoids interference from the notch filter or from harmonics of the power line interference.

[0010] In one embodiment, the common multiple is 1200, with the demodulation frequency being between 5 and 20 Hz away from 1200, preferably approximately 1211 in one embodiment.

[0011] In another aspect of the invention, dark signals, or ambient light, are measured both before and after each of the light emitter wavelengths (red and infrared in one embodiment). Instead of simply subtracting one of the dark levels, the two dark levels are averaged and then subtracted from the detected signal. This compensates for a variation in ambient light during the detected signal, reducing the effect of power line interference or any other low frequency interference.

[0012] In another aspect of the present invention, digital filtering and decimation are done in the digital domain. When there is a change in a gain setting on the front end hardware, or in the LED power, the filters are preloaded to put values in their memory to correspond to an estimate of the settled value of the output at the new gain or power settings. This preloading speeds up when valid data will be available at the output of the filter.

BRIEF DESCRIPTION OF THE DRAWINGS

[0013] FIG. 1 is a block diagram of an oximeter incorporating the present invention.

[0014] FIG. 2 is a block diagram of a portion of the digital manipulations in one embodiment of the invention, including a notch filter.

[0015] FIG. 3 is a diagram illustrating the multiple dark levels that are averaged in an embodiment of the invention.

[0016] FIG. 4 is a diagram illustrating the preloading of the digital filter and decimator according to an embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

Overall System

[0017] FIG. 1 illustrates an embodiment of an oximetry system incorporating the present invention. A sensor **10** includes red and infrared LEDs and a photodetector. These are connected by a cable **12** to a board **14**. LED drive current is provided by an LED drive interface **16**. The received photocurrent from the sensor is provided to an I-V interface **18**.

The IR and red voltages are then provided to a sigma-delta interface **20** incorporating the present invention. The output of sigma-delta interface **20** is provided to a microcontroller **22**. Microcontroller **22** includes flash memory for a program, and EEPROM memory for data. The oximeter also includes a microprocessor chip **24** connected to a flash memory **26**. Finally, a clock **28** is used and an interface **30** to a digital calibration in the sensor **10** is provided. A separate host **32** receives the processed information, as well as receiving an analog signal on a line **34** for providing an analog display.

Notch Filter

[0018] FIG. 2 shows an analog-to-digital converter **40** which provides a digital signal to be manipulated by microcontroller **22** of FIG. 1. The microprocessor would include a demodulator **42**, four stages of filter/decimators **44**, a low pass filter with a notch **46**, as well as other blocks for digital manipulation of the signals and calculation of oxygen saturation as is well known in the art. Only the red channel is shown after the demodulation, but a similar channel is used for the IR signal.

[0019] Notch filter **46** deals with power line interference which, in the United States, comes from lights which operate on 60 Hz or 120 Hz, depending upon the power requirements. Europe and other areas use 50 Hz and 100 Hz. A common multiple of 50, 60, 100, and 120 Hz is 1200 Hz. The modulation bandwidth is chosen to be higher than the highest possible human pulse rate, preferably higher than 5 Hz. At the same time, it is chosen to be lower than any harmonic of the power line interference signals. Twenty hertz is chosen as a desirable upper limit because a second harmonic of 2450 will alias in at 2025 Hz. In one embodiment, the modulation frequency chosen is 1211.23 Hz. This is 11.23 Hz distant from 1200 Hz. (within a range of 5-20 Hz). Accordingly, in a preferred embodiment, a zero is provided in the notch filter at 11.23 Hz. The low pass filter with notch (**46**), in one embodiment, is an 8 pole Bessel filter with a notch at 11.25 Hz.

[0020] The present invention thus provides an effective means of eliminating interference from power line interference, such as the ripple on fluorescent lights which can alias onto the detected signal. Although anti-aliasing filters have been provided in hardware before a demodulator, it is difficult to make these effective, and thus there will be some residual line interference in the detected signal to be dealt with in the digital domain.

Averaging Ambient Dark Levels to Reduce Low Frequency Interference

[0021] FIG. 3 illustrates another aspect of the present invention, reducing ambient interference by averaging the ambient dark levels before and after a sampling period to account for low frequency interference from power lines or other sources. FIG. 3 shows a signal at a sampling rate of 2400. The upward sloping line in FIG. 3 is due to 60 Hz power line interference. It is desirable to eliminate the effect of this upward slope (which will be downward on other parts of the 60 Hz (or 50 Hz, etc.) signal).

[0022] FIG. 3 shows a detected signal during different periods of modulation. The detected signal level is illustrated by a line **50**. During a first dark period **52**, neither the red nor IR LED are on, allowing a sampling of the dark, or ambient, light. After this sampling, during a time period **54**, the red LED is turned on, with signal **50** rising during this period as

the red LED comes on to its full intensity. During the time period **56**, the detected signal corresponds to the red LED being on.

[0023] After the red LED is turned off and the signal decays during a period **58**, a second dark period **60** is sampled.

[0024] Subsequently, the IR LED is turned on during a period **62**, and sampled during a period **64**. It is turned off and the signal decays during a period **66**, with a third dark sample being taken during a period **68**. The third dark sample also corresponds to the first dark period **52**, as the process repeats itself.

[0025] As can be seen from FIG. 3, if only one of the dark levels is used, an inaccurate ambient level may be measured if the ambient level is varying, such as due to a low frequency interference. By averaging the dark periods before and after the sampling period for a particular wavelength, a more accurate measurement of the ambient dark level signal is obtained. For example, the ambient interference during the red modulation period **56** is determined by measuring the dark 1 signal during period **52** and the dark 2 signal during period **60** and averaging these signals. Similarly, for the infrared modulation period **64**, the dark 2 signal during period **60** and the dark 3 signal during period **68** are averaged and subtracted from the detected IR signal to eliminate the ambient interference. All of these calculations are done in the digital domain by microcontroller **22** of FIG. 1.

Preloading Decimation and Bessel Filters

[0026] FIG. 4 illustrates another aspect of the present invention where filters and software are preloaded. Before the analog input signal is processed through the sigma-delta modulator and multi-bit analog digital converter, it is typically amplified in a hardware amplifier **84**. After processing by the sigma-delta modulator **86** and conversion into digital domain, it is decimated to reduce the sample rate by a decimator **88** and filtered by a Bessel filter **88**. A controller **92** pre-loads the memories of the Bessel filter and decimator with an estimate of what the settled value of the output would be. This will significantly reduce the settling time of the filter after a step change in its input. Such a step change in the input can occur from a change in the gain settings of the amplifier **84**. Alternately, a step change can be the result of a change in the particular LED being activated, the power of the LED, or other gain settings of the front end hardware. Since the controller **92** would be activating such changes, it will have the knowledge of when to pre-load the filter and decimator with the appropriate values. Although these are shown as blocks in FIG. 4, it is understood that in the preferred embodiment this is done by a software program which functions as controller **92**, filter **88** and decimator **90**. This preloading of the filter and decimator provides that valid data is available sooner by shortening the settling time.

[0027] As will be understood by those skilled in the art, the present invention may be embodied in other specific forms without departing from the essential characteristics thereof. For example, more than two different wavelengths of light could be used. Alternately, a different demodulation frequency could be chosen. In addition, the notch filtering can be done either before or after other digital processing of the detected signal. Accordingly, the foregoing description is intended to be illustrative, but not limiting, of the scope of the invention which is set forth in the following claims.

1-17. (canceled)

18-35. (canceled)

- 36.** A pulse oximetry system comprising:
 an emitter capable of directing one or more wavelengths of light into a tissue;
 a detector capable of detecting the one or more wavelengths of light to provide an analog sensor signal;
 an amplifier configured to amplify the analog sensor signal to provide an amplified analog sensor signal;
 a sigma-delta modulator having an input coupled to receive the amplified analog sensor signal;
 a multiple bit analog-to-digital converter coupled to an output of the sigma-delta modulator to provide a digital signal;
 a decimator configured to receive the digital signal and output a decimated signal;
 a digital filter configured to operate on the decimated signal; and
 a controller configured to preload the decimator and digital filter with an estimate of a settled output value.
- 37.** The pulse oximetry system, as set forth in claim **36**, wherein the amplifier comprises a hardware amplifier.
- 38.** The pulse oximetry system, as set forth in claim **36**, wherein the digital filter comprises a Bessel filter.
- 39.** The pulse oximetry system, as set forth in claim **36**, wherein the controller comprises a control program.
- 40.** The pulse oximetry system, as set forth in claim **36**, wherein the controller is configured to preload the decimator and the digital filter after a step change in the decimated signal.
- 41.** The pulse oximetry system, as set forth in claim **36**, wherein the controller is configured to preload the decimator and the digital filter in response to a change in a gain setting of the amplifier.
- 42.** The pulse oximetry system, as set forth in claim **36**, wherein the controller is configured to preload the decimator and the digital filter in response to a change in an LED associated with the analog sensor signal being activated.
- 43.** The pulse oximetry system, as set forth in claim **36**, wherein the controller is configured to preload the decimator and the digital filter in response to a power change in an LED associated with the analog sensor signal.
- 44.** The pulse oximetry system, as set forth in claim **36**, wherein the controller is configured to preload the decimator and the digital filter in response to the controller changing a setting of the oximeter apparatus.
- 45.** A tangible computer-readable medium, comprising instructions for:
 controlling light at two wavelengths to be alternately driven into a tissue site using a modulation frequency that is a predetermined distance from a common multiple of 50, 60, 100, and 120, where the predetermined distance is greater than a highest pulse rate of a person and lower than a distance of any harmonic of 50, 60, 100, or 120;
 processing a signal received from the tissue site to generate a processed signal;
 notch filtering the processed signal at a frequency equivalent to the predetermined distance to produce a filtered signal; and
 calculating at least one patient characteristic based on the filtered signal.
- 46.** The tangible computer-readable medium, as set forth in claim **45** wherein processing the received signal comprises digitizing the received signal.
- 47.** The tangible computer-readable medium, as set forth in claim **45** wherein the common multiple comprises 1200.
- 48.** The tangible computer-readable medium, as set forth in claim **45** wherein the predetermined distance is between 5 and 20 hertz.
- 49.** The tangible computer-readable medium, as set forth in claim **45** wherein the predetermined distance is approximately 11 hertz.
- 50.** The tangible computer-readable medium, as set forth in claim **45** wherein the notch filtering is performed by providing a zero in a digital filter at the predetermined distance.
- 51.** The tangible computer-readable medium, as set forth in claim **45** wherein calculating at least one patient characteristic comprises calculating a blood flow characteristic.
- 52.** A tangible computer-readable medium for measuring a detected light signal in a pulse oximeter, comprising instructions for:
 controlling light to be alternately driven into a tissue site using a modulation frequency to alternate between a first period of time when a first wavelength is being generated, a dark period of time when no light is being generated, and a second period of time when a second wavelength is being generated;
 estimating a first level of ambient light in a signal received from the tissue site during the first period of time by averaging detected light received during the dark periods before and after the first period;
 estimating a second level of ambient light in the signal received from the tissue site during the second period of time by averaging detected light received during the dark periods before and after the second period;
 calculating a total light signal by subtracting the first level of ambient light from the signal received from the tissue site generated during the first period of time and subtracting the second level of ambient light from the signal received from the tissue site generated during the second period of time; and
 calculating at least one patient characteristic based on the total light signal.
- 53.** The tangible computer-readable medium, as set forth in claim **52** wherein calculating at least one patient characteristic comprises calculating a blood flow characteristic.
- 54.** The tangible computer-readable medium, as set forth in claim **52** wherein calculating at least one patient characteristic comprises calculating an oxygen saturation.
- 55.** The tangible computer-readable medium, as set forth in claim **52** wherein calculating at least one patient characteristic comprises calculating a pulse rate.

* * * * *

专利名称(译)	血氧计环境光消除		
公开(公告)号	US20090005662A1	公开(公告)日	2009-01-01
申请号	US12/172981	申请日	2008-07-14
[标]申请(专利权)人(译)	内尔科尔普里坦贝内特公司		
申请(专利权)人(译)	NELLCOR PURITAN BENNETT INC		
当前申请(专利权)人(译)	COVIDIEN LP		
[标]发明人	PETERSEN ETHAN SHEA WILLIAM CHEW BRADFORD B		
发明人	PETERSEN, ETHAN SHEA, WILLIAM CHEW, BRADFORD B.		
IPC分类号	A61B5/02 A61B5/00 A61B5/024		
CPC分类号	A61B5/02416 A61B5/14551 A61B5/7203 A61B5/7228 A61B5/7278 A61B5/14552 A61B5/7225 A61B5/725 A61B5/0205		
其他公开文献	US8315684		
外部链接	Espacenet USPTO		

摘要(译)

一种脉冲血氧计方法和装置，其在调制频率和常用电力线频率（50,60,100和120）的公倍数之间的距离处提供（1）陷波滤波器，并且还提供（2）大于的解调频率。一个人的最高脉冲率，低于50,60,100或120 Hz的任何谐波，以滤除环境光干扰，同时选择最佳解调频率，避免陷波滤波器的干扰或线路干扰的谐波。此外，在每个光发射器波长之前和之后测量用于任何低频干扰（例如电力线干扰）的环境光，然后从检测到的信号中减去环境光的平均值。

