



US 20050267380A1

(19) **United States**

(12) **Patent Application Publication** (10) **Pub. No.: US 2005/0267380 A1**

Poezevara

(43) **Pub. Date: Dec. 1, 2005**

(54) **ACTIVE IMPLANTABLE MEDICAL DEVICE
EQUIPPED WITH MEANS FOR THE
DIAGNOSIS OF RESPIRATORY DISORDERS,
WITH SOPHISTICATED DETECTION OF
RESPIRATORY CYCLES WITH ARTIFACTS**

Publication Classification

(51) **Int. Cl.⁷ A61B 5/08**

(52) **U.S. Cl. 600/529; 600/536**

(75) **Inventor: Yann Poezevara, Courcouronnes (FR)**

(57) **ABSTRACT**

Correspondence Address:
**Rodger A. Sadler
Orrick, Herrington & Sutcliffe LLP
666 Fifth Avenue
New York, NY 10103 (US)**

An active implantable medical device comprising circuits for measuring trans-thoracic impedance and delivering an impedance signal varying with respiratory activity of a patient. A signal representative of the respiratory activity of the patient is delivered starting from the impedance signal, and circuits for diagnosing respiratory disorder analyze variations of the respiratory signal on a plurality of successive cycles to detect there a profile of predetermined variation in relation to a given respiratory disorder. The device also includes circuits for automatically controlling respiratory cycles with artifacts, able to identify in the impedance signal a jump of static impedance, and/or to identify in a respiratory cycle or in a sequence of respiratory cycles a predetermined singularity representative of a cycle with artifact.

(73) **Assignee: Ela Medical S.A.**

(21) **Appl. No.: 11/096,277**

(22) **Filed: Mar. 31, 2005**

(30) **Foreign Application Priority Data**

Apr. 4, 2004 (FR)..... 04 - 03528

**ACTIVE IMPLANTABLE MEDICAL DEVICE
EQUIPPED WITH MEANS FOR THE DIAGNOSIS
OF RESPIRATORY DISORDERS, WITH
SOPHISTICATED DETECTION OF RESPIRATORY
CYCLES WITH ARTIFACTS**

FIELD OF THE INVENTION

[0001] The present invention relates to the diagnosis of respiratory sleep disorders, such as apnea or hypopnea with an "active implantable medical device" as defined by the Jun. 20, 1990 directive 90/385/CEE of the Council of the European Communities, and more particularly to a device such as a cardiac pacemaker, defibrillator, or multisite device.

BACKGROUND OF THE INVENTION

[0002] Various techniques for detecting respiratory sleep disorders are known. These techniques implement a variety of sensors. For example EP-A-0 970 713 and its counterpart, U.S. Pat. No. 6,574,507, commonly assigned herewith to ELA Médical, describe diagnosis of the occurrence of an apnea starting from the minute-ventilation signal (the "VE signal," sometimes referred to as the "MV signal"), which is a parameter with physiological preponderance generally obtained by measuring a trans-thoracic impedance, giving a continuous indication of the respiration rate of the patient.

[0003] The detection of the apnea or of hypopnea makes it possible to diagnose conditions such as the syndrome of sleep apnea (SSA), obstructive apnea, or central apnea, which is a pathology likely to involve a number of disorders, such as diurnal hyper somnolence, heart rate disturbances, or hypertension. SSA can be defined by a significant recurrence of apnea or hypopnea associated clinical signs. An "apnea" or "respiratory pause" is a temporary pause of the respiratory function lasting longer than 10 seconds and occurring while the patient is sleeping. An "hypopnea" is defined as a significant decrease of the minute-ventilation, for example, a decrease of more than 50%, compared to an average of former reference, but without pause of the respiratory function (the minute-ventilation is the product of the amplitude multiplied by the frequency of the successive respiratory cycles).

[0004] The measurement of the minute-ventilation necessary for this detection of the apnea or of hypopnea is carried out by injecting of impulses of a constant current of a few hundred microamperes at a frequency of some Hertz between two electrodes laid out in the rib cage of the patient, or between the case of the implanted device and an electrode, for example, a stimulation electrode. The variations of impedance reproduce the variations of thoracic volume, with peaks of impedance at the time of an inspiration, i.e., when the lungs are filled with air, and a decreasing impedance over time as the air is expired from the lungs.

[0005] It was noted in clinical studies that a system implementing a respiratory activity sensor recording variations of pulmonary volume at the thoracic level can be deluded in certain circumstances, leading to risks of false positive and false negative readings that can disturb interpretation of the signals by the device and thus lead to an erroneous diagnosis. Some of these disturbances can be eliminated by known adapted filtering techniques.

[0006] The trans-thoracic impedance varies according to the resistivity of tissue at the time current impulses are injected. As this resistivity depends primarily on the quantity of air in the lungs and the quantity of blood in the cardiac cavities, the impedance signal collected is modulated at the same time by breathing and the heart rate of the patient. The impedance is also modulated by variations in spacing between the measurement electrode and the case of the implanted device, which can change as the heart beats. These cardiac components can be eliminated by simple low-pass filtering, the heart rate being in the majority of the cases about three times higher than the respiratory frequency. In addition, in order to extract from the signal only the respiratory component (only the dynamic variation is significant), it is advisable to eliminate any static impedance related to the impedance from tissue recorded in a stable body position and in the absence of any breathing and cardiac beat. This static component can be eliminated by implementation of a high-pass filter.

[0007] When the trans-thoracic impedance is used to estimate the minute-ventilation and to control the heart rate, this estimate of the minute-ventilation is based on an average of several successive respiratory cycles, so that the impact of some respiratory cycles with artifacts remains low.

[0008] The starting point of the present invention lies in the observation that certain phenomena, which are not eliminated by existing low-pass and high-pass filtering, are able to disturb measurement of the trans-thoracic impedance. In particular, if one wishes to use the trans-thoracic impedance to follow instantaneous variations in respiratory activity, in particular to detect apnea and hypopnea, it is essential to eliminate all the cycles with artifacts, at the risk of producing false positives and false negatives, that can lead to erroneous diagnoses of respiratory disorders of the patient. Thus, the trans-thoracic impedance can be modified by a movement of the patient, or varied by contractions of the diaphragm during an obstructive apnea. These phenomena can produce artifacts that will disturb the system and can lead to erroneous detection of particularly full or fast respiratory cycles, or of low amplitude or long periods, which can lead to a false positive.

[0009] Another type of artifact can result from the presence in the impedance signal of a component related to cardiac beats that is not eliminated by existing high-pass filters. Indeed, in certain circumstances (for example, if bradycardia and hyperventilation occur at the same time), the respiratory frequency and the heart rate can become sufficiently close that the cardiac beats influence the impedance signal to a significant degree. The heart rate can then be incorrectly interpreted as the respiration rate, which may mask the presence of an hypopnea or an apnea (a false negative, at the time a true respiratory pathological event occurs).

[0010] When external equipment is being used (e.g., polysomnography), these disturbances can be detected by the person interpreting the signals, who can decide not to take into account one or more channels when the signal appears disturbed. This subjective appreciation of the signals is not possible in an implanted apparatus, however, which functions in an entirely automatic way according to rules defined by an analysis algorithm.

OBJECTS AND SUMMARY OF THE INVENTION

[0011] A goal of the present invention is to improve analysis of respiratory activity by an implanted device, and in particular to eliminate false positives and false negatives resulting from cycles with artifacts not taken into account by known filtering means.

[0012] The detection of cycles with artifacts according to the invention applies advantageously to implanted devices including means for diagnosing and treating respiratory disorders, which require a cycle by cycle follow-up of the respiratory activity of the patient, so as to be able to diagnose without delay occurrence of a pathological respiratory event. To this end, the invention proposes a medical device that includes in a way in itself known (for example, according to the above-mentioned EP-A-0 970 713 and its counterpart, U.S. Pat. No. 6,574,507, commonly assigned herewith to ELA Médical): means for measuring the trans-thoracic impedance, delivering an impedance signal that varies with respiratory activity of the patient; means for processing the impedance signal able to deliver, starting from this signal, a respiratory signal presenting a succession of consecutive respiratory cycles and representative of respiratory activity of the patient; and means for diagnosis of respiratory disorder, able to analyze variations of the respiratory signal over a plurality of successive cycles.

[0013] The device of the present invention also includes means for automatic control of respiratory cycles with artifacts, comprising means able to identify, in the impedance signal, a jump of static impedance, or means able to identify, in a respiratory cycle or a sequence of respiratory cycles, a predetermined singularity representative of a cycle with artifact.

[0014] The means able to identify a jump of static impedance can include means able to detect saturation of an amplifying circuit of the impedance signal processing means circuit, or the crossing of a threshold value in a circuit of digitalization of the impedance signal processing means circuit, or a modification of the cut-off frequency of the aforesaid means of high-pass or low-pass filtering.

[0015] The means able to identify a predetermined singularity can in particular include means able to detect a respiratory cycle in which:

[0016] the period is shorter than a first limit, for example, 2 seconds, or

[0017] the period is shorter than a second limit, for example, 10 seconds, and presenting an increase higher than a third limit, for example, 4 seconds, compared to the period of the preceding cycle, or

[0018] the amplitude presents an increase higher than a fourth limit compared to the amplitude in the preceding cycle, and for which the means for the diagnosis did not detect a respiratory disorder in the preceding cycle. This fourth limit can be a predetermined value, for example, 50 millivolts, or a relative value, determined compared to an average of the amplitudes measured over one former period, for example, +25% compared to the average of the amplitudes measured during a previous day.

[0019] According to various forms of implementation of the invention, in the event of identification of a static jump of impedance or a predetermined singularity:

[0020] the means for the automatic control of respiratory cycle artifacts inhibit the means for diagnosing respiratory disorder, preferably for a minimal length of time of temporization given after identification of the static jump of impedance or the predetermined singularity;

[0021] when the means for the diagnosis calculates and updates an average of the respiratory cycle periods, the means for the automatic control of respiratory cycle artifacts inhibit the update of the aforementioned average;

[0022] the means for the automatic control of respiratory cycle artifacts invalidate the aforementioned profile of predetermined variation eventually detected by the means of diagnosis, in the event of identification of jumps of static impedance or in the event of predetermined singularities of which the number exceeds a fifth limit given during a sequence of former cycles, for example, four identifications for a sequence of sixteen former cycles.

DETAILED DESCRIPTION OF THE INVENTION

[0023] A more detailed example of implementing the present invention will now be described.

[0024] The invention can in particular be applied to the active implantable medical devices marketed by ELA Médical, Montrouge, France. These devices are microcompressor-based devices comprising circuits for receiving, formatting, and treating electric signals collected by implanted electrodes. It is possible to charge therein by telemetry the software that will be stored and will be carried out to implement the below-described functions of the invention.

[0025] The invention is applicable to an implanted device comprising means for detecting the occurrence of apnea or hypopnea by analyzing the respiration rate of the patient during his or her sleep, this rate being given by the evolution over the course of the time of the minute-ventilation signal (MV signal).

[0026] The MV signal is a parameter with physiological preponderance obtained by a trans-thoracic measurement of impedance. This measurement is operated between two electrodes laid out in the rib cage of a patient, or between an electrode (for example, a stimulation electrode, if the implanted device is a cardiac pacemaker) and the case of the device. The impedance is measured by injecting a constant current of a few hundred microamperes, at a frequency of some Hertz, typically 8 Hz. This technique, for example, is described by Bonnet J L et al., Measurement of Minute-Ventilation with Different DDDR Pacemaker Electrode Configurations, *PACE*, vol. 21, 98, Part 1, and is implemented in devices like ELA Médical's *Chorus RM 7034*.

[0027] The device considers that there is apnea when it detects a respiratory pause lasting longer than 10 seconds, a phenomenon that is easy to detect by follow-up of the MV signal. To detect hypopnea, the device can compare successive sliding of the MV signal, established, for example, over

a 10 second duration. If between two consecutive averages a significant decrease of the minute-ventilation is detected, for example, a decrease of more than 50%, then the device considers that there has been an hypopnea.

[0028] As indicated above, the invention proposes implementing a monitoring of the respiratory signal so as to identify certain categories of artifacts and to engage in preventive actions during the diagnosis.

[0029] The first series of artifacts taken into account by the invention are those related to movement, which are probably most frequent and generally lead to a sudden modification of the static impedance. To this end, the device of the present invention comprises in the circuit for measuring the trans-thoracic impedance means for identifying a static impedance jump. For that, the software of the device can be programmed to function to scan in real time one or more parameters of the measuring circuit in order to detect, in particular:

[0030] the saturation of an amplifier,

[0031] extreme values reached in the digitalization circuit, or

[0032] modification of a cut-off frequency in the filtering of the signal.

[0033] If a static jump of impedance is detected, the device reacts by suspending the diagnosis of a respiratory sleep disorder as long as the signal is not stabilized to its new value, i.e., during the time necessary for filtering of the new static component. It is possible to introduce a temporization before reactivating the function of diagnosis.

[0034] According to another aspect of the invention, the artifacts can also be identified based on their effects on detection of respiratory cycles, starting from the amplitude or the period of these cycles, or the variation of these parameters cycle to cycle. Indeed, it has been noted in practice that the respiratory period is generally rather stable, and thus presents rather slow variations. Therefore, when an apnea occurs, a significant variation of the respiratory period appears, but this period passes directly from a normal value (typically 3 to 4 seconds) to a high value (longer than 10 seconds, in accordance with the definition of apnea). Therefore, variations of periods of about several seconds, but shorter than 10 seconds, can lead to suspicion of an artifact. One can also define the minimum duration of a respiratory cycle (for example, 2 seconds), such that any cycle of shorter duration can lead to suspicion of an artifact.

[0035] It is also possible to analyze the amplitude of the respiratory cycles. The measuring equipment of the minute-ventilation is dimensioned to be able to measure large respiratory cycles, occurring during an effort, for example. But when a large cycle occurs in a perfectly isolated way, it is still possible to suspect an artifact. To take these situations into account, the algorithm according to the invention analyzes the successive respiratory cycles after having determined and classified them (e.g., amplitude, period). Any respiratory cycle fulfilling one of the following criteria then will be regarded as an artifact:

[0036] the period of the cycle is less than or equal to X seconds (for example, shorter than X=2 seconds),

[0037] the period of the cycle is less than 10 seconds and presents an increase in Y seconds (for example, Y=4 seconds) compared to the period of the preceding cycle,

[0038] the amplitude of the cycle increased by Z units compared to the preceding cycle, if this preceding cycle does not coincide with a diagnosis of apnea or of hypopnea (because in this last case a significant ventilatory resumption is awaited).

[0039] Parameter Z can take a predetermined value (for example, Z=50 mV) or a relative value, calculated on a representative number of respiratory cycles (for example, an increase in Z=25% compared to the average in the amplitudes measured during the previous day).

[0040] In the presence of cycles considered as artifacts, the device can react in various ways. First of all, cycles considered as artifacts can be simply kept out in the management of the various functions of the device (typically, the enslavement function) and will not be taken into account for the update of the average of the respiratory cycles representative of the running rate, which average will be used to detect hypopnea.

[0041] Another action concerns inhibiting the means for diagnosing respiratory disorders in the event of cycles with artifacts, so as to suspend the search for an apnea or an hypopnea, in the same manner as on detection of a jump of static impedance. This inhibition of the diagnosis can be started either on identification of an isolated cycle with artifact, or only in the event of too frequent repetition of the cycles with artifacts. For example, the algorithm determines with each cycle the number of cycles with artifacts that have occurred during the last 16 respiratory cycles (sliding window). If this account reaches a determined threshold, then the algorithm invalidates the apnea or hypopnea possibly diagnosed during these preceding cycles.

[0042] In the alternative, if the system has several sensors for detection of respiratory disorders (for example, a sensor for oxygen saturation in addition to the circuit measuring the trans-thoracic impedance), the algorithm can inhibit only the research of the apnea or hypopnea based on the sensor of the trans-thoracic impedance, by continuing the research of the respiratory disorders starting only from the signal of oxygen saturation.

[0043] One skilled in the art will appreciate that the present invention can be practiced by other than the described embodiments which are presented for purposes of illustration and not of limitation.

We claim:

1. An active implantable medical device comprising:

means for measuring a trans-thoracic impedance, capable of delivering an impedance signal varying with respiratory activity of the patient;

means for processing the impedance signal, capable of delivering a respiratory signal presenting a succession of consecutive respiratory cycles and representative of respiratory activity of the patient; and

means for diagnosing a respiratory disorder, capable of analyzing variations of the respiratory signal over a plurality of successive cycles;

said device characterized in that it further comprises:

means for automatically controlling respiratory cycles with artifacts comprising:

means capable of identifying in the impedance signal a jump of static impedance, or

means capable of identifying, in at least one respiratory cycle, a predetermined singularity representative of a cycle with artifact.

2. The device of claim 1, wherein the means for processing the impedance signal further comprises an amplifying circuit in which the means capable of identifying in the impedance signal a jump of static impedance comprise means capable of detecting saturation of said amplifying circuit.

3. The device of claim 1, in which the means capable of identifying in the impedance signal a jump of static impedance further comprise means capable of detecting the crossing of a threshold value in a circuit of digitalization of a circuit of the means for processing the impedance signal.

4. The device of claim 1, in which the means capable of identifying in the impedance signal a jump of static impedance further comprise means capable of detecting a modification of the cut-off frequency of the means of high-pass or low-pass filtering.

5. The device of claim 1, in which the means capable of identifying a predetermined singularity further comprise means capable of detecting a respiratory cycle whose period is shorter than a first limit.

6. The device of claim 5, in which the first limit is 2 seconds.

7. The device of claim 1, in which the means capable of identifying a predetermined singularity further comprise means capable of detecting a respiratory cycle whose period is shorter than a second limit and presenting an increase higher than a third limit compared to the period in the preceding cycle.

8. The device of claim 7, in which the second limit is 10 seconds and the third limit is 4 seconds.

9. The device of claim 1, in which the means capable of identifying a predetermined singularity further comprise means capable of detecting a respiratory cycle whose amplitude presents an increase higher than a fourth limit compared to the amplitude in the preceding cycle, and for which

the means for the diagnosis did not detect a respiratory disorder in the preceding cycle.

10. The device of claim 9, in which the fourth limit is a predetermined value.

11. The device of claim 10, in which the fourth limit is 50 millivolts.

12. The device of claim 9, in which the fourth limit is a relative value, determined by comparison with an average of amplitudes measured over a former period.

13. The device of claim 12, in which the fourth limit is +25% compared to the average of amplitudes measured over the previous day.

14. The device of claim 1, in which the means for automatically controlling respiratory cycles with artifacts are able to inhibit the means for diagnosing a respiratory disorder in the event of identification of a jump of static impedance or a predetermined singularity.

15. The device of claim 1, in which the means for automatically controlling respiratory cycles with artifacts are able to inhibit the means for diagnosing a respiratory disorder for one minimal length of time of temporization given after identification of a jump of static impedance or a predetermined singularity.

16. The device of claim 1, in which the means for diagnosing a respiratory disorder are also able to calculate and update an average of the periods of the respiratory cycles, and in which the means for automatically controlling respiratory cycles with artifacts are able to inhibit the update of the average in the event of identification of a jump of static impedance or a predetermined singularity.

17. The device of claim 1, in which the means for automatically controlling respiratory cycles with artifacts are moreover able to invalidate the profile of predetermined variation eventually detected by the means for the diagnosis in the event of identification of jumps of static impedance or predetermined singularities of which the number exceeds a fifth limit given during a sequence of former cycles.

18. The device of claim 1, in which the fifth limit given is four for a sequence of sixteen former cycles.

* * * * *

专利名称(译)	有源植入式医疗设备，配备有诊断呼吸系统疾病的方法，具有复杂的呼吸周期检测和伪影		
公开(公告)号	US20050267380A1	公开(公告)日	2005-12-01
申请号	US11/096277	申请日	2005-03-31
[标]申请(专利权)人(译)	ELA MEDICAL		
申请(专利权)人(译)	ELA医疗S.A.		
当前申请(专利权)人(译)	索林CRM SAS		
[标]发明人	POEZEVARA YANN		
发明人	POEZEVARA, YANN		
IPC分类号	A61B5/00 A61B5/0205 A61B5/08 A61N1/36 A61N1/365		
CPC分类号	A61B5/0809 A61B5/0816 A61B5/145 A61B5/7207 A61N1/3601 A61N1/36521 A61B5/4818		
优先权	2004003528 2004-04-04 FR		
其他公开文献	US8043225		
外部链接	Espacenet USPTO		

摘要(译)

一种有源可植入医疗装置，包括用于测量经胸阻抗并传递随患者呼吸活动而变化的阻抗信号的电路。从阻抗信号开始递送表示患者呼吸活动的信号，并且用于诊断呼吸障碍的电路在多个连续循环中分析呼吸信号的变化，以检测与给定呼吸相关的预定变化的分布。紊乱。该装置还包括用于自动控制具有伪影的呼吸循环的电路，能够在阻抗信号中识别静态阻抗的跳跃，和/或在呼吸循环或呼吸循环序列中识别代表循环的预定奇点。神器。