



US008195262B2

(12) **United States Patent**
Chew et al.

(10) **Patent No.:** **US 8,195,262 B2**
(45) **Date of Patent:** ***Jun. 5, 2012**

(54) **SWITCH-MODE OXIMETER LED DRIVE WITH A SINGLE INDUCTOR**

(75) Inventors: **Bradford B. Chew**, San Ramon, CA (US); **Ethan Petersen**, Castro Valley, CA (US); **William Shea**, Livermore, CA (US)

(73) Assignee: **Nellcor Puritan Bennett LLC**, Boulder, CO (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 1665 days.

This patent is subject to a terminal disclaimer.

(21) Appl. No.: **11/494,394**

(22) Filed: **Jul. 26, 2006**

(65) **Prior Publication Data**

US 2006/0264720 A1 Nov. 23, 2006

Related U.S. Application Data

(63) Continuation of application No. 10/787,852, filed on Feb. 25, 2004, now Pat. No. 7,120,479.

(51) **Int. Cl.**
A61B 5/1455 (2006.01)
H05B 37/00 (2006.01)

(52) **U.S. Cl.** **600/323; 600/310; 315/186**

(58) **Field of Classification Search** **600/310, 600/323; 315/186, 313; 356/41**
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,638,640 A 2/1972 Shaw
4,714,341 A 12/1987 Hamaguri et al.
4,742,294 A 5/1988 Gallios
4,802,486 A 2/1989 Goodman et al.

4,805,623 A 2/1989 Jöbbsis
4,807,631 A 2/1989 Hersh et al.
4,911,167 A 3/1990 Corenman et al.
4,913,150 A 4/1990 Cheung et al.
4,928,692 A 5/1990 Goodman et al.
4,934,372 A 6/1990 Corenman et al.
4,936,679 A 6/1990 Mersch
4,938,218 A 7/1990 Goodman et al.
4,945,332 A * 7/1990 Sakamoto et al. 336/69
4,971,062 A 11/1990 Hasebe et al.
4,972,331 A 11/1990 Chance
4,974,591 A 12/1990 Awazu et al.
5,028,787 A 7/1991 Rosenthal et al.

(Continued)

FOREIGN PATENT DOCUMENTS

GB 2044550 A 10/1980

(Continued)

OTHER PUBLICATIONS


International Search Report dated Sep. 12, 2007; 12 pages.

Primary Examiner — Eric Winakur

(57) **ABSTRACT**

A light emitter drive circuit for an oximeter which utilizes a single inductor for driving multiple light emitters. The inductor is connected to a switching circuit to multiple energy storage circuits, such as capacitors. These are alternately charged up, using the same inductor. Subsequently, the capacitors are alternatively discharged for their corresponding light emitters through the same inductor. Also, the magnetic susceptibility of the LED drive circuit is reduced by using magnetic flux canceling in the inductor. In one embodiment, a toroidal inductor is used with geometric symmetry and its magnetic flux. In other embodiment, a dual core closed bobbin shielded inductor is used.

27 Claims, 3 Drawing Sheets



U.S. PATENT DOCUMENTS							
5,065,749	A	11/1991	Hasebe et al.	6,461,305	B1	10/2002	Schnall
5,084,327	A	1/1992	Stengel	6,466,809	B1	10/2002	Riley
5,119,815	A	6/1992	Chance	6,487,439	B1	11/2002	Skladnev et al.
5,122,974	A	6/1992	Chance	6,501,974	B2	12/2002	Huiku
5,165,162	A	11/1992	Charles et al.	6,501,975	B2	12/2002	Diab et al.
5,167,230	A	12/1992	Chance	6,526,301	B2	2/2003	Larsen et al.
5,190,038	A	3/1993	Polson et al.	6,544,193	B2	4/2003	Abreu
5,227,676	A	7/1993	Bahr et al.	6,546,267	B1	4/2003	Sugiura et al.
5,246,003	A	9/1993	DeLonzor	6,549,795	B1	4/2003	Chance
5,247,931	A	9/1993	Norwood	6,580,086	B1	6/2003	Schulz et al.
5,263,244	A	11/1993	Centa et al.	6,591,122	B2	7/2003	Schmitt
5,275,159	A	1/1994	Griebel	6,594,513	B1	7/2003	Jobsis et al.
5,279,295	A	1/1994	Martens et al.	6,606,509	B2	8/2003	Schmitt
5,297,548	A	3/1994	Pologe	6,606,511	B1	8/2003	Ali et al.
5,351,685	A	10/1994	Potratz	6,615,064	B1	9/2003	Aldrich
5,355,880	A	10/1994	Thomas et al.	6,618,042	B1	9/2003	Powell
5,368,026	A	11/1994	Swedlow et al.	6,622,095	B2	9/2003	Kobayashi et al.
5,372,136	A	12/1994	Steuer et al.	6,654,621	B2	11/2003	Palatnik et al.
5,385,143	A	1/1995	Aoyagi	6,654,624	B2	11/2003	Diab et al.
5,390,670	A	2/1995	Centa et al.	6,658,276	B2	12/2003	Pishney et al.
5,413,099	A	5/1995	Schmidt et al.	6,658,277	B2	12/2003	Wasserman
5,469,845	A	11/1995	DeLonzor et al.	6,662,030	B2	12/2003	Khalil et al.
5,482,036	A	1/1996	Diab et al.	6,665,551	B1	12/2003	Suzuki
5,483,646	A	1/1996	Uchikoga	6,668,183	B2	12/2003	Hicks et al.
5,553,614	A	9/1996	Chance	6,671,526	B1	12/2003	Aoyagi et al.
5,564,417	A	10/1996	Chance	6,671,528	B2	12/2003	Steuer et al.
5,575,285	A	11/1996	Takanashi et al.	6,678,543	B2	1/2004	Diab et al.
5,611,337	A	3/1997	Bukta	6,684,090	B2	1/2004	Ali et al.
5,630,413	A	5/1997	Thomas et al.	6,690,958	B1	2/2004	Walker et al.
5,645,059	A	7/1997	Fein et al.	6,697,658	B2	2/2004	Al-Ali
5,645,060	A	7/1997	Yorkey	6,707,257	B2	3/2004	Norris
5,662,106	A	9/1997	Swedlow et al.	6,708,048	B1	3/2004	Chance
5,680,857	A	10/1997	Pelikan et al.	6,711,424	B1	3/2004	Fine et al.
5,692,503	A	12/1997	Kuenstner	6,711,425	B1	3/2004	Reuss
5,713,355	A	2/1998	Richardson et al.	6,714,245	B1	3/2004	Ono
5,730,124	A	3/1998	Yamauchi	6,731,274	B2	5/2004	Powell
5,746,697	A	5/1998	Swedlow et al.	6,785,568	B2	8/2004	Chance
5,758,644	A	6/1998	Diab et al.	6,793,654	B2	9/2004	Lemberg
5,779,631	A	7/1998	Chance	6,801,797	B2	10/2004	Mannheimer et al.
5,782,757	A	7/1998	Diab et al.	6,801,798	B2	10/2004	Geddes et al.
5,786,592	A	7/1998	Hök	6,801,799	B2	10/2004	Mendelson
5,803,910	A	9/1998	Potratz	6,829,496	B2	12/2004	Nagai et al.
5,830,136	A	11/1998	DeLonzor et al.	6,850,053	B2	2/2005	Daalmans et al.
5,830,139	A	11/1998	Abreu	6,863,652	B2	3/2005	Huang et al.
5,831,598	A	11/1998	Kauffert et al.	6,873,865	B2	3/2005	Steuer et al.
5,842,981	A	12/1998	Larsen et al.	6,889,153	B2	5/2005	Dietiker
5,871,442	A	2/1999	Madarasz et al.	6,897,754	B2	5/2005	Jeong et al.
5,873,821	A	2/1999	Chance et al.	6,898,451	B2	5/2005	Wuori
5,920,263	A	7/1999	Huttenhoff et al.	6,939,307	B1	9/2005	Dunlop
5,921,921	A	7/1999	Potratz et al.	6,947,780	B2	9/2005	Scharf
5,924,979	A	7/1999	Swedlow et al.	6,949,081	B1	9/2005	Chance
5,995,855	A	11/1999	Kiani et al.	6,961,598	B2	11/2005	Diab
5,995,856	A	11/1999	Mannheimer et al.	6,983,178	B2	1/2006	Fine et al.
5,995,859	A	11/1999	Takahashi	6,993,371	B2	1/2006	Kiani et al.
6,011,986	A	1/2000	Diab et al.	6,996,427	B2	2/2006	Ali et al.
6,064,898	A	5/2000	Aldrich	7,006,865	B1	2/2006	Cohen
6,081,742	A	6/2000	Amano et al.	7,024,235	B2	4/2006	Melker et al.
6,088,607	A	7/2000	Diab et al.	7,027,849	B2	4/2006	Al-Ali
6,120,460	A	9/2000	Abreu	7,030,749	B2	4/2006	Al-Ali
6,134,460	A	10/2000	Chance	7,035,697	B1	4/2006	Brown
6,150,951	A	11/2000	Olejniczak	7,047,056	B2	5/2006	Hannula et al.
6,154,667	A	11/2000	Miura et al.	7,120,479	B2	10/2006	Chew
6,163,715	A	12/2000	Larsen et al.	7,127,278	B2	10/2006	Melker et al.
6,181,958	B1	1/2001	Steuer et al.	7,162,306	B2	1/2007	Caby et al.
6,181,959	B1	1/2001	Schöllermann et al.	7,209,775	B2	4/2007	Bae et al.
6,198,405	B1	3/2001	Anderson et al.	7,236,811	B2	6/2007	Schmitt
6,226,539	B1	5/2001	Potratz	7,263,395	B2	8/2007	Chan et al.
6,230,035	B1	5/2001	Aoyagi et al.	7,272,426	B2	9/2007	Schmid
6,266,546	B1	7/2001	Steuer et al.	7,373,193	B2	5/2008	Al-Ali et al.
6,285,895	B1	9/2001	Ristolainen et al.	2001/0005773	A1	6/2001	Larsen et al.
6,298,252	B1	10/2001	Kovach	2001/0020122	A1	9/2001	Steuer et al.
6,312,393	B1	11/2001	Abreu	2001/0039376	A1	11/2001	Steuer et al.
6,353,750	B1	3/2002	Kimura et al.	2001/0044700	A1	11/2001	Kobayashi et al.
6,397,091	B2	5/2002	Diab et al.	2002/0026106	A1	2/2002	Khalil et al.
6,411,045	B1	6/2002	Nerone	2002/0035318	A1	3/2002	Mannheimer et al.
6,415,236	B2	7/2002	Kobayashi et al.	2002/0038079	A1	3/2002	Steuer et al.
6,419,671	B1	7/2002	Lemberg	2002/0042558	A1	4/2002	Mendelson
6,438,399	B1	8/2002	Kurth	2002/0049389	A1	4/2002	Abreu
				2002/0062071	A1	5/2002	Diab et al.

2002/0111748 A1	8/2002	Kobayashi et al.	2005/0168722 A1	8/2005	Forstner et al.
2002/0133068 A1	9/2002	Huiku	2005/0177034 A1	8/2005	Beaumont
2002/0156354 A1	10/2002	Larson	2005/0192488 A1	9/2005	Bryenton et al.
2002/0161287 A1	10/2002	Schmitt	2005/0203357 A1	9/2005	Debreczeny et al.
2002/0161290 A1	10/2002	Chance	2005/0228248 A1	10/2005	Dietiker
2002/0165439 A1	11/2002	Schmitt	2005/0267346 A1	12/2005	Faber et al.
2002/0198443 A1	12/2002	Ting	2005/0283059 A1	12/2005	Iyer et al.
2003/0023140 A1	1/2003	Chance	2006/0009688 A1	1/2006	Lamego et al.
2003/0055324 A1	3/2003	Wasserman	2006/0015021 A1	1/2006	Cheng
2003/0060693 A1	3/2003	Monfre et al.	2006/0020181 A1	1/2006	Schmitt
2003/0139687 A1	7/2003	Abreu	2006/0030763 A1	2/2006	Mannheimer et al.
2003/0144584 A1	7/2003	Mendelson	2006/0052680 A1	3/2006	Diab
2003/0220548 A1	11/2003	Schmitt	2006/0058683 A1	3/2006	Chance
2003/0220576 A1	11/2003	Diab	2006/0064024 A1	3/2006	Schnall
2004/0010188 A1	1/2004	Wasserman	2006/0195028 A1	8/2006	Hannula et al.
2004/0054270 A1	3/2004	Pewzner et al.	2006/0224058 A1	10/2006	Mannheimer
2004/0087846 A1	5/2004	Wasserman	2006/0247501 A1	11/2006	Ali
2004/0107065 A1	6/2004	Al-Ali	2006/0258921 A1	11/2006	Addison et al.
2004/0127779 A1	7/2004	Steuer et al.	2006/0264720 A1	11/2006	Chew
2004/0171920 A1	9/2004	Mannheimer et al.			
2004/0176670 A1	9/2004	Takamura et al.			
2004/0176671 A1	9/2004	Fine et al.			
2004/0230106 A1	11/2004	Schmitt et al.			
2005/0080323 A1	4/2005	Kato			
2005/0101850 A1	5/2005	Parker			
2005/0113651 A1	5/2005	Wood et al.			
2005/0113656 A1	5/2005	Chance			

FOREIGN PATENT DOCUMENTS

JP	6098881	4/1994
JP	9192120	7/1997
JP	2004290412	10/2004

* cited by examiner




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6

SWITCH-MODE OXIMETER LED DRIVE WITH A SINGLE INDUCTOR

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a continuation of U.S. application Ser. No. 10/787,852, filed on Feb. 25, 2004.

BACKGROUND OF THE INVENTION

The present invention relates to oximeters, and in particular to LED drive circuits in pulse oximeters.

Pulse oximetry is typically used to measure various blood chemistry characteristics including, but not limited to, the blood-oxygen saturation of hemoglobin in arterial blood, the volume of individual blood pulsations supplying the tissue, and the rate of blood pulsations corresponding to each heart-beat of a patient. Measurement of these characteristics has been accomplished by use of a non-invasive sensor which scatters light through a portion of the patient's tissue where blood perfuses the tissue, and photoelectrically senses the absorption of light in such tissue. The amount of light absorbed at various wavelengths is then used to calculate the amount of blood constituent being measured.

The light scattered through the tissue is selected to be of one or more wavelengths that are absorbed by the blood in an amount representative of the amount of the blood constituent present in the blood. The amount of transmitted light scattered through the tissue will vary in accordance with the changing amount of blood constituent in the tissue and the related light absorption. For measuring blood oxygen level, such sensors have typically been provided with a light source that is adapted to generate light of at least two different wavelengths, and with photodetectors sensitive to both of those wavelengths, in accordance with known techniques for measuring blood oxygen saturation.

Known non-invasive sensors include devices that are secured to a portion of the body, such as a finger, an ear or the scalp. In animals and humans, the tissue of these body portions is perfused with blood and the tissue surface is readily accessible to the sensor.

The light sources, typically light emitting diodes (LEDs), need to be driven with current to activate them. Because of the significant amount of current required, this can interfere with reducing power consumed by an oximeter. One solution is shown in U.S. Pat. No. 6,226,539. There, an inductor and capacitor circuit is used to first store charge in a first switch position, and then subsequently, in a second switch position, deliver that stored charge to the LED. Two different inductor and capacitor circuits are used, one for each LED. It would be desirable to reduce the number of components required in the circuit of this patent.

BRIEF SUMMARY OF THE INVENTION

The present invention provides a light emitter drive circuit for an oximeter which utilizes a single inductor for driving multiple light emitters. The inductor is connected through a switching circuit to multiple energy storage circuits, such as capacitors. These are alternately charged up, using the same inductor. Subsequently, the capacitors are alternately discharged to activate their corresponding light emitters through the same inductor.

In another aspect of the present invention, the magnetic susceptibility of the LED drive circuit is reduced by using magnetic flux canceling in the inductor. In one embodiment,

a toroidal inductor is used with geometric symmetry in its magnetic flux. In another embodiment, a dual core closed bobbin shielded inductor is used. This embodiment has windings of both cores in series that are used to cancel the effect of an external magnetic field.

For a further understanding of the nature and advantages of the present invention, reference should be made to the following description taken in conjunction with the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram of an oximeter incorporating the present invention.

FIG. 2 is a circuit diagram of a LED drive circuit according to an embodiment of the present invention.

FIG. 3 is a block diagram of one embodiment of the logic for generating the timing and control signals for the circuit of FIG. 2.

FIG. 4 is a diagram of a toroidal inductor used in one embodiment of the present invention.

FIGS. 5 and 6 are diagrams of a dual core inductor according to an embodiment of the present invention.

DETAILED DESCRIPTION OF THE INVENTION

Oximeter System

FIG. 1 illustrates an embodiment of an oximetry system incorporating the present invention. A sensor 10 includes red and infrared LEDs and a photodetector. These are connected by a cable 12 to a board 14. LED drive current is provided by an LED drive interface 16. The received photocurrent from the sensor is provided to an I-V interface 18. The IR and red voltages are then provided to a sigma-delta interface 20 incorporating the present invention. The output of sigma-delta interface 20 is provided to a microcontroller 22. Microcontroller 22 includes flash memory for a program, and SRAM memory for data. The processor also includes a microprocessor chip 24 connected to a flash memory 26. Finally, a clock 28 is used and an interface 30 to a digital calibration in the sensor 10 is provided. A separate host 32 receives the processed information, as well as receiving an analog signal on a line 34 for providing an analog display.

LED Drive Circuit

FIG. 2 is a circuit diagram of the LED drive circuit according to an embodiment of the invention, which forms a portion of LED drive interface 16 of FIG. 1. A voltage regulator 36 provides a voltage separate from the voltage supply for the overall oximeter circuitry. The output is provided as a 4.5 volt signal on line 38, with the level being set by the feedback resistor divider of resistors R89 and R90. The voltage on line 38 is provided to a FET transistor Q11 to an inductor L6. The current through inductor L6 is provided by a switch 40 to one of capacitors C65 and C66, which store charge for the red and IR LEDs, respectively. A red/IR control signal on line 42 selects the switch position under control of the oximeter processor. A control signal LED PWM gate on line 44 controls the switching of transistor switch Q11.

Once the capacitors are charged up, the control signal on line 44 turns off switch Q11 and current is provided from either capacitor C65 or C66, through switch 40 and inductor L6 to either the red anode line 46 or the IR anode line 48 by way of transistors Q5 and Q6, respectively. A signal "red gate" turns on transistor Q5, while its inverse, "red gate" turns off transistor Q7. This provides current through the red anode line 46 to the back to back LEDs 50, with the current returning through the IR anode to transistor Q8 and through

resistor R10 to ground. Transistor Q8 is turned on by the signal “/IR gate” while the inverse of this signal, “IR gate” turns off transistor Q6. The signals are reversed when the IR anode is to be driven, with the “IR gate” and “red gate” signals, and their inverses, changing state, so that current is provided through transistor Q6 to IR anode 48 and returns through red anode 46 and through transistor Q7 to resistor R10 and ground. The “LED current sense” signal is read for calibration purposes not relevant to the present invention.

When the current from the capacitor C65 or C66 is provided through inductor L6 to the LEDs, and that current is switched off at the desired time, transistor Q11 is turned on so that the remaining current during the transition can be dumped into capacitor C64. This addresses the fact that the FET transistor switching is not instantaneous. Subsequently, C64 will dump its current through Q11 and inductor L6 into the capacitors when they are recharged.

Resistor R38 and capacitor C67 are connected in parallel to inductor L6 to protect against signal spikes, and provide a smooth transition. Connected to inductor L6 is a sampling circuit with a switch 52 controlled by an LED sample hold signal on line 54 to sample the signals and provide them through an amplifier 56 to a “LED current” signal on line 58 which is read by the processor. Operational amplifier 56 operates between 4.5 volts and ground. Thus, a voltage reference slightly above ground, of 0.2 volts, is provided as a voltage reference on pin 3. An integrating capacitor C68 is provided in parallel to amplifier 56. A switch 60 responds to a “clear LED sample” signal to operate the switch to short out the capacitor between samples.

The sample and hold circuit measures the voltage at node T18, between capacitor C69 and inductor L6, to determine the current. Capacitor C69 is $1/1000$ of the value of capacitors C65 and C66. Thus, a proportional current is provided through C69, which is injected through switch 52 to integrating capacitor C68 to provide a voltage which can be measured at the output of amplifier 56 on line 58. The voltage measured by the processor on line 58 is used as a feedback, with the processor varying the width of the pulse delivered to transistor Q11 to selectively vary the amount of energy that’s delivered to the capacitors 65 and 66, and then is eventually discharged to the LEDs 50. A PI (Proportional Integral) loop inside the processor then controls the PWM signal at Q11. This allows precise control of the LED intensity, allowing it to be maximized, if desired, without exceeding the desired limits (to avoid burning the patent, etc.).

The lower left of the diagram shows a “4.5 v LED disable” signal which is used by the microprocessor to turn off the voltage regulator 36 in certain instances. For example, diagnostics looking for shorts in a new sensor plugged in will turn off the voltage regulator if there is a problem with the LED line.

FIG. 3 illustrates processor 22, from FIG. 1, connected to programmed logic 62, which is in the LED drive interface 16 in FIG. 1. Programmed logic 62 provides the different control signals used by the circuit of FIG. 2 in response to basic timing signals from the processor of a clock, a sync pulse, and a pulse width signal.

Thus, the present invention provides an improvement over the circuit shown in U.S. Pat. No. 6,226,539 by moving the switch position between the inductor and the capacitors to eliminate the need for two inductors. This not only reduces the part count, requiring only one inductor instead of two, but also provides better matching between the red and IR drive currents since both use the same inductor.

In another aspect of the invention, the LED drive circuit’s susceptibility to magnetic interference is reduced. This mag-

netic interference can distort the detected pleth waveform. This is minimized by using magnetic flux canceling in the inductor. In one embodiment, this is a toroidal inductor as shown in FIG. 4. The toroidal inductor has a geometric symmetry in its magnetic flux. Another embodiment uses a dual core closed bobbin shielded inductor, such as shown in FIGS. 5 and 6. The windings of both cores in series are used to cancel the effect of an external magnetic field. These magnetic flux canceling inductors can be used either in the circuit of FIG. 2, or could be used in the dual inductor embodiment of the prior art. FIG. 5 shows the dual core inductor with a bobbin 70 in a cylinder 72. The wires are wound through gaps 76, as shown in FIG. 6. A first winding 78 is clockwise, while a second winding 80 is counterclockwise. A top view 82 is also shown. Ideally, the combined inductance in one embodiment is 680 uH.

The invention as illustrated in the embodiment of FIG. 2 enables the multiplexing of current, through an H-bridge topology, to back-to-back LEDs. Alternately, a different number of loads could be provided. The present invention is scalable to N-loads. The present invention is scalable to N-loads. The present invention provides significant efficiencies through reduction of support components, choice of components, and the properties of “loss-less” capacitor and inductor storage devices. The circuit of FIG. 2 can handle a range of forward voltage drops across the LEDs. The voltage provided varies automatically in accordance with the LED voltage drop, and does not put out more energy than it needs to.

The circuit is dynamically controlled through a PI loop in the processor, with current feedback being provided by the capacitive current divider from each storage capacitor (C65 and C66), which provides isolation. The feedback can be calibrated with a traditional in-line sense resistor, R10. In addition, this technique allows adjustment of the peak current for optimal signal-to-noise during the sampling period.

The addition of the upstream linear regulator 36 enhances power supply rejection capability, while the PI loop provides additional power supply insensitivity (to draft, P-P, surge, etc.).

As will be appreciated by those with skill in the art, the present invention can be embodied in other specific forms without departing from the essential characteristics thereof. For example, instead of two drive lines, three drive lines could be provided by adding another leg with FET transistor switches connected to the inductor. Additionally, this could be scalable to more than three legs connected in parallel, similar to the leg of Q6, Q8, and the leg of Q5, Q7. Accordingly, the foregoing description is intended to be illustrative, but not limiting, of the scope of the invention which is set forth in the following claims.

We claim:

1. A light emitter drive circuit for an oximeter comprising:
 - a voltage generating circuit;
 - an inductor coupled to the voltage generating circuit;
 - a first switching circuit coupled to a first node of the inductor;
 - first and second energy storage circuits connected to the first switching circuit, such that current from the inductor can be steered by the first switching circuit to one of the energy storage circuits;
 - a second switching circuit coupled to a second node of the inductor; and
 - first and second light emitter drive lines connected to the second switching circuit, such that energy from the first and second energy storage circuits can be alternately coupled to the first and second light emitter drive lines.

- 2. The circuit of claim 1 wherein the first and second energy storage circuits comprise first and second capacitors.
- 3. The circuit of claim 1 wherein the voltage generating circuit is a voltage regulator separate from a supply voltage for a remainder of the oximeter.
- 4. The circuit of claim 1 comprising a resistor and a capacitor in parallel with the inductor.
- 5. The circuit of claim 1 wherein the inductor is a magnetic flux canceling inductor.
- 6. The circuit of claim 5 wherein the inductor is a torodial inductor.
- 7. The circuit of claim 5 wherein the inductor is a dual core closed bobbin shielded inductor.
- 8. The circuit of claim 1 comprising a sample and hold circuit connected to the second node of the inductor.
- 9. The circuit of claim 1 comprising at least a third energy storage circuit connected to the first switching circuit, such that current from the inductor can be steered by the first switching circuit to one of the energy storage circuits.
- 10. A light emitter drive circuit for an oximeter comprising: a voltage generating circuit; first and second energy storage circuits; a magnetic flux canceling inductor coupled to the voltage generating circuit; and switching circuitry including an element disposed between the inductor and the first and second energy storage circuits, wherein the switching circuitry is configured to first steer current passing through the inductor into the energy storage circuits, and then provide energy from the first and second energy storage circuits back through the inductor to drive lines for light emitters.
- 11. A method comprising: directing electrical current through an inductor in a first direction to an energy storage device; storing energy in the energy storage device, wherein storing energy in the energy storage device comprises coupling the energy storage device to the inductor using a switching device; directing electrical current from the energy storage device through the inductor in a second direction; and providing a drive signal to a light emitter drive line, wherein the drive signal comprises the electrical current in the second direction.
- 12. The method of claim 11 wherein directing electrical current through the inductor in a first direction comprises coupling the inductor to a voltage generating source.
- 13. The method of claim 11 wherein directing energy through the inductor in a second direction comprises uncoupling the inductor from a voltage generating source.
- 14. The method of claim 11 wherein coupling the energy storage device to the inductor using the switching device comprises alternately coupling a first energy storage device and a second energy storage device to the inductor.
- 15. The method of claim 11 wherein providing the drive signal to the light emitter drive line comprises alternately

- providing the drive signal to a red light emitting diode and an infrared light emitting diode using switches.
- 16. The method of claim 11 comprising using a magnetic flux canceling inductor.
- 17. The method of claim 16 wherein the magnetic flux canceling inductor comprises a torodial inductor.
- 18. The method of claim 16 wherein the magnetic flux canceling inductor comprises a dual core bobbin shielded inductor.
- 19. A method of manufacture comprising: providing a switch to couple a voltage generating circuit to an inductor; coupling a first node of the inductor to a first switching circuit and a second node of the inductor to a second switching circuit; configuring the first switching circuit to alternately connect with a first energy storage device and a second energy storage device; and configuring the second switching circuit to alternately supply power to a first light emitting drive line and a second light emitting drive line.
- 20. A system comprising: a sensor comprising a first light emitter drive line and a second light emitter drive line; a board electrically coupled to the sensor, the board comprising: a voltage generating circuit; an inductor coupled to the voltage generating circuit; a first switching circuit coupled to a first node of the inductor; first and second energy storage circuits connected to the first switching circuit, such that current from the inductor can be steered by the first switching circuit to one of the energy storage circuits; a second switching circuit coupled to a second node of the inductor, the second switching circuit connected to the first and second light emitter drive lines such that energy from the first and second energy storage circuits can be alternately coupled to the first and second light emitter drive lines.
- 21. The circuit of claim 20 wherein the first and second energy storage circuits comprise first and second capacitors.
- 22. The circuit of claim 20 wherein the voltage generating circuit is a voltage regulator separate from a supply voltage for a remainder of the system.
- 23. The circuit of claim 20 comprising a resistor and a capacitor in parallel with the inductor.
- 24. The circuit of claim 20 wherein the inductor comprises a magnetic flux canceling inductor.
- 25. The circuit of claim 24 wherein the inductor comprises a torodial inductor.
- 26. The circuit of claim 24 wherein the inductor comprises a dual core closed bobbin shielded inductor.
- 27. The circuit of claim 20 comprising a sample and hold circuit connected to the second node of the inductor.

* * * * *

专利名称(译)	具有单个电感器的开关模式血氧计LED驱动器		
公开(公告)号	US8195262	公开(公告)日	2012-06-05
申请号	US11/494394	申请日	2006-07-26
[标]申请(专利权)人(译)	内尔科尔普里坦贝内特公司		
申请(专利权)人(译)	NELLCOR PURITAN BENNETT注册成立的股份有限公司特拉华		
当前申请(专利权)人(译)	COVIDIEN LP		
[标]发明人	CHEW BRADFORD B PETERSEN ETHAN SHEA WILLIAM		
发明人	CHEW, BRADFORD B. PETERSEN, ETHAN SHEA, WILLIAM		
IPC分类号	A61B5/1455 H05B37/00 A61B5/00		
CPC分类号	A61B5/14551		
其他公开文献	US20060264720A1		
外部链接	Espacenet USPTO		

摘要(译)

一种用于血氧计的光发射器驱动电路，其利用单个电感器来驱动多个光发射器。电感器连接到多个能量存储电路（例如电容器）的开关电路。使用相同的电感器交替充电。随后，电容器通过相同的电感器交替地为其相应的光发射器放电。而且，通过在电感器中使用磁通消除来降低LED驱动电路的磁化率。在一个实施例中，使用具有几何对称性及其磁通量的环形电感器。在其他实施例中，使用双芯闭合线轴屏蔽电感器。

