




US 20150359451A1

(19) **United States**(12) **Patent Application Publication**
Yu et al.(10) **Pub. No.: US 2015/0359451 A1**(43) **Pub. Date: Dec. 17, 2015**(54) **HEART RATE METER AND METHOD THEREOF****Publication Classification**(51) **Int. Cl.***A61B 5/0432* (2006.01)*A61B 5/00* (2006.01)(52) **U.S. Cl.**CPC *A61B 5/0432* (2013.01); *A61B 5/681* (2013.01); *A61B 5/6844* (2013.01)(71) Applicant: **Quanta Computer Inc.**, Kuei Shan Hsiang (TW)(72) Inventors: **Chih-Hsiung Yu**, Kuei Shan Hsiang (TW); **Yung-Ming Chung**, Kuei Shan Hsiang (TW); **Yen-Chih Huang**, Kuei Shan Hsiang (TW)(21) Appl. No.: **14/458,562**(22) Filed: **Aug. 13, 2014**(30) **Foreign Application Priority Data**

Jun. 11, 2014 (TW) 103120133

(57) **ABSTRACT**

A heart rate meter and a method thereof are provided. The method is adopted by a sensing circuit of a heart rate meter, wherein the sensing circuit includes a pulse sensor and a proximity sensor. The method includes: determining whether the sensing circuit is close to a neighboring object according to a proximity output signal of the proximity sensor; determining whether the sensing circuit is hung in the air according to a direct current (DC) output signal of the pulse sensor; and when the sensing circuit is close to the neighboring object and is not hung in the air, determining that the measuring circuit can measure an electrocardiographic signal of the neighboring object.






FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5A




FIG. 5B




FIG. 5C

HEART RATE METER AND METHOD THEREOF

CROSS REFERENCE TO RELATED APPLICATIONS

[0001] This Application claims priority of Taiwan Patent Application No. 103120133, filed on Jun. 11, 2014, the entirety of which is incorporated by reference herein.

BACKGROUND OF THE INVENTION

[0002] 1. Field of the Invention

[0003] The present invention relates to medical equipment, and in particular to a heart rate meter and a method thereof.

[0004] 2. Description of the Related Art

[0005] As percentage of the population having any form of cardiovascular diseases continues growing, the market for heart rate meters increases accordingly.

[0006] Typically, conventional heart rate meters employ green light lasers and optical sensors to measure pulses on a patient's wrist. This type of pulse sensor integrates a green light laser and an optical sensor into a single package, consequently it cannot identify whether the pulse sensor has already been positioned on the wrist so that it can start sensing the pulses correctly.

[0007] Therefore, a heart rate meter and a sensing method are required to accurately identify when a pulse sensor has been placed on a wrist, effectively eliminating noises in calculating pulses and a heart rate and reducing power consumption in the system.

BRIEF SUMMARY OF THE INVENTION

[0008] A detailed description is given in the following embodiments with reference to the accompanying drawings.

[0009] An embodiment of a method is disclosed, adopted by a sensing circuit of a heart rate meter, wherein the sensing circuit comprises a pulse sensor and a proximity sensor. The method includes: determining whether the sensing circuit is close to a neighboring object according to a proximity output signal of the proximity sensor; determining whether the sensing circuit is hung in the air according to a direct current (DC) output signal of the pulse sensor; and when the sensing circuit is close to the neighboring object and is not hung in the air, determining that the measuring circuit can measure an electrocardiographic signal of the neighboring object.

[0010] An embodiment of a heart rate meter is disclosed, including a sensing circuit and a controller. The sensing circuit includes a proximity sensor and a pulse sensor. The proximity sensor is configured to determine a proximity output signal representing whether the sensing circuit is close to a neighboring object. The pulse sensor is configured to determine a direct current (DC) output signal representing whether the sensing circuit is hung in the air. The controller is configured to determine whether the sensing circuit is close to a neighboring object according to the proximity output signal, determine whether the sensing circuit is hung in the air according to the DC output signal, and when the sensing circuit is close to the neighboring object and is not hung in the air, determine that the measuring circuit can measure an electrocardiographic signal of the neighboring object.

BRIEF DESCRIPTION OF THE DRAWINGS

[0011] The present invention can be more fully understood by reading the subsequent detailed description and examples with references made to the accompanying drawings, wherein:

[0012] FIG. 1 is a block diagram of a heart rate (heartbeat) meter 1 according to an embodiment of the invention;

[0013] FIG. 2 is a block diagram of a sensing circuit 2 according to an embodiment of the invention;

[0014] FIG. 3 is a schematic diagram illustrating how the sensing circuit 10 senses a neighboring object according to an embodiment of the invention;

[0015] FIG. 4 is a flowchart of a sensing method 4 according to an embodiment of the invention; and

[0016] FIGS. 5A through 5C show signals output from a sensing circuit of a heart rate meter according to embodiments of the invention.

DETAILED DESCRIPTION OF THE INVENTION

[0017] The following description is of the best-contemplated mode of carrying out the invention. This description is made for the purpose of illustrating the general principles of the invention and should not be taken in a limiting sense. The scope of the invention is best determined by reference to the appended claims.

[0018] FIG. 1 is a block diagram of a heart rate (heartbeat) meter 1 according to an embodiment of the invention, including a sensing circuit 2, a signal transmitter 11, a microcontroller unit (MCU) 12 (controller), a power supply circuit 13, a battery 14, a display panel 15, a Bluetooth circuit 16, a memory 17, and an alarm 18. The heart rate meter 1 is a piece of medical electronic equipment which automatically records a bioelectrical signal (electrocardiographic signal) generated by a cardiac muscle during heart actions, often employed in clinic trials and scientific studies.

[0019] The sensing circuit 2 is configured to sense the bioelectrical signal generated in the heart actions of an end-user, containing a heartbeat sensing circuit 100 (pulse sensor) and a proximity sensing circuit 102 (proximity sensor). When the heart rate meter 1 measures an electrocardiographic signal S_{wave} , the sensing circuit 2 will be stuck, tied, or otherwise fixed to an object under test such as a wrist or a body part on which the electrocardiographic signal may be detected. The electrocardiographic signal S_{wave} includes a heartbeat or a pulse signal. The heartbeat sensing circuit 100 and proximity sensing circuit 102 on the sensing circuit 2 are configured to sense the location of the object under test, to prevent it from measuring an incorrect electrocardiographic signal S_{wave} . The proximity sensing circuit 102 is configured to sense whether a neighboring object such as a wrist is present beyond a predetermined range, and output a proximity output signal S_{PROX} which represents whether the sensing circuit 2 is close to the neighboring object. For example, the proximity sensing circuit 102 can detect a neighboring object beyond a range of 1cm; and cannot detect the proximity sensing circuit 102 within the range of 1 cm, thus it relies on the heartbeat sensing circuit 100 to determine whether the sensing circuit 2 is hung in the air or fixed to the object under test. As a result, the heartbeat sensing circuit 100 is configured to sense whether the sensing circuit 2 is hung in the air and output a direct current (DC) output signal S_{DC} which represents whether the sensing circuit 2 is hung in the air. For example, when the sensing circuit 2 is fixed to an object under test, the

heartbeat sensing circuit 100 will generate a DC output signal S_{DC} that is less than a predetermined voltage, such as 2.9V. The heartbeat sensing circuit 100 may also output a sensed electrocardiographic signal S_{wave} .

[0020] The MCU 12 receives the proximity output signal S_{PROX} from the proximity sensing circuit 102 and determines whether the sensing circuit 2 is close to the neighboring object based on the proximity output signal S_{PROX} . In addition, the MCU 12 further receives the DC output signal S_{DC} from the heartbeat sensing circuit 100 and determines whether the sensing circuit 2 is close to the neighboring object based on the DC output signal S_{DC} . Only when the sensing circuit 2 is close to the neighboring object and is not hung in the air, the MCU 12 can determine that the sensing circuit 2 can measure an electrocardiographic signal S_{wave} of the neighboring object, i.e., the electrocardiographic signal S_{wave} measured by the heartbeat sensing circuit 100 is valid. When the sensing circuit 2 is beyond the predetermined range, the MCU 12 determines that the sensing circuit 2 is not fixed to the neighboring object, and thus the electrocardiographic signal S_{wave} measured by the heartbeat sensing circuit 100 is invalid. When the sensing circuit 2 is close to the object under test and is hung in the air, the MCU 12 determines that the sensing circuit 2 is close to the neighboring object but not in direct contact, and thus the electrocardiographic signal S_{wave} measured by the heartbeat sensing circuit 100 is invalid.

[0021] The MCU 12 can communicate with the heartbeat sensing circuit 100 and proximity sensing circuit 102 by means of wired or wireless connections. For example, the MCU 12 may communicate with the heartbeat sensing circuit 100 and proximity sensing circuit 102 by the I2C wired communication protocol. In another example, the MCU 12 may communicate with the heartbeat sensing circuit 100 and proximity sensing circuit 102 by the Bluetooth wireless communication protocol. Moreover, the MCU 12 and the sensing circuit 2 may be disposed on the same or different devices.

[0022] The signal transmitter 11 is configured to transmit a light signal such as a green beam laser to a neighboring object or a body part. During heart contractions and relaxations, blood will carry different concentrations of red blood cells, the red blood cells will absorb a part of the transmitted light signal and reflect another part of the transmitted light signal to the heartbeat sensing circuit 100. As a result, the heartbeat sensing circuit 100 can determine the electrocardiographic signal S_{wave} by sensing the reflected light signal. The power supply circuit 13 and battery 14 are configured to provide the power supply to all circuits in the heart rate meter 1. The display panel 15 is configured to display the measured electrocardiographic signal S_{wave} . The Bluetooth circuit 16 is configured to perform Bluetooth communications. The memory 17 is configured to record the electrocardiographic signal S_{wave} and store an application for measuring the electrocardiographic signal, wherein the application may be loaded into the MCU 12 to determine when to measure the electrocardiographic signal S_{wave} of a body part, process the measured electrocardiographic signal S_{wave} , and determine an emergency condition based on the measured electrocardiographic signal S_{wave} . For example, when the magnitude of the measured electrocardiographic signal S_{wave} is less than a predetermined magnitude, the application may determine that an emergency has occurred. The application may implement a sensing method 4 shown in FIG. 4. The alarm 18 is configured to generate an alert sound in an emergency.

[0023] The heart rate meter 1 in FIG. 1 adopts the heartbeat sensing circuit 100 and the proximity sensing circuit 102 to sense the location of an object under test, to prevent the measurement of an invalid electrocardiographic signal S_{wave} , eliminate noises from a valid electrocardiographic signal S_{wave} effectively, and reduce power consumption in the system of the heart rate meter 1.

[0024] FIG. 2 is a block diagram of a sensing circuit 2 according to an embodiment of the invention, including a heartbeat sensing circuit 100, a proximity sensing circuit 102 and an MCU 12.

[0025] The sensing circuit 2 adopts the proximity sensing circuit 102 to sense whether a neighboring object is beyond a predetermined range, the heartbeat sensing circuit 100 to sense whether the sensing circuit is hung in the air, and the MCU 12 to determine whether the sensing circuit may measure an electrocardiographic signal of the neighboring object. The proximity sensing circuit 102 can output a proximity output signal S_{PROX} representing whether the sensing circuit 2 is close to the neighboring object. Because the proximity sensing circuit 102 can only detect a neighboring object beyond a predetermined range, after the proximity output signal S_{PROX} indicates that no neighboring object is present beyond the predetermined range, the heartbeat sensing circuit 100 may subsequently sense whether a neighboring object is present within the predetermined range. The heartbeat sensing circuit 100 can output a DC output signal S_{DC} representing whether the sensing circuit 2 is hung in the air or in direct contact with a neighboring object. When the sensing circuit 2 is in direct contact with a neighboring object, the heartbeat sensing circuit 100 can sense a stable DC voltage that is less than a predetermined voltage, e.g., 2.9V, with the stable DC voltage being the DC output signal S_{DC} . When the sensing circuit 2 is hung above in the predetermined range but not in direct contact with a neighboring object, the heartbeat sensing circuit 100 will sense a DC output signal S_{DC} that exceeds the predetermined voltage, and the MCU 12 will determine whether a neighboring object is present in close proximity, and determine the location of the neighboring object based on the proximity output signal S_{PROX} and DC output signal S_{DC} . The MCU 12 will then determine whether the sensing circuit 2 may measure an electrocardiographic signal of the neighboring object based on the information thereof. Specifically, only when the MCU 12 determines that a neighboring object is close to the sensing circuit 2 and that the sensing circuit 2 is not hung in the air based on the proximity output signal S_{PROX} and DC output signal S_{DC} , an electrocardiographic signal S_{wave} of the neighboring object then can be measured.

[0026] The heartbeat sensing circuit 100 includes a current source 20, a heartbeat sensor 21, an amplifier and filter 22, a first amplification circuit 23, and a second amplification circuit 24. The current source 20 provides a current to the heartbeat sensor 21 to sense a reflected light signal for producing a pulse signal S_{PLS} , which is subsequently amplified and noise-filtered by the amplifier and filter 22 to generate the DC output signal S_{DC} . The first amplification circuit 23 and second amplification circuit 24 then eliminate a DC component from the DC output signal S_{DC} , and keep an alternative current (AC) component of the DC output signal S_{DC} to generate the electrocardiographic signal S_{wave} .

[0027] FIG. 3 is a schematic diagram illustrating that the sensing circuit 10 senses a neighboring object according to an embodiment of the invention. The heartbeat sensing circuit

100 and the proximity sensing circuit **102** are disposed on the same side and adjacent to each other for sensing a neighboring object **30**.

[0028] When the sensing circuit **10** is near the neighboring object **30**, the heartbeat sensing circuit **100** or the proximity sensing circuit **102** will detect the presence of the neighboring object **30**. When the distance between the sensing circuit **10** and the neighboring object **30** exceeds a predetermined range, e.g., 1 cm, the proximity sensing circuit **102** will sense the neighboring object **30**, and the heartbeat sensing circuit **100** will sense an unstable and erratic DC output signal S_{DC} . Please refer to FIG. 5B: when the distance between the sensing circuit **10** and the neighboring object **30** exceeds the predetermined range, the heartbeat sensing circuit **100** will sense a constantly changing ambient light, and consequently output a DC output signal S_{DC} ranging from 1V to 3V, wherein the corresponding electrocardiographic signal S_{wave} shows an unstable and erratic behavior.

[0029] In FIG. 3, when the distance between the sensing circuit **10** and the neighboring object **30** is less than the predetermined range and the two are not in direct contact, the proximity sensing circuit **102** will not detect the presence of the neighboring object **30**, the heartbeat sensing circuit **100** will detect the neighboring object **30** and produce a DC output signal S_{DC} which exceeds a predetermined voltage, e.g., 3V. Please refer to FIG. 5C: when the distance between the sensing circuit **10** and the neighboring object **30** is less than the predetermined range and not in direct contact, the heartbeat sensing circuit **100** will sense a small and stable ambient light, and consequently output a DC output signal S_{DC} exceeding 3V, and the corresponding electrocardiographic signal S_{wave} shows an unstable and erratic behavior.

[0030] In FIG. 3, when the distance between the sensing circuit **10** and the neighboring object **30** is in direct contact, the heartbeat sensing circuit **100** will generate a DC output signal S_{DC} which is less than a predetermined voltage, e.g., 3V. Please refer to FIG. 5A, when the sensing circuit **10** and the neighboring object **30** are in direct contact, the heartbeat sensing circuit **100** will sense a light signal reflected by the neighboring object **30**. The reflected light signal is typically less than the ambient light, and consequently the heartbeat sensing circuit **100** will output a DC output signal S_{DC} less than 3V. When the neighboring object **30** is a human body part, the heartbeat sensing circuit **100** will generate a regular electrocardiographic signal S_{wave} based on the DC output signal S_{DC} .

[0031] FIG. 4 is a flowchart of a sensing method **4** according to an embodiment of the invention, incorporating the heart rate meter **1** in FIG. 1. The sensing method **4** may be implemented by program code stored in the memory **17**.

[0032] When the heart rate meter **1** is powered on, the MCU **12** is configured to load program code from the memory **17** to determine the distance between the sensing circuit **10** and the neighboring object and whether an electrocardiographic signal S_{wave} should be measured (**S400**). Initially, the proximity sensing circuit **102** continues sensing and outputs a proximity output signal S_{PROX} representing whether the sensing circuit **10** is close to the neighboring object to the MCU **12** (**S402**). Subsequently, the MCU **12** determines whether the sensing circuit **10** is close to any neighboring object based on the proximity output signal S_{PROX} (**S404**). If the sensed neighboring object is present beyond the predetermined range, the MCU **12** determines that the sensing circuit **10** is hung high in the air and does not close to any neighboring object, thus no

pulse or other electrocardiographic signals are not measured (**S408**). If the sensed neighboring object is present within the predetermined range, the MCU **12** then receives a DC output signal S_{DC} from the heartbeat sensing circuit **100** to determine whether the sensing circuit **10** is hung in the air (**S410**). When the DC output signal S_{DC} exceeds a predetermined voltage, it indicates that the sensing **10** is hung in the air; whereas when the DC output signal S_{DC} is less than the predetermined voltage, it indicates that the sensing circuit **10** is in direct contact with a neighboring object. As a result, when determining that the DC output signal S_{DC} exceeds the predetermined voltage, the MCU **12** will determine that the sensing circuit **10** is hung low in the air and is not in direct contact with the neighboring object, and thus no pulse or other electrocardiographic signals are measured (**S414**). In contrast, when determining that the DC output signal S_{DC} is less than the predetermined voltage, the MCU **12** will determine that the sensing circuit is in direct contact with the neighboring object, and pulses or other electrocardiographic signals should be measured (**S412**). After the sensing method **4** has determined whether an electrocardiographic signal of a neighboring object should be measured in Steps **S408**, **S412**, and **S414**, it can return to Step **S402** to restart the sensing method **4** to determine whether there is an electrocardiographic signal of another neighboring object to be measured.

[0033] The sensing method **4** in FIG. 4 adopts the heartbeat sensing circuit **100** and the proximity sensing circuit **102** to sense the location of an object under test, to prevent the measurement of an invalid electrocardiographic signal S_{wave} , eliminate noises from a valid electrocardiographic signal S_{wave} effectively, and reduce power consumption in the system of the heart rate meter **1**.

[0034] As used herein, the term “determining” encompasses calculating, computing, processing, deriving, investigating, looking up (e.g., looking up in a table, a database or another data structure), ascertaining and the like. Also, “determining” may include resolving, selecting, choosing, establishing and the like.

[0035] The various illustrative logical blocks, modules and circuits described in connection with the present disclosure may be implemented or performed with a general purpose processor, a digital signal processor (DSP), an application specific integrated circuit (ASIC), a field programmable gate array signal (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components or any combination thereof designed to perform the functions described herein. A general purpose processor may be a microprocessor, but in the alternative, the processor may be any commercially available processor, microprocessor or state machine.

[0036] The operations and functions of the various logical blocks, modules, and circuits described herein may be implemented in circuit hardware or embedded software codes that can be accessed and executed by a processor.

[0037] While the invention has been described by way of example and in terms of the preferred embodiments, it is to be understood that the invention is not limited to the disclosed embodiments. On the contrary, it is intended to cover various modifications and similar arrangements (as would be apparent to those skilled in the art). Therefore, the scope of the appended claims should be accorded the broadest interpretation so as to encompass all such modifications and similar arrangements.

What is claimed is:

1. A method, adopted by a sensing circuit of a heart rate meter, wherein the sensing circuit comprises a pulse sensor and a proximity sensor, the method comprising:

determining whether the sensing circuit is close to a neighboring object according to a proximity output signal of the proximity sensor;

determining whether the sensing circuit is hung in the air according to a direct current (DC) output signal of the pulse sensor; and

when the sensing circuit is close to the neighboring object and is not hung in the air, determining that the measuring circuit can measure an electrocardiographic signal of the neighboring object.

2. The method of claim 1, wherein the step of determining whether the sensing circuit is hung in the air comprises:

when the DC output signal is less than a predetermined voltage, determining that the sensing circuit is not hung in the air.

3. The method of claim 1, wherein the step of determining whether the sensing circuit is close to the neighboring object comprises:

when the proximity output signal indicates that a predetermined distance is not exceeded, determining whether the sensing circuit is close to the neighboring object.

4. The method of claim 1, wherein the pulse sensor and the proximity sensor are disposed alongside one another on a sensing circuit.

5. The method of claim 1, further comprising:

when the sensing circuit is not close to the neighboring object or hung in the air, determining that the measuring circuit cannot measure an electrocardiographic signal of the neighboring object.

6. A heart rate meter, comprising:

a sensing circuit, comprising:

a proximity sensor, configured to determine a proximity output signal representing whether the sensing circuit is close to a neighboring object;

a pulse sensor, configured to determine a direct current (DC) output signal representing whether the sensing circuit is hung in the air; and

a controller, configured to determine whether the sensing circuit is close to a neighboring object according to the proximity output signal, determine whether the sensing circuit is hung in the air according to the DC output signal, and when the sensing circuit is close to the neighboring object and is not hung in the air, determine that the measuring circuit can measure an electrocardiographic signal of the neighboring object.

7. The heart rate meter of claim 6, wherein when the DC output signal is less than a predetermined voltage, the controller is configured to determine that the sensing circuit is not hung in the air.

8. The heart rate meter of claim 6, wherein when the proximity output signal indicates that a predetermined distance is not exceeded, the controller is configured to determine whether the sensing circuit is close to the neighboring object.

9. The heart rate meter of claim 6, wherein the pulse sensor and the proximity sensor are disposed alongside one another on a sensing circuit.

10. The heart rate meter of claim 6, wherein when the sensing circuit is not close to the neighboring object or hung in the air, the controller is configured to determine that the measuring circuit cannot measure an electrocardiographic signal of the neighboring object.

* * * * *

专利名称(译)	心率计及其方法		
公开(公告)号	US20150359451A1	公开(公告)日	2015-12-17
申请号	US14/458562	申请日	2014-08-13
[标]申请(专利权)人(译)	广达电脑股份有限公司		
申请(专利权)人(译)	广达电脑股份有限公司.		
当前申请(专利权)人(译)	广达电脑股份有限公司.		
[标]发明人	YU CHIH HSIUNG CHUNG YUNG MING HUANG YEN CHIH		
发明人	YU, CHIH-HSIUNG CHUNG, YUNG-MING HUANG, YEN-CHIH		
IPC分类号	A61B5/0432 A61B5/00		
CPC分类号	A61B5/0432 A61B5/6844 A61B5/681 A61B5/7203 A61B2560/0209		
优先权	103120133 2014-06-11 TW		
其他公开文献	US9545214		
外部链接	Espacenet USPTO		

摘要(译)

提供了一种心率计及其方法。该方法被心率计的感测电路采用，其中感测电路包括脉冲传感器和接近传感器。该方法包括：根据接近传感器的接近输出信号确定感测电路是否接近相邻物体；根据脉冲传感器的直流（DC）输出信号确定传感电路是否悬空。当感测电路靠近相邻物体并且没有悬挂在空中时，确定测量电路可以测量相邻物体的心电信号。

