



US010172546B2

(12) **United States Patent**
Cho et al.

(10) **Patent No.:** **US 10,172,546 B2**
(45) **Date of Patent:** **Jan. 8, 2019**

(54) **SENSOR, NETWORK SYSTEM AND CONTROLLING METHOD FOR USING THE SAME**

(71) Applicant: **LG INNOTEK CO., LTD.**, Seoul (KR)

(72) Inventors: **Sung Bae Cho**, Seoul (KR); **Sang Hun Lee**, Seoul (KR); **Ju Bong Park**, Seoul (KR)

(73) Assignee: **LG INNOTEK CO., LTD.**, Seoul (KR)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 209 days.

(21) Appl. No.: **14/442,548**

(22) PCT Filed: **Nov. 28, 2013**

(86) PCT No.: **PCT/KR2013/010940**

§ 371 (c)(1),

(2) Date: **May 13, 2015**

(87) PCT Pub. No.: **WO2014/084646**

PCT Pub. Date: **Jun. 5, 2014**

(65) **Prior Publication Data**

US 2016/0277871 A1 Sep. 22, 2016

(30) **Foreign Application Priority Data**

Nov. 29, 2012 (KR) 10-2012-0137390

Nov. 30, 2012 (KR) 10-2012-0138228

(51) **Int. Cl.**

A61B 5/00 (2006.01)

H04W 4/80 (2018.01)

(Continued)

(52) **U.S. Cl.**

CPC **A61B 5/4809** (2013.01); **A61B 5/024** (2013.01); **A61B 5/02055** (2013.01);

(Continued)

(58) **Field of Classification Search**

CPC . A61B 5/02055; A61B 5/0402; A61B 5/4812; A61B 5/4809; A61B 2560/0242; H04W

4/008; H04L 12/12

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

6,547,728 B1 * 4/2003 Cornuejols G04B 25/04 600/300

6,807,438 B1 * 10/2004 Brun Del Re A61B 5/04004 128/902

(Continued)

FOREIGN PATENT DOCUMENTS

CN 102573615 A 7/2012

OTHER PUBLICATIONS

Harland et al. "Electric potential probes—new directions in the remote sensing of the human body." Meas. Sci. Technol. 13 (2002). 163-169.*

(Continued)


Primary Examiner — Meredith Weare

(74) *Attorney, Agent, or Firm* — Saliwanchik, Lloyd & Eisenschenk

(57) **ABSTRACT**


Disclosed are a sensor, which includes a cardiac impulse sensor for sensing a cardiac impulse of a human body spaced apart from the cardiac impulse sensor to generate an output signal, and a wireless processing unit for processing and outputting an operation signal of an electronic device according to an output signal of the cardiac impulse sensor, a network system including the sensor, and a method of controlling an electronic device. The electronic device is effectively controlled.

14 Claims, 5 Drawing Sheets




- (51) **Int. Cl.**
A61B 5/024 (2006.01)
H04L 12/12 (2006.01)
A61B 5/0205 (2006.01)
A61B 5/0402 (2006.01)
- (52) **U.S. Cl.**
 CPC *A61B 5/02444* (2013.01); *A61B 5/0402*
 (2013.01); *A61B 5/4812* (2013.01); *H04L*
12/12 (2013.01); *H04W 4/80* (2018.02); *A61B*
5/6891 (2013.01); *A61B 5/6898* (2013.01);
A61B 2560/0242 (2013.01)
- (56) **References Cited**
 U.S. PATENT DOCUMENTS
- 8,274,386 B1 9/2012 Dea et al.
 8,306,265 B2 * 11/2012 Fry A61B 5/0452
 348/143
 8,535,222 B2 * 9/2013 Ni A61B 5/0205
 600/300
 8,536,505 B2 * 9/2013 Page H05B 37/0218
 250/205
 8,781,568 B2 * 7/2014 Dugan A61B 5/0002
 600/519
 2005/0075553 A1 * 4/2005 Sakai A61B 5/02438
 600/372
- 2006/0071798 A1 4/2006 Kiff et al.
 2007/0161873 A1 * 7/2007 Ni A61B 5/0205
 600/300
 2008/0027337 A1 1/2008 Dugan et al.
 2008/0157964 A1 7/2008 Eskildsen et al.
 2010/0177968 A1 * 7/2010 Fry A61B 5/0452
 382/224
 2011/0251495 A1 * 10/2011 Province A61B 5/01
 600/483
 2011/0270446 A1 11/2011 Scharf et al.
 2012/0136218 A1 * 5/2012 Lee G06F 19/3418
 600/300
 2012/0139427 A1 * 6/2012 Tsai H05B 33/0854
 315/158
 2012/0203117 A1 8/2012 Chen et al.
 2013/0009552 A1 * 1/2013 Page H05B 37/0218
 315/152
- OTHER PUBLICATIONS
- International Search Report in International Application No. PCT/
 KR2013/010940, filed Nov. 28, 2013.
 Office Action dated Nov. 3, 2017 in Chinese Application No.
 201380061614.4.
- * cited by examiner


[Fig. 1]




[Fig. 2]




[Fig. 3]




[Fig. 4]




[Fig. 5]



[Fig. 6]




[Fig. 7]



[Fig. 8]

21A



SENSOR, NETWORK SYSTEM AND CONTROLLING METHOD FOR USING THE SAME

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is the U.S. national stage application of international Patent Application No. PCT/KR2013/010940, filed Nov. 28, 2013, which claims priority to Korean Application Nos. 10-2012-0137390, filed Nov. 29, 2012, and 10-2012-0138228, filed Nov. 30, 2012, the disclosures of each of which are incorporated herein by reference in their entirety.

TECHNICAL FIELD

The disclosure relates to a sensor, a network system including the same, and a method of controlling an electronic device using the same.

BACKGROUND ART

In general, home appliances such as home network systems and the like include various sensors.

For example, a conventional pyroelectric infrared ray sensor to mainly sense the presence/absence of a person detects the temperature difference between heat radiated from a moving human body and a background space, so that the absence or the presence of the user can be detected.

However, the pyroelectric infrared ray sensor does not detect the presence state of the person when the person moves at a low speed or stops. In addition the pyroelectric infrared ray sensor may erroneously operate due to the interference resulting from the temperature variation caused by heating/cooling devices such as an indoor air conditioner or a heater.

In addition, the pyroelectric infrared ray sensor cannot sense an optic angle when the optic angle exceeds a predetermined range within the line of sight even if a sensing angle of the pyroelectric infrared ray sensor is increased by using a Fresnel optical lens.

DISCLOSURE OF INVENTION

Technical Problem

The embodiment provides a sensor, a network system including the same, and a method of controlling an electronic device using the same.

Solution to Problem

According to the embodiment, there is provided a sensor including a cardiac impulse sensor for sensing a cardiac impulse of a human body spaced apart from the cardiac impulse sensor to generate an output signal, and a wireless processing unit for processing and outputting an operation signal of an electronic device according to an output signal of the cardiac impulse sensor.

Meanwhile according to the embodiment, there is provided a network system including at least one electronic device, and a sensor module comprising a cardiac impulse sensor for generating an output signal by sensing a cardiac impulse of a human body spaced apart from the sensor module, the sensor module for transmitting an operation signal of the electronic device according to the output signal.

According to the embodiment, there is provided a method of controlling an electronic device. The method includes periodically sensing a cardiac impulse of a human body, generating an operation signal of the electronic device according to the sensed cardiac impulse, and outputting the operation signal.

Advantageous Effects of Invention

As described above, according to the embodiment, since a non-contact cardiac impulse sensor is employed, even if a person stops indoor, the variation in an electric field resulting from the movement of muscles of the person according to the cardiac impulse or the respiration of the person is detected, thereby improving the accuracy of the detection of the presence/absence of the person. In addition, since the electric field can be detected in all directions without an additional lens, the production cost can be improved.

In addition, the home network system according to the embodiment controls the automatic on/off operation according to the presence/absence state of a person, controls the lighting operation according to the illuminance control using the sunlight, and controls an air conditioning operation to reduce the whole load. Accordingly, the total power consumption in a building can be reduced.

Further, a sleep mode is set in the home network system, so that the sleep state/non-sleep state of the person can be determined based on the information from the sensor to control the electronic device.

In addition, the electronic device is formed in a dongle type so that the sensor can be inserted into the communication module through the outer surface of the electronic device. Accordingly, the detachable communication module can be easily coupled with the sensor.

According to the embodiment, the sensor enables the selective implementation of various wireless communication schemes, such as a ZigBee scheme, a Wi-Fi scheme, and a Bluetooth scheme. Accordingly, the optimal wireless communication scheme is selected based on the speed/distance/power consumption, so that the effective data transmission/reception and the effective control can be performed.

BRIEF DESCRIPTION OF DRAWINGS

FIG. 1 is a view showing the structure of a home network system according to one embodiment.

FIG. 2 is a block diagram showing a sensor module of FIG. 1.

FIG. 3 is a flowchart showing the operation of the home network system.

FIG. 4 is a graph showing the waveform of an output signal of the cardiac impulse sensor of FIG. 2.

FIG. 5 is a flowchart showing the operation of the home network system according to a sleep mode.

FIG. 6 is a block diagram showing another application of the sensing module of FIG. 1.

FIG. 7 is a flowchart showing the operation of the home network system employing the sensing module of FIG. 6 according to the sleep mode.

FIG. 8 is a view showing a lighting device as one example of an electronic device in the home network system of FIG. 1.

MODE FOR THE INVENTION

Hereinafter, embodiments will be described in detail with reference to accompanying drawings so that those skilled in

3

the art can easily work with the embodiments. However, the embodiments may not be limited to those described below, but have various modifications. In addition, only components related to the embodiment are shown in drawings for the clarity of explanation. In the following description, the similar reference numerals will be assigned to the similar elements.

In the following description, when a predetermined part “includes” a predetermined component, the predetermined part does not exclude other components, but may further include other components if there is a specific opposite description.

The disclosure provides a home network system to control an electronic device by a sensor.

Hereinafter, a home network system will be described with reference to FIGS. 1 to 4.

FIG. 1 is a view showing the structure of a home network system 10 according to one embodiment. FIG. 2 is a block diagram showing a communication module assembled with a home appliance 21. FIG. 3 is a flowchart showing the operation of the home network system 10. FIG. 4 is a graph showing the waveform of an output signal of the cardiac impulse sensor 140 of FIG. 2.

The home network system 10 includes a home gateway system 40 and a plurality of electronic devices 21.

As shown in drawings, the home gateway system 40 is connected with an external communication network, and connected with a plurality of electronic devices 21 through an internal communication network.

The home gateway system 40 makes an interface for data transceived between an external communication network and the electronic devices 21.

At least one electronic device 21 may be provided. According to the present embodiment, three electronic devices 21 are shown.

In this case, the electronic device 21 may include a portable terminal 30, such as a laptop computer, or a smart phone, connected with the home gateway system 40.

Each electronic device 21 is connected with the home gateway system 40 through a plurality of networks having various shapes.

In this case, the networks having various shapes may transceive data with mutually different transmission bandwidths. The networks may employ wireless schemes such as ZigBee, Bluetooth, Z-wave, or Wi-Fi according to the coverage of the home gateway system 40.

The electronic device 21 not only representatively include a telephone and a computer, but also includes various home appliances, such as an Internet refrigerator, a digital TV, and a set top-box, which are equipped with network functions and may be connected with an external communication network such as an ultra-high speed communication network in home, as various multi-media services are employed.

In addition, the electronic device 21 includes at least one lighting device controlled by a dimming device connected with the home gateway system 40.

Further, the electronic device 21 includes at least one sensing module 22 provided in home. The configuration of the sensing module 22 will be described later.

As shown in FIG. 1, the home gateway system 40 includes a wireless communication unit 41 and a server 42.

The wireless communication unit 41 transmits a turn-on signal to the electronic device 21, which is controlled through a wireless communication scheme in home, through at least one wireless communication scheme.

The server 42 is connected between the wireless communication unit 41 and the external communication network.

4

The server 42 stores a device operating signal of the electronic device 21 to be transmitted to the wireless communication unit 41, and stores the turn-on signal received from the wireless communication unit 41.

The server 42 may further include a storage unit to store the device operating signal and the turn-on signal.

The server 42 may be connected with a portable terminal 30 through a cloud network serving as an external network to control the electronic device 21 in home.

The electronic device 21 includes at least one sensing module 22 provided in home, and the configuration of the sensing module 22 is shown in FIG. 2.

Referring to FIG. 2, the sensing module 22 includes an input unit 110 connected with an antenna 101, a wireless processing unit 120, a control unit 130, and a cardiac impulse sensor 140.

The antenna 101 transmits the device operating signal to the home gateway system 40 through the wireless network.

The input unit 110 amplifies and filters a signal received therein from the wireless processing unit 120 and transmits the signal to the antenna 101.

The wireless processing unit 120 processes the device operating signal generated from the control unit 130 and generates and outputs a wireless signal having an appropriate frequency.

The control unit 130 obtains an output signal from the cardiac impulse sensor 140, and deciphers the output signal to generate the device operating signal to turn-on a home appliance 21.

The cardiac impulse sensor 140 detects the cardiac impulse of a person spaced apart from the sensor, and may include a potentiometric sensor or an electric field sensor.

In other words, the variation of the fine electric potential difference or the variation of the electric field on a free space according to the cardiac impulse of a human body is detected through a capacitive coupling scheme so that a voltage is output.

In the home network system 10 having the sensing module 22 including a non-contact cardiac impulse sensor 140, the cardiac impulse sensor 140 may generate an output signal according to the absence/presence of a person in home to turn on/turn off the electronic device 21.

Hereinafter, the operation of the home network system 10 of the embodiment will be described with reference to FIGS. 3 and 4.

If the operation of the home network system 10 is started, the cardiac impulse sensor 140 detects the cardiac impulse of a person in a free space (in home according to the embodiment) and generates an output signal related to the cardiac impulse.

The control unit 130 of the sensing module 22 obtains the output signal from the cardiac impulse sensor 140 at a predetermined period (step S10) and determines the absence/presence state of the person.

The output signal of the cardiac impulse sensor 140 is shown in FIG. 4.

In other words, the voltage of a coupled sensing capacitor is varied depending on the variation of the electric field in the free space according to the elapse of time, so that the output voltage is varied.

If a person is present in the free space, so that the potential difference of the free space is greatly made, the output voltage becomes greater than a threshold voltage V_{th} .

In this case, if the output signal having the threshold voltage V_{th} or greater is obtained, the person is determined as being present in the free space (step S30).

If the person is determined as being present, the control unit **130** determines if a first reference time **T1** elapses after the device operating signal is output (step **S40**).

If the first reference time **T1** elapses, the control unit **130** generates a device operating signal (step **S50**).

The first reference time **T1** may be longer than a period at which the control unit **130** obtains the output signal.

The device operating signal is to turn on the electronic device **21** internetworked in the home network system **10**. The electronic device **21** may include a lighting device, an air-conditioner, or a TV.

If the device operating signal is generated, the control unit **130** turns on the wireless processing unit **120**, processes the device operating signal as a wireless signal by the wireless processing unit **120**, and outputs the wireless signal to the home gateway system **40** through the antenna **101** (step **S60**).

The home gateway system **40** receives the device operating signal from the sensing module **22** and transmits a turn-on signal to the electronic device **21** through a wireless network (step **S70**).

In this case, the server **42** stores therein information of the received device operating signal and the output turn-on signal for the electronic device (step **S80**).

The electronic device **21**, which has received the turn-on signal, is turned on according to the turn-on signal. The electronic device **21** keeps on operating during a second reference time **T2** even if another turn-on signal is not obtained.

Meanwhile, if the first reference time **T1** does not elapse, the sensing module **22** does not generate the device operating signal even if the output signal has the threshold voltage **Vth** or more.

In other words, an operation according to a previous device operating signal is maintained during the first reference time **T1**. Accordingly, the power consumption according to the turn-on of the wireless processing unit **120** can be reduced.

The control unit **130** of the sensing module **22** generates the device operating signal according to the output signal having the threshold voltage **Vth** or more if the first reference time **T1** elapses.

The home network system **10** does not transmit the device operating signal to the home gate system **40**, but transmits the device operating signal to a dimming device or a switching device internetworking with the home network system **10** through wireless network so that the electronic device **21** may be controlled.

The dimming device or the switching device may record therein the device operating signal and the turn-on signal through a wired/wireless network connected with the home gateway system **40**.

The home network system **10** is set to the sleep mode so that the sensing module **22** and the electronic device **21**, preferably, a lighting device can be controlled.

Hereinafter, the home network system **10** set to the sleep mode will be described with reference to FIG. **5**.

Referring to FIG. **5**, a user may set the sleep mode in the home network system **10**.

The sleep mode is a mode in which the cardiac impulse of the human body is sensed by using the sensing module **22** to determine if a person is in a sleep state, so that an electronic device **21**, preferably, a lighting device is controlled.

If the sleep mode is applied to the home network system **10**, the sleep mode is set in the sensing module **22** (step **S100**).

If the sleep mode is set in the sensing module **22**, the sensing module **22** senses a base cardiac impulse (step **S110**).

The base cardiac impulse is a cardiac impulse within a current sensing range when a human body is in a non-sleep state.

If the sensing of the base cardiac impulse has been finished, the data of the base cardiac impulse are stored in the control unit **130** of the sensing module **22**, and the base cardiac impulse is stored in the home gateway system **40**.

The sensing module **22** sets the stored base cardiac impulses to a heart rate in a non-sleep sleep and defines the base cardiac impulses as a threshold value used to determine the sleep state/non-sleep state of the human body.

Next, the sensing module **22** senses the cardiac impulses of a human body at a predetermined time as shown in FIG. **3** (step **S130**).

The sensing scheme of the sensing module **22** is the same as that described with reference to FIG. **3**.

In this case, if the sleep mode is set, the threshold value of FIG. **3** becomes the threshold value of the base cardiac impulse, and determination is made regarding if the voltage value of the sensed cardiac impulse is different from the threshold voltage (step **S140**).

If the voltage value of the sensed cardiac impulse is not different from the threshold voltage, or if the difference between the voltage value of the sensed cardiac impulse and the threshold voltage is within an error margin, the sensing module **22** determines a present state as a non-sleep state and generates a device operating signal to turn on the electronic device **21**, preferably, the lighting device (step **S150**).

Meanwhile, if the difference between the voltage value of the sensed cardiac impulse and the threshold voltage is beyond the error margin, the present state is determined as being a sleep state to generate a device turn-off signal to turn off the lighting device.

The device turn-off/on signal may be directly transmitted to the lighting device from the sensing module **22** according to the home network system **10**, or may directly control the lighting device while control information is being transmitted to the gateway system **40** and recorded.

On the contrary, as shown in FIG. **3**, the device turn-off signal is transmitted to the home gateway system **40**, and the home gateway system **40** may transmit the device turn-off signal to the lighting device.

The home network system **10** having the sensing module **22** including the cardiac impulse sensor **140** sets a present mode to a sleep mode to control the lighting device according to the sleep state/the non-sleep state of the person.

Hereinafter, another embodiment will be described with reference to FIG. **6**.

Referring to FIG. **6**, the sensing module **22** includes the input unit **110** connected with the antenna **101**, the wireless processing unit **120**, the control unit **130**, the cardiac impulse sensor **140**, and an auxiliary sensor **150**.

The antenna **101** transmits the device operating signal to the home gateway system **40** through a wireless network.

A wireless communication unit **430** processes the device operating signal generated from the control unit **130** and produces and outputs a wireless signal having an appropriate frequency.

The control unit **130** obtains an output signal from the cardiac impulse sensor **140**, and deciphers the output signal to produce the device operating signal to turn-on the home appliance **21**.

The cardiac impulse sensor **140** detects the cardiac impulse of a person spaced apart from the sensor, and may include a potentiometric sensor or an electric field sensor.

The home network system **10** having the sensing module **22** including a non-contact cardiac impulse sensor **140** may produce output signals according to the absence/presence of a person in home to turn on/turn off the electronic device **21**.

The auxiliary sensor **150** may include an illuminance sensor or a temperature sensor.

The illuminance sensor may read the current variation of the sunlight in home in real time and transmit a value measured as interior illuminance to the control unit **130**.

The control unit **130** may generate a device operating signal, that is, an on/off signal of a lighting module **500** by combining output signals of the cardiac impulse sensor **140** and the illuminance sensor.

If the illuminance sensor is provided and if an amount of the sunlight represents a threshold or more even if the person is present indoor, the device operating signal for the lighting module **500** may not be generated.

The temperature sensor reads the variation of the interior temperature in real time and transmits the variation of the interior temperature to the control unit **130**.

The control unit **130** may generate a device operating signal, that is, an on/off signal of a lighting device, an air-conditioner, or a boiler by combining the output signals of the cardiac impulse sensor **140** and the temperature sensor.

If the temperature sensor is provided and if a temperature is within a threshold value range even if a person is present indoor, the device operating signal for a temperature adjusting device may not be generated.

Hereinafter, the sleep mode of a home network system including a sensing module **22** of FIG. **6** will be described with reference to FIG. **7**.

Referring to FIG. **7**, a user may set a sleep mode in the home network system **10**.

The sleep mode is a mode in which cardiac impulse and temperature variation of the human body are sensed by using the sensing module **22** to determine if a person is in a sleep state, so that an electronic device **21**, preferably, a lighting device is controlled.

If the sleep mode is applied to the home network system **10**, the sleep mode is set in the sensing module **22** (step **S200**).

If the sleep mode is set in the sensing module **22**, the sensing module **22** senses a base cardiac impulse and a base body temperature (step **S210**).

The base cardiac impulse is a cardiac impulse within a current sensing range when a human body is in a non-sleep state.

The base temperature refers to a temperature of a human body within a current sensing range when the human body is in the non-sleep state.

If the base cardiac impulse and the base body temperature are sensed completely, the base cardiac impulse and the base body temperature data are stored in the control unit **130** of the sensing module **22**. The base cardiac impulse and the base body temperature are stored in the home gateway system **40**.

The sensing module **22** sets the base cardiac impulse and the base body temperature to a heart rate and a body temperature in the non-sleep state, respectively, to define the cardiac impulse and the body temperature in the non-sleep state as threshold values for the determination of the sleep state/the non-sleep state of the human body (step **S220**).

Next, the sensing module **22** periodically senses the cardiac impulse of the human body as shown in FIG. **3** (step **S230**).

The sensing scheme of the sensing module **22** is the same as that described with reference to FIG. **3**.

In this case, if a present mode is set as the sleep mode, the threshold voltage of FIG. **3** becomes a threshold value of the base cardiac impulse, and determination is made regarding if the sensed voltage value of the cardiac impulse is different from the threshold voltage (step **S240**).

If the difference between the sensed voltage value and the threshold voltage is not made, or is within an error margin, the electronic device **21**, preferably, the lighting device is maintained in the turn-on state, so that the sensing of the cardiac impulse is periodically performed (step **S250**).

On the contrary, if the difference between the sensed voltage value and the threshold value is beyond the error margin, the sensing module **22** senses the temperature (step **S260**).

If the difference between the temperature and the threshold value is not made, or the difference between the temperature and the threshold value is within the error margin, the electronic device **21**, preferably, the lighting device is maintained in the turn-on state (step **S290**).

On the contrary, if the difference between the temperature value and the threshold value exceeds the error margin, the person is determined as being in the sleep state, so that the device turn-off signal to turn off the lighting device is transmitted (step **S295**).

The device turn-off/on signal may be directly transmitted to the lighting device from the sensing module **22** according to the home network system **10**, or may directly control the lighting device while control information is being transmitted to the gateway system **40** and recorded.

On the contrary, as shown in FIG. **3**, the device turn-off signal is transmitted to the home gateway system **40**, and the home gateway system **40** may transmit the device turn-off signal to the lighting device.

As described above, two sensing operations are performed through the cardiac impulse sensor **140** and the temperature sensor, so that accurate data can be found. In addition, the sleep mode is set, so that the lighting device can be controlled according to the sleep state and the non-sleep state of a person.

Meanwhile, the sensing module **22** may be provided separately from the electronic device **21** controlled according to the device operating signal as shown in FIG. **1**, or may be attached to the electronic device **21**.

Referring to FIG. **8**, an electronic device **21A** includes the sensing module **22** of FIG. **2**. For example, the electronic device **21A** includes a lighting device.

In other words, if the electronic device **21A** is a lighting device, a wireless communication module is required to make communication through the home gateway system **40** and a wireless network.

The electronic device **21A** of FIG. **6** serves as the wireless communication module and includes the sensing module **22**.

If the sensing module **22** is attached to the electronic device **21A**, the control unit **130** of the sensing module **22** receives output signals from the cardiac impulse sensor **140** and the auxiliary sensor **150** to generate a device operating signal, and the wireless processing unit **120** processes and outputs the device operating signal.

In this case, if the home gateway system **40** generates and outputs the turn-on signal according to the device operating signal, the sensing module **22** receives the turn-on signal and

transmits the turn-on signal to the control unit **130** of the connected electronic device **21**.

Accordingly, the electronic device **21** can receive the control signal by using the wireless processing unit **120** of the sensing module **22** without an additional wireless communication module, so that the cost can be reduced.

The sensing module **22** serving as a communication module constituting the lighting device is a detachable sensing module that is fixedly inserted into an insertion groove **511** of a lighting module **500** to transmit a control signal.

The lighting device includes an insertion groove in which a plurality of pins provided in an interface unit of the sensing module **22** are fixedly inserted.

As shown in FIG. 8, the insertion groove **511** may be exposed to the surface, and may be connected with the control unit **130** including a power supply unit of the lighting module **500**.

Since the sensing module **22** constituting the communication module of the lighting device is detachably assembled with the lighting module **500** as described above, the communication module can be reused when a lighting unit (not shown) or a power supply unit of the lighting module **500** is replaced with new one.

The sensing module **22** may constitute one housing, or may constitute one unit provided in the housing.

Meanwhile, the lighting module **500** includes a connector **575** provided at the upper portion thereof, and includes an inner case **570** provided in the lower portion thereof with an insertion part, a heat radiation body (not shown), into which an insertion part of the inner case **570** is inserted, a light emitting module unit to radiate heat downward of the heat radiation body and including a plurality of light emitting devices, a guide member **505** coupled with a lower peripheral portion of the heat radiation body and securely fixed to the heat radiation body of the light emitting module unit, a lens **510** between the guide member **505** and the light emitting module unit, and an external case **580** provided outside the heat radiation body.

The lens **510** includes a lens opening **512** into which a communication module **400** is inserted, and the sensing module **22** inserted through the lens opening **512** is connected with a connector of the power supply unit to transmit an output signal according to the control signal transmitted through the wireless network to the lighting module **500**.

Although embodiments have been described in detail, the scope of the disclosure is not limited thereto, but various variations and modifications made by those skilled in the art based on the basic concept of the disclosure defined in claims belong to the scope of the disclosure.

The invention claimed is:

1. A sensing device comprising:

a cardiac impulse sensor for sensing a cardiac impulse of a human body physically spaced apart from the cardiac impulse sensor to generate an output signal;

a control unit for periodically receiving the output signal of the cardiac impulse sensor, comparing the output signal with a threshold value, and generating a first operation signal of an electronic device, and transmitting the first operation signal to a processing unit; and the processing unit for processing and outputting the first operation signal to the electronic device according to the output signal of the cardiac impulse sensor,

wherein the sensing device is configured to be capable of operating in a sleep mode where:

if the sleep mode is set in the cardiac impulse sensor, the cardiac impulse sensor senses a base cardiac impulse;

the base cardiac impulse is a cardiac impulse of the human body existing within a present sensing range of the cardiac impulse sensor at a time when the sleep mode is set;

the control unit stores the output signal corresponding to the base cardiac impulse, sets the stored base cardiac impulse to a heart rate in a non-sleep state, and defines the base cardiac impulse as the threshold value used to determine a sleep state or a non-sleep state of the human body;

the cardiac impulse sensor continues to sense a continuing cardiac impulse of the human body; and

the control unit periodically compares the output signal corresponding to the continuing cardiac impulses to the threshold value and determines whether a difference between the output signal corresponding to the continuing cardiac impulse and the threshold value is within or greater than an error margin, determines whether a first reference time has elapsed after determination that the difference between the output signal corresponding to the continuing cardiac impulse and the threshold value is greater than the error margin, and generates the first operation signal if both the first reference time has elapsed and the difference between the output signal corresponding to the continuing cardiac impulse and the threshold value is greater than the error margin;

wherein the control unit does not generate the first operation signal in the event that the first reference time does not elapse or the difference is within the error margin, wherein the control unit turns the processing unit on when the first operation signal is generated,

wherein the cardiac impulse sensor is configured to be inserted into the electronic device, wherein the first operation signal directly controls the electronic device, and

wherein control information of the first operation signal to the electronic device is wirelessly transmitted to a home gateway system and recorded.

2. The sensing device of claim 1, wherein the cardiac impulse sensor generates the output signal by sensing variation of an electric field in a free space according to the cardiac impulse of the human body.

3. The sensing device of claim 1, further comprising an auxiliary sensor,

wherein the control unit generates the first operation signal by combining the output signal of the cardiac impulse sensor with an output signal of the auxiliary sensor.

4. The sensor of claim 3, wherein the auxiliary sensor includes an illuminance sensor that reads a present variation of sunlight in real time.

5. The sensor of claim 3, wherein the auxiliary sensor includes a temperature sensor that reads a variation of temperature in real time.

6. A network system, comprising:

the sensing device of claim 1;

the electronic device, operation of which is managed by the first operation signal of the sensing device; and the home gateway system comprising a wireless communication unit for wirelessly communicating with the processing unit, and a server.

7. The network system of claim 6, wherein the home gateway system communicates with the electronic device

11

and the processing unit through a wireless network, and the wireless network is formed through at least one of a ZigBee scheme, a Bluetooth scheme, a Z-wave scheme, and a Wi-Fi scheme.

8. The network system of claim 6, wherein the electronic device is formed in a dongle type such that the sensing device is inserted thereinto.

9. The network system of claim 6, wherein the sensing device includes an auxiliary sensor, the control unit generating the first operation signal based on the output signal from the cardiac impulse sensor and an output signal from the auxiliary sensor.

10. The network system of claim 9, wherein the auxiliary sensor includes an illuminance sensor that reads a present variation of sunlight in real time.

11. The network system of claim 9, wherein the auxiliary sensor includes a temperature sensor that reads a variation of temperature in real time.

12. A method of controlling an electronic device, the method comprising:

sensing a base cardiac impulse of a human body when a sleep mode is set in a cardiac impulse sensor, wherein the base cardiac impulse is a cardiac impulse of the human body existing within a present sensing range of the cardiac impulse sensor at a time when the sleep mode is set;

storing an output signal corresponding to the base cardiac impulse as a threshold value to establish a non-sleep state heart rate;

periodically sensing a continuing cardiac impulse of the human body within the present

sensing range after the threshold value is stored;

comparing an output signal corresponding to the continuing cardiac impulse to the threshold value;

determining whether a difference between the output signal corresponding to the continuing cardiac impulse and the threshold value is within or greater than an error margin;

12

determining whether a first reference time elapses upon determination that the difference between the output signal corresponding to the continuing cardiac impulse and the threshold value is greater than the error margin; and

generating an operation signal if both the first reference time has elapsed and the difference between the output signal corresponding to the continuing cardiac impulse and the threshold value is greater than the error margin,

wherein the operation signal is not generated when the first reference time does not elapse or the difference between the output signal corresponding to the continuing cardiac impulse and the threshold value is within the error margin,

wherein the operation signal directly controls the electronic device, and

wherein control information of the operation signal to the electronic device is wirelessly transmitted to a home gateway system and recorded.

13. The method of claim 12, wherein the generating of the operation signal comprises:

generating the operation signal configured to power the electronic device off.

14. The method of claim 13, wherein the generating of the operation signal comprises:

sensing a temperature of the human body if the difference between the output signal corresponding to the continuing cardiac impulse and the threshold value is greater than the error margin;

determining a sleep state of the human body according to the sensed temperature of the human body; and

generating the operation signal according to the sleep state of the human body.

* * * * *

专利名称(译)	传感器，网络系统及其使用的控制方法		
公开(公告)号	US10172546	公开(公告)日	2019-01-08
申请号	US14/442548	申请日	2013-11-28
[标]申请(专利权)人(译)	印诺泰克公司		
申请(专利权)人(译)	LG INNOTEK CO. , LTD.		
当前申请(专利权)人(译)	LG INNOTEK CO. , LTD.		
[标]发明人	CHO SUNG BAE LEE SANG HUN PARK JU BONG		
发明人	CHO, SUNG BAE LEE, SANG HUN PARK, JU BONG		
IPC分类号	A61B5/00 H04W4/80 A61B5/024 H04L12/12 A61B5/0205 A61B5/0402		
CPC分类号	A61B5/4809 A61B5/024 A61B5/02055 A61B5/02444 A61B5/0402 H04L12/12 H04W4/80 A61B5/4812 A61B2560/0242 A61B5/6891 A61B5/6898		
优先权	1020120137390 2012-11-29 KR 1020120138228 2012-11-30 KR		
其他公开文献	US20160277871A1		
外部链接	Espacenet		

摘要(译)

公开了一种传感器，其包括用于感测与心脏脉冲传感器间隔开的人体的心脏脉冲以产生输出信号的心脏脉冲传感器，以及用于处理和输出电子设备的操作信号的无线处理单元。心脏脉冲传感器的输出信号，包括传感器的网络系统，以及控制电子设备的方法。电子设备得到有效控制。

