




US 20170079595A1

(19) **United States**(12) **Patent Application Publication**
Fishler et al.(10) **Pub. No.: US 2017/0079595 A1**
(43) **Pub. Date: Mar. 23, 2017**(54) **SYSTEMS AND METHODS FOR
CLASSIFYING SIGNALS OF INTEREST IN A
CARDIAC RHYTHM MANAGEMENT
DEVICE**(52) **U.S. Cl.**
CPC **A61B 5/7264** (2013.01); **A61B 5/04012**
(2013.01); **A61N 1/365** (2013.01)(71) Applicant: **Pacesetter, Inc.**, Sunnyvale, CA (US)(57) **ABSTRACT**(72) Inventors: **Matthew G. Fishler**, Santa Cruz, CA
(US); **Gene A. Bornzin**, Simi Valley,
CA (US); **Benjamin T. Persson**,
Sunnyvale, CA (US); **Kenneth J.**
Carroll, Los Altos, CA (US)

The present disclosure provides systems and methods for classifying signals of interest in a cardiac rhythm management (CRM) device. A CRM device includes an intrinsic activation sensing circuit configured to pass signals falling within a first passband, a crosstalk sensing circuit configured to pass signals falling within a second passband, wherein the second passband contains higher frequencies than the first passband, and a computing device communicatively coupled to the intrinsic activation sensing circuit and the crosstalk sensing circuit, the computing device configured to classify a signal of interest as one of an intrinsic activation signal and a crosstalk signal based on whether the signal of interest is passed by the intrinsic activation sensing circuit and the crosstalk sensing circuit.

(21) Appl. No.: **14/862,810**(22) Filed: **Sep. 23, 2015****Publication Classification**(51) **Int. Cl.**
A61B 5/00 (2006.01)
A61N 1/365 (2006.01)
A61B 5/04 (2006.01)




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8

SYSTEMS AND METHODS FOR CLASSIFYING SIGNALS OF INTEREST IN A CARDIAC RHYTHM MANAGEMENT DEVICE

FIELD OF THE DISCLOSURE

[0001] The present disclosure relates generally to cardiac rhythm management devices, and more particularly to discriminating between intrinsic activation signals and crosstalk signals in cardiac rhythm management devices.

BACKGROUND ART

[0002] Multi-chamber cardiac rhythm management (CRM) devices include, for example, dual-chamber pacemakers and implantable defibrillators. In such devices, there is a risk that a pacing pulse (or similar pulse) delivered at one location within a patient's heart (e.g., the right atrium) may be detected by electrodes and associated sense circuitry in another location within the patient's heart (e.g., the right ventricle). This event is referred to as crosstalk.

[0003] This crosstalk, if not properly recognized, may be sensed and misclassified as an intrinsic local activation event, such as a premature ventricular contraction (PVC). In the event of such a misclassification, improper actions may be taken (e.g., withholding the next pace pulse as part of a PVC response algorithm). Accordingly, it is desirable to accurately discriminate crosstalk from intrinsic activations.

BRIEF SUMMARY OF THE DISCLOSURE

[0004] In one embodiment, the present disclosure is directed to a cardiac rhythm management (CRM) device. The CRM device includes an intrinsic activation sensing circuit configured to pass signals falling within a first passband, a crosstalk sensing circuit configured to pass signals falling within a second passband, wherein the second passband contains higher frequencies than the first passband, and a computing device communicatively coupled to the intrinsic activation sensing circuit and the crosstalk sensing circuit, the computing device configured to classify a signal of interest as one of an intrinsic activation signal and a crosstalk signal based on whether the signal of interest is passed by the intrinsic activation sensing circuit and the crosstalk sensing circuit.

[0005] In another embodiment, the present disclosure is directed to a method of classifying a signal of interest using a cardiac rhythm management (CRM) device. The method includes receiving the signal of interest at an intrinsic activation sensing circuit configured to pass signals falling within a first passband, receiving the signal of interest at a crosstalk sensing circuit configured to pass signals falling within a second passband, wherein the second passband contains higher frequencies than the first passband, determining, using a computing device, whether the signal of interest is passed by the intrinsic activation sensing circuit and the crosstalk sensing circuit, and classifying the signal of interest as one of an intrinsic activation signal and a crosstalk signal based on the determination.

[0006] In another embodiment, the present disclosure is directed to a computing device for use in classifying a signal of interest detected by a cardiac rhythm management (CRM) device. The computing device includes a memory device, and a processor communicatively coupled to the memory device, the processor configured to determine whether the

signal of interest is passed by an intrinsic activation sensing circuit configured to pass signals falling within a first passband, determine whether the signal of interest is passed by a crosstalk sensing circuit configured to pass signals falling within a second passband, wherein the second passband contains higher frequencies than the first passband, and classify the signal of interest as one of an intrinsic activation signal and a crosstalk signal based on whether the signal of interest is passed by the intrinsic activation sensing circuit and the crosstalk sensing circuit.

[0007] The foregoing and other aspects, features, details, utilities and advantages of the present disclosure will be apparent from reading the following description and claims, and from reviewing the accompanying drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

[0008] FIG. 1 is a block diagram of one embodiment of a cardiac rhythm management (CRM) device.

[0009] FIG. 2 is a frequency diagram including a passband for one embodiment of an intrinsic activation sensing circuit.

[0010] FIG. 3 is a frequency diagram including a passband for one embodiment of a crosstalk sensing circuit.

[0011] FIG. 4 is a block diagram of one embodiment of a computing device that may be used with the CRM device shown in FIG. 1.

[0012] FIG. 5 is a diagram illustrating a response to an intrinsic activation signal by the CRM device shown in FIG. 1.

[0013] FIG. 6 is a diagram illustrating a response to a crosstalk signal by the CRM device shown in FIG. 1.

[0014] FIG. 7 is a diagram illustrating a response to a crosstalk signal by the CRM device shown in FIG. 1.

[0015] FIG. 8 is a flow diagram of one embodiment of a method for classifying signals.

[0016] Corresponding reference characters indicate corresponding parts throughout the several views of the drawings.

DETAILED DESCRIPTION OF THE DISCLOSURE

[0017] The present disclosure provides a cardiac rhythm management (CRM) device with a crosstalk sensing circuit in addition to at least one intrinsic activation sensing circuit configured to sense typical intrinsic activity (e.g., P/R waves, evoked responses, etc.). The crosstalk sensing circuit has a passband that is shifted to significantly higher frequencies than the intrinsic activation sensing circuit. This enables the crosstalk sensing circuit to be more discriminative of relatively fast rising and falling edges of a locally-sensed crosstalk signal produced, for example, by a remote pacing pulse. Accordingly, signals detected by both the intrinsic activation sensing circuit and the crosstalk sensing circuit can, with a relatively high degree of confidence, be identified as crosstalk rather than intrinsic activity.

[0018] With reference to FIG. 1, a cardiac rhythm management (CRM) device is indicated generally at **100**. CRM device **100** may be, for example, a dual-chamber pacemaker, an implantable defibrillator, and/or a leadless medical device. Alternatively, CRM device **100** may be any type of assistive cardiac device capable of implementing the methods and systems described herein.

[0019] CRM device **100** senses local events via a pair of sensing electrodes **102**. The sensed events may be, for

example, intrinsic activation events and/or crosstalk events. The sensed signals are then processed by at least one intrinsic activation sensing circuit **104**. Intrinsic activation sensing circuit **104** may be, for example, an amplifier that has a predefined passband designed to provide desired signal-to-noise performance that passes relevant signals (e.g., intrinsic activations) while rejecting irrelevant signals (e.g., noise, baseline drift, etc.). An upper tail of the predefined passband may at least partially overlap with frequency content of a crosstalk signal. Accordingly, intrinsic activation sensing circuit **104** may inadvertently pass at least some energy content derived from crosstalk signals.

[0020] FIG. 2 is a frequency diagram **200** illustrating an example passband **202** for intrinsic activation sensing circuit **104**. Diagram **200** also shows an intrinsic activation band **204** and a crosstalk band **206** that represent the bands of potential frequency content of intrinsic activation signals and crosstalk signals, respectively. As shown in FIG. 2, passband **202** passes at least some crosstalk signals falling within crosstalk band **206**. The likelihood of detecting (i.e., passing) crosstalk signals is further increased as the sensitivity of intrinsic activation sensing circuit **104** is increased and/or the amplitude of the crosstalk signals are increased.

[0021] Accordingly, as shown in FIG. 1, in this embodiment, CRM device **100** includes a crosstalk sensing circuit **106** that has a passband shifted to higher frequencies, as compared to intrinsic activation sensing circuit **104**. As described herein, the passband of crosstalk sensing circuit **106** passes frequency content of crosstalk signals with greater sensitivity than intrinsic activation sensing circuit **104**. Further, a lower cutoff frequency of the passband of crosstalk sensing circuit **106** is sufficiently greater than the frequency content of intrinsic activation signals such that crosstalk sensing circuit **106** substantially rejects any intrinsic activation signals.

[0022] FIG. 3 is a frequency diagram **300** illustrating an example passband **302** for crosstalk sensing circuit **106**, as well as passband **202** for intrinsic activation sensing circuit **104**. As shown in FIG. 3, as compared to passband **202**, passband **302** is preferentially sensitive to signals in crosstalk band **206**. Further, passband **302** is insensitive to signals in intrinsic activation band **204**. Accordingly, in operation, passband **302** passes crosstalk signals and rejects intrinsic activation signals.

[0023] To accurately discriminate crosstalk due to a remote pacing pulse from local intrinsic activity, CRM device **100** takes advantage of the fact that each pacing pulse has nearly-instantaneous voltage discontinuities at its leading and trailing edges that are associated with the initiation and termination of that pacing pulse. These voltage discontinuities are not present in intrinsic activity events, and accordingly, can be used to discriminate between crosstalk and intrinsic activity. For example, the frequency content of intrinsic activity is almost always less than 300 Hertz (Hz). Therefore, passband **302** is shifted to significantly higher frequencies relative to passband **202**. That is, in this embodiment, passband **302** is located at frequencies associated with the fast rising and falling edges of a remote pacing pulse. Further, pacing pulses are generally much shorter than intrinsic activations. That is, pacing pulses may generally be between 0.1 milliseconds (ms) and 1.5 ms (e.g., 0.4-0.5 ms). This relatively short length also contributes to the pacing pulses being located in a higher frequency band.

[0024] Passband **302** extends from a lower cutoff frequency to an upper cutoff frequency. The lower cutoff frequency may be, for example, greater than or equal to 500 Hz, greater than or equal to 1000 Hz, greater than or equal to 5000 Hz, etc. The higher the lower cutoff frequency is, the more discriminatory passband **302** is of the voltage discontinuity in crosstalk due to a remote pacing pulse. In some embodiments, passband **302** may have a center frequency of approximately 25,000 Hz. Accordingly, passband **302** has a frequency range significantly higher than that of passband **202**.

[0025] Referring back to FIG. 1, in this embodiment, CRM device **100** includes a computing device **110** coupled to intrinsic activation sensing circuit **104** and crosstalk sensing circuit **106**. Computing device **110** determines, based on an output of intrinsic activation sensing circuit **104** and crosstalk sensing circuit **106**, whether a signal of interest is a crosstalk signal or an intrinsic activation signal, as described herein.

[0026] FIG. 4 is a block diagram of one embodiment of computing device **110** that may be used with CRM device **100** (shown in FIG. 1). Computing device **110** includes at least one memory device **410** and a processor **415** that is coupled to memory device **410** for executing instructions. In some embodiments, executable instructions are stored in memory device **410**. In the illustrated embodiment, computing device **110**, and by extension CRM device **100**, performs one or more operations described herein by programming processor **415**. For example, processor **415** may be programmed by encoding an operation as one or more executable instructions and by providing the executable instructions in memory device **410**.

[0027] Processor **415** may include one or more processing units (e.g., in a multi-core configuration). Further, processor **415** may be implemented using one or more heterogeneous processor systems in which a main processor is present with secondary processors on a single chip. In another illustrative example, processor **415** may be a symmetric multi-processor system containing multiple processors of the same type. Further, processor **415** may be implemented using any suitable programmable circuit including one or more systems and microcontrollers, microprocessors, reduced instruction set circuits (RISC), application specific integrated circuits (ASIC), programmable logic circuits, field programmable gate arrays (FPGA), and any other circuit capable of executing the functions described herein. In the illustrated embodiment, processor **415** determines, based on an output of intrinsic activation sensing circuit **104** and crosstalk sensing circuit **106**, whether a signal of interest is a crosstalk signal or an intrinsic activation signal, as described herein.

[0028] In the illustrated embodiment, memory device **410** is one or more devices that enable information such as executable instructions and/or other data to be stored and retrieved. Memory device **410** may include one or more computer readable media, such as, without limitation, dynamic random access memory (DRAM), read-only memory (ROM), electrically erasable programmable read-only memory (EEPROM), static random access memory (SRAM), a solid state disk, and/or a hard disk. Memory device **410** may be configured to store, without limitation, application source code, application object code, source

code portions of interest, object code portions of interest, configuration data, execution events and/or any other type of data.

[0029] Computing device 110, in the illustrated embodiment, includes a communication interface 440 coupled to processor 415. Communication interface 440 communicates with one or more remote devices, such as a clinician or patient programmer, or another CRM device. To communicate with remote devices, communication interface 440 may include, for example, a wired network adapter, a wireless network adapter, a radio-frequency (RF) adapter, and/or a mobile telecommunications adapter. For example, programmer to implant (“p2i”) and/or implant to implant (“i2i”) communication may be used. In some embodiments, an i2i sensing channel is leveraged to implement crosstalk sensing circuit 106.

[0030] FIGS. 5-7 schematically illustrate how CRM device 100 distinguishes between crosstalk signals and intrinsic activation signals using intrinsic activation sensing circuit 104 and crosstalk sensing circuit 106.

[0031] FIG. 5 illustrates a response by CRM device 100 to an intrinsic activation signal 502. Because intrinsic activation signal 502 is substantially within passband 202 of intrinsic activation sensing circuit 104 and has sufficient relative amplitude to exceed a sensing threshold of intrinsic activation sensing circuit 104, intrinsic activation signal 502 is passed (i.e., detected) by intrinsic activation sensing circuit 104, as indicated at block 504. However, intrinsic activation signal 502 is substantially outside of passband 302 of crosstalk sensing circuit 106. Accordingly, intrinsic activation signal 502 is not passed (i.e., not detected) by crosstalk sensing circuit 106, as indicated at block 506.

[0032] Computing device 110 determines whether the signal of interest was detected by crosstalk sensing circuit 106. As such, in the example of FIG. 5, because intrinsic activation signal 502 is detected by intrinsic activation sensing circuit 104, but is not detected by crosstalk sensing circuit 106, computing device 110 correctly identifies intrinsic activation signal 502 as an intrinsic activation signal, as indicated at block 508.

[0033] FIG. 6 illustrates a response by CRM device 100 to a crosstalk signal 602. Because crosstalk signal 602 partially overlaps the upper tail of passband 202 of intrinsic activation sensing circuit 104 and has sufficient relative amplitude to exceed a sensing threshold of intrinsic activation sensing circuit 104, crosstalk signal 602 is passed (i.e., detected) by intrinsic activation sensing circuit 104, as indicated at block 504.

[0034] Crosstalk signal 602 is also substantially within passband 302 of crosstalk sensing circuit 106 and has sufficient relative amplitude to exceed a sensing threshold of crosstalk sensing circuit 106. Accordingly, crosstalk signal 602 is also passed (i.e., detected) by crosstalk sensing circuit 106, as indicated at block 506. Crosstalk signal 602 is detected substantially concurrently by both intrinsic activation sensing circuit 104 and by crosstalk sensing circuit 106 (e.g., taking into account some timing tolerance to account for different lags between reaching detection thresholds by intrinsic activation sensing circuit 104 and crosstalk sensing circuit 106). Because crosstalk signal 602 is detected by intrinsic activation sensing circuit 104 and crosstalk sensing circuit 106, computing device 110 correctly identifies crosstalk signal 602 as a crosstalk signal (as indicated at block

608), and rejects the false positive detection by intrinsic activation sensing circuit 104 of crosstalk signal 602 as an intrinsic activation signal.

[0035] FIG. 7 illustrates a response by CRM device 100 to a crosstalk signal 702. Unlike crosstalk signal 602, crosstalk signal 702 partially overlaps the upper tail of passband 202 of intrinsic activation sensing circuit 104, but does not have sufficient relative amplitude to exceed a sensing threshold of intrinsic activation sensing circuit 104. Accordingly crosstalk signal 702 is rejected (i.e., not detected) by intrinsic activation sensing circuit 104, as indicated at block 504.

[0036] Crosstalk signal 702 is also substantially within passband 302 of crosstalk sensing circuit 106 and has sufficient relative amplitude to exceed a sensing threshold of crosstalk sensing circuit 106. Accordingly, crosstalk signal 702 is also passed (i.e., detected) by crosstalk sensing circuit 106, as indicated at block 506. Because crosstalk signal 702 is not detected by intrinsic activation sensing circuit 104 but is detected by crosstalk sensing circuit 106, computing device 110 correctly identifies crosstalk signal 702 as a crosstalk signal, as indicated at block 708.

[0037] FIG. 8 is a flow diagram of one embodiment of a method 800 for classifying signals that may be performed, for example, using CRM device 100 (shown in FIG. 1). At block 802, a signal of interest is detected by intrinsic activation sensing circuit 104. At block 804, computing device 110 determines whether the signal of interest was also detected substantially concurrently by crosstalk sensing circuit 106. If the signal of interest was detected by crosstalk sensing circuit 106, it is identified as a crosstalk signal at block 806 and processed accordingly (e.g., ignoring the signal, initiating a crosstalk signal processing algorithm, etc.). Alternatively, if the signal of interest was not detected by crosstalk sensing circuit 106, it is identified as an intrinsic activation signal at block 808 and processed accordingly.

[0038] Based on the classification of a signal, appropriate action may be taken (e.g., by a physician, or by an algorithm operating on the CRM device). For example, pacing of a patient's heart may be adjusted based on whether the signal is classified as a crosstalk signal or an intrinsic activation signal. Alternatively, any other suitable actions may be taken in response to the classification.

[0039] The systems and methods described herein facilitate accurately classifying signals of interest in a CRM device as either intrinsic activation signals or crosstalk signals. The signals are discriminated by using both an intrinsic activation sensing circuit and a crosstalk sensing circuit. By accurately classifying signals, appropriate action may be taken to address the signals, improving patient care.

[0040] Although certain embodiments of this disclosure have been described above with a certain degree of particularity, those skilled in the art could make numerous alterations to the disclosed embodiments without departing from the spirit or scope of this disclosure. All directional references (e.g., upper, lower, upward, downward, left, right, leftward, rightward, top, bottom, above, below, vertical, horizontal, clockwise, and counterclockwise) are only used for identification purposes to aid the reader's understanding of the present disclosure, and do not create limitations, particularly as to the position, orientation, or use of the disclosure. Joinder references (e.g., attached, coupled, connected, and the like) are to be construed broadly and may include intermediate members between a connection of elements and relative movement between elements. As such,

joinder references do not necessarily infer that two elements are directly connected and in fixed relation to each other. It is intended that all matter contained in the above description or shown in the accompanying drawings shall be interpreted as illustrative only and not limiting. Changes in detail or structure may be made without departing from the spirit of the disclosure as defined in the appended claims.

[0041] When introducing elements of the present disclosure or the preferred embodiment(s) thereof, the articles “a”, “an”, “the”, and “said” are intended to mean that there are one or more of the elements. The terms “comprising”, “including”, and “having” are intended to be inclusive and mean that there may be additional elements other than the listed elements.

[0042] As various changes could be made in the above constructions without departing from the scope of the disclosure, it is intended that all matter contained in the above description or shown in the accompanying drawings shall be interpreted as illustrative and not in a limiting sense.

What is claimed is:

1. A cardiac rhythm management (CRM) device comprising:

- an intrinsic activation sensing circuit configured to pass signals falling within a first passband;
- a crosstalk sensing circuit configured to pass signals falling within a second passband, wherein the second passband contains higher frequencies than the first passband; and
- a computing device communicatively coupled to the intrinsic activation sensing circuit and the crosstalk sensing circuit, the computing device configured to classify a signal of interest as one of an intrinsic activation signal and a crosstalk signal based on whether the signal of interest is passed by the intrinsic activation sensing circuit and the crosstalk sensing circuit.

2. The CRM device of claim 1, wherein to classify a signal of interest, the computing device is configured to classify the signal of interest as an intrinsic activation signal when the signal of interest is passed by the intrinsic activation sensing circuit and not passed by the crosstalk sensing circuit.

3. The CRM device of claim 1, wherein to classify a signal of interest, the computing device is configured to classify the signal of interest as a crosstalk signal when the signal of interest is passed by the intrinsic activation sensing circuit and passed by the crosstalk sensing circuit.

4. The CRM device of claim 1, wherein to classify a signal of interest, the computing device is configured to classify the signal of interest as a crosstalk signal when the signal of interest is not passed by the intrinsic activation sensing circuit and passed by the crosstalk sensing circuit.

5. The CRM device of claim 1, further comprising a pair of sensing electrodes communicatively coupled to the intrinsic activation sensing circuit and the crosstalk sensing circuit.

6. The CRM device of claim 1, wherein the second passband has a lower cutoff frequency greater than or equal to 500 Hz.

7. The CRM device of claim 1, wherein the second passband has a lower cutoff frequency greater than or equal to 1000 Hz.

8. The CRM device of claim 1, wherein the second passband has a center frequency equal to approximately 25,000 Hz.

9. A method of classifying a signal of interest using a cardiac rhythm management (CRM) device, the method comprising:

receiving the signal of interest at an intrinsic activation sensing circuit configured to pass signals falling within a first passband;

receiving the signal of interest at a crosstalk sensing circuit configured to pass signals falling within a second passband, wherein the second passband contains higher frequencies than the first passband;

determining, using a computing device, whether the signal of interest is passed by the intrinsic activation sensing circuit and the crosstalk sensing circuit; and

classifying the signal of interest as one of an intrinsic activation signal and a crosstalk signal based on the determination.

10. The method of claim 9, wherein classifying the signal of interest comprises classifying the signal of interest as an intrinsic activation signal when the signal of interest is passed by the intrinsic activation sensing circuit and not passed by the crosstalk sensing circuit.

11. The method of claim 9, wherein classifying the signal of interest comprises classifying the signal of interest as a crosstalk signal when the signal of interest is passed by the intrinsic activation sensing circuit and passed by the crosstalk sensing circuit.

12. The method of claim 9, wherein classifying the signal of interest comprises classifying the signal of interest as a crosstalk signal when the signal of interest is not passed by the intrinsic activation sensing circuit and passed by the crosstalk sensing circuit.

13. The method of claim 9, wherein receiving the signal of interest at a crosstalk sensing circuit comprises receiving the signal of interest at a crosstalk sensing circuit in which the second passband has a lower cutoff frequency greater than or equal to 500 Hz.

14. The method of claim 9, further comprising pacing a patient's heart based on the classification of the signal of interest.

15. The method of claim 9, wherein receiving the signal of interest at a crosstalk sensing circuit comprises receiving the signal of interest at a crosstalk sensing circuit in which the second passband has a center frequency equal to approximately 25,000 Hz.

16. A computing device for use in classifying a signal of interest detected by a cardiac rhythm management (CRM) device, the computing device comprising:

a memory device; and

a processor communicatively coupled to the memory device, the processor configured to:

determine whether the signal of interest is passed by an intrinsic activation sensing circuit configured to pass signals falling within a first passband;

determine whether the signal of interest is passed by a crosstalk sensing circuit configured to pass signals falling within a second passband, wherein the second passband contains higher frequencies than the first passband; and

classify the signal of interest as one of an intrinsic activation signal and a crosstalk signal based on

whether the signal of interest is passed by the intrinsic activation sensing circuit and the crosstalk sensing circuit.

17. The computing device of claim **16**, wherein to classify the signal of interest, the processor is configured to classify the signal of interest as an intrinsic activation signal when the signal of interest is passed by the intrinsic activation sensing circuit and not passed by the crosstalk sensing circuit.

18. The computing device of claim **16**, wherein to classify the signal of interest, the processor is configured to classify the signal of interest as a crosstalk signal when the signal of interest is passed by the intrinsic activation sensing circuit and passed by the crosstalk sensing circuit.

19. The computing device of claim **16**, wherein to classify the signal of interest, the processor is configured to classify the signal of interest as a crosstalk signal when the signal of interest is not passed by the intrinsic activation sensing circuit and passed by the crosstalk sensing circuit.

20. The computing device of claim **16**, wherein to determine whether the signal of interest is passed by a crosstalk sensing circuit, the processor is configured to determine whether the signal of interest is passed by a crosstalk sensing circuit in which the second passband has a lower cutoff frequency greater than or equal to 500 Hz.

* * * * *

专利名称(译)	用于对心律管理设备中的感兴趣信号进行分类的系统和方法		
公开(公告)号	US20170079595A1	公开(公告)日	2017-03-23
申请号	US14/862810	申请日	2015-09-23
[标]申请(专利权)人(译)	标兵		
申请(专利权)人(译)	PACESETTER , INC.		
当前申请(专利权)人(译)	PACESETTER , INC.		
[标]发明人	FISHLER MATTHEW G BORNZIN GENE A PERSSON BENJAMIN T CARROLL KENNETH J		
发明人	FISHLER, MATTHEW G. BORNZIN, GENE A. PERSSON, BENJAMIN T. CARROLL, KENNETH J.		
IPC分类号	A61B5/00 A61N1/365 A61B5/04		
CPC分类号	A61B5/7264 A61N1/365 A61B5/04012 A61B5/04014 A61N1/36507 G16H50/20		
其他公开文献	US10182765		
外部链接	Espacenet USPTO		

摘要(译)

本公开提供了用于对心律管理 (CRM) 设备中的感兴趣信号进行分类的系统和方法。 CRM设备包括：内部激活感测电路，被配置为传递落在第一通带内的信号;串扰感测电路，被配置为传递落入第二通带内的信号，其中，第二通带包含比第一通带更高的频率，以及计算设备，通信地耦合到固有激活感测电路和串扰感测电路的计算设备被配置为基于感兴趣的信号是否通过固有激活感测电路来将感兴趣的信号分类为固有激活信号和串扰信号之一。串扰传感电路。

