



US009775527B2

(12) **United States Patent**
Phan et al.

(10) **Patent No.:** **US 9,775,527 B2**
(45) **Date of Patent:** **Oct. 3, 2017**

(54) **METHOD AND APPARATUS FOR
SIMULATION OF PRESSURE TRANSDUCER
FOR MEASUREMENT OF BLOOD
PRESSURE**

5/7278 (2013.01); A61B 2560/0223 (2013.01);
A61B 2560/045 (2013.01)

(58) **Field of Classification Search**

CPC A16B 5/02141
See application file for complete search history.

(71) Applicant: **Edwards Lifesciences Corporation**,
Irvine, CA (US)

(56) **References Cited**

(72) Inventors: **Luong N. Phan**, San Clemente, CA
(US); **Feras Al Hatib**, Irvine, CA (US);
Mark A. Konno, Laguna Beach, CA
(US); **Lindon A. Baker**, Yorba Linda,
CA (US); **Richard A. Gros**, Yorba
Linda, CA (US)

U.S. PATENT DOCUMENTS

3,868,679 A	2/1975	Arneson
2003/0045781 A1	3/2003	Rosenheimer
2012/0071744 A1	3/2012	Euliano, II et al.
(Continued)		

(73) Assignee: **Edwards Lifesciences Corporation**,
Irvine, CA (US)

OTHER PUBLICATIONS

Int'l. Search Report, Dec. 17, 2013.

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 156 days.

Primary Examiner — Clayton E Laballe

Assistant Examiner — Dennis Hancock

(21) Appl. No.: **14/710,329**

(74) *Attorney, Agent, or Firm* — Blakely, Sokoloff, Taylor
& Zafman LLP; Eric T. King

(22) Filed: **May 12, 2015**

(57) **ABSTRACT**

(65) **Prior Publication Data**

US 2016/0324428 A1 Nov. 10, 2016

Disclosed is an apparatus, system, and method for utilizing a pressure transducer simulator that is configured for use with a pressure sensor device and a patient monitoring device. The pressure transducer simulator may be configured to generate a simulation of the output of an analog pressure sensing device to be compatible with the patient monitoring device. The simulation may be based upon a pressure signal received from the pressure sensor device. In one embodiment, the pressure transducer simulator includes a digital potentiometer that is configured to generate an analog signal based upon the pressure signal received from the pressure sensor device and wherein the digital potentiometer is configured to transmit the analog signal to the patient monitoring device.

Related U.S. Application Data

(63) Continuation of application No.
PCT/US2013/054558, filed on Aug. 12, 2013.

(60) Provisional application No. 61/695,742, filed on Aug.
31, 2012.

(51) **Int. Cl.**


A61B 5/00 (2006.01)

A61B 5/021 (2006.01)

(52) **U.S. Cl.**

CPC **A61B 5/02141** (2013.01); **A61B 5/0002**
(2013.01); **A61B 5/021** (2013.01); **A61B**

17 Claims, 3 Drawing Sheets




(56)

References Cited

U.S. PATENT DOCUMENTS

2012/0316794 A1 12/2012 Goh et al.
2014/0182352 A1* 7/2014 Hersh A61B 5/02141
73/1.57

* cited by examiner

**FIG. 1**




FIG. 2




FIG. 3

1

METHOD AND APPARATUS FOR SIMULATION OF PRESSURE TRANSDUCER FOR MEASUREMENT OF BLOOD PRESSURE

BACKGROUND

Field

The present invention relates to a pressure transducer simulator that is configured for use with a pressure sensor device and a patient monitoring device. The pressure transducer simulator may be configured to generate a simulation of the output of an analog pressure sensing device to be compatible with the patient monitoring device.

Relevant Background

A standard analog pressure device for measuring blood pressure (typically known as a Disposable Pressure Transducer or DPT) includes a pressure transducer, which is basically a bridge circuit in which a reference signal is applied to one branch of the bridge and the pressure signal is obtained on the other branch. The pressure sensing element (typically a piezoelectric sensor) is placed in one, two, three or four of the four arms of the bridge. The pressure sensing element is basically a variable resistance that varies with the applied pressure. The analog pressure sensing device is usually connected through a fluid filled system to a catheter placed in a vein or an artery, where the pressure pulsations are captured by the pressure sensing element. The analog pressure sensing device is typically for blood pressure monitoring.

The other side of the analog pressure sensing device is typically connected to a measurement instrument, typically a bedside monitor, a blood pressure monitor, or any other monitor that uses the blood pressure signal (e.g., pulse contour Cardiac Output monitors). A reference signal to the analog pressure sensing device is typically provided by the measurement instrument and it is typically used by the instrument to scale the measured blood pressure signal. Different monitors have different reference signals. The reference signal may be either DC or AC and may be typically in the 1-10 Volt range. In AC-based instruments, the operating frequency typically ranges from a few kHz up to 5 kHz.

Unfortunately, standard monitors are generally configured to only interact with particular types of analog pressure sensing devices (e.g., blood pressure devices) and cannot interact with waveforms from other types of pressure sensing devices, such as digital non-invasive blood pressure monitors (NIBMs).

SUMMARY

Embodiments of the invention may relate to an apparatus, system, and method for utilizing a pressure transducer simulator that is configured for use with a pressure sensor device and a patient monitoring device. The pressure transducer simulator may be configured to generate a simulation of the output of an analog pressure sensing device to be compatible with the patient monitoring device. The simulation may be based upon a pressure signal received from the pressure sensor device. In one embodiment, a pressure transducer simulator includes a digital potentiometer that is configured to generate an analog signal based upon the pressure signal received from the pressure sensor device and

2

wherein the digital potentiometer is configured to transmit the analog signal to the patient monitoring device.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a diagram of a system in which embodiments of the invention related to a pressure transducer simulator may be practiced.

FIG. 2 is a block diagram illustrating components of the pressure transducer simulator, according to one embodiment of the invention.

FIG. 3 is a diagram illustrating examples of circuit components of the pressure transducer simulator, according to one embodiment of the invention.

DETAILED DESCRIPTION

Embodiments of the invention generally relate to an apparatus, system, and method to simulate the function of a standard analog pressure sensor. In particular, an apparatus, system, and method is provided that allows for broad and universal connectivity to existing pressure monitoring devices, regardless of the type of reference signal (AC or DC) and/or the amplitude of the reference signal, and regardless of the type of input signal (e.g., analog or digital). Embodiments of the invention have many practical applications.

In particular, embodiments of the invention provide an easy and universal connectivity to all types of blood pressure measuring monitors. This capability of universal connectivity makes it possible to connect various continuous noninvasive blood pressure monitors (NIBMs) (i.e., blood pressure sensing devices) to already existing and clinically adopted blood pressure measuring monitors, which are currently used for invasive measurements only (i.e., from analog blood pressure sensing devices, or disposable pressure transducers—DPTs).

Many new technologies for noninvasive continuous measurement of blood pressure (i.e., digital pressure sensor devices) are available today. The possibility of connecting those various technologies to standard patient monitoring devices is an easy and low cost way to provide noninvasive measurements in the clinical setting. Embodiments of the invention allow for the noninvasive pressure signal to be directly acquired through the regular pressure transducer connector with no need to develop special modules for the different blood pressure measuring devices or patient monitors. This allows the display of the noninvasive pressure measurements (i.e., measurements from noninvasive pressure sensor devices) on the patient monitoring device in the exact same way as the currently used invasive pressure measurements (i.e., analog measurements from analog pressure sensor devices, or DPTs).

Embodiments of the invention to achieve this functionality will be hereinafter described. It should be noted that although digital pressure sensor devices and analog pressure sensor devices in conjunction with a patient monitoring device have been previously described for use with blood pressure measurements that embodiments of the invention may relate to the pressure measurements of many different types of patient measurements (e.g., cardiac measurements, breathing measurements, intracranial pressure measurements etc.)

In order to achieve this functionality, with reference to FIGS. 1 and 2, in one embodiment, a pressure transducer simulator integrated into a noninvasive blood pressure measuring instrument **202** may be configured for use with an

invasive or noninvasive blood pressure module **204** and a patient monitoring device **206**. The patient monitoring device **206** may include a display screen to show a patient's blood pressure reading. The pressure transducer simulator integrated in the noninvasive blood pressure measuring instrument **202** may be directly connected to a pre-existing connector of the invasive blood pressure module of the patient monitoring device **206**.

The pressure transducer simulator in measuring instrument **202** may be configured to generate a simulation of the output of an analog pressure sensing device compatible with the monitoring device **206**, wherein the simulation is based upon a pressure signal **208** received from the pressure sensor device **204**. The pressure transducer simulator in **202** may comprise a digital potentiometer **220** and a processor **224**, as well as other components to be hereinafter described. The pressure transducer simulator in measuring instrument **202** will hereinafter be referred to as pressure transducer simulator **202**.

In one embodiment, the pressure transducer simulator **202** may include a digital potentiometer **220** that is configured to generate an analog signal **230/232** that is transmitted to the patient monitoring device **206** for display on the patient monitoring device **206**. It should be noted that the connections of digital or analog signals between a patient (not shown) to digital or analog pressure sensor devices **204**, to pressure transducer simulator **202**, to patient monitoring device **206**, etc., may be through wired or wireless connections. Further, as will be described, the pressure transducer simulator **202** may be utilized with either digital or analog pressure sensing devices **204** that transmit digital or analog pressure signals **208**. Also, it should be appreciated that pressure sensing device **204** may relate to the pressure measurements of many different types of patient measurements (e.g., blood pressure measurements, cardiac measurements, breathing measurements, intracranial pressure measurements etc.) and may communicate in a wired or wireless manner and may be connected to different patient body parts (e.g., finger, ear, nose, arm, etc.). Any type of commonly utilized pressure sensing device **204** may be utilized with embodiments of invention utilizing the pressure transducer simulator.

With additional reference to FIG. 3, digital potentiometer **220** may include first and second adjustable wipers **222** and **223**. The first and second adjustable wipers **222** and **223** are adjustable to select the resistances of the first and second adjustable wipers **222** and **223**. In this way, the analog output voltage signals (+SIG and -SIG) **230** and **232** may be selected and transmitted to the patient monitoring device **206**. It should be noted that a connector **239** may connect the circuitry of the pressure transducer simulator **202** to the patient monitoring device **206**. This may be to a pre-existing connector of the patient monitoring device **206**. In this way, the pressure transducer simulator **202** is directly attachable to existing patient monitoring devices **206** and can provide signal inputs from either digital pressure sensor devices **204** or analog pressure sensor devices **205**, as will be described. It should be noted that only one digital pressure sensor device **204** or one analog pressure sensor device **205** may be attached at a given time.

As is known to those of skill in the art, a digital potentiometer may be a digitally controlled electronic component that mimics the analog functions of a potentiometer. In particular, the resistance of the wipers may be digitally controlled such that a desired voltage is outputted.

In one embodiment, processor **224** may determine digital wiper settings for the adjustable wipers **222** and **223** to select

the resistances of the digital wipers **222** and **223** and the analog output voltages (+SIG and -SIG) **230** and **232** of the digital potentiometer **200**. Processor **224** may transmit digital wiper settings **209** and **210** to each of the adjustable wipers **222** and **223** to set their analog output voltages (+SIG and -SIG) **230** and **232**.

In one embodiment, processor **224** of the pressure transducer simulator **202** may implement an auto-zeroing command. For example, an auto-zeroing button **243** may be configured for pressing by a medical technician to implement the auto-zeroing command. When the auto-zeroing command is implemented, each of the adjustable wipers **222** and **223** may be adjusted by digital wiper settings **209** and **210** selected by processor **224** and transmitted to the adjustable wipers **222** and **223** to set the resistances of the adjustable wipers **222** and **223** such that the analog signal produced by the digital potentiometer **220** and transmitted to the monitoring device **206** is approximately zero.

As an example, the resistances of the adjustable wipers **222** and **223** are controlled by processor **224** to set the resistances of the digital potentiometer **220** such that the analog signals (+SIG and -SIG) **230** and **232** produced by the digital potentiometer **220** are equal to one another such that they subtract each other out and are approximately zero. As one particular example, digital wiper settings **209** and **210** may be selected by processor **224** and transmitted to the adjustable wipers **222** and **223** to set the resistances of the adjustable wipers **222** and **223** to .5, then the analog signal produced by each of the adjustable wipers **222** and **223** of the digital potentiometer **220** would be .5*+SIG and .5*-SIG, respectively, such that (.5*+SIG)-(.5*-SIG) transmitted to the patient monitoring device **206** results in an approximately zero signal input. Based upon the auto-zeroing function, the patient monitoring device **206** can calibrate itself to the pressure transducer simulator **202**.

Processor **224** may also implement an operate command. For example, an operate button **244** configured for pressing may be pressed by a medical technician and the operate command implemented. After implementation of the operate command, the digital potentiometer **220** produces analog signals (+SIG and -SIG) **230** and **232** based upon digital signals **208** from the digital pressure sensor device **204** and the digital wiper settings **209** and **210** selected by the processor **224**. The analog signals (+SIG and -SIG) **230** and **232** are transmitted to the patient monitoring device **206**. It should be appreciated that the use of an auto-zeroing button **243** and an operate button **244** to implement auto-zeroing commands and operate commands by processor **224** are merely examples, and that processor **224** may implement these commands automatically without the use of input commands from buttons or other input mechanisms. Further, a wide variety of different types of command input mechanisms at the pressure transducer simulator or at other locations may be utilized.

In particular, processor **224** may determine digital wiper settings **209** and **210** for the adjustable wipers **222** and **223** to select the resistances of the digital wipers **222** and **223** and the analog output voltages (+SIG and -SIG) **230** and **232** of the digital potentiometer **200**. Processor **224** may transmit digital wiper settings **209** and **210** to each of the adjustable wipers **222** and **223** to select the analog output voltages (+SIG and -SIG) **230** and **232**. In this way, processor **224** can ensure that analog output voltages (+SIG and -SIG) **230** and **232** match or are approximately equivalent to the digital pressure signal **208** from the digital pressure sensor device **204**.

The previously-described pressure transducer simulator **202** of FIG. 3 accepts the DC or AC excitation voltage typically applied to an industry standard bridge type disposable pressure transducer (DPT) and outputs a standard differential signal of 5 μ V per mmHg per volt of excitation. The pressure transducer simulator **202** accepts any excitation voltage within the range of -10 volts to +10 volts at pin **1** of connector **239** (signal name +EX) referenced to the excitation reference at pin **4** connector **239** (signal name -EX). The excitation can be constant or varying.

The digital potentiometer **220** is applied in a potentiometer voltage divider mode, analogous to a mechanical potentiometer. Digital potentiometer **220** performs an electronic adjustment function, similar to a mechanical potentiometer, but with enhanced resolution, solid state reliability, and strong temperature coefficient performance. In particular, as previously described, the desired wiper position of the adjustable wipers **222** and **223** for varying the resistance of the resistors is commanded digitally by processor **224**.

The pressure transducer simulator **202** is universally compatible with a myriad of commercially available patient monitoring devices **206**, because the differential output signals between +SIG and -SIG **230** and **232** are ratiometric to the instantaneous applied excitation voltage at 5 μ V per mmHg per volt of excitation, and the differential output signals **230** and **232** ride on a common mode level tracking 50% of the instantaneous applied excitation voltage. Furthermore the output differential resistance of the pressure transducer simulator circuit, which is determined by resistors **R107** and **R108** is equivalent to the actual, differential resistance of the standard DPTs (the measurement arms of the bridge). Additionally, the resistance of the excitation path, which is determined by resistors **R101**, **R102**, **R103**, **R104** and the resistances **222** and **223** of the digital potentiometer **220** is equivalent to the excitation resistance of the standard DPTs (the excitation arms of the bridge).

Resistor divider **R101**, **R102**, **R103**, and **R104** scales the applied excitation voltage (+EX **240** and -EX **242**) down based on the desired full scale differential output voltage. Advantageously, the circuit "ground" reference point (**ISO1_GND 250**) is at the midpoint of the applied excitation voltage. This will also be the midpoint, or common mode level, of the differential output signal. Thus, from the circuit perspective, the common mode voltage is zero, or ground, reducing circuit complexity.

As previously described, the pressure to be represented at the output is set by adjusting the adjustable wiper positions **222** and **223** of the digital potentiometer **220** under the control of processor **224**. Because of the known excitation voltage of 5 μ V per mmHg per volt of excitation utilized for patient monitoring devices and the known parameters of the wipers of the digital potentiometer **220**, processor **224** implements a scaling function based upon the pressure signal **208** from the digital pressure sensor device **204** to select the wiper positions **222** and **223** of the digital potentiometer **220** to ensure that analog output voltages (+SIG and -SIG) **230** and **232** match or are approximately equivalent to the digital pressure signal **208** from the digital pressure sensor device **204**. To provide an example, assuming a digital input **208** from digital pressure sensor device **204** of 100 mmHg or 1V, processor **224** would determine and transmit digital wiper settings **209** and **210** to the adjustable wipers **222** and **223** to select the resistances of the digital wipers **222** and **223** such that the analog output voltages (+SIG and -SIG) **230** and **232** of the digital potentiometer match and are approximately equivalent to the digital input. As an example, +SIG **230** may be set to 300

mmHg or 3V and -SIG **232** may be set to 200 mmHg or 2V such that these values are received by the patient monitoring device **206**. In this example, the ultimate value would be (+SIG-(-SIG)) which is 100 mmHg or 1V that is equivalent to the digital input **208** from digital pressure sensor device **204**. In this way, processor **224** can ensure that analog output voltages (+SIG and -SIG) **230** and **232** result in a match to the digital pressure input **208** from the digital pressure sensor device **204**.

Further, as previously described, the pressure simulator transducer **202**, in the same way, operates with analog pressure sensor devices. For example, analog pressure sensor device **205** may output a 100 mmHg or 1V analog input signal **208**. Analog to digital converter (ADC) **207** may convert this to a digital input signal for use by processor **224**, as previously described. It should be noted that ADC **207** may be a part of processor **224** or may be a separate component of the pressure transducer simulator **202** connected to processor **224**. In the same way, processor **224** would determine and transmit digital wiper settings **209** and **210** to the adjustable wipers **222** and **223** to select the resistances of the digital wipers **222** and **223** such that the analog output voltages (+SIG and -SIG) **230** and **232** of the digital potentiometer match and are approximately equivalent to the digital input. As an example, +SIG **230** may be set to 300 mmHg or 3V and -SIG **232** may be set to 200 mmHg or 2V such that these values are received by the patient monitoring device **206**. In this example, the ultimate value would be (+SIG-(-SIG)) which is 100 mmHg or 1V that is equivalent to the initial analog input from the analog pressure device **205**. In this way, processor **204** can ensure that analog output voltages (+SIG and -SIG) **230** and **232** result in a match to the analog pressure input **208** from the analog pressure device **205**.

Further, buffers **235** and **236** may be coupled to the digital potentiometer **220** to provide unity gain buffering for the adjustable wipers **222** and **223**. It should be appreciated by those of skill in the art that because the digital potentiometer **220** is capable of only limited current and may have relatively high and non-constant source impedance, that the voltages at the wipers **222** may be unity gain buffered by buffers **235** and **236**. Those skilled in the art will understand that the buffers **235** and **236** may have some offset voltage. Excessive offset voltage could result in unacceptable zero offset at the differential output, potentially resulting in rejection by some patient monitoring devices **206** such that resistor dividers **R105**, **R107** and **R106**, **R108** may be used to reduce the zero offset of the buffers **235** and **236** by a factor of approximately **13**, ensuring low zero offset at the output. The **R107** and **R108** components of the dividers also provide a 300 ohm resistive path between +SIG and -SIG to satisfy a detection requirement of some commercially available pressure monitoring instruments. Moreover, in this previously described implementation, the desired output may be 5 μ V per mmHg per volt of excitation, with 300 mmHg as full scale, so the full scale differential output is 1500 μ V per volt of excitation, and the ratio of **R101** to **R102** is established taking into account the **R105**, **R107** divider. Persons of ordinary skill in the art will recognize that other divider ratios could be used at **R101** and **R102** to accommodate other full scale ranges, or other ratios at **R105**, **R107**.

Additionally, the pressure transducer simulator **202** circuit may contain an additional feature to assist with presence detection by industry standard pressure monitoring instruments. **R109** may present a current load on the excitation output (+EX **240**) of the pressure monitoring instrument which is needed by some instruments to ensure detection.

Thus, embodiments of the invention relate to a pressure transducer simulator **202** that allows for broad and universal connectivity of a patient monitoring device **206** to both digital pressure sensor devices **204** and analog pressure sensor devices **205**, regardless of the excitation voltages of patient monitoring device and/or the type of input signals (e.g., analog or digital) from either digital or analog pressure sensor devices.

In particular, embodiments of the invention provide an easy and universal connectivity to all types of blood pressure measuring monitors. This capability of universal connectivity makes it possible to connect various continuous noninvasive blood pressure monitors (NIBMs) (i.e., blood pressure sensing devices) to already existing and clinically adopted blood pressure measuring monitors, which are currently used for invasive measurements only (i.e., from analog blood pressure sensing devices, or disposable pressure sensors—DPTs). Embodiments of the invention allow for the noninvasive pressure signal to be directly acquired through the regular pressure transducer connector with no need to develop special modules for the different blood pressure measuring devices or patient monitors. This allows the display of the noninvasive pressure measurements (i.e., measurements from noninvasive pressure sensor devices) on the patient monitoring device in the exact same way as the currently used invasive pressure measurements (i.e., analog measurements from analog pressure sensor devices, or DPTs).

It should be appreciated that aspects of the invention previously described may be implemented in conjunction with the execution of instructions by processor **224** of pressure transducer simulator **202**. Processor **224** may operate under the control of a program, routine, or the execution of instructions to execute methods or processes in accordance with embodiments of the invention. For example, such a program may be implemented in firmware or software (e.g. stored in memory and/or other locations) and may be implemented by processors and/or other circuitry of the pressure transducer simulator **202**. Further, it should be appreciated that the terms processor, microprocessor, circuitry, controller, etc., refer to any type of logic or circuitry capable of executing logic, commands, instructions, software, firmware, functionality, etc

The various illustrative logical blocks, modules, and circuits described in connection with the embodiments disclosed herein may be implemented or performed with a general purpose processor, a microcontroller, a digital signal processor (DSP), an application specific integrated circuit (ASIC), a field programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A processor may be a microprocessor or any conventional processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, a plurality of microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

The steps of a method or algorithm described in connection with the embodiments disclosed herein may be embodied directly in hardware, in a software module executed by a processor, or in a combination of the two. A software module may reside in RAM memory, flash memory, ROM memory, EPROM memory, EEPROM memory, registers, hard disk, a removable disk, a CD-ROM, or any other form of storage medium known in the art. An exemplary storage

medium is coupled to the processor such the processor can read information from, and write information to, the storage medium. In the alternative, the storage medium may be integral to the processor.

The previous description of the disclosed embodiments is provided to enable any person skilled in the art to make or use the present invention. Various modifications to these embodiments will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other embodiments without departing from the spirit or scope of the invention. Thus, the present invention is not intended to be limited to the embodiments shown herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein.

What is claimed is:

1. A pressure transducer simulator configured for use with a pressure sensor device and a monitoring device, the pressure transducer simulator configured to generate a simulation of the output of an analog pressure sensing device compatible with the monitoring device, wherein the simulation is based upon a pressure signal received from a pressure sensor device, the pressure transducer simulator comprising:

a digital potentiometer configured to generate an analog signal based upon the pressure signal, wherein the digital potentiometer is configured to transmit the analog signal to the monitoring device; and

a processor to implement a scaling function applied to the digital potentiometer based upon the pressure signal from the pressure sensor device and a reference excitation signal from the monitoring device to ensure the analog signal transmitted to the monitoring device is approximately equivalent to the pressure signal from the pressure sensor device.

2. The pressure transducer simulator of claim 1, wherein the digital potentiometer includes an adjustable wiper that is adjustable to select the resistance of the digital potentiometer.

3. The pressure transducer simulator of claim 2, wherein the processor determines a digital wiper setting for the adjustable wiper to select the resistance of the digital potentiometer.

4. The pressure transducer simulator of claim 3, wherein the processor implements an auto-zeroing command.

5. The pressure transducer simulator of claim 4, wherein, when the auto-zeroing command is implemented, the adjustable wiper is adjusted to set the resistance of the digital potentiometer such that the analog signal produced by the digital potentiometer and transmitted to the monitoring device is approximately zero.

6. The pressure transducer simulator of claim 3, wherein the processor implements an operate command.

7. The pressure transducer simulator of claim 6, wherein, after implementation of the operate command, the digital potentiometer produces an analog signal based upon the pressure signal from the pressure sensor device and the digital wiper setting and transmits the analog signal to the monitoring device, wherein the analog signal is approximately equivalent to the pressure signal from the pressure sensor device.

8. The pressure transducer simulator of claim 3, further comprising a buffer coupled to the digital potentiometer.

9. A method for simulating a pressure sensor device as an analog pressure sensing device to generate a simulation of the output of an analog pressure sensing device compatible with a monitoring device, wherein the simulation is based

9

upon a pressure signal received from the pressure sensor device, the method comprising:

configuring a digital potentiometer to generate an analog signal based upon the pressure signal;

transmitting the analog signal to the monitoring device; 5 and

implementing a scaling function applied to the digital potentiometer based upon the pressure signal from the pressure sensor device and a reference excitation signal from the monitoring device to ensure the analog signal transmitted to the monitoring device is approximately equivalent to the pressure signal from the pressure sensor device. 10

10. The method of claim 9, wherein the digital potentiometer includes an adjustable wiper that is adjustable to select the resistance of the digital potentiometer. 15

11. The method of claim 10, further comprising determining a digital wiper setting for the adjustable wiper to select the resistance of the digital potentiometer.

12. The method of claim 11, further comprising implementing an auto-zeroing command, wherein the adjustable wiper is adjusted to set the resistance of the digital potentiometer such that the analog signal produced by the digital potentiometer and transmitted to the monitoring device is approximately zero. 20

13. The method of claim 11, further comprising implementing an operate command, wherein the adjustable wiper is adjusted to set the resistance of the digital potentiometer to produce an analog signal approximately equivalent to the pressure signal from the pressure sensor device and to transmit the analog signal to the monitoring device. 25

14. A pressure transducer simulator configured for use with a pressure sensor device and a monitoring device, the pressure transducer simulator configured to generate a simulation of the output of an analog pressure sensing device compatible with the monitoring device, wherein the simu- 30

10

lation is based upon a pressure signal received from the pressure sensor device, the pressure transducer simulator comprising:

a digital potentiometer including an adjustable wiper that is adjustable to select the resistance of the digital potentiometer, wherein the digital potentiometer is configured to generate an analog signal based upon the pressure signal and a digital wiper setting and to transmit the analog signal to the monitoring device; and

a processor to implement an auto-zeroing command and an operate command and to apply a scaling function to the digital potentiometer based upon the pressure signal from the pressure sensor device and a reference excitation signal from the monitoring device to ensure the analog signal transmitted to the monitoring device is approximately equivalent to the pressure signal from the pressure sensor device. 35

15. The pressure transducer simulator of claim 14, wherein the processor determines a digital wiper setting for the adjustable wiper to select the resistance of the digital potentiometer.

16. The pressure transducer simulator of claim 15, wherein, when the auto-zeroing command is implemented, the adjustable wiper is adjusted to set the resistance of the digital potentiometer such that the analog signal produced by the digital potentiometer and transmitted to the monitoring device is approximately zero.

17. The pressure transducer simulator of claim 15, wherein, after implementation of the operate command, the digital potentiometer produces an analog signal based upon the pressure signal from the pressure sensor device and the digital wiper setting and transmits the analog signal to the monitoring device, wherein the analog signal is approximately equivalent to the pressure signal from the pressure sensor device.

* * * * *

专利名称(译)	用于模拟压力传感器以测量血压的方法和装置		
公开(公告)号	US9775527	公开(公告)日	2017-10-03
申请号	US14/710329	申请日	2015-05-12
[标]申请(专利权)人(译)	爱德华兹生命科学公司		
申请(专利权)人(译)	爱德华生命科学公司		
当前申请(专利权)人(译)	爱德华生命科学公司		
[标]发明人	PHAN LUONG N AL HATIB FERAS KONNO MARK A BAKER LINDON A GROS RICHARD A		
发明人	PHAN, LUONG N. AL HATIB, FERAS KONNO, MARK A. BAKER, LINDON A. GROS, RICHARD A.		
IPC分类号	A61B5/00 A61B5/021		
CPC分类号	A61B5/02141 A61B5/0002 A61B5/021 A61B5/7278 A61B2560/0223 A61B2560/045		
代理人(译)	KING , ERIC T.		
助理审查员(译)	汉考克 , DENNIS		
优先权	61/695742 2012-08-31 US		
其他公开文献	US20160324428A1		
外部链接	Espacenet USPTO		

摘要(译)

公开了一种用于利用压力传感器模拟器的装置，系统和方法，所述压力传感器模拟器被配置为与压力传感器装置和患者监测装置一起使用。压力换能器模拟器可以被配置为生成模拟压力感测设备的输出的模拟以与患者监测设备兼容。模拟可以基于从压力传感器装置接收的压力信号。在一个实施例中，压力传感器模拟器包括数字电位计，其被配置为基于从压力传感器装置接收的压力信号产生模拟信号，并且其中数字电位计被配置为将模拟信号传输到患者监测装置。

