



US010660609B2

(12) **United States Patent**
Weinstein et al.

(10) **Patent No.:** **US 10,660,609 B2**
(45) **Date of Patent:** **May 26, 2020**

(54) **METHODS AND SYSTEMS FOR DETERMINING FLUID CONTENT OF TISSUE**

(71) Applicant: **KYMA MEDICAL TECHNOLOGIES LTD.**, Kfar Saba (IL)

(72) Inventors: **Uriel Weinstein**, Mazkeret Batya (IL); **Assaf Bernstein**, Givat Nilly (IL); **Eyal Cohen**, Ariel (IL)

(73) Assignee: **ZOLL MEDICAL ISRAEL LTD.**, Kfar-Saba (IL)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 398 days.

(21) Appl. No.: **15/422,416**

(22) Filed: **Feb. 1, 2017**

(65) **Prior Publication Data**

US 2017/0135598 A1 May 18, 2017

Related U.S. Application Data

(60) Division of application No. 14/621,252, filed on Feb. 12, 2015, now Pat. No. 9,572,512, which is a (Continued)

(51) **Int. Cl.**
A61B 8/00 (2006.01)
A61N 1/365 (2006.01)

(Continued)

(52) **U.S. Cl.**
CPC **A61B 8/4254** (2013.01); **A61B 5/0507** (2013.01); **A61B 5/6823** (2013.01); (Continued)

(58) **Field of Classification Search**

CPC A61B 2560/0412; A61B 2562/0209; A61B 2562/14; A61B 2562/166; A61B 5/0402; (Continued)

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,240,445 A 12/1980 Durney et al.
4,344,440 A 8/1982 Aaby et al.
(Continued)

FOREIGN PATENT DOCUMENTS

CN 101032400 A 9/2007
CN 101516437 A 8/2009
(Continued)

OTHER PUBLICATIONS

Haude et al., Intracoronary Doppler—and Quantitative Coronary Angiography-Derived Predictors of Major Adverse Cardiac Events After Stent Implantation, Mar. 6, 2011, Circulation, vol. 103(9), pp. 1212-1217.

(Continued)


Primary Examiner — Mark D Remaly

(74) *Attorney, Agent, or Firm* — Cooley IP

(57) **ABSTRACT**

Diagnostic apparatus includes a plurality of antennas, which are configured to be disposed at different, respective locations on a thorax of a living body so as to direct radio frequency (RF) electromagnetic waves from different, respective directions toward a heart in the body and to output RF signals responsively to the waves that are scattered from the heart. Processing circuitry is configured to process the RF signals over time so as to provide a multi-dimensional measurement of a movement of the heart.

21 Claims, 8 Drawing Sheets



Related U.S. Application Data

continuation of application No. 12/759,715, filed on Apr. 14, 2010, now Pat. No. 8,989,837, which is a continuation-in-part of application No. PCT/IB2009/055438, filed on Dec. 1, 2009.

(51) Int. Cl.

A61B 5/00 (2006.01)

A61B 5/05 (2006.01)

A61B 5/06 (2006.01)

A61B 8/08 (2006.01)

(52) U.S. Cl.

CPC *A61N 1/36578* (2013.01); *A61B 5/061* (2013.01); *A61B 8/085* (2013.01); *A61B 2560/0412* (2013.01); *A61B 2562/0217* (2017.08); *A61B 2562/14* (2013.01); *A61B 2562/166* (2013.01)

(58) Field of Classification Search

CPC *A61B 5/05*; *A61B 5/0507*; *A61B 5/08*; *A61B 5/1107*; *A61B 5/4878*; *A61B 5/6823*; *A61B 5/7285*; *A61B 8/085*; *A61B 8/4254*; *A61N 1/36578*

See application file for complete search history.

(56)**References Cited**

U.S. PATENT DOCUMENTS

4,557,272	A	12/1985	Carr	6,755,856	B2	6/2004	Fierens et al.
4,632,128	A	12/1986	Paglione et al.	6,933,811	B2	8/2005	Enokihara et al.
4,640,280	A	2/1987	Sterzer	6,940,457	B2	9/2005	Lee et al.
4,641,659	A	2/1987	Sepponen	7,020,508	B2	3/2006	Stivoric et al.
4,774,961	A	10/1988	Carr	7,122,012	B2	10/2006	Bouton et al.
4,825,880	A	5/1989	Stauffer et al.	7,130,681	B2	10/2006	Gebhardt et al.
4,926,868	A	5/1990	Larsen	7,184,824	B2	2/2007	Hashimshony
4,945,914	A	8/1990	Allen	7,191,000	B2	3/2007	Zhu et al.
4,958,638	A	9/1990	Sharpe	7,197,356	B2	3/2007	Carr
4,986,870	A	1/1991	Frohlich	7,266,407	B2	9/2007	Li et al.
5,003,622	A	3/1991	Ma et al.	7,267,651	B2	9/2007	Nelson
5,109,855	A	5/1992	Guner	7,272,431	B2	9/2007	McGrath
5,394,882	A	3/1995	Mawhinney	7,280,863	B2	10/2007	Shachar
5,404,877	A	4/1995	Nolan	7,454,242	B2	11/2008	Fear et al.
5,474,574	A	12/1995	Payne et al.	7,474,918	B2	1/2009	Frants et al.
5,540,727	A	7/1996	Tockman et al.	7,479,790	B2	1/2009	Choi
5,549,650	A	8/1996	Bornzin et al.	7,493,154	B2	2/2009	Bonner et al.
5,668,555	A	9/1997	Starr	7,529,398	B2	5/2009	Zwirn et al.
5,704,355	A	1/1998	Bridges	7,570,063	B2	8/2009	Van Veen et al.
5,766,208	A	6/1998	McEwan	7,591,792	B2	9/2009	Bouton
5,807,257	A	9/1998	Bridges	7,697,972	B2	4/2010	Verard et al.
5,829,437	A	11/1998	Bridges	7,719,280	B2	5/2010	Lagae et al.
5,841,288	A	11/1998	Meaney et al.	7,747,302	B2	6/2010	Milledge et al.
5,865,177	A	2/1999	Segawa	7,868,627	B2	1/2011	Turkovskiy
5,967,986	A	10/1999	Cimochowski et al.	8,032,211	B2	10/2011	Hashimshony et al.
6,019,724	A	2/2000	Gronningsaeter et al.	8,211,040	B2	7/2012	Kojima et al.
6,061,589	A	5/2000	Bridges et al.	8,295,920	B2	10/2012	Bouton et al.
6,064,903	A	5/2000	Riechers et al.	8,352,015	B2	1/2013	Bernstein et al.
6,093,141	A	7/2000	Mosseri et al.	8,473,054	B2	6/2013	Pillai et al.
6,144,344	A	11/2000	Kim	8,682,399	B2	3/2014	Rabu
6,161,036	A	12/2000	Matsumura et al.	8,882,759	B2	11/2014	Manley et al.
6,193,669	B1	2/2001	Degany et al.	8,938,292	B2	1/2015	Hettrick et al.
6,208,286	B1	3/2001	Rostislavovich et al.	8,983,592	B2	3/2015	Belalcazar
6,233,479	B1	5/2001	Haddad et al.	8,989,837	B2	3/2015	Weinstein et al.
6,267,723	B1	7/2001	Matsumura et al.	9,220,420	B2	12/2015	Weinstein et al.
6,330,479	B1	12/2001	Stauffer	9,265,438	B2	2/2016	Weinstein et al.
6,409,662	B1	6/2002	Lloyd et al.	9,572,512	B2	2/2017	Weinstein et al.
6,454,711	B1	9/2002	Haddad et al.	9,629,561	B2	4/2017	Weinstein et al.
6,471,655	B1	10/2002	Baura	9,788,752	B2	10/2017	Weinstein et al.
6,480,733	B1	11/2002	Turcott	10,136,833	B2	11/2018	Weinstein et al.
6,526,318	B1	2/2003	Ansarinia	2002/0032386	A1	3/2002	Sackner et al.
6,592,518	B2	7/2003	Denker et al.	2002/0045836	A1	4/2002	Alkawwas
6,604,404	B2	8/2003	Paltiel et al.	2002/0049394	A1	4/2002	Roy et al.
6,729,336	B2	5/2004	Da Silver et al.	2002/0050954	A1	5/2002	Jeong-Kun et al.
6,730,033	B2	5/2004	Yao et al.	2002/0147405	A1	10/2002	Denker et al.
				2002/0151816	A1	10/2002	Rich et al.
				2003/0036713	A1	2/2003	Bouton et al.
				2003/0088180	A1	5/2003	Van Veen et al.
				2003/0100815	A1	5/2003	Da Silva et al.
				2003/0199770	A1	10/2003	Chen et al.
				2003/0219598	A1	11/2003	Sakurai
				2004/0015087	A1	1/2004	Boric-Lubecke et al.
				2004/0073081	A1	4/2004	Schramm
				2004/0077943	A1	4/2004	Meaney et al.
				2004/0077952	A1	4/2004	Rafter et al.
				2004/0249257	A1	12/2004	Tupin et al.
				2004/0254457	A1	12/2004	Van Der Weide
				2004/0261721	A1	12/2004	Steger
				2005/0038503	A1	2/2005	Greenhalgh et al.
				2005/0107693	A1	5/2005	Fear et al.
				2005/0192488	A1	9/2005	Bryenton
				2005/0245816	A1	11/2005	Candidus et al.
				2006/0004269	A9	1/2006	Caduff et al.
				2006/0009813	A1	1/2006	Taylor et al.
				2006/0025661	A1	2/2006	Sweeney et al.
				2006/0101917	A1	5/2006	Merkel
				2006/0265034	A1	11/2006	Aknine et al.
				2007/0016032	A1	1/2007	Aknine
				2007/0016050	A1	1/2007	Moehring et al.
				2007/0055123	A1	3/2007	Takiguchi
				2007/0100385	A1	5/2007	Rawat Prashant
				2007/0123770	A1	5/2007	Bouton et al.
				2007/0123778	A1	5/2007	Kantorovich
				2007/0135721	A1	6/2007	Zdeblick
				2007/0152812	A1	7/2007	Wong et al.
				2007/0156057	A1	7/2007	Cho et al.
				2007/0162090	A1	7/2007	Penner
				2007/0191733	A1	8/2007	Gianchandani et al.
				2007/0263907	A1	11/2007	McMakin et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

2008/0027313 A1 1/2008 Shachar
 2008/0030284 A1 2/2008 Tanaka et al.
 2008/0036668 A1 2/2008 White et al.
 2008/0097199 A1 4/2008 Mullen
 2008/0129511 A1 6/2008 Yuen et al.
 2008/0139934 A1 6/2008 McMorro et al.
 2008/0167566 A1 7/2008 Unver et al.
 2008/0169961 A1 7/2008 Steinway et al.
 2008/0183247 A1 7/2008 Harding
 2008/0200802 A1 8/2008 Bahavaraju et al.
 2008/0224688 A1 9/2008 Rubinsky et al.
 2008/0269589 A1 10/2008 Thijs et al.
 2008/0283282 A1 11/2008 Kawasaki et al.
 2008/0294036 A1 11/2008 Hoi et al.
 2008/0316124 A1 12/2008 Hook
 2008/0319301 A1 12/2008 Busse
 2009/0021720 A1 1/2009 Hecker
 2009/0048500 A1 2/2009 Corn
 2009/0076350 A1 3/2009 Bly et al.
 2009/0153412 A1 6/2009 Chiang et al.
 2009/0187109 A1 7/2009 Hashimshony
 2009/0203972 A1 8/2009 Heneghan et al.
 2009/0227882 A1 9/2009 Foo
 2009/0240132 A1 9/2009 Friedman
 2009/0240133 A1 9/2009 Friedman
 2009/0248450 A1 10/2009 Fernandez
 2009/0262028 A1 10/2009 Mumbru et al.
 2009/0281412 A1 11/2009 Boyden et al.
 2009/0299175 A1 12/2009 Bernstein et al.
 2009/0312615 A1 12/2009 Caduff et al.
 2009/0322636 A1 12/2009 Brigham et al.
 2010/0052992 A1 3/2010 Okamura et al.
 2010/0056907 A1 3/2010 Rappaport et al.
 2010/0076315 A1 3/2010 Erkamp et al.
 2010/0081895 A1 4/2010 Zand
 2010/0106223 A1 4/2010 Grevious
 2010/0152600 A1 6/2010 Droicour et al.
 2010/0256462 A1 10/2010 Rappaport et al.
 2010/0265159 A1 10/2010 Ando et al.
 2010/0312301 A1 12/2010 Stahmann
 2010/0321253 A1 12/2010 Ayala Vazquez et al.
 2010/0332173 A1 12/2010 Watson et al.
 2011/0004076 A1 1/2011 Janna et al.
 2011/0009754 A1 1/2011 Wenzel et al.
 2011/0022325 A1 1/2011 Craddock et al.
 2011/0040176 A1 2/2011 Razansky et al.
 2011/0060215 A1 3/2011 Tupin et al.
 2011/0068995 A1 3/2011 Baliarda et al.
 2011/0125207 A1 5/2011 Nabutovsky et al.
 2011/0130800 A1 6/2011 Weinstein et al.
 2011/0257555 A1 10/2011 Banet et al.
 2012/0029323 A1 2/2012 Zhao
 2012/0065514 A1 3/2012 Naghavi et al.
 2012/0068906 A1 3/2012 Asher et al.
 2012/0098706 A1 4/2012 Lin et al.
 2012/0104103 A1 5/2012 Manzi
 2012/0330151 A1 12/2012 Weinstein et al.
 2013/0041268 A1 2/2013 Rimoldi et al.
 2013/0069780 A1 3/2013 Tran et al.
 2013/0090566 A1 4/2013 Muhlstett et al.
 2013/0123614 A1 5/2013 Bernstein et al.
 2013/0184573 A1 7/2013 Pahlevan et al.
 2013/0190646 A1 7/2013 Weinstein et al.
 2013/0225989 A1 8/2013 Saroka et al.
 2013/0231550 A1 9/2013 Weinstein et al.
 2013/0297344 A1 11/2013 Cosentino et al.
 2013/0310700 A1 11/2013 Wiard et al.
 2014/0046690 A1 2/2014 Gunderson et al.
 2014/0081159 A1 3/2014 Tao et al.
 2014/0128032 A1 5/2014 Muthukumar
 2014/0163425 A1 6/2014 Tran
 2014/0288436 A1 9/2014 Venkatraman et al.
 2015/0025333 A1 1/2015 Weinstein et al.
 2015/0150477 A1 6/2015 Weinstein et al.
 2015/0164349 A1 6/2015 Gopalakrishnan et al.

2015/0335310 A1 11/2015 Bernstein et al.
 2016/0073924 A1 3/2016 Weinstein et al.
 2016/0198957 A1 7/2016 Arditi et al.
 2016/0198976 A1 7/2016 Weinstein et al.
 2016/0213321 A1 7/2016 Weinstein et al.
 2016/0317054 A1 11/2016 Weinstein et al.
 2016/0345845 A1 12/2016 Ravid et al.
 2017/0035327 A1 2/2017 Yuen et al.
 2017/0238966 A1 8/2017 Weinstein et al.
 2017/0296093 A1 10/2017 Weinstein et al.
 2019/0046038 A1 2/2019 Weinstein et al.

FOREIGN PATENT DOCUMENTS

DE 10008886 9/2001
 EP 1834588 A1 9/2007
 EP 2506917 A1 1/2015
 JP 10-137193 A 5/1998
 JP 2000-235006 A 8/2000
 JP 2001-525925 A 12/2001
 JP 2004-526488 A 9/2004
 JP 2006-208070 A 8/2006
 JP 2006-319767 A 11/2006
 JP 2007-061359 A 3/2007
 JP 2008-515548 5/2008
 JP 2008-148141 A 6/2008
 JP 2008-518706 A 6/2008
 JP 2008-530546 A 7/2008
 JP 2008-542759 A 11/2008
 JP 2009-514619 A 4/2009
 JP 2009-522034 A 6/2009
 JP 2010-512190 4/2010
 JP 2010-537766 A 12/2010
 JP 2011-507583 A 3/2011
 JP 2011-524213 A 9/2011
 WO WO 2003/009752 A2 2/2003
 WO WO 2006/127719 A2 11/2006
 WO WO 2006/130798 A2 12/2006
 WO WO 2007/017861 A2 2/2007
 WO WO 2008/070856 A2 6/2008
 WO WO 2008/148040 A1 12/2008
 WO WO 2009/031149 A2 3/2009
 WO WO 2009/031150 3/2009
 WO WO 2009/060182 A1 5/2009
 WO WO 2009/081331 A1 7/2009
 WO WO 2009/152625 12/2009
 WO WO 2011/067623 6/2011
 WO WO 2011/067685 A1 6/2011
 WO WO 2011/141915 A2 11/2011
 WO WO 2012/011065 A1 1/2012
 WO WO 2012/011066 A1 1/2012
 WO WO 2013/118121 A1 8/2013
 WO WO 2013/121290 A2 8/2013
 WO WO 2015/118544 A1 8/2015

OTHER PUBLICATIONS

Beyer-Enke et al., Intra-arterial Doppler flowmetry in the superficial femoral artery following angioplasty., 2000, European Radiology, vol. 10, No. 4, pp. 642-649.
 Ringer et al., Follow-up of Stented Carotid Arteries by Doppler Ultrasound, Sep. 2002, Neurosurgery, vol. 51, No. 3, pp. 639-643.
 Kantarci et al., Follow-up of Extracranial Vertebral Artery Stents with Doppler Sonography., Sep. 2006, American Journal of Roentgenology, vol. 187, pp. 779,787.
 Ghosh, et al., Immediate Evaluation of Angioplasty and Stenting Results in Supra-Aortic Arteries by Use of a Doppler-Tipped Guidewire, Aug. 2004, American Journal of Neuroradiology, vol. 25, pp. 1172-1176.
 Miura et al., "Time Domain Reflectometry: Measurement of Free Water in Normal Lung and Pulmonary Edema," American Journal of Physiology—Lung Physiology 276:1 (1999), pp. L207-L212.
 International Search Report and Written Opinion, dated Nov. 26, 2013 for Application No. PCT/IB2013/00663 filed Feb. 15, 2013.
 International Patent Application PCT/IB2009/055438, "Locating Features in the Heart Using Radio Frequency Imaging", Filed on Dec. 1, 2009.

(56)

References Cited

OTHER PUBLICATIONS

International Application PCT/IB2009/055438 Search Report dated Jul. 20, 2010.

International Application PCT/IB2010/054861 Search Report dated Apr. 5, 2011.

International Search Report for International Application No. PCT/IB2011/053244, dated Dec. 2, 2011.

Ascension Technology Corporation, "TrakSTAR Adds Versatility to Ascension's New Product Line: Desktop Model Joins driveBAY Tracker for Fast Guidance of Miniaturized Sensor", USA, Apr. 7, 2008.

Claron Technology Inc., "MicronTracker 3: A New Generation of Optical Trackers", Canada, 2009.

Immersion Corporation, "Immersion Introduces New 3D Digitizing Product—MicroScribe G2; Faster Data Transfer, USB Compatibility, New Industrial Design", Press Release, San Jose, USA, Jul. 1, 2002.

Polhemus, "Fastrak: The Fast and Easy Digital Tracker", USA, 2008.

Czum et al., "The Vascular Diagnostic Laboratory", The Heart & Vascular Institute Newsletter, vol. 1, USA, Winter, 2001.

Lal et al., "Duplex ultrasound velocity criteria for the stented carotid artery", Journal of Vascular Surgery, vol. 47, No. 1, pp. 63-73, Jan. 2008.

Larsson et al., "State Diagrams of the Heart—a New Approach to Describing Cardiac Mechanics", Cardiovascular Ultrasound 7:22 (2009).

Bell et al., "A Low-Profile Achimedean Spiral Antenna Using an EBG Ground Plane", IEEE Antennas and Wireless Propagation Letters 3, pp. 223-226 (2004).

Supplementary European Search Report for Application No. EP 10834292.4 (PCT/IB2010/054861) dated Dec. 4, 2014.

Lin, J.C. et al., "Microwave Imaging of Cerebral Edema", Proceedings of the IEEE, IEEE, NY, US, vol. 70, No. 5; May 1, 1982, pp. 523-524.

Guido Biffi Gentili et al., "A Versatile Microwave Plethysmograph for the Monitoring of Physiological Parameters", IEEE Transactions on Biomedical Engineering, IEEE Service Center, Piscataway, NJ, US, vol. 49, No. 10, Oct. 1, 2002.

Pedersen P C et al., "Microwave Reflection and Transmission Measurements for Pulmonary Diagnosis and Monitoring", IEEE Transactions on Biomedical Engineering, IEEE Service Center, Piscataway, NJ, US, vol. BME-19, No. 1, Jan. 1, 1978; pp. 40-48.

International Search Report for International Application No. PCT/IB2011/053246 dated, Dec. 13, 2011.

Extended Search Report for European Application No. 11809360.8, dated, Mar. 11, 2014.

Written Opinion of the International Searching Authority, dated Jul. 20, 2010, for International Application No. PCT/IB2009/055438. International Preliminary Report on Patentability, dated Jun. 14, 2012, for International Application No. PCT/IB2009/055438.

Christine N. Paulson et al. "Ultra-wideband radar methods and techniques of medical sensing and imaging" Proceedings of Spie, vol. 6007, Nov. 9, 2005, p. 60070L.

S. I. Alekseev et al. "Human Skin permittivity determined by millimeter wave reflection measurements", Bioelectromagnetics, vol. 28, No. 5, Jul. 1, 2007, pp. 331-339.

Supplementary European Search Report and European Search Opinion, dated Jun. 13, 2013, for European Application No. 09851811.1.

Notice of Reasons for Rejection, dated Apr. 28, 2014, for JP 2012-541588.

Notice of Reasons for Rejection, dated Mar. 31, 2015, for JP 2012-541588.

Written Opinion of the International Searching Authority, dated Dec. 2, 2011, for International Application No. PCT/IB2011/053244.

International Preliminary Report on Patentability, dated Jan. 31, 2013, for International Application No. PCT/IB2011/053244.

Supplementary European Search Report and European Search Opinion, dated Feb. 26, 2014, for European Application No. 11809359.

International Search Report and Written Opinion, dated Feb. 26, 2015, for International Application No. PCT/IL2014/050937.

Notice of Reasons for Rejection, dated Apr. 17, 2015, for JP 2013-520273.

International Preliminary Report on Patentability, dated Jan. 31, 2013, for International Application No. PCT/IB2011/053246, 22 pages.

International Preliminary Report on Patentability, dated Aug. 19, 2014 for International Application No. PCT/IB2013/000663 filed Feb. 15, 2013.

International Preliminary Report on Patentability, dated Jun. 5, 2012, for International Application No. PCT/IB2010/054861.

International Search Report and Written Opinion, dated Nov. 28, 2018 for International Application No. PCT/IL2018/050808 filed Jul. 20, 2018.


Liang, Jing et al., Microstrip Patch Antennas on Tunable Electromagnetic Band-Gap Substrates, IEEE Transactions on Antennas and Propagation, vol. 57, No. 6, Jun. 2009.

Partial Supplementary Search Report, dated Oct. 19, 2015, for EP Application No. 13748671.8.

Supplementary European Search Report, dated Mar. 7, 2016, for EP Application No. 13748671.8.

Written Opinion for International Application No. PCT/IB2010/054861 dated Apr. 5, 2011.

Yang, F. et al. "Enhancement of Printed Dipole Antennas Characteristics Using Semi-EBG Ground Plane", Journal of Electromagnetic Waves and Application, U.S., Taylor & Francis, Apr. 3, 2006, vol. 8, pp. 993-1006.






FIG. 2




FIG. 3






FIG. 4






FIG. 6




FIG. 7




FIG. 8

METHODS AND SYSTEMS FOR DETERMINING FLUID CONTENT OF TISSUE

CROSS-REFERENCE TO RELATED APPLICATION

This application is a divisional application of U.S. patent application Ser. No. 14/621,252, filed Feb. 12, 2015, titled "Methods and Systems for Determining Fluid Content of Tissue," which in turn is a continuation of U.S. patent application Ser. No. 12/759,715, filed Apr. 14, 2010, titled "Methods and Systems for Determining Fluid Content of Tissue," (issued as U.S. Pat. No. 8,989,837), which in turn is a continuation-in-part of PCT patent application PCT/IB2009/055438, filed Dec. 1, 2009. The disclosures of each of the above applications are incorporated herein by reference in their entireties.

FIELD OF THE INVENTION

The present invention relates generally to methods and systems for medical diagnostic measurement and monitoring, and specifically to radio frequency (RF)-based measurement and monitoring of the heart.

BACKGROUND OF THE INVENTION

RF imaging is best known in the context of radar systems, but RF diagnostic imaging and measurement systems have also been developed for medical applications. For example, U.S. Patent Application Publication 2008/0169961, whose disclosure is incorporated herein by reference, describes computerized tomography using radar, which may be used for generating an image of living tissue.

As another example, U.S. Patent Application Publication 2009/0299175, whose disclosure is incorporated herein by reference, describes a method and apparatus for determining and tracking the location of a metallic object in a living body, using a radar detector adapted to operate on a living body. Applications described in this publication include determination of the extent of in-stent restenosis, performing therapeutic thrombolysis, and determining operational features of a metallic implant.

Yet another example is U.S. Pat. No. 5,766,208, whose disclosure is incorporated herein by reference. This patent describes a non-acoustic pulse-echo radar monitor, which is employed in the repetitive mode, whereby a large number of reflected pulses are averaged to produce a voltage that modulates an audio oscillator to produce a tone that corresponds to the heart motion. The monitor output potential can be separated into a cardiac output indicative of the physical movement of the heart, and a pulmonary output indicative of the physical movement of the lung.

U.S. Pat. No. 4,926,868, whose disclosure is incorporated herein by reference, describes a method and apparatus for cardiac hemodynamic monitoring based on the complex field amplitudes of microwaves propagated through and scattered by thoracic cardiovascular structures, particularly the heart chambers, as a function of time during the cardiac cycle. The apparatus uses conformal microstrip antennas that operate in the UHF band. The basic measurement technique is vector network analysis of the power wave scattering parameter.

U.S. Patent Application Publication 2009/0240133, whose disclosure is incorporated herein by reference, describes a radio apparatus and method for non-invasive,

thoracic radio interrogation of a subject for the collection of hemodynamic, respiratory and/or other cardiopulmonary related data. A radio transmitter transmits an unmodulated radio interrogation signal from an antenna into a subject, and a radio receiver captures, through the antenna, reflections of the transmitted radio interrogation signal returned from the subject. A Doppler component of the reflections contains the data that can be extracted from the captured reflections.

SUMMARY OF THE INVENTION

Embodiments of the present invention that are described hereinbelow provide methods and devices for assessment of cardiovascular function by transmission and detection of RF waves through the body.

There is therefore provided, in accordance with an embodiment of the present invention, diagnostic apparatus, including a plurality of antennas, which are configured to be disposed at different, respective locations on a thorax of a living body so as to direct radio frequency (RF) electromagnetic waves from different, respective directions toward a heart in the body and to output RF signals responsively to the waves that are scattered from the heart. Processing circuitry is configured to process the RF signals over time so as to provide a multi-dimensional measurement of a movement of the heart.

In some embodiments, the plurality of antennas includes at least three antennas, and the respective locations are chosen so as to at least partially surround the thorax.

In disclosed embodiments, each antenna has a front surface, which is configured to contact an outer surface of the body and includes a planar antenna element. The planar antenna element may include a conductive spiral. Additionally or alternatively, each antenna may include a ground plane behind the front surface with an electromagnetic band gap (EBG) structure between the ground plane and the front surface. Typically, a dielectric gel is applied between the antenna and the outer surface of the body.

In one embodiment, each antenna is configured to contact an outer surface of the body and, the processing circuitry is configured to receive and process an electrocardiogram signal received from the body by at least one of the antennas, in addition to the RF signals.

In a disclosed embodiment, the apparatus includes excitation circuitry, which is coupled to select different ones of the antennas to serve as transmitting and receiving antennas and to apply a RF excitation waveform at multiple different frequencies to the selected transmitting antennas, while the processing circuitry receives the RF signals from the selected receiving antennas, wherein the transmitting and receiving antennas and the different frequencies are selected according to a predetermined temporal pattern. Typically, the excitation circuitry includes a driver circuit, which is configured to generate the RF excitation waveform with a variable frequency, and a switching matrix, which is configured to select sets of the antennas in alternation, each set including at least one transmitting antenna and at least one receiving antenna, and for each selected set, to couple the driver circuit to excite the at least one transmitting antenna at a selected frequency while coupling the processing circuitry to receive the RF signals from the at least one receiving antenna.

In one embodiment, the plurality of antennas includes at least first and second antennas disposed on respective opposite sides of the thorax, so that the second antenna receives the RF electromagnetic waves transmitted by the first antenna after passage of the RF electromagnetic waves

3

through at least one lung in the body, and the processor is configured to process the RF signals output by the second antenna so as to assess an amount of fluid accumulation in the at least one lung.

In another embodiment, the apparatus includes at least one pacing electrode, wherein the processing circuitry is configured to drive the at least one pacing electrode so as to pace the heart responsively to the measurement of the movement of the heart.

In yet another embodiment, the processing circuitry is configured to compare the measure of the movement of the heart before, during and after heart stress.

There is also provided, in accordance with an embodiment of the present invention, diagnostic apparatus, including an antenna, which is configured to be disposed on a thorax of a living body so as to direct radio frequency (RF) electromagnetic waves toward a heart in the body while sweeping the waves over multiple different frequencies and to output an ultra-wideband RF signal responsively to the waves that are scattered from the heart. Processing circuitry is configured to process the RF signal over time so as to provide a measurement of a movement of the heart.

In some embodiments, the apparatus includes a package, which contains the antenna and the processing circuitry and is configured to be affixed as a patch to an outer surface of the body. The apparatus may include a conductive element associated with the package, which is configured to receive electrocardiogram (ECG) signals from the outer surface of the body. Additionally or alternatively, the apparatus includes a wireless communication interface for communicating with a remote console.

There is additionally provided, in accordance with an embodiment of the present invention, diagnostic apparatus, including one or more antennas, which are configured to be disposed on a thorax of a living body so as to direct radio frequency (RF) electromagnetic waves through a lung in the body and to output RF signals responsively to the waves that have passed through the lung. Processing circuitry is configured to process the RF signals over time so as to measure RF path characteristic of the RF electromagnetic waves and, based on the path characteristic, to assess a fluid content of the lung.

The processing circuitry may be configured to measure a change in the path characteristic over one or more respiratory cycles of the lung, and to assess the fluid content responsively to the change.

In disclosed embodiments, the path characteristic includes an effective RF path length of the RF electromagnetic waves through the body. In some embodiments, the processing circuitry is configured to receive a measure of a physical distance traversed by the RF electromagnetic waves through the thorax, and to compare the effective RF path length to the physical distance in order to assess the amount of the fluid accumulation. In one embodiment, the one or more antennas include a transmitting antenna at a first location on a first side of the thorax, which transmits the RF electromagnetic waves through the lung, and a receiving antenna, which receives the waves that have passed through the lung at a second location on a second side of the thorax, opposite the first side, and the physical distance is measured between the first and second locations.

Alternatively, the one or more antennas include at least one antenna that is configured to direct the RF electromagnetic waves through the lung toward a heart in the body, and to output the RF signals responsively to the RF electromagnetic waves reflected from the heart. The apparatus may include an ultrasonic transducer, which is adjacent to the at

4

least one antenna and is configured to direct ultrasonic waves toward the heart and receive the ultrasonic waves reflected from the heart so as to provide a measure of the physical distance.

Additionally or alternatively, the path characteristic includes an amplitude of the RF signals.

There is further provided, in accordance with an embodiment of the present invention, diagnostic apparatus, including an antenna unit, which has a front surface configured to be brought into contact with an outer surface of a living body. The antenna unit includes a planar antenna element, which is configured to direct radio frequency (RF) electromagnetic waves from the front surface into the body and to output RF signals responsively to the waves that are scattered from within the body, and a conductive element, which is configured to receive electrocardiogram (ECG) signals from the outer surface of the body. A cable is connected to the antenna unit so as to communicate with the planar antenna element and the conductive element. Processing circuitry is connected to the cable so as to receive and process the RF and ECG signals.

Typically, the apparatus includes a diplexer coupled between the cable and the processing circuitry for separating the RF signals from the ECG signals.

The antenna unit may include an adhesive patch for attachment to the body. Alternatively, the antenna unit may be configured to be worn on the body as part of a garment.

In a disclosed embodiment, the antenna unit is coated with metal and electrolytes.

There is moreover provided, in accordance with an embodiment of the present invention, diagnostic apparatus, including an antenna unit, which has a front surface configured to be brought into contact with an outer surface of a living body. The antenna unit includes a planar antenna element, which is formed on the front surface and is configured to direct radio frequency (RF) electromagnetic waves into the body and to output RF signals responsively to the waves that are scattered from within the body, with a ground plane behind the front surface and an electromagnetic band gap (EBG) structure between the ground plane and the front surface. Processing circuitry is coupled to the antenna unit so as to receive and process the RF signals.

There is furthermore provided, in accordance with an embodiment of the present invention, therapeutic apparatus, including at least one pacing electrode, configured to apply a pacing signal to a heart in a living body. One or more antennas are configured to be disposed on a thorax of the body so as to direct radio frequency (RF) electromagnetic waves toward the heart and to output RF signals responsively to the waves that are scattered from the heart. Processing circuitry is configured to process the RF signals over time so as to measure a movement of the heart and to drive the at least one pacing electrode so as to pace the heart responsively to the measured movement.

There is also provided, in accordance with an embodiment of the present invention, a method for diagnosis, including directing radio frequency (RF) electromagnetic waves from a plurality of antennas, which are disposed at different, respective locations on a thorax of a living body, toward a heart in the body from different, respective directions, and outputting RF signals responsively to the waves that are scattered from the heart. The RF signals are processed over time so as to provide a multi-dimensional measurement of a movement of the heart.

There is additionally provided, in accordance with an embodiment of the present invention, a method for diagnosis, including directing radio frequency (RF) electromag-

netic waves from an antenna, which is disposed on a thorax of a living body, toward a heart in the body while sweeping the waves over multiple different frequencies, and outputting an ultra-wideband RF signal responsively to the waves that are scattered from the heart. The RF signal is processed over time so as to provide a measurement of a movement of the heart.

There is further provided, in accordance with an embodiment of the present invention, a method for diagnosis, including directing radio frequency (RF) electromagnetic waves from one or more antennas disposed on a thorax of a living body so that the waves pass through a lung in the body, and outputting RF signals responsively to the waves that have passed through the lung. The RF signals are processed over time so as to measure a RF path characteristic of the RF electromagnetic waves and, based on the path characteristic, to assess a fluid content of the lung.

There is moreover provided, in accordance with an embodiment of the present invention, a method for diagnosis, including bringing a front surface of an antenna unit into contact with an outer surface of a living body. The antenna unit included a planar antenna element and a conductive element, which is configured to receive electrocardiogram (ECG) signals from the outer surface of the body. The planar antenna element is driven to direct radio frequency (RF) electromagnetic waves from the front surface into the body and to output RF signals responsively to the waves that are scattered from within the body. Both the RF and the ECG signals from the antenna unit are received and processed.

There is furthermore provided, in accordance with an embodiment of the present invention, a therapeutic method, including directing radio frequency (RF) electromagnetic waves toward a heart in a living body from one or more antennas disposed on a thorax of the body, and outputting RF signals responsively to the waves that are scattered from the heart. The RF signals are processed over time so as to measure a movement of the heart, and the heart is paced responsively to the measured movement.

The present invention will be more fully understood from the following detailed description of the embodiments thereof, taken together with the drawings in which:

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic, pictorial illustration showing a system for monitoring of heart function, in accordance with an embodiment of the present invention;

FIG. 2 is a schematic representation of a display screen in a system for monitoring of heart function, in accordance with an embodiment of the present invention;

FIG. 3 is a block diagram that schematically shows functional elements of a system for monitoring of heart function, in accordance with an embodiment of the present invention;

FIG. 4 is a schematic exploded view of a patch antenna, in accordance with an embodiment of the present invention;

FIGS. 5A and 5B are schematic plots of propagation delay and amplitude, respectively, of RF waves reflected from the heart, in accordance with an embodiment of the present invention;

FIG. 6 is a schematic, pictorial illustration showing elements of a system for diagnosis of pulmonary edema, in accordance with an embodiment of the present invention;

FIG. 7 is a schematic, pictorial illustration showing elements of a system for pacing the heart, in accordance with an embodiment of the present invention; and

FIG. 8 is a block diagram that schematically illustrates a patch antenna unit, in accordance with another embodiment of the present invention.

DETAILED DESCRIPTION OF EMBODIMENTS

Overview

PCT Patent Application PCT/IB2009/055438, whose disclosure is incorporated herein by reference, describes the use of radar imaging techniques to identify and locate features in the body, based on the difference in their complex dielectric constant relative to the dielectric constant of the surrounding tissue. In the disclosed embodiments, an array of antennas (also referred to as antenna elements) directs RF electromagnetic waves toward the heart and receives the waves that are scattered from within the body. Excitation circuitry applies a RF excitation waveform at multiple different frequencies to different transmitting antennas in the array. Processing circuitry receives and processes signals from different receiving antenna elements in order to locate a feature or features of interest, and possibly to track the movement of such features over the course of the heart cycle. The selection of transmitting and receiving antennas, as well as the selection of excitation frequency, follows a predetermined temporal pattern, which may be implemented by a switching matrix connected to the antenna elements.

As a result of this scheme of excitation and reception, the processing circuitry receives and processes signals from multiple spatial channels (corresponding to different pairs of antennas) at multiple different frequencies for each channel. Taken together in the time domain, these multi-frequency signals are equivalent to short pulses of RF energy. To reconstruct a three-dimensional (3D) image of the interior of the body and find the location of a feature or features, the processing circuitry applies a spatial transform to the set of received signals. The transform may, for example, comprise an inverse spherical Radon transform or an algebraic approximation of such a transform.

Embodiments of the present invention that are described hereinbelow apply techniques similar to those described in PCT/IB2009/055438 for purposes of cardiovascular diagnosis and therapy. In one embodiment, multiple antennas are disposed at different, respective locations on the thorax of a patient, typically surrounding all or at least a part of the thorax. The antennas direct RF waves from different, respective directions toward the heart and output RF signals in response to the scattered waves that they receive. The RF signals received over time are processed so as to provide a multi-dimensional (two- or even three-dimensional) measurement of movement of the heart. This approach can give a picture of heart wall movement that resembles the sort of information provided by cardiac ultrasound imaging, but does not require the active involvement of an expert operator and can even be carried out over a long period while the patient is ambulatory.

Heart wall motion measured by embodiments of the present invention provides detailed diagnostic information regarding functioning of the heart muscle. For example, the heart motion information is useful in diagnosis and monitoring of cardiac ischemia and heart failures, and can also give an indication of cardiac performance, such as chamber volume or ejection fraction. The information provided by embodiments of the present invention can be used in diagnosis, as well as prediction, of ischemic disease and/or ischemic events, such as acute myocardial infarction. The heart wall motion may be compared before, during and after

heart stress caused by physical exercise or by medication, in a manner similar to ECG-based stress testing.

As yet another example, the heart wall motion information provided by embodiments of the present invention may be used in place of ultrasonic imaging data in analyzing and diagnosing cardiac mechanical function. For instance, radar-based measurements may be used instead of the Doppler imaging techniques described by Larsson et al., in "State Diagrams of the Heart—a New Approach to Describing Cardiac Mechanics," *Cardiovascular Ultrasound* 7:22 (2009), which is incorporated herein by reference.

Additionally or alternatively, embodiments of the present invention can be used in long-term monitoring of heart conditions, and particularly as an ambulatory monitor for the detection of "silent ischemias" in coronary artery disease. Heart wall motion monitoring of this sort can thus be used as a diagnostic tool in addition to or instead of conventional stress testing or Holter monitoring.

The heart motion information provided by embodiments of the present invention may also be used for therapeutic purposes. For example, in one embodiment, a pacemaker is driven to pace the heart based on this sort of measurement, as an addition to other parameters, so that the amplitude and timing of the pacing signal give an optimal result in terms of the actual profile of contraction of the heart muscle. This sort of approach can be particularly useful in cardiac resynchronization therapy.

In some embodiments, these RF-based techniques are used to assess fluid accumulation in the lungs, typically for diagnosis and follow-up of pulmonary edema or lung congestion. In these embodiments, one or more antennas on the thorax direct RF waves through one (or both) of the lungs and output RF signals in response to the waves that have passed through the lung. The RF signals are processed over time in order to measure a path characteristic of the RF waves passing through the body, such as the effective RF path length of the RF waves. The RF path length, as opposed to the actual, physical distance, is defined by the length of time required for the waves to pass through the chest (either directly, from one side to the other, or by reflection from the heart and return to an antenna). This path length depends on the dielectric constant of the tissue along the path. When there is fluid in the lungs, the dielectric constant is greater (relative to normal, air-filled lungs), and the RF path length increases accordingly. This RF path length may thus be used to assess the fluid content of the lung.

In some embodiments, monitoring information is sent from a local controller attached to the antennas on the patient's body to a center where the information can be accessed by a referring physician, experts, technicians, and/or the patient himself. The data may flow via a local gateway device, such as a cell-phone or personal computer, via a network, such as the Internet or telephone network, to the center, where it is stored.

Various types of antennas may be used in implementing embodiments of the present invention, including the sort of cavity-backed antenna that is described in PCT/IB2009/055438. Alternatively, some embodiments of the present invention use a planar antenna comprising a conductive spiral, which is formed on the front surface of the antenna. The antenna is backed by an in-phase reflective structure based on an electromagnetic band gap (EBG) structure between the antenna ground plane and the front surface. This design provides a flat, possibly flexible antenna, which can be fixed to the body surface by a gel or other adhesive. (Suitable types of gels for this purpose are described in PCT/IB2009/055438.) The antenna may also comprise a

conductive element, which receives electrocardiogram (ECG) signals from the body surface along with the RF signals output by the antenna itself. The antenna thus performs two complementary measurements simultaneously and obviates the need for separate ECG electrodes.

In one embodiment, the antenna is part of a self-contained patch that also includes radar processing circuits and a power source. The patch may also include a transmitter, such as a wireless unit, for transmission of data to a monitor or gateway.

System Description

FIG. 1 is a schematic, pictorial illustration of a system for monitoring the function of a heart 22, in accordance with an embodiment of the present invention. Multiple antennas 24, 26, 28, 30, 32 are disposed at different, respective locations around a thorax 34 of the patient. (The thorax is transparent in the figure so as to make visible heart 22 and lungs 36, as well as antennas 28 and 30 on the patient's side and back.) The antennas in this embodiment partially surround the thorax. In alternative embodiments, a larger number of antennas may surround the thorax completely. In other embodiments, a smaller number of antennas, possibly only one or two antennas, may be used. The use of three or more antennas, however, is advantageous in providing multi-dimensional heart motion data, as explained further hereinbelow.

Typically, for good RF coupling, antennas 24, 26, 28, 30, 32 are fixed to the skin of the torso. For this purpose, the antennas may have the form of adhesive patches, as described in greater detail with reference to FIG. 4, for example. Additionally or alternatively, for improved coupling, a dielectric gel may be spread between the front surfaces of the antennas and the skin, as described, for example, in the above-mentioned PCT/IB2009/055438. This gel may have a high dielectric constant at microwave frequencies, to give good RF impedance matching, and high conductivity at low frequencies to enhance electrocardiogram signal acquisition. Further additionally or alternatively, the antennas may be attached to and held in place by a suitable garment, such as a vest (not shown), which the patient wears during the monitoring procedure. Typically, the procedure takes a short time, on the order of a few hours or less, although it is possible to monitor patients in this manner over the course of a day or even several days.

Antennas 24, 26, 28, 30, 32 are connected by cables to a control console 40. The console comprises a front end 42, which drives the antennas to direct RF electromagnetic waves from different, respective directions toward heart 22. In response to the waves that are scattered from the heart (and from other features in the body), the antennas output RF signals. Front end 42 receives these signals via cables 38, filters and digitizes the signals, and passes the resulting digital samples to processing circuitry 44. This processing circuitry processes the RF signals over time so as to provide a multi-dimensional measurement of movement of the heart, as shown and described below. Typically, processing circuitry 44 comprises a general-purpose computer processor, which is programmed in software to carry out the functions described herein. Additionally or alternatively, processing circuitry 44 may comprise dedicated or programmable hardware logic circuits.

In the pictured embodiment, processing circuitry 44 drives a display 46 to show a measurement of the movement of the heart, either graphically or numerically, or both. Additionally or alternatively, the processing circuitry may

make other measurements based on the RF signals, such as measuring the amount of fluid accumulated in lungs **36**, as described in greater detail hereinbelow. Further additionally or alternatively, front end **42** may receive ECG signals from the antennas on the body surface, and processor **44** may process and output ECG information in addition to measurement of heart motion. The combination of ECG and motion measurement in a single unit is efficient and useful in providing a complete picture of heart function, both electrical and mechanical.

In some embodiments, it is useful to know the precise locations, and possibly also the orientations, of the antennas. For this purpose, antennas **24** and **30** are shown in the figure as comprising position sensors **48**. (The other antennas may also comprise position sensors, but these sensors are omitted from the figures for the sake of simplicity.) Various types of position sensors that are known in the art, such as magnetic, ultrasonic, optical or even mechanical position sensors, may be used for this purpose. PCT/IB2009/055438 includes further details of such position sensors and their integration in a radar-based measurement system.

FIG. 2 is a schematic representation of the screen of display **46** in system **20**, in accordance with an embodiment of the present invention. Typically, the display is configurable by the user to show different measurements in various different formats. In the example shown in FIG. 2, display **46** shows traces **50** that are indicative of the motion of selected points on the heart wall over time, as measured by system **20**. An ECG trace **52** is displayed alongside the wall motion traces for comparison. (Although only two motion traces and one ECG trace are shown in FIG. 2 for the sake of simplicity, a larger number of traces may alternatively be displayed.)

A graphical window **54** gives a two-dimensional (2D) view of the measured heart motion and also enables the user to choose the points whose motion is to be shown by traces **50**. Alternatively, given a sufficient number of measurement points around the heart, window **54** may show a real-time three-dimensional (3D) representation of heart wall motion.

Display **46** may optionally include other information and user interface features. For example, a parameter window **56** may show parameters derived from the measurements made by system **20**, such as cardiovascular and/or respiratory parameters, in either graphical or numerical form (or both). A status window **58** shows the current status of each of the antennas. This window may indicate, for example, an antenna that is not properly attached to the body (based on measurement of impedance between the antenna and the skin or on characteristics of the RF signals from the antenna), so that the operator can correct the situation. A control window **60** displays status messages and operational buttons to turn system functions on and off.

FIG. 3 is a block diagram that schematically shows functional elements of system **20**, and specifically of front end **42**, in accordance with an embodiment of the present invention. The elements of the front end exchange data and control instructions via a high-speed bus **62**, which is connected to processing circuitry **44** via a bridge **64**. To enable ECG measurements, antennas **24**, **26**, **28**, **30**, **32** are connected via cables **38** and a switching matrix **78** to a diplexer **66** at the input to front end **42**. The diplexer separates out the low-frequency ECG signals from the RF signals, passing the ECG signals to an ECG preprocessing circuit **68**. This circuit filters and digitizes the ECG signals and passes the ECG data via bus **62** to processing circuitry **44**.

Front end **42** comprises a RF generator **70**, which serves as a driver circuit to generate signals at multiple different frequencies for exciting the transmitting antennas. A RF digitizer **72** demodulates and digitizes the signals received by the receiving antennas. Typically, the signals are in the range of about 400 MHz to about 4 GHz, although higher and lower frequencies outside this range may also be used. An I/Q cancellation unit **74** performs signal conditioning functions, including amplification of the outgoing and the incoming signals and cancellation of background components in the received signals. The background cancellation functions of unit are controlled by an I/Q controller **76**, as is described in greater detail hereinbelow.

Switching matrix **78** selects different sets of the antennas to transmit and receive signals at different, respective times and frequencies, in a predetermined temporal pattern. Typically, the sets comprise pairs of antennas—one transmitting and one receiving. Alternatively, the switching matrix may select a set consisting of a single monostatic antenna, which both transmits and receives. Further alternatively, other antenna groupings may also be used. The structure and operation of a switching matrix of this sort are described in detail in PCT/IB2009/055438. Switching matrix **78** and RF generator **70** together serve as excitation circuitry and generate a temporal excitation pattern comprising a sequence of measurement frames, wherein each frame typically defines a sweep of the excitation signal both in frequency and over spatial channels (antennas or antenna pairs). The beginning of each frame is triggered by a trigger controller **80**, which also provides a clock input to the other components of front end **42**.

The sweep over multiple different frequencies creates, in effect, an ultra-wideband signal, which is equivalent, in the signal processing domain, to a very short radar pulse. The use of this sort of ultra-wideband signal enables system **20** to measure path length and heart wall range more accurately and robustly than can generally be achieved using narrow-band methods that are known in the art. Although system **20** is shown and described as comprising multiple antennas at different locations on the patient's thorax, the ultra-wideband approach described here may alternatively be used advantageously in measurements of heart wall movement using only a single antenna.

The functions of I/Q cancellation unit **74** are also described in detail in PCT/IB2009/055438. Briefly, unit modifies the phase and amplitude of the sampled signals from RF digitizer **72**, under the control of I/Q controller **76**, so as to generate an anti-phased signal matching a background component that is to be canceled. This background component may, for example, be a constant and/or slowly-varying part of the incoming signals, which is canceled in order to enhance the time-varying signal component that is due to heart motion. The I/Q cancellation unit generates a signal that is equal in amplitude to the background component but 180° out of phase and adds this anti-phased signal to the received signal from switching matrix **78** and digitizer **72**. The I/Q cancellation unit thus cancels the background component without degrading the actual radar signal from the body.

Processing circuitry **44** collects samples of the received signals, following background cancellation, and processes the samples to identify and locate reflecting volumes within the thorax that correspond to points on the heart surface. One method that may be used for this purpose is the inverse spherical Radon transform. More specifically, PCT/IB2009/055438 describes a first-order approximation of the inverse

spherical Radon transform, which can be applied efficiently and effectively to the sampled RF signals.

Alternatively, processing circuitry **44** may apply other transform techniques. For example, the processing circuitry may compute a frequency response vector for each pair of antennas, and may then apply a window function, such as a Kaiser window, to each vector and transform the windowed frequency data to the time domain using an inverse Fast Fourier Transform (FFT). A time-domain filter, such as a Kalman filter, may be applied to the transformed data in order to model the location and motion of the heart wall. The processing circuitry may correlate location and motion data between different antenna pairs, as well as correlating the motion with ECG measurements. Additionally or alternatively, circuitry **44** may perform ECG-gated or ECG-phased background subtraction, wherein the subtracted background signal is computed as a combination of the different phases in the heartbeat.

In estimating the heart wall location, circuitry **44** may treat the returned signal as a superposition of a number of point reflectors, each moving and scintillating at a pre-defined rate and in a predefined manner. The locations of the point reflectors are estimated using optimization techniques, such as a modified simplex technique. The estimated locations are then used to calculate path length and amplitude and thereby to calculate heart wall movement and/or liquid content of the lungs.

Further additionally or alternatively, processing circuitry **44** may receive and process other physiological parameters in conjunction with the RF signals. For example, the processing circuitry may receive breathing information, as well as data concerning patient posture, patient weight, and blood pressure.

Antenna Design

FIG. 4 is a schematic exploded view of a patch antenna unit **82**, in accordance with an embodiment of the present invention. The pictured antenna design may be used, for example, for any or all of the antennas shown in FIG. 1, as well as the antennas in the figures that follow. This design is suitable for production as a flexible patch, similar to a large ECG electrode, which can be glued onto the body surface with a suitable adhesive. Antenna unit **82** is shown solely by way of example, however, and other types of antennas may similarly be used in system **20**, as well as in the embodiments that are described below.

Antenna unit **82** comprises a front surface **84** in the form of a planar printed circuit board (PCB), on which a conductive spiral **86** is printed to serve as the radiating element of the antenna, using methods of printed circuit fabrication that are known in the art. The front surface is made of suitable biocompatible materials in order to be brought into contact with the body surface. (A layer of gel may be applied between front surface **84** and the body surface, as explained above.) A rear element **88** of the antenna, behind the front surface, serves as a reflective structure. Element **88** comprises a ground plane and a periodic structure that create an electromagnetic band gap (EBG) between the ground plane and the front surface. Details of the theory and design of this sort of antenna are provided by Bell et al., in "A Low-Profile Archimedean Spiral Antenna Using an EBG Ground Plane," *IEEE Antennas and Wireless Propagation Letters* 3, pages 223-226 (2004), which is incorporated herein by reference.

The EBG structure in antenna unit **82** is made up of a periodic mesh of conductive patches **92**, which are connected to ground plane **90** by vias **94** through a thin

dielectric layer (omitted from the figure for visual clarity). The periodic mesh of rear element **88** can have Cartesian or cylindrical symmetry. Since different frequencies exhibit different power densities at different locations on the rear element surface, the components of the EBG structure can have variable dimension to reflect the different frequencies accordingly. For the frequency range mentioned above (400 MHz to 4 GHz), the PCB making up front surface **84** may be 1.6 mm thick, for example, while patches **92** are spaced 1.6 mm from ground plane **90** and contact the rear side of the front surface PCB when assembled. The thickness of front surface **84** and the height of the EBG (as defined by vias **94**) can be optimized for the target VSWR performance, front lobe pattern and gain. Under these conditions, the mesh of patches **92** creates an array of cavities having a parallel resonant response that mimics a perfect magnetic conductor in the specified frequency range. The EBG structure thus reflects the backward wave from spiral **86** in phase with the forward beam, thereby constructively adding to the main forward beam from the antenna.

A flexible backing **96** covers the rear side of rear element **88**. Backing **96** extends over the edges of the front surface and rear element in order to facilitate secure attachment of antenna unit **82** to the body surface. For this purpose, backing **96** may comprise an adhesive margin **98**. Backing **96** may comprise a conductive element for receiving ECG signals from the body surface. Alternatively, front surface **84** may contain such a conductive element (not shown) alongside spiral **86**, or the conductive spiral itself may serve to pick up the ECG signals. Additionally or alternatively, the antenna can be coated with metal and electrolytes to enable ECG measurement without affecting RF performance. A RF connector **100** connects antenna unit **82** to cable **38**. This connector conveys the RF excitation signal to spiral **86** and returns both RF and ECG signals from the antenna unit to the cable.

Assessment of Pulmonary Edema

Referring back to FIG. 1, some of antennas **24**, **26**, **28**, **30** and **32** are positioned in such a way that the RF waves they emit and/or receive pass through one of lungs **36**. For example, when antenna **26** operates in monostatic mode, it directs RF waves through the left lung toward heart **24** and then receives reflected waves from the heart back through the left lung. As another example, in bistatic mode, antenna **30** receives RF waves emitted by antenna **24** after transmission through the lung. The RF path length in either case will vary over the respiration cycle, as the lung fills with air and then empties, and it will vary depending on the amount of fluid accumulated in the lung. Processing circuitry **44** may analyze these path length variations in order to assess the amount of fluid accumulation in the lung.

FIGS. 5A and 5B are schematic plots of propagation delay and amplitude, respectively, of RF waves reflected from the heart, in accordance with an embodiment of the present invention. These plots represent measurements made on a healthy subject using an antenna configured and positioned similarly to antenna **26**. The scales are arbitrary. The delay and, to a lesser extent, the amplitude vary periodically with the heart cycle, as shown particularly by the sharp peaks in FIG. 5A.

The depressed portions of both plots between marks **260** and **290** on the horizontal scale correspond to a period of inhalation during the respiratory cycle. This depression in FIG. 5A shows that when the lungs are full of air, the effective RF path length through the lung decreases, since

the physical distance between antenna **24** and heart **22** remains about the same, while the average dielectric constant along the path decreases. Exhalation empties the lungs of air and thus increases the effective RF path length. The amplitude of the reflected wave in FIG. **5B** also drops during inhalation, presumably because of increased variations of the dielectric constant, and hence more reflections, along the RF path through the lung when the lung is filled with air.

For a lung with a high fluid content, the average dielectric constant will typically be higher than a healthy lung, and the path delay of RF waves traversing the lung will therefore be greater. The overall amplitude may also be greater due to reduced reflections as the waves traverse the lungs. On the other hand, the difference between air-filled and empty lungs over the respiratory cycle is expected to be smaller in both delay and amplitude than the differences shown in FIGS. **5A** and **5B**. Thus, to diagnose and monitor pulmonary edema, processing circuitry **44** may, for example, compare the delay and possibly the amplitude of the reflected waves to benchmarks provided by healthy and edematous lungs, or to previous measurements made on the same patient. Additionally or alternatively, the processing circuitry may assess the amount of fluid in the lungs by analyzing the changes in delay and/or amplitude of the reflected waves over the course of one or more respiratory cycles.

In order to quantify the assessment of fluid accumulation, the actual physical distance traversed by the RF waves passing through the lung may be measured, and a relation (such as a ratio) may be computed between the effective RF path length and the physical distance. For example, referring back to FIG. **1**, if antennas **24** and on opposite sides of the thorax are used to make a transmission-based measurement of the RF path length through lung **36**, the physical distance between these antennas may also be measured. One way to measure the physical distance is by mechanical measurement, using a large caliper, for example. Alternatively or additionally, position sensors **48** attached to the antennas may be used to compute the spatial coordinates of each antenna, and the physical distance may then be computed simply as the Cartesian distance between the coordinate points.

FIG. **6** is a schematic, pictorial illustration showing elements of a system **110** for diagnosis of pulmonary edema, in accordance with an embodiment of the present invention. In this embodiment, antenna **26** is operated monostatically to measure the effective path length of RF waves that are reflected from heart **22** via lung **36**. An ultrasound transducer **112** alongside antenna **26** is used to measure the physical distance to the heart and back. (Although antenna **26** and transducer **112** are shown, for the sake of clarity, as separate units, they may alternatively be integrated in a single package.) The heart wall is identified in both the RF and ultrasound data as the nearest significantly moving reflective surface.

Processing circuitry **44** computes the relation between the physical distance traversed by the ultrasonic waves and the effective path length traversed by the RF waves. Variations in this relation among different patients and among measurements at different points in time for a given patient are indicative of the amount of fluid in the lung.

Therapeutic Applications

Mechanical sensing of cardiac activity has been proposed for use in cardiac stimulation therapy, such as optimizing timing intervals during cardiac pacing. Detection of peak endocardial wall motion in the apex of the right ventricle for

optimizing AV intervals has been validated clinically. Systems and methods for using cardiac wall motion sensor signals to provide hemodynamically-optimal values for heart rate and AV interval have been described, for example, in U.S. Pat. No. 5,549,650, whose disclosure is incorporated herein by reference. A cardiac stimulating system designed to automatically optimize both the pacing mode and one or more pacing cycle parameters in a way that results in optimization of a cardiac performance parameter, such as heart accelerations, is generally described in U.S. Pat. No. 5,540,727, whose disclosure is also incorporated herein by reference.

FIG. **7** is a schematic, pictorial illustration showing elements of a system **120** for pacing heart **22** based on measurements of heart wall motion, in accordance with an embodiment of the present invention. For the sake of simplicity, this figure shows a single antenna **26** used to measure motion of heart **22**, but alternatively, multiple antennas may be used (as shown in FIG. **1**, for example) to provide multi-dimensional wall motion data. A pacing circuit **122** receives and processes the RF signals from the antennas in order to measure the heart wall movement. Based on this measurement, the pacing circuit generates pacing signals to drive pacing electrodes **124** in the heart. The pacing circuit may adjust the timing and/or amplitude of the pacing signals adaptively, while measuring the wall movement, in order to reach an optimal therapeutic result.

As noted above, antenna **26** may also be used in assessing the fluid content of the lungs. The level of fluid content may then be used in adjusting the pacing regime of electrodes **124**, as described, for example, in U.S. Pat. No. 7,191,000, whose disclosure is incorporated herein by reference.

Self-Contained Antenna Patch Unit

FIG. **8** is a block diagram that schematically illustrates a patch antenna unit **130**, in accordance with another embodiment of the present invention. Patch **130**, in effect, performs most of the functions of system **20**, using components that are contained inside an integrated package **142** having the form of a patch, which is typically no more than 20×50 mm across (and may be smaller). As in the preceding embodiments, package **142** may include an adhesive layer (as shown in FIG. **4**, for example), by means of which unit **130** can be affixed to the patient's skin.

Patch unit **130** comprises a flat antenna **132**, which may be of one of the types described above. A transceiver **136** generates driving signals for transmission by antenna **132** and filters and digitizes the reflected signals that the antenna receives from the patient's body. An active background cancellation circuit **134** cancels background components from the reflected signals, in a manner similar to that of I/Q cancellation unit **74**, shown in FIG. **3**. A processor **138** controls the operation of the other components of patch **130** and processes the digitized signals output by transceiver **136** in order to extract heart wall motion data, in a similar manner to processing circuitry **44**. A power module **144**, such as a low-profile battery, provides power to the components of the patch unit.

Patch unit **130** also comprises an ECG electrode **140**, in electrical contact with the patient's skin, and an ECG acquisition circuit **150**, which filters and digitizes the ECG signals for input to processor **138**.

Patch unit **130** may comprise a user interface, such as one or more indicator LEDs **146**, which signal the operational state of the patch (on/off, and possibly parameters such as battery level, quality of skin contact or signal strength).

15

Alternatively or additionally, the user interface may comprise a more informative display, such as a LCD, as well as user controls, such as on/off and adjustment buttons.

A communication interface **148** communicates with a remote console (not shown), in order to transmit radar and ECG measurement data and possibly to receive operational commands. The communication interface typically comprises a wireless link, such as a Bluetooth™ or WiFi link. The console may be located in proximity to the patient's location and may thus receive data from interface **148** directly. Alternatively, interface **148** may communicate with a local gateway, such as a personal computer or smart phone, which communicates with the console over a network, such as the Internet or a telephone network. In this sort of embodiment, for example, the console may comprise a server, which stores the data for subsequent viewing and analysis by a physician or other expert. This sort of system configuration is particularly useful for extended ambulatory monitoring.

It will be appreciated that the embodiments described above are cited by way of example, and that the present invention is not limited to what has been particularly shown and described hereinabove. Rather, the scope of the present invention includes both combinations and subcombinations of the various features described hereinabove, as well as variations and modifications thereof which would occur to persons skilled in the art upon reading the foregoing description and which are not disclosed in the prior art.

The invention claimed is:

1. A method for diagnosis, comprising:
directing radio frequency (RF) electromagnetic waves from one or more antennas disposed on a thorax of a body of a patient so that the RF electromagnetic waves pass through or reflect off a lung in the body;
outputting signals responsively to the RF electromagnetic waves that have passed through the lung;
processing the signals over time so as to measure a path characteristic of the RF electromagnetic waves;
comparing the measured path characteristic to one or more benchmark path characteristic values corresponding to identified levels of fluid content of lungs; and
determining fluid content of the lung based on the comparison.
2. The method of claim 1, wherein processing the signals comprises measuring a change in the path characteristic over one or more respiratory cycles of the lung, and determining the fluid content responsively to the change.
3. The method of claim 1, wherein the path characteristic comprises an effective RF path length of the RF electromagnetic waves through the body.
4. The method of claim 1, wherein the benchmark path characteristic values comprise a physical distance traversed by the RF electromagnetic waves through the thorax of the body.
5. The method of claim 4, wherein:
directing RF electromagnetic waves comprises transmitting the RF electromagnetic waves through the lung by a transmitting antenna at a first location on a first side of the thorax, and further comprising:
receiving, by a receiving antenna, the waves that have passed through the lung at a second location on a second side of the thorax, opposite the first side, and wherein the physical distance is measured between the first and second locations.

16

6. The method of claim 4, wherein
directing RF electromagnetic waves comprises the RF electromagnetic waves through the lung toward a heart in the body, and further comprising:
outputting the RF signals responsively to the RF electromagnetic waves reflected from the heart.
7. The method of claim 6, further comprising:
directing, via an ultrasonic transducer located adjacent to the at least one antenna, ultrasonic waves toward the heart, and
receiving the ultrasonic waves reflected from the heart so as to provide a measure of the physical distance.
8. The method of claim 1, wherein the path characteristic comprises an amplitude of the RF electromagnetic waves.
9. The method of claim 1, wherein the path characteristic comprises a phase of the RF electromagnetic waves.
10. A method, comprising:
directing radio frequency (RF) electromagnetic waves from one or more antennas disposed on a body of a patient so that the RF electromagnetic waves pass through a first tissue of the body;
outputting signals responsively to the RF electromagnetic waves that have passed through the first tissue;
processing the signals at a plurality of different points over a period of time so as to determine a path characteristic of the RF electromagnetic waves relative to the first tissue at the different points;
comparing the determined path characteristic at the plurality of different points over the period of time; and
determining a change in fluid content of the first tissue over the period of time based on the comparison.
11. The method of claim 10, wherein the path characteristic includes an amplitude of the RF electromagnetic waves.
12. The method of claim 10, wherein the path characteristic includes a phase of the RF electromagnetic waves.
13. The method of claim 10, wherein the path characteristic includes an effective RF path length of the RF electromagnetic waves that have passed through the first tissue.
14. The method of claim 13, wherein comparing the determined path characteristic includes comparing the effective RF path length of the RF electromagnetic waves to a physical distance traversed by the RF electromagnetic at the plurality of different points over the period of time.
15. The method of claim 14, wherein an ultrasonic transducer is used to obtain a measurement of the physical distance.
16. The method of claim 14, wherein:
the one or more antennas comprises a transmitting antenna and a receiving antenna located across the first tissue, the transmitting antenna and the receiving antenna each including a position sensor for measuring a first location and a second location of the transmitting antenna and the receiving antenna, respectively, and
the physical distance is a distance between the first location and the second location.
17. The method of claim 10, further comprising determining attachment level of the one or more antennas disposed on the body to skin of the body based on analysis of characteristics of the RF electromagnetic waves.
18. The method of claim 10, further comprising performing an impedance measurement between the one or more antennas disposed on the body and skin of the body so as to determine an attachment level of the one or more antennas to the skin.
19. The method of claim 10, further comprising adjusting a pacing of an electrode configured to apply a pacing signal into the body based on the change in the fluid content.

17

20. The method of claim **10**, wherein processing the signals includes processing physiological data of the patient in conjunction with the signals.

21. The method of claim **20**, wherein the physiological data include information on one or more of patient weight, 5 blood pressure, posture and breathing.

* * * * *

18

专利名称(译)	确定组织液含量的方法和系统		
公开(公告)号	US10660609	公开(公告)日	2020-05-26
申请号	US15/422416	申请日	2017-02-01
[标]申请(专利权)人(译)	基马医疗科技有限公司		
申请(专利权)人(译)	Kyma酒店MEDICAL TECHNOLOGIES LTD.		
[标]发明人	WEINSTEIN URIEL BERNSTEIN ASSAF COHEN EYAL		
发明人	WEINSTEIN, URIEL BERNSTEIN, ASSAF COHEN, EYAL		
IPC分类号	A61B8/00 A61N1/365 A61B5/00 A61B5/05 A61B5/06 A61B8/08		
CPC分类号	A61N1/36578 A61B8/4254 A61B5/6823 A61B5/0507 A61B2560/0412 A61B2562/0217 A61B8/085 A61B5/061 A61B2562/14 A61B2562/166		
其他公开文献	US20170135598A1		
外部链接	Espacenet		

摘要(译)

诊断设备包括多个天线，这些天线被配置为设置在活体胸部的不同位置上，以便将来自不同方向的射频（RF）电磁波引向体内的心脏并指向响应从心脏散射的波，输出射频信号。处理电路被配置为随着时间处理RF信号，以便提供心脏运动的多维测量。

