



US010342518B2

(12) **United States Patent**
Specht et al.

(10) **Patent No.:** US 10,342,518 B2
(45) **Date of Patent:** *Jul. 9, 2019

(54) **POINT SOURCE TRANSMISSION AND SPEED-OF-SOUND CORRECTION USING MULTI-APERTURE ULTRASOUND IMAGING**

(71) Applicant: **MAUI IMAGING, INC.**, Sunnyvale, CA (US)

(72) Inventors: **Donald F. Specht**, Los Altos, CA (US); **Kenneth D. Brewer**, Santa Clara, CA (US)

(73) Assignee: **MAUI IMAGING, INC.**, San Jose, CA (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

This patent is subject to a terminal disclaimer.

(21) Appl. No.: **16/000,507**

(22) Filed: **Jun. 5, 2018**

(65) **Prior Publication Data**

US 2018/0279998 A1 Oct. 4, 2018

Related U.S. Application Data

(63) Continuation of application No. 15/364,075, filed on Nov. 29, 2016, now Pat. No. 9,986,975, which is a (Continued)

(51) **Int. Cl.**


A61B 8/08 (2006.01)
G01S 7/52 (2006.01)

(Continued)

(52) **U.S. Cl.**

CPC **A61B 8/5246** (2013.01); **A61B 8/14** (2013.01); **A61B 8/145** (2013.01); **A61B 8/4444** (2013.01);

(Continued)



(58) **Field of Classification Search**

CPC A61B 8/5246; A61B 8/463; A61B 8/4444; A61B 8/4455; A61B 8/145; A61B 8/5269;

(Continued)

(56) **References Cited**

U.S. PATENT DOCUMENTS

7,293,462 B2 * 11/2007 Lee H04R 23/00 73/649
8,279,705 B2 * 10/2012 Choi A61B 8/00 367/7

(Continued)


Primary Examiner — Sanjay Cattungal

(74) *Attorney, Agent, or Firm* — Shay Glenn LLP

(57) **ABSTRACT**

A Multiple Aperture Ultrasound Imaging system and methods of use are provided with any number of features. In some embodiments, a multi-aperture ultrasound imaging system is configured to transmit and receive ultrasound energy to and from separate physical ultrasound apertures. In some embodiments, a transmit aperture of a multi-aperture ultrasound imaging system is configured to transmit an omnidirectional unfocused ultrasound waveform approximating a first point source through a target region. In some embodiments, the ultrasound energy is received with a single receiving aperture. In other embodiments, the ultrasound energy is received with multiple receiving apertures. Algorithms are described that can combine echoes received by one or more receiving apertures to form high resolution ultrasound images. Additional algorithms can solve for variations in tissue speed of sound, thus allowing the ultrasound system to be used virtually anywhere in or on the body.

18 Claims, 7 Drawing Sheets



Related U.S. Application Data		(56)	References Cited
	continuation of application No. 14/846,374, filed on Sep. 4, 2015, now Pat. No. 9,526,475, which is a continuation of application No. 13/029,907, filed on Feb. 17, 2011, now Pat. No. 9,146,313.		U.S. PATENT DOCUMENTS
(60)	Provisional application No. 61/305,784, filed on Feb. 18, 2010.		8,412,307 B2 * 4/2013 Willis A61B 5/0422 600/374
(51)	Int. Cl. <i>G01S 15/89</i> (2006.01) <i>A61B 8/00</i> (2006.01) <i>A61B 8/14</i> (2006.01)		8,419,642 B2 * 4/2013 Sandrin A61B 8/08 600/438
(52)	U.S. Cl. CPC <i>A61B 8/4455</i> (2013.01); <i>A61B 8/4477</i> (2013.01); <i>A61B 8/4483</i> (2013.01); <i>A61B 8/463</i> (2013.01); <i>A61B 8/5207</i> (2013.01); <i>A61B 8/5269</i> (2013.01); <i>G01S 7/52049</i> (2013.01); <i>G01S 15/8913</i> (2013.01); <i>G01S 15/8927</i> (2013.01); <i>G01S 15/8961</i> (2013.01); <i>G01S 15/8977</i> (2013.01); <i>G01S 15/8993</i> (2013.01); <i>G01S 15/8997</i> (2013.01)		8,473,239 B2 * 6/2013 Specht A61B 8/00 702/100
(58)	Field of Classification Search CPC A61B 8/4483; A61B 8/5207; A61B 8/14; A61B 8/4477; G01S 7/52049; G01S 15/8977; G01S 15/8961; G01S 15/8927; G01S 15/8913; G01S 15/8997; G01S 15/8993 USPC 600/437-469 See application file for complete search history.		8,478,382 B2 * 7/2013 Burnside A61B 1/00158 128/899
			8,532,951 B2 * 9/2013 Roy A61B 8/58 702/85
			8,582,848 B2 * 11/2013 Funka-Lea G06T 7/0002 128/922
			8,602,993 B2 * 12/2013 Specht A61B 8/4281 600/437
			8,627,724 B2 * 1/2014 Papadopoulos G01N 29/075 73/598
			8,634,615 B2 * 1/2014 Brabec G06T 5/20 382/128
			8,672,846 B2 * 3/2014 Napolitano G01S 7/52019 600/407
			8,684,936 B2 * 4/2014 Specht A61B 8/42 600/437
			9,146,313 B2 * 9/2015 Specht G01S 7/52049
			9,220,478 B2 * 12/2015 Smith A61B 8/58
			9,265,484 B2 * 2/2016 Brewer A61B 8/486
			9,282,945 B2 * 3/2016 Smith A61B 8/00
			9,526,485 B2 * 12/2016 Yang A61B 17/0206
			2009/0182233 A1 * 7/2009 Wodnicki G10K 11/345 600/443
			2017/0224312 A1 * 8/2017 Call A61B 8/5246

* cited by examiner

FIG. 1A




FIG. 1B




FIG. 1C




FIG. 2




FIG. 3




FIG. 4





FIG. 5



**POINT SOURCE TRANSMISSION AND
SPEED-OF-SOUND CORRECTION USING
MULTI-APERTURE ULTRASOUND
IMAGING**

**CROSS REFERENCE TO RELATED
APPLICATIONS**

This application is a continuation of U.S. application Ser. No. 15/364,075, filed Nov. 29, 2016, now U.S. Pat. No. 9,986,975, which is a continuation of U.S. application Ser. No. 14/846,374, filed Sep. 4, 2015, now U.S. Pat. No. 9,526,475, which is a continuation of U.S. application Ser. No. 13/029,907, filed Feb. 17, 2011, now U.S. Pat. No. 9,146,313, which application claims the benefit of U.S. Provisional Application No. 61/305,784, filed Feb. 18, 2010, entitled "Alternative Method for Medical Multi-Aperture Ultrasound Imaging".

This application is also related to U.S. application Ser. No. 11/865,501, filed Oct. 1, 2007, now U.S. Pat. No. 8,007,439, titled "Method and Apparatus to Produce Ultrasonic Images Using Multiple Apertures", and to U.S. application Ser. No. 11/532,013, filed Sep. 14, 2006, now U.S. Pat. No. 8,105,239, titled "Method and Apparatus to Visualize the Coronary Arteries Using Ultrasound"; all of which are herein incorporated by reference in their entirety.

INCORPORATION BY REFERENCE

All publications, including patents and patent applications, mentioned in this specification are herein incorporated by reference in their entirety to the same extent as if each individual publication was specifically and individually indicated to be incorporated by reference.

BACKGROUND OF THE INVENTION

In conventional ultrasonic imaging, a focused beam of ultrasound energy is transmitted into body tissues to be examined and the returned echoes are detected and plotted to form an image. The basic principles of conventional ultrasonic imaging are well described in the first chapter of "Echocardiography," by Harvey Feigenbaum (Lippincott Williams & Wilkins, 5th ed., Philadelphia, 1993).

In order to insonify body tissues, an ultrasound beam is typically formed and focused either by a phased array or a shaped transducer. Phased array ultrasound is a commonly used method of steering and focusing a narrow ultrasound beam for forming images in medical ultrasonography. A phased array probe has many small ultrasonic transducer elements, each of which can be pulsed individually. By varying the timing of ultrasound pulses (e.g., by pulsing elements one by one in sequence along a row), a pattern of constructive interference is set up that results in a beam directed at a chosen angle. This is known as beam steering. Such a steered ultrasound beam may then be swept through the tissue or object being examined. Data from multiple beams are then combined to make a visual image showing a slice through the object.

Traditionally, the same transducer or array used for transmitting an ultrasound beam is used to detect the returning echoes. This design configuration lies at the heart of one of the most significant limitations in the use of ultrasonic imaging for medical purposes: poor lateral resolution. Theoretically, the lateral resolution could be improved by increasing the width of the aperture of an ultrasonic probe, but practical problems involved with aperture size increase have

kept apertures small. Unquestionably, ultrasonic imaging has been very useful even with this limitation, but it could be more effective with better resolution.

In the practice of cardiology, for example, the limitation on single aperture size is dictated by the space between the ribs (the intercostal spaces). Such intercostal apertures are typically limited to no more than about one to two centimeters. For scanners intended for abdominal and other use, the limitation on aperture size is less a matter of physical constraints, and more a matter of difficulties in image processing. The problem is that it is difficult to keep the elements of a large aperture array in phase because the speed of ultrasound transmission varies with the type of tissue between the probe and the area of interest. According to the book by Wells (cited above), the speed varies up to plus or minus 10% within the soft tissues. When the aperture is kept small (e.g. less than about 2 cm), the intervening tissue is, to a first order of approximation, all the same and any variation is ignored. When the size of the aperture is increased to improve the lateral resolution, the additional elements of a phased array may be out of phase and may actually degrade the image rather than improving it.

US Patent Publication 2008/0103393, now U.S. Pat. No. 8,007,439, to Specht teaches embodiments of ultrasound imaging systems utilizing multiple apertures which may be separated by greater distances, thereby producing significant improvements in lateral resolution of ultrasound images.

SUMMARY OF THE INVENTION

One embodiment of a method describes a method of constructing an ultrasound image, comprising transmitting an omni-directional unfocused ultrasound waveform approximating a first point source within a transmit aperture on a first array through a target region, receiving ultrasound echoes from the target region with first and second receiving elements disposed on a first receive aperture on a second array, the first array being physically separated from the second array, determining a first time for the waveform to propagate from the first point source to a first pixel location in the target region to the first receiving element, and determining a second time for the waveform to propagate from the first point source to the first pixel location in the target region to the second receiving element, and forming a first ultrasound image of the first pixel by combining the echo received by the first receiving element at the first time with the echo received by the second receiving element at the second time.

In some embodiments, the method further comprises repeating the determining and forming steps for additional pixel locations in the target region. In one embodiment, additional pixel locations are located on a grid without scan-conversion.

In one embodiment, determining the first time and the second time comprises assuming a uniform speed of sound.

In another embodiment, the method further comprises transmitting a second omni-directional unfocused ultrasound waveform approximating a second point source within the transmit aperture through the target region, receiving ultrasound echoes from the target region with first and second receiving elements disposed on the first receive aperture, determining a third time for the second waveform to propagate from the second point source to the first pixel location in the target region to the first receiving element, and determining a fourth time for the second waveform to propagate from the second point source to the first pixel location in the target region to the second receiving element,

and forming a second ultrasound image of the first pixel by combining the echo received by the first receiving element at the third time with the echo received by the second receiving element at the fourth time.

In some embodiments, the method further comprises combining the first ultrasound image with the second ultrasound image. The combining step can comprise coherent addition. In another embodiment, the combining step can comprise incoherent addition. In yet another embodiment, the combining step can comprise a combination of coherent addition and incoherent addition.

In some embodiments, the method can further comprise receiving ultrasound echoes from the target region with third and fourth receiving elements disposed on a second receive aperture on a third array, the third array being physically separated from the first and second arrays, determining a third time for the waveform to propagate from the first point source to the first pixel location in the target region to the third receiving element, and determining a fourth time for the waveform to propagate from the first point source to the first pixel location in the target region to the fourth receiving element, and forming a second ultrasound image of the first pixel by combining the echo received by the third receiving element at the third time with the echo received by the fourth receiving element at the fourth time.

In some embodiments, the method further comprises repeating the determining and forming steps for additional pixel locations in the target region. In some embodiments, the additional pixel locations are located on a grid without scan-conversion.

In one embodiment, the method further comprises transmitting a second omni-directional unfocused ultrasound waveform approximating a second point source within the transmit aperture through the target region, receiving ultrasound echoes from the target region with first and second receiving elements disposed on the first receive aperture and with the third and fourth receiving elements disposed on the second receive aperture, determining a fifth time for the second waveform to propagate from the second point source to the first pixel location in the target region to the first receiving element, determining a sixth time for the second waveform to propagate from the second point source to the first pixel location in the target region to the second receiving element, determining a seventh time for the second waveform to propagate from the second point source to the first pixel location in the target region to the third receiving element, determining an eighth time for the second waveform to propagate from the second point source to the first pixel location in the target region to the fourth receiving element, and forming a third ultrasound image of the first pixel by combining the echo received by the first receiving element at the fifth time with the echo received by the second receiving element at the sixth time, and forming a fourth ultrasound image of the first pixel by combining the echo received by the third receiving element at the seventh time with the echo received by the fourth receiving element at the eighth time.

In some embodiments, the method further comprises combining the first, second, third, and fourth ultrasound images. In some embodiments, the combining step comprises coherent addition. In other embodiments, the combining step comprises incoherent addition. In additional embodiments, the combining step comprises a combination of coherent addition and incoherent addition.

In some embodiments, the method comprises combining the first ultrasound image with the second ultrasound image. The combining step can comprise coherent addition. In

another embodiment, the combining step can comprise incoherent addition. In yet another embodiment, the combining step can comprise a combination of coherent addition and incoherent addition.

In some embodiments, the method further comprises comparing the first ultrasound image to the second, third, and fourth ultrasound images to determine displacements of the second, third, and fourth ultrasound images relative to the first ultrasound image.

In another embodiment, the method further comprises correcting the displacements of the second, third, and fourth ultrasound images relative to the first ultrasound image and then combining the first, second, third and fourth ultrasound images.

In an additional embodiment, the method comprises adjusting the third, fourth, fifth, sixth, seventh, and eighth times to correct the displacements of the second, third, and fourth ultrasound images relative to the first ultrasound image.

In some embodiments, the method further comprises comparing the first ultrasound image to the second ultrasound image to determine a displacement of the second ultrasound image relative to the first ultrasound image.

The method can further comprise correcting the displacement of the second ultrasound image relative to the first ultrasound image and then combining the first and second ultrasound images.

In another embodiment, the method comprises adjusting the third time and the fourth time to correct the displacement of the second ultrasound image relative to the first ultrasound image.

In some embodiments, the first pixel is disposed outside a plane defined by the point source, the first receiving element, and the second receiving element. In other embodiments, the first pixel is disposed inside a plane defined by the point source, the first receiving element, and the second receiving element.

Various embodiments of a multi-aperture ultrasound imaging system are also provided, comprising a transmit aperture on a first array configured to transmit an omni-directional unfocused ultrasound waveform approximating a first point source through a target region, a first receive aperture on a second array having first and second receiving elements, the second array being physically separated from the first array, wherein the first and second receiving elements are configured to receive ultrasound echoes from the target region, and a control system coupled to the transmit aperture and the first receive aperture, the control system configured to determine a first time for the waveform to propagate from the first point source to a first pixel location in the target region to the first receiving element, and is configured to determine a second time for the waveform to propagate from the first point source to the first pixel location in the target region to the second receiving element, the control system also being configured to form a first ultrasound image of the first pixel by combining the echo received by the first receiving element at the first time with the echo received by the second receiving element at the second time.

In some embodiments of the system, there are no transducer elements disposed between the physical separation of the transmit aperture and the first receive aperture.

In one embodiment of the system, the transmit aperture and the first receive aperture are separated by at least twice a minimum wavelength of transmission from the transmit

aperture. In another embodiment, the transmit aperture and the receive aperture comprise a total aperture ranging from 2 cm to 10 cm.

In some embodiments, the ultrasound system further comprises a second receive aperture on a third array having third and fourth receiving elements, the third array being physically separated from the first and second arrays, wherein the third and fourth receiving elements are configured to receive ultrasound echoes from the target region.

In another embodiment of the multi-aperture ultrasound imaging system, the control system can be coupled to the transmit aperture and the first and second receive apertures, wherein the control system is configured to determine a third time for the waveform to propagate from the first point source to a first pixel location in the target region to the third receiving element, and is configured to determine a fourth time for the waveform to propagate from the first point source to the first pixel location in the target region to the fourth receiving element, the control system also being configured to form a second ultrasound image of the first pixel by combining the echo received by the third receiving element at the third time with the echo received by the fourth receiving element at the fourth time.

In some embodiments, the control system is configured to correct a displacement of the second ultrasound image relative to the first ultrasound image due to speed of sound variation.

In other embodiments of the multi-aperture ultrasound imaging system, the transmit aperture, the first receive aperture, and the second receive aperture are not all in a single scan plane.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1A: A two-aperture system.

FIG. 1B: Equidistant time delay points forming an ellipse around a transmit transducer element and receive transducer element.

FIG. 1C: Loci of points relative to equidistant time delays for different receive transducer elements.

FIG. 2: A three-aperture system.

FIG. 3: Grid for display and coordinate system.

FIG. 4: Fat layer model with a three-aperture system.

FIG. 5: Construction for estimation of point spread function.

DETAILED DESCRIPTION OF THE INVENTION

Greatly improved lateral resolution in ultrasound imaging can be achieved by using multiple separate apertures for transmit and receive functions. Systems and methods herein may provide for both transmit functions from point sources and for compensation for variations in the speed-of-sound of ultrasound pulses traveling through potentially diverse tissue types along a path between a transmit aperture and one or more receive apertures. Such speed-of-sound compensation may be performed by a combination of image comparison techniques (e.g., cross-correlation), and the coherent and/or incoherent averaging of a plurality of received image frames.

As used herein the terms “ultrasound transducer” and “transducer” may carry their ordinary meanings as understood by those skilled in the art of ultrasound imaging technologies, and may refer without limitation to any single component capable of converting an electrical signal into an ultrasonic signal and/or vice versa. For example, in some

embodiments, an ultrasound transducer may comprise a piezoelectric device. In some alternative embodiments, ultrasound transducers may comprise capacitive micromachined ultrasound transducers (CMUT). Transducers are often configured in arrays of multiple elements. An element of a transducer array may be the smallest discrete component of an array. For example, in the case of an array of piezoelectric transducer elements, each element may be a single piezoelectric crystal.

10 As used herein, the terms “transmit element” and “receive element” may carry their ordinary meanings as understood by those skilled in the art of ultrasound imaging technologies. The term “transmit element” may refer without limitation to an ultrasound transducer element which at least momentarily performs a transmit function in which an electrical signal is converted into an ultrasound signal. Similarly, the term “receive element” may refer without limitation to an ultrasound transducer element which at least momentarily performs a receive function in which an ultrasound signal impinging on the element is converted into an electrical signal. Transmission of ultrasound into a medium may also be referred to herein as “insonifying.” An object or structure which reflects ultrasound waves may be referred to as a “reflector” or a “scatterer.”

20 25 As used herein the term “aperture” refers without limitation to one or more ultrasound transducer elements collectively performing a common function at a given instant of time. For example, in some embodiments, the term aperture may refer to a group of transducer elements performing a transmit function. In alternative embodiments, the term aperture may refer to a plurality of transducer elements performing a receive function. In some embodiments, group of transducer elements forming an aperture may be redefined at different points in time. FIG. 3 demonstrates multiple

30 35 40 45 50 55 60 65 70 75 80 85 90 95 100 105 110 115 120 125 130 135 140 145 150 155 160 165 170 175 180 185 190 195 200 205 210 215 220 225 230 235 240 245 250 255 260 265 270 275 280 285 290 295 300 305 310 315 320 325 330 335 340 345 350 355 360 365 370 375 380 385 390 395 400 405 410 415 420 425 430 435 440 445 450 455 460 465 470 475 480 485 490 495 500 505 510 515 520 525 530 535 540 545 550 555 560 565 570 575 580 585 590 595 600 605 610 615 620 625 630 635 640 645 650 655 660 665 670 675 680 685 690 695 700 705 710 715 720 725 730 735 740 745 750 755 760 765 770 775 780 785 790 795 800 805 810 815 820 825 830 835 840 845 850 855 860 865 870 875 880 885 890 895 900 905 910 915 920 925 930 935 940 945 950 955 960 965 970 975 980 985 990 995 1000 1005 1010 1015 1020 1025 1030 1035 1040 1045 1050 1055 1060 1065 1070 1075 1080 1085 1090 1095 1100 1105 1110 1115 1120 1125 1130 1135 1140 1145 1150 1155 1160 1165 1170 1175 1180 1185 1190 1195 1200 1205 1210 1215 1220 1225 1230 1235 1240 1245 1250 1255 1260 1265 1270 1275 1280 1285 1290 1295 1300 1305 1310 1315 1320 1325 1330 1335 1340 1345 1350 1355 1360 1365 1370 1375 1380 1385 1390 1395 1400 1405 1410 1415 1420 1425 1430 1435 1440 1445 1450 1455 1460 1465 1470 1475 1480 1485 1490 1495 1500 1505 1510 1515 1520 1525 1530 1535 1540 1545 1550 1555 1560 1565 1570 1575 1580 1585 1590 1595 1600 1605 1610 1615 1620 1625 1630 1635 1640 1645 1650 1655 1660 1665 1670 1675 1680 1685 1690 1695 1700 1705 1710 1715 1720 1725 1730 1735 1740 1745 1750 1755 1760 1765 1770 1775 1780 1785 1790 1795 1800 1805 1810 1815 1820 1825 1830 1835 1840 1845 1850 1855 1860 1865 1870 1875 1880 1885 1890 1895 1900 1905 1910 1915 1920 1925 1930 1935 1940 1945 1950 1955 1960 1965 1970 1975 1980 1985 1990 1995 2000 2005 2010 2015 2020 2025 2030 2035 2040 2045 2050 2055 2060 2065 2070 2075 2080 2085 2090 2095 2100 2105 2110 2115 2120 2125 2130 2135 2140 2145 2150 2155 2160 2165 2170 2175 2180 2185 2190 2195 2200 2205 2210 2215 2220 2225 2230 2235 2240 2245 2250 2255 2260 2265 2270 2275 2280 2285 2290 2295 2300 2305 2310 2315 2320 2325 2330 2335 2340 2345 2350 2355 2360 2365 2370 2375 2380 2385 2390 2395 2400 2405 2410 2415 2420 2425 2430 2435 2440 2445 2450 2455 2460 2465 2470 2475 2480 2485 2490 2495 2500 2505 2510 2515 2520 2525 2530 2535 2540 2545 2550 2555 2560 2565 2570 2575 2580 2585 2590 2595 2600 2605 2610 2615 2620 2625 2630 2635 2640 2645 2650 2655 2660 2665 2670 2675 2680 2685 2690 2695 2700 2705 2710 2715 2720 2725 2730 2735 2740 2745 2750 2755 2760 2765 2770 2775 2780 2785 2790 2795 2800 2805 2810 2815 2820 2825 2830 2835 2840 2845 2850 2855 2860 2865 2870 2875 2880 2885 2890 2895 2900 2905 2910 2915 2920 2925 2930 2935 2940 2945 2950 2955 2960 2965 2970 2975 2980 2985 2990 2995 3000 3005 3010 3015 3020 3025 3030 3035 3040 3045 3050 3055 3060 3065 3070 3075 3080 3085 3090 3095 3100 3105 3110 3115 3120 3125 3130 3135 3140 3145 3150 3155 3160 3165 3170 3175 3180 3185 3190 3195 3200 3205 3210 3215 3220 3225 3230 3235 3240 3245 3250 3255 3260 3265 3270 3275 3280 3285 3290 3295 3300 3305 3310 3315 3320 3325 3330 3335 3340 3345 3350 3355 3360 3365 3370 3375 3380 3385 3390 3395 3400 3405 3410 3415 3420 3425 3430 3435 3440 3445 3450 3455 3460 3465 3470 3475 3480 3485 3490 3495 3500 3505 3510 3515 3520 3525 3530 3535 3540 3545 3550 3555 3560 3565 3570 3575 3580 3585 3590 3595 3600 3605 3610 3615 3620 3625 3630 3635 3640 3645 3650 3655 3660 3665 3670 3675 3680 3685 3690 3695 3700 3705 3710 3715 3720 3725 3730 3735 3740 3745 3750 3755 3760 3765 3770 3775 3780 3785 3790 3795 3800 3805 3810 3815 3820 3825 3830 3835 3840 3845 3850 3855 3860 3865 3870 3875 3880 3885 3890 3895 3900 3905 3910 3915 3920 3925 3930 3935 3940 3945 3950 3955 3960 3965 3970 3975 3980 3985 3990 3995 4000 4005 4010 4015 4020 4025 4030 4035 4040 4045 4050 4055 4060 4065 4070 4075 4080 4085 4090 4095 4100 4105 4110 4115 4120 4125 4130 4135 4140 4145 4150 4155 4160 4165 4170 4175 4180 4185 4190 4195 4200 4205 4210 4215 4220 4225 4230 4235 4240 4245 4250 4255 4260 4265 4270 4275 4280 4285 4290 4295 4300 4305 4310 4315 4320 4325 4330 4335 4340 4345 4350 4355 4360 4365 4370 4375 4380 4385 4390 4395 4400 4405 4410 4415 4420 4425 4430 4435 4440 4445 4450 4455 4460 4465 4470 4475 4480 4485 4490 4495 4500 4505 4510 4515 4520 4525 4530 4535 4540 4545 4550 4555 4560 4565 4570 4575 4580 4585 4590 4595 4600 4605 4610 4615 4620 4625 4630 4635 4640 4645 4650 4655 4660 4665 4670 4675 4680 4685 4690 4695 4700 4705 4710 4715 4720 4725 4730 4735 4740 4745 4750 4755 4760 4765 4770 4775 4780 4785 4790 4795 4800 4805 4810 4815 4820 4825 4830 4835 4840 4845 4850 4855 4860 4865 4870 4875 4880 4885 4890 4895 4900 4905 4910 4915 4920 4925 4930 4935 4940 4945 4950 4955 4960 4965 4970 4975 4980 4985 4990 4995 5000 5005 5010 5015 5020 5025 5030 5035 5040 5045 5050 5055 5060 5065 5070 5075 5080 5085 5090 5095 5100 5105 5110 5115 5120 5125 5130 5135 5140 5145 5150 5155 5160 5165 5170 5175 5180 5185 5190 5195 5200 5205 5210 5215 5220 5225 5230 5235 5240 5245 5250 5255 5260 5265 5270 5275 5280 5285 5290 5295 5300 5305 5310 5315 5320 5325 5330 5335 5340 5345 5350 5355 5360 5365 5370 5375 5380 5385 5390 5395 5400 5405 5410 5415 5420 5425 5430 5435 5440 5445 5450 5455 5460 5465 5470 5475 5480 5485 5490 5495 5500 5505 5510 5515 5520 5525 5530 5535 5540 5545 5550 5555 5560 5565 5570 5575 5580 5585 5590 5595 5600 5605 5610 5615 5620 5625 5630 5635 5640 5645 5650 5655 5660 5665 5670 5675 5680 5685 5690 5695 5700 5705 5710 5715 5720 5725 5730 5735 5740 5745 5750 5755 5760 5765 5770 5775 5780 5785 5790 5795 5800 5805 5810 5815 5820 5825 5830 5835 5840 5845 5850 5855 5860 5865 5870 5875 5880 5885 5890 5895 5900 5905 5910 5915 5920 5925 5930 5935 5940 5945 5950 5955 5960 5965 5970 5975 5980 5985 5990 5995 6000 6005 6010 6015 6020 6025 6030 6035 6040 6045 6050 6055 6060 6065 6070 6075 6080 6085 6090 6095 6100 6105 6110 6115 6120 6125 6130 6135 6140 6145 6150 6155 6160 6165 6170 6175 6180 6185 6190 6195 6200 6205 6210 6215 6220 6225 6230 6235 6240 6245 6250 6255 6260 6265 6270 6275 6280 6285 6290 6295 6300 6305 6310 6315 6320 6325 6330 6335 6340 6345 6350 6355 6360 6365 6370 6375 6380 6385 6390 6395 6400 6405 6410 6415 6420 6425 6430 6435 6440 6445 6450 6455 6460 6465 6470 6475 6480 6485 6490 6495 6500 6505 6510 6515 6520 6525 6530 6535 6540 6545 6550 6555 6560 6565 6570 6575 6580 6585 6590 6595 6600 6605 6610 6615 6620 6625 6630 6635 6640 6645 6650 6655 6660 6665 6670 6675 6680 6685 6690 6695 6700 6705 6710 6715 6720 6725 6730 6735 6740 6745 6750 6755 6760 6765 6770 6775 6780 6785 6790 6795 6800 6805 6810 6815 6820 6825 6830 6835 6840 6845 6850 6855 6860 6865 6870 6875 6880 6885 6890 6895 6900 6905 6910 6915 6920 6925 6930 6935 6940 6945 6950 6955 6960 6965 6970 6975 6980 6985 6990 6995 7000 7005 7010 7015 7020 7025 7030 7035 7040 7045 7050 7055 7060 7065 7070 7075 7080 7085 7090 7095 7100 7105 7110 7115 7120 7125 7130 7135 7140 7145 7150 7155 7160 7165 7170 7175 7180 7185 7190 7195 7200 7205 7210 7215 7220 7225 7230 7235 7240 7245 7250 7255 7260 7265 7270 7275 7280 7285 7290 7295 7300 7305 7310 7315 7320 7325 7330 7335 7340 7345 7350 7355 7360 7365 7370 7375 7380 7385 7390 7395 7400 7405 7410 7415 7420 7425 7430 7435 7440 7445 7450 7455 7460 7465 7470 7475 7480 7485 7490 7495 7500 7505 7510 7515 7520 7525 7530 7535 7540 7545 7550 7555 7560 7565 7570 7575 7580 7585 7590 7595 7600 7605 7610 7615 7620 7625 7630 7635 7640 7645 7650 7655 7660 7665 7670 7675 7680 7685 7690 7695 7700 7705 7710 7715 7720 7725 7730 7735 7740 7745 7750 7755 7760 7765 7770 7775 7780 7785 7790 7795 7800 7805 7810 7815 7820 7825 7830 7835 7840 7845 7850 7855 7860 7865 7870 7875 7880 7885 7890 7895 7900 7905 7910 7915 7920 7925 7930 7935 7940 7945 7950 7955 7960 7965 7970 7975 7980 7985 7990 7995 8000 8005 8010 8015 8020 8025 8030 8035 8040 8045 8050 8055 8060 8065 8070 8075 8080 8085 8090 8095 8100 8105 8110 8115 8120 8125 8130 8135 8140 8145 8150 8155 8160 8165 8170 8175 8180 8185 8190 8195 8200 8205 8210 8215 8220 8225 8230 8235 8240 8245 8250 8255 8260 8265 8270 8275 8280 8285 8290 8295 8300 8305 8310 8315 8320 8325 8330 8335 8340 8345 8350 8355 8360 8365 8370 8375 8380 8385 8390 8395 8400 8405 8410 8415 8420 8425 8430 8435 8440 8445 8450 8455 8460 8465 8470 8475 8480 8485 8490 8495 8500 8505 8510 8515 8520 8525 8530 8535 8540 8545 8550 8555 8560 8565 8570 8575 8580 8585 8590 8595 8600 8605 8610 8615 8620 8625 8630 8635 8640 8645 8650 8655 8660 8665 8670 8675 8680 8685 8690 8695 8700 8705 8710 8715 8720 8725 8730 8735 8740 8745 8750 8755 8760 8765 8770 8775 8780 8785 8790 8795 8800 8805 8810 8815 8820 8825 8830 8835 8840 8845 8850 8855 8860 8865 8870 8875 8880 8885 8890 8895 8900 8905 8910 8915 8920 8925 8930 8935 8940 8945 8950 8955 8960 8965 8970 8975 8980 8985 8990 8995 9000 9005 9010 9015 9020 9025 9030 9035 9040 9045 9050 9055 9060 9065 9070 9075 9080 9085 9090 9095 9100 9105 9110 9115 9120 9125 9130 9135 9140 9145 9150 9155 9160 9165 9170 9175 9180 9185 9190 9195 9200 9205 9210 9215 9220 9225 9230 9235 9240 9245 9250 9255 9260 9265 9270 9275 9280 9285 9290 9295 9300 9305 9310 9315 9320 9325 9330 9335 9340 9345 9350 9355 9360 9365 9370 9375 9380 9385 9390 9395 9400 9405 9410 9415 9420 9425 9430 9435 9440 9445 9450 9455 9460 9465 9470 9475 9480 9485 9490 9495 9500 9505 9510 9515 9520 9525 9530 9535 9540 9545 9550 9555 9560 9565 9570 9575 9580 9585 9590 9595 9600 9605 9610 9615 9620 9625 9630 9635 9640 9645 9650 9655 9660 9665 9670 9675 968

of imaging a 2D slice it creates a uniform circular wave front within the 2D slice. This point source transmission differs in its spatial characteristics from a “phased array transmission” which focuses energy in a particular direction from the transducer element array. Phased array transmission manipulates the phase of a group of transducer elements in sequence so as to strengthen or steer an insonifying wave to a specific region of interest. A short duration point source transmission is referred to herein as a “point source pulse.” Likewise, a short duration phased array transmission is referred to herein as a “phased array pulse.”

As used herein, the terms “receive aperture,” “insonifying aperture,” and/or “transmit aperture” can carry their ordinary meanings as understood by those skilled in the art of ultrasound imaging, and may refer to an individual element, a group of elements within an array, or even entire arrays within a common housing, that perform the desired transmit or receive function from a desired physical viewpoint or aperture at a given time. In some embodiments, these various apertures may be created as physically separate components with dedicated functionality. In alternative embodiments, the functionality may be electronically designated and changed as needed. In still further embodiments, aperture functionality may involve a combination of both fixed and variable elements.

In some embodiments, an aperture is an array of ultrasound transducers which is separated from other transducer arrays. Such multiple aperture ultrasound imaging systems provide greatly increased lateral resolution. According to some embodiments, a multi-aperture imaging method comprises the steps of insonifying a target object with an ultrasound pulse from a first aperture, detecting returned echoes with a second aperture positioned at a distance from the first aperture, determining the relative positions of the second aperture with respect to the first aperture, and processing returned echo data to combine images while correcting for variations in speed-of-sound through the target object.

In some embodiments, a distance and orientation between adjacent apertures may be fixed relative to one another, such as by use of a rigid housing. In alternative embodiments, distances and orientations of apertures relative to one another may be variable, such as with a movable linkage. In further alternative embodiments, apertures may be defined as groups of elements on a single large transducer array where the groups are separated by at least a specified distance. For example, some embodiments of such a system are shown and described in U.S. Provisional Application No. 61/392,896, filed Oct. 13, 2010, titled “Multiple Aperture Medical Ultrasound Transducers”. In some embodiments of a multi-aperture ultrasound imaging system, a distance between adjacent apertures may be at least a width of one transducer element. In alternative embodiments, a distance between apertures may be as large as possible within the constraints of a particular application and probe design.

A multi-aperture ultrasound imaging system with a large effective aperture (the total aperture of the several sub apertures) can be made viable by compensation for the variation of speed-of-sound in the target tissue. This may be accomplished in one of several ways to enable the increased aperture to be effective rather than destructive, as described below.

FIG. 1A illustrates one embodiment of a simplified multi-aperture ultrasound imaging system 100 comprising two apertures, aperture 102 and aperture 104. Each of apertures 102 and 104 can comprise a plurality of transducer elements. In the two-aperture system shown in FIG. 1A, aperture 102

can comprise transmit elements T1 . . . Tn to be used entirely for transmit functions, and aperture 104 can comprise receive elements R1 . . . Rm to be used entirely for receive functions. In alternative embodiments, transmit elements 5 may be interspersed with receive elements, or some elements may be used both for transmit and receive functions. The multi-aperture ultrasound imaging system 100 of FIG. 1A can be configured to be placed on a skin surface of a patient to image target object or internal tissue T with ultrasound energy. As shown in FIG. 1A, aperture 102 is positioned a distance “a” from tissue T, and aperture 104 is positioned a distance “b” from tissue T. Also shown in FIG. 1A, MAUI electronics may be coupled to the transmit and receive apertures 102 and 104. In some embodiments, the 15 MAUI electronics can comprise a processor, control system, or computing system, including hardware and software configured to control the multi-aperture imaging system 100. In some embodiments, the MAUI electronics can be configured to control the system to transmit an omni-directional unfocused ultrasound waveform from an aperture, receive echoes on an aperture, and form images from the transmitted waveform and the received echoes. As will be described in further detail below, the MAUI electronics 20 can be configured to control and achieve any of the methods 25 described herein.

Ultrasound elements and arrays described herein may also be multi-function. That is, the designation of transducer elements or arrays as transmitters in one instance does not preclude their immediate re-designation as receivers in the 30 next instance. Moreover, embodiments of the control system described herein include the capabilities for making such designations electronically based on user inputs or pre-set scan or resolution criteria.

Another embodiment of a multi-aperture ultrasound 35 imaging system 200 is shown in FIG. 2 and includes transducer elements arranged to form three apertures 202, 204, and 206. In one embodiment, transmit elements T1 . . . Tn in aperture 202 may be used for transmit, and receive elements R₁ . . . R_m in apertures 204 and 206 may be used for receive. In alternative embodiments, elements in all the 40 apertures may be used for both transmit and receive. The multi-aperture ultrasound imaging system 200 of FIG. 2 can be configured to image tissue T with ultrasound energy. Also shown in FIG. 2, MAUI electronics may be coupled to the transmit and receive apertures 202 and 204. In some 45 embodiments, the MAUI electronics can comprise a processor, control system, or computing system, including hardware and software configured to control the multi-aperture imaging system 200. In some embodiments, the MAUI electronics can be configured to control the system to transmit an omni-directional unfocused ultrasound waveform from an aperture, receive echoes on an aperture, and form images from the transmitted waveform and the received echoes. As will be described in further detail below, the MAUI electronics 50 can be configured to control and achieve any of the methods described herein.

Multi-aperture ultrasound imaging systems described herein may be configured to utilize transducers of any desired construction. For example, 1D, 1.5D, 2D, CMUT or 55 any other transducer arrays may be utilized in multi-aperture configurations to improve overall resolution and field of view.

Point Source Transmission

In some embodiments, acoustic energy may be transmitted to as wide a two-dimensional slice as possible by using point source transmission. For example, in some 60 embodiments, a transmit aperture, such as transmit apertures 102 or

202 in FIGS. 1A and 2, respectively, may transmit acoustic energy in the form of a point source pulse from a single substantially omni-directional transducer element in an array. In alternative embodiments, a plurality of transducer elements may be provisioned to transmit a point source pulse that is relatively wide in three dimensions to insonify objects in a three dimensional space. In such embodiments, all of the beam formation may be achieved by the software or firmware associated with the transducer arrays acting as receivers. There are several advantages to using a multi-aperture ultrasound imaging technique by transmitting with a point source pulse rather than a phased array pulse. For example when using a phased array pulse, focusing tightly on transmit is problematic because the transmit pulse would have to be focused at a particular depth and would be somewhat out of focus at all other depths. Whereas, with a point source transmission an entire two-dimensional slice or three-dimensional volume can be insonified with a single point source transmit pulse.

Each echo detected at a receive aperture, such as receive apertures 104 or 204/206 in FIGS. 1A and 2, respectively, may be stored separately. If the echoes detected with elements in a receive aperture are stored separately for every point source pulse from an insonifying or transmit aperture, an entire two-dimensional image can be formed from the information received by as few as just one element. Additional copies of the image may be formed by additional receive apertures collecting data from the same set of insonifying point source pulses. Ultimately, multiple images can be created simultaneously from one or more apertures and combined to achieve a comprehensive 2D or 3D image.

Although several point source pulses are typically used in order to produce a high-quality image, fewer point source pulses are required than if each pulse were focused on a particular scan line. Since the number of pulses that can be transmitted in a given time is strictly limited by the speed of ultrasound in tissue, this yields the practical advantage that more frames can be produced per second by utilizing a point source pulse. This is very important when imaging moving organs, and in particular, the heart.

In some embodiments, a spread spectrum waveform may be imposed on a transmit aperture made up of one or more ultrasound transducer elements. A spread spectrum waveform may be a sequence of frequencies such as a chirp (e.g., frequencies progressing from low to high, or vice versa), random frequency sequence (also referred to as frequency hop), or a signal generated by a pseudo random waveform (PN sequence). These techniques can be collectively referred to as pulse compression. Pulse compression provides longer pulses for greater depth penetration without loss of depth resolution. In fact, the depth resolution may be greatly improved in the process. Spread spectrum processing typically involves much more signal processing in the form of matched filtering of each of the received signals before the delay and summation steps. The above examples of transmit pulse forms are provided for illustration only. The techniques taught herein may apply regardless of the form of the transmit pulse.

Basic Image Rendering

FIG. 1A illustrates one embodiment of a multi-aperture ultrasound imaging system 100 containing a first aperture 102 with ultrasound transmitting elements T1, T2, . . . Tn and a second aperture 104 with ultrasound receive elements R1, R2, . . . Rm. This multi-aperture ultrasound imaging system 100 is configured to be placed on the surface of an object or body to be examined (such as a human body). In some embodiments, both apertures may be sensitive to the

same plane of scan. In other embodiments, one of the apertures may be in a different plane of scan. The mechanical and acoustic position of each transducer element of each aperture must be known precisely relative to a common reference point or to each other.

In one embodiment, an ultrasound image may be produced by insonifying the entire region to be imaged, such as internal tissue or target object T, (e.g., a plane through the heart, organ, tumor, or other portion of the body) with a transmitting element (e.g., transmit element T1 of aperture 102), and then receiving echoes from the entire imaged plane on a receive element (e.g., receive element R1 of aperture 104). In some embodiments, receive functions may be performed by all elements in the receive probe (e.g., R1 through Rm). In alternative embodiments, echoes are received on only one or a select few elements of the receive aperture. The method proceeds by using each of the elements on the transmitting aperture 102 (e.g., T2, . . . Tn) and insonifying the entire region to be imaged with each of the transmitting elements in turn, and receiving echoes on the receive aperture after each insonifying pulse. Transmit elements may be operated in any desired sequential order, and need not follow a prescribed pattern. Individually, the images obtained after insonification by each transmitting element may not be sufficient to provide a high resolution image, but the combination of all the images may provide a high resolution image of the entire region to be imaged. For a scanning point represented by coordinates (i,j) as shown in FIG. 1A, it is a simple matter to calculate the total distance "a" from a particular transmit element Tx to an element of internal tissue or target object T at (i,j), and the distance "b" from that point to a particular receive element. These calculations may be performed using basic trigonometry. The sum of these distances is the total distance traveled by one ultrasound wave.

When the speed of ultrasound in tissue is assumed to be uniform throughout the tissue, it is possible to calculate the time delay from the onset of the transmit pulse to the time that an echo is received at the receive element. (Non uniform speed-of-sound in tissue is discussed below.) This one fact means that a scatterer (i.e., a reflective point within the target object) is a point in the medium for which a+b=the given time delay. The same method can be used to calculate delays for any point in the desired tissue to be imaged, creating a locus of points. FIG. 1B demonstrates that points (g,h), (i,j), (k,m), (n,p) (q,r), (s,t) all have the same time delay for transmit element T₁ and receive element R₁. A map of scatter positions and amplitudes can be rendered by tracing the echo amplitude to all of the points for the locus of equal-time-delay points. This locus takes the form of an ellipse 180 with foci at the transmit and receive elements. FIG. 1B also illustrates MAUI electronics, which can comprise the MAUI electronics described above with reference to FIGS. 1A and 2.

The fact that all points on the ellipse 180 are returned with the same time delay presents a display challenge, since distinguishing points along the ellipse from one another within a single image is not possible. However, by combining images obtained from multiple receive points, the points may be more easily distinguished, since the equal-time-delay ellipses defined by the multiple receive apertures will be slightly different.

FIG. 1C shows that with a transmit pulse from element T1, echoes from a single scatterer (n,p) are received by different receive elements such as R1, R2, and R3 at different times. The loci of the same scatterer can be represented by ellipses 180, 185 and 190 of FIG. 1C. The

location at which these ellipses intersect (point n,p) represents the true location of the scatterer. Beam forming hardware, firmware, or software can combine the echoes from each receive element to generate an image, effectively reinforcing the image at the intersection of the ellipses. In some embodiments, many more receiver elements than the three shown may be used in order to obtain a desirable signal-to-noise ratio for the image. FIG. 1C also illustrates MAUI electronics, which can comprise the MAUI electronics described above with reference to FIGS. 1A and 2.

A method of rendering the location of all of the scatterers in the target object, and thus forming a two dimensional cross section of the target object, will now be described with reference to multi-aperture ultrasound imaging system 300 of FIG. 3. FIG. 3 illustrates a grid of points to be imaged by apertures 302 and 304. A point on the grid is given the rectangular coordinates (i,j). The complete image will be a two dimensional array called "echo." In the grid of FIG. 3, m_h is the maximum horizontal dimension of the array and m_v is the maximum vertical dimension. FIG. 3 also illustrates MAUI electronics, which can comprise the MAUI electronics described above with reference to FIGS. 1A and 2.

In one embodiment, the following pseudo code may be used to accumulate all of the information to be gathered from a transmit pulse from one transmit element (e.g., one element of $T_1 \dots T_n$ from aperture 302), and the consequent echoes received by one receive element (e.g., one element of $R_1 \dots R_m$ from aperture 304) in the arrangement of FIG. 3.

```

for (i = 0; i < mh; i++){
  for (j = 0; j < mv; j++){
    compute distance a
    compute distance b
    compute time equivalent of a+b
    echo[i][j] = echo[i][j] + stored received echo at the computed time delay.
  }
}

```

40

The fixed delay is primarily the time from the transmit pulse until the first echoes are received. As will be discussed later, an increment can be added or subtracted to compensate for varying fat layers.

A complete two dimensional image may be formed by repeating this process for every receive element in aperture 304 (e.g., $R_1 \dots R_m$). In some embodiments, it is possible to implement this code in parallel hardware resulting in real time image formation.

Combining similar images resulting from pulses from other transmit elements will improve the quality (e.g., in terms of signal-to-noise ratio) of the image. In some embodiments, the combination of images may be performed by a simple summation of the single point source pulse images (e.g., coherent addition). Alternatively, the combination may involve taking the absolute value of each element of the single point source pulse images first before summation (e.g., incoherent addition). In some embodiments, the first technique (coherent addition) may be best used for improving lateral resolution, and the second technique (incoherent addition) may be best applied for the reduction of speckle noise. In addition, the incoherent technique may be used with less precision required in the measurement of the relative positions of the transmit and receive apertures. A combination of both techniques may be used to provide an optimum balance of improved lateral resolution and reduced

speckle noise. Finally, in the case of coherent addition, the final sum should be replaced by the absolute value of each element, and in both cases, some form of compression of the dynamic range may be used so that both prominent features and more-subtle features appear on the same display. In some embodiments, additional pixel locations are located on a grid without scan-conversion.

In some embodiments, compression schemes may include taking the logarithm (e.g., $20 \log_{10}$ or "dB") of each element before display, or taking the nth root (e.g., 4th root) of each element before display. Other compression schemes may also be employed.

Referring still to FIG. 3, any number of receive probes and transmit probes may be combined to enhance the image of scatterer(i,j) as long as the relative positions of the transducer elements are known to a designed degree of precision, and all of the elements are in the same scan plane and are focused to either transmit energy into the scan plane or receive energy propagated in the scan plane. Any element in any probe may be used for either transmit or receive or both.

The speed-of-sound in various soft tissues throughout the body can vary by +/-10%. Using typical ultrasound techniques, it is commonly assumed that the speed-of-sound is constant in the path between the transducer and the organ of interest. This assumption is valid for narrow transducer arrays in systems using one transducer array for both transmit and receive. However, the constant speed-of-sound assumption breaks down as the transducer's aperture becomes wider because the ultrasound pulses pass through

40

more tissue and possibly diverse types of tissue, such as fat, muscle, blood vessels, etc. Tissue diversity under the width of the transducer array affects both the transmit and the receive functions.

When a scatterer is insonified by a point source pulse from a single transmit element, it reflects back an echo to all of the elements of the receiver group. Coherent addition of images collected by elements in this receive aperture can be effective if the speed-of-sound variations in the paths from scatterer (i,j) to each of the receiver elements do not exceed +/-180 degrees phase shift relative to one path chosen as reference. Referring to FIG. 3, the maximum size of the receive aperture for which coherent addition can be effective is dependent on tissue variation within the patient and cannot be computed in advance. However, a practical maximum for a particular transmit frequency can be determined from experience.

When insonifying with unfocused point source pulses, the aperture size of the transmit group is not highly critical since variation in the path time from transmitter elements to a scatterer such as scatterer (i,j) will change only the displayed position of the point. For example, a variation resulting in a phase shift of 180 degrees in the receive paths results in complete phase cancellation when using coherent addition, whereas the same variation on the transmit paths results in a displayed position error of only a half wavelength (typically about 0.2 mm), a distortion that would not be noticed.

Thus, in a multi-aperture imaging system with one aperture used only for transmit and the other used only for receive during a single transmit/receive cycle, as is illustrated in FIG. 1A, very little additional compensation for the speed-of-sound variation is needed. Although the aperture has been increased from element T1 to Rm which can be many times the width of a conventional sector scanner probe, the concern of destructive interference of the signals from scatterer (i,j) is independent of the width of the transmit aperture or the separation of the apertures, and is dependent only on the width of the receive aperture (element R1 to Rm). The standard width for which speed-of-sound variation presents a minimal problem in practice is about 16-20 mm for 3.5 MHz systems (and smaller for higher frequencies). Therefore, no explicit compensation for speed-of-sound variation is necessary if the receive aperture has the same or smaller width than standard apertures.

Substantial improvement in lateral resolution is achieved with a receive aperture of the same width as a conventional single array 1D, 1.5D or 2D ultrasound probe used for both transmit and receive, because received energy when imaging adjacent cells (i.e., regions of the target object) to that which represents a scatterer is dependent on the time difference between when an echo is expected to arrive and the time that it actually arrives. When the transmit pulse originates from the same array used for receive, the time difference is small. However, when the transmit pulse originates from a second array at some distance from the receive array, the time difference is larger and therefore more out of phase with the signal for the correct cell. The result is that fewer adjacent cells will have signals sufficiently in phase to falsely represent the true scatterer.

Referring to FIG. 4, consider the signal received at a single element (e.g., one of receive elements R1 . . . Rm) of a receive aperture 404 from a scatterer at "S". If both the transmit and receive functions are performed on the same element, the time for the ultrasound to propagate to "S" and be returned would be $2a/C$ (where C is the speed-of-sound in tissue). When the reconstruction algorithm is evaluating the signal received for a possible scatterer in an adjacent cell "S" separated "c" distance from the true scatterer, "S", the expected time of arrival is $2(\sqrt{a^2+c^2})/C$. When "c" is small, this time is almost the same and so the signal from "S" will be degraded only slightly when estimating the magnitude of the scatterer "S" in the adjacent cell. FIG. 4 also illustrates MAUI electronics, which can comprise the MAUI electronics described above.

Now consider moving the transmitting aperture 402 away from the receive aperture 404 by an angle theta ("θ"). For convenience in comparison, let the distance "b" from aperture 402 to scatterer "S" be equal to the distance "a" from aperture 404 to scatterer "S". The time for the ultrasound to propagate from the transmit aperture 402 to "S" and be returned to the receive aperture 404 would still be $(a+b)/C=2a/C$ (with $a=b$), but the expected time for the signal to propagate to the adjacent cell "S" would be $(d+\sqrt{a^2+c^2})/C=(\sqrt{(a \sin \theta - c)^2 + (a \cos \theta)^2} + \sqrt{a^2+c^2})/C$. The difference between the expected time of arrival and actual would then be $\text{Diff}=(\sqrt{(a \sin \theta - c)^2 + (a \cos \theta)^2} + \sqrt{a^2+c^2})-2a/C$.

To put some numbers in this equation, suppose that the separation of aperture 402 and aperture 404 is only 5 degrees, distance $a=400$ cells, and distance $c=1$ cell. Then the ratio of the difference in time-of-arrival for $\theta=5$ degrees to that for $\theta=0$ degrees is 33.8. That is, the drop off of display amplitude to adjacent cells is 33 times faster with $\theta=5$ degrees. The larger difference in time-of-arrival greatly

simplifies the ability to uniquely distinguish echo information from adjacent cells. Therefore, with high theta angles, the display of a point will be less visible as noise in adjacent cells and the result will be higher resolution of the real image. With multiple aperture transmitters and receivers, we can make the angle as high as needed to improve resolution.

Simulation for a realistic ultrasound system with multiple reflectors in multiple cells shows that the effect is still significant, but not as dramatic as above. For a system comprising a receive aperture of 63 elements, a θ of 10 degrees, and a transmit pulse from a point-source transmit aperture that extends for 5 cycles with cosine modulation, the lateral spread of the point spread function was improved by a factor of 2.3.

15 Explicit Compensation for Speed-of-Sound Variation

A single image may be formed by coherent averaging of all of the signals arriving at the receiver elements as a result of a single point source pulse for insonification. Summation of these images resulting from multiple point source pulses 20 can be accomplished either by coherent addition, incoherent addition, or a combination of coherent addition by groups and incoherent addition of the images from the groups. Coherent addition (retaining the phase information before addition) maximizes resolution whereas incoherent addition 25 (using the magnitude of the signals and not the phase) minimizes the effects of registration errors and averages out speckle noise. Some combination of the two modes may be preferred. Coherent addition can be used to average point source pulse images resulting from transmit elements that 30 are close together and therefore producing pulses transmitted through very similar tissue layers. Incoherent addition can then be used where phase cancellation would be a problem. In the extreme case of transmission time variation due to speed-of-sound variations, 2D image correlation can 35 be used to align images prior to addition.

When an ultrasound imaging system includes a second aperture, using the second aperture for receiving as well as transmitting produces much better resolution. In combining the images from two or more receive arrays; it is possible 40 and beneficial to use explicit compensation for the speed-of-sound variation.

Consider the tissue layer model for the three-aperture ultrasound imaging system 500 as shown in FIG. 5, which 45 illustrates the effects of varying thicknesses of different types of tissue, such as fat or muscle. A fat layer "F" is shown in FIG. 5, and the thickness of the tissue layers f1, f2, and f3 under each aperture 502, 504, and 506, respectively, is different and unknown. It is not reasonable to assume that the tissue layer at aperture 506 will be the same as at aperture 504, and so coherent addition of the signals from all of the receive elements together is not usually possible. In one example, if the tissue layer at aperture 504 were as much as 3 cm larger than that at aperture 506, this corresponds to about 3 wavelengths (at 3.5 MHz) displacement of the signals, but this is only 1.3 mm displacement of the representation of the deep tissues. For such small displacements, only a tiny amount of geometric distortion of the image would be observed. Therefore, although coherent addition is not possible, incoherent addition with displacement of one 55 image relative to the other is possible.

Image comparison techniques may be used to determine the amount of displacement needed to align image frames from left and right apertures (e.g., apertures 506 and 504, respectively). In one embodiment, the image comparison technique can be cross-correlation. Cross-correlation involves evaluating the similarity of images or image sections to identify areas with a high degree of similarity. Areas

with at least a threshold value of similarity may be assumed to be the same. Thus, by identifying areas within images with high degrees of similarity, one image (or a section thereof) may be shifted such that areas with substantial similarity overlap and enhance overall image quality. FIG. 5 also illustrates MAUI electronics, which can comprise the MAUI electronics described above.

Further, these image comparison techniques can also be used by applying sub-image analysis, which can be used to determine displacement of sub-images and accommodate for localized variation in speed-of-sound in the underlying tissue. In other words, by breaking down the images into smaller segments (e.g., halves, thirds, quarters, etc.), small portions of a first image may be compared to the corresponding small portion of a second image. The two images may then be combined by warping to assure alignment. Warping is a technique understood by those skilled in the art, and is described, for example in U.S. Pat. No. 7,269,299 to Schroeder.

The same technique of incoherent addition of images from multiple receive transducer arrays may be applied to any number of apertures. The same idea may be applied even to a single element array which is too wide to be used for coherent addition all at once. An ultrasound imaging system with a single wide array of elements may be divided into sections (apertures) each of which is small enough for coherent addition, and then the images resulting from these sections may be combined incoherently (with displacement if necessary).

Even a slight distortion of the image may be compensated for with sufficient computational power. Image renderings may be computed for one receive array using varying amounts of delay in the rendering algorithm ($\text{echo}[i][j] = \text{echo}[i][j] + \text{stored receive echo at the computed time} + \text{delay}$). Then the best matched of these (by cross-correlation or some other measure of acuity) may be incoherently added to the image from the other receive array(s). A faster technique includes calculating the cross correlation network for the uncorrected pair of images, and feeding this into a neural network trained to pick the correction delay.

Because multiple aperture ultrasound systems that can correct for speed of sound incongruities allow for significantly larger apertures, some embodiments of the multi-aperture ultrasound systems described herein can have apertures located 10 cm apart from one another. Since resolution is proportional to $2\lambda/D$, this larger aperture leads to higher resolution of tissues located well below the surface of the skin. For instance, the renal arteries are frequently located 10 cm to 15 cm below the skin and are 4 mm to 6 mm in size near the abdominal aorta. Phased array, linear array and synthetic aperture ultrasound systems usually cannot detect this physiology in most patients; specifically because the aperture size is not large enough to have adequate lateral resolution. Typically, phased array systems have aperture sizes of approximately 2 cm. Increasing the aperture size from larger than 2 cm to approximately 10 cm in a multi-aperture ultrasound system can increase the resolution by up to 5x.

3D Imaging

In some embodiments, three-dimensional information may be obtained by moving a two-dimensional imaging system and acquiring 2D slices at a number of positions or angles. From this information and using interpolation techniques, a 3D image at any position or angle may be reconstructed. Alternatively, a 2D projection of all of the data in the 3D volume may be produced. A third alternative is to use the information in a direct 3D display.

Because multi-aperture ultrasound imaging systems may result in wider probe devices, the easiest way to use them to obtain 3D data is to not move them on the patient's skin but merely rock them so that the 2D slices span the 3D volume to be imaged. In some embodiments, a mechanical rotator mechanism which records position data may be used to assist in the collection the 2D slices. In other embodiments, a freely operated ultrasound probe with precision position sensors (such as gyroscopic sensors) located in the head of the probe may be used instead. Such an apparatus allows for complete freedom of movement while collecting 2D slices. Finally, intravenous and intracavity probes may also be manufactured to accommodate wide apertures. Such probes may be manipulated in similar ways in order to collect 2D slices.

This combination is particularly desirable for 3D cardiac imaging using a multi-aperture ultrasound imaging system. Most patients have good acoustic windows in two intercostal spaces next to the sternum. A multi-aperture imaging system is ideal in this case since the intervening rib would render a flat probe useless, while a probe with at least two widely spaced apertures can be positioned such that a send aperture and a receive aperture align with separate intercostal spaces. Once a probe with multiple apertures is in place, it cannot be rotated, but it can be rocked to obtain the 3D information. A multi-aperture probe may also be used in the same intercostal space but across the sternum.

3D information may also be obtained directly with multi-aperture imaging systems having apertures that are not all in the same scan plane. In this case the elements making up the transmit aperture preferably propagate spherical waveforms (rather than circular waveforms confined to one plane of scan). The elements making up the receive apertures may likewise be sensitive to energy arriving from all directions (rather than being sensitive only to ultrasonic energy in a single plane of scan). The reconstruction pseudo code provided above may then be extended to three dimensions.

As for additional details pertinent to the present invention, materials and manufacturing techniques may be employed as within the level of those with skill in the relevant art. The same may hold true with respect to method-based aspects of the invention in terms of additional acts commonly or logically employed. Also, it is contemplated that any optional feature of the inventive variations described may be set forth and claimed independently, or in combination with any one or more of the features described herein. Likewise, reference to a singular item, includes the possibility that there are plural of the same items present. More specifically, as used herein and in the appended claims, the singular forms "a," "an," "said," and "the" include plural referents unless the context clearly dictates otherwise. It is further noted that the claims may be drafted to exclude any optional element. As such, this statement is intended to serve as antecedent basis for use of such exclusive terminology as "solely," "only" and the like in connection with the recitation of claim elements, or use of a "negative" limitation. Unless defined otherwise herein, all technical and scientific terms used herein have the same meaning as commonly understood by one of ordinary skill in the art to which this invention belongs. The breadth of the present invention is not to be limited by the subject specification, but rather only by the plain meaning of the claim terms employed.

What is claimed is:

1. A method of constructing an ultrasound image, comprising:
transmitting an omni-directional unfocused ultrasound waveform through a target region from a transmit

aperture comprising at least one transducer element and approximating a first point source; receiving ultrasound echoes from the target region with first and second receiving elements of a first receive aperture, the first receive aperture separated from the first transmit aperture; digitizing phase information and magnitude information of the ultrasound echoes received at the first receiving element as first echo data, and digitizing phase information and magnitude information of the ultrasound echoes received at the second receiving element as second echo data; retrieving position data describing a mechanical and acoustic position of each of the first receiving element, the second receiving element, and the at least one transducer element of the transmit aperture relative to a common reference point; determining, using the position data, a first time for the waveform to propagate from the first point source to a first pixel location in the target region and return to the first receiving element, and determining a second time for the waveform to propagate from the first point source to the first pixel location in the target region to return to the second receiving element; and forming a first image of the first pixel location by combining magnitude and phase of the first echo data received at the first receiving element with magnitude and phase of the second echo data received at the second receiving element.

2. The method of claim 1, further comprising:

receiving ultrasound echoes from the target region with third and fourth receiving elements of a second receive aperture, the second receive aperture separated from the first transmit aperture and the first receive aperture; digitizing phase information and magnitude information of the ultrasound echoes received at the third receiving element as third echo data, and digitizing phase information and magnitude information of the ultrasound echoes received at the fourth receiving element as fourth echo data; retrieving position data describing a mechanical and acoustic position of each of the third receiving element, the fourth receiving element relative to the common reference point; determining, using the position data, a third time for the waveform to propagate from the first point source to a first pixel location in the target region and return to the third receiving element, and determining a fourth time for the waveform to propagate from the first point source to the first pixel location in the target region to return to the fourth receiving element; and forming a second image of the first pixel location by combining magnitude and phase of the third echo data received at the third receiving element with magnitude and phase of the fourth echo data received at the fourth receiving element.

3. The method of claim 2, further comprising combining magnitude data of the first image with magnitude data of the second image without combining phase data.
4. The method of claim 1 wherein determining the first time and the second time comprises assuming a uniform speed of sound.
5. The method of claim 2 wherein determining the third time and the fourth time comprises assuming a uniform speed of sound.
- 10 6. The method of claim 1 wherein the first pixel location is disposed outside a plane defined by the first point source, the first receiving element, and the second receiving element.
- 15 7. The method of claim 1 wherein the first pixel location is disposed inside a plane defined by the first point source, the first receiving element, and the second receiving element.
- 20 8. The method of claim 1 wherein the first point source, the first receive element, and the second receive element all lie in a common plane.
- 25 9. The method of claim 2 wherein a plane defined by the first point source, the first receive element, and the second receive element is different than a plane defined by the first point source, the third receive element, and the fourth receive element.
10. The method of claim 2 wherein the first point source, the first receive element, the second receive element, the third receive element, and the fourth receive element all lie in a common plane.
- 30 11. The method of claim 1 wherein there are no transducer elements disposed within the separation between the transmit aperture and the first receive aperture.
- 35 12. The method of claim 2 wherein there are no transducer elements disposed within the separation between the transmit aperture and the second receive aperture.
13. The method of claim 2 wherein there are no transducer elements disposed within the separation between the first receive aperture and the second receive aperture.
- 40 14. The method of claim 1 wherein there are transducer elements disposed within the separation between the transmit aperture and the first receive aperture.
- 45 15. The method of claim 2 wherein there are transducer elements disposed within the separation between the transmit aperture and the second receive aperture.
16. The method of claim 2 wherein there are no transducer elements disposed within the separation between the transmit aperture and the second receive aperture.
- 50 17. The method of claim 1 wherein there are transducer elements disposed within the separation between the transmit aperture and the first receive aperture.
18. The method of claim 2 wherein the second receive aperture is separated from the first receive aperture by a distance of at least twice a minimum wavelength of ultrasound transmitted from the transmit aperture.

* * * * *

专利名称(译)	使用多孔径超声成像的点源传输和声速校正		
公开(公告)号	US10342518	公开(公告)日	2019-07-09
申请号	US16/000507	申请日	2018-06-05
[标]申请(专利权)人(译)	SPECHT DONALD F BREWER KENNETH D		
申请(专利权)人(译)	SPECHT 唐纳德 F. 布鲁尔, KENNETH D.		
当前申请(专利权)人(译)	MAUI IMAGING , INC.		
[标]发明人	SPECHT DONALD F BREWER KENNETH D		
发明人	SPECHT, DONALD F. BREWER, KENNETH D.		
IPC分类号	A61B8/08 A61B8/00 G01S15/89 G01S7/52 A61B8/14		
CPC分类号	A61B8/5246 A61B8/145 A61B8/4444 A61B8/4455 A61B8/4477 A61B8/4483 A61B8/463 A61B8/5207 A61B8/5269 G01S7/52049 G01S15/8913 G01S15/8927 G01S15/8961 G01S15/8977 A61B8/14 G01S15/8997 G01S15/8993		
优先权	61/305784 2010-02-18 US		
其他公开文献	US20180279998A1		
外部链接	Espacenet		

摘要(译)

多孔径超声成像系统和使用方法具有许多特征。在一些实施例中，多孔径超声成像系统被配置为向分离的物理超声孔径发送超声能量和从多个物理超声孔径接收超声能量。在一些实施例中，多孔径超声成像系统的发射孔径被配置为发射通过目标区域近似第一点源的全向未聚焦超声波形。在一些实施例中，利用单个接收孔接收超声能量。在其他实施例中，利用多个接收孔接收超声能量。描述了可以组合由一个或多个接收孔接收的回波以形成高分辨率超声图像的算法。额外的算法可以解决声速组织速度的变化，从而允许超声系统几乎可以在身体内或身体上的任何地方使用。

