



US010231713B2

(12) **United States Patent**
Chen et al.

(10) **Patent No.:** **US 10,231,713 B2**
(45) **Date of Patent:** **Mar. 19, 2019**

(54) **ANALOG-TO-DIGITAL DRIVE CIRCUITRY
HAVING BUILT-IN TIME GAIN
COMPENSATION FUNCTIONALITY FOR
ULTRASOUND APPLICATIONS**

(71) Applicant: **Butterfly Network, Inc.**, Guilford, CT
(US)

(72) Inventors: **Kailiang Chen**, Guilford, CT (US);
Keith G. Fife, Palo Alto, CA (US)

(73) Assignee: **Butterfly Network, Inc.**, Guilford, CT
(US)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 269 days.

(21) Appl. No.: **15/263,939**

(22) Filed: **Sep. 13, 2016**

(65) **Prior Publication Data**

US 2018/0070925 A1 Mar. 15, 2018

(51) **Int. Cl.**

A61B 8/00 (2006.01)

H03M 1/12 (2006.01)

H03M 1/06 (2006.01)

G01S 7/52 (2006.01)

A61B 8/08 (2006.01)

(52) **U.S. Cl.**

CPC **A61B 8/56** (2013.01); **A61B 8/5207**
(2013.01); **A61B 8/54** (2013.01); **G01S**
7/52033 (2013.01); **H03M 1/0617** (2013.01);
H03M 1/1245 (2013.01); **H03M 1/129**
(2013.01)

(58) **Field of Classification Search**

CPC **A61B 8/56**; **G01S 7/52033**; **H03M 1/0617**;
H03M 1/1245; **H03M 1/129**

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,810,949 A	3/1989	Schiemenz et al.
4,852,576 A	8/1989	Inbar et al.
5,233,305 A	8/1993	Nishizawa et al.
5,263,092 A	11/1993	Jang
5,351,030 A	9/1994	Kobayashi et al.
5,408,199 A	4/1995	Nagano et al.
5,482,044 A	1/1996	Lin et al.
5,757,220 A	5/1998	Murden et al.
5,955,670 A	9/1999	Goodman et al.
5,963,882 A	10/1999	Vierl et al.

(Continued)

FOREIGN PATENT DOCUMENTS

WO	WO 2010/055427 A1	5/2010
WO	WO 2011/163475 A1	12/2011

OTHER PUBLICATIONS

International Search Report and Written Opinion dated Mar. 27,
2017 in connection with International Application No. PCT/US2016/
064322.

Agarwal et al., Single-Chip Solution for Ultrasound Imaging Sys-
tems: Initial Results. 2007 IEEE Ultrasonics Symposium. Oct. 1,
2007;1563-6.

(Continued)

Primary Examiner — Daniel Pihulic


(74) *Attorney, Agent, or Firm* — Wolf, Greenfield &
Sacks, P.C.

(57)

ABSTRACT

A time gain compensation (TGC) circuit for an ultrasound
device includes a first amplifier having an integrating
capacitor and a control circuit configured to generate a TGC
control signal that controls an integration time of the inte-
grating capacitor, thereby controlling a gain of the first
amplifier. The integration time is an amount of time an input
signal is coupled to the first amplifier before the input signal
is isolated from the first amplifier.

31 Claims, 11 Drawing Sheets



(56)

References Cited


U.S. PATENT DOCUMENTS

6,163,288 A 12/2000 Yoshizawa
 6,229,375 B1 5/2001 Koen
 6,693,491 B1 2/2004 Delano
 6,828,873 B2 12/2004 Ludwig et al.
 7,253,700 B1 8/2007 Chiu
 7,313,053 B2 12/2007 Wodnicki
 8,076,995 B2 12/2011 Chiu
 8,330,536 B1 12/2012 Quinn
 8,514,007 B1 8/2013 Ahmed et al.
 8,653,890 B1 2/2014 Ahmed et al.
 8,852,103 B2 10/2014 Rothberg et al.
 9,100,046 B2 8/2015 Granger-Jones
 9,229,097 B2 1/2016 Rothberg et al.
 9,327,142 B2 5/2016 Rothberg et al.
 9,351,706 B2 5/2016 Rothberg et al.
 9,444,432 B2 9/2016 Shrivastava et al.
 9,543,925 B2 1/2017 Hau
 2002/0180520 A1 12/2002 Ueno et al.
 2007/0030070 A1 2/2007 Brueske et al.
 2007/0069934 A1 3/2007 Mills et al.
 2007/0090877 A1 4/2007 Bagheri et al.
 2007/0242567 A1 10/2007 Daft et al.
 2009/0250729 A1 10/2009 Lemmerhirt et al.
 2010/0063399 A1 3/2010 Walker et al.
 2010/0152587 A1 6/2010 Haider et al.
 2010/0164656 A1 7/2010 Chiu
 2010/0317972 A1 12/2010 Baumgartner et al.
 2011/0133841 A1 6/2011 Shifrin
 2011/0148682 A1 6/2011 Rigby et al.
 2013/0043962 A1 2/2013 Granger-Jones
 2013/0120061 A1 5/2013 van der Zanden et al.
 2014/0077874 A1 3/2014 Ahmed et al.
 2014/0114190 A1 4/2014 Chiang et al.
 2014/0184330 A1 7/2014 Dusad
 2014/0288428 A1 9/2014 Rothberg et al.
 2014/0293738 A1 10/2014 Yoshioka
 2015/0032002 A1 1/2015 Rothberg et al.
 2015/0091646 A1 4/2015 Shifrin
 2015/0280662 A1 10/2015 Nimran et al.
 2015/0297193 A1 10/2015 Rothberg et al.
 2015/0374335 A1 12/2015 Brown et al.
 2018/0070925 A1* 3/2018 Chen A61B 8/56

OTHER PUBLICATIONS

Chen et al., Ultrasonic Imaging Front-End Design for CMUT: A 3-Level 30Vpp Pulse-Shaping Pulser with Improved Efficiency and a Noise-Optimized Receiver. IEEE Asian Solid-State Circuits Conference. Nov. 12-14, 2012;173-6.
 Cheng et al., An Efficient Electrical Addressing Method Using Through-Wafer Vias for Two-Dimensional Ultrasonic Arrays. 2000 IEEE Ultrasonics Symposium. 2000;2:1179-82.
 Cheng et al., CMUT-in-CMOS ultrasonic transducer arrays with on-chip electronics. Transducers 2009. IEEE. Jun. 21, 2009;1222-5.
 Cheng et al., Electrical Through-Wafer Interconnects with Sub-PicoFarad Parasitic Capacitance. 2001 Microelectromechan Syst Conf. Aug. 24, 2001;18-21.
 Daft et al., 5F-3 A Matrix Transducer Design with Improved Image Quality and Acquisition Rate. 2007 IEEE Ultrasonics Symposium. Oct. 1, 2007;411-5.
 Daft et al., Microfabricated Ultrasonic Transducers Monolithically Integrated with High Voltage Electronics. 2004 IEEE Ultrasonics Symposium. Aug. 23, 2004;1:493-6.
 Gurun et al., Front-end CMOS electronics for monolithic integration with CMUT arrays: circuit design and initial experimental results. Proc Ultrason Symp. 2008;390-3.
 Jiajian, Time-Gain-Compensation Amplifier for Ultrasonic Echo Signal Processing. Electronics Instrumentation Laboratory, Department of Microelectronics. Delft University of Technology. Feb. 2010 81 pages.
 Khuri-Yakub et al., Miniaturized Ultrasound Imaging Probes Enabled by CMUT Arrays with Integrated Frontend Electronic Circuits. Conf Proc IEEE Eng Med Biol Soc. 2010;1:5987-90. doi:10.1109/IEMBS.2010.5627580. Epub Dec. 6, 2010. 13 pages.
 Kim et al., Design and Test of a Fully Controllable 64x128 2-D CMUT Array Integrated with Reconfigurable Frontend ASICs for Volumetric Ultrasound Imaging. IEEE. International Ultrasonics Symposium Proceedings. Oct. 7-10, 2012;77-80. doi: 10.1109/ULTSYM.2012.0019.
 Tang et al., Automatic Time Gain Compensation in Ultrasound Imaging System. 3rd International Conference on Bioinformatics and Biomedical Engineering. Jun. 11-13, 2009. 4 pages.
 International Search Report and Written Opinion dated Nov. 20, 2017 in connection with International Application No. PCT/US2017/049024.

* cited by examiner



16





FIG. 2






FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8





FIG. 9






FIG. 11

1

ANALOG-TO-DIGITAL DRIVE CIRCUITRY HAVING BUILT-IN TIME GAIN COMPENSATION FUNCTIONALITY FOR ULTRASOUND APPLICATIONS

BACKGROUND

The present disclosure relates to ultrasound devices. In particular, the present disclosure relates to analog-to-digital conversion (ADC) drive circuitry having built-in time gain compensation (TGC) functionality for ultrasound applications.

Ultrasound devices may be used to perform diagnostic imaging and/or treatment. Ultrasound imaging may be used to see internal soft tissue body structures, and to find a source of disease or to exclude any pathology. Ultrasound devices use sound waves with frequencies that are higher with respect to those audible to humans. Ultrasonic images are created by transmitting pulses of ultrasound into tissue using a probe. The sound waves are reflected off the tissue, with different tissues reflecting varying degrees of sound. These reflected sound waves may be converted to electrical signals, amplified, digitized, recorded and displayed as an image to the operator. The strength (amplitude) of the sound signal and the time it takes for the wave to travel through the body provide information used to produce an image.

Many different types of images can be formed using ultrasound devices. The images can be real-time images. For example, images can be generated that show two-dimensional cross-sections of tissue, blood flow, motion of tissue over time, the location of blood, the presence of specific molecules, the stiffness of tissue, or the anatomy of a three-dimensional region.

SUMMARY

In one embodiment, a time gain compensation (TGC) circuit for an ultrasound device includes a first amplifier having a first integrating capacitor; and a control circuit configured to generate a TGC control signal that controls an integration time of the first integrating capacitor, thereby controlling a gain of the first amplifier, the integration time comprising an amount of time an input signal is coupled to the first amplifier before the input signal is isolated from the first amplifier.

In another embodiment, an analog-to-digital converter (ADC) driver circuit for an ultrasound device includes a first amplifier having first and second integrating capacitors in a feedback configuration; and a control circuit configured to generate a time gain compensation (TGC) control signal that controls an integration time of the first and second integrating capacitors, thereby providing time gain compensation by controlling a gain of the first amplifier, the integration time comprising an amount of time that an input signal is coupled to the first amplifier before the input signal is isolated from the first amplifier.

In another embodiment, an ultrasound system includes a receive channel configured to receive electrical signals from an ultrasonic transducer; and an analog circuit block having an input coupled to the receive channel and an output coupled to an analog-to-digital converter (ADC), the analog circuit block further including an ADC driver circuit including a differential amplifier having first and second integrating capacitors in a feedback configuration; and a control circuit configured to generate a time gain compensation (TGC) control signal that controls an integration time of the first and second integrating capacitors, thereby providing

2

time gain compensation by controlling a gain of the differential amplifier, the integration time comprising an amount of time that an input signal is coupled to the differential amplifier before the input signal is isolated from the differential amplifier.

BRIEF DESCRIPTION OF THE DRAWINGS

Various aspects and embodiments of the disclosed technology will be described with reference to the following Figures. It should be appreciated that the figures are not necessarily drawn to scale. Items appearing in multiple figures are indicated by the same reference number in all the figures in which they appear, and where:

FIG. 1 is a schematic block diagram illustrating an exemplary circuit configured for transmitting and receiving ultrasound signals;

FIG. 2 is a schematic block diagram illustrating an exemplary circuit configured for transmitting and receiving ultrasound signals, according to an exemplary embodiment;

FIG. 3 is a schematic diagram of the ADC driver/TGC gain circuit block of FIG. 2;

FIG. 4 is a schematic diagram of an alternative embodiment of the ADC driver/TGC gain circuit block of FIG. 2;

FIG. 5 is a schematic block diagram illustrating an exemplary circuit configured for transmitting and receiving ultrasound signals, according to another exemplary embodiment;

FIG. 6 is a schematic diagram of the ADC driver/TGC gain/offset cancellation circuit block of FIG. 5;

FIG. 7 is a series of waveform diagrams illustrating the relationship between a varying voltage signal, V_G , which is proportional to the desired gain provided by the TGC function, and the output of the ADC driver amplifier;

FIG. 8 is a series of waveform diagrams illustrating the relationship between the varying voltage signal, V_G , and various clock signals used to control the ADC driver amplifier;

FIG. 9 illustrates the portion of the sequence represented by time segment 9 of FIG. 8;

FIG. 10 illustrates the portion of the sequence represented by time segment 10 of FIG. 8;

FIG. 11 illustrates the portion of the sequence represented by time segment 11 of FIG. 8.

DETAILED DESCRIPTION

The present disclosure recognizes that certain analog circuit components in an ultrasound receiver circuit such as an ADC driver the TGC circuit, and optionally an auto-zero block may advantageously be combined. Such functional combinations may provide one or more benefits such as, for example: reducing the number of circuit stages, providing better power performance, and/or providing finer time gain compensation control.

Aspects of the present disclosure relate to a TGC circuit for an ultrasound device and a control circuit configured to generate a TGC control signal that controls the integration time of an integrating capacitor of an amplifier (and thus the gain of the amplifier). The integration time is the amount of time an input signal is coupled to the amplifier before being isolated from the amplifier.

Embodiments of the present disclosure are described more fully hereinafter with reference to the accompanying drawings, in which some, but not all, embodiments of the present disclosure are shown. Indeed, the present disclosure can be embodied in many different forms and should not be

construed as limited to the embodiments set forth herein. Rather, these embodiments are provided so that this disclosure clearly satisfies applicable legal requirements. Like numbers refer to like elements throughout. As used herein, the terms “approximately”, “substantially,” and “about” may be used to mean within $\pm 20\%$ of a target value in some embodiments.

Ultrasonic signals are attenuated as they pass through body tissues, and thus signals received from deeper tissues are attenuated more than signals received from near field tissues. In addition, reflected signals from the deeper tissues may take longer to reach the transducer than those reflected from the near field tissues. Because of this attenuation, later arriving echoes from deep layers may be expected to have smaller amplitudes with respect to earlier arriving echoes from superficial layers, even if the deep and superficial layers have the same echogenicity. If an ultrasound image were formed by using such “raw” returned echoes, the image would appear lighter in superficial layers and darker in deep layers. Accordingly, one way to address ultrasound attenuation is through the use of time gain compensation (TGC) circuitry, in which signal gain is increased as time passes from the emitted wave pulse. This correction makes equally echogenic tissues look the same in the resulting image even if they are located at different depths.

By way of further illustration, FIG. 1 is a schematic block diagram depicting an exemplary circuit 100 configured for processing received ultrasound signals. The circuit 100 includes N ultrasonic transducers 102a . . . 102n, wherein N is an integer. The ultrasonic transducers 102a-102n are sensors in some embodiments, producing electrical signals representing received ultrasound signals. The ultrasonic transducers 102a-102n may also transmit ultrasound signals in some embodiments. In addition, the ultrasonic transducers 102a-102n may be capacitive micromachined ultrasonic transducers (CMUTs) in some embodiments. In other embodiments, ultrasonic transducers 102a-102n may be piezoelectric micromachined ultrasonic transducers (PMUTs). Further alternative types of ultrasonic transducers may also be used in other embodiments.

As also illustrated in FIG. 1, the circuit 100 further includes circuitry channels 104a . . . 104n which may correspond to a respective ultrasonic transducer 102a . . . 102n. For example, there may be eight ultrasonic transducers 102a . . . 102n and eight corresponding circuitry channels 104a . . . 104n. In some embodiments, the number of ultrasonic transducers 102a . . . 102n may be greater than the number of circuitry channels 104a . . . 104n.

The circuitry channels 104a . . . 104n may include transmit circuitry, receive circuitry, or both. For example, the transmit circuitry may include transmit decoders 106a . . . 106n coupled to respective pulsers 108a . . . 108n. The pulsers 108a . . . 108n may control the respective ultrasonic transducers 102a . . . 102n to emit ultrasound signals. The receive circuitry of the circuitry channels 104a . . . 104n may receive the electrical signals output from respective ultrasonic transducers 102a . . . 102n. In the illustrated example, each circuitry channel 104a . . . 104n includes a respective receive switch 110a . . . 110n and an amplifier 112a . . . 112n. The receive switches 110a . . . 110n may be controlled to activate/deactivate readout of an electrical signal from a given ultrasonic transducer 102a . . . 102n. More generally, the receive switches 110a . . . 110n may be receive circuits, since alternatives to a switch may be employed to perform the same function. The amplifiers 112a . . . 112n may be trans-impedance amplifiers (TIAs).

The circuit 100 may also include an averaging circuit 114, which is also referred to herein as a summer or a summing amplifier. In some embodiments, the averaging circuit 114 is a buffer or an amplifier. The averaging circuit 114 may receive output signals from one or more of the amplifiers 112a . . . 112n and may provide an averaged output signal. The averaged output signal may be formed in part by adding or subtracting the signals from the various amplifiers 112a . . . 112n. The averaging circuit 114 may include, for example, a variable feedback resistance, the value of which may be adjusted dynamically based upon the number of amplifiers 112a . . . 112n from which the averaging circuit receives signals.

The averaging circuit 114 is coupled to an auto-zero block 116. Although not specifically depicted as such, the auto-zero block 116 receives a differential input signal and is used to sample and store any offset present on the differential pair. An output of the auto-zero block 116 is coupled to a time gain compensation (TGC) circuit 118 as discussed above. In the example shown, the TGC circuit 118 further includes a variable attenuator 120 and a fixed gain amplifier 122. An output of the TGC circuit 118 is coupled to an analog-to-digital converter (ADC) 126 via ADC drivers 124. In the illustrated example, the ADC drivers 124 include a first ADC driver 125a and a second ADC driver 125b. The ADC 126 digitizes the signal(s) from the averaging circuit 114.

In one embodiment, the ADC 126 may be a successive approximation register (SAR) ADC, which samples and holds an analog input voltage and implements a binary search algorithm using a multibit register (not shown). The multibit register is initialized to midscale, where the most significant bit (MSB) of the register is set to 1 and the remaining bits are set to 0. This in turn sets an internal digital-to-analog converter (DAC) output to be $V_{REF}/2$, where V_{REF} (not shown) is a reference voltage provided to the ADC 126. A comparison is then performed to determine if the sampled input voltage V_{IN} (not shown) is less than, or greater than the DAC output V_{DAC} (not shown). If V_{IN} is greater than V_{DAC} , the comparator output is a logic high, or 1, and the MSB of the multibit register remains at 1. Conversely, if V_{IN} is less than V_{DAC} , the comparator output is a logic low and the MSB of the register is cleared to logic 0. The SAR control logic then moves to the next bit down, forces that bit high, and does another comparison. The sequence continues all the way down to the least significant bit (LSB). Once this is done, the conversion is complete and the digital word is available in the register.

It should be appreciated that various components illustrated in FIG. 1 may be located on a single substrate or on different substrates. For example, the ultrasonic transducers 102a . . . 102n may be on a first substrate 128a and the remaining illustrated components may be on a second substrate 128b. The first and/or second substrates 128a, 128b may be semiconductor substrates, such as silicon substrates. Alternatively, the components of FIG. 1 may be on a single substrate. For example, the ultrasonic transducers 102a . . . 102n and the illustrated circuitry may be monolithically integrated on the same semiconductor die. Such integration may be facilitated by using CMUTs as the ultrasonic transducers. Furthermore, the components of FIG. 1 form part of an ultrasound probe device. The ultrasound probe may, in one example, be handheld. In another example, the components of FIG. 1 form part of an ultrasound patch configured to be worn by a patient.

The present disclosure recognizes that certain components shown in FIG. 1 (and their respective functions), such as the ADC driver 124, the TGC circuit 118, and optionally

the auto-zero block **116** may advantageously be combined. Such functional combinations may provide one or more benefits such as, for example: reducing the number of circuit stages, providing better power performance, and/or providing finer time gain compensation control.

By way of further description, FIG. 2 is a schematic block diagram illustrating an exemplary circuit **200** configured for processing received ultrasound signals, according to a non-limiting embodiment of the present application. In comparison to FIG. 1, it will be seen that the circuit **200** of FIG. 2 replaces the individual TGC circuit **118** and ADC driver **124** with a single circuit block **202** representing an ADC driver having TGC gain functionality. One example of a circuit configuration for circuit block **202** is illustrated in FIG. 3.

As particularly shown in FIG. 3, the circuit block **202** includes an ADC driver circuit **302** and an auxiliary amplifier circuit **304**. The ADC driver circuit **302** includes a fully differential integrating amplifier **306**, integrating (gain) capacitors C0, C1, input resistors R0, R1, and NMOS/PMOS switches S0-S5. The auxiliary amplifier circuit **304** includes an operational amplifier **308**, feedback capacitor C2, constant current resistor R2, NMOS/PMOS switch S6, and output clock logic **310**.

The integrating capacitors C0 and C1 of the ADC driver circuit **302** provide time gain compensation, since the duration during which they integrate charge from the input signal may be varied. This varying integration time is based on an output clock signal (clks_new) generated by the auxiliary amplifier circuit **304**. The output clock signal clks_new is in turn a function of a varying voltage gain control input signal, V_G , which is proportional to the desired gain provided by the TGC function.

In operation, the state of output clock signal clks_new is low during a reset phase (with its complementary signal clks_new_b being high), with a master sample clock signal clks (which is an input to clock logic **310**) being held low. When clks_new is low during the reset phase, switches S2 and S3 of the ADC driver circuit are open, which decouples the differential input signal V_{in} from the integrating amplifier **306**. In addition, switches S0 and S1 are closed so as to clear charge on C0 and C1 and restore the amplifier **306** essentially to unity gain. Switches S4 and S5 are also closed in order to apply a common mode voltage (V_{CM}) to the inputs of the integrating amplifier **306**.

During a sample phase, an input clock signal (clks) to the clock logic **310** will be high, which passes a comparator output signal (cmpOUT) of the auxiliary amplifier circuit **304** as the output clock signal clks_new. Initially, during the sample phase, cmpOUT is high, meaning that clks_new is also high. This results in switches S2 and S3 being closed, coupling the input signal V_{in} to the differential amplifier **306**, and integrating the input signal onto capacitors C0 and C1 (with switches S0, S1, S4 and S5 being open). The amount of time that the input signal V_{in} is allowed to integrate onto C0 and C1 (and thus the amount of gain provided by differential amplifier **306**) depends on the amount of time switches S2 and S3 are closed, which in turn depends on the amount of time output clock signal clks_new remains high. In the auxiliary amplifier circuit **304**, the variable voltage V_G is applied across the capacitor C2 by closing switch S6 via an appropriate pulse of clock signal clkg and its complementary signal clkg_b. The state of cmpOUT (and hence the state of clks_new) flips from logic high to logic low after an amount of time proportional to the value of V_G . This amount of time, T_{-int} , is given by the expression:

$$T_{-int} = V_G \cdot (R_2 C_2) / V_0.$$

In turn, the integration time T_{-int} relates to an output gain for the input signal in accordance with the expression:

$$V_{out} = V_{in} / (R_0 C_0) \cdot T_{-int} = (V_{in} \cdot V_G) / V_0 (R_2 C_2) / (R_0 C_0)$$

One observation to be made from the above expression (as well as an advantage of the present TGC topology embodiments) is the ratio of two RC time constants—the time constant of the RC network $R_2 C_2$ and the time constant of the RC network $R_0 C_0$. In semiconductor chip manufacturing, actual resistor and capacitor values may deviate from the desired design values due to fabrication imperfections. However, resistor and capacitor values for such components formed on the same chip may deviate in a consistent manner, meaning that a ratio between two resistors or between two capacitors can be made very accurate, even though each individual resistor value may be off. Here, because there is a ratio of resistors and capacitors in the TGC gain equation, the TGC gain may be accurately controlled, even in a case of electrical components having inaccurate values due to semiconductor fabrication processes.

FIG. 4 illustrates an alternative topology **402** for the ADC driver circuit **302** of circuit block **200**. In this embodiment, additional switches are used with respect to the embodiment of FIG. 3. As shown in FIG. 4, switches S0 and S2 are coupled to an SAR ADC stage **126** and discharge capacitor C0 by connecting both terminals to the common mode voltage V_{CM} during the reset phase. Correspondingly, switches S1 and S3 discharge capacitor C1 by connecting both terminals to the common mode voltage V_{CM} during the reset phase. In addition, switches S9 and S10 short circuit V_{in} and V_{out} during the reset phase. During sampling and integration, switches S4 and S5 allow the input signal V_{in} to be integrated onto capacitor C0, while switches S7 and S8 allow the input signal V_{in} to be integrated onto capacitor C1.

As will further be observed from the embodiment of FIG. 4, integrating capacitors C0 and C1 may also serve as sample and hold (S/H) capacitors for ADC inputs of an SAR ADC topology, in addition to providing time gain compensation. After the integration phase, switches S0/S2 and S1/S3 may be used to connect capacitors C0 and C1, respectively, via the SAR ADC stage **126** to perform the analog to digital conversion using the aforementioned SAR algorithm. After the end of each ADC conversion operation, capacitors C0 and C1 are reset to V_{CM} and their respective charges cleared.

In addition to ADC driver and TGC functionality, alternative embodiments herein may also be used to further combine these features with zero-offset capability. Accordingly, FIG. 5 is a schematic block diagram illustrating an exemplary circuit **500** configured for processing received ultrasound signals, according to a non-limiting embodiment of the present application. In comparison to FIG. 1 and FIG. 2, it will be seen that the circuit **500** of FIG. 5 replaces the individual auto-zero block **116**, TGC circuit **118** and ADC driver **124** with a single circuit block **502** representing an ADC driver having TGC gain and offset cancellation functionality.

As more particularly shown in FIG. 6, circuit block **502** includes an ADC driver circuit **602** and an auxiliary amplifier circuit **604**. For ease of description and comparison, embodiments having similar components are designated with like reference numerals. The ADC driver circuit **602** includes a fully differential integrating amplifier **306**, integrating (gain) capacitors C0, C1, sample and hold capacitors C3, C4, offset voltage capacitors C5, C6, input resistors R0, R1, and NMOS/PMOS switches S0, S1, S2, S3, S4, S5, S7 and S8. The auxiliary amplifier circuit **604** includes an

operational amplifier 308, feedback capacitor C2, constant current resistor R2, NMOS/PMOS switch S6, and output clock logic 606. As further shown in FIG. 5, clock logic 608 illustrates the generation of additional clock signals used by the ADC driver circuit 602 to implement ADC sample and hold functionality, TGC functionality, and offset cancellation (auto-zero) functionality. In comparison with the embodiments of FIG. 3 and FIG. 4, the integrating (gain) capacitors C0 and C1 are different than sample and hold capacitors C3 and C4, and may have smaller capacitance values than C3 and C4. This in turn allows for larger resistance values for R0 and R1, thus reducing power.

Referring now to FIG. 7, there is shown a series of waveform diagrams illustrating the TGC functionality provided by circuit block 502 in the embodiment of FIG. 6. It should be understood that the voltage levels and frequencies of the signals depicted in FIG. 7 are exemplary only, and may not necessarily correspond to an actual operation of receiving ultrasound signals. Rather, the exemplary waveforms depict example inputs to and outputs from the circuit block 500 for purposes of illustration. As shown, the uppermost waveform is the varying voltage V_G , which again is proportional to the desired TGC. In the example depicted, V_G is a simple sinusoid wave oscillating at about 500 kHz, having a low value of about 0.55 volts (V) and a peak value of about 1.35 V. It will be noted that V_G varies at a much slower rate with respect to the other signals. The waveform V_{in} represents the value of the differential input signal received by circuit block 502, and is also a simple sinusoid of constant amplitude that oscillates at about 10x faster (i.e., 5 MHz) than V_G . V_{out} (sample) is the resulting output value of the integrating amplifier 306, as seen at capacitors C3 and C4, and V_{out} (smooth) is a smoothed version of V_{out} (sample).

As will be noted from FIG. 7, the value of V_G determines the amount of gain provided by the integrating amplifier 306 as seen at V_{out} . From about 1.0 μ s to about 1.5 μ s, V_G decreases from a midrange value to a minimum value. Correspondingly, the resulting gain as seen by the amplitude of V_{out} decreases to a minimum value. Subsequently, from about 1.5 μ s to about 2.5 μ s, V_G transitions from the minimum value to a maximum value, which again is reflected by the gain of V_{out} increasing from a minimum to a maximum value.

For a further understanding of the operation of circuit block 502, reference may be made to the waveform diagrams in FIG. 8, which includes the TGC signal V_G , as well as various clock signals used by the ADC driver circuit 602 and the auxiliary amplifier circuit 604. More specifically, the clock signals include: clkoff and complementary signal clkoff_b (an input to clock logic 608 which controls the auto-zero offset cancellation function); clkr2 (a first output of clock logic 608 which controls reset of the TGC gain), clks2 and complementary signal clks2_b (a second output of clock logic 608 which controls the sample and hold function for the ADC input); clki2 and complementary signal clki2_b (a third output of clock logic 608 which controls integration time and thus TGC gain, and also works in conjunction with offset cancellation); and clkg (which controls operation of the auxiliary amplifier circuit 604 to ultimately generate clki2).

As shown in FIG. 8, the timing sequence begins with a relatively long offset cancellation (auto-zero) operation. This is reflected by clock signal clkoff going high for a duration of about 0.8 μ s (e.g., from about 0.1 μ s to about 0.9 μ s), during which time there is no input differential signal present at the amplifier input. Rather, only the signal chain

DC offset is present. As also illustrated by the clock logic 608 in FIG. 6, clkr2 and clks2 are both held low during the offset cancellation time period. That is, both input clock signals clkr and clks are gated off by the complementary clock signal (clkoff_b) of clkoff. In comparison, the OR logic included in clock logic 608 causes clock signal clki2 to be held high when clkoff is high. Clock signal clkg is also off during the offset period.

In terms of the ADC driver circuit 602, during the offset period switches S4 and S5 are closed, which equalizes the input and outputs of the integrating amplifier 306. Concurrently, switches S2 and S3 are closed, which couples V_{in} to capacitors C5 and C6. Any offset voltage present (represented by V_{offset} in FIG. 6) will be captured by a difference in voltage on C5 and C6, and during the offset reset phase, there is no input differential AC signal present.

It will be noted that the offset cancellation phase is only performed once before the ultrasound receiving phase, and the offset voltage is sampled and stored in capacitors C5 and C6 throughout the whole ultrasound receiving period (typically about 50~200 μ s). In order to prevent sampling of any AC signal during this period (which may otherwise contribute to error in the offset cancellation), controls may be implemented from a higher level in the overall system control sequence to disconnect the ultrasonic transducers from the analog chain, such that only the DC offset is sampled without any AC signal in.

At the end of the offset cancellation period, clkoff goes low, which allows sampling of input signals to begin, incorporating TGC. Due to the relative high speed of the clock signals with respect to the 3.0 μ s time scale in FIG. 8, certain portions of the overall sequence labeled by time segments 9, 10 and 11 are shown in greater detail in subsequent figures.

Referring to FIG. 9, the timing diagram depicts the portion of the sequence represented by time segment 9 of FIG. 8. This period of time covers the beginning of the data sampling and reset period post-offset cancellation, at about 1.0 μ s, when clkg initially pulses high. The duration of the clkg pulse (about 8 ns) coincides with a sample clock pulse by clks2 (about 4 ns) immediately followed by a reset clock pulse by clkr2 (also about 4 ns). So long as clkg is high, capacitor C2 of the auxiliary amplifier circuit 604 is discharged, which holds the output voltage of operational amplifier 308 below the value of V_G . As a result, the comparator output signal cmpOUT is held low. Since the output clock logic 606 uses clkg_b as a gating signal, clki (and consequently clki2) is held low during sampling and reset. Once clkg turns off, the comparator output signal cmpOUT is allowed to propagate through output clock logic 606, being inverted high at clki.

Thus, immediately after a sample and reset operation, S2 and S3 close to couple the input signal V_{in} to the integrating amplifier 306. Since clkr2 and clks2 are also off when clkg goes low, switches S0 and S1 open to allow current to be integrated onto C0 and C1, and switches S7 and S8 open to decouple sample capacitors C3 and C4 from the output of integrating amplifier 306.

Another effect of clkg turning off is to allow current to begin charging capacitor C2 of the auxiliary amplifier circuit 604, which causes the output voltage of operational amplifier 308 to increase. Once this output voltage exceeds the threshold compare value as set by V_G , cmpOUT will change state from low to high, which in turn causes clki and clki2 to switch low and discontinue integration on capacitors C0 and C1. The time taken to reach this threshold compare

value is again dependent upon the magnitude of V_G , in accordance with the expression:

$$T_{-in} = V_G(R_2C_2)/V_0;$$

with the output gain for the input signal given by:

$$V_{out} = V_{in}/(R_0C_0) \cdot T_{-int} = (V_{in} \cdot V_G)/V_0(R_2C_2)/(R_0C_0)$$

The ratio of the two RC time constants $(R_2C_2)/(R_0C_0)$ may be set as desired to achieve a desired gain range. In one exemplary embodiment, the ratio of $(R_2C_2)/(R_0C_0)$ may be about 5; however, other values are also contemplated.

In the specific time segment shown in FIG. 9, the value of V_G is at about a midpoint with respect to its maximum and minimum values, and decreasing. Consequently, the on-time of $clk2$ in this segment (about 8 ns) is roughly half the available amount of total integration time allowed by the off duration of clk (e.g., about 16 ns). Once clk pulses high, $C2$ is discharged, $clk2$ turns off to isolate the input signal V_{in} from integrating amplifier 306. $Clks2$ then pulses to capture the output on $C3$ and $C4$, followed by $clkr2$ pulsing high to discharge $C0$ and $C1$ thereby resetting the integrating amplifier 306 to unity gain.

Referring now to FIG. 10, the timing diagram illustrates the time segment 10 of FIG. 8, which occurs from about 1.42 μ s to about 1.60 μ s. This segment corresponds to a time period where V_G is at a minimum value. When V_G is at a minimum, the integration time T_{int} is also at a minimum, meaning that $clk2$ has the shortest clock pulse. As shown in FIG. 10, $clk2$ has a pulse duration of about 2 ns, corresponding to the smallest TGC value provided by the ADC driver circuit 602.

By way of comparison, the timing diagram of FIG. 11 illustrates the time segment 11 of FIG. 8, which occurs from about 2.40 μ s to about 2.58 μ s. This segment corresponds to a time period where V_G is at a maximum value. When V_G is at a maximum, the integration time T_{int} is also at a maximum, meaning that $clk2$ has its longest clock pulse duration. As shown in FIG. 11, the pulse duration of $clk2$ corresponds to the entire time of the off duration of clk , resulting in the largest TGC value provided by the ADC driver circuit 602. Here, it is possible for V_G to be large enough such that the state of $cmpOUT$ does not flip prior to clk going high. In this case, it would actually be the transition of clk going high that gates off $clk2$.

As will thus be appreciated, embodiments of a TGC amplifier, which integrates and amplifies an input signal according to control signals generated from an auxiliary amplifier are disclosed. The input signal to the TGC amplifier is a continuous analog signal, operated based on a sampling clock. The amplifier outputs are discrete time analog voltage samples stored on capacitors, where the analog voltage is the amplified version of the input signal amplitude, having a gain proportional to a TGC control voltage. Prior to generating each sample, the TGC amplifier resets to clear the previous charge stored on its capacitors. The TGC amplifier is then configured into an integrating amplifier which integrates the input signal onto the capacitors, until to the point when the auxiliary amplifier trips a threshold. The integrating time, T_{int} , is proportional to a gain control input signal, V_G , and as a result the input signal is amplified up by a value proportional to V_G .

Discrete time analog voltage samples stored on capacitors may be directly coupled to an ADC, such that the analog voltage samples are turned into digital words. In this sense, a TGC amplifier may serve as an ADC driver at the same time. Furthermore, the offset cancellation functionality may be implemented in the TGC amplifier, which cancels not

only the offset from the fully differential TGC amplifier, but all the upstream offsets coming from analog front-end amplifiers preceding the TGC stage.

It should also be appreciated that although the integrating amplifier 306 is described as a fully differential amplifier in the embodiments illustrated, it can also be implemented as a single-ended amplifier in other embodiments. Conversely, while the operational amplifier 308 of the auxiliary amplifier circuit 304 is described as a single-ended amplifier, it may also be implemented as a differential amplifier in other embodiments.

The techniques described herein are exemplary, and should not be construed as implying any particular limitation on the present disclosure. It should be understood that various alternatives, combinations and modifications could be devised by those skilled in the art from the present disclosure. For example, steps associated with the processes described herein can be performed in any order, unless otherwise specified or dictated by the steps themselves. The present disclosure is intended to embrace all such alternatives, modifications and variances that fall within the scope of the appended claims.

What is claimed is:

1. A time gain compensation (TGC) circuit for an ultrasound device, comprising:

a first amplifier having a first integrating capacitor; and
a control circuit configured to control a gain of the first amplifier by generating a TGC control signal that controls an integration time of the first integrating capacitor, the integration time comprising an amount of time an input signal is coupled to the first amplifier before the input signal is isolated from the first amplifier.

2. The TGC circuit of claim 1, wherein the first amplifier comprises a differential amplifier.

3. The TGC circuit of claim 2, wherein the differential amplifier comprises an analog-to-digital converter (ADC) driver.

4. The TGC circuit of claim 1, wherein the control circuit further comprises:

a second amplifier having a feedback capacitor, the second amplifier configured as a comparator circuit, wherein the control circuit generates the TGC control signal by a comparison between an output voltage of the second amplifier and a threshold voltage determined by a value of a variable gain control input signal.

5. The TGC circuit of claim 4, wherein the second amplifier comprises an operational amplifier.

6. The TGC circuit of claim 4, wherein the integration time controlled by the TGC control signal is dependent upon an RC time constant of the control circuit and a voltage of the variable gain control input signal.

7. The TGC circuit of claim 6, wherein an output gain of the first amplifier is proportional to a ratio between resistance and capacitance values of the control circuit and resistance and capacitance values of the first amplifier.

8. The TGC circuit of claim 7, wherein the ratio is about 5.

9. The TGC circuit of claim 1, wherein the first integrating capacitor also comprises a sample and hold capacitor of an analog-to-digital converter (ADC).

10. The TGC circuit of claim 9, further comprising an offset voltage capacitor configured to store and cancel an offset voltage associated with the input signal to the first amplifier, and to store and cancel an offset voltage associated with the first amplifier itself.

11

11. An analog-to-digital converter (ADC) driver circuit for an ultrasound device, comprising:

a first amplifier having first and second integrating capacitors in a feedback configuration; and

a control circuit configured to provide time gain compensation by controlling a gain of the first amplifier by generating a time gain compensation (TGC) control signal that controls an integration time of the first and second integrating capacitors, the integration time comprising an amount of time that an input signal is coupled to the first amplifier before the input signal is isolated from the first amplifier.

12. The ADC driver circuit of claim 11, wherein the first amplifier comprises a differential amplifier.

13. The ADC driver circuit of claim 12, further comprising a pair of ADC sample and hold capacitors selectively coupled to output terminals of the differential amplifier.

14. The ADC driver circuit of claim 13, further comprising a pair of offset voltage capacitors coupled to input terminals of the differential amplifier.

15. The ADC driver circuit of claim 14, further comprising:

a first pair of switches configured to discharge the first and second integrating capacitors during a reset mode of operation;

a second pair of switches configured to couple the input signal to the differential amplifier following the reset mode of operation, and to thereafter isolate the input signal from the differential amplifier according to the TGC control signal, the second pair of switches also configured to couple the input signal to the offset voltage capacitors during an offset cancellation mode of operation;

a third pair of switches configured to equalize the input and output terminals of the differential amplifier during the offset cancellation mode; and

a fourth pair of switches configured to couple the output terminals of the differential amplifier to the ADC sample and hold capacitors during a sample mode of operation.

16. The ADC driver circuit of claim 11, wherein the control circuit further comprises:

a second amplifier having a feedback capacitor, the second amplifier configured as a comparator circuit; and wherein the TGC control signal is generated by a comparison between an output voltage of the second amplifier and a threshold voltage determined by a value of a variable gain control input signal.

17. The ADC driver circuit of claim 16, wherein the second amplifier comprises an operational amplifier.

18. The ADC driver circuit of claim 17, wherein the integration time controlled by the TGC control signal is dependent upon an RC time constant and a voltage of the variable gain control input signal.

19. The ADC driver circuit of claim 18, wherein the feedback capacitor of the control circuit is charged with a constant current such that a state of the TGC control signal changes once the output voltage of the operational amplifier exceeds the threshold voltage determined by the variable gain control input signal.

20. The ADC driver circuit of claim 19, further comprising a switch configured to selectively discharge the feedback capacitor.

21. An ultrasound system, comprising:

a receive channel configured to receive electrical signals from an ultrasonic transducer; and

12

an analog circuit block having an input coupled to the receive channel and an output coupled to an analog-to-digital converter (ADC), the analog circuit block further comprising:

an ADC driver circuit including a differential amplifier having first and second integrating capacitors in a feedback configuration; and

a control circuit configured to provide time gain compensation by generating a time gain compensation (TGC) control signal that controls an integration time of the first and second integrating capacitors, the integration time comprising an amount of time that an input signal is coupled to the differential amplifier before the input signal is isolated from the differential amplifier.

22. The ultrasound system of claim 21, wherein the ADC driver circuit further comprises:

a pair of ADC sample and hold capacitors selectively coupled to output terminals of the differential amplifier; a pair of offset voltage capacitors coupled to input terminals of the differential amplifier;

a first pair of switches configured to discharge the first and second integrating capacitors during a reset mode of operation;

a second pair of switches configured to couple the input signal to the differential amplifier following the reset mode of operation, and to thereafter isolate the input signal from the differential amplifier according to the TGC control signal, the second pair of switches also configured to couple the input signal to the offset voltage capacitors during an offset cancellation mode of operation;

a third pair of switches configured to equalize the input and output terminals of the differential amplifier during the offset cancellation mode; and

a fourth pair of switches configured to couple the output terminals of the differential amplifier to the ADC sample and hold capacitors during a sample mode of operation.

23. The ultrasound system of claim 22, wherein the control circuit further comprises:

an operational amplifier having a feedback capacitor, the operational amplifier configured as a comparator circuit; and

wherein the TGC control signal is generated by a comparison between an output voltage of the operational amplifier and a threshold voltage determined by a value of a variable gain control input signal.

24. The ultrasound system of claim 23, wherein the integration time controlled by the TGC control signal is dependent upon a capacitance of the feedback capacitor and a voltage of the variable gain control input signal.

25. The ultrasound system of claim 24, wherein the feedback capacitor of the control circuit is charged with a constant current such that a state of the TGC control signal changes once the output voltage of the operational amplifier exceeds the threshold voltage determined by the variable gain control input signal.

26. The ultrasound system of claim 25, wherein the control circuit further comprises a switch configured to selectively discharge the feedback capacitor.

27. The ultrasound system of claim 21, wherein the first and second integrating capacitors also serve as a pair of ADC sample and hold capacitors.

13

28. The ultrasound system of claim 27, further comprising:

a first pair of switches configured to discharge the first and second integrating capacitors during a reset mode of operation;

a second pair of switches configured to couple the input signal to the differential amplifier following the reset mode of operation, and to thereafter isolate the input signal from the differential amplifier according to the TGC control signal; and

a third pair of switches configured to couple a common mode voltage to input and output terminals of the differential amplifier during the reset mode of operation.

29. The ultrasound system of claim 27, further comprising:

a first pair of switches configured to discharge the first integrating capacitor during a reset mode of operation;

a second pair of switches configured to discharge the second integrating capacitor during the reset mode of operation;

14

a third pair of switches configured to equalize input and output terminals of the differential amplifier during the reset mode of operation; and

a fourth pair of switches configured to couple the first integrating capacitor to the input and output terminals of the differential amplifier following the reset mode of operation.

30. The ultrasound system of claim 27, wherein the control circuit further comprises:

an operational amplifier having a feedback capacitor, the operational amplifier configured as a comparator circuit; and

wherein the TGC control signal is generated by a comparison between an output voltage of the operational amplifier and a threshold voltage determined by a value of a variable gain control input signal.

31. The ultrasound system of claim 30, wherein the integration time controlled by the TGC control signal is dependent upon an RC time constant of the control circuit and a voltage of the variable gain control input signal.

* * * * *

专利名称(译)	具有用于超声应用的内置时间增益补偿功能的模数转换驱动电路		
公开(公告)号	US10231713	公开(公告)日	2019-03-19
申请号	US15/263939	申请日	2016-09-13
[标]申请(专利权)人(译)	蝴蝶网络有限公司		
申请(专利权)人(译)	蝶形网络，INC.		
当前申请(专利权)人(译)	蝶形网络，INC.		
[标]发明人	CHEN KAILIANG FIFE KEITH G		
发明人	CHEN, KAILIANG FIFE, KEITH G.		
IPC分类号	A61B8/00 G01S7/52 H03M1/06 H03M1/12 A61B8/08		
CPC分类号	A61B8/56 A61B8/5207 A61B8/54 H03M1/0617 H03M1/1245 G01S7/52033 H03M1/129		
其他公开文献	US20180070925A1		
外部链接	Espacenet		

摘要(译)

用于超声装置的时间增益补偿（TGC）电路包括具有积分电容器的第一放大器和被配置为产生控制积分电容器的积分时间的TGC控制信号的控制电路，从而控制第一放大器的增益。积分时间是在输入信号与第一放大器隔离之前输入信号耦合到第一放大器的时间量。

