



US 20170000553A1

(19) **United States**(12) **Patent Application Publication**
Wiener et al.(10) **Pub. No.: US 2017/0000553 A1**(43) **Pub. Date: Jan. 5, 2017**(54) **SURGICAL SYSTEM WITH USER
ADAPTABLE TECHNIQUES EMPLOYING
MULTIPLE ENERGY MODALITIES BASED
ON TISSUE PARAMETERS**(71) Applicant: **Ethicon Endo-Surgery, LLC,**
Guaynabo, PR (US)(72) Inventors: **Eitan T. Wiener,** Cincinnati, OH (US);
Benjamin J. Danziger, Cincinnati, OH
(US); **David C. Yates,** West Chester,
OH (US); **Kevin L. Houser,**
Springboro, OH (US)(21) Appl. No.: **15/177,449**(22) Filed: **Jun. 9, 2016****Related U.S. Application Data**


(60) Provisional application No. 62/186,984, filed on Jun. 30, 2015, provisional application No. 62/235,260, filed on Sep. 30, 2015, provisional application No. 62/235,368, filed on Sep. 30, 2015, provisional application No. 62/235,466, filed on Sep. 30, 2015, provisional application No. 62/279,635, filed on Jan. 15, 2016, provisional application No. 62/330,669, filed on May 2, 2016.


Publication Classification(51) **Int. Cl.****A61B 18/14** (2006.01)**A61B 17/32** (2006.01)(52) **U.S. Cl.****CPC ... A61B 18/1445** (2013.01); **A61B 17/320092**
(2013.01); **A61B 2017/0003** (2013.01)


(57)

ABSTRACT

Various forms are directed to systems and methods for dissection and coagulation of tissue. A method for detecting a short circuit in a surgical system configured to apply radio frequency energy and ultrasonic energy to a target surgical site that includes delivering radio frequency (RF) energy to an electrode of a surgical instrument, transitioning from delivering the RF energy to delivering ultrasonic energy to an ultrasonic blade of the surgical instrument, delivering an exploratory ultrasonic pulse to the ultrasonic blade, measuring an ultrasonic property of tissue engaged by the surgical instrument, wherein the ultrasonic property is associated with the exploratory ultrasonic pulse, determining whether the measured ultrasonic property is consistent with a behavior of low impedance tissue, and delivering ultrasonic energy to the ultrasonic blade to cut the tissue upon determining that the measured ultrasonic property is consistent with ultrasonic energy being applied to low impedance tissue.










FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16






FIG. 17






FIG. 20




FIG. 21




FIG. 22




FIG. 23




FIG. 24




FIG. 25




FIG. 26




FIG. 27




FIG. 28




FIG. 29




FIG. 30




FIG. 31




FIG. 32




FIG. 33




FIG. 34




FIG. 35




FIG. 36




FIG. 37




FIG. 38




FIG. 39




FIG. 40




FIG. 41




FIG. 42A




FIG. 42B




FIG. 43A




FIG. 43B




FIG. 44




FIG. 45




FIG. 46




FIG. 47




FIG. 48




FIG. 49




FIG. 50




FIG. 51




FIG. 52




FIG. 53




FIG. 54




FIG. 55




FIG. 56




FIG. 57




FIG. 58




FIG. 59




FIG. 60




FIG. 61




FIG. 62




FIG. 63




FIG. 64




FIG. 65




FIG. 66




FIG. 67




FIG. 68




FIG. 69




FIG. 70




FIG. 71




FIG. 72




FIG. 73

**SURGICAL SYSTEM WITH USER
ADAPTABLE TECHNIQUES EMPLOYING
MULTIPLE ENERGY MODALITIES BASED
ON TISSUE PARAMETERS**

PRIORITY

[0001] This application claims the benefit of U.S. Provisional Application Ser. No. 62/186,984 filed Jun. 30, 2015, U.S. Provisional Application Ser. No. 62/235,260, filed Sep. 30, 2015, U.S. Provisional Application Ser. No. 62/235,368, filed Sep. 30, 2015, U.S. Provisional Application Ser. No. 62/235,466, filed Sep. 30, 2015, U.S. Provisional Application Ser. No. 62/279,635, filed Jan. 15, 2016, and U.S. Provisional Application Ser. No. 62/330,669, filed May 2, 2016, the contents of which are incorporated herein by reference in their entirety.

TECHNICAL FIELD

[0002] The present disclosure generally relates to ultrasonic surgical systems and, more particularly, to ultrasonic and electrosurgical systems that allows surgeons to perform cutting and coagulation and adapt and customize techniques for performing such procedures and employing multiple energy modalities based on tissue parameters.

BACKGROUND

[0003] Ultrasonic surgical instruments are finding increasingly widespread applications in surgical procedures by virtue of the unique performance characteristics of such instruments. Depending upon specific instrument configurations and operational parameters, ultrasonic surgical instruments can provide substantially simultaneous cutting of tissue and hemostasis by coagulation, desirably minimizing patient trauma. The cutting action is typically realized by an end effector, or blade tip, at the distal end of the instrument, which transmits ultrasonic energy to tissue brought into contact with the end effector. Ultrasonic instruments of this nature can be configured for open surgical use, laparoscopic, or endoscopic surgical procedures including robotic-assisted procedures.

[0004] Some surgical instruments utilize ultrasonic energy for both precise cutting and controlled coagulation. Ultrasonic energy cuts and coagulates by vibrating a blade in contact with tissue. Vibrating at high frequencies (e.g., 55,500 times per second), the ultrasonic blade denatures protein in the tissue to form a sticky coagulum. Pressure exerted on tissue with the blade surface collapses blood vessels and allows the coagulum to form a hemostatic seal. The precision of cutting and coagulation is controlled by the surgeon's technique and adjusting the power level, blade edge, tissue traction, and blade pressure.

[0005] Electrosurgical devices for applying electrical energy to tissue in order to treat and/or destroy the tissue are also finding increasingly widespread applications in surgical procedures. An electrosurgical device typically includes a hand piece, an instrument having a distally-mounted end effector (e.g., one or more electrodes). The end effector can be positioned against the tissue such that electrical current is introduced into the tissue. Electrosurgical devices can be configured for bipolar or monopolar operation. During bipolar operation, current is introduced into and returned from the tissue by active and return electrodes, respectively, of the end effector. During monopolar operation, current is intro-

duced into the tissue by an active electrode of the end effector and returned through a return electrode (e.g., a grounding pad) separately located on a patient's body. Heat generated by the current flowing through the tissue may form hemostatic seals within the tissue and/or between tissues and thus may be particularly useful for sealing blood vessels, for example. The end effector of an electrosurgical device also may include a cutting member that is movable relative to the tissue and the electrodes to transect the tissue.

[0006] Electrical energy applied by an electrosurgical device can be transmitted to the instrument by a generator in communication with the hand piece. The electrical energy may be in the form of radio frequency ("RF") energy. RF energy is a form of electrical energy that may be in the frequency range of 200 kilohertz (kHz) to 1 megahertz (MHz). In application, an electrosurgical device can transmit low frequency RF energy through tissue, which causes ionic agitation, or friction, in effect resistive heating, thereby increasing the temperature of the tissue. Because a sharp boundary is created between the affected tissue and the surrounding tissue, surgeons can operate with a high level of precision and control, without sacrificing un-targeted adjacent tissue. The low operating temperatures of RF energy is useful for removing, shrinking, or sculpting soft tissue while simultaneously sealing blood vessels. RF energy works particularly well on connective tissue, which is primarily comprised of collagen and shrinks when contacted by heat.

[0007] The RF energy may be in a frequency range described in EN 60601-2-2:2009+A11:2011, Definition 201.3.218—HIGH FREQUENCY. For example, the frequency in monopolar RF applications may be typically restricted to less than 5 MHz. However, in bipolar RF applications, the frequency can be almost anything. Frequencies above 200 kHz can be typically used for monopolar applications in order to avoid the unwanted stimulation of nerves and muscles that would result from the use of low frequency current. Lower frequencies may be used for bipolar applications if the risk analysis shows the possibility of neuromuscular stimulation has been mitigated to an acceptable level. Normally, frequencies above 5 MHz are not used in order to minimize the problems associated with high frequency leakage currents. Higher frequencies may, however, be used in the case of bipolar applications. It is generally recognized that 10 mA is the lower threshold of thermal effects on tissue.

[0008] A challenge of using these medical devices is the inability to control and customize the power output depending on the type of tissue being treated by the devices. It would be desirable to provide a surgical instrument that overcomes some of the deficiencies of current instruments. The surgical system described herein overcomes those deficiencies.

SUMMARY

[0009] In one aspect, a method for detecting a short circuit in a surgical system configured to apply radio frequency energy and ultrasonic energy to a target surgical site is provided. The method comprises applying radio frequency (RF) energy with an end effector to the target surgical site; transitioning from applying the RF energy to applying ultrasonic energy with the end effector to the target surgical site; transmitting an exploratory ultrasonic pulse to the surgical site; measuring an ultrasonic property about the ultrasonic pulse upon transmission to the surgical site;

determining whether the ultrasonic property is consistent with a behavior of low impedance tissue when ultrasonic energy is applied to the low impedance tissue; and continuing to apply ultrasonic energy to cut the low impedance tissue if it is determined that the ultrasonic property is consistent with ultrasonic energy being applied to low impedance tissue.

[0010] In addition to the foregoing, various other method and/or system and/or program product aspects are set forth and described in the teachings such as text (e.g., claims and/or detailed description) and/or drawings of the present disclosure.

[0011] The foregoing is a summary and thus may contain simplifications, generalizations, inclusions, and/or omissions of detail; consequently, those skilled in the art will appreciate that the summary is illustrative only and is NOT intended to be in any way limiting. Other aspects, features, and advantages of the devices and/or processes and/or other subject matter described herein will become apparent in the teachings set forth herein.

[0012] In one or more various aspects, related systems include but are not limited to circuitry and/or programming for effecting herein-referenced method aspects; the circuitry and/or programming can be virtually any combination of hardware, software, and/or firmware configured to affect the herein-referenced method aspects depending upon the design choices of the system designer. In addition to the foregoing, various other method and/or system aspects are set forth and described in the teachings such as text (e.g., claims and/or detailed description) and/or drawings of the present disclosure.

[0013] Further, it is understood that any one or more of the following-described forms, expressions of forms, examples, can be combined with any one or more of the other following-described forms, expressions of forms, and examples.

[0014] The foregoing summary is illustrative only and is not intended to be in any way limiting. In addition to the illustrative aspects, embodiments, and features described above, further aspects, embodiments, and features will become apparent by reference to the drawings and the following detailed description.

FIGURES

[0015] The novel features of the described forms are set forth with particularity in the appended claims. The described forms, however, both as to organization and methods of operation, may be best understood by reference to the following description, taken in conjunction with the accompanying drawings in which:

[0016] FIG. 1 illustrates one aspect of a surgical system comprising a generator and various surgical instruments usable therewith;

[0017] FIG. 2 is a diagram of one aspect of the ultrasonic surgical instrument of FIG. 16;

[0018] FIG. 3 is a diagram of one aspect of the surgical system of FIG. 16;

[0019] FIG. 4 is a model illustrating one aspect of a motional branch current;

[0020] FIG. 5 is a structural view of one aspect of a generator architecture;

[0021] FIG. 6 illustrates one aspect of a drive system of a generator, which creates the ultrasonic electrical signal for driving an ultrasonic transducer;

[0022] FIG. 7 illustrates one aspect of a drive system of a generator comprising a tissue impedance module;

[0023] FIG. 8 illustrates one aspect of a generator for delivering multiple energy modalities to a surgical instrument;

[0024] FIG. 9 is an example graph of two waveforms of energy from one aspect of a generator;

[0025] FIG. 10 is an example graph of the sum of the waveforms of FIG. 9;

[0026] FIG. 11 is an example graph of sum of the waveforms of FIG. 9 with the RF waveform dependent on the ultrasonic waveform;

[0027] FIG. 12 is an example graph of the sum of the waveforms of FIG. 9 with the RF waveform being a function of the ultrasonic waveform;

[0028] FIG. 13 is an example graph of a complex RF waveform;

[0029] FIG. 14 illustrates one aspect of an end effector comprising RF data sensors located on the clamp arm;

[0030] FIG. 15 illustrates one aspect of the flexible circuit shown in FIG. 14 in which the sensors may be mounted to or formed integrally therewith;

[0031] FIG. 16 is a cross-sectional view of the flexible circuit shown in FIG. 15;

[0032] FIG. 17 illustrates one aspect of a segmented flexible circuit configured to fixedly attach to a clamp arm of an end effector;

[0033] FIG. 18 illustrates one aspect of a segmented flexible circuit configured to mount to a clamp arm of an end effector;

[0034] FIG. 19 illustrates one aspect of an end effector configured to measure a tissue gap G_T ;

[0035] FIG. 20 illustrates one aspect of a left-right segmented flexible circuit;

[0036] FIG. 21 illustrates one aspect of an end effector comprising segmented flexible circuit as shown in FIG. 20;

[0037] FIG. 22 illustrates the end effector shown in FIG. 21 with the clamp arm clamping tissue between the clamp arm and the ultrasonic blade;

[0038] FIG. 23 illustrates graphs of energy applied by the right and left side of an end effector based on locally sensed tissue parameters;

[0039] FIG. 24 illustrates a graph depicting one aspect of adjustment of threshold due to the measurement of a secondary tissue parameter such as continuity, temperature, pressure, and the like;

[0040] FIG. 25 is a cross-sectional view of one aspect of a flexible circuit comprising RF electrodes and data sensors embedded therein;

[0041] FIG. 26 is a cross-sectional view of one aspect of an end effector configured to sense force or pressure applied to tissue located between a clamp arm and an ultrasonic blade;

[0042] FIG. 27 is a schematic diagram of one aspect of a signal layer of a flexible circuit;

[0043] FIG. 28 is a schematic diagram of sensor wiring for the flexible circuit shown in FIG. 27;

[0044] FIG. 29 is a schematic diagram of one aspect of an RF energy drive circuit;

[0045] FIG. 30 is a graphical representation of measuring tissue gap at a preset time;

[0046] FIG. 31 is a time to preset force versus time graph for thin, medium, and thick tissue types;

[0047] FIG. 32 is a graphical depiction of a graph of three curves, where the first curve represents power (P), voltage (V_{RF}), and current (I_{RF}) versus tissue impedance (Z), the second curve and third curve represent tissue impedance (Z) versus time (t);

[0048] FIG. 33 is a plan view of one aspect of an end effector;

[0049] FIG. 34 is a side view of the end effector shown in FIG. 33 with a partial cut away view to expose the underlying structure of the clamp arm and an ultrasonic blade;

[0050] FIG. 35 is partial sectional view of the end effector shown in FIGS. 33, 34 to expose the ultrasonic blade and right and left electrodes, respectively;

[0051] FIG. 36 is a cross-sectional view taken at section 36-36 of the end effector shown in FIG. 33;

[0052] FIG. 37 is cross-sectional view taken at section 37-37 of the end effector shown in FIG. 33;

[0053] FIG. 38 is a cross-sectional view taken at section 36-36 of the end effector shown in FIG. 33, except that the ultrasonic blade has a different geometric configuration;

[0054] FIG. 39 is cross-sectional view taken at section 37-37 of the end effector shown in FIG. 33, except that the ultrasonic blade has a different geometric configuration;

[0055] FIG. 40 is a cross-sectional view taken at section 36-36 of the end effector shown in FIG. 33, except that the ultrasonic blade has a different geometric configuration;

[0056] FIG. 41 is cross-sectional view taken at section 37-37 of the end effector shown in FIG. 33, except that the ultrasonic blade has a different geometric configuration;

[0057] FIG. 42A is a graphical representation of one aspect of a medical device surrounding tissue;

[0058] FIG. 42B is a graphical representation of one aspect of a medical device compressing tissue;

[0059] FIG. 43A is a graphical representation of one aspect of a medical device compressing tissue;

[0060] FIG. 43B also depicts example forces exerted by one aspect of an end-effector of a medical device compressing tissue;

[0061] FIG. 44 illustrates a logic flow diagram of one aspect of a feedback system;

[0062] FIG. 45 is a logic flow diagram of one aspect of a process for sealing or sealing and cutting large vessels or large tissue bundles;

[0063] FIG. 46 is a logic flow diagram of one aspect of a process for sealing or sealing and cutting large vessels or large tissue bundles by dynamically changing energy being delivered from the generator during the treatment of the tissue based on the changing aperture defined by the end effector;

[0064] FIG. 47 is a logic flow diagram of one aspect of a process for sealing or sealing and cutting large vessels or large tissue bundles by dynamically communicating energy parameters to the generator during the treatment of the tissue based on the changing aperture defined by the end effector of the surgical instrument;

[0065] FIG. 48 is a logic flow diagram of a technique to seal or seal and cut vessels using RF and ultrasonic energy in conjunction with tissue impedance measurements and the aperture defined by the clamp jaw measurements;

[0066] FIG. 49 is a logic flow diagram of one aspect of a method of dynamically changing the energy delivered to a surgical instrument based on a determination of a state of coagulation of tissue being treated by the surgical instrument;

[0067] FIG. 50 is a logic flow diagram of a technique to seal or seal and cut vessels using RF and ultrasonic energy in conjunction with tissue impedance measurements;

[0068] FIG. 51 is a logic flow diagram of a technique to seal or seal and cut vessels using RF and ultrasonic energy in conjunction with tissue impedance measurements and the aperture defined by the clamp jaw measurements;

[0069] FIG. 52 is a logic flow diagram of a technique for distinguishing a short circuit from low impedance tissue while utilizing RF energy by measuring voltage properties of an exploratory ultrasonic pulse;

[0070] FIG. 53 is a logic flow diagram of a technique for distinguishing a short circuit from low impedance tissue while delivering RF energy and measuring acoustic properties of an exploratory ultrasonic pulse, according to some aspects;

[0071] FIG. 54 is a logic flow diagram of a technique for conducting a tissue sealing technique without cutting by using a combination of ultrasonic energy and RF energy, according to some aspects;

[0072] FIG. 55 is a logic flow diagram of a technique for conducting a tissue sealing technique without cutting by using a combination of ultrasonic energy and RF energy, according to some aspects;

[0073] FIG. 56 is logic flow diagram 3600 of a technique for detecting low impedance tissue or metal shorts that may cause false short circuits in RF mode;

[0074] FIG. 57 is a timing diagram of a seal only pulse sequence illustrating a basic configuration of pulsing RF and ultrasonic energy for "Seal Only" mode;

[0075] FIG. 58 is a timing diagram of a seal only pulse sequence illustrating a basic configuration of pulsing RF and ultrasonic energy for "Seal Only" mode;

[0076] FIG. 59 is a timing diagram of a seal only pulse sequence;

[0077] FIG. 60 is a timing diagram of a seal only pulse sequence;

[0078] FIG. 61 is a timing diagram of a seal and cut pulse sequence, which begins and ends with ultrasonic energy pulses delivered at the same amplitude during the sealing a cutting cycles;

[0079] FIG. 62 is a timing diagram of a seal and cut pulse sequence, which begins and ends with ultrasonic energy pulses delivered at variable amplitude during the sealing a cutting cycles;

[0080] FIG. 63 is a timing diagram of a seal only pulse sequence where the ultrasonic energy pulse current is be set based on the impedance measured with the preceding RF energy pulse;

[0081] FIG. 64 is a logic flow diagram of a technique for delivering pulses of different energy modalities to tissue;

[0082] FIG. 65 is a logic flow diagram of a technique for delivering pulses of different energy modalities to tissue;

[0083] FIG. 66 is a logic flow diagram of a technique for delivering pulses of different energy modalities to tissue;

[0084] FIG. 67 is a logic flow diagram of one aspect of a process of applying simultaneous activation of different energy modalities to tissue;

[0085] FIG. 68 is a graphical representation of RF Impedance versus Time in connection with the logic flow diagram of FIG. 67 to illustrate the ultrasonic termination impedance;

[0086] FIG. 69 illustrates an example of the quality of a seal made in a vessel using the simultaneous activation of

RF and ultrasonic energy modalities as described in connection with FIGS. 67 and 68;

[0087] FIG. 70 is a graphical representation of seal burst pressure of carotid bundles versus an RF only seal and a simultaneous RF/ultrasonic seal as described in connection with FIGS. 67-69;

[0088] FIG. 71 is a logic flow diagram of a process of simultaneous activation of RF and ultrasonic energy modalities;

[0089] FIG. 72 is a block diagram of one aspect describing the selection and application of composite load curves in a tissue seal control process; and

[0090] FIG. 73 illustrates one aspect of a neural network for controlling a generator.

DESCRIPTION

[0091] Before explaining various forms of surgical instruments in detail, it should be noted that the illustrative forms are not limited in application or use to the details of construction and arrangement of parts illustrated in the accompanying drawings and description. The illustrative forms may be implemented or incorporated in other forms, variations and modifications, and may be practiced or carried out in various ways. Further, unless otherwise indicated, the terms and expressions employed herein have been chosen for the purpose of describing the illustrative forms for the convenience of the reader and are not for the purpose of limitation thereof.

[0092] Further, it is understood that any one or more of the following-described forms, expressions of forms, examples, can be combined with any one or more of the other following-described forms, expressions of forms, and examples.

[0093] Various forms are directed to improved ultrasonic and/or electrosurgical (RF) instruments configured for effecting tissue dissecting, cutting, and/or coagulation during surgical procedures. In one form, a combined ultrasonic and electrosurgical instrument may be configured for use in open surgical procedures, but has applications in other types of surgery, such as laparoscopic, endoscopic, and robotic-assisted procedures. Versatile use is facilitated by selective use of ultrasonic and RF energy.

[0094] The various forms will be described in combination with an ultrasonic instrument as described herein. Such description is provided by way of example, and not limitation, and is not intended to limit the scope and applications thereof. For example, any one of the described forms is useful in combination with a multitude of ultrasonic instruments including those described in, for example, U.S. Pat. Nos. 5,938,633; 5,935,144; 5,944,737; 5,322,055; 5,630,420; and 5,449,370.

[0095] As will become apparent from the following description, it is contemplated that forms of the surgical instruments described herein may be used in association with an oscillator unit of a surgical system, whereby ultrasonic energy from the oscillator unit provides the desired ultrasonic actuation for the present surgical instrument. It is also contemplated that forms of the surgical instrument described herein may be used in association with a signal generator unit of a surgical system, whereby electrical energy in the form of radio frequencies (RF), for example, is used to provide feedback to the user regarding the surgical instrument. The ultrasonic oscillator and/or the signal generator unit may be non-detachably integrated with the sur-

gical instrument or may be provided as separate components, which can be electrically attachable to the surgical instrument.

[0096] One form of the present surgical apparatus is particularly configured for disposable use by virtue of its straightforward construction. However, it is also contemplated that other forms of the present surgical instrument can be configured for non-disposable or multiple uses. Detachable connection of the present surgical instrument with an associated oscillator and signal generator unit is presently disclosed for single-patient use for illustrative purposes only. However, non-detachable integrated connection of the present surgical instrument with an associated oscillator and/or signal generator unit is also contemplated. Accordingly, various forms of the presently described surgical instruments may be configured for single use and/or multiple use with either detachable and/or non-detachable integral oscillator and/or signal generator unit, without limitation, and all combinations of such configurations are contemplated to be within the scope of the present disclosure.

[0097] The surgical instruments disclosed herein are related to surgical instruments described in the following commonly owned applications and filed concurrently herewith: END7747USNP titled "Surgical System With User Adaptable Techniques Based On Tissue Type" by Yates et al., END7747USNP1 titled "Surgical System With User Adaptable Techniques" by Stulen et al., END7747USNP3 titled "Surgical System With User Adaptable Techniques Based On Tissue Impedance" by Yates et al., and END7747USNP4 titled "Surgical System With User Adaptable Techniques Employing Simultaneous Energy Modalities Based On Tissue Parameters" by Yates et al., each of which is incorporated herein by reference in its entirety.

[0098] With reference to FIGS. 1-5, one form of a surgical system 10 including an ultrasonic surgical instrument is illustrated. FIG. 1 illustrates one form of a surgical system 100 comprising a generator 102 and various surgical instruments 104, 106, 108 usable therewith. FIG. 2 is a diagram of the ultrasonic surgical instrument 104 of FIG. 1.

[0099] FIG. 1 illustrates a generator 102 configured to drive multiple surgical instruments 104, 106, 108. The first surgical instrument 104 comprises a handpiece 105, an ultrasonic transducer 120, a shaft 126, and an end effector 122. The end effector 122 comprises an ultrasonic blade 128 acoustically coupled to the transducer 120 and a clamp arm 140. The handpiece 105 comprises a trigger 143 to operate the clamp arm 140 and a combination of the toggle buttons 134a, 134b, 134c to energize and drive the ultrasonic blade 128 or other function. The toggle buttons 134a, 134b, 134c can be configured to energize the ultrasonic transducer 120 with the generator 102.

[0100] Still with reference to FIG. 1, the generator 102 also is configured to drive a second surgical instrument 106. The second surgical instrument 106 is an RF electrosurgical instrument and comprises a handpiece 107, a shaft 127, and an end effector 124. The end effector 124 comprises electrodes in the clamp arms 143 and return through the ultrasonic blade 149. The electrodes are coupled to and energized by a bipolar energy source within the generator 102. The handpiece 107 comprises a trigger 147 to operate the clamp arm 145 and an energy button 135 to actuate an energy switch to energize the electrodes in the end effector 124.

[0101] Still with reference to FIG. 1, the generator 102 also is configured to drive a combination electrosurgical and

ultrasonic instrument 108. The combination electrosurgical and ultrasonic multifunction surgical instrument 108 comprises a handpiece 109, a shaft 129, and an end effector 125. The end effector comprises an ultrasonic blade 149 and a clamp arm 145. The ultrasonic blade 149 is acoustically coupled to the ultrasonic transducer 120. The handpiece 109 comprises a trigger 147 to operate the clamp arm 145 and a combination of the toggle buttons 137a, 137b, 137c to energize and drive the ultrasonic blade 149 or other function. The toggle buttons 137a, 137b, 137c can be configured to energize the ultrasonic transducer 120 with the generator 102 and energize the ultrasonic blade 149 with a bipolar energy source also contained within the generator 102.

[0102] With reference to both FIGS. 1 and 2, the generator 102 is configurable for use with a variety of surgical devices. According to various forms, the generator 102 may be configurable for use with different surgical devices of different types including, for example, the ultrasonic surgical instrument 104, the electrosurgical or RF surgical devices, such as, the RF electrosurgical instrument 106, and the multifunction surgical instrument 108 that integrate electrosurgical RF and ultrasonic energies delivered simultaneously from the generator 102. Although in the form of FIG. 1, the generator 102 is shown separate from the surgical instruments 104, 106, 108, in one form, the generator 102 may be formed integrally with either of the surgical instrument 104, 106, 108 to form a unitary surgical system. The generator 102 comprises an input device 110 located on a front panel of the generator 102 console. The input device 110 may comprise any suitable device that generates signals suitable for programming the operation of the generator 102. The generator 102 also may comprise one or more output devices 112.

[0103] The generator 102 is coupled to an ultrasonic transducer 120 via a cable 144. The ultrasonic transducer 120 and a waveguide extending through a shaft 126 (waveguide not shown in FIG. 2) may collectively form an ultrasonic drive system driving an ultrasonic blade 128 of an end effector 122. The end effector 122 further may comprise a clamp arm 140 to clamp tissue between the clamp arm 140 and the ultrasonic blade 128. In one form, the generator 102 may be configured to produce a drive signal of a particular voltage, current, and/or frequency output signal that can be stepped or otherwise modified with high resolution, accuracy, and repeatability.

[0104] Still with reference to FIG. 2, It will be appreciated that a surgical instrument 104 may comprise any combination of the toggle buttons 134a, 134b, 134c. For example, the surgical instrument 104 could be configured to have only two toggle buttons: a toggle button 134a for producing maximum ultrasonic energy output and a toggle button 134c for producing a pulsed output at either the maximum or less than maximum power level. In this way, the drive signal output configuration of the generator 102 could be 5 continuous signals and 5 or 4 or 3 or 2 or 1 pulsed signals. In certain forms, the specific drive signal configuration may be controlled based upon, for example, EEPROM settings in the generator 102 and/or user power level selection(s).

[0105] In certain forms, a two-position switch may be provided as an alternative to a toggle button 134c. For example, a surgical instrument 104 may include a toggle button 134a for producing a continuous output at a maximum power level and a two-position toggle button 134b. In a first detented position, toggle button 134b may produce a

continuous output at a less than maximum power level, and in a second detented position the toggle button 134b may produce a pulsed output (e.g., at either a maximum or less than maximum power level, depending upon the EEPROM settings).

[0106] Still with reference to FIG. 2, forms of the generator 102 may enable communication with instrument-based data circuits. For example, the generator 102 may be configured to communicate with a first data circuit 136 and/or a second data circuit 138. For example, the first data circuit 136 may indicate a burn-in frequency slope, as described herein. Additionally or alternatively, any type of information may be communicated to second data circuit for storage therein via a data circuit interface (e.g., using a logic device). Such information may comprise, for example, an updated number of operations in which the instrument has been used and/or dates and/or times of its usage. In certain forms, the second data circuit may transmit data acquired by one or more sensors (e.g., an instrument-based temperature sensor). In certain forms, the second data circuit may receive data from the generator 102 and provide an indication to a user (e.g., an LED indication or other visible indication) based on the received data. The second data circuit 138 contained in the multifunction surgical instrument 108 of a surgical device. In some forms, the second data circuit 138 may be implemented in a many similar to that of the first data circuit 136 described herein. An instrument interface circuit may comprise a second data circuit interface to enable this communication. In one form, the second data circuit interface may comprise a tri-state digital interface, although other interfaces also may be used. In certain forms, the second data circuit may generally be any circuit for transmitting and/or receiving data. In one form, for example, the second data circuit may store information pertaining to the particular surgical instrument with which it is associated. Such information may include, for example, a model number, a serial number, a number of operations in which the surgical instrument has been used, and/or any other type of information. In some forms, the second data circuit 138 may store information about the electrical and/or ultrasonic properties of an associated transducer 120, end effector 122, or ultrasonic drive system. Various processes and techniques described herein may be executed by a generator. It will be appreciated, however, that in certain example forms, all or a part of these processes and techniques may be performed by internal logic 139 of the multifunction surgical instrument 108.

[0107] FIG. 3 is a diagram of the surgical system 100 of FIG. 1. In various forms, the generator 102 may comprise several separate functional elements, such as modules, circuits, and/or blocks. Different functional elements or modules may be configured for driving the different kinds of surgical instruments 104, 106, 108. For example, an ultrasonic generator drive circuit 114 may drive ultrasonic devices such as the ultrasonic surgical instrument 104 via a cable 142. An electrosurgery/RF generator drive circuit 116 may drive the electrosurgical instrument 106 via a cable 144. For example, the respective drive circuits 114, 116 may generate respective drive signals for driving the surgical instruments 104, 106, 108. In various forms, the ultrasonic generator drive circuit 114 (e.g., ultrasonic drive circuit) and/or the electrosurgery/RF generator drive circuit 116 (e.g., RF drive circuit) each may be formed integrally with the generator 102. Alternatively, one or more of the drive

circuits **114**, **116** may be provided as a separate circuit module electrically coupled to the generator **102**. (The drive circuits **114** and **116** are shown in phantom to illustrate this option.) Also, in some forms, the electrosurgery/RF generator drive circuit **116** may be formed integrally with the ultrasonic generator drive circuit **114**, or vice versa. Also, in some forms, the generator **102** may be omitted entirely and the drive circuits **114**, **116** may be executed by processors or other hardware within the respective surgical instruments **104**, **106**, **108**.

[0108] In other forms, the electrical outputs of the ultrasonic generator drive circuit **114** and the electrosurgery/RF generator drive circuit **116** may be combined into a single circuit to provide a single electrical signal capable of driving the multifunction surgical instrument **108** simultaneously with electrosurgical RF and ultrasonic energies via a cable **146**. The multifunction surgical instrument **108** comprises an ultrasonic transducer **120** coupled to an ultrasonic blade **149** and one or more electrodes in the end effector **124** to receive electrosurgical RF energy. In such implementations, the combined RF/ultrasonic signal is coupled to the multifunction surgical instrument **108**. The multifunction surgical instrument **108** comprises signal processing components to split the combined RF/ultrasonic signal such that the RF signal can be delivered to the electrodes in the end effector **124** and the ultrasonic signal can be delivered to the ultrasonic transducer **120**.

[0109] In accordance with the described forms, the ultrasonic generator drive circuit **114** may produce a drive signal or signals of particular voltages, currents, and frequencies, e.g., 55,500 cycles per second (Hz). The drive signal or signals may be provided to the ultrasonic surgical instrument **104**, and specifically to the transducer **120**, which may operate, for example, as described herein. The transducer **120** and a waveguide extending through the shaft **126** (waveguide not shown in FIG. 2) may collectively form an ultrasonic drive system driving an ultrasonic blade **128** of an end effector **122**. In one form, the generator **102** may be configured to produce a drive signal of a particular voltage, current, and/or frequency output signal that can be stepped or otherwise modified with high resolution, accuracy, and repeatability.

[0110] The generator **102** may be activated to provide the drive signal to the transducer **120** in any suitable manner. For example, the generator **102** may comprise a foot switch **130** coupled to the generator **102** via a foot switch cable **132**. A clinician may activate the transducer **120** by depressing the foot switch **130**. In addition, or instead of the foot switch **130** some forms of the ultrasonic surgical instrument **104** may utilize one or more switches positioned on the hand piece that, when activated, may cause the generator **102** to activate the transducer **120**. In one form, for example, the one or more switches may comprise a pair of toggle buttons **134a**, **134b** (FIG. 2), for example, to determine an operating mode of the surgical instrument **104**. When the toggle button **134a** is depressed, for example, the ultrasonic generator **102** may provide a maximum drive signal to the transducer **120**, causing it to produce maximum ultrasonic energy output. Depressing toggle button **134b** may cause the ultrasonic generator **102** to provide a user-selectable drive signal to the transducer **120**, causing it to produce less than the maximum ultrasonic energy output. The surgical instrument **104** additionally or alternatively may comprise a second switch (not shown) to, for example, indicate a position of a jaw closure

trigger for operating jaws of the end effector **122**. Also, in some forms, the ultrasonic generator **102** may be activated based on the position of the jaw closure trigger, (e.g., as the clinician depresses the jaw closure trigger to close the jaws, ultrasonic energy may be applied).

[0111] Additionally or alternatively, the one or more switches may comprise a toggle button **134c** that, when depressed, causes the generator **102** to provide a pulsed output. The pulses may be provided at any suitable frequency and grouping, for example. In certain forms, the power level of the pulses may be the power levels associated with toggle buttons **134a**, **134b** (maximum, less than maximum), for example.

[0112] In accordance with the described forms, the electrosurgery/RF generator drive circuit **116** may generate a drive signal or signals with output power sufficient to perform bipolar electrosurgery using radio frequency (RF) energy. In bipolar electrosurgery applications, the drive signal may be provided, for example, to electrodes of the electrosurgical instrument **106**, for example. Accordingly, the generator **102** may be configured for therapeutic purposes by applying electrical energy to the tissue sufficient for treating the tissue (e.g., coagulation, cauterization, tissue welding).

[0113] The generator **102** may comprise an input device **110** (FIG. 1) located, for example, on a front panel of the generator **102** console. The input device **110** may comprise any suitable device that generates signals suitable for programming the operation of the generator **102**. In operation, the user can program or otherwise control operation of the generator **102** using the input device **110**. The input device **110** may comprise any suitable device that generates signals that can be used by the generator (e.g., by one or more processors contained in the generator) to control the operation of the generator **102** (e.g., operation of the ultrasonic generator drive circuit **114** and/or electrosurgery/RF generator drive circuit **116**). In various forms, the input device **110** includes one or more of buttons, switches, thumbwheels, keyboard, keypad, touch screen monitor, pointing device, remote connection to a general purpose or dedicated computer. In other forms, the input device **110** may comprise a suitable user interface, such as one or more user interface screens displayed on a touch screen monitor, for example. Accordingly, by way of the input device **110**, the user can set or program various operating parameters of the generator, such as, for example, current (I), voltage (V), frequency (f), and/or period (T) of a drive signal or signals generated by the ultrasonic generator drive circuit **114** and/or electrosurgery/RF generator drive circuit **116**.

[0114] The generator **102** also may comprise an output device **112** (FIGS. 1, 3), such as an output indicator, located, for example, on a front panel of the generator **102** console. The output device **112** includes one or more devices for providing a sensory feedback to a user. Such devices may comprise, for example, visual feedback devices (e.g., a visual feedback device may comprise incandescent lamps, light emitting diodes (LEDs), graphical user interface, display, analog indicator, digital indicator, bar graph display, digital alphanumeric display, LCD display screen, LED indicators), audio feedback devices (e.g., an audio feedback device may comprise speaker, buzzer, audible, computer generated tone, computerized speech, voice user interface (VUI) to interact with computers through a voice/speech

platform), or tactile feedback devices (e.g., a tactile feedback device comprises any type of vibratory feedback, haptic actuator).

[0115] Although certain modules, circuits, and/or blocks of the generator **102** may be described by way of example, it can be appreciated that a greater or lesser number of modules, circuits, and/or blocks may be used and still fall within the scope of the forms. Further, although various forms may be described in terms of modules, circuits, and/or blocks to facilitate description, such modules, circuits, and/or blocks may be implemented by one or more hardware components, e.g., processors, Digital Signal Processors (DSPs), Programmable Logic Devices (PLDs), Application Specific Integrated Circuits (ASICs), circuits, registers and/or software components, e.g., programs, subroutines, logic and/or combinations of hardware and software components. Also, in some forms, the various modules described herein may be implemented utilizing similar hardware positioned within the surgical instruments **104**, **106**, **108** (i.e., the generator **102** may be omitted).

[0116] In one form, the ultrasonic generator drive circuit **114** and electrosurgery/RF drive circuit **116** may comprise one or more embedded applications implemented as firmware, software, hardware, or any combination thereof. The drive circuits **114**, **116** may comprise various executable modules such as software, programs, data, drivers, application program interfaces (APIs), and so forth. The firmware may be stored in nonvolatile memory (NVM), such as in bit-masked read-only memory (ROM) or flash memory. In various implementations, storing the firmware in ROM may preserve flash memory. The NVM may comprise other types of memory including, for example, programmable ROM (PROM), erasable programmable ROM (EPROM), electrically erasable programmable ROM (EEPROM), or battery backed random-access memory (RAM) such as dynamic RAM (DRAM), Double-Data-Rate DRAM (DDRAM), and/or synchronous DRAM (SDRAM).

[0117] In one form, the drive circuits **114**, **116** comprise a hardware component implemented as a processor for executing program instructions for monitoring various measurable characteristics of the surgical instruments **104**, **106**, **108** and generating a corresponding output control signals for operating the surgical instruments **104**, **106**, **108**. In forms in which the generator **102** is used in conjunction with the surgical instrument **104**, the output control signal may drive the ultrasonic transducer **120** in cutting and/or coagulation operating modes. Electrical characteristics of the surgical instrument **104** and/or tissue may be measured and used to control operational aspects of the generator **102** and/or provided as feedback to the user. In forms in which the generator **102** is used in conjunction with the electrosurgical instrument **106**, the output control signal may supply electrical energy (e.g., RF energy) to the end effector **124** in cutting, coagulation and/or desiccation modes. Electrical characteristics of the electrosurgical instrument **106** and/or tissue may be measured and used to control operational aspects of the generator **102** and/or provide feedback to the user. In various forms, as previously discussed, the hardware component may be implemented as a DSP, PLD, ASIC, circuits, and/or registers. In one form, the processor may be configured to store and execute computer software program instructions to generate the output signal functions for

driving various components of the surgical instruments **104**, **106**, **108**, such as the ultrasonic transducer **120** and the end effectors **122**, **124**.

[0118] FIG. 4 illustrates an equivalent circuit **150** of an ultrasonic transducer, such as the ultrasonic transducer **120** shown in FIGS. 1-3, according to one form. The circuit **150** comprises a first "motional" branch having a serially connected inductance L_s , resistance R_s and capacitance C_s that define the electromechanical properties of the resonator, and a second capacitive branch having a static capacitance C_o . Drive current I_g may be received from a generator at a drive voltage V_g , with motional current I_m flowing through the first branch and current $I_g - I_m$ flowing through the capacitive branch. Control of the electromechanical properties of the ultrasonic transducer may be achieved by suitably controlling I_g and V_g . As explained above, conventional generator architectures may include a tuning inductor L_t (shown in phantom in FIG. 4) for tuning out in a parallel resonance circuit the static capacitance C_o at a resonant frequency so that substantially all of generator's current output I_g flows through the motional branch. In this way, control of the motional branch current I_g is achieved by controlling the generator current output I_g . The tuning inductor L_t is specific to the static capacitance C_o of an ultrasonic transducer, however, and a different ultrasonic transducer having a different static capacitance requires a different tuning inductor L_t . Moreover, because the tuning inductor L_t is matched to the nominal value of the static capacitance C_o at a resonant frequency, accurate control of the motional branch current I_m is assured only at that frequency, and as frequency shifts down with transducer temperature, accurate control of the motional branch current is compromised.

[0119] Forms of the generator **102** shown in FIGS. 1-3 do not rely on a tuning inductor L_t to monitor the motional branch current I_m . Instead, the generator **102** may use the measured value of the static capacitance C_o in between applications of power for a specific ultrasonic surgical instrument **104** (along with drive signal voltage and current feedback data) to determine values of the motional branch current I_m on a dynamic and ongoing basis (e.g., in real-time). Such forms of the generator **102** are therefore able to provide virtual tuning to simulate a system that is tuned or resonant with any value of static capacitance C_o at any frequency, and not just at the resonant frequency dictated by a nominal value of the static capacitance C_o .

[0120] FIG. 5 is a simplified block diagram of a generator **200** which is one form of the generator **102** shown in FIGS. 1-3 for providing inductorless tuning as described herein, among other benefits. Additional details of the generator **102** are described in commonly assigned and contemporaneously filed U.S. patent application Ser. No. 12/896,360, titled "Surgical Generator For Ultrasonic And Electrosurgical Devices," Attorney Docket Number END6673USNP/100558, the disclosure of which is incorporated herein by reference in its entirety. With reference to FIG. 5, the generator **200** may comprise a patient isolated stage **202** in communication with a non-isolated stage **204** via a power transformer **206**. A secondary winding **208** of the power transformer **206** is contained in the isolated stage **202** and may comprise a tapped configuration (e.g., a center-tapped or a non-center-tapped configuration) to define drive signal outputs **210a**, **210b**, **210c** for outputting drive signals to different surgical devices, such as, for example, an ultrasonic surgical instrument **104** and an electrosurgical instrument

106 (as shown in FIGS. 1-3). In particular, the drive signal outputs **210a**, **210c** may output an ultrasonic drive signal (e.g., a 420V RMS drive signal) to an ultrasonic surgical instrument **104**, and the drive signal outputs **210b**, **210c** may output an electrosurgical RF drive signal (e.g., a 100V RMS drive signal) to an electrosurgical instrument **106**, with the output **210b** corresponding to the center tap of the power transformer **206**.

[0121] In certain forms, the ultrasonic and electrosurgical drive signals may be provided simultaneously to distinct surgical instruments and/or to a single surgical instrument having the capability to deliver both ultrasonic and electrosurgical energy to tissue, such as multifunction surgical instrument **108** (FIGS. 1 and 3). It will be appreciated that the electrosurgical signal, provided either to a dedicated electrosurgical instrument and/or to a combined multifunction ultrasonic/electrosurgical instrument may be either a therapeutic or sub-therapeutic level signal. For example, the ultrasonic and radio frequency signals can be delivered separately or simultaneously from a generator with a single output port in order to provide the desired output signal to the surgical instrument, as will be discussed in more detail below. Accordingly, the generator can combine the ultrasonic and electrosurgical RF energies and deliver the combined energies to the multifunction ultrasonic/electrosurgical instrument. Bipolar electrodes can be placed on one or both jaws of the end effector. One jaw may be driven by ultrasonic energy in addition to electrosurgical RF energy, working simultaneously. The ultrasonic energy may be employed to dissect tissue while the electrosurgical RF energy may be employed for vessel sealing.

[0122] The non-isolated stage **204** may comprise a power amplifier **212** having an output connected to a primary winding **214** of the power transformer **206**. In certain forms the power amplifier **212** may comprise a push-pull amplifier. For example, the non-isolated stage **204** may further comprise a logic device **216** for supplying a digital output to a digital-to-analog converter (DAC) **218**, which in turn supplies a corresponding analog signal to an input of the power amplifier **212**. In certain forms the logic device **216** may comprise a programmable gate array (PGA), a field-programmable gate array (FPGA), programmable logic device (PLD), among other logic circuits, for example. The logic device **216**, by virtue of controlling the input of the power amplifier **212** via the DAC **218**, may therefore control any of a number of parameters (e.g., frequency, waveform shape, waveform amplitude) of drive signals appearing at the drive signal outputs **210a**, **210b**, **210c**. In certain forms and as discussed below, the logic device **216**, in conjunction with a processor (e.g., a digital signal processor discussed below), may implement a number of digital signal processing (DSP)-based and/or other control techniques to control parameters of the drive signals output by the generator **200**.

[0123] Power may be supplied to a power rail of the power amplifier **212** by a switch-mode regulator **220**. In certain forms the switch-mode regulator **220** may comprise an adjustable buck regulator, for example. The non-isolated stage **204** may further comprise a first processor such as DSP processor **222**, which in one form may comprise a DSP processor such as an Analog Devices ADSP-21469 SHARC DSP, available from Analog Devices, Norwood, Mass., for example, although in various forms any suitable processor may be employed. In certain forms the DSP processor **222** may control operation of the switch-mode power converter

220 responsive to voltage feedback data received from the power amplifier **212** by the DSP processor **222** via an analog-to-digital converter (ADC) **224**. In one form, for example, the DSP processor **222** may receive as input, via the ADC **224**, the waveform envelope of a signal (e.g., an RF signal) being amplified by the power amplifier **212**. The DSP processor **222** may then control the switch-mode regulator **220** (e.g., via a pulse-width modulated (PWM) output) such that the rail voltage supplied to the power amplifier **212** tracks the waveform envelope of the amplified signal. By dynamically modulating the rail voltage of the power amplifier **212** based on the waveform envelope, the efficiency of the power amplifier **212** may be significantly improved relative to a fixed rail voltage amplifier schemes.

[0124] In certain forms, the logic device **216**, in conjunction with the DSP processor **222**, may implement a direct digital synthesizer (DDS) control scheme to control the waveform shape, frequency and/or amplitude of drive signals output by the generator **200**. In one form, for example, the logic device **216** may implement a DDS control technique by recalling waveform samples stored in a dynamically-updated look-up table (LUT), such as a RAM LUT, which may be embedded in an FPGA. This control technique is particularly useful for ultrasonic applications in which an ultrasonic transducer, such as the ultrasonic transducer **120** (FIGS. 1-3), may be driven by a clean sinusoidal current at its resonant frequency. Because other frequencies may excite parasitic resonances, minimizing or reducing the total distortion of the motional branch current may correspondingly minimize or reduce undesirable resonance effects. Because the waveform shape of a drive signal output by the generator **200** is impacted by various sources of distortion present in the output drive circuit (e.g., the power transformer **206**, the power amplifier **212**), voltage and current feedback data based on the drive signal may be input into a technique, such as an error control technique implemented by the DSP processor **222**, which compensates for distortion by suitably pre-distorting or modifying the waveform samples stored in the LUT on a dynamic, ongoing basis (e.g., in real-time). In one form, the amount or degree of pre-distortion applied to the LUT samples may be based on the error between a computed motional branch current and a desired current waveform shape, with the error being determined on a sample-by-sample basis. In this way, the pre-distorted LUT samples, when processed through the drive circuit, may result in a motional branch drive signal having the desired waveform shape (e.g., sinusoidal) for optimally driving the ultrasonic transducer. In such forms, the LUT waveform samples will therefore not represent the desired waveform shape of the drive signal, but rather the waveform shape that is required to ultimately produce the desired waveform shape of the motional branch drive signal when distortion effects are taken into account.

[0125] The non-isolated stage **204** may further comprise an ADC **226** and an ADC **228** coupled to the output of the power transformer **206** via respective isolation transformers **230**, **232** for respectively sampling the voltage and current of drive signals output by the generator **200**. In certain forms, the ADCs **226**, **228** may be configured to sample at high speeds (e.g., 80 MSPS) to enable oversampling of the drive signals. In one form, for example, the sampling speed of the ADCs **226**, **228** may enable approximately 200× (depending on frequency) oversampling of the drive signals. In certain forms, the sampling operations of the ADC **226**,

228 may be performed by a single ADC receiving input voltage and current signals via a two-way multiplexer. The use of high-speed sampling in forms of the generator **200** may enable, among other things, calculation of the complex current flowing through the motional branch (which may be used in certain forms to implement DDS-based waveform shape control described herein), accurate digital filtering of the sampled signals, and calculation of real power consumption with a high degree of precision. Voltage and current feedback data output by the ADCs **226**, **228** may be received and processed (e.g., FIFO buffering, multiplexing) by the logic device **216** and stored in data memory for subsequent retrieval by, for example, the DSP processor **222**. As noted above, voltage and current feedback data may be used as input to a technique for pre-distorting or modifying LUT waveform samples on a dynamic and ongoing basis. In certain forms, this may require each stored voltage and current feedback data pair to be indexed based on, or otherwise associated with, a corresponding LUT sample that was output by the logic device **216** when the voltage and current feedback data pair was acquired. Synchronization of the LUT samples and the voltage and current feedback data in this manner contributes to the correct timing and stability of the pre-distortion technique.

[0126] In certain forms, the voltage and current feedback data may be used to control the frequency and/or amplitude (e.g., current amplitude) of the drive signals. In one form, for example, voltage and current feedback data may be used to determine impedance phase. The frequency of the drive signal may then be controlled to minimize or reduce the difference between the determined impedance phase and an impedance phase setpoint (e.g., 0°), thereby minimizing or reducing the effects of ultrasonic distortion and correspondingly enhancing impedance phase measurement accuracy. The determination of phase impedance and a frequency control signal may be implemented in the DSP processor **222**, for example, with the frequency control signal being supplied as input to a DDS control technique implemented by the logic device **216**.

[0127] In another form, for example, the current feedback data may be monitored in order to maintain the current amplitude of the drive signal at a current amplitude setpoint. The current amplitude setpoint may be specified directly or determined indirectly based on specified voltage amplitude and power setpoints. In certain forms, control of the current amplitude may be implemented by control technique, such as, for example, a PID control technique, in the DSP processor **222**. Variables controlled by the control technique to suitably control the current amplitude of the drive signal may include, for example, the scaling of the LUT waveform samples stored in the logic device **216** and/or the full-scale output voltage of the DAC **218** (which supplies the input to the power amplifier **212**) via a DAC **234**.

[0128] The non-isolated stage **204** may further comprise a second processor such as UI processor **236** for providing, among other things user interface (UI) functionality. In one form, the UI processor **236** may comprise an Atmel AT91SAM9263 processor having an ARM 926EJ-S core, available from Atmel Corporation, San Jose, Calif., for example. Examples of UI functionality supported by the UI processor **236** may include audible and visual user feedback, communication with peripheral devices (e.g., via a Universal Serial Bus (USB) interface), communication with the foot switch **130**, communication with an input device **118**

(e.g., a touch screen display) and communication with an output device **112** (e.g., a speaker), as shown in FIG. 3, for example. The UI processor **236** may communicate with the DSP processor **222** and the logic device **216** (e.g., via serial peripheral interface (SPI) buses). Although the UI processor **236** may primarily support UI functionality, it also may coordinate with the DSP processor **222** to implement hazard mitigation in certain forms. For example, the UI processor **236** may be programmed to monitor various aspects of user input and/or other inputs (e.g., touch screen inputs, foot switch **130** inputs (FIG. 3), temperature sensor inputs) and may disable the drive output of the generator **200** when an erroneous condition is detected.

[0129] In certain forms, both the DSP processor **222** and the UI processor **236**, for example, may determine and monitor the operating state of the generator **200**. For the DSP processor **222**, the operating state of the generator **200** may dictate, for example, which control and/or diagnostic processes are implemented by the DSP processor **222**. For the UI processor **236**, the operating state of the generator **200** may dictate, for example, which elements of a user interface (e.g., display screens, sounds) are presented to a user. The respective DSP and UI processors **222**, **236** may independently maintain the current operating state of the generator **200** and recognize and evaluate possible transitions out of the current operating state. The DSP processor **222** may function as the master in this relationship and determine when transitions between operating states are to occur. The UI processor **236** may be aware of valid transitions between operating states and may confirm if a particular transition is appropriate. For example, when the DSP processor **222** instructs the UI processor **236** to transition to a specific state, the UI processor **236** may verify that requested transition is valid. In the event that a requested transition between states is determined to be invalid by the UI processor **236**, the UI processor **236** may cause the generator **200** to enter a failure mode.

[0130] The non-isolated stage **204** may further comprise a controller **238** for monitoring input devices **110** (e.g., a capacitive touch sensor used for turning the generator **200** on and off, a capacitive touch screen, e.g., as shown in FIGS. 1 and 3). In certain forms, the controller **238** may comprise at least one processor and/or other controller device in communication with the UI processor **236**. In one form, for example, the controller **238** may comprise a processor (e.g., a Mega168 8-bit controller available from Atmel) configured to monitor user input provided via one or more capacitive touch sensors. In one form, the controller **238** may comprise a touch screen controller (e.g., a QT5480 touch screen controller available from Atmel) to control and manage the acquisition of touch data from a capacitive touch screen.

[0131] In certain forms, when the generator **200** is in a "power off" state, the controller **238** may continue to receive operating power (e.g., via a line from a power supply of the generator **200**). In this way, the controller **238** may continue to monitor an input device **110** (e.g., a capacitive touch sensor located on a front panel of the generator **200**) for turning the generator **200** on and off. When the generator **200** is in the power off state, the controller **238** may wake the power supply (e.g., enable operation of one or more DC/DC voltage converters of the power supply) if activation of the "on/off" input device **110** by a user is detected. The controller **238** may therefore initiate a sequence for transitioning the generator **200** to a "power on" state. Conversely, the

controller 238 may initiate a sequence for transitioning the generator 200 to the power off state if activation of the “on/off” input device 110 is detected when the generator 200 is in the power on state. In certain forms, for example, the controller 238 may report activation of the “on/off” input device 110 to the UI processor 236, which in turn implements the necessary process sequence for transitioning the generator 200 to the power off state. In such forms, the controller 238 may have no independent ability for causing the removal of power from the generator 200 after its power on state has been established.

[0132] In certain forms, the controller 238 may cause the generator 200 to provide audible or other sensory feedback for alerting the user that a power on or power off sequence has been initiated. Such an alert may be provided at the beginning of a power on or power off sequence and prior to the commencement of other processes associated with the sequence.

[0133] In certain forms, the isolated stage 202 may comprise an instrument interface circuit 240 to, for example, provide a communication interface between a control circuit of a surgical device (e.g., a control circuit comprising hand piece switches) and components of the non-isolated stage 204, such as, for example, the programmable logic device 216, the DSP processor 222 and/or the UI processor 236. The instrument interface circuit 240 may exchange information with components of the non-isolated stage 204 via a communication link that maintains a suitable degree of electrical isolation between the stages 202, 204, such as, for example, an infrared (IR)-based communication link. Power may be supplied to the instrument interface circuit 240 using, for example, a low-dropout voltage regulator powered by an isolation transformer driven from the non-isolated stage 204.

[0134] In one form, the instrument interface circuit 240 may comprise a logic device 242 (e.g., logic circuit, programmable logic circuit, PGA, FPGA, PLD) in communication with a signal conditioning circuit 244. The signal conditioning circuit 244 may be configured to receive a periodic signal from the logic circuit 242 (e.g., a 2 kHz square wave) to generate a bipolar interrogation signal having an identical frequency. The interrogation signal may be generated, for example, using a bipolar current source fed by a differential amplifier. The interrogation signal may be communicated to a surgical device control circuit (e.g., by using a conductive pair in a cable that connects the generator 200 to the surgical device) and monitored to determine a state or configuration of the control circuit. The control circuit may comprise a number of switches, resistors and/or diodes to modify one or more characteristics (e.g., amplitude, rectification) of the interrogation signal such that a state or configuration of the control circuit is uniquely discernable based on the one or more characteristics. In one form, for example, the signal conditioning circuit 244 may comprises an ADC for generating samples of a voltage signal appearing across inputs of the control circuit resulting from passage of interrogation signal therethrough. The logic device 242 (or a component of the non-isolated stage 204) may then determine the state or configuration of the control circuit based on the ADC samples.

[0135] In one form, the instrument interface circuit 240 may comprise a first data circuit interface 246 to enable information exchange between the logic circuit 242 (or other element of the instrument interface circuit 240) and a first

data circuit disposed in or otherwise associated with a surgical device. In certain forms, for example, a first data circuit 136 (FIG. 2) may be disposed in a cable integrally attached to a surgical device hand piece, or in an adaptor for interfacing a specific surgical device type or model with the generator 200. The first data circuit 136 may be implemented in any suitable manner and may communicate with the generator according to any suitable protocol including, for example, as described herein with respect to the first circuit 136. In certain forms, the first data circuit may comprise a non-volatile storage device, such as an electrically erasable programmable read-only memory (EEPROM) device. In certain forms and referring again to FIG. 5, the first data circuit interface 246 may be implemented separately from the logic device 242 and comprise suitable circuitry (e.g., discrete logic devices, a processor) to enable communication between the programmable logic device 242 and the first data circuit. In other forms, the first data circuit interface 246 may be integral with the logic device 242.

[0136] In certain forms, the first data circuit 136 (FIG. 2) may store information pertaining to the particular surgical device with which it is associated. Such information may include, for example, a model number, a serial number, a number of operations in which the surgical device has been used, and/or any other type of information. This information may be read by the instrument interface circuit 1098 (e.g., by the logic device 242), transferred to a component of the non-isolated stage 204 (e.g., to logic device 216, DSP processor 222 and/or UI processor 236) for presentation to a user via an output device 112 (FIGS. 1 and 3) and/or for controlling a function or operation of the generator 200. Additionally, any type of information may be communicated to first data circuit 136 for storage therein via the first data circuit interface 246 (e.g., using the logic device 242). Such information may comprise, for example, an updated number of operations in which the surgical device has been used and/or dates and/or times of its usage.

[0137] As discussed previously, a surgical instrument may be detachable from a hand piece (e.g., as shown in FIGS. 1 and 2, the transducer 120 and the shaft 126 is detachable from the handpiece 105 of the ultrasonic surgical instrument 104) to promote instrument interchangeability and/or disposability. In such cases, conventional generators may be limited in their ability to recognize particular instrument configurations being used and to optimize control and diagnostic processes accordingly. The addition of readable data circuits to surgical device instruments to address this issue is problematic from a compatibility standpoint, however. For example, designing a surgical device to remain backwardly compatible with generators that lack the requisite data reading functionality may be impractical due to, for example, differing signal schemes, design complexity, and cost. Forms of instruments discussed herein address these concerns by using data circuits that may be implemented in existing surgical instruments economically and with minimal design changes to preserve compatibility of the surgical devices with current generator platforms.

[0138] With reference to FIGS. 1-3 and 5, additionally, forms of the generator 200 may enable communication with instrument-based data circuits. For example, the generator 200 may be configured to communicate with a second data circuit 138 contained in the ultrasonic surgical instrument 104 (e.g., and/or the other surgical instruments 106, 108). In some forms, the second data circuit 138 may be imple-

mented in a many similar to that of the first data circuit 136 described herein. The instrument interface circuit 240 may comprise a second data circuit interface 248 to enable this communication. In one form, the second data circuit interface 248 may comprise a tri-state digital interface, although other interfaces also may be used. In certain forms, the second data circuit may generally be any circuit for transmitting and/or receiving data. In one form, for example, the second data circuit may store information pertaining to the particular surgical instrument with which it is associated. Such information may include, for example, a model number, a serial number, a number of operations in which the surgical instrument has been used, and/or any other type of information. In some forms, the second data circuit 138 may store information about the electrical and/or ultrasonic properties of an associated transducer 120, end effector 122, or ultrasonic drive system. For example, the first data circuit 136 may indicate a burn-in frequency slope, as described herein. Additionally or alternatively, any type of information may be communicated to second data circuit for storage therein via the second data circuit interface 248 (e.g., using the logic device 242). Such information may comprise, for example, an updated number of operations in which the instrument has been used and/or dates and/or times of its usage. In certain forms, the second data circuit may transmit data acquired by one or more sensors (e.g., an instrument-based temperature sensor). In certain forms, the second data circuit may receive data from the generator 200 and provide an indication to a user (e.g., an LED indication or other visible indication) based on the received data.

[0139] In certain forms, the second data circuit and the second data circuit interface 248 may be configured such that communication between the logic device 242 and the second data circuit can be effected without the need to provide additional conductors for this purpose (e.g., dedicated conductors of a cable connecting a hand piece to the generator 200). In one form, for example, information may be communicated to and from the second data circuit using a 1-wire bus communication scheme implemented on existing cabling, such as one of the conductors used transmit interrogation signals from the signal conditioning circuit 244 to a control circuit in a hand piece. In this way, design changes or modifications to the surgical device that might otherwise be necessary are minimized or reduced. Moreover, because different types of communications implemented over a common physical channel can be frequency-band separated, the presence of a second data circuit may be “invisible” to generators that do not have the requisite data reading functionality, thus enabling backward compatibility of the surgical device instrument.

[0140] In certain forms, the isolated stage 202 may comprise at least one blocking capacitor 250-1 connected to the drive signal output 210b to prevent passage of DC current to a patient. A single blocking capacitor may be required to comply with medical regulations or standards, for example. While failure in single-capacitor designs is relatively uncommon, such failure may nonetheless have negative consequences. In one form, a second blocking capacitor 250-2 may be provided in series with the blocking capacitor 250-1, with current leakage from a point between the blocking capacitors 250-1, 250-2 being monitored by, for example, an ADC 252 for sampling a voltage induced by leakage current. The samples may be received by the logic device 242, for example. Based changes in the leakage

current (as indicated by the voltage samples in the form of FIG. 5), the generator 200 may determine when at least one of the blocking capacitors 250-1, 250-2 has failed. Accordingly, the form of FIG. 5 provides a benefit over single-capacitor designs having a single point of failure.

[0141] In certain forms, the non-isolated stage 204 may comprise a power supply 254 for outputting DC power at a suitable voltage and current. The power supply may comprise, for example, a 400 W power supply for outputting a 48 VDC system voltage. The power supply 254 may further comprise one or more DC/DC voltage converters 256 for receiving the output of the power supply to generate DC outputs at the voltages and currents required by the various components of the generator 200. As discussed above in connection with the controller 238, one or more of the DC/DC voltage converters 256 may receive an input from the controller 238 when activation of the “on/off” input device 110 (FIG. 3) by a user is detected by the controller 238 to enable operation of, or wake, the DC/DC voltage converters 256.

[0142] With reference back to FIG. 1, having described operational details of various forms of the surgical system 100 operations for the above surgical system 100 may be further described generally in terms of a process for cutting and coagulating tissue employing a surgical instrument comprising an input device 110 and the generator 102. Although a particular process is described in connection with the operational details, it can be appreciated that the process merely provides an example of how the general functionality described herein can be implemented by the surgical system 100. Further, the given process does not necessarily have to be executed in the order presented herein unless otherwise indicated. As previously discussed, the input devices 110 may be employed to program the output (e.g., impedance, current, voltage, frequency) of the surgical instruments 104, 106, 108.

[0143] FIG. 6 illustrates a generator 300 comprising one form of drive system 302, according to one aspect of the present disclosure. The generator 300 is similar to the generators 102, 200 described in connection with in FIGS. 1 and 5. The generator 300 produces an ultrasonic electrical signal for driving an ultrasonic transducer, also referred to as a drive signal. The drive system 302 is flexible and can create an ultrasonic electrical output drive signal 304 at a desired frequency and power level setting for driving an ultrasonic transducer 306. In various forms, the generator 300 may comprise several separate functional elements, such as modules, circuits, and/or blocks. Although certain modules, circuits, and/or blocks may be described by way of example, it can be appreciated that a greater or lesser number of modules, circuits, and/or blocks may be used and still fall within the scope of the forms. Further, although various forms may be described in terms of modules, circuits, and/or blocks to facilitate description, such modules, circuits, and/or blocks may be implemented by one or more hardware components, e.g., processors, Digital Signal Processors (DSPs), Programmable Logic Devices (PLDs), Application Specific Integrated Circuits (ASICs), circuits, registers and/or software components, e.g., programs, sub-routines, logic and/or combinations of hardware and software components.

[0144] In one form, the drive system 302 of the generator 300 may comprise one or more embedded applications implemented as firmware, software, hardware, or any com-

bination thereof. The drive system 302 may comprise various executable modules such as software, programs, data, drivers, application program interfaces (APIs), and so forth. The firmware may be stored in nonvolatile memory (NVM), such as in bit-masked read-only memory (ROM) or flash memory. In various implementations, storing the firmware in ROM may preserve flash memory. The NVM may comprise other types of memory including, for example, programmable ROM (PROM), erasable programmable ROM (EPROM), electrically erasable programmable ROM (EEPROM), or battery backed random-access memory (RAM) such as dynamic RAM (DRAM), Double-Data-Rate DRAM (DDRAM), and/or synchronous DRAM (SDRAM).

[0145] In one form, the drive system 302 comprises a hardware component implemented as a processor 308 for executing program instructions for monitoring various measurable characteristics of the ultrasonic surgical instrument 104 (FIG. 1) and generating various functions as an output signal for driving the ultrasonic transducer 306 in cutting and/or coagulation operating modes. It will be appreciated by those skilled in the art that the generator 300 and the drive system 302 may comprise additional or fewer components and only a simplified version of the generator 300 and the drive system 302 are described herein for conciseness and clarity. In various forms, as previously discussed, the hardware component may be implemented as a DSP, PLD, ASIC, circuits, and/or registers. In one form, the processor 308 may be configured to store and execute computer software program instructions to generate the output signal functions for driving various components of the ultrasonic surgical instrument 104 (FIG. 1), such as an ultrasonic transducer 306, an end effector, and/or a blade 340.

[0146] In one form, under control of one or more software program routines, the processor 308 executes the methods in accordance with the described forms to generate a function formed by a stepwise waveform of drive signals comprising current (I), voltage (V), and/or frequency (f) for various time intervals or periods (T). The stepwise waveforms of the drive signals may be generated by forming a piecewise linear combination of constant functions over a plurality of time intervals created by varying the generator 300 drive signals, e.g., output drive current (I), voltage (V), and/or frequency (f). The time intervals or periods (T) may be predetermined (e.g., fixed and/or programmed by the user) or may be variable. Variable time intervals may be defined by setting the drive signal to a first value and maintaining the drive signal at that value until a change is detected in a monitored characteristic. Examples of monitored characteristics may comprise, for example, transducer impedance, tissue impedance, tissue heating, tissue transection, tissue coagulation, and the like. The ultrasonic drive signals generated by the generator 300 include, without limitation, ultrasonic drive signals capable of exciting the ultrasonic transducer 306 in various vibratory modes such as, for example, the primary longitudinal mode and harmonics thereof as well flexural and torsional vibratory modes.

[0147] In one form, the executable modules comprise one or more technique(s) 310 stored in memory that when executed causes the processor 308 to generate a function formed by a stepwise waveform of drive signals comprising current (I), voltage (V), and/or frequency (f) for various time intervals or periods (T). The stepwise waveforms of the drive signals may be generated by forming a piecewise linear combination of constant functions over two or more

time intervals created by varying the generator 300 output drive current (I), voltage (V), and/or frequency (f). The drive signals may be generated either for predetermined fixed time intervals or periods (T) of time or variable time intervals or periods of time in accordance with the one or more technique(s) 310. Under control of the processor 308, the generator 300 varies (e.g., increment or decrement over time) the current (I), voltage (V), and/or frequency (f) up or down at a particular resolution for a predetermined period (T) or until a predetermined condition is detected, such as a change in a monitored characteristic (e.g., transducer impedance, tissue impedance). The steps can change in programmed increments or decrements. If other steps are desired, the generator 300 can increase or decrease the step adaptively based on measured system characteristics.

[0148] In operation, the user can program the operation of the generator 300 using the input device 312 located on the front panel of the generator 300 console. The input device 312 may comprise any suitable device that generates signals 314 that can be applied to the processor 308 to control the operation of the generator 300. In various forms, the input device 312 includes buttons, switches, thumbwheels, keyboard, keypad, touch screen monitor, pointing device, remote connection to a general purpose or dedicated computer. In other forms, the input device 312 may comprise a suitable user interface. Accordingly, by way of the input device 312, the user can set or program the current (I), voltage (V), frequency (f), and/or period (T) for programming the output function of the generator 300. The processor 308 then displays the selected power level by sending a signal on line 316 to an output indicator 318.

[0149] In various forms, the output indicator 318 may provide visual, audible, and/or tactile feedback to the surgeon to indicate the status of a surgical procedure, such as, for example, when tissue cutting and coagulating is complete based on a measured characteristic of the ultrasonic surgical instrument 104 (FIG. 1), e.g., transducer impedance, tissue impedance, or other measurements as subsequently described. By way of example, and not limitation, visual feedback comprises any type of visual indication device including incandescent lamps or light emitting diodes (LEDs), graphical user interface, display, analog indicator, digital indicator, bar graph display, digital alphanumeric display. By way of example, and not limitation, audible feedback comprises any type of buzzer, computer generated tone, computerized speech, voice user interface (VUI) to interact with computers through a voice/speech platform. By way of example, and not limitation, tactile feedback comprises any type of vibratory feedback provided through an instrument housing handle assembly.

[0150] In one form, the processor 308 may be configured or programmed to generate a digital current drive signal 320 and a digital frequency signal 322. These drive signals 320, 322 are applied to a direct digital synthesizer (DDS) circuit 324 to adjust the amplitude and the frequency (f) of the output drive signal 304 to the ultrasonic transducer 306. The output of the DDS circuit 324 is applied to an amplifier 326 whose output is applied to a transformer 328. The output of the transformer 328 is the output drive signal 304 applied to the ultrasonic transducer 306, which is coupled to the blade 340 by way of a waveguide.

[0151] In one form, the generator 300 comprises one or more measurement modules or components that may be configured to monitor measurable characteristics of the

ultrasonic surgical instrument **104** (FIG. 1). In the illustrated form, the processor **308** may be employed to monitor and calculate system characteristics. As shown, the processor **308** measures the impedance Z of the ultrasonic transducer **306** by monitoring the current supplied to the transducer **306** and the voltage applied to the ultrasonic transducer **306**. In one form, a current sense circuit **330** is employed to sense the current supplied to the ultrasonic transducer **306** and a voltage sense circuit **332** is employed to sense the output voltage applied to the ultrasonic transducer **306**. These signals may be applied to the analog-to-digital converter **336** (ADC) via an analog multiplexer **334** circuit or switching circuit arrangement. The analog multiplexer **334** routes the appropriate analog signal to the ADC **336** for conversion. In other forms, multiple ADCs **336** may be employed for each measured characteristic instead of the multiplexer **334** circuit. The processor **308** receives the digital output **338** of the ADC **336** and calculates the transducer impedance Z based on the measured values of current and voltage. The processor **308** adjusts the output drive signal **304** such that it can generate a desired power versus load curve. In accordance with programmed techniques **310**, the processor **308** can vary the drive signal **320**, e.g., the current or frequency, in any suitable increment or decrement in response to the transducer impedance Z .

[0152] Having described operational details of various forms of the surgical system **100** shown in FIG. 1, operations for the above surgical system **100** may be further described in terms of a process for cutting and coagulating a blood vessel employing a surgical instrument comprising the input device **110** and the transducer impedance measurement capabilities of the drive system **302** described with reference to FIG. 6. Although a particular process is described in connection with the operational details, it can be appreciated that the process merely provides an example of how the general functionality described herein can be implemented by the surgical system **100**. Further, the given process does not necessarily have to be executed in the order presented herein unless otherwise indicated.

[0153] FIG. 7 illustrates one aspect of a drive system of a generator **400** comprising a tissue impedance module **442**. The drive system **402** generates the ultrasonic electrical drive signal **404** to drive the ultrasonic transducer **406**. In one aspect, the tissue impedance module **442** may be configured to measure the impedance Z_t of tissue grasped between the blade **440** and the clamp arm assembly **444**. The tissue impedance module **442** comprises an RF oscillator **446**, a voltage sensing circuit **448**, and a current sensing circuit **450**. The voltage and current sensing circuits **448**, **450** respond to the RF voltage V_{rf} applied to the blade **440** electrode and the RF current I_{rf} flowing through the blade **440** electrode, the tissue, and the conductive portion of the clamp arm assembly **444**. The sensed current I_{rf} and the sensed voltage V_{rf} from the current sense circuit **430** and the voltage sense circuit **432** are converted to digital form by the ADC **436** via the analog multiplexer **434**. The processor **408** receives the digitized output **438** of the ADC **436** and determines the tissue impedance Z_t by calculating the ratio of the RF voltage V_{rf} to current I_{rf} measured by the voltage sensing circuit **448** and the current sense circuit **450**.

[0154] In one form, the processor **408** may be configured or programmed to generate a digital current signal **420** and a digital frequency signal **422**. These signals **420**, **422** are applied to a direct digital synthesizer (DDS) circuit **424** to

adjust the amplitude and the frequency (f) of the current output signal **404** to the transducer **406**. The output of the DDS circuit **424** is applied to an amplifier **426** whose output is applied to a transformer **428**. The output of the transformer **428** is the signal **404** applied to the ultrasonic transducer **406**, which is coupled to the blade **440** by way of a waveguide.

[0155] In one aspect, the transection of the inner muscle layer and the tissue may be detected by sensing the tissue impedance Z_t . Accordingly, detection of the tissue impedance Z_t may be integrated with an automated process for separating the inner muscle layer from the outer adventitia layer prior to transecting the tissue without causing a significant amount of heating, which normally occurs at resonance.

[0156] In one form, the RF voltage V_{rf} applied to the blade **440** electrode and the RF current I_{rf} flowing through the blade **440** electrode, the tissue, and the conductive portion of the clamp arm assembly **444** are suitable for vessel sealing and/or dissecting. Thus, the RF energy output of the generator **400** can be selected for non-therapeutic functions such as tissue impedance measurements as well as therapeutic functions such as vessel sealing and/or dissection. It will be appreciated, that in the context of the present disclosure, the ultrasonic and the RF electrosurgical energies can be supplied by the generator either individually or simultaneously.

[0157] In operation, the user can program the operation of the generator **400** using the input device **412** located on the front panel of the generator **400** console. The input device **412** may comprise any suitable device that generates signals **414** that can be applied to the processor **408** to control the operation of the generator **400**. In various forms, the input device **412** includes buttons, switches, thumbwheels, keyboard, keypad, touch screen monitor, pointing device, remote connection to a general purpose or dedicated computer. In other forms, the input device **412** may comprise a suitable user interface. Accordingly, by way of the input device **412**, the user can set or program the current (I), voltage (V), frequency (f), and/or period (T) for programming the function output of the generator **400**. The processor **408** then displays the selected power level by sending a signal on line **416** to an output indicator **418**.

[0158] In various forms, feedback is provided by the output indicator **418**. The output indicator **418** is particularly useful in applications where the tissue being manipulated by the end effector is out of the user's field of view and the user cannot see when a change of state occurs in the tissue. The output indicator **418** communicates to the user that a change in tissue state has occurred. As previously discussed, the output indicator **418** may be configured to provide various types of feedback to the user including, without limitation, visual, audible, and/or tactile feedback to indicate to the user (e.g., surgeon, clinician) that the tissue has undergone a change of state or condition of the tissue. By way of example, and not limitation, as previously discussed, visual feedback comprises any type of visual indication device including incandescent lamps or LEDs, graphical user interface, display, analog indicator, digital indicator, bar graph display, digital alphanumeric display. By way of example, and not limitation, audible feedback comprises any type of buzzer, computer generated tone, computerized speech, VUI to interact with computers through a voice/speech platform. By way of example, and not limitation, tactile feedback comprises any type of vibratory feedback provided through

the instrument housing handle assembly. The change of state of the tissue may be determined based on transducer and tissue impedance measurements as previously described, or based on voltage, current, and frequency measurements.

[0159] In one form, the various executable modules (e.g., algorithms **410**) comprising computer readable instructions can be executed by the processor **408** portion of the generator **400**. In various forms, the operations described with respect to the techniques may be implemented as one or more software components, e.g., programs, subroutines, logic; one or more hardware components, e.g., processors, DSPs, PLDs, ASICs, circuits, registers; and/or combinations of software and hardware. In one form, the executable instructions to perform the techniques may be stored in memory. When executed, the instructions cause the processor **408** to determine a change in tissue state provide feedback to the user by way of the output indicator **418**. In accordance with such executable instructions, the processor **408** monitors and evaluates the voltage, current, and/or frequency signal samples available from the generator **400** and according to the evaluation of such signal samples determines whether a change in tissue state has occurred. As further described below, a change in tissue state may be determined based on the type of ultrasonic instrument and the power level that the instrument is energized at. In response to the feedback, the operational mode of the ultrasonic surgical instrument may be controlled by the user or may be automatically or semi-automatically controlled.

[0160] As noted above, a single output generator can deliver both RF and ultrasonic energy through a single port and these signals can be delivered separately or simultaneously to the end effector to treat tissue. A single output port generator can include a single output transformer with multiple taps to provide power, either RF or ultrasonic energy, to the end effector depending on the type of treatment of tissue being performed. For example, the generator can deliver energy with higher voltage and lower current to drive an ultrasonic transducer, with lower voltage and higher current as required to drive electrodes for sealing tissue, or with a coagulation waveform for spot coagulation using either monopolar or bipolar electrosurgical electrodes. The output waveform from the generator can be steered, switched, or filtered to provide the desired frequency to the end effector of the surgical instrument.

[0161] FIG. 8 illustrates an example of a generator **500** for delivering multiple energy modalities to a surgical instrument. The generator **500** is similar to the generator **102** described in connection with FIG. 1 and includes functionalities of the generators **200**, **300**, **400** shown in FIGS. 5-7. For conciseness and clarity of disclosure, hereinbelow, the various logic flow diagrams are described in connection with the generator **500**, which is a high level block diagram representation. Accordingly, the reader is directed to the description of the functional blocks of the generators **200**, **300**, **400** in FIGS. 5-7 for additional details that may be necessary to understand and practice the logic flow diagrams described hereinbelow in connection with the generator **500**.

[0162] Turning back to FIG. 8, the generator **500** provides radio frequency and ultrasonic signals for delivering energy to a surgical instrument. The radio frequency and ultrasonic signals may be provided alone or in combination and may be provided simultaneously. As noted above, at least one generator output can deliver multiple energy modalities (e.g., ultrasonic, bipolar or monopolar RF, irreversible and/or

reversible electroporation, and/or microwave energy, among others) through a single port and these signals can be delivered separately or simultaneously to the end effector to treat tissue. The generator **500** comprises a processor **502** coupled to a waveform generator **504**. The processor **502** and waveform generator **504** are configured to generate a variety of signal waveforms based on information stored in a memory coupled to the processor **502**, not shown for clarity of disclosure. The digital information associated with a waveform is provided to the waveform generator **504** which includes one or more digital-to-analog (DAC) converters to convert the digital input into an analog output. The analog output is fed to an amplifier **1106** for signal conditioning and amplification. The conditioned and amplified output of the amplifier **506** is coupled to a power transformer **508**. The signals are coupled across the power transformer **508** to the secondary side, which is in the patient isolation side. A first signal of a first energy modality is provided to the surgical instrument between the terminals labeled ENERGY1 and RETURN. A second signal of a second energy modality is coupled across a capacitor **510** and is provided to the surgical instrument between the terminals labeled ENERGY2 and RETURN. It will be appreciated that more than two energy modalities may be output and thus the subscript "n" may be used to designate that up to n ENERGYn terminals may be provided, where n is a positive integer greater than 1. It also will be appreciated that up to "n" return paths RETURNn may be provided without departing from the scope of the present disclosure.

[0163] A first voltage sensing circuit **512** is coupled across the terminals labeled ENERGY1 and the RETURN path to measure the output voltage therebetween. A second voltage sensing circuit **524** is coupled across the terminals labeled ENERGY2 and the RETURN path to measure the output voltage therebetween. A current sensing circuit **514** is disposed in series with the RETURN leg of the secondary side of the power transformer **508** as shown to measure the output current for either energy modality. If different return paths are provided for each energy modality, then a separate current sensing circuit should be provided in each return leg. The outputs of the first and second voltage sensing circuits **512**, **524** are provided to respective isolation transformers **516**, **522** and the output of the current sensing circuit **514** is provided to another isolation transformer **518**. The outputs of the isolation transformers **516**, **518**, **522** in the on the primary side of the power transformer **508** (non-patient-isolated side) are provided to a one or more analog-to-digital converters **526** (ADC). The digitized output of the ADC **526** is provided to the processor **502** for further processing and computation. The output voltages and output current feedback information can be employed to adjust the output voltage and current provided to the surgical instrument and to compute output impedance, among other parameters. Input/output communications between the processor **502** and patient isolated circuits is provided through an interface circuit **520**. Sensors also may be in electrical communication with the processor **502** by way of the interface **520**.

[0164] In one aspect, the impedance may be determined by the processor **502** by dividing the output of either the first voltage sensing circuit **512** coupled across the terminals labeled ENERGY1/RETURN or the second voltage sensing circuit **524** coupled across the terminals labeled ENERGY2/RETURN by the output of the current sensing circuit **514** disposed in series with the RETURN leg of the secondary

side of the power transformer **508**. The outputs of the first and second voltage sensing circuits **512**, **524** are provided to separate isolations transformers **516**, **522** and the output of the current sensing circuit **514** is provided to another isolation transformer **516**. The digitized voltage and current sensing measurements from the ADC **526** are provided to the processor **502** for computing impedance. As an example, the first energy modality ENERGY1 may be ultrasonic energy and the second energy modality ENERGY2 may be RF energy. Nevertheless, in addition to ultrasonic and bipolar or monopolar RF energy modalities, other energy modalities include irreversible and/or reversible electroporation and/or microwave energy, among others. Also, although the example illustrated in FIG. 8 shows a single return path RETURN may be provided for two or more energy modalities, in other aspects multiple return paths RETURNn may be provided for each energy modality ENERGYn. Thus, as described herein, the ultrasonic transducer impedance may be measured by dividing the output of the first voltage sensing circuit **512** by the current sensing circuit **514** and the tissue impedance may be measured by dividing the output of the second voltage sensing circuit **524** by the current sensing circuit **514**.

[0165] As shown in FIG. 8, the generator **500** comprising at least one output port can include a power transformer **508** with a single output and with multiple taps to provide power in the form of one or more energy modalities, such as ultrasonic, bipolar or monopolar RF, irreversible and/or reversible electroporation, and/or microwave energy, among others, for example, to the end effector depending on the type of treatment of tissue being performed. For example, the generator **500** can deliver energy with higher voltage and lower current to drive an ultrasonic transducer, with lower voltage and higher current to drive RF electrodes for sealing tissue, or with a coagulation waveform for spot coagulation using either monopolar or bipolar RF electrosurgical electrodes. The output waveform from the generator **500** can be steered, switched, or filtered to provide the frequency to the end effector of the surgical instrument. The connection of an ultrasonic transducer to the generator **500** output would be preferably located between the output labeled ENERGY1 and RETURN as shown in FIG. 8. An In one example, a connection of RF bipolar electrodes to the generator **500** output would be preferably located between the output labeled ENERGY2 and RETURN. In the case of monopolar output, the preferred connections would be active electrode (e.g., pencil or other probe) to the ENERGY2 output and a suitable return pad connected to the RETURN output.

[0166] In other aspects, the generators **102**, **200**, **300**, **400**, **500** described in connection with FIGS. 1-3 and 5-8, the ultrasonic generator drive circuit **114**, and/or electrosurgery/RF drive circuit **116** as described in connection with FIG. 3 may be formed integrally with any one of the surgical instruments **104**, **106**, **108** described in connection with FIGS. 1 and 2. Accordingly, any of the processors, digital signal processors, circuits, controllers, logic devices, ADCs, DACs, amplifiers, converters, transformers, signal conditioners, data interface circuits, current and voltage sensing circuits, direct digital synthesis circuits, multiplexer (analog or digital), waveform generators, RF generators, memory, and the like, described in connection with any one of the generators **102**, **200**, **300**, **400**, **500** can be located within the surgical instruments **104**, **106**, **108** or may be located remotely from the surgical instruments **104**, **106**, **108** and

coupled to the surgical instruments via wired and/or wireless electrical connections. Examples of waveforms representing energy for delivery from a generator are illustrated in FIGS. 9-13. FIG. 9 illustrates an example graph **600** showing first and second individual waveforms representing an RF output signal **602** and an ultrasonic output signal **604** superimposed on the same time and voltage scale for comparison purposes. These output signals **602**, **604** are provided at the ENERGY output of the generator **500** shown in FIG. 8. Time (t) is shown along the horizontal axis and voltage (V) is shown along the vertical axis. The RF output signal **602** has a frequency of about 330 kHz RF and a peak-to-peak voltage of $\pm 1V$. The ultrasonic output signal **604** has a frequency of about 55 kHz and a peak-to-peak voltage of $\pm 1V$. It will be appreciated that the time (t) scale along the horizontal axis and the voltage (V) scale along the vertical axis are normalized for comparison purposes and may be different actual implementations, or represent other electrical parameters such as current.

[0167] FIG. 10 illustrates an example graph **610** showing the sum of the two output signals **602**, **604** shown in FIG. 9. Time (t) is shown along the horizontal axis and voltage (V) is shown along the vertical axis. The sum of the RF output signal **602** and the ultrasonic output signal **604** shown in FIG. 9 produces a combined output signal **612** having a 2V peak-to-peak voltage, which is twice the amplitude of the original RF and ultrasonic signals shown (1V peak-to-peak) shown in FIG. 9. An amplitude of twice the original amplitude can cause problems with the output section of the generator, such as distortion, saturation, clipping of the output, or stresses on the output components. Thus, the management of a single combined output signal **612** that has multiple treatment components is an important aspect of the generator **500** shown in FIG. 8. There are a variety of ways to achieve this management. In one form, one of the two RF or ultrasonic output signals **602**, **604** can be dependent on the peaks of the other output signal.

[0168] For example, FIG. 11 illustrates an example graph **620** showing a combined output signal **622** representative of a dependent sum of the output signals **602**, **604** shown in FIG. 9. Time (t) is shown along the horizontal axis and voltage (V) is shown along the vertical axis. As shown in FIG. 11, the RF output signal **602** component of FIG. 9 depends on the peaks of the ultrasonic output signal **604** component of FIG. 9 such that the amplitude of the RF output signal component of the dependent sum combined output signal **622** is reduced when an ultrasonic peak is anticipated. As shown in the example graph **620** in FIG. 11, the peaks have been reduced from 2 to 1.5. In another form, one of the output signals is a function of the other output signal.

[0169] For example, FIG. 11 illustrates an example graph **630** showing an output signal **632** representative of a dependent sum of the output signals **602**, **604** shown in FIG. 9. Time (t) is shown along the horizontal axis and voltage (V) is shown along the vertical axis. As shown in FIG. 12, the RF output signal is a function of the ultrasonic output signal. This provides a hard limit on the amplitude of the output. As shown in FIG. 12, the ultrasonic output signal is extractable as a sine wave while the RF output signal has distortion but not in a way to affect the coagulation performance of the RF output signal.

[0170] A variety of other techniques can be used for compressing and/or limiting the waveforms of the output

signals. It should be noted that the integrity of the ultrasonic output signal **604** (FIG. 9) can be more important than the integrity of the RF output signal **602** (FIG. 9) as long as the RF output signal **602** has low frequency components for safe patient levels so as to avoid neuro-muscular stimulation. In another form, the frequency of an RF waveform can be changed on a continuous basis in order to manage the peaks of the waveform. Waveform control is important as more complex RF waveforms, such as a coagulation-type waveform **644**, as illustrated in the graph **640** shown in FIG. 13, are implemented with the system. Again, time (t) is shown along the horizontal axis and voltage (V) is shown along the vertical axis.

[0171] FIGS. 14-42 (26-54) illustrate various configurations of sensors, circuits, and techniques for measuring tissue parameters to facilitate executing the various adaptive tissue identification and treatment technique described herein. FIG. 14 illustrates one aspect of an end effector **700** comprising RF data sensors **706**, **708a**, **708b** located on the clamp arm **702**. The end effector **700** comprises a clamp arm **702** and an ultrasonic blade **704**. The clamp arm **702** is shown clamping tissue **710** located between the clamp arm **702** and the ultrasonic blade **704**. A first sensor **706** is located in a center portion of the clamp arm **702**. Second and third sensors **708a**, **708b** are located on lateral portions of the clamp arm **702**. The sensors **706**, **708a**, **708b** are mounted or formed integrally with on a flexible circuit **712** (shown more particularly in FIG. 15 and more particularly segmented flexible circuits **800**, **900** shown in FIGS. 17 and 18) configured to be fixedly mounted to the clamp arm **702**.

[0172] The end effector **700** is an example end effector for the multifunction surgical instrument **108** shown in FIGS. 1 and 2. The sensors **706**, **708a**, **708b** are electrically connected to an energy source, such as for example, the generator **500** shown in FIG. 8. The sensors **706**, **708a**, **708b** are powered by suitable sources within the generator and the signals generated by the sensors **706**, **708a**, **708b** are provided to analog and/or digital processing circuits of the generator **500**.

[0173] In one aspect, the first sensor **706** is a force sensor to measure a normal force F_3 applied to the tissue **710** by the clamp arm **702**. The second and third sensors **708a**, **708b** include one or more elements to apply RF energy to the tissue **710**, measure tissue impedance, down force F_1 , transverse forces F_2 , and temperature, among other parameters. Electrodes **709a**, **709b** are electrically coupled to the generator and apply RF energy to the tissue **710**. In one aspect, the first sensor **706** and the second and third sensors **708a**, **708b** are strain gauges to measure force or force per unit area. It will be appreciated that the measurements of the down force F_1 , the lateral forces F_2 , and the normal force F_3 may be readily converted to pressure by determining the surface area upon which the force sensors **706**, **708a**, **708b** are acting upon. Additionally, as described with particularity herein, the flexible circuit **712** may comprise temperature sensors embedded in one or more layers of the flexible circuit **712**. The one or more temperature sensors may be arranged symmetrically or asymmetrically and provide tissue **710** temperature feedback to control circuits of the generator.

[0174] FIG. 15 illustrates one aspect of the flexible circuit **712** shown in FIG. 14 in which the sensors **706**, **708a**, **708b** may be mounted to or formed integrally therewith. The flexible circuit **712** is configured to fixedly attach to the

clamp arm **702**. As shown particularly in FIG. 15, asymmetric temperature sensors **714a**, **714b** are mounted to the flexible circuit **712** to enable measuring the temperature of the tissue **710** (FIG. 14).

[0175] FIG. 16 is a cross-sectional view of the flexible circuit **712** shown in FIG. 15. The flexible circuit **712** comprises multiple layers and is fixedly attached to the clamp arm **702**. A top layer of the flexible circuit **712** is an electrode **709a**, which is electrically coupled to an energy source, such as the generators **102**, **200**, **300**, **400**, **500** (FIGS. 1-3 and 4-8), to apply RF energy to the tissue **710** (FIG. 14). A layer of electrical insulation **718** is provided below the electrode **709a** layer to electrically isolate the sensors **714a**, **706**, **708a** from the electrode **709a**. The temperature sensors **714a** are disposed below the layer of electrical insulation **718**. The first force (pressure) sensor **706** is located below the layer containing the temperature sensors **714a** and above a compressive layer **720**. The second force (pressure) sensor **708a** is located below the compressive layer **720** and above the clamp arm **702** frame.

[0176] FIG. 17 illustrates one aspect of a segmented flexible circuit **800** configured to fixedly attach to a clamp arm **804** of an end effector. The segmented flexible circuit **800** comprises a distal segment **802a** and lateral segments **802b**, **802c** that include individually addressable sensors to provide local tissue control, as described herein in connection with FIGS. 14-16, for example. The segments **802a**, **802b**, **802c** are individually addressable to treat tissue and to measure tissue parameters based on individual sensors located within each of the segments **802a**, **802b**, **802c**. The segments **802a**, **802b**, **802c** of the segmented flexible circuit **800** are mounted to the clamp arm **804** and are electrically coupled to an energy source, such as the generators **102**, **200**, **300**, **400**, **500** (FIGS. 1-3 and 4-8), via electrical conductive elements **806**. A Hall effect sensor **808**, or any suitable magnetic sensor, is located on a distal end of the clamp arm **804**. The Hall effect sensor **808** operates in conjunction with a magnet to provide a measurement of an aperture defined by the clamp arm **804** aperture or tissue gap as shown with particularity in FIG. 19.

[0177] FIG. 18 illustrates one aspect of a segmented flexible circuit **900** configured to mount to a clamp arm **904** of an end effector. The segmented flexible circuit **900** comprises a distal segment **902a** and lateral segments **902b**, **902c** that include individually addressable sensors for tissue control, as described herein in connection with FIGS. 14-17, for example. The segments **902a**, **902b**, **902c** are individually addressable to treat tissue and to read individual sensors located within each of the segments **902a**, **902b**, **902c**. The segments **902a**, **902b**, **902c** of the segmented flexible circuit **900** are mounted to the clamp arm **904** and are electrically coupled to an energy source, such as the generators **102**, **200**, **300**, **400**, **500** (FIGS. 1-3 and 4-8), via electrical conductive elements **906**. A Hall effect sensor **908**, or other suitable magnetic sensor, is provided on a distal end of the clamp arm **904**. The Hall effect sensor **908** operates in conjunction with a magnet to provide a measurement of clamp arm **904** aperture defined by the end effector or tissue gap as shown with particularity in FIG. 19. In addition, a plurality of lateral asymmetric temperature sensors **910a**, **910b** are mounted on or formed integrally with the segmented flexible circuit **900** to provide tissue temperature feedback to control circuits in the generator.

[0178] FIG. 19 illustrates one aspect of an end effector 1000 configured to measure a tissue gap G_T . The end effector 1000 comprises a jaw member 1002 and a clamp arm 904. The flexible circuit 900 as described in FIG. 18, is mounted to the clamp arm 904. The flexible circuit 900 comprises a Hall effect sensor 908 that operates with a magnet 1004 mounted to the jaw member 1002 to measure the tissue gap G_T . This technique can be employed to measure the aperture defined between the clamp arm 904 and the jaw member 1002. The jaw member 1002 may be an ultrasonic blade.

[0179] FIG. 20 illustrates one aspect of a left-right segmented flexible circuit 1100. The left-right segmented flexible circuit 1100 comprises a plurality of segments L1-L5 on the left side of the left-right segmented flexible circuit 1100 and a plurality of segments R1-R5 on the right side of the left-right segmented flexible circuit 1100. Each of the segments L1-L5 and R1-R5 comprise temperature sensors and force sensors to sense tissue parameters locally within each segment L1-L5 and R1-R5. The left-right segmented flexible circuit 1100 are configured to influence the RF treatment energy based on tissue parameters sensed locally within each of the segments L1-L5 and R1-R5.

[0180] FIG. 21 illustrates one aspect of an end effector 1200 comprising segmented flexible circuit 1100 as shown in FIG. 20. The end effector 1200 comprises a clamp arm 1202 and an ultrasonic blade 1204. The segmented flexible circuit 1100 is mounted to the clamp arm 1202. Each of the sensors disposed within the segments 1-5 are configured to detect the presence of tissue positioned between the clamp arm 1202 and the ultrasonic blade 1204 and represent tissue zones 1-5. In the configuration shown in FIG. 21, the end effector 1200 is shown in an open position ready to receive or grasp tissue between the clamp arm 1202 and the ultrasonic blade 1204.

[0181] FIG. 22 illustrates the end effector 1200 shown in FIG. 21 with the clamp arm 1202 clamping tissue 1206 between the clamp arm 1202 and the ultrasonic blade 1204. As shown in FIG. 22, the tissue 1206 is positioned between segments 1-3 and represents tissue zones 1-3. Accordingly, tissue 1206 is detected by the sensors in segments 1-3 and the absence of tissue (empty) is detected in section 1208 by segments 4-5. The information regarding the presence and absence of tissue 1206 positioned within certain segments 1-3 and 4-5, respectively, is communicated to a control circuit of the generator, such as the generators 102, 200, 300, 400, 500 (FIGS. 1-3 and 4-8). The generator 500 is configured to energize only the segments 1-3 where tissue 1206 is detected and does not energize the segments 4-5 where tissue is not detected. It will be appreciated that the segments 1-5 may contain any suitable temperature, force/pressure, and/or Hall effect magnetic sensors to measure tissue parameters of tissue located within certain segments 1-5 and electrodes to deliver RF energy to tissue located in certain segments 1-5.

[0182] FIG. 23 illustrates graphs 1300 of energy applied by the right and left side of an end effector based on locally sensed tissue parameters. As discussed herein, the clamp arm of an end effector may comprise temperature sensors, force/pressure sensors, Hall effect sensors, among others, along the right and left sides of the clamp arm as shown, for example, in FIGS. 14-22. Thus, RF energy can be selectively applied to tissue positioned between the clam jaw and the ultrasonic blade. The top graph 1302 depicts power P_R applied to a right side segment of the clamp arm versus time

(t) based on locally sensed tissue parameters. Thus, the generator, such as the generators 102, 200, 300, 400, 500 (FIGS. 1-3 and 4-8), is configured to measure the sensed tissue parameters and to apply power P_R to a right side segment of the clamp arm. The generator 500 delivers an initial power level P_1 to the tissue via the right side segment and then decreases the power level to P_2 based on local sensing of tissue parameters (e.g., temperature, force/pressure, thickness) in one or more segments. The bottom graph 1304 depicts power P_L applied to a left side segment of the clamp arm versus time (t) based on locally sensed tissue parameters. The generator 500 delivers an initial power level of P_1 to the tissue via the left side segment and then increases the power level to P_3 based local sensing of tissue parameters (e.g., temperature, force/pressure, thickness). As depicted in the bottom graph 1304, the generator is configured to re-adjust the energy delivered P_3 based on sensing of tissue parameters (e.g., temperature, force/pressure, thickness).

[0183] FIG. 24 illustrates a graph 1400 depicting one aspect of adjustment of threshold due to the measurement of a secondary tissue parameter such as continuity, temperature, pressure, and the like. The horizontal axis of the graph 1400 is time (t) and the vertical axis is tissue impedance (Z). The curve 1412 represents the change of tissue impedance (Z) over time (t) as different energy modalities are applied to the tissue. With reference also to FIGS. 20-22, the original threshold 1402 is applied when tissue is detected in all five segments 1-5 (tissue zones 1-5) and the adjusted threshold 1404 is applied when the tissue is detected in tissue segments 1-3 (tissue zones 1-3). Accordingly, once the tissue is located in particular segments (zones) the control circuit in the generator adjusts the threshold accordingly.

[0184] As shown in FIG. 24, the curve 1412 includes three separate sections 1406, 1408, 1410. The first section 1406 of the curve 1412 represents the time when RF energy is applied to the tissue in tissue zones 1-3 until the tissue impedance drops below the adjusted threshold 1404. At that point 1414, which may indicate that a tissue seal is completed, the energy modality applied to tissue zones 1-3 is changed from RF energy to ultrasonic energy. The ultrasonic energy is then applied in the second and third sections 1408, 1410 and the impedance rises exponentially until the tissue is severed or cut.

[0185] FIG. 25 is a cross-sectional view of one aspect of a flexible circuit 1500 comprising RF electrodes and data sensors embedded therein. The flexible circuit 1500 can be mounted to the right or left portion of an RF clamp arm 1502, which is made of electrically conductive material such as metal. Below the RF clamp arm 1502 down force/pressure sensors 1506a, 1506b are embedded below a laminate layer 1504. A transverse force/pressure sensor 1508 is located below the down force/pressure sensor 1506a, 1506b layer and a temperature sensor 1510 is located below the transverse force/pressure sensor 1508. An electrode 1512 electrically coupled to the generator and configured to apply RF energy to the tissue 1514 is located below the temperature sensor 1510.

[0186] FIG. 26 is a cross-sectional view of one aspect of an end effector 1600 configured to sense force or pressure applied to tissue located between a clamp arm and an ultrasonic blade. The end effector 1600 comprises a clamp jaw 1602 and a flexible circuit 1604 fixedly mounted to the clamp arm 1602. The clamp arm 1602 applies forces F_1 and

F_2 to the tissue **1606** of variable density and thickness, which can be measure by first and second force/pressure sensors **1608**, **1610** located in different layers of the flexible circuit **1604**. A compressive layer **1612** is sandwiched between the first and second force/pressure sensors **1608**, **1610**. An electrode **1614** is located on outer portion of the flexible circuit **1604** which contacts the tissue. As described herein, other layers of the flexible circuit **1604** may comprise additional sensors such temperature sensors, thickness sensors, and the like.

[0187] FIGS. 27-29 illustrate various schematic diagrams of flexible circuits of the signal layer, sensor wiring, and an RF energy drive circuit. FIG. 27 is a schematic diagram of one aspect of a signal layer of a flexible circuit **1700**. The flexible circuit **1700** comprises multiple layers (–4 to –6, for example). One layer will supply the integrated circuits with power and another layer with ground. Two additional layers will carry the RF energy RF1 and RF2 separately. An analog multiplexer switch **1702** has eight bidirectional translating switches that can be controlled through the I²C bus. The SCL/SDA upstream pair fans out to eight downstream pairs, or channels. Any individual SCn/SDn channel or combination of channels can be selected, determined by the contents of a programmable control register. The upstream pairs SCL/SDA are connected to a control circuit in the generator. There are six down stream sensors, three on each side of the clamp arm. A first side **1704a** comprises a first thermocouple **1706a**, a first pressure sensor **1708a**, and a first Hall effect sensor **1710a**. A second side **1704b** comprises a second thermocouple **1706b**, a second pressure sensor **1708b**, and a second Hall effect sensor **1710b**. FIG. 28 is a schematic diagram **1750** of sensor wiring for the flexible circuit **1700** shown in FIG. 27.

[0188] FIG. 29 is a schematic diagram of one aspect of an RF energy drive circuit **1800**. The RF energy drive circuit **1800** comprises an analog multiplexer **1702** described in connection with FIG. 27. The analog multiplexer multiplexes various signals from the upstream channels SCL/SDA. A current sensor **1802** is coupled in series with the return or ground leg of the power supply circuit to measure the current supplied by the power supply. An FET temperature sensor **1804** provided the ambient temperature. A pulse width modulation (PWM) watchdog timer **1808** automatically generates a system reset if the main program neglects to periodically service it. It is provided to automatically reset the RF energy drive circuit **1800** when it hangs because of a software or hardware fault.

[0189] A drive circuit **1806** provides left and right RF energy outputs. The digital signal is provided to the SCL/SDA inputs of the analog multiplexer **1702** from a control circuit of the generator. A digital-to-analog converter (DAC) converts the digital input to an analog output to drive a pulse width modulation (PWM) circuit **1812** coupled to an oscillator **1814**. The PWM circuit **1812** provides a first gate drive signal **1816a** to a first transistor output stage **1818a** to drive a first RF (Left) energy output. The PWM circuit **1812** also provides a second gate drive signal **1816b** to a second transistor output stage **1818ab** to drive a second RF (Right) energy output.

[0190] The circuits **1700**, **1750**, **1800** described in connection with FIGS. 27-29 are electrically coupled to the generators **200**, **300**, **400**, **500** shown in FIGS. 5-7. For example, the circuits **1700**, **1750**, **1800** may be coupled to

the generator **200** via the signal conditioning circuit **244** and may be coupled to the generator **500** through the interface circuit **520**.

[0191] FIG. 30 is a graphical representation **1900** of measuring tissue gap at a preset time. A first graph **1902** represents tissue impedance Z versus time (t) where the horizontal axis represents time (t) and the vertical axis represents tissue impedance Z . A second graph **1904** represents change in tissue gap Δ_{gap} versus time (t) where the horizontal axis represents time (t) and the vertical axis represents change in tissue gap Δ_{gap} . A third graph **1906** represents force F versus time (t) where the horizontal axis represents time (t) and the vertical axis represents force F . With a constant force F applied to tissue and impedance Z interrogation to define a wait period, energy modality (e.g., RF and ultrasonic) and motor control parameters, displacement at a time provides velocity. With reference to the three graphs **1902**, **1904**, **1906**, impedance sensing energy is applied during a first period **1908** to determine the tissue type such as thin mesentery tissue (solid line), intermediate thickness vessel tissue (dashed line), or thick uterus/bowel tissue (dash-dot line).

[0192] As shown in the third graph **1906**, the clamp arm initially applies a force which ramps up from zero exponentially until it reaches a constant force **1924**. The preset time t_1 is selected such that it occurs some time after the clamp arm force reaches a constant force **1924**. As shown in the first and second graphs **1902**, **1904**, from the time the clamp force is applied to the mesentery tissue until the preset time t_1 is reached, the change in tissue gap Δ_{gap} curve **1912** decreases exponentially and the tissue impedance curve **1918** also decreases until the preset time t_1 is reached. From the preset time t_1 , a short delay **1928** is applied before treatment energy is applied to the mesentery tissue at t_{E1} .

[0193] As shown in the first and second graphs **1902**, **1904**, from the time the clamp force is applied to the vessel tissue until the preset time t_1 is reached, the change in tissue gap Δ_{gap} curve **1916** also decrease exponentially and the tissue impedance curve **1920** also decreases until the preset time t_1 is reached. From the preset time t_1 , a medium delay **1930** is applied before treatment energy is applied to the vessel tissue at t_{E2} .

[0194] As shown in the first and second graphs **1902**, **1904**, from the time the clamp force is applied to the uterus/bowel tissue until the preset time t_1 is reached, the change in tissue gap Δ_{gap} curve **1914** drops exponentially and the tissue impedance curve **1914** also drops until the preset time t_1 is reached. From the preset time t_1 , a short delay **1928** is applied before treatment energy is applied to the mesentery tissue at t_{E1} .

[0195] FIG. 31 is a time to preset force **2008** versus time graph **2000** for thin, medium, and thick tissue types. The horizontal axis represents time (t) and the vertical axis represents force (F) applied by the clamp arm to the tissue. The graph **2000** depicts three curves, one for thin tissue **2002** shown in solid line, one for medium thickness tissue **2004** shown in dash-dot line, and thick tissue **2006** in dashed line. The graph **2000** depicts measuring time at a preset force as an alternative to tissue gap to control delayed energy mode and other control parameters. Accordingly, the time to preset force **2008** for thick tissue **2006** is t_{1a} , the time to preset force **2008** for medium thickness tissue **2004** is t_{1b} , and the time to preset force **2008** for thin tissue **2002** is t_{1c} .

[0196] Once the force reaches the preset force **2008**, energy is applied to the tissue. For thin tissue **2002** the time to preset $t_{1c} > 0.5$ seconds and then RF energy is applied for an energizing period t_e of about 1-3 seconds. For thick tissue **2006** the time to preset $t_{1a} < 0.5$ seconds and then RF energy is applied for an energizing period t_e of about 5-9 seconds. For medium thickness tissue **2004** the time to preset t_{1b} is about 0.5 seconds and then RF energy is applied for an energizing period t_e of about 3 to 5 seconds.

[0197] FIG. 32 is a graphical depiction of a graph **2100** of three curves **2102**, **2104**, **2106**, where the first curve **2102** represents power (P), voltage (V_{RF}), and current (I_{RF}) versus tissue impedance (Z), the second curve **2104** and third curve **2106** represent tissue impedance (Z) versus time (t). The first curve **2102** illustrates the application of power (P) for thick tissue impedance range **2110** and thin tissue impedance range **2112**. As the tissue impedance Z increases, the current I_{RF} decrease and the voltage V_{RF} increases. The power curve P increases until it reaches a maximum power output **2108** which coincides with the intersection **2114** of the current I_{RF} and voltage V_{RF} curves.

[0198] The second curve **2104** represents the measured tissue impedance Z versus time (t). The tissue impedance threshold limit **2120** is the cross over limit for switching between the RF and ultrasonic energy modalities. For example, as shown in FIG. 32, RF energy is applied while the tissue impedance is above the tissue impedance threshold limit **2120** and ultrasonic energy **2124** is applied while the tissue impedance is below the tissue impedance threshold limit **2120**. Accordingly, with reference back to the second curve **2104**, the tissue impedance of the thin tissue curve **2116** remains above the tissue impedance threshold limit **2120**, thus only RF energy modality is applied to the tissue. On the other hand, RF energy modality is applied to the thick tissue while the impedance is above the tissue impedance threshold limit **2120** and ultrasonic energy is applied to the tissue when the impedance is below the tissue impedance threshold limit **2120**. Accordingly, the energy modality switches from RF to ultrasonic when the tissue impedance falls below the tissue impedance threshold limit **2120** and the energy modality switches from ultrasonic to RF when the tissue impedance rises above the tissue impedance threshold limit **2120**.

[0199] FIG. 33 is a plan view of one aspect of an end effector **2200**. The end effector **2200** comprises a clamp arm **2202** and a shaft **2204**. The clamp arm **2202** pivots about pivot point **2206** and defines a pivot angle. FIG. 34 is a side view of the end effector **2200** shown in FIG. 33 with a partial cut away view to expose the underlying structure of the clamp arm **2202** and an ultrasonic blade **2208**. An electrode **2210** is fixedly mounted to the clamp arm **2202**. The electrode **2210** is electrically coupled to the generator and is configured to apply RF energy to tissue located between the clamp arm **2202** and the ultrasonic blade **2208**. FIG. 35 is partial sectional view of the end effector shown in FIGS. 33, 34 to expose the ultrasonic blade and right and left electrodes **2210a**, **2210b**, respectively.

[0200] FIG. 36 is a cross-sectional view taken at section 36-36 of the end effector **2200** shown in FIG. 33. The end effector **2200** comprises an ultrasonic blade **2208** acoustically coupled to an ultrasonic transducer which is electrically driven by the generator. The clamp arm **2202** comprises an electrode **2210a** on the right side and an electrode **2210b** on the left side (from the perspective of the operator).

The right side electrode **2210a** defines a first width W_1 and defines a first gap G_1 between the electrode **2210a** and the ultrasonic blade **2208**. The left side electrode **2210b** defines a second width W_2 and defines a second gap G_2 between the electrode **2210b** and the ultrasonic blade **2208**. In one aspect the first width W_1 is less than the second width W_2 and the first gap G_1 is less than the second gap G_2 . With reference also to FIG. 35, a soft polymeric pad **2212** is located between the ultrasonic blade **2208** and the clamp arm **2202**. A high density polymeric pad **2214** is located adjacent the soft polymeric pad **2212** to prevent the ultrasonic blade **2208** from shorting the electrodes **2210a**, **2210b**. In one aspect, the soft polymeric pads **2212**, **2214** can be made of polymers known under the tradename TEFLON (polytetrafluoroethylene polymers and copolymers), for example.

[0201] FIG. 37 is cross-sectional view taken at section 37-37 of the end effector **2200** shown in FIG. 33. At the plane where section 37-37 the end effector **2200** is thinner and has more curvature than section 36-36. The right side electrode **2210a** defines a third width W_3 and defines a third gap G_3 between the electrode **2210a** and the ultrasonic blade **2208**. The left side electrode **2210b** defines a fourth width W_4 and defines a fourth gap G_4 between the electrode **2210b** and the ultrasonic blade **2208**. In one aspect the third width W_3 is less than the fourth width W_4 and the third gap G_3 is less than the fourth gap G_4 .

[0202] FIG. 38 is a cross-sectional view taken at section 36-36 of the end effector **2200** shown in FIG. 33, except that the ultrasonic blade **2208'** has a different geometric configuration. The end effector **2200'** comprises an ultrasonic blade **2208'** acoustically coupled to an ultrasonic transducer which is electrically driven by the generator. The clamp arm **2202'** comprises an electrode **2210a'** on the right side and an electrode **2210b'** on the left side (from the perspective of the operator). The right side electrode **2210a'** defines a first width W_1 and defines a first gap G_1 between the electrode **2210a'** and the ultrasonic blade **2208'**. The left side electrode **2210b'** defines a second width W_2 and defines a second gap G_2 between the electrode **2210b'** and the ultrasonic blade **2208'**. In one aspect the first width W_1 is less than the second width W_2 and the first gap G_1 is less than the second gap G_2 . A high density polymeric pad **2214'** is located adjacent the soft polymeric pad **2212'** to prevent the ultrasonic blade **2208'** from shorting the electrodes **2210a'**, **2210b'**. In one aspect, the soft polymeric pads **2212'**, **2214'** can be made of polymers known under the tradename TEFLON (polytetrafluoroethylene polymers and copolymers), for example.

[0203] FIG. 39 is cross-sectional view taken at section 37-37 of the end effector **2200** shown in FIG. 33, except that the ultrasonic blade **2208'** has a different geometric configuration. At the plane where section 37-37 the end effector **2200'** is thinner and has more curvature than the end effector **2200'** at section 36-36. The right side electrode **2210a'** defines a third width W_3 and defines a third gap G_3 between the electrode **2210a'** and the ultrasonic blade **2208'**. The left side electrode **2210b'** defines a fourth width W_4 and defines a fourth gap G_4 between the electrode **2210b'** and the ultrasonic blade **2208'**. In one aspect the third width W_3 is less than the fourth width W_4 and the third gap G_3 is less than the fourth gap G_4 .

[0204] FIG. 40 is a cross-sectional view taken at section 36-36 of the end effector **2200** shown in FIG. 33, except that the ultrasonic blade **2208''** has a different geometric configuration. The end effector **2200''** comprises an ultrasonic

blade **2208**" acoustically coupled to an ultrasonic transducer which is electrically driven by the generator. The clamp arm **2202**" comprises an electrode **2210a**" on the right side and an electrode **2210b**" on the left side (from the perspective of the operator). The right side electrode **2210a**" defines a first width W_1 and defines a first gap G_1 between the electrode **2210a**" and the ultrasonic blade **2208**". The left side electrode **2210b**" defines a second width W_2 and defines a second gap G_2 between the electrode **2210b**" and the ultrasonic blade **2208**". In one aspect the first width W_1 is less than the second width W_2 and the first gap G_1 is less than the second gap G_2 . A high density polymeric pad **2214**" is located adjacent the soft polymeric pad **2212**" to prevent the ultrasonic blade **2208**" from shorting the electrodes **2210a**", **2210b**". In one aspect, the polymeric pads **2212**", **2214**" can be made of polymers known under the tradename TEFLON (polytetrafluoroethylene polymers and copolymers), for example.

[0205] FIG. 41 is cross-sectional view taken at section 37-37 of the end effector **2200** shown in FIG. 33, except that the ultrasonic blade **2208**" has a different geometric configuration. At the plane where section 37-37 the end effector **2200**" is thinner and has more curvature than the end effector **2200**" at section 36-36. The right side electrode **2210a**" defines a third width W_3 and defines a third gap G_3 between the electrode **2210a**" and the ultrasonic blade **2208**". The left side electrode **2210b**" defines a fourth width W_4 and defines a fourth gap G_4 between the electrode **2210b**" and the ultrasonic blade **2208**". In one aspect the third width W_3 is less than the fourth width W_4 and the third gap G_3 is less than the fourth gap G_4 .

[0206] The surgical instruments described herein also can include features to allow the energy being delivered by the generator to be dynamically changed based on the type of tissue being treated by an end effector of a surgical instrument and various characteristics of the tissue. In one aspect, a technique for controlling the power output from a generator, such as the generators **102**, **200**, **300**, **400**, **500** (FIGS. 1-3 and 4-8), that is delivered to the end effector of the surgical instrument can include an input that represents the tissue type to allow the energy profile from the generator to be dynamically changed during the procedure based on the type of tissue being effected by the end effector of the surgical instrument.

[0207] As disclosed herein, techniques for controlling a generator based on the tissue type may be provided. Various techniques can be used to select a power profile to allow the energy being delivered from the generator to dynamically change based on the tissue type being treated by the surgical instrument.

[0208] FIG. 42A illustrates an end effector **2300** comprising a clamp arm **2302** and an ultrasonic blade **2304**, where the clamp arm **2302** includes electrodes **2306**. The end effector **2300** can be employed in one of the surgical instruments **104**, **106**, **108** referred to in FIGS. 1-3. In addition to the end effector **122**, **124**, **125**, the surgical instruments **104**, **106**, **108** include a handpiece **105**, **107**, **109** and a shaft **126**, **127**, **129**, respectively. The end effectors **122**, **124**, **125** may be used to compress, cut, and/or seal tissue. Referring to FIG. 42A, the end effector **2300**, similar to the end effectors **122**, **124**, **125** shown in FIGS. 1-3, may be positioned by a physician to surround tissue **2308** prior to compression, cutting, or stapling. As shown in FIG. 42A, no compression may be applied to the tissue while preparing to

use the end effector **2300**. As shown in FIG. 42A, the tissue **2308** is not under compression between the clamp arm **2302** and the ultrasonic blade **2304**.

[0209] Referring now to FIG. 42B, by engaging the trigger on the handle of a surgical instrument, the physician may use the end effector **2300** to compress the tissue **2308**. In one aspect, the tissue **2308** may be compressed to its maximum threshold, as shown in FIG. 42B. As shown in FIG. 42A, the tissue **2308** is under maximum compression between the clamp arm **2302** and the ultrasonic blade **2304**.

[0210] Referring to FIG. 43A, various forces may be applied to the tissue **2308** by the end effector **2300**. For example, vertical forces F_1 and F_2 may be applied by the clamp arm **2302** and the ultrasonic blade **2304** of the end effector **2300** as tissue **2308** is compressed between the two. Referring now to FIG. 43B, various diagonal and/or lateral forces also may be applied to the tissue **2308** when compressed by the end effector **2300**. For example, a force F_3 may be applied. For the purposes of operating a medical device such as the surgical instruments **104**, **106**, **108** it may be desirable to sense or calculate the various forms of compression being applied to the tissue by the end effector. For example, knowledge of vertical or lateral compression may allow the end effector to more precisely or accurately apply a staple operation or may inform the operator of the surgical instrument such that the surgical instrument can be used more properly or safely.

[0211] In one form, a strain gauge can be used to measure the force applied to the tissue **2308** by the end effector shown in FIGS. 42A-B and 43A-B. A strain gauge can be coupled to the end effector **2300** to measure the force on the tissue **2308** being treated by the end effector **2300**. With reference now also to FIG. 44, in the aspect illustrated in FIG. 44, a system **2400** for measuring forces applied to the tissue **2308** comprises a strain gauge sensor **2402**, such as, for example, a micro-strain gauge, is configured to measure one or more parameters of the end effector **2300** such as, for example, the amplitude of the strain exerted on a clamp arm of an end effector, such as the clamp arm **2302** of FIGS. 43A-B, during a clamping operation, which can be indicative of the tissue compression. The measured strain is converted to a digital signal and provided to a processor **2410** of a microcontroller **2408**. A load sensor **2404** can measure the force to operate the ultrasonic blade **2304** to cut the tissue **2308** captured between the clamp arm **2302** and the ultrasonic blade **2304** of the end effector **2300**. A magnetic field sensor **2406** can be employed to measure the thickness of the captured tissue **2308**. The measurement of the magnetic field sensor **2406** also may be converted to a digital signal and provided to the processor **2410**.

[0212] Further to the above, a feedback indicator **2414** also can be configured to communicate with the microcontroller **2408**. In one aspect, the feedback indicator **2414** can be disposed in the handle of a surgical instrument, such as those shown in FIGS. 1-3. Alternatively, the feedback indicator **2414** can be disposed in a shaft assembly of a surgical instrument, for example. In any event, the microcontroller **2408** may employ the feedback indicator **2414** to provide feedback to an operator of the surgical instrument with regard to the adequacy of a manual input such as, for example, a selected position of a firing trigger that is used to cause the end effector to clamp down on tissue. To do so, the microcontroller **2408** may assess the selected position of the clamp arm **2302** and/or firing trigger. The measurements of

the tissue **2308** compression, the tissue **2308** thickness, and/or the force required to close the end effector **2300** on the tissue, as respectively measured by the sensors **2402**, **2404**, **2406**, can be used by the microcontroller **2408** to characterize the selected position of the firing trigger and/or the corresponding value of the speed of end effector. In one instance, a memory **2412** may store a technique, an equation, and/or a look-up table which can be employed by the microcontroller **2408** in the assessment.

[0213] The generators **102**, **200**, **300**, **400**, **500** (FIGS. 1-3 and 4-8), surgical instruments **104**, **106**, **108** (FIGS. 1-3), and end effectors **122**, **124**, **125**, **700**, **800**, **900**, **1000**, **1100**, **1200**, **2200**, **2200'**, **2200''**, **2300** (FIGS. 1-3, 14-22, 33-43B) described herein may be employed alone or in combination to perform surgical procedures in accordance with the techniques and processes described hereinbelow. Nevertheless, for conciseness and clarity, the surgical procedures are described with reference to the multifunction surgical instrument **108** and the generator **500**. The multifunction surgical instrument **108** comprises an end effector **125** which includes a clamp arm **145** and an ultrasonic blade **149**. The end effector **125** may be configured with any of the structural or functional features of any one of the end effectors **122**, **124**, **125**, **700**, **800**, **900**, **1000**, **1100**, **1200**, **2200**, **2200'**, **2200''**, **2300** to provide electrodes to apply RF energy to tissue, temperature sensors, force/pressure sensors, and gap measurement sensors, as described hereinabove.

Techniques for Sealing or Sealing and Cutting Large Vessels and Tissue-Bundles

[0214] In one aspect, the present disclosure provides a technique for sealing or sealing and cutting large vessels/tissue bundles by controlling the power delivered to an end effector from a generator, such as any one of the generators **102**, **200**, **300**, **400**, **500** (FIGS. 1-3 and 4-8), or a surgical instrument, such as the surgical instrument **108** (FIGS. 1-3). In accordance with the present technique, the power delivered to an end effector of a surgical instrument can be varied based on the size of vessels and tissue bundles interacting with the end effector. For conciseness and clarity of disclosure, the techniques for sealing or sealing and cutting large vessels/tissue bundles will be described with reference to the multifunction surgical instrument **108** of FIG. 2 coupled to the generator **500** of FIG. 8, although it will be appreciated that other configurations of instruments, generators, and end effectors described herein may be readily substituted without departing from the scope of the present disclosure.

[0215] A technique for controlling the power output from a generator **500** that is delivered to the end effector **125** of a surgical instrument **108** can include an input that represents a state of coagulation of the tissue to allow the energy profile from the generator **500** to be dynamically changed during the tissue treatment process between RF and ultrasonic energy based on the state of coagulation of the tissue being treated by the end effector **125** of the surgical instrument **108** or the size of the vessels or tissue interacting with the end effector **108**. This allows the processor **502** to control the generator **500** to switch from RF energy (ENERGY2/RETURN) when a tissue seal is complete to ultrasonic energy (ENERGY1/RETURN) to cut the tissue and complete a procedure. Also, this technique allows the generator **500** to switch to ultrasonic energy at the initial stages of treatment when either the vessel or tissue bundle is too large to seal with RF energy alone. Thus, ultrasonic energy is

applied until the size of the vessel or tissue bundle is sufficiently reduced to enable the RF to complete a proper seal. It will be appreciated that the switch between a first form of energy and a second form of energy, and vice versa, can be done by first turning OFF the first form of energy and thereafter turning on the second form of energy. Alternatively, the switch between a first form of energy and a second form of energy, and vice versa, can be done by transitioning from the first form of energy to the second form of energy, and vice versa, such that for brief period both the first and second forms of energy are turned ON simultaneously while one form ramps up and the other ramps down. Thus, according to the latter approach, the RF and ultrasonic energies can be blended during the transition rather than "one then the other" approach.

[0216] In one aspect, the present disclosure provides techniques to improve the capability of the generator **500** to quickly and efficiently seal or seal and cut large vessels or large tissue bundles that present an initial extremely low impedance to the generator **500**. These techniques shorten transaction times when sealing or sealing and cutting big tissue bundles that present low RF impedance to the generator **500**. When RF energy is applied to tissue with real low impedance, due to electrical current capacity limitations (maximum output current capability) of the generator **500**, the maximum power that can be delivered into tissue is limited, which results in very long transaction cycles. Note that the current limitation is not unique to the generators described herein and are applicable to other generators.

[0217] In one aspect, the state of coagulation of the tissue can be determined using a variety of techniques. In one aspect, the state of coagulation of the tissue is determined using a calculated tissue impedance and comparing it to a threshold to find the termination impedance, as explained above. The calculated tissue impedance, as described herein, is used by a technique to control the energy being delivered from the generator **500** to the surgical instrument **108**.

[0218] In another aspect, the state of coagulation is determined using a "vector machine" or other techniques. In another aspect, the state of coagulation is determined using neural networks that are configured to take a plurality of factors into account. As discussed herein, a neural network refers to a series of techniques that attempt to identify underlying relationships in a set of data by using a process that mimics the way the human brain operates. Neural networks have the ability to adapt to changing input so that the network produces the best possible result without the need to redesign the output criteria. For example, the neural networks can take into account the tissue impedance as measured using the RF signal, the initial tissue impedance as measured using the RF signal, the energy that went into the transection, for example, in joules, the transection time, the initial aperture of the jaw, the current aperture of the jaw, and/or the rate of change of the tissue impedance. One example of a neural network **4700** for controlling a generator is described hereinbelow in connection with FIG. 73.

[0219] FIG. 45 is a logic flow diagram **2500** of one aspect of a process for sealing or sealing and cutting large vessels or large tissue bundles. As described herein, the logic flow diagram **2500** may be implemented in the generator **500**, the multifunction surgical instrument **108**, or a combination thereof. With reference now to the logic flow diagram **2500** shown in FIG. 45 and the surgical system **10** of FIG. 1, the state of coagulation of the tissue is determined as described

herein. The generator **500** is configured to deliver RF energy (ENERGY2/RETURN) and ultrasonic energy (ENERGY1/RETURN) to switch between the RF and ultrasonic energy according to various techniques. The end effector **125** of the surgical instrument **108** is advanced and the tissue is clamped **2502** between the clamp arm **145** and the ultrasonic blade **149**. The end effector **125** is activated with RF energy from the generator **500** and RF energy is delivered **2504** to the tissue to effect a seal employing a process such as a composite load curve (CLC) control process described in connection with the logic diagram **4600** shown FIG. **72**. With reference back to FIG. **45**, the processor **502** determines **2506** the state of coagulation to determine if a state of completion of coagulation of the tissue has been achieved, at which time the processor **502** signals the waveform generator **504** and amplifier **506** to switch from RF energy for coagulating tissue to ultrasonic energy for cutting tissue. If the desired tissue of coagulation or seal has not been achieved, the processor **502** continues along the NO branch and RF energy is continued to be delivered. When the proper state of coagulation has been reached, the processor **502** continues along the YES branch and the RF energy is switched **2508** to ultrasonic energy to cut the tissue. The tissue is released **2510** from the end effector **125** once the tissue cut is completed with the ultrasonic energy.

[0220] Also disclosed herein are techniques for dynamically changing the energy delivered from a generator based on end effector aperture. According to one aspect, a technique for controlling the power output from a generator, such as the generator **500** of FIG. **8**, that is delivered to the end effector of a surgical instrument, such as surgical instrument **108** (FIGS. **1-3**) can include an input that represents the aperture of the end effector **125** of the surgical instrument **108**. The energy profile from the generator **500** can be dynamically changed during the procedure between RF and ultrasonic energy based on the size of the aperture defined by the end effector **125** clamping the tissue. This allows the generator **500** to switch from RF energy to ultrasonic energy based on the amount that the end effector **125** is clamping on the tissue being treated by the surgical instrument **108**. The aperture of the clamp arm **145** is related to the creation of a proper coagulation seal, for example, when RF energy is delivered from the generator **500** to the end effector **125** of the surgical instrument **108**, such that RF energy is used when there is sufficient closure of the end effector **125** on the tissue. Thus, if the aperture defined by the end effector is too large and there is insufficient clamp on the tissue for proper coagulation, only ultrasonic energy is delivered to the end effector **125**.

[0221] For example, false information regarding various tissue measurements and/or characteristics can be transmitted to the generator **500** for controlling the energy delivered depending on the aperture defined by the end effector **125**. One such measurement that can be affected by the aperture defined by the end effector **125** is tissue impedance. An incorrect tissue impedance determination can lead to early termination of a coagulation “sealing” cycle as the generator **500** may switch from RF to ultrasonic energy before a proper coagulation seal has been achieved.

[0222] The aperture defined by the end effector **125** can be determined using a variety of techniques. In one form, the aperture defined by the end effector **125** is determined by detecting the pivot angle of the end effector **125**. This can be accomplished using a potentiometer, a Hall effect sensor, an

optical encoder, an optical IR sensor, an inductance sensor, or a combination thereof. In another form, the proximity of first and second components of an end effector **125** is measured to determine the aperture defined by the end effector **125** using, for example, a Hall effect sensor, an optical IR, inductance sensor, or combination thereof. In another form, a surgical instrument **125** is configured to detect the aperture defined by the end effector **125** by measuring a change in a tissue impedance of the tissue interacting with the end effector **125**. In another form, a surgical instrument is configured to detect the aperture defined by the end effector **125** by measuring a load applied by the end effector **125** on the tissue as ultrasonic energy is pulsed to the end effector **125**. In another form, the surgical instrument includes a switch or other mechanism for closing the end effector **125** that can detect the aperture defined by the end effector **125**. As previously discussed, the tissue impedance is determined by the processor **502** by dividing the voltage applied to the end effector **125** by the current delivered to the end effector **125**. For example, the processor **502** can determine the tissue impedance by dividing the voltage sensed by the second voltage sensing circuit **524** by the current sensed by the current sensing circuit **514**.

[0223] FIG. **46** is a logic flow diagram **2600** of one aspect of a process for sealing or sealing and cutting large vessels or large tissue bundles by dynamically changing energy being delivered from the generator **500** during the treatment of the tissue based on the changing aperture defined by the end effector. As described herein, the logic flow diagram **2600** may be implemented in the generator **500**, the multi-function surgical instrument **108**, or a combination thereof. With reference now to the logic flow diagram **2600** shown in FIG. **46**, the processor **502** determines the aperture defined by the end effector **125** as described above. The processor **502** then determines the state of coagulation of the tissue as described herein. The generator **500** or the surgical instrument **108** may be configured to deliver RF energy (ENERGY2/RETURN) and ultrasonic energy (ENERGY1/RETURN) to switch between the RF and ultrasonic energy according to various techniques. The end effector **125** of the surgical instrument **108** is advanced and the tissue and the end effector **125** of the surgical instrument **108** is closed **2602** on tissue and the end effector **125** is activated with energy from the generator **500**. The processor **502** determines **2604** the aperture defined by the end effector **125** using any of the techniques described above. The processor **502** signals the energy delivered from the generator **500** to the end effector **125** and controls when the generator **500** switches between RF and ultrasonic energy based on the aperture defined by the end effector **125**. Accordingly, the processor **502** selects **2606** the generator **500** power delivery profile based on the aperture defined by the end effector **125**. The processor **502** monitors **2608** the aperture defined by the end effector **125** during the tissue treatment process to dynamically change **2610** the energy delivered from the generator **500** during the tissue treatment process based on the changing aperture defined by the end effector **125**.

[0224] In another aspect, a technique for controlling the power delivered from the generator **500** to the end effector **125** of the surgical instrument **108** can include an input that includes energy parameters based on an aperture of the end effector **125** of the surgical instrument **108**. During the tissue treatment process, the processor **502** can dynamically change the energy output profile of the generator **500**

between RF energy and ultrasonic energy using energy parameters based on the aperture defined by the end effector 125 clamping the tissue. This allows the generator 500 to switch from RF energy to ultrasonic energy based on how much clamping force the end effector is applying to the tissue during the treatment process. As explained above, the aperture of the clamp arm 145 is related to creating a proper coagulation seal. For example, RF energy should be delivered by the generator 500 to the end effector 125 only when there is sufficient closure of the end effector 125 on the tissue. Thus, when the aperture defined by the end effector 125 is too large and there is insufficient clamping force on the tissue for proper coagulation, only ultrasonic energy should be delivered to the end effector 125.

[0225] The aperture defined by the end effector 125 can be determined using any of the methods described above. For example, the surgical instrument 108 can include an aperture sensor in the end effector 125 that can be fed through a connector to the ASIC in the handle 109 of the surgical instrument 108. The surgical instrument 108 also can include a sensor in the handle 109 of the surgical instrument 108 that is configured to detect the aperture defined by the end effector 125.

[0226] Energy parameters are configured to be loaded into the generator 500, and can include a plurality of different parameters, including but not limited to voltage, current, power, and one or more techniques for use in treating tissue. These parameters can be related to the RF energy and ultrasonic energy that can be delivered from the generator 500. The energy parameters can include information such as maximum and/or minimum values to be used to control the energy delivered from the generator 500. The energy parameters can be stored in a variety of locations, including an EEPROM on the surgical instrument 108 or some other non-volatile memory. In addition, there can be multiple sets of energy parameters. For example, the processor 502 can use a first set of energy parameters to optimize tissue transection, and a second set of energy parameters to optimize tissue spot coagulation. It will be understood that there can be any number of set of energy parameters that correspond to various types of tissue treatments to allow the generator 500 to switch between the various sets of energy parameters based on the necessary tissue treatments.

[0227] When the end effector 125 of the surgical instrument 108 is activated, the processor 502 utilizes the various techniques described above to detect the aperture defined by the end effector 125. In one aspect, when the end effector 125 is closed around the tissue, the generator 500 can utilize the energy parameters for optimizing tissue transection. When the end effector 125 has a larger aperture and is not clamped on the tissue, the generator 500 can utilize the energy parameters for optimizing spot coagulation of the tissue.

[0228] FIG. 47 is a logic flow diagram 2700 of one aspect of a process for sealing or sealing and cutting large vessels or large tissue bundles by dynamically communicating energy parameters to the generator 500 during the tissue treatment process based on the changing aperture defined by the end effector 125 of the surgical instrument 108. As described herein, the logic flow diagram 2700 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to the logic flow diagram 2700 shown in FIG. 47, the processor 502 determines the aperture defined by the end

effector 125 as described above. The generator 500 is configured to deliver RF energy (ENERGY2/RETURN) and ultrasonic energy (ENERGY1/RETURN) and to switch between the RF and ultrasonic energy according to various techniques. The end effector 125 of the surgical instrument 108 is advanced, the end effector 125 of the surgical instrument 108 is closed 2702 on the tissue, and the end effector 125 is activated with energy from the generator 500. The processor 502 determines 2704 the aperture defined by the end effector 125 using any of the techniques described above. The processor 502 signals the energy delivered from the generator 500 and to switch between RF and ultrasonic energy based on the aperture defined by the end effector 125 based on sets of energy parameters previously loaded into the generator 500. Accordingly, energy parameters are communicated 2706 to the generator 500 based on the measured aperture defined by the end effector 125. The aperture defined by the end effector 125 is monitored 2708 during the tissue treatment process such that the energy delivered from the generator 500 can be dynamically changed during the tissue treatment process based on the changing aperture defined by the end effector 125. Accordingly, the processor 502 dynamically communicates 2710 energy parameters to the generator 500 based on the measured aperture defined by the end effector 125. This allows the generator 500 to dynamically switch between various sets of energy parameters based on the changing aperture defined by the end effector 125.

[0229] It will be understood that various combinations of information can be used to determine which set of energy parameters are to be used during the tissue treatment process. For example, the aperture defined by the end effector 125 and calculated tissue impedance can be used by the processor 502 to determine which set of energy parameters are needed to control the energy being delivered from the generator 500. As previously discussed, the tissue impedance is determined by the processor 502 by dividing the voltage applied to the end effector 125 by the current delivered to the end effector 125. For example, the processor 502 can determine the tissue impedance by dividing the voltage sensed by the second voltage sensing circuit 524 by the current sensed by the current sensing circuit 514.

[0230] In another aspect, a technique for controlling the power output from the generator 500 and delivered to the end effector 125 of the surgical instrument 108 can include an input that includes inputs related to the size of the tissue being treated by the end effector 125 of the surgical instrument 108. During the tissue treatment process, the processor 502 dynamically changes the energy delivered from the generator 500 between RF energy and ultrasonic energy to achieve dissection and coagulation of large vessels and large tissue bundles based on a determination of the effectiveness of the RF energy in coagulating the large vessels or large tissue bundles. A determination of the effectiveness of the RF energy in coagulating a tissue includes a calculation of tissue impedance, as explained above, of the large tissue interacting with the end effector 125, which is used to determine the type of energy delivered by the generator 500 to the end effector 125.

[0231] FIG. 48 is a logic flow diagram 2800 of a technique to seal or seal and cut vessels using RF and ultrasonic energy in conjunction with tissue impedance measurements and the aperture defined by the clamp arm measurements. As described herein, the logic flow diagram 2800 may be

implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to the logic flow diagram 2800 shown in FIG. 48, the end effector 125 is advanced and the clamp arm 145 is closed 2802 on tissue located between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125. The end effector 125 is then activated with RF energy (ENERGY2/RETURN) from the generator 500 to form a seal. The processor 502 determines 2804 the tissue impedance and the aperture defined by the end effector 125 as described herein. As previously discussed, the tissue impedance is determined by the processor 502 by dividing the voltage applied to the end effector 125 by the current delivered to the end effector 125. For example, the processor 502 can determine the tissue impedance by dividing the voltage sensed by the second voltage sensing circuit 524 by the current sensed by the current sensing circuit 514.

[0232] The aperture defined by the end effector 125 and the processor 502 determines 2804 the tissue impedance using any of the techniques described herein. The processor 502 compares 2806 the tissue impedance values to stored threshold values and determines 2808 whether or not these values are greater than the threshold values. If either the tissue impedance or the aperture defined by the end effector 125 is less than the threshold value, the processor 502 continues along the NO branch and RF energy (ENERGY2/RETURN) continues to be delivered from the generator 500 to the end effector 125. If the tissue impedance and the aperture defined by the end effector 125 are greater than the threshold value, the processor 502 continues along the YES branch and switches 2810 the to delivering ultrasonic energy (ENERGY1/RETURN) from the generator 500. This allows the large vessels and large tissue bundles to be reduced in size or shrunk with ultrasonic energy to a size that would allow the RF energy to form a more optimal seal.

[0233] The processor 502 determines 2812 the aperture defined by the end effector 125 using any of the techniques described herein. The processor 502 then compares 2814 these aperture values to stored threshold aperture values and determines whether or not these aperture values represent that the tissue has been shrunk by the ultrasonic energy to a size that would allow the RF energy to properly seal the tissue. If the processor 502 determines that tissue is too large for RF energy sealing, the processor 502 continues along the NO branch and ultrasonic energy continues to be delivered from the generator 500 to the end effector 125 to continue shrinking the tissue. If the processor 502 determines that the tissue is has been shrunk to an appropriate size suitable for sealing with RF energy, the processor 502 continues along the YES branch and switches 2816 the energy delivered from the generator 500 to RF energy. The processor 502 signals can optionally switch back 2818 to delivering ultrasonic energy upon determining that the RF energy has completed the tissue seal.

[0234] FIG. 49 is a logic flow diagram 2900 of one aspect of a process for sealing or sealing and cutting large vessels or large tissue bundles. As described herein, the logic flow diagram 2900 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to the logic flow diagram 2900 shown in FIG. 49, tissue is initially grasped 2902 by the end effector 125 between the clamp arm 145 and the ultrasonic blade 149. RF energy (ENERGY2/RETURN) is delivered 2904 to the end effector 125. The processor 502 monitors

2906 the tissue impedance Z_T and jaw aperture A_j for a predetermined period T_o , which may be selected from a range of 0.5 to 2.0 seconds, and preferably about 1.5 seconds, for example. As previously discussed, the tissue impedance is determined by the processor 502 by dividing the voltage applied to the end effector 125 by the current delivered to the end effector 125. For example, the processor 502 can determine the tissue impedance by dividing the voltage sensed by the second voltage sensing circuit 524 by the current sensed by the current sensing circuit 514.

[0235] Until the predetermined period T_o elapses 2908, the processor 502 continues along the NO branch and the generator 500 continues to deliver RF energy and the processor 502 continues to monitor (measure) tissue impedance Z_T and jaw aperture A_j . At the end of the time period T_o , if tissue impedance Z_T has not increased to a value equal to or greater than a predetermined threshold and the jaw aperture is equal to or less than a predetermined threshold, the processor 502 proceeds along the YES branch and switches 2910 the generator 500 to ultrasonic energy mode. Ultrasonic energy is delivered 2912 to the tissue while the processor 502 monitors the tissue impedance Z_T and jaw aperture A_j until the tissue shrinks to a size that is suitable for sealing with RF energy. The processor 502 compares 2914 the jaw aperture A_j to a threshold jaw aperture and if it is less than or equal to the threshold the processor 502 continues along the YES branch assuming that the tissue is sized for sealing by RF energy. The processor 502 switches the generator 500 to RF energy mode and delivers 2916 RF energy to complete the seal while the processor 502 monitors the tissue impedance Z_T to determine 2918 if the seal is complete. If the seal is complete and seal-only is desired, the processor 502 completes 2920 the operation. If the seal is complete and seal and cut is desired, the processor 502 switches the generator 500 to ultrasonic energy mode and delivers 2922 ultrasonic energy to cut the sealed tissue. Upon cutting the tissue, the processor 502 completes 2920 the operation.

[0236] FIG. 50 is a logic flow diagram 3000 of a technique to seal or seal and cut vessels using RF and ultrasonic energy in conjunction with tissue impedance measurements. As described herein, the logic flow diagram 3000 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to the logic flow diagram 3000 shown in FIG. 50, tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108. The processor 502 signals the waveform generator 504 and amplifier 506 to deliver 3002 RF energy (ENERGY2/RETURN) to the end effector 125 of the surgical instrument 108 interacting with tissue to create a tissue seal using the RF energy. The processor 502 calculates 3004 a first tissue impedance Z_{T1} of the tissue interacting with the end effector 125 at the start of the period T_o of the delivery of the RF energy and then calculates 3006 a second tissue impedance Z_{T2} of the tissue interacting with the end effector after the RF energy is delivered for a predetermined period T_1 . As previously discussed, the tissue impedance is determined by the processor 502 by dividing the voltage applied to the end effector 125 by the current delivered to the end effector 125. For example, the processor 502 can determine the tissue impedance by dividing the voltage sensed by the second voltage sensing circuit 524 by the current sensed by the current sensing circuit 514.

[0237] The processor 502 compares Z_{T1} to Z_{T2} . If Z_{T2} is less than or equal to Z_{T1} after RF energy is delivered for a period of T_1 , there may be a short circuit or the tissue impedance is too low for RF energy to deliver power to the tissue. Accordingly, the processor 502 proceeds along the YES branch and controls the waveform generator 504 and amplifier 506 to stop 3010 delivering RF energy to the end effector 125 and start delivering 3012 ultrasonic energy to the end effector 125 until Z_{T2} is greater than Z_{T1} . Once Z_{T2} exceeds Z_{T1} , the processor 502 continues along the NO branch and controls the waveform generator 504 and amplifier 506 to continue 3014 delivering RF energy to the end effector 125 until the tissue is sealed 3016. Once the tissue is sealed, the processor 502 continues along the YES branch and controls the waveform generator 504 and amplifier 506 to stop delivering RF energy to the end effector 125 and to start delivering 3020 ultrasonic energy to cut the tissue. If the tissue is not sealed, the processor 502 continues along the NO branch and the generator 500 continues delivering RF energy to the end effector until the tissue seal is completed.

[0238] In another aspect, a technique for controlling the power output from the generator 500 delivered to the end effector 125 of the surgical instrument 108 can include an input that includes inputs related to the size of the tissue being treated by the end effector 125 of the surgical instrument 108. The energy delivered from the generator 500 can be dynamically changed during the procedure between RF and ultrasonic energy to achieve dissection and coagulation of a large tissue based on a determination of the effectiveness of the RF energy in coagulating the large tissue. A determination of the effectiveness of the RF energy in coagulating a tissue includes a calculation of tissue impedance, as explained above, of the large tissue interacting with the end effector 125, which is used to determine the type of energy being delivered by the generator 500 to the end effector 125.

[0239] FIG. 51 is a logic flow diagram 3100 of a technique to seal or seal and cut vessels using RF and ultrasonic energy in conjunction with tissue impedance measurements and the aperture defined by the clamp jaw measurements. As described herein, the logic flow diagram 3100 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to the logic flow diagram 3100 shown in FIG. 51, tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108. The processor 502 signals the waveform generator 504 and amplifier 506 to deliver 3102 RF energy (ENERGY2/RETURN) to the end effector 125 of the surgical instrument 108 interacting with tissue to create a tissue seal using the RF energy. The processor 502 calculates 3104 a first tissue impedance Z_{T1} of the tissue interacting with the end effector 125 at the start of a period T_0 of delivery of the RF energy and then calculates 3106 a second tissue impedance Z_{T2} of the tissue interacting with the end effector 125 after the RF energy is delivered for a predetermined period T_1 and measures the aperture A_j defined by the clamp arm 145. As previously discussed, the tissue impedance is determined by the processor 502 by dividing the voltage applied to the end effector 125 by the current delivered to the end effector 125. For example, the processor 502 can determine the tissue

impedance by dividing the voltage sensed by the second voltage sensing circuit 524 by the current sensed by the current sensing circuit 514.

[0240] The processor 502 compares Z_{T1} to Z_{T2} . If Z_{T2} is less than or equal to Z_{T1} after RF energy is delivered for a period of T_1 , the processor 502 determines that there may be a short circuit or extremely low the tissue impedance present at the end effector 125 that is too low for RF energy to deliver any power to the tissue. Accordingly, the processor 502 proceeds along the YES branch and the generator 500 and compares the measured aperture A_j defined by the clamp arm 145 to a predetermined threshold aperture A_{jo} defined by the clamp arm 145, where the predetermined threshold aperture A_{jo} corresponds to a thick vessel or a thick tissue bundle located between the clamp arm 145 and the ultrasonic blade 149. If the measured aperture A_j defined by the clamp arm 145 is less than or equal to the predetermined threshold aperture A_{jo} , the processor 502 continues along the NO branch and controls the waveform generator 504 and amplifier 506 to continue delivering RF energy to the end effector 125 until the tissue impedance Z_{T2} is less than the initial tissue impedance Z_{T1} . If the measured aperture A_j defined by the clamp arm 145 is greater than the predetermined threshold aperture A_{jo} , the processor 502 continues along the YES branch and controls the generator to stop 3110 delivering RF energy to the end effector 125 and start delivering 3112 ultrasonic energy (ENERGY1/RETURN) to the end effector 125 until Z_{T2} is greater than Z_{T1} . Once Z_{T2} is greater than Z_{T1} , the processor 502 continues along the NO branch and controls the waveform generator 504 and amplifier 506 to continue 3114 delivering RF energy to the end effector 125 until the tissue is sealed 3116. Once the tissue is sealed, the processor 502 continues along the YES branch and controls the waveform generator 504 and amplifier 506 to stop delivering RF energy and start delivering 3120 ultrasonic energy to the end effector 125 to cut the tissue. If the tissue is not sealed, the processor 502 continues along the NO branch and controls the waveform generator 504 and amplifier 506 to continue delivering RF energy to the end effector 125 until the tissue seal is complete.

Techniques for Switching Between RF and Ultrasonic Energy Based on the State of Coagulation of Tissue

[0241] In one aspect, the present disclosure provides a technique for switching between RF and ultrasonic energy based on the state of coagulation of tissue by controlling the power delivered to an end effector from a generator, such as any one of the generators 102, 200, 300, 400, 500 (FIGS. 1-3 and 4-8), or a surgical instrument, such as the surgical instrument 108 (FIGS. 1-3). In accordance with the present technique, the power delivered to an end effector of a surgical instrument can be switched between RF and ultrasonic based on the state of coagulation of tissue interacting with the end effector. For conciseness and clarity of disclosure, the techniques for switching between RF and ultrasonic energy based on the state of coagulation of tissue will be described with reference to the multifunction surgical instrument 108 of FIG. 2 coupled to the generator 500 of FIG. 8, although it will be appreciated that other configurations of instruments, generators, and end effectors described herein may be readily substituted without departing from the scope of the present disclosure.

[0242] To address these issues, in some aspects, a generator 500 capable of handling both ultrasonic and RF electro-surgical systems may include a completely nested neural network to identify whether the generator 500 is presented with a true short circuit vs. a low impedance tissue. In addition, in some aspects, to assist in the detection of short circuits, the neural network may be configured to track and store at least the following factors: a. Measured resistance/impedance; b. Drive current (RMS); c. Drive Voltage (RMS); and d. Moving average of measured impedance. In some aspects, the neural network will be thought to in order to be capable of discerning between a true short and low impedance tissue.

[0243] Furthermore, in some aspects, methods for detecting a short circuit may utilize the ultrasonic functionality to cut low impedance tissue and to identify a true short circuit. For example, instead of faulting, the generator 500 may send in an exploratory pulse to the ultrasonic transducer 120. The tissue properties initially assessed by the ultrasonic blade 149 touching a metal short would result in a higher output drive voltage and resulting impedance. This level of impedance may be measured to determine whether the material was actually metal versus low impedance tissue. If the processor 502 determines that metal is not present in the end effector 125, the generator 500 continues to deliver ultrasonic energy to the end effector 125 and cut through the load. Thus, if the impedance is too low for the application of RF energy to seal the tissue in a timely manner, ultrasonic energy could be applied cut through non-metal low impedances without difficulty.

[0244] FIG. 52 is a logic flow diagram 3200 of one aspect of a technique for distinguishing a short circuit from low impedance tissue while utilizing RF energy by measuring voltage properties of an exploratory ultrasonic pulse. As described herein, the logic flow diagram 3200 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to FIG. 52, the logic flow diagram 3200 provides a method for distinguishing a short circuit from low impedance tissue. With reference to the surgical instrument 108 of FIG. 2 coupled to the generator 500 of FIG. 8, tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108. In accordance with the method, the processor 502 signals the waveform generator 504 and amplifier 506 to transition 3202 from delivering RF energy (ENERGY2/RETURN) to delivering ultrasonic energy (ENERGY1/RETURN). The processor 502 then controls the waveform generator 504 and amplifier 506 to transmit 3204 an exploratory pulse to the ultrasonic transducer 120 to apply ultrasonic energy to the short circuit area in question. The processor 502 then measures 3206 the output drive voltage and drive current and determines the impedance. As previously discussed, the tissue impedance is determined by the processor 502 by dividing the voltage applied to the end effector 125 by the current delivered to the end effector 125. For example, the processor 502 can determine the tissue impedance by dividing the voltage sensed by the second voltage sensing circuit 524 by the current sensed by the current sensing circuit 514. At this juncture, the processor 502 determines 3208 whether the impedance is consistent with low impedance tissue. When the impedance is consistent with low impedance tissue, the processor 502 proceeds along the YES branch and controls the waveform generator

504 and amplifier 506 to continue 3210 delivering ultrasonic energy to cut through tissue. When the impedance is not consistent with low impedance tissue, the processor 502 proceeds along the NO branch and controls the waveform generator 504 and amplifier 506 to stop 3212 the application of ultrasonic energy.

[0245] Additionally, in some aspects, if a short is detected while in RF mode and delivering RF energy to the end effector 125, the processor 502 signals the waveform generator 504 and amplifier 506 to transmit an ultrasonic pulse to the ultrasonic transducer 120. A microphone and ultrasonic application can be configured to detect the sound of characteristic ultrasonic vibrations against metal, since it would be very apparent and instantly or easily recognizable. Using knowledge in acoustics and waveform engineering, the processor 502 can account for what frequencies are heard due to the ultrasonic blade 149 acting on metal and on other non-tissue materials.

[0246] FIG. 53 is a logic flow diagram 3300 of a technique for distinguishing a short circuit from low impedance tissue while delivering RF energy and measuring acoustic properties of an exploratory ultrasonic pulse, according to some aspects. As described herein, the logic flow diagram 3300 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to FIG. 53, the logic flow diagram 3300 provides a method for distinguishing a short circuit from low impedance tissue. The tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108. In accordance with the method, the processor 502 signals the waveform generator 504 and amplifier 506 to transition 3302 from delivering RF energy (ENERGY2/RETURN) to delivering ultrasonic energy (ENERGY1/RETURN). The processor 502 then controls the waveform generator 504 and amplifier 506 to transmit 3304 an exploratory pulse to the ultrasonic transducer 120 to apply ultrasonic energy to the short circuit area in question. The processor 502 measures 3306 the acoustic properties of the area in question based on applied ultrasonic vibrations. At this juncture, the processor 502 determines 3308 whether the acoustic properties are consistent with the low impedance tissue. When the processor 502 determines acoustic properties are consistent with low impedance tissue, the processor 502 proceeds along the YES branch and controls the waveform generator 504 and amplifier 506 to continue 3210 delivering ultrasonic energy to cut through tissue. When the processor 502 determines that the acoustic properties are consistent with low impedance tissue, the processor 502 proceeds along the NO branch and controls the waveform generator 504 and amplifier 506 to stop 3312 delivering ultrasonic energy.

[0247] In some aspects, a neural network, such as neural network 4700 for controlling a generator shown in FIG. 73, may be programmed to identify these properties in metal, tissues, and other non-tissue materials. The neural network also may be configured to transmit the exploratory pulse to the ultrasonic transducer. In addition, new developments or additional programs, including receiving feedback from the attempts to detect short circuits, may be incorporated back into the neural network to increase its situational awareness and effectively better learn how to detect a true short circuit. With confirmation of a short circuit both by RF and ultra-

sonic functionality, this can allow for less time spent getting repeat errors on RF and faster transection on low impedance tissue.

[0248] Also disclosed herein are techniques for combining RF energy and ultrasonic energy to seal tissue without cutting. In some aspects, the surgical system including the generator of the present disclosures may be configured to implement a method for sealing tissue at a surgical site without cutting, by using a combination of ultrasonic energy and RF energy. In some aspects, the method includes superimposing the ultrasonic drive signal together with a fixed low RF signal (e.g., ultrasonic at 55.5 KHz and RF at 330 KHz). For example, during a sealing procedure, the ultrasonic drive signal may be configured to dynamically change in order to: (1) track the resonance of the ultrasonic drive signal, and (2) provide the desired strength or amplitude of vibrations in order to achieve the desired tissue effect. The fixed low RF signal will be provided in order to measure the tissue impedance and modify the ultrasonic drive to achieve the desired seal without cutting.

[0249] The RF signal may be superimposed in several non-exhaustive ways. In one way, the RF drive signal may be superimpose on top of the ultrasonic drive signal in a continuous fashion. In another way, the ultrasonic drive signal may be time sliced in such way that periodically or aperiodically, e.g., every 250 mSec, the ultrasonic drive signal will cease and a short burst of the RF drive signal of, e.g., 50 mSec, will be driving the output at a sub-therapeutic level which will still be sufficient to measure tissue impedance. After this burst, the processor 502 will control the waveform generator 504 and the amplifier 506 to switch the output of the generator 500 back to delivering the ultrasonic drive signal. The overall control loop may be configured to monitor the RF tissue impedance and adjust the ultrasonic drive signal output to achieve a tissue seal without cutting the tissue.

[0250] FIG. 54 is a logic flow diagram 3400 of a technique for conducting a tissue sealing technique without cutting by using a combination of ultrasonic energy and RF energy, according to some aspects. As described herein, the logic flow diagram 3400 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to FIG. 54, the logic flow diagram 3400 provides an example iterative technique for cyclically combining RF energy (ENERGY2/RETURN) and ultrasonic energy (ENERGY1/RETURN) to seal tissue without cutting, according to some aspects. Tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108. In accordance with the method, the processor 502 signals the waveform generator 504 to deliver 3402 an ultrasonic drive signal during a first interval of time to seal tissue at a surgical site. The processor 502 then controls the waveform generator 504 and the amplifier 506 to cease 3404 the ultrasonic drive signal after the first interval. The processor 502 then controls the waveform generator 504 and the amplifier 506 to deliver an RF drive signal at a sub-therapeutic amplitude during a second interval of time to measure tissue impedance. The processor 502 then controls the waveform generator 504 and the amplifier 506 to cease 3408 the RF drive signal after the second interval of time. The processor 502 then adjusts 3410 an ultrasonic drive

signal based on the measured impedance from the RF drive signal. The processor 502 repeats 3412 the procedure until the surgical site is sealed.

[0251] The input to this control system to reduce/modify the ultrasonic drive signal and at eventually completely terminate the ultrasonic drive signal can utilize the following non-exhaustive methods: follow a power reduction and termination technique based on regular logic, fuzzy logic, vector machine, or neural network utilizing the following example: initial tissue impedance, initial jaws-aperture, current tissue impedance, rate of change of tissue impedance, energy driven into tissue, and transection time.

[0252] In some aspects, the surgical system may be configured to measure these terms through one or more sensors. Example methods for monitoring these terms and the ultrasonic functionality of the combination RF and ultrasonic surgical system may be based on methods described in U.S. Pat. No. 9,017,326, titled "Impedance Monitoring Apparatus, System, And Method For Ultrasonic Surgical Instruments," which is hereby incorporated by reference in its entirety.

[0253] FIG. 55 is a logic flow diagram 3500 of a technique for conducting a tissue sealing technique without cutting by using a combination of ultrasonic energy and RF energy, according to some aspects. As described herein, the logic flow diagram 3500 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to FIG. 55, the logic flow diagram 3500 provides an example iterative technique for cyclically combining RF energy (ENERGY2/RETURN) and ultrasonic energy (ENERGY1/RETURN) to seal tissue without cutting, according to some aspects. Tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108. In accordance with the method, the processor 502 signals the waveform generator 504 to deliver 3502 an ultrasonic drive signal to the tissue during a first interval of time T_1 . The processor 502 then controls the waveform generator 504 and the amplifier 506 to cease 3504 the ultrasonic drive signal after the first interval T_1 . The processor 502 then controls the waveform generator 504 and the amplifier 506 to deliver 3506 an RF drive signal at a sub-therapeutic amplitude during a second interval T_1 of time to measure the tissue impedance. The processor 502 then controls the waveform generator 504 and the amplifier 506 to cease 3508 the RF drive signal after the second time interval T_2 . The processor 502 then controls the waveform generator 504 and the amplifier 506 to iteratively adjust 3510 the ultrasonic drive signal based on the measured tissue impedance until the processor 502 determines that the tissue is sealed. As previously discussed, the tissue impedance is determined by the processor 502 by dividing the voltage applied to the end effector 125 by the current delivered to the end effector 125. For example, the processor 502 can determine the tissue impedance by dividing the voltage sensed by the second voltage sensing circuit 524 by the current sensed by the current sensing circuit 514.

Techniques for Improving Short Circuit Detection in a Combination Ultrasonic/RF Surgical Instrument

[0254] In one aspect, the present disclosure provides a technique for detecting extremely low impedances or actual short circuits in the end effector by controlling the power

delivered to an end effector from a generator, such as any one of the generators **102, 200, 300, 400, 500** (FIGS. 1-3 and 4-8), or a surgical instrument, such as the surgical instrument **108** (FIGS. 1-3). In accordance with the present technique, the power delivered to an end effector of a surgical instrument can be varied based on whether a very low impedance or actual short circuit condition is present at the end effector. For conciseness and clarity of disclosure, the techniques for detecting extremely low impedances or actual short circuits in the end effector will be described with reference to the multifunction surgical instrument **108** of FIG. 2 coupled to the generator **500** of FIG. 8, although it will be appreciated that other configurations of instruments, generators, and end effectors described herein may be readily substituted without departing from the scope of the present disclosure.

[0255] Disclosed herein are techniques for detecting short circuits, including implementing detection methods in a neural network. In some aspects, the ultrasonic generator **500** of the present disclosures includes components configured to accurately and reliably detect short circuits. Particularly when performing surgeries on body tissue typical with use of the end effectors described herein, detecting a short circuit can be difficult for a number of reasons. For example, many times tissue presents itself as a short circuit, thereby fooling the detection software and at low signal magnitudes, which are inherent when driving signals with a short circuit, the measurement(s) error(s) is/are substantial and can result in making the wrong decision whether the generator is presented with a true short circuit. In addition, in some aspects of the generator described herein, low impedance tissue or metal shorts cause the generator to fault while in RF mode. In general, it may be difficult for the generator to distinguish between low impedance tissue and metal, where one may result in a true short circuit while the other is merely based on low impedance tissue.

[0256] FIG. 56 is logic flow diagram **3600** of a technique for detecting low impedance tissue or metal shorts that may cause false short circuits in RF mode. As described herein, the logic flow diagram **3600** may be implemented in the generator **500**, the multifunction surgical instrument **108**, or a combination thereof. With reference now to FIG. 56, the logic flow diagram **3600** provides an example technique for detecting low impedance tissue or metal shorts that may cause false short circuits in RF mode. Tissue is clamped between the clamp arm **145** and the ultrasonic blade **149** of the end effector **125** of the surgical instrument **108**. In accordance with the method, if the processor **502** cannot distinguish low impedance tissue from metal located between the clamp arm **145** and the ultrasonic blade **149** of the end effector **125**, the processor **502** signals the waveform generator **504** to deliver ultrasonic energy (ENRGY1/RETURN) to cut low impedance tissue and to identify a true short circuit, such as metal to metal contact between the clamp arm **145** and the ultrasonic blade **149**. In accordance with the method, the processor **502** signals the waveform generator **504** to deliver **3602** RF energy (ENERGY2/RETURN) with the end effector **125** to the target surgical site. The processor **502** then controls the waveform generator **504** and the amplifier **506** to transition **3604** from delivering RF energy to delivering ultrasonic energy to the end effector **125**. The processor **502** signals the waveform generator **504** to transmit **3606** an exploratory ultrasonic

pulse to the end effector **125** and then measures **3608** an ultrasonic property of the ultrasonic pulse upon transmission to the end effector **125**.

Techniques for Delivering Pulsed RF and Ultrasonic Energy in a Combination Ultrasonic/RF Surgical Instrument

[0257] In one aspect, the present disclosure provides a technique for delivering RF and ultrasonic energy to an end effector of a surgical instrument by controlling the power delivered to an end effector from a generator, such as any one of the generators **102, 200, 300, 400, 500** (FIGS. 1-3 and 4-8), or a surgical instrument, such as the surgical instrument **108** (FIGS. 1-3). In accordance with the present technique, the power delivered to an end effector of a surgical instrument can be varied based on properties or parameters of tissue interacting with the end effector. For conciseness and clarity of disclosure, the techniques for delivering RF and ultrasonic energy to the end effector will be described with reference to the multifunction surgical instrument **108** of FIG. 2 coupled to the generator **500** of FIG. 8, although it will be appreciated that other configurations of instruments, generators, and end effectors described herein may be readily substituted without departing from the scope of the present disclosure.

[0258] FIGS. 57-66 illustrate aspects of timing diagrams of energy pulses for delivering different energy modalities to tissue. In one aspect the first energy modality is RF energy and the second energy modality is ultrasonic energy. There are many benefits to a surgical device that is capable of delivering both RF and ultrasonic energy. A surgical instrument capable of delivering both modalities provides stronger seals and can cut tissue without the need of a separate knife. The following disclosure provides multiple pulsing techniques than can be utilized for vessel sealing. These techniques employ tissue impedance measurements, current measurements, can seal only, and can seal and cut tissue. These techniques may be implemented using multiple generators, one generator configured to deliver RF energy and another generator configured to deliver ultrasonic energy. Alternatively, these techniques may be implemented with a single generator configured to deliver both RF and ultrasonic energy. In other aspects, these techniques may be implemented with a single generator that is configured to deliver RF and ultrasonic energy simultaneously through a single output port.

[0259] These techniques comprise pulsing between RF and ultrasonic energy modalities to create strong seals. Multiple configurations of pulsing are disclosed. The pulse sequence timing diagrams illustrated in FIGS. 57-63 and the logic flow diagrams shown in FIGS. 64-66 will be described with reference to the surgical instrument **108** of FIG. 2 coupled to the generator **500** of FIG. 8. Tissue is clamped between the clamp arm **145** and the ultrasonic blade **149** of the end effector **125** of the surgical instrument **108** and then the generator **500** delivers the pulse sequences discussed below.

[0260] FIG. 57 is a timing diagram of a seal only pulse sequence **3700** illustrating a basic configuration of pulsing RF and ultrasonic energy for "Seal Only" mode. The horizontal axis is time (t) in seconds that the energy is delivered or "pulsed." The vertical axis is the current pulse amplitude in milliamperes (mA) that the pulse is capable of sourcing. The ultrasonic energy pulses **3702** are shown in dashed line and

the RF pulses 3704 are shown in solid line. As shown in FIG. 57, the generator 500 switches between the ultrasonic energy pulses 3702 and RF energy pulses 3704 at fixed time intervals. During a first half cycle, the pulse sequence starts with the RF energy pulse 3704 ON for about 1 mS at a current pulse of about 750 mA amplitude while the ultrasonic energy pulse 3702 is OFF for about 1 mS at 0 mA current amplitude. During the next half cycle, the RF energy pulse 3704 is OFF for about 1 mS at 0 mA current amplitude while ultrasonic energy pulse 3702 is ON for about 1 ms at a current pulse of about 350 mA amplitude. The cycle is repeated until a strong tissue seal is developed. It will be appreciated that the application of the sequence of ultrasonic energy pulses 3702 and RF energy pulses 3704 shown in the pulse sequence 3700 is suitable for effecting a tissue seal only. This configuration of pulse sequence can start either with an RF energy pulse 3704 or an ultrasonic energy pulse 3702. Ultimately energy delivery for a "Seal Only" mode would be stopped based on the tissue impedance measured on the RF pulses 3704.

[0261] In order to reduce the risk of cutting tissue with the ultrasonic energy pulses 3702, the number of ultrasonic energy pulses 3702 should be minimized. This configuration is shown in FIG. 58, which is a timing diagram of a seal only pulse sequence 3710 illustrating a basic configuration of pulsing RF and ultrasonic energy for "Seal Only" mode. As shown, the pulse sequence 3700 starts with an active RF energy pulse 3704. After two ultrasonic energy pulses 3702, or other predetermined limited number of ultrasonic energy pulses 3702, no more ultrasonic energy pulses 3702 are delivered after the last ultrasonic energy pulse 3702' and the RF energy pulse 3704' is delivered for an extended period to effect a seal only. To avoid cutting the tissue with the ultrasonic energy pulse 3704 the last RF energy pulse 3704' remains ON at high amplitude while the ultrasonic energy pulse 3702 remains OFF.

[0262] It can be appreciated that the seal on the clamp arm 145 side may be wider and more complete than a seal on the ultrasonic blade 149 side. This may be caused by insufficient heating on the ultrasonic blade 149 side due to the higher thermal mass of the ultrasonic blade 149. In order to address this issue, the ultrasonic energy pulse 3702 could be left ON longer at the beginning to get the ultrasonic blade 149 up to the sealing temperature. FIG. 59 is a timing diagram of a seal only pulse sequence 3720 illustrating a basic configuration of pulsing RF and ultrasonic energy to preheat the ultrasonic blade 149. FIG. 59 is a timing diagram of a seal only pulse sequence 3720. As shown in FIG. 59, the first energy pulse delivered is an ultrasonic energy pulse 3702, which is left ON for an extended period sufficient to preheat the ultrasonic blade 149 prior to applying the RF energy pulses 3704. To avoid cutting the tissue with the ultrasonic energy pulse 3704 the last RF energy pulse 3704' remains ON at high amplitude while the ultrasonic energy pulse 3702 remains OFF.

[0263] FIG. 60 is a timing diagram of a seal only pulse sequence 3730. One of the main benefits to having more than one pulse of ultrasonic energy 3702 is to maintain the ultrasonic blade 149 temperature. In order to maintain ultrasonic blade 149 temperature and reduce the risk of cutting tissue with the ultrasonic blade 149, the pulse sequence 3730 shown in FIG. 60 provides the first ultrasonic energy pulse 3702 at a high amplitude and then the subsequent ultrasonic energy pulses 3702', 3702'' at lower ampli-

tudes. To avoid cutting the tissue with the ultrasonic energy pulse 3704 the last RF energy pulse 3704' remains ON at high amplitude while the ultrasonic energy pulse 3702 remains OFF.

[0264] The conditions for switching between the RF energy pulse 3704 and the ultrasonic energy pulse 3702 could be based on a fixed time or it could be based on tissue impedance. For example, when a "Seal Only" mode is desired, as shown in FIGS. 57-60, if a certain Impedance threshold is reached, the technique would not switch over to ultrasonic energy to minimize the risk of cutting through the tissue. The frequency slope could also be used as a trigger to switch from ultrasonic energy pulse 3702 delivery to RF energy pulse 3704 delivery.

[0265] If a "Seal and Cut" energy modality is desired, an ultrasonic energy pulse 3702 step could be added to the end of any of the techniques described in connection with FIGS. 57-60. This could occur once a certain impedance threshold is met. FIGS. 61 and 62 illustrate timing diagrams for seal and cut pulse sequences 3740, 3750 for issue seal and cut modes.

[0266] FIG. 61 is a timing diagram of a seal and cut pulse sequence 3740, which begins and ends with ultrasonic energy pulses 3702 delivered at the same amplitude during the sealing a cutting cycles. A first ultrasonic energy pulse 3702 is delivered at a predetermined amplitude and subsequent ultrasonic energy pulses 3702 are delivered at the same predetermined amplitude. The RF energy pulses 3704 are delivered until the tissue is sealed or until the tissue impedance is equal to or greater than a predetermined threshold. After the last delivered RF energy pulse 3704' is turned OFF, the last ultrasonic energy pulse 3702' is turned ON to cut tissue.

[0267] FIG. 62 is a timing diagram of a seal and cut pulse sequence 3750, which begins and ends with ultrasonic energy pulses 3702 delivered at variable amplitude during the sealing a cutting cycles. A first ultrasonic energy pulse 3702 is delivered at a predetermined amplitude and subsequent ultrasonic energy pulses 3702 are delivered at different amplitudes, and in one example as a stepped down amplitude. As shown, for example, a second ultrasonic energy pulse 3702' is delivered at an amplitude lower than the first amplitude and a third ultrasonic energy pulse 3702'' is delivered at an amplitude that is lower the second predetermined amplitude. The RF energy pulses 3704 are delivered until the tissue is sealed or until the tissue impedance is equal to or greater than a predetermined threshold. After the last delivered RF energy pulse 3704' is turned OFF, the last ultrasonic energy pulse 3702''' is turned ON to cut tissue. The last ultrasonic energy pulse 3702''' may be delivered at an amplitude that either the same as the first amplitude, may be different than previous amplitudes, or may be equal to one of the intermittent amplitudes.

[0268] For the seal and cut pulse sequences 3740, 3750, on thick tissue applications, the ultrasonic modality take approximately 250 ms to seek, meaning that low pulse widths result in a short amount of therapeutic time. In some aspects, pulse widths longer than 500 ms, for example, may provide certain benefits.

[0269] FIG. 63 is a timing diagram of a seal only pulse sequence 3760 where the ultrasonic energy pulse 3702 current is be set based on the impedance measured with the preceding RF energy pulse 3704. The right vertical axis is tissue impedance in Ohms. The ultrasonic energy pulse 3702

current could be set based on the impedance measured with the preceding RF energy pulse 3704. It would be preferred to have the ultrasonic energy pulse 3702 current high when the preceding RF impedance was low. As the RF impedance increases the ultrasonic energy pulse 3702 current of the next pulse would decrease. This would allow the technique to compensate for the amount of tissue positioned within the jaws of the end effector 125, where thick tissue/bundle applications would stay at lower impedance for a longer period of time and would require more energy/heat to seal. As shown in FIG. 63, based on the first two low tissue impedance 3706 measurements the ultrasonic energy pulse 3702 current amplitude remains the same. After the third tissue impedance 3706' measurement, the amplitude of the ultrasonic energy pulse 3702' current is reduced until the tissue impedance exceeds a predetermined threshold and the RF energy pulse 3704' current remains ON while the ultrasonic energy pulse 3702 current amplitude remains at 0 mA.

[0270] In one aspect the first energy modality is RF energy and the second energy modality is ultrasonic energy. In one aspect, the process depicted by the logic flow diagram 3800 may be repeated until the tissue is sealed. As discussed in connection with FIGS. 57-60, in a seal only method, the ultrasonic energy modality may be turned off after a few predetermined number of cycles or based on tissue impedance measurements to avoid cutting the tissue while the RF energy modality is delivered to make a tissue seal. The ultrasonic and/or the RF energy modalities may be delivered at the same amplitude or at variable amplitudes. For example, the RF energy modality may be delivered at the same amplitude whereas the amplitude of the ultrasonic energy modality is stepped down. As discussed in connection with FIGS. 61 and 62, during a seal and cut cycle, the ultrasonic energy modality is delivered last to effect a tissue after the tissue is sealed. As previously discussed, during the sealing cycle, the amplitude of the ultrasonic energy modality may be the same or may be stepped down. As discussed in connection with FIG. 63, in a seal only method, the amplitude of the ultrasonic energy modality is adjusted based on the previous tissue impedance measurement utilizing the RF energy modality. In any of the seal or seal and cut methods discussed above, the ultrasonic energy may be delivered first to preheat the ultrasonic blade 149 because of the higher thermal mass of the ultrasonic blade 149 with respect to the thermal mass of the clamp arm 145.

[0271] FIG. 64 is a logic flow diagram 3800 of a technique for delivering pulses of different energy modalities to tissue. As described herein, the logic flow diagram 3800 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to the logic flow diagram 3800 of FIG. 64, initially, tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108 and then the processor 502 signals the waveform generator 504 to deliver the pulse sequences discussed below. In accordance with the method, the processor 502 activates 3802 a first energy modality of the surgical instrument 108. After a first period, the processor 502 deactivates 3804 the first energy modality and activates 3806 a second energy modality for a second period. The second energy modality is activated 3806 independent of the first energy modality. After the second period expires, the processor 502 deactivates 3808 the second energy modality.

[0272] FIG. 65 is a logic flow diagram 3900 of a technique for delivering pulses of different energy modalities to tissue. As described herein, the logic flow diagram 3900 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to the logic flow diagram 3900 of FIG. 65, initially, tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108 and then the processor 502 signals the waveform generator 504 to deliver the pulse sequences discussed herein. In accordance with the method, the processor 502 activates 3902 an RF energy modality of the surgical instrument 108 to drive RF energy through electrodes located in the clamp arm 145 of the end effector 125. The processor 502 deactivates 3904 the RF energy modality upon detecting a first predetermined tissue impedance Z_{T1} measured at the end effector 125 of the surgical instrument 108. The generator 500 then activates 3906 an ultrasonic energy modality of the surgical instrument 108 to drive the ultrasonic blade 149. The processor 502 deactivates 3908 the ultrasonic energy modality upon detecting a second predetermined tissue impedance Z_{T2} at the end effector 125 of the surgical instrument 108. As previously discussed, the tissue impedance is determined by the processor 502 by dividing the voltage applied to the end effector 125 by the current delivered to the end effector 125. For example, the processor 502 can determine the tissue impedance by dividing the voltage sensed by the second voltage sensing circuit 524 by the current sensed by the current sensing circuit 514.

[0273] FIG. 66 is a logic flow diagram 4000 of a technique for delivering pulses of different energy modalities to tissue. As described herein, the logic flow diagram 4000 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to the logic flow diagram 4000 of FIG. 66, initially, tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108 and then the processor 502 signals the waveform generator 504 to deliver the pulse sequences discussed herein. In accordance with the method, the processor 502 activates 4002 an RF energy modality of the surgical instrument 108 to drive RF energy through electrodes located in the clamp arm 145 of the end effector 125. The processor 502 deactivates 4004 the RF energy modality upon the expiration of a first predetermined period T_1 . The processor 502 activates 4006 an ultrasonic energy modality of the surgical instrument 108 to drive the ultrasonic blade 149. The processor 502 deactivates 4008 the ultrasonic energy modality upon the expiration of a second predetermined period T_2 .

Techniques for Simultaneously Delivering Blasts of Ultrasonic and RF Energy in a Combination Ultrasonic/RF Surgical Instrument

[0274] In one aspect, the present disclosure provides a technique for delivering a combination simultaneous blast of RF and ultrasonic energy to an end effector of a surgical instrument by controlling the power delivered to an end effector from a generator, such as any one of the generators 102, 200, 300, 400, 500 (FIGS. 1-3 and 4-8), or a surgical instrument, such as the surgical instrument 108 (FIGS. 1-3). In accordance with the present technique, a combination simultaneous blast of RF and ultrasonic energy can be delivered to an end effector of a surgical instrument can be

varied based on properties or parameters of tissue interacting with the end effector. For conciseness and clarity of disclosure, the techniques for delivering a combination simultaneous blast of RF and ultrasonic energy to the end effector will be described with reference to the multifunction surgical instrument 108 of FIG. 2 coupled to the generator 500 of FIG. 8, although it will be appreciated that other configurations of instruments, generators, and end effectors described herein may be readily substituted without departing from the scope of the present disclosure.

[0275] FIGS. 67-71 illustrate aspects of delivering multiple energy modalities to tissue. In one aspect the first energy modality is RF energy and the second energy modality is ultrasonic energy. There are many benefits to a surgical device that is capable of delivering both RF and ultrasonic energy. A surgical instrument capable of delivering both modalities provides stronger seals and can cut tissue without the need of a separate knife. The following disclosure provides multiple pulsing techniques that can be utilized for vessel sealing. These techniques employ tissue impedance measurements, current measurements, can seal only, and can seal and cut tissue.

[0276] The various aspects described below provides simultaneous activation of multiple energy modalities such as RF and ultrasonic energy modalities. Initially both RF and ultrasonic modalities are delivered to tissue. The RF energy modality is utilized for the first portion of the seal. After a set amount of time T_1 , based off the RF impedance Z_T detected, the ultrasonic modality is terminated. A short blast of ultrasonic energy at the beginning of the seal cycle provides benefits to sealing, as it aids in heating the ultrasonic blade and subsequently the tissue surface in contact with the blade while the electrode is simultaneously heating the tissue surface in contact with the RF electrodes.

[0277] These techniques may be implemented using multiple generators, one generator configured to deliver RF energy and another generator configured to deliver ultrasonic energy. Alternatively, these techniques may be implemented with a single generator configured to deliver both RF and ultrasonic energy. In other aspects, these techniques may be implemented with a single generator that is configured to deliver RF and ultrasonic energy simultaneously through a single output port. These techniques comprise simultaneous pulsing of RF and ultrasonic energy modalities to create strong seals. Multiple configurations of pulsing are disclosed. Multiple configurations of the simultaneous techniques are disclosed.

[0278] FIG. 67 is a logic flow diagram 4100 of one aspect of a process of applying simultaneous activation of different energy modalities to tissue. As described herein, the logic flow diagram 4100 may be implemented in the generator 500, the multifunction surgical instrument 108, or a combination thereof. With reference now to the logic flow diagram 4100 of FIG. 67, tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108 and then the generator 500 delivers the simultaneous energy modalities. The total seal time 4102 is shown along a vertical axis.

[0279] Once tissue is clamped between the clamp arm 145 and the ultrasonic blade 149 of the end effector 125 of the surgical instrument 108, the processor 502 signals the waveform generator 504 to deliver the pulse sequences discussed herein. In accordance with the logic flow diagram 4100 of FIG. 67, the RF energy modality application process 4104 is

shown on the left and ultrasonic energy modality application process 4116 is shown on the right. The processor 502 activates 4196 the RF energy modality at the same time that the ultrasonic energy modality is activated 4118. Once the RF energy modality is activated 4106, the processor 502 signals the waveform generator 504 to deliver 4108 RF energy in accordance with a variety of RF sealing techniques, including RF sealing techniques described herein in connection with the logic diagram 4600 shown FIG. 72. Turning back to FIG. 67, the processor 502 activates 4120 the ultrasonic energy modality at a constant power level. During the simultaneous application of the RF and ultrasonic energy modalities, the processor 502 measures the RF tissue impedance Z_{tissue} and when the RF tissue impedance Z_{tissue} meets or exceeds an ultrasonic termination impedance $Z_{US-term}$ (see FIG. 68) it is provided 4110 as feedback to the processor 502 to signal 4122 the waveform generator 504 and amplifier 506 to terminate 4124 delivery of ultrasonic energy to the end effector 125. Meantime, the RF energy modality is continuously delivered until an RF termination impedance $Z_{RF-term}$ is reached 4112 at which point the processor 502 signals the waveform generator 504 to terminate 4114 delivery of RF energy. The short blast of the ultrasonic energy at the beginning of the seal cycle provides benefits to sealing, as it aids in heating the ultrasonic blade 149 and subsequently the tissue surface in contact with the blade 149 while the electrode in the clamp arm 145 is simultaneously heating the tissue surface in contact with the electrode. As previously discussed, the tissue impedance is determined by the processor 502 by dividing the voltage applied to the end effector 125 by the current delivered to the end effector 125. For example, the processor 502 can determine the tissue impedance by dividing the voltage sensed by the second voltage sensing circuit 524 by the current sensed by the current sensing circuit 514.

[0280] FIG. 68 is a graphical representation of RF Impedance versus Time in connection with the logic flow diagram 4100 of FIG. 67 to illustrate the ultrasonic termination impedance. The horizontal axis is time (ms) and the vertical axis is RF impedance (Ohms). The tissue impedance Z_{tissue} curve 4202 is monitored during the sealing period utilizing the RF energy. When the tissue impedance Z_{tissue} reaches the ultrasonic termination impedance $Z_{US-term}$ 4204 the ultrasonic power is terminated and when the tissue impedance Z_{tissue} reaches the RF termination impedance $Z_{RF-term}$ 4206 the RF energy is terminated.

[0281] FIG. 69 illustrates an example of the quality of a seal 4302 made in a vessel 4300 using the simultaneous activation of RF and ultrasonic energy modalities as described in connection with FIGS. 67 and 68. The main advantage of simultaneous activation of RF and ultrasonic energy modalities is that the ultrasonic energy heats up the ultrasonic blade 149 and helps to create a reduction in the difference in thermal mass between the ultrasonic blade 149 and the electrode in the clamp arm 145. During a non-simultaneous activation seal cycle utilizing both RF and ultrasonic modalities, a challenge is posed to create a strong seal with varying thermal masses on either side of the end effector 125 jaw.

[0282] FIG. 70 is a graphical representation 4400 of seal burst pressure of carotid bundles versus an RF only seal and a simultaneous RF/ultrasonic seal as described in connection with FIGS. 67-69. The horizontal axis is an RF seal only boxplot 4402 and a simultaneous RF/ultrasonic boxplot

4404. The boxplots **4402**, **4404** demonstrate the tissue effect advantages described in connection with the simultaneous RF/ultrasonic energy modality activation process **4100** shown in connection with FIG. 67 where simultaneously heating the ultrasonic blade and electrode provides a high quality **4302** in a vessel as shown in FIG. 69.

[**0283**] FIG. 71 is a logic flow diagram **4500** of a process of simultaneous activation of RF and ultrasonic energy modalities. As described herein, the logic flow diagram **4500** may be implemented in the generator **500**, the multifunction surgical instrument **108**, or a combination thereof. With reference now to the logic flow diagram **4500** of FIG. 71, initially, tissue is clamped between the clamp arm **145** and the ultrasonic blade **149** of the end effector **125** of the surgical instrument **108** and then the processor **502** signals the waveform generator **504** to deliver the pulse sequences discussed herein. In accordance with the logic flow diagram **4500**, the processor **502** simultaneously activates **4502** an RF energy modality and an ultrasonic energy modality of the surgical instrument **108**. The processor **502** monitors **4504** the tissue impedance using RF energy modality. When the tissue impedance is equal to or greater than a first termination impedance, the generator **500** deactivates **4506** the ultrasonic energy modality of the surgical instrument **108**. The RF energy modality is delivered until the tissue impedance is equal to or greater than a second termination impedance, at which time the processor **502** deactivates **4508** the RF energy modality of the surgical instrument **108** and the tissue seal is complete.

[**0284**] In some aspects utilizing a pulsed drive signal, a generator, such as, for example, one of generators **102**, **200**, **300**, **400**, **500** described in connection with FIGS. 1-3 and 5-8, may apply one or more composite load curves to the drive signal, and ultimately to the tissue. Composite load curves may define a level of power to be delivered to the tissue as a function of a measured tissue property or properties (e.g., impedance). Composite load curves may, additionally, define pulse characteristics, such as pulse width, in terms of the measured tissue properties.

[**0285**] FIG. 72 illustrates one aspect of a logic diagram **4600** for the selection and application of composite load curves by any one of generators **102**, **200**, **300**, **400**, **500**. It will be appreciated that the logic diagram **4600** may be implemented with any suitable type of generator or surgical device. According to various aspects, the logic diagram **4600** may be implemented utilizing an electrosurgical instrument, such as the electrosurgical instrument **106** described above with respect to FIG. 1, an ultrasonic surgical instrument **104** described above with respect to FIG. 1, or a combination surgical instrument **108** described above with respect to FIGS. 1-3.

[**0286**] Referring back to FIG. 72, a control process **4602** may be executed, for example by a digital device of the generator **102** to select and apply composite load curves **4606**, **4608**, **4610**, **4612**. The control process **4602** may receive a time input from a clock **4604** and may also receive loop input **4624** from sensors **4618**. The loop input **4624** may represent properties or characteristics of the tissue that may be utilized in the control process **4602** to select and/or apply a composite load curve. Examples of such characteristics may comprise, for example, current, voltage, temperature, reflectivity, force delivered to the tissue, resonant frequency, rate of change of resonant frequency, etc. The sensors **4618** may be dedicated sensors (e.g., thermometers,

pressure sensors, etc.) or may be software implemented sensors for deriving tissue characteristics based on other system values (e.g., for observing and/or calculating voltage, current, tissue temperature, etc., based on the drive signal). The control process **4602** may select one of the composite load curves **4606**, **4608**, **4610**, **4612** to apply, for example based on the loop input **4624** and/or the time input from the clock **4604**. Although four composite load curves are shown, it will be appreciated that any suitable number of composite load curves may be used.

[**0287**] The control process **4602** may apply a selected composite load curve in any suitable manner. For example, the control process **4602** may use the selected composite load curve to calculate a power level and one or more pulse characteristics based on tissue impedance (e.g., currently measured tissue impedance may be a part of, or may be derived from, the loop input) or resonant frequency characteristics of a ultrasonic surgical instrument **104**. Examples of pulse characteristics that may be determined based on tissue impedance according to a composite load curve may include pulse width, ramp time, and off time.

[**0288**] At set point **4614**, the derived power and pulse characteristics may be delivered to the drive signal. In various aspects, a feedback loop **4622** may be implemented to allow for more accurate modulation of the drive signal. At the output of the set point **4614**, the drive signal may be provided to an amplifier **4616**, which may provide suitable amplification. The amplified drive signal may be provided to a load **4620** (e.g., via sensors **4618**). The load **4620** may comprise the tissue, the surgical instrument **104**, **106**, **108**, and/or any cable electrically coupling a generator with the surgical instrument **104**, **106**, **108** (e.g., cables **142**, **144**, **146**).

[**0289**] In various aspects the state of coagulation may be determined using neural networks that are configured to take a plurality of factors into account. In some aspects, a generator may be configured to drive both ultrasonic and electrosurgical systems and include a nested neural network to identify whether the generator is presented with a true short circuit vs. a low impedance tissue. In addition, in some aspects, to assist in the detection of short circuits, the neural network may be configured to track and store at least the following factors: a. Measured resistance/impedance; b. Drive current (RMS); c. Drive Voltage (RMS); and d. Moving average of measured impedance. In some aspects, the neural network will be thought to in order to be capable of discerning between a true short and low impedance tissue. In other aspects, a neural network may be programmed to identify properties in metal, tissues, and other non-tissue elements. The neural network also may be configured to transmit the exploratory pulse to the transducer. In addition, new developments or additional programs, including receiving feedback from the attempts to detect short circuits, may be incorporated back into the neural network to increase its situational awareness and effectively better learn how to detect a true short circuit. With confirmation of a short circuit both by RF and ultrasonic functionality, this can allow for less time spent getting repeat errors on RF and faster transection on low impedance tissue. An example of a neural network is described in connection with FIG. 73.

[**0290**] FIG. 73 illustrates one aspect of a neural network **4700** for controlling a generator. FIG. 73 illustrates one aspect of an artificial neural network **4700** for generating an estimated temperature T_{est} resulting from an application of

ultrasonic energy using an ultrasonic surgical instrument, such as the ultrasonic surgical instruments 104, 106, 108 (FIGS. 1-3). In certain aspects, the neural network 4700 may be implemented in the processor and/or the programmable logic device of the generator 102 (FIG. 1). The neural network 4700 may comprise an input layer 4702, one or more nodes 4704 defining a hidden layer 4706, and one or more nodes 4708 defining an output layer 4710. For the sake of clarity, only one hidden layer 4706 is shown. In certain aspects, the neural network 4700 may comprise one or more additional hidden layers in a cascaded arrangement, with each additional hidden layer having a number of nodes 4704 that may be equal to or different from the number of nodes 4704 in the hidden layer 4706.

[0291] Each node 4704, 4708 in the layers 4702, 4710 may include one or more weight values w 4712, a bias value b 4714, and a transform function f 4716. In FIG. 73, the use of different subscripts for these values and functions is intended to illustrate that each of these values and functions may be different from the other values and functions. The input layer 4702 comprises one or more input variables p 4718, with each node 4704 of the hidden layer 4706 receiving as input at least one of the input variables p 4718. As shown in FIG. 73, for example, each node 4704 may receive all of the input variables p 4718. In other aspects, less than all of the input variables p 4718 may be received by a node 4704. Each input variable p 4718 received by a particular node 4704 is weighted by a corresponding weight value w 4712, then added to any other similarly weighted input variables p 4718, and to the bias value b 4712. The transform function f 4716 of the node 4704 is then applied to the resulting sum to generate the node's output. In FIG. 73, for example, the output of node 4704-1 may be given as $f_1(n_1)$, where $n_1 = (w_{1,1} \cdot p_1 + w_{1,2} \cdot p_2 + \dots + w_{1,j} \cdot p_{1,j} + b_1$.

[0292] A particular node 4708 of the output layer 4710 may receive an output from one or more of the nodes 4704 of the hidden layer 4706 (e.g., each node 4708 receives outputs $f_1(\bullet)$, $f_2(\bullet)$, \dots , $f_i(\bullet)$ from respective nodes 4704-1, 4704-2, \dots , 4704- i in FIG. 73), with each received output being weighted by a corresponding weight value w 4712 and subsequently added to any other similarly weighted received outputs, and to a bias value b 4714. The transform function f 4716 of the node 4708 is then applied to the resulting sum to generate the node's output, which corresponds to an output of the neural network 4700 (e.g., the estimated temperature T_{est} in the aspect of FIG. 73). Although the aspect of the neural network 4700 in FIG. 73 comprises only one node 4708 in the output layer 4710, in other aspects the neural network 4700 may comprise more than one output, in which case the output layer 4710 may comprise multiple nodes 4708.

[0293] In certain aspects, the transform function f 4716 of a node 4704, 4708 may be a nonlinear transfer function. In one aspect, for example, one or more of the transform functions f 4716 may be a sigmoid function. In other aspects, the transform functions f 4716 may include a tangent sigmoid, a hyperbolic tangent sigmoid, a logarithmic sigmoid, a linear transfer function, a saturated linear transfer function, a radial basis transfer function, or some other type of transfer function. The transform function f 4716 of a particular node 4704, 4708 may be the same as, or different from, a transform function f 4716 in another node 4704, 4708.

[0294] In certain aspects, the input variables p 4718 received by the nodes 4704 of the hidden layer 4706 may represent, for example, signals and/or other quantities or conditions known or believed to have an effect on the temperature or heating resulting from an application of ultrasonic energy. Such variables may comprise, for example, one or more of: drive voltage output by the generator 102, drive current output by the generator 102, drive frequency of the generator output 102, drive power output by the generator 102, drive energy output by the generator 102, impedance of the ultrasonic transducer 120, and time duration over which ultrasonic energy is delivered. Additionally, one or more of the input variables p 4718 may be unrelated to outputs of the generator 102 and may comprise, for example, characteristics of the end effector 122, 125 (e.g., blade tip size, geometry, and/or material) and a particular type of tissue targeted by the ultrasonic energy.

[0295] The neural network 4700 may be trained (e.g., by changing or varying the weight values w 4712, the bias values b 4714, and the transform functions f 4716) such that its output (e.g., estimated temperature T_{est} in the aspect of FIG. 73) suitably approximates a measured dependency of the output for known values of the input variables p 4718. Training may be performed, for example, by supplying known sets of input variables p 4718, comparing output of the neural network 4700 to measured outputs corresponding to the known sets of input variables p 4718, and modifying the weight values w 4712, the bias values b 4714, and/or the transform functions f 4716 until the error between the outputs of the neural network 4700 and the corresponding measured outputs is below a predetermined error level. For example, the neural network 4700 may be trained until the mean square error is below a predetermined error threshold. In certain aspects, aspects of the training process may be implemented by the neural network 4700 (e.g., by propagating errors back through the network 4700 to adaptively adjust the weight values w 4712 and/or the bias values b 4714).

[0296] While various details have been set forth in the foregoing description, it will be appreciated that the various aspects of the serial communication protocol for medical device may be practiced without these specific details. For example, for conciseness and clarity selected aspects have been shown in block diagram form rather than in detail. Some portions of the detailed descriptions provided herein may be presented in terms of instructions that operate on data that is stored in a computer memory. Such descriptions and representations are used by those skilled in the art to describe and convey the substance of their work to others skilled in the art. In general, a technique refers to a self-consistent sequence of steps leading to a desired result, where a "step" refers to a manipulation of physical quantities which may, though need not necessarily, take the form of electrical or magnetic signals capable of being stored, transferred, combined, compared, and otherwise manipulated. It is common usage to refer to these signals as bits, values, elements, symbols, characters, terms, numbers, or the like. These and similar terms may be associated with the appropriate physical quantities and are merely convenient labels applied to these quantities.

[0297] Unless specifically stated otherwise as apparent from the foregoing discussion, it is appreciated that, throughout the foregoing description, discussions using terms such as "processing" or "computing" or "calculating"

or “determining” or “displaying” or the like, refer to the action and processes of a computer system, or similar electronic computing device, that manipulates and transforms data represented as physical (electronic) quantities within the computer system’s registers and memories into other data similarly represented as physical quantities within the computer system memories or registers or other such information storage, transmission or display devices.

[0298] It is worthy to note that any reference to “one aspect,” “an aspect,” “one form,” or “an form” means that a particular feature, structure, or characteristic described in connection with the aspect is included in at least one aspect. Thus, appearances of the phrases “in one aspect,” “in an aspect,” “in one form,” or “in an form” in various places throughout the specification are not necessarily all referring to the same aspect. Furthermore, the particular features, structures or characteristics may be combined in any suitable manner in one or more aspects.

[0299] Some aspects may be described using the expression “coupled” and “connected” along with their derivatives. It should be understood that these terms are not intended as synonyms for each other. For example, some aspects may be described using the term “connected” to indicate that two or more elements are in direct physical or electrical contact with each other. In another example, some aspects may be described using the term “coupled” to indicate that two or more elements are in direct physical or electrical contact. The term “coupled,” however, also may mean that two or more elements are not in direct contact with each other, but yet still co-operate or interact with each other.

[0300] It is worthy to note that any reference to “one aspect,” “an aspect,” “one form,” or “an form” means that a particular feature, structure, or characteristic described in connection with the aspect is included in at least one aspect. Thus, appearances of the phrases “in one aspect,” “in an aspect,” “in one form,” or “in an form” in various places throughout the specification are not necessarily all referring to the same aspect. Furthermore, the particular features, structures or characteristics may be combined in any suitable manner in one or more aspects.

[0301] Although various forms have been described herein, many modifications, variations, substitutions, changes, and equivalents to those forms may be implemented and will occur to those skilled in the art. Also, where materials are disclosed for certain components, other materials may be used. It is therefore to be understood that the foregoing description and the appended claims are intended to cover all such modifications and variations as falling within the scope of the disclosed forms. The following claims are intended to cover all such modification and variations.

[0302] In a general sense, those skilled in the art will recognize that the various aspects described herein which can be implemented, individually and/or collectively, by a wide range of hardware, software, firmware, or any combination thereof can be viewed as being composed of various types of “electrical circuitry.” Consequently, as used herein “electrical circuitry” includes, but is not limited to, electrical circuitry having at least one discrete electrical circuit, electrical circuitry having at least one integrated circuit, electrical circuitry having at least one application specific integrated circuit, electrical circuitry forming a general purpose computing device configured by a computer program (e.g., a general purpose computer configured by a computer

program which at least partially carries out processes and/or devices described herein, or a microprocessor configured by a computer program which at least partially carries out processes and/or devices described herein), electrical circuitry forming a memory device (e.g., forms of random access memory), and/or electrical circuitry forming a communications device (e.g., a modem, communications switch, or optical-electrical equipment). Those having skill in the art will recognize that the subject matter described herein may be implemented in an analog or digital fashion or some combination thereof.

[0303] The foregoing detailed description has set forth various forms of the devices and/or processes via the use of block diagrams, flowcharts, and/or examples. Insofar as such block diagrams, flowcharts, and/or examples contain one or more functions and/or operations, it will be understood by those within the art that each function and/or operation within such block diagrams, flowcharts, or examples can be implemented, individually and/or collectively, by a wide range of hardware, software, firmware, or virtually any combination thereof. In one form, several portions of the subject matter described herein may be implemented via Application Specific Integrated Circuits (ASICs), Field Programmable Gate Arrays (FPGAs), digital signal processors (DSPs), or other integrated formats. However, those skilled in the art will recognize that some aspects of the forms disclosed herein, in whole or in part, can be equivalently implemented in integrated circuits, as one or more computer programs running on one or more computers (e.g., as one or more programs running on one or more computer systems), as one or more programs running on one or more processors (e.g., as one or more programs running on one or more microprocessors), as firmware, or as virtually any combination thereof, and that designing the circuitry and/or writing the code for the software and or firmware would be well within the skill of one of skill in the art in light of this disclosure. In addition, those skilled in the art will appreciate that the mechanisms of the subject matter described herein are capable of being distributed as a program product in a variety of forms, and that an illustrative form of the subject matter described herein applies regardless of the particular type of signal bearing medium used to actually carry out the distribution. Examples of a signal bearing medium include, but are not limited to, the following: a recordable type medium such as a floppy disk, a hard disk drive, a Compact Disc (CD), a Digital Video Disk (DVD), a digital tape, a computer memory, etc.; and a transmission type medium such as a digital and/or an analog communication medium (e.g., a fiber optic cable, a waveguide, a wired communications link, a wireless communication link (e.g., transmitter, receiver, transmission logic, reception logic, etc.), etc.).

[0304] All of the above-mentioned U.S. patents, U.S. patent application publications, U.S. patent applications, foreign patents, foreign patent applications, non-patent publications referred to in this specification and/or listed in any Application Data Sheet, or any other disclosure material are incorporated herein by reference, to the extent not inconsistent herewith. As such, and to the extent necessary, the disclosure as explicitly set forth herein supersedes any conflicting material incorporated herein by reference. Any material, or portion thereof, that is said to be incorporated by reference herein, but which conflicts with existing definitions, statements, or other disclosure material set forth

herein will only be incorporated to the extent that no conflict arises between that incorporated material and the existing disclosure material.

[0305] One skilled in the art will recognize that the herein described components (e.g., operations), devices, objects, and the discussion accompanying them are used as examples for the sake of conceptual clarity and that various configuration modifications are contemplated. Consequently, as used herein, the specific exemplars set forth and the accompanying discussion are intended to be representative of their more general classes. In general, use of any specific exemplar is intended to be representative of its class, and the non-inclusion of specific components (e.g., operations), devices, and objects should not be taken limiting.

[0306] With respect to the use of substantially any plural and/or singular terms herein, those having skill in the art can translate from the plural to the singular and/or from the singular to the plural as is appropriate to the context and/or application. The various singular/plural permutations are not expressly set forth herein for sake of clarity.

[0307] The herein described subject matter sometimes illustrates different components contained within, or connected with, different other components. It is to be understood that such depicted architectures are merely example, and that in fact many other architectures may be implemented which achieve the same functionality. In a conceptual sense, any arrangement of components to achieve the same functionality is effectively “associated” such that the desired functionality is achieved. Hence, any two components herein combined to achieve a particular functionality can be seen as “associated with” each other such that the desired functionality is achieved, irrespective of architectures or intermedial components. Likewise, any two components so associated also can be viewed as being “operably connected,” or “operably coupled,” to each other to achieve the desired functionality, and any two components capable of being so associated also can be viewed as being “operably couplable,” to each other to achieve the desired functionality. Specific examples of operably couplable include but are not limited to physically mateable and/or physically interacting components, and/or wirelessly interactable, and/or wirelessly interacting components, and/or logically interacting, and/or logically interactable components.

[0308] In some instances, one or more components may be referred to herein as “configured to,” “configurable to,” “operable/operative to,” “adapted/adaptable,” “able to,” “conformable/conformed to,” etc. Those skilled in the art will recognize that “configured to” can generally encompass active-state components and/or inactive-state components and/or standby-state components, unless context requires otherwise.

[0309] While particular aspects of the present subject matter described herein have been shown and described, it will be apparent to those skilled in the art that, based upon the teachings herein, changes and modifications may be made without departing from the subject matter described herein and its broader aspects and, therefore, the appended claims are to encompass within their scope all such changes and modifications as are within the true spirit and scope of the subject matter described herein. It will be understood by those within the art that, in general, terms used herein, and especially in the appended claims (e.g., bodies of the appended claims) are generally intended as “open” terms (e.g., the term “including” should be interpreted as “includ-

ing but not limited to,” the term “having” should be interpreted as “having at least,” the term “includes” should be interpreted as “includes but is not limited to,” etc.). It will be further understood by those within the art that if a specific number of an introduced claim recitation is intended, such an intent will be explicitly recited in the claim, and in the absence of such recitation no such intent is present. For example, as an aid to understanding, the following appended claims may contain usage of the introductory phrases “at least one” and “one or more” to introduce claim recitations. However, the use of such phrases should not be construed to imply that the introduction of a claim recitation by the indefinite articles “a” or “an” limits any particular claim containing such introduced claim recitation to claims containing only one such recitation, even when the same claim includes the introductory phrases “one or more” or “at least one” and indefinite articles such as “a” or “an” (e.g., “a” and/or “an” should typically be interpreted to mean “at least one” or “one or more”); the same holds true for the use of definite articles used to introduce claim recitations.

[0310] In addition, even if a specific number of an introduced claim recitation is explicitly recited, those skilled in the art will recognize that such recitation should typically be interpreted to mean at least the recited number (e.g., the bare recitation of “two recitations,” without other modifiers, typically means at least two recitations, or two or more recitations). Furthermore, in those instances where a convention analogous to “at least one of A, B, and C, etc.” is used, in general such a construction is intended in the sense one having skill in the art would understand the convention (e.g., “a system having at least one of A, B, and C” would include but not be limited to systems that have A alone, B alone, C alone, A and B together, A and C together, B and C together, and/or A, B, and C together, etc.). In those instances where a convention analogous to “at least one of A, B, or C, etc.” is used, in general such a construction is intended in the sense one having skill in the art would understand the convention (e.g., “a system having at least one of A, B, or C” would include but not be limited to systems that have A alone, B alone, C alone, A and B together, A and C together, B and C together, and/or A, B, and C together, etc.). It will be further understood by those within the art that typically a disjunctive word and/or phrase presenting two or more alternative terms, whether in the description, claims, or drawings, should be understood to contemplate the possibilities of including one of the terms, either of the terms, or both terms unless context dictates otherwise. For example, the phrase “A or B” will be typically understood to include the possibilities of “A” or “B” or “A and B.”

[0311] With respect to the appended claims, those skilled in the art will appreciate that recited operations therein may generally be performed in any order. Also, although various operational flows are presented in a sequence(s), it should be understood that the various operations may be performed in other orders than those which are illustrated, or may be performed concurrently. Examples of such alternate orderings may include overlapping, interleaved, interrupted, reordered, incremental, preparatory, supplemental, simultaneous, reverse, or other variant orderings, unless context dictates otherwise. Furthermore, terms like “responsive to,” “related to,” or other past-tense adjectives are generally not intended to exclude such variants, unless context dictates otherwise.

[0312] In certain cases, use of a system or method may occur in a territory even if components are located outside the territory. For example, in a distributed computing context, use of a distributed computing system may occur in a territory even though parts of the system may be located outside of the territory (e.g., relay, server, processor, signal-bearing medium, transmitting computer, receiving computer, etc. located outside the territory).

[0313] A sale of a system or method may likewise occur in a territory even if components of the system or method are located and/or used outside the territory. Further, implementation of at least part of a system for performing a method in one territory does not preclude use of the system in another territory.

[0314] Although various forms have been described herein, many modifications, variations, substitutions, changes, and equivalents to those forms may be implemented and will occur to those skilled in the art. Also, where materials are disclosed for certain components, other materials may be used. It is therefore to be understood that the foregoing description and the appended claims are intended to cover all such modifications and variations as falling within the scope of the disclosed forms. The following claims are intended to cover all such modification and variations.

[0315] In summary, numerous benefits have been described which result from employing the concepts described herein. The foregoing description of the one or more forms has been presented for purposes of illustration and description. It is not intended to be exhaustive or limiting to the precise form disclosed. Modifications or variations are possible in light of the above teachings. The one or more forms were chosen and described in order to illustrate principles and practical application to thereby enable one of ordinary skill in the art to utilize the various forms and with various modifications as are suited to the particular use contemplated. It is intended that the claims submitted herewith define the overall scope.

1. A method for detecting a short circuit in a surgical system configured to apply radio frequency energy and ultrasonic energy to a target surgical site, the method comprising:

- delivering, by a radio frequency (RF) drive circuit, RF energy to an electrode of a surgical instrument;
- transitioning from delivering, by the RF drive circuit, the RF energy to delivering, by an ultrasonic drive circuit, ultrasonic energy to an ultrasonic blade of the surgical instrument;
- delivering, by the ultrasonic drive circuit, an exploratory ultrasonic pulse to the ultrasonic blade;
- measuring, by a processor, an ultrasonic property of tissue engaged by the surgical instrument, wherein the ultrasonic property measured by the processor is associated with the exploratory ultrasonic pulse;
- determining, by the processor, whether the ultrasonic property measured by the processor is consistent with a behavior of low impedance tissue; and
- delivering, by the ultrasonic drive circuit, ultrasonic energy to the ultrasonic blade to cut the tissue upon determining that the ultrasonic property measured by the processor is consistent with ultrasonic energy being applied to low impedance tissue.

2. The method of claim 1, wherein the ultrasonic property measured by the processor comprises an output drive voltage of the ultrasonic pulse.

3. The method of claim 1, wherein the ultrasonic property measured by the processor comprises an acoustic characteristic of the ultrasonic pulse.

4. The method of claim 1, further comprising:

determining, by the processor, that a short circuit has occurred based on determining that the ultrasonic property measured by processor is not consistent with the behavior of low impedance tissue when ultrasonic energy is applied to the tissue; and

upon determining, by the processor, that a short circuit has occurred, ceasing delivery of the ultrasonic energy to the surgical instrument.

5. The method of claim 1, wherein determining whether the ultrasonic property measured by the processor is consistent with the behavior of low impedance tissue comprises determining whether the ultrasonic property measured by the processor is consistent with the behavior of low impedance tissue by a nested neural network of the surgical system.

6. The method of claim 5, further comprising:

measuring, by the neural network, at least one of: a tissue impedance of the tissue, a drive current, or a moving average of tissue impedance of the tissue when the exploratory ultrasonic pulse is delivered to the ultrasonic blade; and

continuing to deliver ultrasonic energy to cut the tissue based on the at least one of the tissue impedance, the drive current, or the moving average of tissue impedance.

7. A surgical instrument for coagulating and dissecting tissue, the surgical instrument comprising:

- a processor;
- an end effector at a distal end of the surgical instrument, the end effector configured to interact with tissue, the end effector comprising:
 - a clamp arm comprising an electrode;
 - an ultrasonic blade;
- an ultrasonic transducer acoustically coupled to the ultrasonic blade and configured to receive a drive signal from a generator to cause ultrasonic motion of the ultrasonic blade and deliver ultrasonic energy to the ultrasonic blade;

wherein the processor is configured to:

- control delivery of radio frequency (RF) energy to the electrode;
- transition from delivery of the RF energy to the electrode to delivery of the ultrasonic energy to the ultrasonic blade;
- control delivery of an exploratory ultrasonic pulse to the ultrasonic transducer;
- measure an ultrasonic property of tissue engaged by the end effector, wherein the ultrasonic property measured by the processor is associated with the exploratory ultrasonic pulse;
- determine whether the ultrasonic property measured by the is consistent with a behavior of low impedance tissue when the exploratory ultrasonic pulse is delivered to the ultrasonic transducer and corresponding ultrasonic energy is delivered to the ultrasonic blade; and

control delivery of the ultrasonic energy to the ultrasonic blade to cut the tissue upon determining that the ultrasonic property measured by the processor is consistent with ultrasonic energy being applied to low impedance tissue.

8. A generator for delivering energy to a surgical instrument for coagulating and dissecting tissue, the surgical instrument comprising an end effector at a distal end thereof, the end effector configured to interact with tissue, the end effector comprising a clamp arm, an ultrasonic blade, an ultrasonic transducer acoustically coupled to the ultrasonic blade and configured to receive a drive signal from the generator to cause ultrasonic motion of the ultrasonic blade and deliver ultrasonic energy to the ultrasonic blade, the generator comprising:

- a first drive circuit configured to deliver a drive signal to an ultrasonic transducer;
- a second drive circuit configured to deliver radio frequency (RF) energy to an electrode; and
- a processor configured to control the first drive circuit and the second drive circuit, and wherein the processor is configured to:
 - control the second drive circuit to deliver RF energy to the electrode;
 - transition from the second drive circuit delivering the RF energy to the electrode to the first drive circuit delivering the drive signal to the ultrasonic transducer;
 - control the first drive circuit to deliver the drive signal comprising an exploratory ultrasonic pulse to the ultrasonic transducer;
 - measure an ultrasonic property of tissue associated with the exploratory ultrasonic pulse;
 - determine whether the ultrasonic property measured by the processor is consistent with a behavior of low impedance tissue; and
 - control the first drive circuit to deliver the drive signal to the ultrasonic transducer to cut the tissue upon determining that the ultrasonic property measured by the processor is consistent with ultrasonic energy being applied to low impedance tissue.

9-73. (canceled)

74. The surgical instrument of claim **7**, wherein the ultrasonic property measured by the processor comprises an output drive voltage of the ultrasonic pulse.

75. The surgical instrument of claim **7**, wherein the ultrasonic property measured by the processor comprises an acoustic characteristic of the ultrasonic pulse.

76. The surgical instrument of claim **7**, wherein the processor is configured to:

- determine that a short circuit has occurred based on determining that the ultrasonic property measured by processor is not consistent with the behavior of low impedance tissue when ultrasonic energy is applied to the tissue; and

upon determining that a short circuit has occurred, cease delivery of the ultrasonic energy to the ultrasonic blade.

77. The surgical instrument of claim **7**, further comprising a nested neural network, and wherein the processor is configured to determine whether the ultrasonic property measured by the processor is consistent with the behavior of low impedance tissue using the nested neural network.

78. The surgical instrument of claim **77**, wherein the processor is configured to use the nested neural network to measure at least one of: a tissue impedance of the tissue, a drive current, or a moving average of tissue impedance of the tissue when the exploratory ultrasonic pulse is delivered to the ultrasonic blade, and wherein the processor is configured to continue to control delivery of the ultrasonic energy to the ultrasonic blade to cut the tissue based on the at least one of: the tissue impedance of the tissue, the drive current, or the moving average of tissue impedance of the tissue when the exploratory ultrasonic pulse is delivered to the ultrasonic blade.

79. The generator of claim **8**, wherein the ultrasonic property measured by the processor comprises an output drive voltage of the ultrasonic pulse.

80. The generator of claim **8**, wherein the ultrasonic property measured by the processor comprises an acoustic characteristic of the ultrasonic pulse.

81. The generator of claim **8**, wherein the processor is configured to:

- determine that a short circuit has occurred based on determining that the ultrasonic property measured by processor is not consistent with the behavior of low impedance tissue when ultrasonic energy is applied to the tissue; and

upon determining that a short circuit has occurred, control the first drive circuit to cease delivery of the drive signal to the ultrasonic transducer.

82. The generator of claim **8**, further comprising a nested neural network, and wherein the processor is configured to determine whether the ultrasonic property measured by the processor is consistent with the behavior of low impedance tissue using the nested neural network.

83. The generator of claim **82**, wherein the processor is configured to use the nested neural network to measure at least one of: a tissue impedance of the tissue, a drive current, or a moving average of tissue impedance of the tissue when the exploratory ultrasonic pulse is delivered to the ultrasonic transducer, and wherein the processor is configured to continue to control the first drive circuit to deliver the drive signal to the ultrasonic transducer to cut the tissue based on the at least one of: the tissue impedance of the tissue, the drive current, or the moving average of tissue impedance of the tissue when the exploratory ultrasonic pulse is delivered to the ultrasonic transducer.

* * * * *

专利名称(译)	具有用户自适应技术的手术系统采用基于组织参数的多种能量模态		
公开(公告)号	US20170000553A1	公开(公告)日	2017-01-05
申请号	US15/177449	申请日	2016-06-09
[标]申请(专利权)人(译)	爱惜康内镜外科，LLC		
申请(专利权)人(译)	爱惜康内镜外科，LLC		
当前申请(专利权)人(译)	爱惜康内镜外科，LLC		
[标]发明人	WIENER EITAN T DANZIGER BENJAMIN J YATES DAVID C HOUSER KEVIN L		
发明人	WIENER, EITAN T. DANZIGER, BENJAMIN J. YATES, DAVID C. HOUSER, KEVIN L.		
IPC分类号	A61B18/14 A61B17/32		
CPC分类号	A61B18/1445 A61B17/320092 A61B2017/0003 A61B2017/00106 A61N7/00 A61B2018/00642 A61B2018/00994 A61B2018/1452 A61B2018/00607 A61B18/1233 A61B2017/00017 A61B2017/00026 A61B2017/320094 A61B2017/320095 A61B2018/00589 A61B2018/00601 A61B2018/00708 A61B2018/ /00875 A61B2018/00886		
优先权	62/186984 2015-06-30 US 62/235260 2015-09-30 US 62/235368 2015-09-30 US 62/235466 2015-09-30 US 62/279635 2016-01-15 US 62/330669 2016-05-02 US		
外部链接	Espacenet USPTO		

摘要(译)

各种形式涉及用于组织的解剖和凝血的系统和方法。一种用于检测手术系统中的短路的方法，所述手术系统被配置为向目标手术部位施加射频能量和超声波能量，所述方法包括将射频（RF）能量递送到外科器械的电极，从递送所述RF能量转换到递送超声能量传递到所述外科器械的超声刀，将探测超声脉冲传递到所述超声刀，测量由所述外科器械接合的组织的超声属性，其中所述超声属性与所述探测超声脉冲相关联，确定所测量的超声性质与低阻抗组织的行为一致，并且在确定所测量的超声属性与施加到低阻抗组织的超声能量一致时，将超声能量递送到超声刀以切割组织。

