



US007272428B2

(12) **United States Patent**
Hopman et al.

(10) **Patent No.:** **US 7,272,428 B2**
(45) **Date of Patent:** ***Sep. 18, 2007**

(54) **WIRELESS ELECTROCARDIOGRAPH
SYSTEM AND METHOD**

3,602,215 A 8/1971 Parnell 128/2.06 B
3,603,881 A 9/1971 Thornton 325/30

(75) Inventors: **Nicholas C. Hopman**, Lake Zurich, IL
(US); **Daniel L. Williams**, Norwell,
MA (US); **Franco Lodato**, Weston, FL
(US)

(Continued)

FOREIGN PATENT DOCUMENTS

(73) Assignee: **Motorola, Inc.**, Schaumburg, IL (US)

EP 0212278 3/1987

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 416 days.

(Continued)

OTHER PUBLICATIONS

This patent is subject to a terminal dis-
claimer.

Performance Specification sheet published for Motorola C.O.R
HT-220 Handie-Talkie FM Radio, printed 1973 by Motorola, 2
pages.

(21) Appl. No.: **10/439,574**

(Continued)

(22) Filed: **May 16, 2003**

(65) **Prior Publication Data**

US 2003/0199777 A1 Oct. 23, 2003

Primary Examiner—Scott M. Getzow

(74) *Attorney, Agent, or Firm*—Brinks Hofer Gilson &
Lione

Related U.S. Application Data

(57)

ABSTRACT

(63) Continuation of application No. 09/908,509, filed on
Jul. 17, 2001, now Pat. No. 6,611,705.

(60) Provisional application No. 60/219,082, filed on Jul.
18, 2000.

(51) **Int. Cl.**
A61N 1/04 (2006.01)

(52) **U.S. Cl.** **600/382**

(58) **Field of Classification Search** 600/382,
600/386, 390

See application file for complete search history.


(56) **References Cited**

U.S. PATENT DOCUMENTS

2,864,943 A 12/1958 Schultz 250/15
2,958,781 A 11/1960 Marchal et al. 250/83.3
3,199,508 A 8/1965 Roth 128/2.06
3,495,584 A 2/1970 Schwalm 128/2.06

A method and system for wireless ECG monitoring is provided. An electrode connector, transmitter and receiver operate with existing electrodes and ECG monitors. The electrode connector includes connectors for attaching to disposable or reusable single electrodes. The transmitter transmits the signals from the electrodes to the receiver. The receiver passes the electrode signals to the ECG monitor for processing. ECG monitors used with an electrical conductor, for example wire connections to electrodes, are connected with the receiver, avoiding the purchase of a new monitor. Any legacy ECG monitor, including different ECG monitors, connects with the receiver using the ECG monitor's lead-wires. The ECG monitor operates as if directly connected to the electrodes without the problems discussed above associated with wires running from the ECG monitor to the patient.

19 Claims, 5 Drawing Sheets



U.S. PATENT DOCUMENTS

3,727,190 A	4/1973	Vogelman et al.	340/172.5	4,802,222 A	1/1989	Weaver	381/35
3,729,708 A	4/1973	Wolfer et al.	340/146.1 F	4,803,625 A	2/1989	Fu et al.	364/413.03
3,757,778 A	9/1973	Graham	128/2.06 R	4,805,631 A	2/1989	Foi du Maroc, II.	128/710
3,774,594 A	11/1973	Huszar	128/2.06 R	4,835,372 A	5/1989	Gombrich et al.	235/375
3,810,102 A	5/1974	Parks, III et al.	340/172.5	4,839,806 A	6/1989	Goldfischer et al. ...	364/413.02
3,830,228 A	8/1974	Foner	128/2.06 R	4,850,009 A	7/1989	Zook et al.	379/96
3,834,373 A	9/1974	Sato	128/2.06 E	4,860,759 A	8/1989	Kahn et al.	128/668
3,905,364 A	9/1975	Cudahy et al.	128/2.06 R	4,865,044 A	9/1989	Wallace et al.	128/736
3,925,762 A	12/1975	Heitlinger et al.	340/150	4,883,064 A	11/1989	Olson et al.	128/696
3,943,918 A	3/1976	Lewis	128/2.1 A	4,889,131 A	12/1989	Salem et al.	128/671
3,949,397 A	4/1976	Wagner et al.	343/6.5 R	4,889,132 A	12/1989	Hutcheson et al.	128/680
3,970,996 A	7/1976	Yasaka et al.	340/172.5	4,907,248 A	3/1990	Bretl	375/27
3,986,498 A	10/1976	Lewis	128/2.06 R	4,909,260 A	3/1990	Salem et al.	
3,998,213 A	12/1976	Price		4,916,441 A	4/1990	Gombrich	340/712
4,027,663 A	6/1977	Fischler et al.	128/2.06 R	4,928,187 A	5/1990	Rees	360/40
4,042,906 A	8/1977	Ezell	340/15.5 TS	4,955,075 A	9/1990	Anderson	455/182
4,051,522 A	9/1977	Healy et al.	358/86	4,957,109 A	9/1990	Groeger et al.	
4,074,228 A	2/1978	Jonscher	340/146.1 AQ	4,958,645 A	9/1990	Cadell et al.	128/903
4,121,573 A	10/1978	Crovella et al.	128/2.1 A	4,966,154 A	10/1990	Cooper et al.	128/671
4,124,894 A	11/1978	Vick et al.	364/417	4,974,607 A	12/1990	Miwa	128/904
4,141,351 A	2/1979	James et al.	128/2.06 R	4,981,141 A	1/1991	Segalowitz	
4,150,284 A	4/1979	Trenkler et al.	250/199	5,012,411 A	4/1991	Policastro et al.	364/413.06
4,156,867 A	5/1979	Bench et al.	340/146.1	5,025,452 A	6/1991	Sohner et al.	375/1
4,173,221 A	11/1979	McLaughlin et al.	128/696	5,025,808 A	6/1991	Hafner	128/696
4,173,971 A	11/1979	Karz	128/702	5,036,462 A	7/1991	Kaufman et al.	364/413.01
4,186,749 A	2/1980	Fryer	128/748	5,036,869 A	8/1991	Inahara	128/903
4,216,462 A	8/1980	McGrath et al.	340/150	5,042,498 A	8/1991	Dukes	128/696
4,233,241 A	11/1980	Kalopissis et al.	564/221	5,051,799 A	9/1991	Paul et al.	375/25
4,237,900 A	12/1980	Schulman et al.	128/630	5,072,383 A	12/1991	Brimm et al.	364/413.02
4,260,951 A	4/1981	Lewyn	328/165	5,077,753 A	12/1991	Grau	375/1
4,262,632 A	4/1981	Hanton et al.	119/1	5,078,134 A	1/1992	Heilman et al.	128/421
4,281,664 A	8/1981	Duggan	128/696	5,085,224 A	2/1992	Galen et al.	128/696
4,321,933 A	3/1982	Baessler	128/736	5,109,845 A	5/1992	Yuuchi et al.	128/421
4,353,372 A	10/1982	Ayer	128/640	5,113,869 A	5/1992	Nappholz et al.	128/696
4,381,012 A *	4/1983	Russek	600/382	5,127,404 A	7/1992	Wyborny et al.	128/419 P
4,396,906 A	8/1983	Weaver	340/347 DD	5,131,399 A	7/1992	Sciarra	128/671
4,425,921 A	1/1984	Fujisaki et al.	128/690	5,137,022 A	8/1992	Henry	128/419 PT
4,441,498 A	4/1984	Nordling	128/419 P	5,153,584 A	10/1992	Engira	340/870.18
4,449,536 A	5/1984	Weaver	128/696	5,157,604 A	10/1992	Axford et al.	364/413.03
4,471,786 A	9/1984	Inagaki et al.	128/748	5,168,874 A	12/1992	Segalowitz	128/639
4,475,208 A	10/1984	Ricketts	375/1	5,171,977 A	12/1992	Morrison	235/375
4,510,495 A	4/1985	Sigrimis et al.	340/825.54	5,177,765 A	1/1993	Holland et al.	375/1
4,521,918 A	6/1985	Challen	455/343	5,177,766 A	1/1993	Holland et al.	375/1
4,531,526 A	7/1985	Genest	128/630	5,179,569 A	1/1993	Sawyer	375/1
4,537,200 A	8/1985	Widrow	128/696	5,179,571 A	1/1993	Schilling	375/1
4,556,061 A	12/1985	Barreras et al.	128/419 PT	5,181,519 A	1/1993	Bible	128/704
4,556,063 A	12/1985	Thompson et al.	128/419 PT	5,192,949 A	3/1993	Suzuki et al.	341/68
4,562,840 A	1/1986	Batina et al.	128/419 PT	5,205,294 A	4/1993	Flach et al.	128/696
4,573,026 A	2/1986	Curtis et al.	332/18	5,212,476 A	5/1993	Maloney	340/825.19
4,583,548 A	4/1986	Schmid	128/639	5,212,715 A	5/1993	Pickert et al.	375/114
4,583,549 A	4/1986	Manoli	128/640	5,224,485 A	7/1993	Powers et al.	128/696
4,585,004 A	4/1986	Brownlee	128/419 PT	5,226,431 A	7/1993	Bible et al.	128/904
4,586,508 A	5/1986	Batina et al.	128/419 PG	5,238,001 A	8/1993	Gallant et al.	128/700
4,598,281 A	7/1986	Maas	340/664	5,270,811 A	12/1993	Ishibashi et al.	358/108
4,599,723 A	7/1986	Eck	371/47	5,272,477 A	12/1993	Tashima et al.	340/870.16
4,601,043 A	7/1986	Hardt et al.	375/1	5,292,343 A	3/1994	Blanchette et al.	607/32
4,606,352 A	8/1986	Geddes et al.	128/702	5,305,202 A	4/1994	Gallant et al.	364/413.06
4,618,861 A	10/1986	Gettens et al.	340/825.54	5,305,353 A	4/1994	Weerackody	375/100
4,625,733 A	12/1986	Sayajakangas	128/687	5,307,372 A	4/1994	Sawyer et al.	375/1
RE32,361 E	2/1987	Duggan	128/696	5,307,817 A	5/1994	Guggenbuhl et al.	128/696
4,653,068 A	3/1987	Kadin	375/1	5,307,818 A	5/1994	Segalowitz	128/696
4,681,118 A	7/1987	Asai et al.	128/643	5,309,920 A	5/1994	Gallant et al.	128/710
4,709,704 A	12/1987	Lukasiewicz	128/644	5,314,450 A	5/1994	Thompson	607/32
4,724,435 A	2/1988	Moses et al.	340/870.13	5,335,664 A	8/1994	Nagashima	128/696
4,747,413 A	5/1988	Bloch	128/736	5,339,824 A	8/1994	Engira	128/712
4,754,483 A	6/1988	Weaver	381/36	5,342,408 A	8/1994	deCoriolis et al.	607/32
4,783,844 A	11/1988	Higashiyama et al.	455/34	5,343,869 A	9/1994	Pross et al.	128/700
4,784,162 A	11/1988	Ricks et al.	128/903	5,348,008 A	9/1994	Bornn et al.	128/642
4,791,933 A	12/1988	Asai et al.	128/640	5,353,791 A	10/1994	Tamura et al.	128/633
4,793,532 A	12/1988	Leckband et al.	364/413.06	5,353,793 A	10/1994	Bornn	
4,799,059 A	1/1989	Grindahl et al.	340/870.03	5,354,319 A	10/1994	Wyborny et al.	607/32
				5,359,641 A	10/1994	Schull et al.	379/106
				5,365,530 A	11/1994	Yoshida	371/37.4

US 7,272,428 B2

Page 3

5,375,604 A	12/1994	Kelly et al.	128/671	5,919,141 A	7/1999	Money et al.	600/513
5,377,222 A	12/1994	Sanderford, Jr.	375/1	5,919,214 A	7/1999	Ciciarelli et al.	607/32
5,381,798 A	1/1995	Burrows	128/696	5,931,791 A	8/1999	Saltzstein et al.	600/513
5,392,771 A	2/1995	Mock et al.	128/205.23	5,935,078 A	8/1999	Feierbach	600/509
5,394,879 A	3/1995	Gorman		5,938,597 A	8/1999	Stratbucker	
5,394,882 A	3/1995	Mawhinney	128/721	5,944,659 A	8/1999	Flach et al.	600/300
5,400,794 A	3/1995	Gorman		5,949,352 A	9/1999	Ferrari	340/870
5,416,695 A	5/1995	Stutman et al.	364/413.02	5,954,536 A	9/1999	Fuerst et al.	439/493
5,417,222 A	5/1995	Dempsey et al.	128/696	5,954,539 A	9/1999	Hornung	439/590
5,438,329 A	8/1995	Gastouniotis et al. ..	340/870.02	5,954,719 A	9/1999	Chen et al.	606/42
5,438,607 A	8/1995	Przygoda, Jr. et al.	379/38	5,957,854 A	9/1999	Besson et al.	
5,441,047 A	8/1995	David et al.	128/670	5,959,529 A	9/1999	Kail, IV	340/539
5,444,719 A	8/1995	Cox et al.	371/37.1	5,960,119 A	9/1999	Echigo et al.	382/248
5,445,149 A *	8/1995	Rotolo et al.	600/382	5,961,448 A	10/1999	Swenson et al.	600/301
5,458,123 A	10/1995	Unger	128/696	5,963,650 A	10/1999	Simionescu et al.	380/49
5,458,124 A	10/1995	Stanko et al.	128/696	5,964,701 A	10/1999	Asada et al.	600/300
5,464,021 A	11/1995	Birnbaum	128/696	5,966,692 A	10/1999	Langer et al.	705/3
5,485,848 A	1/1996	Jackson et al.	128/672	5,970,105 A	10/1999	Dacus	375/344
5,491,474 A	2/1996	Suni et al.	340/870.31	5,995,861 A	11/1999	Price	600/372
5,507,035 A	4/1996	Bantz et al.	455/133	5,999,857 A	12/1999	Weijand et al.	607/60
5,511,553 A	4/1996	Segalowitz	128/696	6,006,125 A	12/1999	Kelly et al.	600/382
5,522,396 A	6/1996	Langer et al.	128/696	6,009,350 A	12/1999	Renken	607/32
5,524,637 A	6/1996	Erickson	128/779	6,010,359 A	1/2000	Etters et al.	439/496
5,538,007 A	7/1996	Gorman		6,027,363 A	2/2000	Watt et al.	439/456
5,544,649 A	8/1996	David et al.	128/630	6,039,600 A	3/2000	Etters et al.	439/496
5,544,661 A	8/1996	Davis et al.	128/700	6,047,201 A	4/2000	Jackson, III	600/344
5,546,950 A *	8/1996	Schoeckert et al.	600/508	6,053,887 A	4/2000	Levitas et al.	604/49
5,549,113 A	8/1996	Halleck et al.	128/671	6,057,758 A	5/2000	Dempsey et al.	340/539
5,564,429 A	10/1996	Bornn et al.	128/696	6,066,093 A	5/2000	Kelly et al.	600/386
5,576,952 A	11/1996	Stutman et al.	364/413.02	6,073,046 A	6/2000	Patel et al.	600/509
5,579,001 A	11/1996	Dempsey et al.	340/870.01	6,074,345 A	6/2000	Van Oostrom et al.	600/300
5,579,378 A	11/1996	Arlinghaus, Jr.	379/106	6,076,003 A	6/2000	Rogel	600/390
5,579,775 A	12/1996	Dempsey et al.	128/670	6,077,124 A	6/2000	Etters et al.	439/632
5,579,781 A	12/1996	Cooke	128/733	6,083,248 A	7/2000	Thompson	607/30
5,582,180 A	12/1996	Manset et al.	128/696	6,086,412 A	7/2000	Watt et al.	439/496
5,586,552 A	12/1996	Sakai	128/633	6,093,146 A	7/2000	Filangeri	600/523
5,617,871 A	4/1997	Burrows	128/696	6,102,856 A	8/2000	Groff	600/301
5,628,324 A	5/1997	Sarbach	128/670	6,117,076 A	9/2000	Cassidy	300/300
5,628,326 A	5/1997	Arand et al.		6,141,575 A	10/2000	Price	600/372
5,634,468 A	6/1997	Platt et al.		6,146,190 A	11/2000	Fuerst et al.	439/496
5,640,953 A	6/1997	Bishop et al.	128/630	6,147,618 A	11/2000	Halleck et al.	340/669
5,646,701 A	7/1997	Duckworth et al. ...	340/825.69	6,149,602 A	11/2000	Arcelus	600/523
5,664,270 A	9/1997	Bell et al.	5/600	6,154,676 A	11/2000	Levine	607/58
5,669,391 A	9/1997	Williams		6,173,198 B1 *	1/2001	Schulze et al.	600/382
5,678,545 A	10/1997	Stratbucker	128/640	6,198,394 B1	3/2001	Jacobsen et al.	340/573.1
5,678,562 A	10/1997	Sellers	128/710	6,206,837 B1	3/2001	Brugnoli	600/529
5,685,303 A	11/1997	Rollman et al.	128/644	6,208,889 B1	3/2001	Gorman	
5,694,940 A	12/1997	Unger et al.	128/696	6,213,942 B1	4/2001	Flach et al.	600/300
5,704,351 A	1/1998	Mortara et al.		6,225,901 B1	5/2001	Kail, IV	340/539
5,718,234 A	2/1998	Warden et al.	128/696	6,236,874 B1	5/2001	Devlin et al.	600/372
5,720,771 A	2/1998	Snell	607/60	6,238,338 B1	5/2001	DeLuca et al.	600/300
5,738,102 A	4/1998	Lemelson	128/671	6,244,890 B1	6/2001	Fuerst et al.	439/357
5,748,103 A	5/1998	Flach et al.	340/870.07	6,267,723 B1	7/2001	Matsumura et al.	600/300
5,755,230 A	5/1998	Schmidt et al.	128/731	6,287,252 B1	9/2001	Lugo	600/300
5,759,199 A	6/1998	Snell et al.	604/60	6,289,238 B1	9/2001	Besson et al.	
5,767,791 A	6/1998	Stoop et al.	340/870.11	6,292,687 B1	9/2001	Lowell et al.	
5,779,630 A	7/1998	Fein et al.	600/323	6,295,466 B1	9/2001	Ishikawa et al.	600/509
5,788,633 A	8/1998	Mahoney	600/382	6,304,774 B1	10/2001	Gorman	
5,800,204 A	9/1998	Niitsu	439/495	6,319,200 B1	11/2001	Lai et al.	600/300
5,813,404 A	9/1998	Devlin et al.	128/639	6,332,094 B1	12/2001	Gorman	
5,819,740 A	10/1998	Muhlenberg	128/696	6,332,940 B1	12/2001	Fujiki et al.	75/243
5,820,567 A	10/1998	Mackie	600/519	6,364,834 B1	4/2002	Reuss et al.	600/300
5,827,179 A	10/1998	Lichter et al.	600/300	6,389,308 B1	5/2002	Shusterman	600/509
5,862,803 A	1/1999	Besson et al.		6,416,471 B1	7/2002	Kumar et al.	600/300
5,865,733 A	2/1999	Malinouskas et al.	600/300	6,440,067 B1	8/2002	DeLuca et al.	600/300
5,868,671 A	2/1999	Mahoney	600/382	6,441,747 B1	8/2002	Khair et al.	
5,871,451 A	2/1999	Unger et al.	600/509	6,450,953 B1	9/2002	Place et al.	600/300
5,873,369 A	2/1999	Laniado et al.	128/903	6,475,153 B1	11/2002	Khair et al.	
5,882,300 A	3/1999	Malinouskas et al.	600/300	6,480,733 B1	11/2002	Turcott	600/516
5,899,928 A	5/1999	Sholder et al.	607/27	6,496,705 B1	12/2002	Ng et al.	
5,899,931 A	5/1999	Deschamp et al.	607/60	6,533,729 B1	3/2003	Khair et al.	
5,913,827 A	6/1999	Gorman					
5,917,414 A	6/1999	Oppelt et al.	340/573.1				

2002/0038094 A1 3/2002 Gorman 600/520 WO WO 00/62667 10/2000

FOREIGN PATENT DOCUMENTS

GB	2271691	4/1994
WO	WO94/01039	1/1994
WO	WO97/49077	12/1997
WO	WO98/00056	1/1998

OTHER PUBLICATIONS

Performance Specification sheet published for Motorola C.O.R. HT-220 "Handie-Talkie" FM Radio, printed 1971 by Motorola, 2 pages.

* cited by examiner




FIG. 2C




FIG. 2D










FIG.5







1

**WIRELESS ELECTROCARDIOGRAPH
SYSTEM AND METHOD****CROSS-REFERENCE TO RELATED
APPLICATIONS**

This application is a continuation of U.S. application Ser. No. 09/908,509, filed Jul. 17, 2001, now U.S. Pat. No. 6,611,705 which claims the benefit of the filing date pursuant to 35 U.S.C. §119(e) of Provisional Application Ser. No. 60/219,082, filed Jul. 18, 2000, for a WIRELESS EKG, the disclosures of which are hereby incorporated by reference.

BACKGROUND

This invention relates to medical monitoring systems and methods. In particular, a biomedical system and method for monitoring a patient is provided.

Biomedical monitoring systems include bedside, transportable, ambulatory and discrete vital sign monitors. In vital signs monitors, electrocardiograph (ECG), temperature, blood pressure or other characteristics of a patient are monitored.

ECG systems are used for monitoring activity of a patient's heart. For example, three electrodes are positioned on the patient. The signal from one electrode is used as a reference signal for a difference between the signals of two other electrodes (e.g. ECG vector). By using this reference signal, and a differential amplifier configuration, common mode interference can be essentially eliminated or reduced. As another example, nine electrodes are positioned on the patient for a "12-lead" analysis of electrical activity of the heart.

Wires are connected from the electrodes to an ECG monitor. The ECG monitor processes the signals and outputs ECG data, such as a plurality of traces representing activity of the heart by measuring electrical signals at different positions on the patient. However, the wires inhibit movement by and around the patient. The wires will stress the electrodes, resulting in malfunction or disconnection from the patient. A caregiver's time is then required to reconnect or replace the electrodes. Patients are often moved during a day, requiring disconnecting one ECG monitor and reconnecting another ECG monitor. Often the electrodes also need to be removed and replaced. If not replaced in exactly the same position, the patient's ECG will be different from ECG monitor to ECG monitor, creating an artifact in the ECG.

Wireless ECG systems connect the electrodes to a transmitter to avoid wires from the patient to a monitor. In the example described in WO 94/01039, a microchip is positioned proximate the electrodes on the patient. The microchip analyzes the signals from the electrodes and transmits the results (see page 42). The results are received and provided to a printer or monitor (see page 26). However, a complete system including a monitor, printer or recorder operable to receive the signals as processed by the microchip on the patient is required.

Holter monitors record a patient's vital signs over a time period. The patient carries the complete monitor and recorder. The information can be downloaded or otherwise obtained for subsequent analysis. However, many of these systems limit the bandwidth of signals to suppress artifacts associated with patient movement, so information can be lost. Special monitors or other devices may be required for obtaining the stored data for analysis, preventing maximum use of other equipment.

2

Wireless ECG systems often use patches or strips for positioning electrodes. The strip is fabricated with a plurality of electrodes electrically connected to the transmitter. If one electrode fails, the entire strip is replaced.

BRIEF SUMMARY

The present invention is defined by the following claims, and nothing in this section should be taken as a limitation on those claims. By way of introduction, the preferred embodiment described below includes a method and system for wireless ECG monitoring.

An electrode connector, transmitter and receiver operate with existing electrodes and ECG monitors. The electrode connector includes connectors for attaching to disposable or reusable single electrodes. The transmitter transmits the signals from the electrodes to the receiver. The receiver passes the electrode signals to the ECG monitor for processing. ECG monitors used with an electrical conductor, for example wire connections to electrodes, are connected with the receiver, avoiding the purchase of a new monitor. Any legacy ECG monitor, including different ECG monitors, connects with the receiver using the ECG monitor's leadwires. The ECG monitor operates as if directly connected to the electrodes without the problems discussed above associated with wires running from the ECG monitor to the patient.

In a first aspect of the invention, an electrode connector for ECG monitoring of a patient is provided. Material is operable to interconnect a plurality of electrodes. The material includes a plurality of electrode releasable connectors.

In a second aspect, a method for connecting electrodes for ECG monitoring is provided. A plurality of electrodes are placed. A plurality of expandable arms, one expandable arm provided for each of the plurality of electrodes, are expanded. The plurality of expandable arms are connected to the plurality of electrodes.

In a third aspect, a system for monitoring electrical signals generated by a patient is provided. A transmitter is operable to transmit electrode signals. A receiver is responsive to the transmitter to generate the electrode signals. The receiver has an output connector operable to connect with electrode wires of an ECG monitor.

In a fourth aspect, a method for monitoring electrical signals generated by a patient is provided. Signals are received from electrodes. Information representing the signals received from electrodes is transmitted. The information is received. The signals received from the electrodes are reconstructed. Existing wires from an ECG monitor are connected. The reconstructed signals are received at the ECG monitor.

In a fifth aspect, a wireless ECG monitoring system for reconstructing signals at a plurality of electrodes is provided. An electrode connector is operable to connect with the plurality of electrodes. A single transmitter is operable to connect with the electrode connector. The single transmitter is operable to transmit signals from the plurality of electrodes. A receiver is operable to reconstruct the signals from the plurality of electrodes.

In a sixth aspect, a method for wireless ECG monitoring with reconstructed signals from a plurality of electrodes is provided. The plurality of electrodes are connected with an electrode connector. Signals from the plurality of electrodes are transmitted with a single transmitter. The signals transmitted by the transmitter are received. The signals from the plurality of electrodes are reconstructed.

Further aspects and advantages of the invention are discussed below in conjunction with the preferred embodiments.

BRIEF DESCRIPTION OF SEVERAL VIEWS OF THE DRAWINGS

FIG. 1 is a block diagram of one embodiment of an ECG monitoring system.

FIGS. 2A-D are front views of various embodiments of electrode connectors and transmitters of the ECG monitoring system of FIG. 1.

FIG. 3 is a perspective view of one embodiment of an expandable arm of the electrode connectors of FIGS. 2A-D.

FIG. 4 is a front view of one embodiment of a belt used with the electrode connector of FIG. 2D.

FIG. 5 is a flow chart of one embodiment for operation of the ECG monitoring system of FIG. 1.

FIG. 6 is a perspective view of another embodiment of an ECG monitoring system.

FIG. 7 is a block diagram of one embodiment of a transmitter.

FIG. 8 is a block diagram of one embodiment of a receiver.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

A wireless ECG system uses existing electrodes and ECG monitors. The wireless ECG system wirelessly bridges between conventional electrodes on a patient and a conventional ECG monitor. The wireless ECG system is an accessory that augments the capability of conventional, or legacy, ECG monitors or systems. The wireless ECG system functions as a wireless extension cord that physically un-tethers a patient from a conventional lead-wire cable connected to a conventional ECG monitor.

The wireless ECG system includes three components: an electrode connector (e.g. sensor array), a transmitter (e.g. ECG-radio) and a receiver (e.g. base station). These components interpose between conventional electrodes worn by a patient and a conventional lead-wire cable of a conventional ECG monitor without requiring any additional changes to the conventional electrodes, the conventional lead-wire cables, or the conventional ECG monitoring systems. An electrode connector with releasable connections, such as snap terminals, and expandable arms electrically connects with existing electrodes, such as snap terminal type electrodes. A transmitter provides signals received from the electrodes to the receiver. The receiver connects to the ECG monitor via conventional lead-wires or electrode wires of the ECG monitor. Signals representing the electrode signals measured or sampled on a patient are provided to the ECG monitor. The existing ECG monitor processes the signal to output ECG data, such as ECG vector data. Consequently, physical coupling between the patient and the electrocardiograph or vital signs monitor is eliminated. This enables the patient to freely ambulate while being monitored by the ECG.

FIGS. 1 and 6 show a wireless ECG monitoring system 20. The ECG monitoring system 20 includes an electrode connector 22, a transmitter 24, a receiver 26 and an ECG monitor 28. Additional or fewer components can be used, such as providing the system 20 without the ECG monitor. Alternative components can be used, such as a strip or patch with electrodes rather than an electrode connector 22 or a printer rather than an ECG monitor 28.

FIGS. 2A-D show electrode connectors 22 of various embodiments used with an array of electrodes 30. The electrodes 30 comprise conductive material. For example, a foam disk with a conductive fabric or a fabric with a conductive metal layer is used. The electrodes 30 include a snap terminal (male, female or both) or tab for connection to a wire. Other connectors may be provided on the electrodes 30. The electrodes 30 are positioned for ECG monitoring, such as positioned for hexaxial-lead monitoring as illustrated in FIGS. 2A-C. For hexaxial-lead monitoring, the electrodes 30 are positioned in left and right arm positions and right and/or left leg positions. With these electrode positions, up to seven leads can be monitored (e.g. Lead I, II, III, aVL, aVR, aVF and chest positions). Other positions of electrodes can be used, such as associated with precordial (e.g. V1-V6) or combinations of hexaxial and precordial (e.g. "12-lead" monitoring). The electrodes 30 are attached to the patient with conductive hydrogel or other adhesives. The electrodes 30 and/or the electrode connector 22 are disposable or reusable.

The electrode connector 22 includes a plurality of expandable arms 32 and a transmitter 24. The expandable arms 32 comprise polypropylene or polyethylene fabric with an electrically conductive element such as a wire 36 and an electrode joiner 38 as shown in FIG. 3. In one embodiment, the expandable arm 32 is formed from Kapton or Mylar, manufactured by DuPont, a cloth, a fabric or another flexible material. Multiple layers of dielectric, and or electrically or magnetically conductive material can be used to shield the wire 36. Alternatively, no shielding is provided. Fabric or other material can be attached to one or both sides of the expandable arm 32, such as to provide comfort for a patient.

The expandable arm 32 of one embodiment comprises memoryless material, such as the materials discussed above. The expandable arm 32 is die cut in a serpentine pattern as shown in FIG. 3. The expandable arm 32 expands by releasing or breaking connections between portions of the serpentine pattern. When expanded, a portion or all of the expandable arm 32 is extended. Where only a portion of the expandable arm 32 is extended, another portion remains folded or unbroken. Pressure on the electrode 30 from elastic or stretchable material is avoided, providing for more stable connection of the electrode 30 to the patient. The expandable arm 32 also allows for extension as needed without extra extension and resulting loose material to be tangled or provide discomfort. In alternative embodiments, a stretchable or elastic expandable arm 32 is used. In yet other alternative embodiments, a non-expandable arm is used.

The electrical conductor or wire 36 in the expandable arm 32 preferably comprises a conductor printed on the Mylar, Kapton or other flexible dielectric material. The printed conductor is flexible, providing electrical connection between the electrode 30 and the transmitter 24 whether expanded or unexpanded. In alternative embodiments, the wire 36 comprises a thread of copper or another conductive material. In yet other embodiments, the wire comprises a coaxial cable. One or more wires 36 are provided for each electrode 30. For some expandable arms 32, one wire 36 electrically connects from one electrode 30 to the transmitter 24 or another expandable arm 32. For other expandable arms 32, a plurality of wires 36 connect from a respective plurality of electrodes 30 on the same and/or another expandable arm 32.

The electrode joiner 38 comprises a clip (e.g. alligator clip), snap terminal, or connector (male, female or both), adhesive tab or other device for electrically and physically joining the electrode 30 to the expandable arm 32. As shown

in FIG. 2D, a plurality of electrode joiners **38** can be used on one expandable arm **32**. In other embodiments, one electrode joiner **38** is provided at an end or other portion of the expandable arm **32**. If one electrode **30** malfunctions, only the electrode **30** is removed and replaced. The electrode connector **22** is kept.

The other end of the expandable arm **32** connects with other expandable arms **32** or the transmitter **24**. The plurality of expandable arms **32** are connected in any of various configurations, such as a spiral configuration shown in FIGS. 2A and 2B. The expandable arms **32** releasably or fixedly connect from a hub **40**. In the embodiment of FIG. 2A, one expandable arm **32** includes wires for all or a sub-set of the electrodes **30** to electrically communicate with the transmitter **24**. The transmitter **24** is spaced away from the hub **40**, such as being positioned on an arm band (shown), or on another location on the patient. For example, FIG. 6 shows the transmitter **24** held to the patient with an arm band **74** comprising neoprene or other fabric. In the embodiment of FIG. 2B, the transmitter **24** is positioned on the hub **40**.

The hub **40** comprises the same material as the expandable arms **40**, such as from using a continuous sheet to form the hub **40** and expandable arms **32**. In other embodiments, the hub **40** comprises the same or different material with releasable connectors for electrically and physically connecting with the expandable arms **32**. For example, the hub **40** comprises plastic or other material with plurality of conductive snap terminals for connecting with the expandable arms.

Another configuration is a "7" or "L" configuration, such as the embodiment shown in FIG. 2C. One of the electrode positions generally corresponds to the hub **40**, and expandable arms **32** expand from the hub **40**. Other alternative configuration embodiments include "C" or "U" shapes with multiple hubs.

Yet another configuration is shown in FIG. 2D. A belt **42** connects with a plurality of expandable arms **32**. The belt **42** comprises neoprene, non-woven polypropylene or polyethylene fabric or other materials. One or more pockets or connectors for the transmitter **24**, other electrical components, batteries, displays, or other devices are provided on the belt **42**. In one embodiment shown in FIG. 4, the belt **42** is formed to fasten or stretch around a waist of the patient, but arm, neck, chest or leg belts can be used. One or more of the expandable arms **32** releasably connects with the belt **40**. In one embodiment, the belt **40** includes separate connectors **44** for each electrode position. In other embodiments, one or more of the connectors **44** on the belt **40** include separate electrical contacts for electrically connecting with multiple wires **36** and associated electrodes **30** on one expandable arm **32**. The connectors **44** are provided on the outer surface of the belt **42**, but can be provided in pockets. The transmitter **24** is positioned on the belt **42** or elsewhere on the patient.

As shown in FIG. 2D, one or more of the expandable arms **32** may include one or more connectors **44** for connecting with other expandable arms **32**, forming a hub **40**. For example, an electrically conductive snap terminal or terminals connect the expandable arms. Other connectors, such as male and female housings with clips and wires associated with connecting multiple separate wires between the expandable arms, can be used.

The configuration is associated with the desired ECG monitoring. FIGS. 2A-C illustrate hexaxial positions for the electrodes **30**, such as associated with continuous monitoring. Electrodes **30** are positioned at hexaxial positions associated with left arm, right arm, left leg and/or right leg.

Many ECG systems use three electrode positions, but some use four or more. FIGS. 2A and 2C show three electrode positions. FIG. 2B shows four electrode positions. More or fewer electrode positions, such as three to five positions, may be provided with additional electrode joiners **38** and/or expandable arms **32**.

FIG. 2D shows both hexaxial and precordial positions for the electrodes **30**, such as associated with "12 lead" ECG monitoring. Two or more expandable arms **32** connect with electrodes **30** in hexaxial positions. One or more expandable arms **32**, such as expandable arm **46**, connect with electrodes **30** in precordial positions. In this embodiment, the precordial expandable arm **46** connects with another of the expandable arms **32** used for hexaxial positions. The resulting hub **40** is associated with one of the precordial electrode positions. In alternative embodiments, the hub **40** is spaced away from any electrode **30**. In yet other alternative embodiments, the precordial expandable arm or arms **46** separately connect with the belt **42**. For example, separate hexaxial and precordial electrode connectors **76** and **78** are provided as illustrated in FIG. 6. The precordial electrode connector **78** connects with the hexaxial electrode connector **76** or the transmitter **24**.

The hubs **40** and expandable arms **32** may include connectors **44** for adding additional expandable arms **32** or electrodes **30**. For example, two or more expandable arms **32** are positioned for hexaxial-lead monitoring as shown in FIG. 2D without the precordial expandable arm **46**. When precordial-lead monitoring is desired, electrodes **30** are positioned along six precordial positions, and the expandable arm **46** is expanded and connected with the precordial electrodes **30**. The expandable arm **46** is also connected to the belt **42** or other expandable arm **32**. Alternatively, different electrode connectors **22** are used for different ECG systems or numbers of electrodes. Since the expandable arms **32** are flexible and expandable, the same electrode connector **22** is used for various electrode positions as represented by the bold arrows in FIGS. 2A-D.

The transmitter **24** receives the signals from the electrodes **30**. The transmitter **24** comprises a wireless transmitter or transceiver, such as a radio, ultrasound, infrared or other transmitter. For example, a transceiver operable according to Bluetooth specifications (i.e. a Bluetooth transceiver) is used. In one embodiment, the transmitter **24** comprises an application specific integrated circuit, a processor or other circuit.

FIG. 7 shows one embodiment of the transmitter **24**. The transmitter **24** includes a plurality of electrode signal channels **80**, a multiplexer **82**, an analog-to-digital converter (ADC) **84**, a controller **86**, a radio **88** and a battery **90**. Additional, fewer or different components can be used. The battery **90** comprises a replaceable or rechargeable lithium battery connected to provide power to the various components of the transmitter **24**.

In one embodiment, nine electrode signal channels **80** corresponding to the typical nine electrodes used for hexaxial-lead and precordial-lead monitoring are provided. Fewer or additional electrode signal channels **80** can be provided. The electrode signal channels **80** each comprise a connector **92**, a filter **94**, an amplifier **96**, a Nyquist filter **98** and a track and hold circuit **100**. The connector **92** comprises snaps, plugs or other electrical connectors for connecting with the wires **36**. The filter **94** comprises a low pass filter, such as for removing electromagnetic interference signals. The amplifier **96** amplifies the signals from the electrodes **30**. The Nyquist filter **98** comprises a low pass filter for removing high frequency content of the amplified signals to

avoid sampling error. The track and hold circuit **100** enables the system to sample all 9 channels of signals at a same or relative times so that there is no differential error created when these signals are combined later in a legacy ECG monitor.

The multiplexer **82** sequentially selects signals from the electrode signal channels **80** using time division multiplexing, but other combination functions can be used. The ADC **84** converts the combined analog signals to digital signals for transmission. The controller **86** controls operation of the various components and may further process the digital signals, such as diagnosing operation, controlling any user interface (e.g. input and/or output devices), and detecting connection to electrodes. Preferably the controller comprises a digital signal processor (DSP) that decimates the digitized signals so as to lessen the bandwidth required to transmit the signals. The radio **88** modulates the digital signals with a carrier signal for transmission. In one embodiment, the radio **88** includes a demodulator for receiving information. The controller **86** processes the received information.

In one embodiment, the transmitter **24** is operable to minimize introducing undesired noise or signals. For example, components are matched such that later application to a differential amplifier in a legacy ECG monitor for determining a heart vector is accurate. In one embodiment, the ECG vectors are not formed by the ECG system **20**, but rather by the legacy ECG monitor. Because the ECG system **20** is essentially "in-series" with the legacy ECG monitor, any error may produce undesirable results. One potential source of error is differential error. This differential error can be observed on the legacy ECG monitor when the ECG monitor forms the ECG lead signals by combining the individual electrode signals in the ECG monitor input stage. This input stage comprises a difference, or differential, amplifier to eliminate common mode interference from the signals produced at the electrodes **30**. If there is any difference in how each of the electrode signals are processed, when the legacy ECG's differential amplifier forms the ECG lead signals or ECG vectors an artifact will be present. For example, in the transmitter **24** if there is a difference in the gain of the amplifiers, a difference in the phase shift associated with the anti-aliasing (Nyquist) filters, a difference in how the respective track and hold circuits treat the electrode signals, this differential error creates an artifact on the legacy ECG monitor. One important technique to minimize this potential source of differential error, is to choose a Nyquist filter **98** cutoff frequency that is very high. This is because each individual filter will have differing group delay performance, and to mitigate that difference the frequency that this group delay will affect is much higher than the frequency of the ECG signals, which are about 0.05 Hz to 150 Hz. By choosing a high cutoff frequency for the Nyquist filters **98**, any mismatch in the Nyquist filter **98** components will not affect accuracy of the individual electrode ECG signals. For example picking a filter cutoff frequency of 1,200 Hz mitigates this source of error. With this approach, the individual electrode ECG signals are oversampled at about 3,000 Hz in order to not introduce aliasing. Of course higher filter cutoff frequencies and correspondingly higher sampling rates may further reduce error. Lower cutoff frequencies and/or sampling rate may be used.

Because the electrode signals are now sampled at such a high rate, these signals may be decimated to minimize the required transmission bandwidth. For example the digital samples are decimated by a factor of 8 in the controller **86**. Greater or lesser rates of decimation can be used, such as decimation as a function of the bandwidth available for

transmission, the number of electrode signals to be represented, and the Nyquist sampling rate. In alternative embodiments, the digital data is compressed, the electrode signals are not oversampled, or no decimation is provided.

The selected signals are transmitted as radio or other signals modulated with a carrier signal. Various formats for transmission can be used, such as Bluetooth, TCP/IP, or other formats. The controller **86** controls the acquisition and transmission of the electrode signals. The transmitted signals comprise data representing the signals received from the electrodes **30**. In alternative embodiments, the controller **86** may also processes the signals prior to transmission, so the transmitted signals comprise ECG vector data. In one embodiment, the transmitter **24** also receives control information from the receiver **26**, such as instructions to resend signals.

The transmitter **24** is positioned near the patient. In the embodiment shown in FIGS. 2A and 2C, the transmitter **24** is positioned on the hub **40** or an expandable arm **32**. In the embodiment shown in FIG. 2B, the transmitter **24** is positioned on an arm band, but leg, chest or other bands can be used. In the embodiment of FIG. 2D, the transmitter **24** is positioned on the belt. Either a pocket or a surface mount is provided for the transmitter **24**. In alternative embodiments, the transmitter **24** is positioned in a pocket of clothing or elsewhere on the patient.

In one embodiment, the transmitter **24** is removable. For example, clips, screws, bolts, latches or other devices releasably hold the transmitter **24** in contact with the electrode connector **22**. Electrical contact is provided by connectors operable to withstand electrical energy produced by a defibrillator. These connectors may also provide the physical connection. The transmitter **24** is removed for recharging the battery or a plug is provided on the electrode connector **22** or the transmitter **24** for recharging the battery without removal. The battery or the transmitter **24**, like the electrode connector **22**, can be used for multiple days or multiple times and is separately disposable to avoid costly replacement of the entire system **20**.

Referring to FIGS. 1 and 6, the receiver **26** receives the transmitted signals. The receiver **26** comprises a radio, infrared, ultrasound or other receiver. An application specific integrated circuit, digital signal processor or other circuit for receiving signals from the transmitter **24**, decoding the received signals, and generating representative electrode signals is used. In one embodiment, the receiver comprises a transceiver for two-way communication with the transmitter **24**. For example, a transceiver operable pursuant to the Bluetooth specification is provided.

FIG. 8 shows one embodiment of the receiver **26**. The receiver **26** includes a radio **110**, a controller **112**, a digital-to-analog converter (DAC) **114**, a demultiplexer **116**, a plurality of electrode signal channels **118** and a battery or power supply **120**. Additional, fewer or different components can be used. Preferably, the power supply **120** comprises a replaceable or rechargeable battery or other power source connected to provide power to the various components of the receiver **26**.

The radio **110** demodulates the received signals for identifying digital data representing the combined electrode signals. In one embodiment, the radio **110** also includes a modulator for transmitting control information. The controller **112** controls operation of the various components and may further process the signals from the radio **110**, such as interpolating data, converting the signals to digital information, generating control signals for the transmitter **24**, operating any user interface, operating any user output or input

devices, and diagnosing operation of the system 20. Preferably, the controller 112 in the receiver 26 interpolates the electrode signals to return the effective sample rate to about 3 kHz or another frequency. This enables the reconstruction filters to have a cutoff frequency many times the bandwidth of the electrode signals, thus minimizing any differences in group delay at the frequencies of interest, i.e. less than 150 Hz. The DAC 114 converts the digital signals to analog signals. The demultiplexer 116 separates the individual regenerated electrode signals onto the separate electrode signal channels 118.

In one embodiment, nine electrode signal channels 118 corresponding to the typical nine electrodes used for hexaxial-lead and precordial-lead monitoring. Fewer or additional electrode signal channels 118 can be provided. The electrode signal channels 118 each comprise a sample and hold circuit 120, a filter 122, an attenuator 124 and a connector 126. The sample and hold circuit 120 is controlled by the controller 112 so that the converted electrode signals appear simultaneously on each electrode signal channel 118. Differential error may be mitigated. Other embodiments may include individual DAC's that provide the signals substantially simultaneously. The filter 122 comprises a low pass reconstruction filter for removing high frequency signals associated with the DAC conversion process. The attenuator 124 comprises an amplifier for decreasing the amplitude to a level associated with signals at the electrodes 30, that were earlier amplified in the amplifiers 96 of the transmitter 24. This results in a unity system gain so as not to introduce error between the electrodes and the legacy ECG monitor. Other gains may be used. The connector 126 comprises posts, snaps, plugs, tabs or other electrical connectors for connecting with the lead wire set 70.

The controller 112 sets the demodulation frequency in response to input from the user input device or memory, or the demodulation frequency is fixed. In one embodiment, the user input comprises buttons associated with manual frequency control, with preprogrammed channels, with numbers or characters, with possible transmitters 24 or other input devices for selecting a demodulation frequency. The receiver 26 electrically connects to the ECG monitor 28.

FIG. 6 shows one embodiment of the wireless ECG system 20 where the wires 70 from a standard ECG monitor 28 attach to the electrically conductive posts 72 or other connectors on the receiver 26. The wires 70 comprise a lead-wire set, cable or electrode connectors from or for the ECG monitor 28. The posts 72 are labeled as electrodes 30, and the wires 70 are connected with corresponding outputs on the receiver 26. The receiver 26 outputs signals as if from the corresponding electrodes 30 for processing by the ECG monitor 28. In alternative embodiments, the receiver 26 includes wires for connecting with the ECG monitor 28.

In one embodiment, the receiver 26 physically connects to the ECG monitor 28. For example, latches, clips or straps on the receiver 26 connect the receiver 26 to the ECG monitor 28. In alternative embodiments, the receiver 26 connects to an equipment pole or wall or is free standing. The receiver 26 may be releasably attached. When a patient is moved, the receiver 26 may be detached and moved adjacent a different ECG monitor. Alternatively, different receivers 26 operate with the same transmitter 24, so another receiver 26 is programmed to receive signals from the transmitter 24 on the patient.

The ECG monitor 28 comprises one or more of a bedside monitor, a transport monitor or a discrete (i.e. diagnostic) monitor. Bedside and transport monitors are used for continuous monitoring, such as associated with hexaxial-lead

monitoring. A discrete monitor typically is used periodically for analysis, such as associated with "12-lead" monitoring or obtaining multiple vectors associated with precordial and/or hexaxial leads. The ECG monitor 28 processes the electrode signals as if the signals were received directly from the electrodes 30. Neither of the transmitter 24 or receiver 26 includes differential amplifiers for determining a heart vector associated with two electrodes.

Some ECG monitors 28 test for failure or malfunction of electrodes 30. For example, a signal is output on the lead wire to the electrode 30 or a direct current level associated with the signal from the electrode 30 is monitored. To continue to provide this functionality, the wireless ECG system 20 tests for electrode failure or malfunction and indicates the results to the ECG monitor 28. For example, the transmitter 24 performs the same or similar tests as the ECG monitor 28. In other embodiments, the transmitter 24 or receiver 26 determines whether the ECG signal is within an expected range. For example, the controller 112 (FIG. 8) compares the digital electrode signals, such as after interpolation, to maximum and minimum thresholds. If either threshold is exceeded by a particular number of samples or for a particular time, a lead-off or faulty electrode 30 is indicated. When one or more samples are subsequently within hysteresis limits of the thresholds, then an error is no longer indicated. When a lead-off condition is indicated, the receiver 26 opens an analog switch or, alternatively does not generate a signal for the output corresponding to the malfunctioning or failed electrode 30. As a result, the ECG monitor 28 indicates a failure of the electrode 30. If the transmitter 24 and receiver 26 are out of radio communication range, a lead-off condition is presented to the ECG monitor 28.

The ECG monitoring system 20 is used for continuous hexaxial-lead or occasional precordial-lead or both hexaxial-lead and precordial-lead monitoring. FIG. 5 shows the acts representing use of the system 20

In act 50, the electrodes 30 are positioned on the patient. For example, electrodes 30 are positioned in hexaxial positions, precordial positions or combinations thereof.

In act 52, the electrode connector 22 and transmitter are positioned. The expandable arms 32 are expanded, such as expanding a portion or all of the expandable arms 32. Another portion of the expandable arms 32 may remain folded or unexpanded. The expandable arms 32 are expanded to reach one or more electrodes.

In act 54, the electrode connector 22 is connected with the electrodes 30. For example, the expandable arms 32 are releasably connected with one or more electrodes 30, such as snapping or clipping to the electrodes 30. Expandable arms 32 may also be connected with other expandable arms 32, hubs 40, the transmitter 24, and/or the belt 42. In an alternative embodiment, the electrodes 30 are connected with the electrode connector 22 prior to positioning the electrodes 30 and expanding the expandable arms 32.

In act 56, the transmitter 24 is operated or turned-on. In one embodiment, a switch on the transmitter 24 activates the transmitter. In alternative embodiments, connection to one or more of the wires 36, expandable arms 32, electrode connector 22 and/or electrodes 30 activates the transmitter 24. In response, the transmitter 24 radiates a signal representing the electrode signals.

In act 58, the receiver 26 is programmed. A code corresponding to the transmitter 24 is entered, or a channel (i.e. frequency) is selected. In an alternative embodiment, the receiver 26 searches a plurality of frequencies for an appropriate signal, such as a signal in an expected format or with

11

a particular code. If more than one signal is identified, an output may be provided for user selection of the appropriate signal. A visual or audible output indicating reception of a signal may be provided.

In act 60, wires or electrode connectors from the ECG monitor 28 are connected to the receiver 26. In alternative embodiments, act 60 occurs before any of acts 50, 52, 54, 56 or 58.

In act 62, the ECG device, such as a monitor, printer or memory, is activated. Analog or digital signals corresponding to signals at the electrodes 30 are received by the ECG device from the receiver 26. The ECG device processes the signals to generate ECG data, such as one or more heart vectors.

In one embodiment, a light emitting diode, a light pipe or multiple light emitting diodes, or other output device is provided on the transmitter 24 and/or one or more of the expandable arms 32. The output device indicates electrical operation of the transmitter or conductance of signals by the wire 36. Different output devices may represent improper operation. In one embodiment, extending the expandable arm 32 activates operation of the output device or devices.

The wireless ECG system 20 provides for fewer artifacts due to wire movement, allows the patient to wear clothing without interfering with wires, and provides less psychological intimidation of the patient due to wire connections to a machine. The electrodes 30 are less likely to disconnect because of lower mass or force due to wires connected to the ECG monitor 28. The wireless ECG system 20 is usable with many different ECG monitors 28 and electrodes 30. Faster setup when a patient is transferred and connected to a different ECG monitor 28 is provided since the same electrodes 30 already positioned on the patient can be used. Since the electrodes 30 are not repositioned due to a transfer, the ECG monitor output is more comparable to the output of previous ECG monitors. If an electrode 30 fails because of patient movement or perspiration, the electrode can be replaced without replacing the electrode connector 22 or other electrodes 30.

While the invention has been described above by reference to various embodiments, it will be understood that many changes and modifications can be made without departing from the scope of the invention. For example, the transmitter and receiver may each comprise transceivers for two-way communication and control. Various aspects can be used with or without other aspects, such as using the electrode connector 22 with a transmitter that processes the electrode signals into ECG vector data rather than transmitted signals representing the electrode signals. Another example is transmitting the electrode signals but using a different electrode connector, strip, patch or mere wires. Other biomedical systems, such as temperature or blood pressure, can be additionally or alternatively monitored using the systems and methods discussed above.

It is therefore intended that the foregoing detailed description be understood as an illustration of the presently preferred embodiments of the invention, and not as a definition of the invention. It is only the following claims, including all equivalents that are intended to define the scope of this invention.

What is claimed:

1. An electrode connector for physiological monitoring of a patient, the connector comprising:
material operable to interconnect a plurality of electrodes;
and
a plurality of electrode connectors provided on the material, the connectors being releasable and rejoinable;

12

wherein the material comprises a plurality of arms, each of the plurality of arms corresponding to respective ones of the plurality of electrode connectors and wherein the plurality of arms are configured relative to each other to aid in positioning the plurality of electrode connectors on the patient.

2. The electrode connector of claim 1 wherein the electrode connectors are adapted to withstand the electrical energy produced by a defibrillator used on the patient.

3. The electrode connector of claim 1 wherein the plurality of arms comprise at least four arms associated with hexaxial electrodes, the at least four arms connected at angles to each other, the angles corresponding to relative hexaxial positions on the patient.

4. The electrode connector of claim 1 wherein each of the plurality of arms include an electrical conductor.

5. The electrode connector of claim 4 wherein each of the electrical conductors electrically connects with the respective electrode connector.

6. The electrode connector of claim 1 wherein at least a first of the plurality of arms corresponds to a hexaxial electrode position and at least a second of the plurality of arms corresponds to a precordial electrode position, the first and second arms being connected such that each of the first and second arms is disposed towards the corresponding electrode positions.

7. The electrode connector of claim 6 wherein the second arm connects to the first arm.

8. The electrode connector of claim 1 further comprising a belt, and wherein at least one of the plurality of arms is expandable, the at least one expandable arms connecting with the belt.

9. The electrode connector of claim 8 wherein a first arm comprises a hexaxial electrode arm connected with the belt and a second arm comprises a hexaxial and precordial electrode arm connected with the belt, the first and second arms connected with the belt such that the first arm extending from the belt to a first hexaxial electrode position avoids intersection with the second arm extending from the belt to a second hexaxial and a first precordial electrode positions.

10. The electrode connector of claim 1 wherein each of the plurality of arms extends from a central position to corresponding electrode positions without intersection, each of the plurality of arms being extendable and comprising a memoryless material.

11. The electrode connector of claim 1 further comprising a releasable arm connector on at least one of the plurality of arms, the releasable arm connector spaced away from at least one of the plurality of electrode connectors associated with the one arm.

12. A method for connecting electrodes for ECG monitoring, the method comprising the acts of:

- (a) placing a plurality of electrodes onto a patient in preselected positions;
- (b) positioning a plurality of arms, one arm provided for each of the plurality of electrodes, the plurality of arms connected or connectable relative to each other to align with the preselected position of each of the plurality of electrodes;
- (c) connecting the plurality of arms to the plurality of electrodes, respectively; and
- (d) connecting a precordial-lead arm with a hexaxial-lead expandable arm.

13. The method of claim 12 wherein (a) comprises placing the plurality of electrodes for hexaxial-lead monitoring, the preselected positions being hexaxial electrode positions.

13

14. The method of claim **12** wherein (a) comprises placing the plurality of electrodes for precordial-lead monitoring, the preselected positions being precordial electrode positions.

15. The method of claim **12** wherein (a) comprises placing the plurality of electrodes for both hexaxial-lead and precordial-lead monitoring, the preselected positions being hexaxial and precordial positions.

16. The method of claim **12** further comprising:

(d) transmitting signals from the plurality of electrodes with a radio.

14

17. The method of claim **12** wherein (c) comprises electrically connecting the plurality of electrodes to the plurality of arms with a snap terminal.

18. The method of claim **12** wherein (b) comprises positioning the plurality of arms at different angles from a central hub.

19. The method of claim **12** further comprising:

(d) connecting at least one of the plurality of arms to a belt.

* * * * *

专利名称(译)	无线心电图仪系统和方法		
公开(公告)号	US7272428	公开(公告)日	2007-09-18
申请号	US10/439574	申请日	2003-05-16
[标]申请(专利权)人(译)	摩托罗拉公司		
申请(专利权)人(译)	MOTOROLA , INC.		
当前申请(专利权)人(译)	LIFESYNC CORPORATION		
[标]发明人	HOPMAN NICHOLAS C WILLIAMS DANIEL L LODATO FRANCO		
发明人	HOPMAN, NICHOLAS C. WILLIAMS, DANIEL L. LODATO, FRANCO		
IPC分类号	A61N1/04 A61B5/04 A61B5/00 A61B5/0408 A61B5/044 A61B5/0478		
CPC分类号	A61B5/0006 A61B5/0408 A61B5/04085 A61B5/6831		
代理机构(译)	BRINKS霍费尔GILSON & LIONE		
优先权	60/219082 2000-07-18 US		
其他公开文献	US20030199777A1		
外部链接	Espacenet USPTO		

摘要(译)

提供了一种用于无线ECG监测的方法和系统。电极连接器，发射器和接收器与现有电极和ECG监视器一起操作。电极连接器包括用于连接到一次性或可重复使用的单个电极的连接器。发射器将信号从电极传输到接收器。接收器将电极信号传递给ECG监视器进行处理。与电导体一起使用的ECG监视器，例如与电极的导线连接，与接收器连接，避免购买新的监视器。任何传统的ECG监护仪，包括不同的ECG监护仪，都使用ECG监护仪的引线与接收器连接。ECG监视器如同直接连接到电极一样操作，而没有上面讨论的与从ECG监视器到患者的导线相关的问题。

