



US010349857B2

(12) **United States Patent**  
**Grunwald**

(10) **Patent No.: US 10,349,857 B2**  
(45) **Date of Patent: Jul. 16, 2019**

(54) **DEVICES AND METHODS FOR ENDOVASCULAR ELECTROGRAPHY**

(56) **References Cited**

U.S. PATENT DOCUMENTS

(71) Applicant: **Bard Access Systems, Inc.**, Salt Lake City, UT (US)

3,795,855 A 3/1974 Browning  
3,817,241 A 6/1974 Grausz

(Continued)

(72) Inventor: **Sorin Grunwald**, Bucharest (RO)

FOREIGN PATENT DOCUMENTS

(73) Assignee: **Bard Access Systems, Inc.**, Salt Lake City, UT (US)

CN 2031655 U 2/1989  
CN 1913833 A 2/2007

(Continued)

(\* ) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

OTHER PUBLICATIONS

(21) Appl. No.: **15/266,977**

AU 2012278809 filed Nov. 12, 2013 Notice of Acceptance dated Sep. 13, 2016.

(22) Filed: **Sep. 15, 2016**

(Continued)

(65) **Prior Publication Data**

US 2017/0000367 A1 Jan. 5, 2017

**Related U.S. Application Data**

*Primary Examiner* — Tammie K Marlen

(74) *Attorney, Agent, or Firm* — Rutan & Tucker, LLP

(60) Division of application No. 12/854,083, filed on Aug. 10, 2010, now Pat. No. 9,445,734, which is a (Continued)

(57) **ABSTRACT**

A method for positioning an endovascular device in or near the heart using electrocardiogram (ECG) signals. The method includes receiving an endovascular ECG signal including a plurality of waveforms, processing the endovascular ECG signal to calculate a P-wave amplitude and a spectral power for each predetermined time period, determining a maximum P-wave amplitude and an associated maximum spectral power, associating the maximum P-wave amplitude and the maximum spectral power with a predetermined location in or near the heart, calculating a location based on a ratio of the P-wave amplitude to the maximum P-wave amplitude and a ratio of the spectral power to the maximum spectral power, and displaying the location to a user.

(51) **Int. Cl.**  
**A61N 1/05** (2006.01)  
**A61B 5/0452** (2006.01)

(Continued)


(52) **U.S. Cl.**  
CPC ..... **A61B 5/0452** (2013.01); **A61B 5/042** (2013.01); **A61B 5/04017** (2013.01); **A61B 5/06** (2013.01);

(Continued)

(58) **Field of Classification Search**  
CPC ... A61B 5/0006; A61B 5/04017; A61B 5/042; A61B 5/0452; A61B 5/06; A61B 5/061; A61B 5/065; A61B 5/066

See application file for complete search history.

**16 Claims, 17 Drawing Sheets**



<b>Related U.S. Application Data</b>					
	continuation-in-part of application No. 12/815,331, filed on Jun. 14, 2010, now Pat. No. 9,339,206.		5,769,786 A	6/1998	Wiegel
			5,820,560 A	10/1998	Sinderby et al.
			5,830,145 A	11/1998	Tenhoff
			5,833,622 A	11/1998	Meathrel et al.
			5,840,030 A	11/1998	Ferek-Petric et al.
			5,840,031 A	11/1998	Crowley
			5,846,198 A	12/1998	Killmann
			5,899,860 A	5/1999	Pfeiffer et al.
			5,908,385 A	6/1999	Chechelski et al.
			5,931,863 A	8/1999	Griffin, III et al.
			5,935,160 A	8/1999	Auricchio et al.
			5,944,022 A	8/1999	Nardella et al.
			5,951,472 A	9/1999	Van Vaals et al.
			5,967,978 A	10/1999	Littmann et al.
			5,983,126 A	11/1999	Wittkamp
			6,006,123 A	12/1999	Nguyen et al.
			6,014,473 A	1/2000	Hossack et al.
			6,019,725 A	2/2000	Vesely et al.
			6,052,618 A	4/2000	Dahlke et al.
			6,058,323 A	5/2000	Lemelson
			6,063,032 A	5/2000	Grunwald
			6,102,862 A	8/2000	Grunwald et al.
			6,107,699 A	8/2000	Swanson
			6,115,624 A	9/2000	Lewis et al.
			6,190,370 B1	2/2001	Tsui
			6,197,001 B1	3/2001	Wilson et al.
			6,212,426 B1	4/2001	Swanson
			6,217,517 B1	4/2001	Grunwald
			6,230,042 B1	5/2001	Slettenmark
			6,231,518 B1	5/2001	Grabek et al.
			6,236,883 B1	5/2001	Ciaccio et al.
			6,246,898 B1	6/2001	Vesely et al.
			6,249,234 B1	6/2001	Ely et al.
			6,254,543 B1	7/2001	Grunwald et al.
			6,259,938 B1	7/2001	Zarychta et al.
			6,266,551 B1	7/2001	Osadchy et al.
			6,266,552 B1	7/2001	Slettenmark
			6,266,563 B1	7/2001	KenKnight et al.
			6,275,724 B1	8/2001	Dickinson et al.
			6,287,259 B1	9/2001	Grunwald
			6,324,416 B1	11/2001	Seibert
			6,350,160 B1	2/2002	Feuersanger et al.
			6,354,999 B1	3/2002	Dgany et al.
			6,360,123 B1	3/2002	Kimchi et al.
			6,379,303 B1	4/2002	Seitz et al.
			6,385,476 B1	5/2002	Osadchy et al.
			6,398,738 B1	6/2002	Millar
			6,406,422 B1	6/2002	Landesberg
			6,471,656 B1	10/2002	Shalman et al.
			6,494,832 B1	12/2002	Feldman et al.
			6,508,802 B1	1/2003	Rosengart et al.
			6,511,413 B2	1/2003	Landesberg
			6,514,202 B2	2/2003	Grunwald
			6,514,249 B1	2/2003	Maguire et al.
			6,522,906 B1	2/2003	Salisbury, Jr. et al.
			6,538,634 B1	3/2003	Chui et al.
			6,540,699 B1	4/2003	Smith et al.
			6,546,270 B1	4/2003	Goldin et al.
			6,569,160 B1	5/2003	Goldin et al.
			6,569,862 B1	5/2003	Marban
			6,577,896 B2	6/2003	Werner et al.
			6,584,343 B1	6/2003	Ransbury et al.
			6,589,181 B2	7/2003	Grunwald et al.
			6,649,914 B1	11/2003	Moorman et al.
			6,690,968 B2	2/2004	Mejia
			6,709,390 B1	3/2004	Marie Pop
			6,719,756 B1	4/2004	Muntermann
			6,733,458 B1	5/2004	Steins et al.
			6,763,261 B2	7/2004	Casscells, III et al.
			6,816,266 B2	11/2004	Varshneya et al.
			6,941,166 B2	9/2005	MacAdam et al.
			6,945,938 B2	9/2005	Grunwald
			6,950,689 B1	9/2005	Willis et al.
			6,959,214 B2	10/2005	Pape et al.
			7,015,393 B2	3/2006	Weiner et al.
			7,096,059 B2	8/2006	Geddes et al.
			7,141,019 B2	11/2006	Pearlman
			7,184,820 B2	2/2007	Jersey-Willuhn et al.
			7,190,819 B2	3/2007	Viswanathan
(60)	Provisional application No. 61/213,474, filed on Jun. 12, 2009, provisional application No. 61/272,025, filed on Aug. 10, 2009.				
(51)	<b>Int. Cl.</b>				
	<i>A61B 5/04</i> (2006.01)				
	<i>A61B 5/042</i> (2006.01)				
	<i>A61B 5/06</i> (2006.01)				
	<i>A61M 25/00</i> (2006.01)				
	<i>A61M 25/01</i> (2006.01)				
	<i>A61B 34/20</i> (2016.01)				
	<i>A61B 5/00</i> (2006.01)				
	<i>A61M 25/09</i> (2006.01)				
	<i>A61M 39/10</i> (2006.01)				
(52)	<b>U.S. Cl.</b>				
	CPC ..... <i>A61B 5/065</i> (2013.01); <i>A61B 5/742</i> (2013.01); <i>A61B 34/20</i> (2016.02); <i>A61M 25/0026</i> (2013.01); <i>A61M 25/0097</i> (2013.01); <i>A61M 25/0102</i> (2013.01); <i>A61M 25/0147</i> (2013.01); <i>A61N 1/056</i> (2013.01); <i>A61B 5/7203</i> (2013.01); <i>A61B 5/726</i> (2013.01); <i>A61M 25/0194</i> (2013.01); <i>A61M 2025/09116</i> (2013.01); <i>A61M 2039/1022</i> (2013.01)				
(56)	<b>References Cited</b>				
	<b>U.S. PATENT DOCUMENTS</b>				
	3,902,501 A	9/1975	Citron et al.		
	3,995,623 A	12/1976	Blake et al.		
	4,365,639 A	12/1982	Goldreyer		
	4,565,201 A	1/1986	Lass		
	4,577,634 A	3/1986	Gessman		
	4,587,975 A	5/1986	Salo et al.		
	4,595,012 A	6/1986	Webler et al.		
	4,644,960 A	2/1987	Johans		
	4,681,117 A	7/1987	Brodman et al.		
	4,793,361 A	12/1988	DuFault		
	4,809,681 A	3/1989	Kantrowitz et al.		
	4,821,731 A	4/1989	Martinelli et al.		
	4,836,214 A	6/1989	Sramek		
	4,852,580 A	8/1989	Wood		
	4,873,987 A	10/1989	Djordjevich et al.		
	4,905,698 A	3/1990	Strohl, Jr. et al.		
	4,957,110 A	9/1990	Vogel et al.		
	5,029,585 A	7/1991	Lieber et al.		
	5,058,583 A	10/1991	Geddes et al.		
	5,058,595 A	10/1991	Kern		
	5,092,341 A	3/1992	Kelen		
	5,109,862 A	5/1992	Kelen et al.		
	5,121,750 A	6/1992	Katims		
	5,146,151 A	9/1992	Korn		
	5,184,627 A	2/1993	de Toledo		
	5,220,924 A	6/1993	Frazin		
	5,243,995 A	9/1993	Maier		
	5,269,306 A	12/1993	Warnking et al.		
	5,330,496 A	7/1994	Alferness		
	5,385,146 A	1/1995	Goldreyer		
	5,398,683 A	3/1995	Edwards et al.		
	5,417,701 A	5/1995	Holmes		
	5,450,846 A	9/1995	Goldreyer		
	5,500,011 A	3/1996	Desai		
	5,517,989 A	5/1996	Frisbie et al.		
	5,540,681 A	7/1996	Strul et al.		
	5,570,671 A	11/1996	Hickey		
	5,640,967 A	6/1997	Fine et al.		
	5,718,241 A	2/1998	Ben-Haim et al.		
	5,727,550 A	3/1998	Montecalvo		
	5,730,129 A	3/1998	Darrow et al.		

(56)

## References Cited

## U.S. PATENT DOCUMENTS

7,207,941	B2	4/2007	Sharf	9,554,716	B2	1/2017	Burnside et al.
7,231,243	B2	6/2007	Tearney et al.	9,636,031	B2	5/2017	Cox
7,261,691	B1	8/2007	Asomani	9,642,986	B2	5/2017	Beasley
7,299,085	B2	11/2007	Bergelson et al.	9,649,048	B2	5/2017	Cox et al.
7,308,296	B2	12/2007	Lys et al.	9,681,823	B2	6/2017	Messerly et al.
7,327,872	B2	2/2008	Vaillant et al.	9,833,169	B2	12/2017	Rothenberg
7,331,462	B2	2/2008	Steppe	9,839,372	B2	12/2017	Bukhman et al.
7,366,563	B2	4/2008	Kleen et al.	9,901,714	B2	2/2018	Lemon et al.
7,479,141	B2	1/2009	Kleen et al.	9,907,513	B2	3/2018	Silverstein
7,529,584	B2	5/2009	Laske et al.	9,999,371	B2	6/2018	Messerly et al.
7,546,158	B2	6/2009	Allison et al.	10,004,875	B2	6/2018	Bown et al.
7,613,478	B2	11/2009	Jabri et al.	10,046,139	B2	8/2018	Powers et al.
7,640,053	B2	12/2009	Verin	10,105,121	B2	10/2018	Burnside et al.
7,666,191	B2	2/2010	Orban, III et al.	10,165,962	B2	1/2019	Messerly et al.
7,699,829	B2	4/2010	Harris et al.	10,231,643	B2	3/2019	Grunwald
7,729,743	B2	6/2010	Sabczynski et al.	10,231,753	B2	3/2019	Burnside et al.
7,774,051	B2	8/2010	Voth	10,238,418	B2	3/2019	Cox et al.
7,774,055	B1	8/2010	Min	10,271,762	B2	4/2019	Grunwald
7,822,464	B2	10/2010	Maschke et al.	2001/0014774	A1	8/2001	Grunwald
7,831,294	B2	11/2010	Viswanathan	2001/0027332	A1	10/2001	Grunwald et al.
7,840,252	B2	11/2010	Strommer et al.	2002/0173721	A1	11/2002	Grunwald et al.
7,846,157	B2	12/2010	Kozel	2002/0193756	A1	12/2002	Prindle
7,869,854	B2	1/2011	Shachar et al.	2003/0009132	A1	1/2003	Schwartz et al.
7,869,865	B2	1/2011	Govari et al.	2003/0013959	A1	1/2003	Grunwald et al.
7,873,402	B2	1/2011	Shachar	2003/0018251	A1	1/2003	Solomon
7,947,040	B2	5/2011	Davies et al.	2003/0036696	A1	2/2003	Willis et al.
7,969,142	B2	6/2011	Krueger et al.	2003/0083698	A1	5/2003	Whitehurst et al.
8,055,327	B2	11/2011	Strommer et al.	2003/0092993	A1	5/2003	Grunwald
8,057,394	B2	11/2011	Dala-Krishna	2003/0149368	A1	8/2003	Hennemann et al.
8,082,025	B2	12/2011	Amitai et al.	2003/0162414	A1	8/2003	Schulz et al.
8,090,430	B2	1/2012	Makower et al.	2003/0220578	A1	11/2003	Ho et al.
8,105,338	B2	1/2012	Anderson et al.	2003/0236445	A1	12/2003	Couvillon
8,155,732	B2	4/2012	Scholz et al.	2004/0059217	A1	3/2004	Kessman et al.
8,241,274	B2	8/2012	Keogh et al.	2004/0059237	A1	3/2004	Narayan et al.
8,244,339	B2	8/2012	Shen et al.	2004/0138569	A1	7/2004	Grunwald et al.
8,255,035	B2	8/2012	Cao et al.	2004/0150963	A1	8/2004	Holmberg et al.
8,303,505	B2	11/2012	Webler et al.	2004/0243118	A1	12/2004	Ayers et al.
8,326,419	B2	12/2012	Rosenberg et al.	2004/0267086	A1	12/2004	Anstadt et al.
8,326,651	B2	12/2012	McLaren et al.	2005/0085715	A1	4/2005	Dukeshere et al.
8,346,343	B2	1/2013	Kimura et al.	2005/0178396	A1	8/2005	Hunter et al.
8,369,922	B2	2/2013	Paul et al.	2005/0182454	A1	8/2005	Gharib et al.
8,388,541	B2	3/2013	Messerly et al.	2005/0256398	A1	11/2005	Hastings et al.
8,391,956	B2	3/2013	Zellers et al.	2005/0283210	A1	12/2005	Blischak et al.
8,400,164	B2	3/2013	Osadchy et al.	2005/0283216	A1	12/2005	Pyles
8,401,616	B2	3/2013	Verard et al.	2006/0217755	A1	9/2006	Eversull et al.
8,412,313	B2	4/2013	Amitai et al.	2006/0241432	A1	10/2006	Herline et al.
8,456,182	B2	6/2013	Bar-Tal et al.	2006/0253029	A1	11/2006	Altmann et al.
8,478,388	B2	7/2013	Nguyen et al.	2006/0253115	A1	11/2006	Avitall et al.
8,494,608	B2	7/2013	Markowitz et al.	2006/0287595	A1	12/2006	Maschke
8,504,139	B2	8/2013	Jacobsen et al.	2007/0010753	A1	1/2007	MacAdam
8,521,122	B2	8/2013	Scott et al.	2007/0016007	A1	1/2007	Govari et al.
8,527,036	B2	9/2013	Jalde et al.	2007/0016013	A1	1/2007	Camus
8,538,509	B2	9/2013	Harlev et al.	2007/0049817	A1	3/2007	Preiss et al.
8,597,193	B2	12/2013	Grunwald et al.	2007/0049846	A1	3/2007	Bown et al.
8,620,412	B2	12/2013	Griffiths et al.	2007/0055141	A1	3/2007	Kruger et al.
8,644,907	B2	2/2014	Hartmann et al.	2007/0055142	A1	3/2007	Webler
8,663,116	B2	3/2014	Hamilton, Jr.	2007/0055294	A1	3/2007	Giap
8,690,776	B2	4/2014	Razzaque et al.	2007/0060992	A1	3/2007	Pappone
8,700,137	B2	4/2014	Albert	2007/0066888	A1	3/2007	Maschke
8,715,195	B2	5/2014	Ziv	2007/0078343	A1	4/2007	Kawashima et al.
8,721,655	B2	5/2014	Viswanathan et al.	2007/0093710	A1	4/2007	Maschke
8,761,862	B2	6/2014	Ridley et al.	2007/0135803	A1	6/2007	Belson
8,942,784	B2	1/2015	Neidert et al.	2007/0135886	A1	6/2007	Maschke
8,965,490	B2	2/2015	Lee et al.	2007/0161914	A1	7/2007	Zdeblick et al.
8,971,994	B2	3/2015	Burnside et al.	2007/0161915	A1	7/2007	Desai
9,014,794	B2	4/2015	Brodnick et al.	2007/0167738	A1	7/2007	Timinger et al.
9,033,889	B2	5/2015	Hamilton, Jr.	2007/0197905	A1	8/2007	Timinger et al.
9,179,860	B2	11/2015	Markowitz et al.	2007/0197926	A1	8/2007	Danehorn et al.
9,198,600	B2	12/2015	Grunwald et al.	2007/0225589	A1	9/2007	Viswanathan
9,415,188	B2	8/2016	He et al.	2007/0225610	A1	9/2007	Mickley et al.
9,456,766	B2	10/2016	Cox et al.	2007/0232882	A1	10/2007	Glossop et al.
9,492,097	B2	11/2016	Wilkes et al.	2007/0232896	A1	10/2007	Gilboa et al.
9,521,961	B2	12/2016	Silverstein et al.	2007/0239004	A1	10/2007	Kakee et al.
9,526,440	B2	12/2016	Burnside et al.	2007/0247454	A1	10/2007	Rahn et al.
9,532,724	B2	1/2017	Grunwald	2007/0299353	A1	12/2007	Harley et al.
				2008/0033282	A1	2/2008	Bar-Tal et al.
				2008/0081958	A1	4/2008	Denison et al.
				2008/0082136	A1	4/2008	Gaudiani
				2008/0108949	A1	5/2008	Beasley et al.

(56)

## References Cited

## U.S. PATENT DOCUMENTS

2008/0119697 A1 5/2008 Vadodaria et al.  
 2008/0137927 A1 6/2008 Altmann et al.  
 2008/0146939 A1 6/2008 McMorrow et al.  
 2008/0146940 A1 6/2008 Jenkins et al.  
 2008/0146941 A1 6/2008 Dala-Krishna  
 2008/0146942 A1 6/2008 Dala-Krishna  
 2008/0190438 A1 8/2008 Harlev et al.  
 2008/0200801 A1 8/2008 Wildes et al.  
 2008/0200913 A1 8/2008 Viswanathan  
 2008/0269581 A1 10/2008 Wood et al.  
 2009/0062646 A1 3/2009 Creighton, IV et al.  
 2009/0062772 A1 3/2009 Wakeford et al.  
 2009/0080738 A1 3/2009 Zur et al.  
 2009/0099468 A1 4/2009 Thiagalingam et al.  
 2009/0115406 A1 5/2009 Anderson et al.  
 2009/0204113 A1 8/2009 MacAdam et al.  
 2009/0209872 A1 8/2009 Pop  
 2009/0209950 A1 8/2009 Starksen  
 2009/0270729 A1 10/2009 Corbucci et al.  
 2009/0270746 A1 10/2009 Min  
 2009/0281419 A1 11/2009 Troesken et al.  
 2009/0312629 A1 12/2009 Razzaque et al.  
 2010/0004547 A1 1/2010 Scholz et al.  
 2010/0041973 A1 2/2010 Vu et al.  
 2010/0049062 A1 2/2010 Ziv  
 2010/0076328 A1 3/2010 Matsumura et al.  
 2010/0106011 A1 4/2010 Byrd et al.  
 2010/0113917 A1 5/2010 Anderson  
 2010/0117659 A1 5/2010 Osadchy et al.  
 2010/0130858 A1 5/2010 Arai et al.  
 2010/0152596 A1 6/2010 Griffiths et al.  
 2010/0152604 A1 6/2010 Kaula et al.  
 2010/0160772 A1 6/2010 Gardeski et al.  
 2010/0204614 A1 8/2010 Lindquist et al.  
 2010/0217116 A1 8/2010 Eck et al.  
 2010/0274150 A1 10/2010 Harley et al.  
 2010/0291521 A1 11/2010 Simon  
 2011/0015496 A1 1/2011 Sherman et al.  
 2011/0106101 A1 5/2011 Tortonese et al.  
 2011/0282187 A1 11/2011 Harlev et al.  
 2011/0282285 A1 11/2011 Blanchard et al.  
 2011/0282686 A1 11/2011 Venon et al.  
 2011/0295108 A1 12/2011 Cox et al.  
 2011/0306859 A1 12/2011 Saldivar et al.  
 2012/0004564 A1 1/2012 Dobak, III  
 2012/0059270 A1 3/2012 Grunwald  
 2012/0059271 A1 3/2012 Amitai et al.  
 2012/0071751 A1 3/2012 Sra et al.  
 2012/0071782 A1 3/2012 Patil et al.  
 2012/0095319 A1 4/2012 Kondrosky et al.  
 2012/0143029 A1 6/2012 Silverstein et al.  
 2012/0265084 A1 10/2012 Stewart et al.  
 2012/0296200 A1 11/2012 Shachar et al.  
 2012/0310052 A1 12/2012 Mahapatra et al.  
 2012/0310066 A1 12/2012 Shachar et al.  
 2012/0310660 A1 12/2012 Liu et al.  
 2013/0006100 A1 1/2013 Shachar et al.  
 2013/0018248 A1 1/2013 Hurezan  
 2013/0041254 A1 2/2013 Hagy et al.  
 2013/0079628 A1 3/2013 Groszmann et al.  
 2013/0085416 A1 4/2013 Mest  
 2013/0090938 A1 4/2013 Fishman et al.  
 2013/0131503 A1 5/2013 Schneider et al.  
 2013/0169272 A1 7/2013 Eichler et al.  
 2013/0281837 A1 10/2013 Ridley et al.  
 2013/0289417 A1 10/2013 Grunwald et al.  
 2013/0296693 A1 11/2013 Wenzel et al.  
 2013/0303878 A1 11/2013 Nevo et al.  
 2013/0303945 A1 11/2013 Blumenkranz et al.  
 2013/0345555 A1 12/2013 Kanade et al.  
 2014/0089836 A1 3/2014 Damani et al.  
 2014/0128712 A1 5/2014 Banet et al.  
 2014/0187917 A1 7/2014 Clark et al.  
 2014/0187990 A1 7/2014 Banet et al.  
 2014/0221862 A1 8/2014 Tambe

2014/0249428 A1 9/2014 Ingold, Jr. et al.  
 2014/0249505 A1 9/2014 Bukhman  
 2014/0253270 A1 9/2014 Nicholls et al.  
 2014/0257080 A1 9/2014 Dunbar et al.  
 2014/0276010 A1 9/2014 Anderson  
 2015/0025365 A1 1/2015 Esguerra Wilczynski et al.  
 2015/0025402 A1 1/2015 Rothenberg  
 2015/0073285 A1 3/2015 Albert et al.  
 2015/0080716 A1 3/2015 Powers et al.  
 2015/0209008 A1 7/2015 Ridley et al.  
 2015/0216445 A1 8/2015 Carmeli et al.  
 2015/0216446 A1 8/2015 Bukhman et al.  
 2015/0223775 A1 8/2015 Hamilton, Jr.  
 2015/0245809 A1 9/2015 Hagy et al.  
 2015/0245872 A1 9/2015 Hagy et al.  
 2015/0246247 A1 9/2015 Binnekamp et al.  
 2015/0282734 A1 10/2015 Schweikert et al.  
 2015/0289781 A1 10/2015 Grunwald et al.  
 2015/0317810 A1 11/2015 Grunwald et al.  
 2015/0335310 A1 11/2015 Bernstein et al.  
 2015/0335383 A9 11/2015 Cohen  
 2016/0067449 A1 3/2016 Misener et al.  
 2016/0278869 A1 9/2016 Grunwald  
 2016/0374589 A1 12/2016 Misener et al.  
 2017/0020561 A1 1/2017 Cox et al.  
 2017/0079548 A1 3/2017 Silverstein et al.  
 2017/0079552 A1 3/2017 Grunwald  
 2017/0079615 A1 3/2017 Burnside et al.  
 2017/0079681 A1 3/2017 Burnside et al.  
 2017/0086782 A1 3/2017 Hagy et al.  
 2017/0151022 A1 6/2017 Jacob et al.  
 2017/0215762 A1 8/2017 Burnside et al.  
 2017/0231700 A1 8/2017 Cox et al.  
 2017/0281029 A1 10/2017 Messerly et al.  
 2018/0070856 A1 3/2018 Grunwald  
 2018/0103869 A1 4/2018 Bukhman et al.  
 2018/0116551 A1 5/2018 Newman et al.  
 2018/0169389 A1 6/2018 Lemon et al.  
 2019/0069877 A1 3/2019 Burnside et al.  
 2019/0099108 A1 4/2019 Messerly et al.

## FOREIGN PATENT DOCUMENTS

CN 101854853 A 10/2010  
 DE 1319033 C1 6/1994  
 EP 0359697 3/1990  
 EP 0362821 4/1990  
 EP 1015967 B1 4/2002  
 EP 1504713 A1 2/2005  
 EP 1117331 B1 5/2005  
 EP 1117332 B1 8/2005  
 EP 1118019 B1 5/2006  
 EP 1717601 A2 11/2006  
 EP 1887940 A2 2/2008  
 EP 2531098 A1 12/2012  
 EP 2605699 A2 6/2013  
 EP 2474268 B1 7/2013  
 EP 2618727 A1 7/2013  
 EP 2992825 B1 5/2017  
 EP 2170162 B1 8/2017  
 EP 2265175 B1 8/2017  
 JP 2001-145630 A 5/2001  
 JP 2002-224069 A 8/2002  
 JP 2007-105450 A 4/2007  
 JP 2007-313122 A 12/2007  
 RU 2009101949 A 7/2010  
 WO 1980002376 A1 11/1980  
 WO 1997/22395 A1 6/1997  
 WO 97/48438 A2 12/1997  
 WO 1998035611 A1 8/1998  
 WO 1999049407 A1 9/1999  
 WO 2000074775 A1 12/2000  
 WO 2001013792 A1 3/2001  
 WO 02/07794 A2 1/2002  
 WO 2003077759 A1 9/2003  
 WO 2004002303 A1 1/2004  
 WO 2005/089851 A1 9/2005  
 WO 2005117690 A1 12/2005  
 WO 2005117733 A2 12/2005

(56)

**References Cited**

## FOREIGN PATENT DOCUMENTS

WO	2007002541	A2	1/2007
WO	2007005976	A1	1/2007
WO	2007067324	A1	6/2007
WO	2007069168	A2	6/2007
WO	2007109123	A2	9/2007
WO	2007126536	A2	11/2007
WO	2008097767	A2	8/2008
WO	2008118992	A1	10/2008
WO	2008126074	A2	10/2008
WO	2008129326	A1	10/2008
WO	2008131017	A2	10/2008
WO	2008136008	A2	11/2008
WO	2009003138	A1	12/2008
WO	2009100158	A1	8/2009
WO	2009123819	A2	10/2009
WO	2009126340	A1	10/2009
WO	2009129477	A1	10/2009
WO	2009134605	A2	11/2009
WO	2010018500	A1	2/2010
WO	2011057289	A2	5/2011
WO	2012039866	A1	3/2012
WO	2012173697	A1	12/2012
WO	2014042329	A1	3/2014
WO	2015/055797	A1	4/2015
WO	2015048514	A1	4/2015
WO	2015073962	A1	5/2015
WO	2015/120256	A2	8/2015
WO	2016/210325	A1	12/2016
WO	2018/112252	A1	6/2018

## OTHER PUBLICATIONS

CA 2,721,715 filed Apr. 17, 2009 Examiner's Report dated Oct. 25, 2016.

CA 2800810 filed Nov. 26, 2012 Office Action dated Mar. 30, 2017.

CN 200980144663.8 filed May 9, 2011 Decision of Re-Examination dated Feb. 21, 2017.

CN 200980144663.8 filed May 9, 2011 Notice of Reexamination dated Aug. 5, 2016.

CN 201180037065.8 filed Jan. 28, 2013 Notice of Grant dated Aug. 30, 2016.

CN 201380051172.5 filed Mar. 30, 2015 Office Action dated May 2, 2017.

CN 201380065663.5 filed Jun. 15, 2015 Office Action dated Mar. 15, 2017.

CN 201510144728.6 filed Apr. 17, 2015 Office Action dated Jan. 23, 2017.

CO 15110530 filed May 14, 2015 Office Action dated May 8, 2017.

CO 15110530 filed May 14, 2015 Office Action dated Nov. 25, 2016.

EP 09743249.6 filed Oct. 18, 2010 Intention to Grant dated Mar. 2, 2017.

EP 11850625.2 filed Jul. 22, 2013 Extended European Search Report dated Jun. 21, 2017.

EP 13840356.3 filed Apr. 27, 2015 Extended European Search Report dated Mar. 22, 2017.

EP 13840356.3 filed Apr. 27, 2015 Partial European Search Report dated Oct. 19, 2016.

EP 13846380.7 filed May 15, 2015 Extended European Search Report dated Sep. 30, 2016.

EP 13846380.7 filed May 15, 2015 Partial European Search Report dated Sep. 30, 2016.

EP 14761249.3 Filed Sep. 3, 2015 Extended European Search Report dated Sep. 19, 2016.

EP 15746326.6 filed Jul. 1, 2016 Extended European Search Report dated Jun. 9, 2017.

EP 17157118.5 filed Feb. 21, 2017 Extended European Search Report Jun. 8, 2017.

JP 2013-530322 filed Mar. 18, 2013, Office Action dated Mar. 2, 2017.

JP 2015-534770 filed Mar. 26, 2015 Office Action dated Jun. 12, 2017.

KR 10-2012-7000866 filed Jan. 11, 2012 Second Office Action dated Nov. 3, 2016.

PCT/US2016/039356 filed Jun. 24, 2016 International Search Report and Written Opinion dated Sep. 16, 2016.

U.S. Appl. No. 12/426,175, filed Apr. 17, 2009 Decision on Appeal dated Nov. 7, 2016.

U.S. Appl. No. 12/426,175, filed Apr. 17, 2009 Notice of Allowance dated Dec. 13, 2016.

U.S. Appl. No. 12/545,762, filed Aug. 21, 2009 Final Office Action dated Apr. 10, 2017.

U.S. Appl. No. 12/545,762, filed Aug. 21, 2009 Non-Final Office Action dated Sep. 26, 2016.

U.S. Appl. No. 12/545,762, filed Aug. 21, 2009 Notice of Panel Decision dated Jul. 14, 2017.

U.S. Appl. No. 12/893,916, filed Sep. 29, 2010 Non-Final Office Action dated Aug. 31, 2016.

U.S. Appl. No. 13/118,033, filed May 27, 2011 Notice of Allowance dated Sep. 2, 2016.

U.S. Appl. No. 13/469,932, filed May 11, 2012 Notice of Allowance dated Jan. 31, 2017.

U.S. Appl. No. 13/665,420, filed Oct. 31, 2012 Non-Final Office Action dated Mar. 15, 2017.

U.S. Appl. No. 13/890,158, filed May 8, 2013 Non-Final Office Action dated Apr. 7, 2017.

U.S. Appl. No. 14/040,205, filed Sep. 27, 2013 Advisory Action dated Dec. 15, 2016.

U.S. Appl. No. 14/040,205, filed Sep. 27, 2013 Examiner's Answer dated Jul. 20, 2017.

U.S. Appl. No. 14/040,205, filed Sep. 27, 2013 Final Office Action dated Oct. 19, 2016.

U.S. Appl. No. 14/054,700, filed Oct. 15, 2013 Advisory Action dated Dec. 15, 2016.

U.S. Appl. No. 14/054,700, filed Oct. 15, 2013 Examiner's Answer dated Jul. 3, 2017.

U.S. Appl. No. 14/054,700, filed Oct. 15, 2013 Final Office Action dated Oct. 19, 2016.

U.S. Appl. No. 14/141,046, filed Dec. 26, 2013 Non-Final Office Action dated Apr. 7, 2017.

U.S. Appl. No. 14/201,300, filed Mar. 7, 2014 Advisory Action dated Mar. 2, 2017.

U.S. Appl. No. 14/201,300, filed Mar. 7, 2014 Final Office Action dated Dec. 19, 2016.

U.S. Appl. No. 14/201,300, filed Mar. 7, 2014 Final Office Action dated Jul. 10, 2017.

U.S. Appl. No. 14/201,300, filed Mar. 7, 2014 Non-Final Office Action dated Mar. 30, 2017.

U.S. Appl. No. 14/548,151, filed Nov. 19, 2014 Final Office Action dated Apr. 19, 2017.

U.S. Appl. No. 14/548,151, filed Nov. 19, 2014 Non-Final Office Action dated Sep. 28, 2016.

U.S. Appl. No. 14/615,932, filed Feb. 6, 2015 Non-Final Office Action dated Dec. 29, 2016.

U.S. Appl. No. 14/846,496, filed Sep. 4, 2015 Non-Final Office Action dated Nov. 25, 2016.

U.S. Appl. No. 15/160,958, filed May 20, 2016 Advisory Action dated Jul. 10, 2017.

CN 201380065663.5 filed Jun. 15, 2015 Office Action dated Oct. 10, 2017.

CN 201480010988.8 filed Aug. 27, 2015 Office Action dated Dec. 13, 2017.

CN 201510144728.6 filed Apr. 17, 2015 Office Action dated Aug. 29, 2017.

CN 201610127217.8 filed Mar. 7, 2016 Office Action dated Dec. 28, 2017.

CN 201610166569.4 filed Dec. 23, 2010, Office Action dated Nov. 1, 2017.

EP 10786978.6 filed Dec. 19, 2011 Office Action dated Aug. 11, 2017.

EP 11827551.0 filed Feb. 7, 2013 Extended European Search Report dated Sep. 19, 2017.

(56)

## References Cited

## OTHER PUBLICATIONS

- EP 14197137.4 filed Dec. 10, 2014 Extended European Search Report dated Nov. 4, 2015.
- EP 14197137.4 filed Dec. 10, 2014 Office Action dated, Sep. 20, 2017.
- EP 14197137.4 filed Dec. 10, 2014, Partial European Search Report dated May 29, 2015.
- EP 14761249.3 Filed Sep. 3, 2015 Office Action dated Sep. 28, 2017.
- EP 15179061.5 filed Jul. 30, 2015 Partial European Search Report dated Jan. 17, 2018.
- JP 2013-530322 filed Mar. 18, 2013, Office Action dated Nov. 6, 2017.
- KR 10-2013-7006933 filed Mar. 19, 2013 Office Action dated Aug. 7, 2017.
- MX/a/2015/004864 filed Apr. 16, 2015 Office Action dated Dec. 18, 2017.
- RU 2015111669 filed Apr. 1, 2015 Office Action dated Sep. 5, 2017.
- U.S. Appl. No. 13/887,166, filed May 3, 2013 Appeal Decision dated Aug. 17, 2017.
- U.S. Appl. No. 13/887,166, filed May 3, 2013 Notice of Allowance dated Nov. 6, 2017.
- U.S. Appl. No. 13/890,158, filed May 8, 2013 Final Office Action dated Nov. 21, 2017.
- U.S. Appl. No. 14/141,046, filed Dec. 26, 2013 Final Office Action dated Dec. 11, 2017.
- U.S. Appl. No. 14/317,501, filed Jun. 27, 2014 Decision on Appeal dated Nov. 17, 2017.
- U.S. Appl. No. 14/548,151, filed Nov. 19, 2014 Advisory Action dated Aug. 1, 2017.
- U.S. Appl. No. 14/548,151, filed Nov. 19, 2014 Non-Final Office Action dated Sep. 21, 2017.
- U.S. Appl. No. 14/788,305, filed Jun. 30, 2015 Non-Final Office Action dated Jan. 10, 2018.
- U.S. Appl. No. 14/788,305, filed Jun. 30, 2015 Restriction Requirement dated Aug. 25, 2017.
- U.S. Appl. No. 15/284,355, filed Oct. 3, 2016 Non-Final Office Action dated Nov. 17, 2017.
- U.S. Appl. No. 15/365,698, filed Nov. 30, 2016 Non-Final Office Action dated Dec. 14, 2017.
- U.S. Appl. No. 15/365,752, filed Nov. 30, 2016 Non-Final Office Action dated Dec. 13, 2017.
- Arrow International, Inc., The Arrow-Johans RAECG Adapter-Making Proper Central Venous Catheter Placement More Reliable (Modle No. EG-04900), Technical Report 1987, USA.
- B. Braun, Certofix Central Venous Catheter for Placement Using the Seldinger Technique with Simultaneous ECG Lead Option, Feb. 2010.
- Colley, Peter S et al, ECG-Guided Placement of Sorenson CVP Catheters via Arm Veins, *Anesthesia and Analgesia*, pp. 953-956, vol. 63, 1984.
- Corsten, et al., "Central Placement Catheter Placement Using the ECG-Guided Cavafix-Certodyn SD Catheter." *Journal of Clinical Anesthesiology*, vol. 6, Nov./Dec. 1994.
- David, et al., "Is ECG-Guidance a Helpful Method to Correctly Position a Central Venous Catheter During Prehospital Emergency Care?" *ACTA Anaesthesiologica Scandinavica*, vol. 49, pp. 1010-1014, 2005.
- Engelhardt, W et al, ECG-Controlled Placement of Central Venous Catheters in Patients with Atrial Fibrillation, *Anaesthesist*, pp. 476-479, vol. 38 No. 9, Sep. 1989 (Abstract only).
- Jeon, Yunseok et al., "Transesophageal Echocardiographic Evaluation of ECG-guided Central Venous Catheter Placement," *Canadian Journal of Anesthesia*, vol. 53, No. 10, Oct. 1, 2006, pp. 978-983.
- Kjelstrup T et al, Positioning of Central Venous Catheters using ECG, *Tidsskr nor Laegeforen*, pp. 599-601, vol. 111 No. 5, Feb. 1999 (Abstract only).
- Lepage Ronan et al. ECG Segmentation and P-wave Feature Extraction: Application to Patients Prone to Atrial Fibrillation, *IEEE/EMBS Proceedings, 23rd Annual Conference, Istanbul, Turkey*, Oct. 25-28, 2001.
- Madias, John E, Intracardiac (Superior Vena Cava/Right Atrial) ECGs using Saline Solution as the Conductive Medium for the Proper Positioning of the Shiley Hemodialysis Catheter: Is it Not Time to Forego the Postinsertion Chest Radiograph?, pp. 2363-2367, *CHEST*, 2003.
- McDonnall, "Intra-Atrial Electrocardiography (ECG) for Catheter Placement." Literature review prepared for Bard Access Systems, Oct. 2007.
- MedGraphics, CardioPerfect® Resting/Stress ECG System, 3 pages, 2001.
- Moureau, Nancy L. et al., "Electrocardiogram (EKG) Guided Peripherally Inserted Central Catheter Placement and Tip Position: Results of a Trial to Replace Radiological Confirmation," *Journal of the Association for Vascular Access*, pp. 8-14, vol. 15, No. 1, 2010.
- Nakatani, K et al, Accurate Placement of Central Venous Catheters—ECG-guided method vs Patient Height Method, *Masui*, pp. 34-38, vol. 51 No. 1, Jan. 2002.
- Pittiruti, et al, "The intracavitary ECG method for positioning the tip of central venous catheters: results of an Italian multicenter study," *J Vasc Access*, pp. 1-9, Nov. 21, 2011.
- Pittiruti, et al, Intracavitary EKG Monitoring: A reliable method for controlling tip position during and after PICC Insertion presentation in Catholic University, Rome, Italy in 2008.
- Pittiruti, et al. "The EKG Method for Positioning the Tip of PICCs: Results from Two Preliminary Studies." *JAVA*, vol. 13, No. 4, pp. 179-185, 2008.
- Schafer et al. "Incorrect placement of a vena cava catheter and its prevention by intra-atrial ECG" *Anaesthesist*. Jan. 1988;37(1):49-51.
- Schummer, et al. "Central Venous Catheters—The inability of 'intra-atrial ECG' to prove adequate positioning." *British Journal of Anaesthesia*, vol. 93, No. 2, pp. 193-198, 2004.
- Schummer, W et al, ECG-guided Central Venous Catheter Positioning: Does it detect the Pericardial Reflection rather than the Right Atrium?, *Eur J Anaesthesiol*, pp. 600-605, vol. 21 No. 8, Aug. 2004 (Abstract only).
- Schummer, W et al, Intra-Atrial ECG is not a Reliable Method for Positioning Left Internal Jugular Vein Catheters, *Br J Anaesth*, pp. 481-486, vol. 91 No. 4, Oct. 2003.
- Schummer, W, Central Venous Catheter—The Inability of "Intra-Atrial ECG" to prove Adequate Positioning, *Br J Anaesth*, pp. 193-198, vol. 93 No. 2, Aug. 2004.
- Starr, David S et al, EKG Guided Placement of Subclavian CVP Catheters Using J-Wire, pp. 673-676, *Ann. Surg*, Dec. 1986.
- Tepa® Health Innovation PC based ECG System Introduction and Technical Specifications, EKG Master USB, 2 pages, Nov. 2003.
- Welch Allyn Cardioperfect® PC-Based Resting ECG, 2003.
- Zachariou, Zacharias et al., Intra-atrial ECG recording: a new and safe method for implantation of Broviac catheters in children, *Pediatr Surg Int* (1994) 9: 457-458.
- U.S. Appl. No. 15/160,958, filed May 20, 2016 Final Office Action dated Apr. 21, 2017.
- U.S. Appl. No. 15/160,958, filed May 20, 2016 Non-Final Office Action dated Dec. 15, 2016.
- U.S. Appl. No. 15/160,958, filed May 20, 2016 Notice of Allowance dated Jul. 26, 2017.
- U.S. Appl. No. 15/284,355, filed Oct. 3, 2016 Non-Final Office Action dated Apr. 24, 2017.
- U.S. Appl. No. 15/585,051, filed May 2, 2017 Non-Final Office Action dated Jul. 14, 2017.
- AZoMaterials. Nickel-Based Super Alloy Inconel 625—Properties and Applications by United Performance Alloys. Oct. 27, 2015. Last accessed Mar. 23, 2018. <URL:https://web.archive.org/web/20151027202821/https://www.azom.com/article.aspx?ArticleID=4461>.
- CA 2800810 filed Nov. 26, 2012 Office Action dated Mar. 13, 2018.
- CA 2800813 filed Nov. 26, 2012 Office Action dated Mar. 5, 2018.
- CN 2013800511725 filed Mar. 30, 2015 Office Action dated Jan. 16, 2018.

(56) **References Cited**

## OTHER PUBLICATIONS

- CN 2013800511725 filed Mar. 30, 2015 Office Action dated Jul. 30, 2018.
- CN 201480010988.8 filed Aug. 27, 2015 Office Action dated Aug. 17, 2018.
- CN 201610127217.8 filed Mar. 7, 2016 Office Action dated Jun. 11, 2018.
- Enrique Company-Bosch, "ECG Front-End Design is Simplified with MicroConverter." Analog Dialogue 37-11, (dated Nov. 2003).
- EP 11850625.2 filed Jul. 22, 2013 Office Action dated Sep. 24, 2018.
- EP 14197137.4 filed Dec. 10, 2014 Office Action dated Apr. 5, 2018.
- EP 17186624.7 filed Aug. 17, 2017 Extended European Search Report dated Jan. 17, 2018.
- EP 17186624.7 filed Aug. 17, 2017 Partial European Search Report dated Jan. 17, 2018.
- Hamza, N. et al. "Interference reduction in ECG signal acquisition: Ground electrode removal." 2013 International Conference on Computer Medical Applications (ICCMA), Jan. 2013.
- Honeywell, "1, 2 and 3 Axis Magnetic Sensors HMC1051/HMC1052L/HMC1053" dated Jan. 2010.
- JP 2013-530322 filed Mar. 18, 2013, Office Action dated Jul. 6, 2018.
- JP 2015-534770 filed Mar. 26, 2015 Office Action dated Feb. 21, 2018.
- KR 10-2014-7002789 filed Feb. 3, 2014 Office Action dated Jun. 21, 2018.
- MX/a/2015/004864 filed Apr. 16, 2015 Office Action dated Apr. 24, 2018.
- Not Resource Center. Magnetic Permeability. Oct. 18, 2014. Last accessed Mar. 23, 2018. <URL:https://web.archive.org/web/20141018213902/https://www.nde-ed.org/EducationResources/CommunityCollege/Materials/Physical\_Chemical/Permeability.htm>.
- PCT/US2017/066503 filed Dec. 14, 2017 International Search Report and Written Opinion dated Feb. 20, 2018.
- RU 2015111669 filed Apr. 1, 2015 Office Action dated Jan. 25, 2018.
- RU 2015111669 filed Apr. 1, 2015 Office Action dated May 18, 2018.
- Thakor, N. V., et al. "Ground-Free ECG Recording with Two Electrodes." IEEE Transactions on Biomedical Engineering, vol. BME-27, No. 12, Dec. 1980.
- U.S. Appl. No. 13/665,420, filed Oct. 31, 2012 Notice of Allowance dated Feb. 7, 2018.
- U.S. Appl. No. 13/890,158, filed May 8, 2013 Advisory Action dated Feb. 13, 2018.
- U.S. Appl. No. 13/890,158, filed May 8, 2013 Notice of Allowance dated May 30, 2018.
- U.S. Appl. No. 14/141,046, filed Dec. 26, 2013 Examiner's Answer dated Oct. 15, 2018.
- U.S. Appl. No. 14/201,300, filed Mar. 7, 2014 Examiner's Answer dated Apr. 19, 2018.
- U.S. Appl. No. 14/317,501, filed Jun. 27, 2014 Notice of Allowance dated Feb. 9, 2018.
- U.S. Appl. No. 14/788,305, filed Jun. 30, 2015 Final Office Action dated Jul. 27, 2018.
- U.S. Appl. No. 15/192,561, filed Jun. 24, 2016 Non-Final Office Action dated Apr. 6, 2018.
- U.S. Appl. No. 15/284,355, filed Oct. 3, 2016 Advisory Action dated Aug. 13, 2018.
- U.S. Appl. No. 15/284,355, filed Oct. 3, 2016 Final Office Action dated May 24, 2018.
- U.S. Appl. No. 15/365,698, filed Nov. 30, 2016 Final Office Action dated Jul. 12, 2018.
- U.S. Appl. No. 15/365,734, filed Nov. 30, 2016 Non-Final Office Action dated Feb. 23, 2018.
- U.S. Appl. No. 15/365,734, filed Nov. 30, 2016 Notice of Allowance dated Jun. 4, 2018.
- U.S. Appl. No. 15/365,752, filed Nov. 30, 2016 Final Office Action dated Jul. 12, 2018.
- U.S. Appl. No. 15/365,872, filed Nov. 30, 2016 Non-Final Office Action dated Aug. 27, 2018.
- U.S. Appl. No. 15/365,872, filed Nov. 30, 2016 Restriction Requirement dated Apr. 5, 2018.
- U.S. Appl. No. 15/585,051, filed May 2, 2017 Final Office Action dated Feb. 28, 2018.
- U.S. Appl. No. 15/585,051, filed May 2, 2017 Final Office Action dated Mar. 15, 2018.
- U.S. Appl. No. 15/900,623, filed Feb. 20, 2018 Final Office Action dated Sep. 20, 2018.
- U.S. Appl. No. 15/900,623, filed Feb. 20, 2018 Non-Final Office Action dated May 3, 2018.
- CN 201580007645.0 filed Aug. 8, 2016 Office Action dated Sep. 12, 2018.
- CN 201610127217.8 filed Mar. 7, 2016 Office Action dated Nov. 19, 2018.
- EP 10786978.6 filed Dec. 19, 2011 Office Action dated Jan. 16, 2019.
- EP 14197137.4 filed Dec. 10, 2014, Office Action dated Nov. 21, 2018.
- EP 15746326.6 filed Jul. 1, 2016 Office Action dated Jan. 29, 2019.
- EP14197136.6 filed Dec. 10, 2014 Office Action dated Nov. 21, 2018.
- RU 2015110633 filed Mar. 26, 2015 Office Action dated Oct. 25, 2018.
- U.S. Appl. No. 14/788,305, filed Jun. 30, 2015 Advisory Action dated Oct. 19, 2018.
- U.S. Appl. No. 14/788,305, filed Jun. 30, 2015 Notice of Allowance dated Nov. 15, 2018.
- U.S. Appl. No. 15/192,561, filed Jun. 24, 2016 Final Office Action dated Nov. 1, 2018.
- U.S. Appl. No. 15/365,752, filed Nov. 30, 2016 Notice of Allowance dated Nov. 6, 2018.
- U.S. Appl. No. 15/365,872, filed Nov. 30, 2016 Notice of Allowance dated Dec. 21, 2018.
- EP 11850625.2 filed Jul. 22, 2013 Office Action dated Feb. 25, 2019.
- KR 10-2014-7002789 filed Feb. 3, 2014 Office Action dated Feb. 22, 2019.
- U.S. Appl. No. 14/040,205 filed Sep. 27, 2013 Board Decision dated May 1, 2019.
- U.S. Appl. No. 14/054,700 filed Oct. 15, 2013 Board Decision dated May 1, 2019.
- U.S. Appl. No. 14/201,300 filed Mar. 7, 2014 Board Decision dated Apr. 12, 2019.
- U.S. Appl. No. 14/996,247 filed Jan. 15, 2016 Restriction Requirement dated Mar. 22, 2019.
- U.S. Appl. No. 15/284,355 filed Oct. 3, 2016 Notice of Allowance dated Feb. 21, 2019.
- U.S. Appl. No. 15/365,698 filed Nov. 30, 2016 Non-Final Office Action dated Apr. 18, 2019.
- U.S. Appl. No. 15/585,051 filed May 2, 2017 Examiner's Answer dated May 2, 2019.




FIG. 1A




FIG. 1B






FIG. 3




FIG. 4A




FIG. 4B




FIG. 4C




FIG. 4D




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10A




FIG. 10B




FIG. 11

1250

## DECISION SUPPORT ALGORITHMS 1 - Based on skin ECG as reference

**A: Upper SVC** $T1 < P_{pp} / P_{pp} \text{ skin} < T2 \text{ AND } T1 < P_{wr} / P_{wr} \text{ skin} < T2 \text{ and unipolar P-wave, e.g., } T1 = 0.9, T2 = 1.2$ **B: Lower third of SVC** $T3 < P_{pp} / P_{pp} \text{ skin} < T4 \text{ AND } T3 < P_{wr} / P_{wr} \text{ skin} < T4 \text{ AND unipolar P-wave, e.g., } T3 = 1.5, T4 = 2$ **C: Caval-atrial junction** $P_{pp} > T5 * P_{pp} \text{ skin AND } P_{wr} > T5 * P_{wr} \text{ skin AND } P > R, \text{ e.g., } T5 = 2.5$ **D: Right atrium** $T6 < P_{wr} / P_{wr} \text{ skin} < T7 \text{ AND bipolar P-wave, e.g., } T6 = 2, T7 = 2.5$ **E: Upper third of the IVC** $T1 < P_{pp} / P_{pp} \text{ skin} < T2 \text{ AND } T1 < P_{wr} / P_{wr} \text{ skin} < T2 \text{ AND unipolar P-wave WITH reversed polarity}$ 

FIG. 12




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17

## DEVICES AND METHODS FOR ENDOVASCULAR ELECTROGRAPHY

### CROSS-REFERENCE TO RELATED APPLICATIONS

This application is a division of U.S. patent application Ser. No. 12/854,083, filed on Aug. 10, 2010, now U.S. Pat. No. 9,445,734, which is a continuation-in-part (CIP) of U.S. patent application Ser. No. 12/815,331, filed on Jun. 14, 2010, now U.S. Pat. No. 9,339,206, which claims priority to U.S. Provisional Patent Application No. 61/213,474, filed on Jun. 12, 2009, the disclosures of which are incorporated herein by reference in their entirety. This application also claims the benefit of U.S. Provisional Patent Application No. 61/272,025, filed on Aug. 10, 2009, the disclosure of which is incorporated herein by reference in its entirety.

### FIELD OF THE INVENTION

The present invention relates to endovascular device positioning. Specifically, the present invention relates to an adapter for an endovascular device and a steering device for a catheter.

### BACKGROUND

The electrical conduction system of the heart creates specific electrical signals, electrical energy distributions and behaviors thereof which are indicative of specific locations in the thoracic cavity and/or of specific heart functions or conditions. When measured endovascularly, i.e., from within blood vessels or from within the heart, certain parameters of the electrical activity of the heart can be used to identify specific locations in the cardiovascular system and/or functional conditions, normal or abnormal. Moreover, by locally and accurately identifying the location and the type of condition, therapy of such conditions can be optimized and the effect of the therapy monitored in real-time.

Two types of clinical applications are typically addressed. The first is related to guiding endovascular devices through the cardiovascular system, while the second is related to the non-invasive or the minimally invasive remote monitoring of the electrical activity of the heart.

The guidance, positioning, and placement confirmation of endovascular catheters are necessary in a number of clinical applications, such as, for example:

1. Central venous access, e.g., CVC, PICC, implantable ports;
2. Hemodialysis catheters;
3. Placement of pacemaker leads;
4. Hemodynamics monitoring catheters, e.g., Swan-Ganz and central pressure monitoring catheters; and
5. Guiding guidewires and catheters into the left heart.

The location of the catheter tip is very important to the patient safety, the duration and the success of the procedure. Today's golden standard for confirming the target location of the catheter tip is the chest X-ray. In addition, there are currently two types of real-time guiding products available on the market, which try to overcome the limitations of chest X-ray confirmation: electromagnetic and ECG-based. In hospitals where real-time guidance is used results have improved in terms of reducing the number of X-rays, the procedure time, and the cost of the procedure. Under real-time guidance first-time success rate has typically increased from 75%-80% to 90%-95%. In addition, in hospitals where ECG guidance is used, e.g., in Italy, Belgium, Germany,

chest X-ray confirmation has been eliminated for more than 90% of the patients. Electromagnetic systems are used mostly in the United States while ECG-based systems are used mostly in Europe. Amongst other factors which determine the difference between the markets in the United States and Europe in terms of technology adoption: a) type of health care personnel allowed to perform procedures: nurses have more flexibility in the United States, b) type of devices placed: PICCs are placed more and more often in the United States, c) price sensitivity: the European market seems to be more price sensitive, and d) the current guiding devices are commercialized by specific manufacturers to work exclusively with their catheters: market penetration of the guiding systems reflects the market penetration of the catheter manufacturer.

It was also found that different opinions exist regarding where the target tip location should be: for example, lower third of the SVC or RA. Therefore guiding technologies should allow for discrimination of these locations. The chest X-ray, which is the current golden standard does not always allow for such discrimination requiring an accuracy of typically better than 2 cm. Also, because ECG-based systems make use of physiological information related to the heart activity, their ability to guide placement is accurate with respect to the anatomy. This is not the case with electromagnetic guiding systems which measure the distance between the catheter tip in the vasculature and an external reference placed typically on the patient's chest. Because of this aspect, ECG-based systems can be used to document the final result of the catheter placement potentially replacing the chest X-ray as the golden standard.

One of the most valuable diagnostic tools available, the ECG records the heart's electrical activity as waveforms. By interpreting these waveforms, one can identify rhythm disturbances, conduction abnormalities, and electrolyte imbalance. An ECG aids in diagnosing and monitoring such conditions as acute coronary syndromes and pericarditis. The heart's electrical activity produces currents that radiate through the surrounding tissue to the skin. When electrodes are attached to the skin, they sense these electrical currents and transmit them the electrocardiograph. Because the electrical currents from the heart radiate to the skin in many directions, electrodes are placed at different locations on the skin to obtain a total picture of the heart's electrical activity. The electrodes are then connected to an electrocardiograph device, or computer, and record information from different perspectives, which are called leads and planes. A lead provides a view of the heart's electrical activity between two points or poles. A plane is a cross section of the heart which provides a different view of the heart's electrical activity. Currently, the interpretation of an ECG waveform is based on identifying waveform component amplitudes, analyzing and then comparing the amplitudes with certain standards. Modifications of these amplitude components are indicative of certain conditions, e.g., the elevation of the ST segment or of certain locations in the heart, e.g., the amplitude of the P-wave. In today's practice ECG monitors are widely used to record ECG waveforms. More and more often applications are made available for automatic identification of the ECG amplitude components. In certain cases tools are available for decision making support and for automatic interpretation of ECG amplitude components with respect to underlying heart conditions.

Remote patient monitoring is a well-established medical field. Still remote monitoring of heart conditions is not as widely accepted as it would be need and possible. One of the reasons is related to the relatively complicated way of

acquiring signals related to the heart activity, in particular ECG signals. Another important limiting factor of the current remote monitoring technologies is the use of communications channels, like the telephone line, which are difficult to interface with at both the patient and the physician ends.

### SUMMARY OF THE INVENTION

Embodiments of the present invention advantageously provide an adapter for an endovascular device and a steering device for a catheter.

According to one embodiment of the present invention, an adapter for an endovascular device includes a body, a conductive metal ring and a conductive wire. The body includes a first open end, a second open end, a central lumen having a substantially cylindrical surface extending from the first open end to the second open end, and a channel extending from the central lumen to an external opening. The conductive metal ring is attached to the surface of the central lumen, and the conductive wire is coupled to the conductive metal ring and extends through the channel and the external opening.

According to another embodiment of the present invention, a steering device for a catheter that has a plurality of lumens with spaced distal openings includes a stylet for disposition within one of the plurality of lumens, and a steering member for disposition within a different one of the plurality of lumens. In the installed position, the stylet and the steering member are connected together at respective distal ends such that a portion of the steering member is disposed outside of the distal end of the catheter.

There has thus been outlined, rather broadly, certain embodiments of the invention in order that the detailed description thereof herein may be better understood, and in order that the present contribution to the art may be better appreciated. There are, of course, additional embodiments of the invention that will be described below and which will form the subject matter of the claims appended hereto.

In this respect, before explaining at least one embodiment of the invention in detail, it is to be understood that the invention is not limited in its application to the details of construction and to the arrangements of the components set forth in the following description or illustrated in the drawings. The invention is capable of embodiments in addition to those described and of being practiced and carried out in various ways. Also, it is to be understood that the phraseology and terminology employed herein, as well as the abstract, are for the purpose of description and should not be regarded as limiting.

As such, those skilled in the art will appreciate that the conception upon which this disclosure is based may readily be utilized as a basis for the designing of other structures, methods and systems for carrying out the several purposes of the present invention. It is important, therefore, that the claims be regarded as including such equivalent constructions insofar as they do not depart from the spirit and scope of the present invention.

### BRIEF DESCRIPTION OF DRAWINGS

FIG. 1A is a block diagram that depicts an apparatus according to an embodiment of the present invention.

FIG. 1B is a block diagram of an electronic module for acquisition and processing of endovascular electrocardiogram according to an embodiment of the present invention.

FIG. 2 depicts an adaptor for an endovascular device according to an embodiment of the present invention.

FIG. 3 depicts a catheter steering device according to an embodiment of the present invention.

FIGS. 4A, 4B, 4C, and 4D depict electrode configurations that provide optimal acquisition of endovascular electrocardiogram according to various embodiments of the present invention. FIG. 4A depicts a single lead configuration, FIG. 4B depicts a modified 3-lead configuration with monitoring and guiding capabilities, FIG. 4C depicts a telemetry configuration with a single grounded lead, and FIG. 4D depicts one use of ECG monitors for guiding endovascular devices.

FIG. 5 illustrates exemplary electrocardiogram signal amplitudes at different locations in the central venous system.

FIG. 6 illustrates exemplary electrocardiogram signal power spectra at different locations in the central venous system.

FIG. 7 illustrates exemplary electrocardiogram signal electrical energy distribution at different locations in the central venous system.

FIG. 8 depicts a graphical user interface according to an embodiment of the present invention.

FIG. 9 depicts a graphical user interface according to another embodiment of the present invention.

FIGS. 10A and 10B depict an exemplary printouts for the information displayed by the graphical user interface, according to an embodiment of the present invention.

FIG. 11 is a block diagram for a computer-based method for positioning an endovascular device in or near the heart using electrocardiogram signals.

FIG. 12 illustrates another decision support algorithm for a computer-based method for positioning an endovascular device in or near the heart using electrocardiogram signals, according to an alternative embodiment.

FIG. 13 illustrates the cardiac conduction system of the heart.

FIG. 14 illustrates electrical signal propagation in the conduction system of the heart.

FIG. 15 illustrates electrical activity in the cardiovascular system due to neuronal control system.

FIG. 16 illustrates a framework for analyzing the endovascular electrography signals, according to an embodiment of the present invention.

FIG. 17 illustrates several embodiments for electrogram waveform processing.

### DETAILED DESCRIPTION

The invention will now be described with reference to the drawing figures, in which like reference numerals refer to like parts throughout.

Embodiments of the present invention advantageously provide an inventive apparatus(es), computer-based data processing algorithms and methods for obtaining and using endovascular ECGs in a number of clinical applications and settings. For example, once device can be used to guide endovascular devices in and around the heart, e.g., guiding central venous access devices in the superior vena cava, right atrium, and right ventricle. Such central venous access devices may include central venous catheters (CVC), peripherally inserted central catheters (PICC), implantable ports, hemodialysis catheters, tunneled catheters and others. Other devices which may benefit from guidance with the inventive apparatus are temporary pacemaker leads placed through the central venous system. Catheters and guidewires used in left heart procedures may also benefit from the

present invention by decreasing the amount of contrast and radiation required to guide these devices in position. In another example, the apparatus can be used for minimally invasive monitoring and assessing heart conditions based on its electrical activity, e.g., assessing preload in a heart cycle or monitoring ST segments and T-waves in congestive heart failure.

In one aspect of the invention, an apparatus is described consisting of sterile adaptors, an electronic module for signal acquisition, a computer module, software, and peripheral devices and connections. In one embodiment, the electronic module for signal acquisition can be dedicated to acquiring and processing endovascular electrical signals generated by the body (endovascular ECG), in another embodiment the electronic module can be dedicated to acquiring and processing endovascular ECGs as well as skin ECGs.

In one embodiment, the electronic module and the computer module can be separate modules, in another embodiment they can be integrated in the same module and enclosure, and yet in another embodiment they can communicate with each other via a wireless connection, such as Bluetooth. In one embodiment, the apparatus can contain an integrated printer, while in another embodiment the printer can be external and attached to the apparatus and the apparatus connected via network, e.g., wireless to other devices. In yet another embodiment the apparatus can be used for telemetry and for transmitting the endovascular electrograms to a remote location, e.g., via a telephone line, Internet, and/or wireless phone. Any combination of embodiments mentioned above is also possible.

In another aspect of the invention, various configurations allow the connection of endovascular devices, such as central venous access devices, to the electronic module for signal acquisition and processing. In one embodiment, the device consists of a connecting wire with two ends and special connectors at each end. At one end, the wire can be connected to a metal or nitinol guidewire or stylet as commonly available on the market. At the other end, the wire can be safely connected to the electronic module. In another embodiment, the device includes a coated guidewire, e.g., made of nitinol or stainless steel with uncoated distal and proximal ends and cm markings. In such an embodiment, the coated guidewire is inserted endovascularly, while the connecting wire is connected to the proximal end of the coated guidewire. In another embodiment, the device includes a catheter-syringe adaptor provided with an electrical connecting wire. At one end, the electrical connecting wire is in contact with the fluid, e.g., saline flowing within the catheter syringe adapter. At the other end the connecting wire can be connected to the electronic module.

In another aspect of the invention, various electrode configurations allow for the optimal acquisition of endovascular ECGs. In one embodiment, a single lead is used to provide information about the tip location of an endovascular device within the vasculature. In another embodiment a modified three lead configuration is used to provide simultaneous 3-lead monitoring of the heart activity at the same time with providing tip location information. In another embodiment a modified single lead configuration plus ground is used for telemetry and transferring information from the tip of the catheter remotely.

In another aspect of the invention algorithms are introduced for the analysis of the ECG waveforms and for supporting decision making based on these waveforms. These algorithms discriminate between different locations in the vasculature and assess body functions (systemic and at

specific locations in the body), in particular heart functionality. In various embodiments, these algorithms use time domain analysis of waveforms: morphologic, for example shape; statistic, for example behavior.

In other embodiments, the algorithms use frequency domain analysis of waveforms: morphologic, for example shape; statistic, for example behavior. In further embodiments, signal energy analysis in time and frequency domains is also performed, morphologic and statistic. Fuzzy, statistical, and knowledge-based decision making are also contemplated by the present invention as decision support tools.

In another aspect of the invention, a user interface is provided that advantageously simplifies interpretation of data and workflow. In one embodiment the user interface includes simplified graphics showing the location in the vasculature and in the heart of the tip of the endovascular device in use without showing any of the ECG waveforms. In another embodiment, the user interface shows, in real-time, the change in location of the tip of the endovascular device in use.

In another aspect of the invention, several inventive methods are presented which use the apparatus described herein in clinical applications. In one embodiment, a computer-based method is provided that guides central venous catheters (CVC, PICCs, hemodialysis, implantable ports, and others) using stylets, guidewires and saline solution to the superior vena cava, inferior vena cava, the right atrium, and the right ventricle. This method is advantageously less sensitive to patients with arrhythmias than the prior art, and represents an alternative to chest X-ray confirmation of tip location of central venous catheters in most clinical cases. In another embodiment, a computer-based method is provided that guides coated guidewires in the right and left heart. In another embodiment, a computer-based method is provided that guides the placement of temporary pacemaker leads through the central venous system. In another embodiment, a method is provided that is minimally invasive and monitors preload using depolarization and heart rhythms. In another embodiment, a method is provided that is minimally invasive and monitors arrhythmias using P-wave analysis. In another embodiment, a method is provided that is minimally invasive and monitors heart failure using ST segment and T-wave analysis.

FIG. 1A is a block diagram that depicts an apparatus according to an embodiment of the present invention.

The apparatus **100** can be attached through an adaptor (**120**) to a large variety of commercially available and custom designed vascular access devices (**110**). Examples of such devices are: central venous catheters (CVC), peripherally inserted central catheters (PICC), implantable ports, tunneled catheters, hemodialysis catheters, guiding catheters for pacemaker leads, guidewires used for coronary and other vascular interventions, guiding catheters for coronary and other vascular interventions, stylets, syringe needles, and others. If the vascular access device is a stylet, a guidewire, or a syringe needle, its material must be sufficiently electrically conductive, e.g., stainless steel or nitinol. In such a case the hook or the alligator clip adaptor according to the present invention should be used. If the vascular access device is a catheter, than saline should be used to establish a conductive path through one of the catheter's lumens. In such a case, the syringe-catheter adaptor according to the present invention should be used.

The electronic module (**130**) receives electrical signals from the adaptor and from one or more other electrodes placed on the patient's skin (**115**). Alternatively, more than one adaptor can be used at the same time to connect to more

than one endovascular device in order to provide different electrical signals to the electronic module. The use of skin electrodes is optional in certain device configurations. The electronic module processes the electrical signals and transmits them to a computer module (140) for further processing and other functions. In one embodiment the electronic module and the computer module can be packaged separately, in another embodiment they can be integrated in the same package. In one embodiment the connection between the electronic module and the computer module can be hardwired, in another embodiment it can be wireless, e.g., using Bluetooth.

The computer module processes the signals from the electronic module applying algorithms (170) as described by the current invention. The computer module can also be connected to peripherals (160), e.g., a printer or a label printer and storage devices and provides connectivity including wireless connectivity (150) to other computers or to the internet. The storage device can be used to store a database of knowledge and information regarding the application at hand. The connectivity interface can be used to update this database remotely with newest relevant knowledge and information, e.g., new clinical cases, new findings regarding the relationship between electrograms and heart conditions. The computer module supports a graphical user interface (180) optimized for the purpose of the clinical application at hand.

FIG. 1B is a block diagram of an electronic module (2) for acquisition and processing of endovascular electrocardiogram according to an embodiment of the present invention.

The patient connector interface (10) allows for connecting electrical leads to the patient (5). Any combination of skin electrodes and/or electrical connections to endovascular devices using the adaptors discussed above can be used. In one embodiment, the amplifier (20) is a four stage amplifier with variable gain, which can amplify electrical signals coming through the patient cable, for example, typical of electrocardiographic values. The analog-to-digital converter (30) converts the signals in digital format readable by the microprocessor (40). Any number and configurations of microprocessors, microcontrollers, or digital signal processors can be used to implement the micro-processing function (45).

In one embodiment, a microcontroller is responsible for controlling the serial communication with a computer module (90) via the serial interface (70) or via the wireless interface (80) and a digital signal processor (DSP) is responsible for implementing one or several of the inventive algorithms described herein. Alternatively, a single processor (46) can be used for both communication and processing.

The micro-processor (40) also receives commands from the computer module (90) and controls different elements of the electronic module, e.g., the amplifier (20) accordingly. The patient isolation block (50) decouples electrically the power (60) and the serial communication channel (70) from the patient interface (10) in order to ensure patient protection to electrical shock. In one embodiment the isolation block (50) can consist of a transformer and/or couplers, e.g. optical couplers.

FIG. 2 depicts an adaptor (200) for an endovascular device according to an embodiment of the present invention. Vascular access devices like catheters, syringes, syringe needles, stopcocks, infusion pumps and others connect to each other through standard connections. For example, in FIG. 2 such a standard connection between two devices is illustrated on device (201) by the luer (202) with inner diameter (203) and outer diameter (204), and on device

(250) by threaded port (251) with inner diameter (252) and fluid opening diameter (253). The threaded port (251) and the luer (202) allow for connecting the two devices (201, 250) by threading, attaching, coupling, etc., the port (251) into the luer (202).

The adaptor (200) has a body (220) with two ends (226, 227) with a length 225, and is made, for example, of strong biocompatible plastic material with some degree of elasticity. End (227) has a shape of a cone. In one embodiment, end (227) has an elastic sealing portion (228) such that end (227) can easily fit in the luer (202) of device (201) to seal the connection for fluid flow. The other end (226) is in the shape of a standard luer, such as, for example, luer (202) of device (201). The threaded port (251) of the device (250) can be connected to end (226) of the adaptor (200). The cone piece (227) also allows a connection to a device that does not have a luer. The stand-alone cone piece (270) allows a connection between two devices with different accessible diameters. The end (227) of adaptor (200) has a diameter (223) and fits inside the diameter (272) of the cone piece (270). The end (271) of the cone piece (270) fits in a simple catheter end portion (261) with a diameter (262) of a typical device (260). For example, device (260) can be a catheter for an implantable port.

In one embodiment, device (201) is a syringe needle, and device (250) is a syringe. Fluid, e.g., a conductive electrolyte, flows through adaptor (200) through a central inner bore or lumen (222) having a certain diameter, and provides a fluid path between the devices (250, 201). A conductive metal ring (240) is attached to a portion of the substantially cylindrical surface of lumen (222) and, preferably, induces very little perturbations to the fluid flow. For example, the metal ring (240) may be disposed within a recessed portion of the substantially cylindrical surface of the lumen (222). One end (230) of a conductive wire (233) is electrically coupled to the metal ring (240); in one embodiment, the end (230) is soldered to metal ring (240). In another embodiment, the end (230) is captured between the surface of the lumen (222) and the metal ring (240), and the end (230) and the metal ring (240) maintain good electrical contact through mechanical pressure. The wire (233) may be bare or insulated. In a preferred embodiment, the metal ring (240) is fixedly attached to the surface of lumen (222) using, for example, adhesive, an interference fit, a press fit, etc., while in other embodiments, the metal ring (240) may be removably attached to the surface of lumen (222), free-floating, etc.

The wire (233) passes through a channel (231), which extends from the lumen (222) to an opening in the outer surface of the body (220). Epoxy (232), or other suitable material, may be used to seal the opening of the channel (231), as well as to provide a strain relief for the wire (233). The metal ring (240) may be advantageously disposed adjacent to the channel (231) to provide additional sealing. Thus, the metal ring (240), the wire (233), the channel (231) and the epoxy (232) provide a sealed, electrical connection to the fluid flowing through the adaptor (200). A connector (234) may provide a standard electrical connection to the electrography system; a non-terminated wire may also be used. In one embodiment, the wire (233) terminates at the opening of the channel (231) and the connector (234) is attached directly to the body (222), while in another embodiment, the wire (233) extends through the opening of the channel (231) and the connector (234) is attached to the free end of the wire (233).

In one embodiment, the substantially cylindrical surface of lumen (222) is tapered along the longitudinal direction.

This taper may extend along the entire length of lumen (222), or restricted to a certain portion thereof. For example, the surface of lumen (222) may be cone-shaped and have a larger diameter at the proximal end, or, alternatively, the larger diameter may be located at the distal end.

In one example, device (201) is a syringe needle that is inserted into a lumen of a catheter for an implantable port, and device (250) is a syringe. The syringe is filled with saline, which is then injected into the catheter through the adaptor (200). Thus, the adaptor (200) becomes filled with saline solution, and, because the conductive metal ring (240) is in contact with saline and the conductive wire (233), an electrical connection is established between the catheter lumen and the wire (233). In this way, the electrical signal at the tip of the catheter may be measured through the saline solution. Other electrically conductive solutions may also be used to obtain the endovascular electrogram using the adaptor (200). In another embodiment, the adaptor (200) may be used with infusion pumps, as well as other types of power injections. In an alternative embodiment, the adaptor (200) does not include the metal ring (240), and the electrically conductive ending (230) is in direct contact with the electrolyte.

FIG. 3 illustrates a catheter steering device according to an embodiment of the present invention. In this embodiment, the catheter (300) is a triple lumen catheter and the distal end of each of the lumens is spaced with respect to each other. The catheter steering device can be used with any catheter having two or more lumens with spaced distal lumen openings. The open end of one lumen (306) of catheter (300) is at the very distal end of the catheter, another end or opening of a lumen (305) is spaced back from the distal end and the end or opening of the third lumen (307) is spaced back compared to the second end (305). The distance between the open end (306) and the end (307) is typically from one to several centimeters.

Several types of catheters have multiple lumens with spaced ends, and the inventive steering device can accommodate such catheters. For example, in the case of a peripherally inserted central catheter, the typical length of a catheter is 50 to 60 centimeters and the spacing between the distal lumen ends (305, 306, and 307) is from one to several centimeters. A hemodialysis catheter with two lumens can typically be 20 to 40 centimeters in length, with one to several centimeters spacing between the distal ends of the two lumens. A multi-lumen central venous catheter (CVC) can typically be 15 to 25 cm in length with spacing between distal ends or openings of the lumens being from several millimeters to several centimeters.

At the proximal end, the catheter has a catheter hub (301) which splits the three lumens and connects each of them with a luer (302, 303, 304). The inventive catheter steering device includes a stylet (310) with a handle (311) at the proximal end to allow for pushing, pulling, and removal after use, and a steering member (320) which connects to the distal end of the stylet (322) and which can be fed back into a distal lumen opening of one of the other lumens, such as, for example, lumen (307). The steering member (320) returns to the proximal end of the catheter through the catheter lumen and exits at the proximal end through the luer corresponding the respective lumen (304). So disposed, the steering device is in the installed position. In one embodiment, the member (320) has a handle (321) which can be used to pull the member through the lumen. In another embodiment, the handle (321) is detachable from the member (320).

The member (320) may be polyurethane, silicone, PTFE, or other similar materials. In different embodiments, the member (320) may be any kind of biocompatible thread, e.g., surgical thread. In another embodiment, the member (320) is stainless steel wire. In one embodiment, the stylet is provided pre-inserted into one of the catheter lumens, typically the central lumen with the most distal opening (306) with the member 320 attached at the distal end of the stylet (322) and pre-inserted into the lumen (304) through the lumen opening (307). In order to steer the catheter, the user pulls the member 320 out of the catheter while preventing the stylet 310 to be pulled into the catheter. Thus, the catheter tip can be bent in a desired direction. This situation is illustrated by the bent catheter tip (350), the member (340) which was pulled back and the member (330) which is its initial position with respect to the catheter. If the stylet (310) or the steering member (320), or both are made of any electrically conductive material, then each or both of them can be used to measure electrical signals or endovascular electrograms at the distal tip of the catheter by connecting their proximal ends to the endovascular electrography system. In one embodiment, the steering member (320) can be tied to the stylet (310) through the opening (307) of the catheter lumen.

In another embodiment, the stylet (310) and the steering member (320) are manufactured as a single component to form an extended steering member that is looped back through the opening (305) of a different catheter lumen. By pulling one of the two ends of the extended steering member coming out through luers (304) and (302), the same effect is achieved and the catheter tip can be bent in a desired direction. In another embodiment, in the case of a double lumen catheter, the stylet (310) can be inserted in one lumen and the steering member (320) can be inserted in the other lumen, such that the effect of bending the catheter tip can be achieved by pulling the proximal ends. In a further embodiment, the steering member (320) can be inserted in the lumen (302) and through the opening (305).

FIGS. 4A, 4B, 4C, and 4D depict electrode configurations that provide optimal acquisition of endovascular electrocardiogram according to various embodiments of the present invention.

FIG. 4A depicts a single lead configuration with a reference electrode (410), for example attached to the patient's skin over the right arm and with the other electrode attached through an adaptor to an endovascular device (415). The reference electrode attached to the skin over the right arm is presented in this configuration for illustration purposes only. Other locations of the reference electrode are possible depending on the type of ECG required. The reference electrode over the right arm together with the tip of the endovascular device used with the adaptor can be similar to lead II of a standard ECG. In this case the ECGs obtained from the superior vena cava (401) and inferior vena cava (402) can be optimized. The reference electrode can be attached to the skin in any other location in order to simulate other leads of the standard ECG. The reference electrode can be also connected to adaptors attached to other endovascular devices in order to obtain more local information from within the patient's heart (400).

FIG. 4B depicts a modified 3-lead configuration, with monitoring and guiding capabilities, with 4 electrodes. Three (3) electrodes correspond to the standard ECG electrodes: right arm (RA, 420), left arm (LA, 425), and left leg (LL, 430) used as reference. The fourth electrode is attached through an adapter to the endovascular device (C, 435). In this configuration, the electronic module and the algorithm

perform two functions simultaneously: the three standard electrodes (RA, LL, and LL) perform a monitoring function of the heart, while the C electrode (435) allow for recording the ECG at the tip of device.

FIG. 4C depicts a telemetry configuration with a single grounded lead, including the configuration illustrated in FIG. 4A and a ground reference (450). This configuration can be used to transmit ECGs remotely through a telemetry system configuration.

FIG. 4D depicts one use of ECG monitors for guiding endovascular devices. A standard ECG monitor is used having standard inputs RA (465), LA (460), and LL (470). LA (460) is connected to the left arm and LL (470) to the left leg of the patient. The RA input (465) is connected to a switch which can be used by the clinician to switch the RA input (465) between the RA electrode and the catheter (C) electrode 475. Thus either monitoring or guiding of catheter placement can be achieved alternatively.

FIG. 5 illustrates exemplary electrocardiogram signal amplitudes at different locations in the central venous system.

The heart (504), right atrium (501), superior vena cava (SVC) (502), and the inferior vena cava (IVC) (503) are illustrated. Location A is in the upper SVC, location B is in the lower third of the SVC, location C is at the caval-atrial junction, location D is in the right atrium, and location E is in the upper inferior vena cava.

Graph 510 illustrates an ECG waveform as a function of time at recorded at location A. The absolute amplitude of the waveforms is recorded on an amplitude scale (590). In the case of an endovascular ECG, the standard elements of the electrocardiogram are illustrated: the P-wave (560), the R-wave (570), and the T-wave (580). The amplitudes and shape at location A recorded with a lead configuration as in FIG. 4D are similar to an electrocardiogram recorded at the skin level with the same electrode configuration.

Graph 520 illustrates an endovascular ECG depicted at location B. The amplitude at this location is higher than the one at location A but the overall shapes of the waveform are similar at location A and B.

Graph 530 illustrates an endovascular ECG depicted at location C. At location C at the caval-atrial junction, the amplitude of the waveform is yet higher than the one at location B and the P-wave has dramatically changed becoming higher than the R-wave. This waveform is an indication of the proximity of the sino-atrial node.

Graph 540 illustrates an endovascular ECG depicted at location D. At location D in the right atrium, the amplitudes are similar to location C but the P-wave changes polarity becoming bi-polar. This is an indication that the measurement of the ECG occurs beyond the sino-atrial node.

Graph 550 illustrates an endovascular ECG depicted at location E. At location E in the inferior vena cava, the waveform is similar to the one at location A in terms of amplitude except the P-wave has reverse polarity. The differences in the ECG waveforms at different locations are used by the algorithms introduced herein to discriminate between the corresponding locations and to assess heart and blood vessel functionality.

FIG. 6 illustrates exemplary electrocardiogram signal power spectra at different locations in the central venous system, using a spectral scale (690).

The heart (604), right atrium (601), superior vena cava (SVC) (602), and the inferior vena cava (IVC) (603) are illustrated. Graph 610 illustrates an endovascular ECG spectrum depicted at location A. At location A, the spectrum (610) has the appearance of a single central frequency or

single band (660) and with a frequency distribution spectral power and energy similar to those at skin level.

Graph 620 illustrates an endovascular ECG spectrum depicted at location B. At location B the frequency distribution has two major bands and a higher energy and spectral power than the one at location A.

Graph 630 illustrates an endovascular ECG spectrum at location C. At location C, there are multiple (3-4) major frequencies or principal spectral components distributed over a wider range of frequencies (670). This spectral distribution is indicative of the energy distribution around the sino-atrial node. The spectral power and signal energy have increased compared to location B.

Graph 640 illustrates an endovascular ECG spectrum depicted at location D. At location D the spectrum is wider and more broadband indicative of the electrical activity of the right atrium.

Graph 650 illustrates an endovascular ECG spectrum depicted at location E. The frequency spectrum at location E is similar to the one at location A. The differences in the spectral waveforms at different locations are used by the algorithms introduced herein to discriminate between the corresponding locations and to assess heart and blood vessel functionality.

FIG. 7 illustrates exemplary electrocardiogram signal electrical energy distribution at different locations in the central venous system. The heart (704), right atrium (701), superior vena cava (SVC) (702), and the inferior vena cava (IVC) (703) are illustrated. Graphs (710, 720, 730, 740, 750) depict the energy distribution at different locations (A, B, C, D and E, respectively) and the changes in time are used by the algorithms introduced herein to discriminate between the corresponding locations and to assess heart and blood vessel functionality.

Considering FIG. 16 for a moment, a framework for analyzing the endovascular electrography signals according to an embodiment of the present invention is illustrated. The heart is represented by (1600), the superior vena cava by (1601), the inferior vena cava by (1602) and the right atrium by (1603). In this embodiment, there are three regions of interest for placing central venous access devices: the lower third of the superior vena cava or SVC (1605), the caval-atrial junction or CAJ (1606), and the upper right atrium or RA (1607).

The graph (1620) illustrates the electrical energy profile as a function of location in the heart and the graph (1640) illustrates the different electrography waveforms which can be obtained at different locations in the heart. The curve (1630) illustrates the increase of electrical energy detected in each of the regions at the tip of an endovascular catheter advancing from the superior vena cava into the heart. In one embodiment, the energy curve is calculated in time domain, while in another embodiment, the energy curve is calculated in the frequency domain using the frequency spectrum. In one embodiment, the energy is calculated for the actual signal levels, while in another embodiment, the baseline value or other mean values are first subtracted from the signal values before energy calculations. The signal energy or power is calculated in time domain by summing up the squared amplitude values before and/or after baseline subtraction over a determined period of time, e.g., a heartbeat. In the frequency domain, the signal energy or power is calculated by summing up the squared values of the frequency components. In one embodiment, the curve is calculated using the entire electrogram, while in other embodiments, only certain segments of the electrogram are used for the energy calculations, e.g., only the segment correspond-

ing to a “P-wave” of an electrocardiogram. Such a “P-wave” segment is representative of the electrical activity of the sino-atrial node.

Different levels of energy characterize the different locations along the catheter path from the SVC to the heart. These regions can be differentiated in terms of their electrical energy level by using thresholds. Threshold (1631) of energy level defines the beginning of the lower third of the superior vena cava. The energy levels (1621) define the regions in the vasculature of low energy which are distant or further away from the sino-atrial node. The energy levels (1622) between thresholds (1631) and (1632) define the region labeled as the lower third of the superior vena cava (1625 and 1605). The energy levels (1623) between thresholds (1632) and (1633) define the region labeled as the caval-atrial junction (1626 and 1606). The energy levels (1624) between thresholds (1633) and (1634) define the region labeled right atrium (1627 and 1607).

Similarly, the shape and size of the electrogram in graph (1640) relative to a baseline (1650) can be correlated to a location in the heart. Thresholds (1631), (1632), (1633), and (1634) are determined specifically for the type of energy considered for calculations, e.g. the entire electrogram, the P-wave, and/or the S-T segment. Before the lower third of the SVC and corresponding to a relatively low level of energy (1621), the P-wave (1651) and the R-wave (1652) are similar in size and shape with a standard electrocardiogram lead II recorded at the skin level if the right arm standard ECG lead is connected to the catheter and measuring the electrogram signal at the tip of the catheter. In the lower third of the SVC (1605 and 1645), the energy level of the electrogram increases, the electrogram amplitudes increase and the P-wave (1653) increases amplitude and energy relative to the R-wave (1654) to where the P-wave amplitude and energy between half and three quarters of the amplitude and energy of the R-wave. At the caval-atrial junction (1606 and 1646), the energy level of the electrogram increases further, the electrogram amplitudes continue to increase and the P-wave (1655) increases amplitude and energy relative to the R-wave (1656) to where the P-wave amplitude and energy are larger or equal to the amplitude and energy of the R-wave. In the right atrium (1607 and 1647), the energy level of the electrogram increases further, the electrogram amplitudes increase, the P-wave (1657) becomes bipolar and its amplitude and energy relative to the R-wave (1658) start decreasing. These behaviors are quantified, analyzed, and used in order to provide location information regarding the tip of the catheter.

Considering FIG. 17 for a moment, several electrogram waveform processing embodiments are illustrated. Graphs (1710) and (1720) illustrate a P-wave analysis embodiment. Since the P-wave corresponds to electrical activity of the heart generated by the sino-atrial node, the changes of the P-wave are most relevant with respect to determining the proximity of the sino-atrial node in an endovascular approach. Therefore, in order to assess proximity of the sino-atrial node and location in the vasculature, signal analysis methods in time and frequency domains, as well as signal energy criteria can be applied only to the P-wave segment of an electrogram. In graph (1710), the segment designated for the P-wave analysis (1711) starts at moment (1713) and ends at moment (1714). During the period of time between the starting moment and the ending moment of the P-wave segment, the highest amplitude detected corresponds to the P-wave peak (1712). The starting moment (1713) of the P-wave segment analysis can be determined in a number of ways. In one embodiment, the heart beat is

calculated and the R-peak is detected as the maximum amplitude of the heartbeat. Going back from each R-peak a certain percentage of the heartbeat, for example between 20% and 30%, determines the moment when the analysis of the P-wave starts (1713). Going back 2% to 5% of the heart beat from each R-peak determines the end of the segment designated for the P-wave analysis (1714). Similarly, in graph (1720), the designated segment for the P-wave analysis (1721) starts at moment (1723) in the heart cycle and ends at moment (1724). The P-wave in this case is bipolar with a positive maximum amplitude (1722) and a negative maximum amplitude (1725) when compared to the baseline (amplitude equals zero). For the P-waveform defined between the starting point (1713 on graph 1710 and 1723 on graph 1720) and the end point (1714 on graph 1710 and 1724 on graph 1720) time-domain and frequency-domain algorithms are applied according to the present invention.

Graph (1730) illustrates the advantages of baseline subtraction prior to signal energy computation. If the signal energy is calculated in time domain as the sum of the squared signal amplitudes over a heartbeat, then the amplitude variations between levels (1731 and 1732) around baseline (1733) may lead to a lower energy level than the signal with amplitude variations between levels (1734 and 1735) whereby the level (1734) is the baseline. The baseline value (1733) is subtracted from the amplitude values (1731 to 1732) and the baseline value (1734) is subtracted from the amplitude values (1734 to 1735). After subtracting the baseline, the sum of squared amplitude values is calculated. Thus, this sum is proportional to the energy of signal variation around the baseline and therefore it is more appropriate to characterize changes in the signal values/behavior.

Graph (1740) shows a typical electrogram waveform with a P-wave (1741) and an R-wave (1742) and a distorted signal with the P-wave covered by high frequency noise (1744) and the R-wave saturated to a maximum value (1743). In the presence of these kind of artifacts (1744 and 1743) it is very difficult and sometimes impossible to recover the original signal (1741 and 1742). Therefore, according to the present invention, an algorithm is used to detect the presence of artifacts and reduce the amount of artifacts as much as possible. If, after reducing the artifacts, the signal cannot be recovered, then the signal is discarded for the computation of signal energy. The presence of artifacts can be detected in time domain by a high value of the derivative and of its integral, a jump in signal energy, a jump in the value of the baseline or in different averages calculated from the signal. In frequency domain, the artifacts can be detected as a jump in the value of the DC component (frequency zero of the spectrum), as the sudden appearance of high frequency components, and in a jump of the spectral power/energy. In the frequency domain, selective filtering can be applied and all components removed, which are not “typical” for the average behavior of the signal. After selective filtering, the signal is reconstructed in the time domain using an inverse Fourier transform in order to allow for verification of the success of the selective filtering.

FIG. 8 depicts a graphical user interface according to an embodiment of the present invention.

Window (810) presents the ECG waveform in real-time as it is acquired by the electronic module using the attached electrode configuration. Window (820) is a reference window and shows a frozen waveform used to compare with the current window. In one embodiment, the reference waveform in window (820) can be obtained through the electrodes connected to the electronic module at a reference location of the catheter and/or using a reference configura-

tion of the skin electrodes. For example, such a reference waveform can be the ECG recorded using an adaptor according to the present invention connected to an endovascular device placed at the caval-atrial junction. In a different embodiment, the reference waveform in window **820** can be a typical waveform at a certain location in the vasculature or of a certain heart condition as it is recorded in a database of waveforms and as it is stored in the storage medium of the computer system. If the electrode configuration allows for simultaneous heart monitoring and recording of electrograms using an endovascular device, window **(830)** shows one of the standard ECG leads for heart monitoring, while window **(810)** shows the ECG at the tip of the endovascular devices when connected to an adaptor, such as the ones discussed above.

The icon **(870)** is a representation of the heart, and the locations A through E **(875)** illustrate different locations in the heart and vascular system which can be discriminated by analyzing endovascular ECGs in accordance with the methods disclosed herein. As a location in the vasculature is identified by the algorithms, the corresponding place and letter on the icon **(875)** becomes highlighted or in some other way is made visible to the user. The bars **(884)**, **(885)**, and **(886)** show signal energy levels. The “E” bar **(885)** presents the amount of electrical energy computed from the ECG frequency spectrum at the current location of the tip of the endovascular device. The “R” bar **(884)** presents the amount of electrical energy computed from the ECG frequency spectrum at a reference location. The “M” bar **(886)** presents amount of electrical energy computed from the ECG frequency spectrum using the monitoring ECG signal from the skin electrodes. The window **(840)** depicts monitoring information, e.g., heart rate. Patient information (name, date of procedure and others) are shown in window **(850)**. Window **(860)** contains system control elements like buttons and status information, e.g., scale, scroll speed, system parameters and system diagnostics.

FIG. 9 depicts a graphical user interface according to another embodiment of the present invention.

The icon **(920)** is a representation of the heart and the locations A through E **(930)** illustrate different locations in the heart and vascular system which can be discriminated by analyzing endovascular ECGs. As a location in the vasculature is identified by the algorithms, the corresponding place and letter on the icon **(930)** becomes highlighted or in some other way is made visible to the user. The bars **(940)**, **(950)**, and **(960)** show signal energy levels. The “E” bar **(940)** depicts the amount of electrical energy computed from the ECG frequency spectrum at the current location of the tip of the endovascular device. The “R” bar **(950)** shows the amount of electrical energy computed from the ECG frequency spectrum at a reference location. The “M” bar **(960)** shows amount of electrical energy computed from the ECG frequency spectrum using the monitoring ECG signal coming from the skin electrodes. The button “Print” **(960)** allows the user to print the information documenting the case on a printer, for example on a label printer for quick attachment to the patient’s chart.

FIGS. 10A and 10B depict an exemplary printouts for the information displayed by the graphical user interface, according to an embodiment of the present invention.

FIG. 10A illustrates a printout **(1000)** for the case of a catheter tip placement procedure in the lower third of the SVC. The field **1010** depicts the heart icon whereby the letter “B” corresponding to the lower third of the superior vena cava (SVC) is highlighted **(1040)**. Field **1030** depicts the reference ECG waveform recorded at the tip of the catheter

at the caval-atrial junction in the proximity of the sino-atrial node. Field **1020** depicts the ECG waveform at the tip of the catheter in the position in which it was placed at the end of the procedure. For FIG. 10A, this location is in the lower third of the SVC and the ECG waveform corresponds to this location. The patient name **(1001)** and the date of procedure **(1002)** are also printed.

FIG. 10B depicts a similar printout **(1050)** except that the final position at the end of the procedure is at the caval-atrial junction at location C **(1090)** on the heart icon **(1060)**. The “SA Node” field depicts the reference ECG waveform **(1080)**, and the “Final Position” field **(1070)** shows that the catheter was placed with the tip at the sino-atrial node: the ECG waveform in final location is similar or even identical with the one in the reference location at the sino-atrial node (SA Node). It is known that the proximity of the SA Node indicates a location at the caval-atrial junction. These locations are sometimes considered identical by some clinicians.

FIG. 11 is a block diagram for a computer-based method **(1100)** for positioning an endovascular device in or near the heart using electrocardiogram signals.

The algorithms are applied to the input signal **(1102)** (ECG) acquired by the adaptor to the endovascular devices and, optionally, through skin electrodes as well. The Error Detection Block **(1105)** detects at least three types of error conditions/exceptions, such as, for example, when a defibrillator has been applied to the patient, when a pacemaker is firing excitation pulses and/or when a lead/electrode is off. These errors/exceptions may be handled differently, and the user may be informed about the presence of an exception and the way of handling the exception **(1110)**.

The Pre-Processing block **(1115)** may amplify the signal, reduce noise, eliminate artifacts, etc. In one embodiment, rescaling the signal to the display range occurs under user control and is not automatic, as with most currently available ECG monitors. Thus, changes in the amplitude of the ECGs are easily noticed. A high-pass filter corrects the baseline and reduces such artifacts as respiratory artifact. Wideband noise suppression may be achieved using a selective filter, e.g., a wavelet transform. Electromagnetic interference with other equipment and the power grid may be suppressed by a notch filter (narrow band filter) centered at 60 Hz or 50 Hz to accommodate domestic or international power supplies. High frequency noise may be suppressed with a low-pass filter, which, in one embodiment, is implemented with variable length averaging, such as, for example, a running window corresponding to a heart cycle, an averaging of the ECG over several consecutive heart cycles, etc. The Adaptive Filtering block **(1120)** optimizes the filter coefficients by minimizing an error signal.

The Time-Domain Pattern Recognition block **(1130)** identifies elements of the ECG waveform, their relationship(s) and their behavior(s) in time. An important aspect of the time-domain pattern recognition algorithm in block **1130**, as well as of the Frequency Domain Patter Recognition block **1140**, is data history. The ECGs are analyzed in real time for certain elements, and, for other elements, a data buffer with an appropriate buffer length is maintained in the memory of the electronic and/or computer modules in order to allow for historic data analysis and prediction based on this analysis. In one embodiment, the data history buffer is several seconds long allowing for the ECG signal corresponding to several heartbeats to be saved in the buffer. A double buffering technique allows the waveform in one buffer to be processed while the second buffer continues to store signals. Thus no signal data are lost while the waveform in one buffer is processed. After data processing on one buffer is

completed, the results are sent to the Decision Support Algorithms (1150) and the two buffers switch roles. The length of the buffer accommodates the time duration of data processing in order to ensure that no data are lost. A similar double buffering technique is also applied to the data subject

to Frequency Domain Pattern Recognition block (1140).  
In the case of an endovascular ECG, elements of interest may include, but are not limited to, one or more of the following:

1. The P, Q, R, S, T, and U waves, their peaks, amplitudes and duration;
2. The duration of the P-R, S-T, and T-P segments/intervals;
3. The elevation of the S-T segment;
4. The variances of the P-P and R-R intervals;
5. The variance of the S-T and of the R-T intervals, etc.;
6. The peak-to-peak values of the P-wave and of the QRS complex;
7. The ratio of the P-wave and R-wave amplitudes and the ratio of the P-wave and QRS complex peak-to-peak amplitudes;
8. The polarity of the P-wave: single positive, single negative, or bipolarity;
9. The derivative of the P-wave, QRS-complex, and T-wave;
10. Temporal average of the R-R interval and the heart beat;
11. Maximum value of the P-wave amplitude/peak and of the P-wave peak-to-peak amplitude over a certain period of time;
12. Maximum value of the R-wave amplitude/peak and of the QRS complex peak-to-peak amplitude over a certain period of time.

Several techniques may be used to derive the information listed above from the ECG waveforms, including, but not limited to, one or more of the following:

1. "Peak detection";
2. Computation of first derivatives;
3. Running averages along the signal in one heartbeat and along multiple heartbeats;
4. Adaptive thresholding;
5. Auto-correlation.

The Fast Fourier Transform in block (1125) performs a Fast Fourier Transform on a number of ECG samples stored in a buffer of a certain length, e.g., 256, 512, 1024, 2048 or more data samples. The Fourier Transform transforms the waveform from the time domain into the frequency domain.

The Frequency-Domain Pattern Recognition block (1140) illustrates various aspects of pattern recognition performed on the ECGs in the frequency domain, including, but not limited to, one or more of the following:

1. Principal components analysis, i.e., determination of the most significant elements of the frequency spectrum (similarly to determining the morphological elements of the electrograms, e.g., certain waves and segments in time domain);
2. Data compression in order to reduce the amount of computation based on the principal components;
3. Determination of the number and morphology of the principal components, in particular determination if the spectrum has only one, two or multiple main frequencies (frequency bands);
4. Calculation of the spectral power and of the signal energy from the frequency spectrum;
5. Running average along the frequency dimension over a single spectrum in order to reduce wideband noise;

6. Running average along several spectra in order to filter out artifacts;
7. Determination of additional morphological elements of the spectrum, e.g., the maximum frequency, the energy contained in the maximum frequency, the frequency histogram, i.e., what frequencies contain how much energy, the frequency of the highest significant maximum energy peak, etc.;
8. Calculation of behavior and averages over time of the principal components and other parameters determined from the spectral distribution, e.g., determining the maximum value of the signal energy and of the spectral power over a certain period of time;
9. Determine/estimate certain heart conditions based on the spectral analysis. This determination/estimation is also performed in more detailed in the decision support blocks 1150 and 1250.

Several decision support algorithms use the information provided by the time domain pattern recognition and frequency-domain pattern recognition algorithms. In one embodiment, block (1150) supports placing an endovascular device in either the lower third of the SVC or at the caval-atrial junction.

In particular, block 1150 is based on the concept of first reaching the caval-atrial junction during catheter placement. At the caval-atrial junction or near the sino-atrial node the P-wave and other electrical parameters reach a maximum value. At the caval-atrial junction the P-wave is unipolar. After reaching the sino-atrial node at the caval-atrial junction, i.e., the maximum value of the P-peak amplitude and spectral power, the catheter is pulled back several centimeters until the P-wave decreases to half the amplitude reached at the caval-atrial junction. At the location where the P-wave has decreased to half the amplitude as the caval-atrial junction, the catheter is considered to be in the lower third of the superior vena cava. The P-wave peak amplitude or peak-to-peak amplitude, as well as the spectral power, is used to map the location in the vasculature to the ECG waveform.

More particularly, after receiving an endovascular ECG signal associated with an endovascular device, the signal is processed, over a plurality of predetermined time periods, to calculate a P-wave amplitude and a spectral power for each predetermined time period. A maximum P-wave amplitude is then determined from the plurality of P-wave amplitudes, as well as an associated maximum spectral power from the plurality of spectral powers. The location at which these maximum values are determined is associated with a predetermined location in or near the heart, such as the caval-atrial junction. The location of the endovascular device is then calculated, for each predetermined time period, based on a ratio of the P-wave amplitude to the maximum P-wave amplitude and a ratio of the spectral power to the maximum spectral power, and the location of the endovascular device is then displayed to the user. Additionally, the polarity of the P-wave and the R-wave amplitude may also be used to determine the location of the endovascular device.

A single criterion or a combination of such criteria can be used to support decision making. In one embodiment, T1, T2, and T3 may be empirically established thresholds which are different for each patient, and the algorithm can use an adaptive loop to adjust the thresholds based on the current measurements. In another embodiment, these thresholds are predetermined.

In alternative embodiments, the ratio between the P-peak/P amplitude or the P-wave peak-to-peak amplitude to the R-peak/R amplitude or to the QRS complex peak-to-

peak amplitude can also be used to establish location relative to the sino-atrial node. In one embodiment the P-peak/amplitude must be approximately half of the R-peak/amplitude and the P-wave must be unipolar for the location to correspond to the lower third of the SVC. In another embodiment, the P-wave peak-to-peak must be half of the QRS peak-to-peak amplitude and the P-wave must be unipolar for the location to correspond to the lower third of the SVC.

As discussed above, the results of the decision support algorithms block **1150** may be presented to the user, for example, by highlighting the appropriate location on the heart icon corresponding to the type of ECG identified by the system (**1160**).

The decision support algorithm block **1250**, depicted in FIG. **12**, is based on comparing the P-wave, R-wave and P-wave spectral power at the current locations with the values of these parameters determined from the skin electrocardiograms in an equivalent lead, e.g., lead II. Thresholds T1 through T6 are empirical values subject to adaptive adjustments relative to each patient. Each of the criteria or a combination of criteria shown in FIG. **12** can be used.

Other decision algorithms can also be used, in particular related to the level of electrical energy as calculated from the ECG spectrum. In the case of placing endovascular devices, one criterion may be that, at the location corresponding to the lower third of the SVC, the average electrical energy calculated from the endovascular ECG is twice as high as the average electrical energy calculated from the endovascular ECG at skin level or from a skin ECG in a corresponding lead, e.g., lead II.

#### Method for Placement of Central Venous Catheters

A method of placing a central venous catheter (CVC) is presented below.

1. Estimate or measure the required length of the vascular access device (CVC) for the given patient.
2. If using saline and adaptor (**200**), go to step 11; if not, proceed as follows. Insert a guidewire into the CVC and flush align the guidewire tip and the catheter tip. Measure the length of the guidewire outside the CVC. This measurement is necessary in order to be able to realign the tip of the catheter and of the guidewire after inserting the guidewire in the vasculature. After taking the measurement, for example with sterile measuring tape or with surgical thread, remove the guidewire from the CVC.
3. Gain vascular access and insert the guidewire for the estimated required length.
4. Insert the CVC over the wire such as to leave outside the CVC the length of the guidewire measured at step 1. Thus the CVC inserted over the wire and the guidewire tip are flush aligned.
5. Connect a sterile electrical adaptor to the guidewire per the instructions for use.
6. Connect the other end of the sterile electrical adapter to the ECG cable of the electrography system.
7. Check that the display of the electrography system indicates desired position of the catheter tip per the instructions for use of the electrography system: in the lower third of the SVC, at the caval-atrial junction or in the right atrium. Typically, the location of the tip of the catheter will be identifiable through the specific shape of the P-wave and of the P-wave relative to the R-wave of the electrogram and/or by the energy levels and thresholds.
8. Adjust the position of the guidewire and CVC by pulling and/or pushing them together as not to change

the flush alignment until the ECG waveform on the screen indicates that the desired position has been reached. Correlate the actual inserted length with the estimated length.

9. After the position has been reached, disconnect the electrical adaptor and remove the guidewire.
10. Secure the CVC in location.
11. Continue here if saline and adaptor (**200**) are used.
12. Gain vascular access and introduce the CVC over the guidewire as currently specified by the existing protocols.
13. Remove the guidewire.
14. Attach the sterile adaptor (**200**) to the CVC.
15. Attach the electrical connection (**234**) of the adaptor (**200**) to the ECG cable of the electrography system.
16. Fill a syringe with saline and connect it to the other end of the adaptor (**200**). Flush the catheter lumen with saline as to create a conductive saline column all way through the catheter tip.
17. Check that the ECG waveform shown on the display of the electrography system indicates desired position of the catheter tip per the instructions for use of the electrography system: in the lower third of the SVC, at the caval-atrial junction or in the right atrium. Typically, the location of the tip of the catheter will be identifiable through the specific shape of the P-wave and of the P-wave relative to the R-wave of the electrogram and/or by energy levels and thresholds.
18. Adjust the position of the CVC by pulling and/or pushing until the ECG waveform on the screen indicates that the desired position has been reached. Correlate the actual length with the estimated length.
19. After the desired position has been reached remove the syringe and the adaptor (**200**).
20. Secure the catheter.

#### Method for Placement of Implantable Ports

A method of placing the catheter piece of an implantable port is similar to the method for placing a CVC. The adaptor (**200**) should be connected to the catheter of the implantable port, and the syringe with saline must be connected to the other end of the universal adaptor. A different electrical adaptor should be connected to a syringe needle placed in the catheter of the implantable port. After reaching the desired position, the catheter should be connected to the implantable port. Method for Placement of Peripherally Inserted Central Catheters Open and Closed Ended

Both open-ended and closed-ended peripherally inserted central catheters (PICC) can be placed as described herein, and the method of PICC placement is similar to the one of placing CVCs. The inventive steering mechanism described herein can be used to bend the tip of the PICC in case the catheter fails to advance in the desired direction.

#### Method for Placement of Hemodialysis Catheters

A method for placing hemodialysis catheters is similar to the method introduced herein for placing CVCs. The inventive steering mechanism described herein can be used to bend the tip of the hemodialysis catheter in case the catheter fails to advance in the desired direction. Two different guidewires with adaptors (**220**) can be used for each of the lumens of the hemodialysis catheter as to guide placement of one lumen into the right atrium and of the other lumen at the caval-atrial junction using the electrography system. Each of the lumens of the hemodialysis catheter can be placed independently in sequence or at the same time by connecting the adaptors (**220**) of each of the lumens with different electrodes of the ECG cable of the electrography system.

### Method for Placing Central Venous Access Devices in Patients with Arrhythmias

Traditionally, patients with arrhythmias have been excluded from procedures of guiding central venous lines placement using the endovascular ECG method because of the lack of visible changes in the shape of the P-wave. The energy criteria for the P-wave analysis described herein can be used to guide the placement of central venous access devices in patients with arrhythmias. In arrhythmia patients, the electrical signals generated by the sino-atrial node have a certain degree of randomness, such that they are not synchronized in order to produce a consistent P-wave. Nevertheless, as previous studies have shown, the electrical activity of the sino-atrial node exists and generates electrical energy of intensities typical to the proximity of the sino-atrial node. In one embodiment, the algorithm uses the energy as measured from the endovascular electrogram in order to map certain location in the vasculature. As such, this algorithm can be used to guide placement in patients with arrhythmias when only the electrical energy is indicative of location but not the shape of the P-wave.

### Method for Monitoring Tip Location and Certain Aspects of the Electrical Activity of the Heart

Certain aspects of the electrical activity of the heart can be monitored continuously or intermittently using the devices introduced herein. Either an electrical adaptor or adaptor (200) connected to the electrography system can be used for monitoring. The electrical adaptor can be connected to any stylet or other conductive member introduced in any venous access device or in any arterial device. Adapter (200) can also be connected to any venous or arterial line as long as the infusion of a conductive solution, e.g., saline is possible. Adapter (200) can also be used when electrically conductive fluids are inserted in the body using an infusion pump. Monitoring the tip location and/or certain aspects of the electrical activity of the heart can be performed in a number of clinical situations.

1. Adaptor (200) can be attached to a number of central venous devices post insertion, e.g., at bedside and/or in home care situations: PICCs, CVC, hemodialysis catheters. By connecting the adaptor to such a catheter and to an electrography system according to the present invention and by injecting saline into the catheter, the location of the tip of the catheter can be confirmed and/or certain electrical activity of the heart can be monitored during the time the adaptor is connected by using methods similar to those introduced above in the present inventions.
2. Adaptor (200) can be connected to an arterial line between the arterial line and the other devices connected to the arterial line. The blood present in the arterial line and in the universal adaptor ensures the electrical connection between the blood and the electrography system. Thus the electrical activity of the heart can be continuously monitored. This is particularly important in the case of monitoring the preload changes which translate in changes of the electrical energy of the heart during the S-T segment of the ECG waveform.
3. Monitoring of the tip location and of the electrical activity of the heart can also be achieved by using the electrography system and connecting the adaptor (200) between a central venous line and a pressure measuring system while performing central venous pressure measurements.
4. In the case of an implanted port, a needle can be inserted into the port chamber and the catheter can be

flushed with saline using a syringe filled with saline. An electrical adaptor can be attached to the needle and to the electrography system. The detected electrogram signal will contain information from the skin level where the needle is in contact with the skin and from the tip of the catheter through the injected saline column. Since the impedance of the path to the catheter tip is lower than the one to the skin, the detected signal contains both components, i.e., at the skin level and at the tip of the catheter. By subtracting the skin level signal, the signal at the tip of the catheter can be estimated and thus the tip position and certain electrical activity of the heart according to the algorithms described in the present invention.

FIG. 13 illustrates the cardiac conduction system of the heart, while FIG. 14 illustrates electrical signal propagation in the conduction system of the heart.

These figures illustrate the conductive mechanism of the heart, which explains why the electrical energy distribution within the heart as measured is indicative of specific locations within the heart. Accordingly, local electrical signals, behaviors and energy concentrations can be measured and locations within the heart and blood vessel can be determined more accurately; local heart conditions can also be described more accurately.

The conduction system of the heart begins with the heart's dominant pacemaker, the sino-atrial node (1310). The intrinsic rate of the SA node is 60 to 100 beats/minute. When an impulse leaves the SA node, it travels through the atria along the Bachmann's bundle (1350) and the inter-nodal pathways, on its way to the atrioventricular (AV) node (1320) and ventricles. After the impulse passes through the AV node, it travels to the ventricles, first down to the bundle of His (1330) then along the bundle branches and finally down to the Purkinje fibers (1340). Pacemaker cells in the junctional tissue and Purkinje fibers on the ventricles normally remain dormant because they receive impulses from the SA node. They initiate an impulse only they do not receive one from the SA node. The intrinsic rate of the AV junction is 40 to 60 beats/minute, the intrinsic rate of the ventricles 20 to 40 beats/minute. The different propagation speeds of the electrical impulses are shown in FIG. 14. From the SA node (1410) the impulses propagate through the atrial muscle (1420) and through the ventricular muscle (1460) at app. 0.5 ms, through the bundle branches (1440) and (1450) at app. 2 m/sec, through the Purkinje fibers (1470) at app 4 m/s and through the AV node (1430) at app. 0.05 m/s.

The electrical signals and the electrical energy distribution are advantageously used to identify the proximity of the sino-atrial node and right atrial electrical activity even in the cases of arrhythmia, i.e., in the absence of a coherent P-wave measured by standard skin electrocardiogram. While in some cases of arrhythmia random electrical signal generated in the right atrium is not coherent enough to propagate through the body to the skin, the electrical energy is still present in the right atrium and can be detected by local endovascular measurements as a non-coherent P-wave, i.e., as significant electrical activity in the P-segment of the ECG waveform. Energy measurements are also less sensitive to some local abnormalities in impulse conduction: altered automaticity (arrhythmias), retrograde conduction of impulses, reentry abnormalities.

The electrical signals and the electrical energy distribution are also advantageously used to quantify heart functionality, e.g., preload which is related to the depolarization and extension of the heart muscle.

The electrical signals and the electrical energy distribution are also advantageously used to guide guidewires and guiding catheters through the aorta into the left heart. This method is useful in simplifying the access to the left atrium and to the coronary arteries and in reducing the amount of contrast and radiation needed to guide endovascular devices to those locations. In a different application, the inventive apparatus can also be used to guide catheters, e.g. Swan-Ganz through the right ventricle into the pulmonary artery. Other endovascular devices can be guided and be used to measure endovascular electrical activity in other locations of the cardiovascular system which are identifiable by the cardiograms measured with the new apparatus introduced in the present invention.

FIG. 15 illustrates electrical activity in the cardiovascular system due to neuronal control system. Several paths of conduction are related to the mechanism of control of heart (1530) and blood vessel (1520) activity: receptors (1510), e.g., pressure receptors transmit information related to the state of the blood vessels and to the state of the heart to the nervous system through the Medullary centers (1500). The hypothalamus (1540) and the higher centers (1550) are involved in processing and reacting to the information received from the sensors/receptors. In turn they send impulses (1560) back to blood vessels and the heart. By measuring electrical activity related to the control system, information regarding heart conditions can be obtained which could not have been obtained previously.

The many features and advantages of the invention are apparent from the detailed specification, and, thus, it is intended by the appended claims to cover all such features and advantages of the invention which fall within the true spirit and scope of the invention. Further, since numerous modifications and variations will readily occur to those skilled in the art, it is not desired to limit the invention to the exact construction and operation illustrated and described, and, accordingly, all suitable modifications and equivalents may be resorted to that fall within the scope of the invention.

What is claimed is:

1. A computer-based method for positioning an endovascular device in or near a heart using electrocardiogram (ECG) signals, comprising:

receiving an endovascular ECG signal, associated with the endovascular device, including a plurality of waveforms, each waveform having at least a P-wave component;

processing the endovascular ECG signal, over a plurality of predetermined time periods, to calculate a P-wave amplitude and a spectral power for each predetermined time period;

determining a maximum P-wave amplitude from a plurality of P-wave amplitudes resulting from processing the endovascular ECG signal over the plurality of predetermined time periods, and an associated maximum spectral power from a plurality of spectral powers resulting from processing the endovascular ECG signal over the plurality of predetermined time periods;

associating the maximum P-wave amplitude and the maximum spectral power with a predetermined location in or near the heart;

calculating a location of the endovascular device, for each predetermined time period, based on a ratio of the P-wave amplitude to the maximum P-wave amplitude and a ratio of the spectral power to the maximum spectral power; and

displaying the location of the endovascular device to a user for each predetermined time period.

2. The computer-based method according to claim 1, wherein the P-wave amplitude for each predetermined time period is a peak-to-peak value, and the maximum P-wave amplitude is a peak-to-peak value.

3. The computer-based method according to claim 2, wherein processing the endovascular ECG signal includes determining a polarity for each P-wave amplitude, for each predetermined time period, and calculating the location of the endovascular device is also based on the P-wave polarity for each predetermined time period.

4. The computer-based method according to claim 3, wherein the predetermined location is a caval-atrial junction.

5. The computer-based method according to claim 4, wherein the location of the endovascular device is an upper portion of a superior vena cava if the ratio of the P-wave amplitude to the maximum P-wave amplitude is less than 0.4, the ratio of the spectral power to the maximum spectral power is less than 0.4, and the P-wave polarity is unipolar.

6. The computer-based method according to claim 5, wherein the location of the endovascular device is a lower third of the superior vena cava if the ratio of the P-wave amplitude to the maximum P-wave amplitude is between 0.4 and 0.6, the ratio of the spectral power to the maximum spectral power is between 0.4 and 0.6, and the P-wave polarity is unipolar.

7. The computer-based method according to claim 6, further comprising: calculating an R-wave amplitude for each predetermined time period when processing the endovascular ECG signal, wherein the location of the endovascular device is the caval-atrial junction if the ratio of the P-wave amplitude to the maximum P-wave amplitude is greater than 0.9, the ratio of the spectral power to the maximum spectral power is greater than 0.9, and the P-wave amplitude is greater than the R-wave amplitude.

8. The computer-based method according to claim 7, wherein the location of the endovascular device is a right atrium if the ratio of the spectral power to the maximum spectral power is between 0.6 and 0.9, and the P-wave polarity is bipolar.

9. The computer-based method according to claim 8, wherein the location of the endovascular device is an upper third of an inferior vena cava if the ratio of the P-wave amplitude to the maximum P-wave amplitude is between 0.4 and 0.6, the ratio of the spectral power to the maximum spectral power is between 0.4 and 0.6, and the P-wave polarity is unipolar with reversed polarity.

10. The computer-based method according to claim 4, wherein the endovascular device is a central venous catheter coupled to an adapter that includes an electrode in contact with a saline solution column exposed to a tip of the catheter, and the endovascular ECG signal is based on an electrical signal measured by the electrode.

11. The computer-based method according to claim 10, further comprising:

simultaneously receiving a skin ECG signal with the endovascular ECG signal, associated with a skin ECG lead, including a plurality of waveforms, each waveform having at least a P-wave component;

processing the skin ECG signal, over the plurality of predetermined time periods, to calculate a skin P-wave amplitude and a skin spectral power for each predetermined time period;

determining a maximum skin P-wave amplitude from a plurality of skin P-wave amplitudes resulting from processing the skin ECG signal over the plurality of predetermined time periods, and an associated maximum skin spectral power from a plurality of skin

25

spectral powers resulting from processing the skin ECG signal over the plurality of predetermined time periods; associating the maximum skin P-wave amplitude and the maximum skin spectral power with the predetermined location in or near the heart; and

calculating the location of the endovascular device, for each predetermined time period, based on a ratio of the skin P-wave amplitude to the maximum skin P-wave amplitude and a ratio of the skin spectral power to the maximum skin spectral power.

12. The computer-based method according to claim 11, wherein the location of the endovascular device is an upper portion of a superior vena cava if the ratio of the skin P-wave amplitude to the maximum skin P-wave amplitude is between 0.9 and 1.2, the ratio of the skin spectral power to the maximum skin spectral power is between 0.9 and 1.2, and the P wave polarity is unipolar.

13. The computer-based method according to claim 12, wherein the location of the endovascular device is a lower third of the superior vena cava if the ratio of the skin P-wave amplitude to the maximum skin P-wave amplitude is between 1.5 and 2.0, the ratio of the skin spectral power to the maximum skin spectral power is between 1.5 and 2.0, and the P-wave polarity is unipolar.

26

14. The computer-based method according to claim 13, further comprising: calculating an R-wave amplitude for each predetermined time period when processing the skin ECG signal, wherein the location of the endovascular device is the caval-atrial junction if the ratio of the skin P-wave amplitude to the maximum skin P-wave amplitude is greater than 2.5, the ratio of the skin spectral power to the maximum skin spectral power is greater than 2.59, and the skin P-wave amplitude is greater than the skin R-wave amplitude.

15. The computer-based method according to claim 14, wherein the location of the endovascular device is a right atrium if the ratio of the skin spectral power to the maximum skin spectral power is between 2.0 and 2.5, and a skin P-wave polarity determined for each skin P-wave amplitude for each predetermined time period is bipolar.

16. The computer-based method according to claim 15, wherein the location of the endovascular device is an upper third of an inferior vena cava if the ratio of the skin P-wave amplitude to the maximum skin P-wave amplitude is between 0.9 and 1.2, the ratio of the skin spectral power to the maximum skin spectral power is between 0.9 and 1.2, and the P-wave polarity is unipolar with reversed polarity.

\* \* \* \* \*

专利名称(译)	用于血管内电图的装置和方法		
公开(公告)号	<a href="#">US10349857</a>	公开(公告)日	2019-07-16
申请号	US15/266977	申请日	2016-09-15
[标]申请(专利权)人(译)	巴德阿克塞斯系统股份有限公司		
申请(专利权)人(译)	BARD接入系统, INC.		
当前申请(专利权)人(译)	BARD接入系统, INC.		
[标]发明人	GRUNWALD SORIN		
发明人	GRUNWALD, SORIN		
IPC分类号	A61N1/05 A61B5/0452 A61B5/04 A61B34/20 A61B5/00 A61B5/042 A61B5/06 A61M25/00 A61M25/01 A61M25/09 A61M39/10		
CPC分类号	A61B5/0452 A61B5/04017 A61B5/06 A61B5/065 A61B5/742 A61B34/20 A61M25/0026 A61M25/0097 A61M25/0102 A61M25/0147 A61N1/056 A61B5/042 A61M2039/1022 A61B5/7203 A61B5/726 A61M25/0194 A61M2025/09116		
代理机构(译)	鲁坦和塔克LLP		
优先权	61/213474 2009-06-12 US 61/272025 2009-08-10 US		
其他公开文献	US20170000367A1		
外部链接	<a href="#">Espacenet</a>		

摘要(译)

一种使用心电图 ( ECG ) 信号将血管内装置定位在心脏中或心脏附近的方法。该方法包括接收包括多个波形的血管内ECG信号, 处理血管内ECG信号以计算每个预定时间段的P波幅度和频谱功率, 确定最大P波幅度和相关的最大频谱功率, 将最大P波幅度和最大频谱功率与心脏中或心脏附近的预定位置相关联, 基于P波幅度与最大P波幅度的比率以及频谱功率的比率来计算位置最大光谱功率, 并向用户显示位置。

