



US009162074B2

(12) **United States Patent**  
**Allavatam et al.**

(10) **Patent No.:** **US 9,162,074 B2**  
(45) **Date of Patent:** **Oct. 20, 2015**

(54) **METHODS AND DEVICES FOR ACCURATELY CLASSIFYING CARDIAC ACTIVITY**

(71) Applicant: **CAMERON HEALTH, INC.**, St. Paul, MN (US)

(72) Inventors: **Venugopal Allavatam**, Maple Grove, MN (US); **Surekha Palreddy**, Maplewood, MN (US); **Rick Sanghera**, San Clemente, CA (US); **Jay A. Warren**, San Juan Capistrano, CA (US)

(73) Assignee: **CAMERON HEALTH, INC.**, St. Paul, MN (US)

(\* ) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

(21) Appl. No.: **14/551,444**

(22) Filed: **Nov. 24, 2014**

(65) **Prior Publication Data**

US 2015/0088214 A1 Mar. 26, 2015

**Related U.S. Application Data**

(62) Division of application No. 14/096,285, filed on Dec. 4, 2013, now Pat. No. 8,929,977, which is a division of

(Continued)

(51) **Int. Cl.**

**A61B 5/0452** (2006.01)

**A61N 1/39** (2006.01)

(Continued)

(52) **U.S. Cl.**

CPC ..... **A61N 1/3987** (2013.01); **A61B 5/04014** (2013.01); **A61B 5/0452** (2013.01); **A61N 1/3704** (2013.01); **A61N 1/3956** (2013.01); **A61B 5/726** (2013.01)

(58) **Field of Classification Search**

CPC ..... **A61B 5/0452**; **A61B 5/7203**; **A61B 5/04525**; **A61B 5/0468**; **A61B 5/7221**

See application file for complete search history.

(56) **References Cited**

**U.S. PATENT DOCUMENTS**

4,184,493 A 1/1980 Langer et al.  
4,300,567 A 11/1981 Kolenik et al.

(Continued)

**FOREIGN PATENT DOCUMENTS**

AU 2009244153 B2 3/2014  
CN 1819855 A 8/2006

(Continued)

**OTHER PUBLICATIONS**

All non-patent literature documents and foreign patent documents have been previously uploaded in parent U.S. Appl. No. 12/399,914, filed Mar. 6, 2009; U.S. Appl. No. 12/637,438, filed Dec. 14, 2009; U.S. Appl. No. 13/436,398, filed Mar. 30, 2012; U.S. Appl. No. 13/607,168, filed Sep. 7, 2012; U.S. Appl. No. 14/057,416, filed Oct. 18, 2013, and U.S. Appl. No. 14/096,285, filed Dec. 4, 2013.

(Continued)


*Primary Examiner* — Eric D. Bertram

(74) *Attorney, Agent, or Firm* — Seager, Tufte & Wickhem LLP

(57) **ABSTRACT**

Methods, systems, and devices for signal analysis in an implanted cardiac monitoring and treatment device such as an implantable cardioverter defibrillator. In illustrative examples, captured data including detected events is analyzed to identify likely overdetection of cardiac events. In some illustrative examples, when overdetection is identified, data may be modified to correct for overdetection, to reduce the impact of overdetection, or to ignore overdetection. New methods for organizing the use of morphology and rate analysis in an overall architecture for rhythm classification and cardiac signal analysis are also discussed.

**7 Claims, 26 Drawing Sheets**



**Related U.S. Application Data**

- application No. 13/436,398, filed on Mar. 30, 2012, now Pat. No. 8,626,280, which is a division of application No. 12/399,914, filed on Mar. 6, 2009, now Pat. No. 8,160,686.
- (60) Provisional application No. 61/051,332, filed on May 7, 2008, provisional application No. 61/034,938, filed on Mar. 7, 2008.
- (51) **Int. Cl.**  
*A61N 1/37* (2006.01)  
*A61B 5/04* (2006.01)  
*A61B 5/00* (2006.01)
- (56) **References Cited**

## U.S. PATENT DOCUMENTS

4,407,288 A	10/1983	Langer et al.	5,876,350 A	3/1999	Lo et al.
4,450,527 A	5/1984	Sramek	5,891,048 A	4/1999	Nigam et al.
4,457,315 A	7/1984	Bennish	5,991,657 A	11/1999	Kim
4,589,420 A	5/1986	Adams et al.	6,029,086 A	2/2000	Kim et al.
4,595,009 A	6/1986	Leinders	6,041,251 A	3/2000	Kim et al.
4,679,144 A	7/1987	Cox et al.	6,047,210 A	4/2000	Kim et al.
4,693,253 A	9/1987	Adams	6,052,617 A	4/2000	Kim
4,750,494 A	6/1988	King	6,058,328 A	5/2000	Levine et al.
4,779,617 A	10/1988	Whigham	6,095,987 A	8/2000	Shmulewitz et al.
4,940,054 A	7/1990	Grevis et al.	6,115,628 A	9/2000	Stadler et al.
4,979,110 A	12/1990	Albrecht et al.	6,144,879 A	11/2000	Gray
4,989,602 A	2/1991	Sholder et al.	6,148,230 A	11/2000	KenKnight
5,000,189 A	3/1991	Throne et al.	6,223,078 B1	4/2001	Marcovecchio
5,105,810 A	4/1992	Collins et al.	6,230,055 B1	5/2001	Sun et al.
5,117,824 A	6/1992	Keimel et al.	6,236,882 B1	5/2001	Lee et al.
5,184,616 A	2/1993	Weiss	6,240,313 B1	5/2001	Esler
5,193,535 A	3/1993	Bardy et al.	6,266,554 B1	7/2001	Hsu et al.
5,215,098 A	6/1993	Steinhaus et al.	6,280,462 B1	8/2001	Hauser et al.
5,217,021 A	6/1993	Steinhaus et al.	6,308,095 B1	10/2001	Hsu et al.
5,240,009 A	8/1993	Williams	6,334,071 B1	12/2001	Lu
5,271,411 A	12/1993	Ripley et al.	6,377,844 B1	4/2002	Graen
5,273,049 A	12/1993	Steinhaus et al.	6,381,493 B1	4/2002	Stadler et al.
5,280,792 A	1/1994	Leong et al.	6,393,316 B1	5/2002	Gillberg et al.
5,299,119 A	3/1994	Kraf et al.	6,397,100 B2	5/2002	Stadler et al.
5,313,953 A	5/1994	Yomtov et al.	6,411,844 B1	6/2002	Kroll et al.
5,331,966 A	7/1994	Bennett et al.	6,438,410 B2	8/2002	Hsu et al.
5,339,820 A	8/1994	Henry et al.	6,449,503 B1	9/2002	Hsu
5,342,402 A	8/1994	Olson et al.	6,493,579 B1	12/2002	Gilkerson et al.
5,342,407 A	8/1994	Dahl et al.	6,493,584 B1	12/2002	Lu
5,351,969 A	10/1994	Smith et al.	6,505,068 B2	1/2003	Bonnet et al.
5,376,104 A	12/1994	Sakai et al.	6,516,225 B1	2/2003	Florio
5,400,795 A	3/1995	Murphy et al.	6,561,984 B1	5/2003	Turcott
5,423,326 A	6/1995	Wang et al.	6,567,691 B1	5/2003	Stadler
5,447,519 A	9/1995	Peterson	6,574,505 B1	6/2003	Warren
5,464,431 A	11/1995	Adams et al.	6,575,912 B1	6/2003	Turcott
5,470,342 A	11/1995	Mann et al.	6,587,720 B2	7/2003	Hsu et al.
5,486,199 A	1/1996	Kim et al.	6,625,490 B1	9/2003	McClure et al.
5,513,644 A	5/1996	McClure et al.	6,643,549 B1	11/2003	Bradley et al.
5,522,852 A	6/1996	White et al.	6,647,292 B1	11/2003	Bardy et al.
5,534,019 A	7/1996	Paspa	6,684,100 B1	1/2004	Sweeney et al.
5,545,186 A	8/1996	Olson et al.	6,699,200 B2	3/2004	Cao et al.
5,558,098 A	9/1996	Fain	6,708,058 B2	3/2004	Kim et al.
5,564,430 A	10/1996	Jacobson et al.	6,708,062 B2	3/2004	Erickson et al.
5,607,455 A	3/1997	Armstrong	6,721,597 B1	4/2004	Bardy et al.
5,620,466 A	4/1997	Haefner et al.	6,728,572 B2	4/2004	Hsu et al.
5,658,317 A	8/1997	Haefner et al.	6,731,978 B2	5/2004	Olson et al.
5,676,690 A	10/1997	Noren	6,745,068 B2	6/2004	Koyrakh et al.
5,685,315 A	11/1997	McClure et al.	6,754,528 B2	6/2004	Bardy et al.
5,702,425 A	12/1997	Wickham	6,889,079 B2	5/2005	Bocek et al.
5,709,215 A	1/1998	Perttu et al.	6,892,092 B2	5/2005	Palreddy et al.
5,755,738 A	5/1998	Kim et al.	6,909,916 B2	6/2005	Spinelli et al.
5,755,739 A *	5/1998	Sun et al. .... 607/14	6,950,702 B2	9/2005	Sweeney
5,776,168 A	7/1998	Gunderson	7,016,730 B2	3/2006	Ternes
5,779,645 A	7/1998	Olson et al.	7,020,523 B1	3/2006	Lu et al.
5,817,134 A	10/1998	Greenhut et al.	7,027,856 B2	4/2006	Zhou et al.
5,827,197 A	10/1998	Bocek et al.	7,027,858 B2	4/2006	Cao et al.
5,857,977 A	1/1999	Caswell et al.	7,027,862 B2	4/2006	Dahl et al.
			7,031,764 B2	4/2006	Schwartz et al.
			7,062,314 B2	6/2006	Zhu et al.
			7,062,315 B2	6/2006	Koyrakh et al.
			7,062,322 B2	6/2006	Stadler et al.
			7,076,289 B2	7/2006	Sarkar et al.
			7,085,599 B2	8/2006	Kim et al.
			7,103,412 B1	9/2006	Kroll
			7,117,035 B2	10/2006	Wagner et al.
			7,123,954 B2	10/2006	Narayan et al.
			7,149,575 B2	12/2006	Ostroff et al.
			7,162,301 B2	1/2007	Kim et al.
			7,167,747 B2	1/2007	Gunderson et al.
			7,184,815 B2	2/2007	Kim et al.
			7,184,818 B2	2/2007	Kim et al.
			7,191,004 B2	3/2007	Kim et al.
			7,194,302 B2	3/2007	Bardy et al.
			7,218,966 B2	5/2007	Haefner
			7,236,819 B2	6/2007	Brockway et al.
			7,248,921 B2	7/2007	Palreddy et al.
			7,266,409 B2	9/2007	Gunderson
			7,283,863 B2	10/2007	Gunderson et al.
			7,302,294 B2	11/2007	Kamath et al.

(56)

## References Cited

## U.S. PATENT DOCUMENTS

7,330,757	B2	2/2008	Ostroff et al.
7,346,392	B2	3/2008	KenKnight
7,376,458	B2	5/2008	Palreddy et al.
7,379,772	B2	5/2008	Bardy et al.
7,386,342	B1	6/2008	Falkenberg et al.
7,392,085	B2	6/2008	Warren et al.
7,444,182	B2	10/2008	Ostroff et al.
7,447,540	B1	11/2008	Nabutovsky et al.
7,467,009	B2	12/2008	Palreddy et al.
7,477,935	B2	1/2009	Palreddy et al.
7,496,408	B2	2/2009	Ghanem et al.
7,496,409	B2	2/2009	Greenhut et al.
7,499,750	B2	3/2009	Haefner et al.
7,522,959	B2	4/2009	Hauser et al.
7,546,159	B1	6/2009	Nabutovsky et al.
7,555,335	B2	6/2009	Kamath et al.
7,559,900	B2	7/2009	Gillberg
7,567,835	B2	7/2009	Gunderson et al.
7,570,997	B2	8/2009	Lovett et al.
7,593,771	B2	9/2009	Yonce et al.
7,623,913	B2	11/2009	Phillips
7,623,916	B2	11/2009	Julian
7,655,014	B2	2/2010	Ko et al.
7,682,316	B2	3/2010	Anderson et al.
7,684,864	B2	3/2010	Olson et al.
7,715,906	B2	5/2010	Krause et al.
7,734,345	B2	6/2010	Cinbis
7,761,142	B2	7/2010	Ghanem et al.
7,774,049	B2	8/2010	Ghanem et al.
7,783,354	B2	8/2010	Gunderson
7,792,571	B2	9/2010	Sweeney et al.
7,797,036	B2	9/2010	Zhang et al.
7,801,594	B1	9/2010	Higham
7,865,233	B2	1/2011	Haefner
7,894,894	B2	2/2011	Stadler et al.
7,904,142	B2	3/2011	Kim et al.
7,904,153	B2	3/2011	Greenhut et al.
7,907,993	B2	3/2011	Ghanem et al.
8,160,686	B2	4/2012	Allavatam et al.
8,160,687	B2	4/2012	Warren et al.
8,265,749	B2	9/2012	Allavatam et al.
8,565,878	B2	10/2013	Allavatam et al.
8,588,896	B2	11/2013	Allavatam et al.
8,600,489	B2	12/2013	Warren et al.
8,626,280	B2	1/2014	Allavatam et al.
2003/0204215	A1	10/2003	Gunderson et al.
2004/0049120	A1	3/2004	Cao et al.
2004/0215239	A1	10/2004	Favet et al.
2004/0215240	A1	10/2004	Lovett et al.
2004/0220628	A1	11/2004	Wagner
2004/0230229	A1	11/2004	Lovett et al.
2004/0230233	A1	11/2004	Gunderson et al.
2005/0107838	A1	5/2005	Lovett et al.
2005/0131464	A1	6/2005	Heinrich et al.
2005/0154421	A1	7/2005	Ousdigian
2006/0116595	A1	6/2006	Palreddy et al.
2006/0116725	A1	6/2006	Palreddy et al.
2006/0122676	A1	6/2006	Ko et al.
2006/0167502	A1	7/2006	Haefner
2006/0167503	A1	7/2006	Warren et al.
2006/0167504	A1	7/2006	Warren et al.
2006/0235476	A1	10/2006	Gunderson et al.
2006/0241701	A1	10/2006	Markowitz et al.
2007/0032829	A1	2/2007	Ostroff
2007/0049975	A1	3/2007	Cates et al.
2007/0135847	A1	6/2007	Kenknight
2007/0142736	A1	6/2007	Cazares et al.
2007/0156190	A1	7/2007	Cinbis
2007/0179539	A1	8/2007	Degroot et al.
2007/0179540	A1	8/2007	Stegemann et al.
2007/0232944	A1	10/2007	Ghanem et al.
2007/0232945	A1	10/2007	Kleckner et al.
2007/0232948	A1	10/2007	Stadler et al.
2007/0233198	A1	10/2007	Ghanem et al.
2007/0244521	A1	10/2007	Bornzin et al.
2007/0255151	A1	11/2007	Struble et al.
2007/0276445	A1	11/2007	Sanghera et al.
2008/0015647	A1	1/2008	Palreddy et al.
2008/0077030	A1	3/2008	Ostroff et al.
2008/0086174	A1	4/2008	Libbus et al.
2008/0091242	A1	4/2008	Kamath et al.
2008/0132965	A1	6/2008	Ostroff et al.
2008/0161870	A1	7/2008	Gunderson
2008/0172098	A1	7/2008	Gunderson
2008/0183085	A1	7/2008	Van Oort et al.
2008/0188901	A1	8/2008	Sanghera et al.
2008/0215110	A1	9/2008	Gunderson
2008/0221632	A1	9/2008	Bardy et al.
2008/0228093	A1	9/2008	Dong et al.
2008/0243200	A1	10/2008	Scinicariello et al.
2008/0262559	A1	10/2008	Zhang et al.
2008/0275516	A1	11/2008	Ghanem et al.
2008/0275517	A1	11/2008	Ghanem et al.
2008/0275519	A1	11/2008	Ghanem et al.
2008/0275521	A1	11/2008	Warren et al.
2008/0288009	A1	11/2008	Kim et al.
2009/0036788	A1	2/2009	Nabutovsky et al.
2009/0043352	A1	2/2009	Brooke et al.
2009/0054796	A1	2/2009	Sanghera et al.
2009/0054938	A1	2/2009	Ostroff et al.
2009/0093731	A1	4/2009	Palreddy et al.
2009/0156957	A1	6/2009	Linder et al.
2009/0157128	A1	6/2009	Seim et al.
2009/0157132	A1	6/2009	Linder et al.
2009/0157137	A1	6/2009	Gilkerson et al.
2009/0187227	A1	7/2009	Palreddy et al.
2009/0228057	A1	9/2009	Allavatam et al.
2009/0240157	A1	9/2009	Lian et al.
2009/0240300	A1	9/2009	Lian et al.
2009/0259271	A1	10/2009	Allavatam et al.
2010/0004713	A1	1/2010	Warren et al.
2010/0094369	A1	4/2010	Allavatam et al.
2010/0152798	A1	6/2010	Sanghera et al.
2010/0152799	A1	6/2010	Sanghera et al.
2010/0185109	A1	7/2010	Zhang et al.
2010/0331904	A1	12/2010	Warren et al.
2011/0098585	A1	4/2011	Warren et al.
2011/0098775	A1	4/2011	Allavatam et al.
2013/0006085	A1	1/2013	Allavatam et al.
2014/0046204	A1	2/2014	Allavatam et al.
2014/0046394	A1	2/2014	Allavatam et al.
2014/0046396	A1	2/2014	Warren et al.

## FOREIGN PATENT DOCUMENTS

CN	1829554	A	9/2006
CN	1915166	A	2/2007
CN	1985750	A	6/2007
CN	101065059	A	10/2007
CN	103285513	A	9/2013
CN	102083496	B	10/2013
EP	0554208	A2	8/1993
EP	1774907	A1	4/2007
EP	2313153	B1	4/2012
EP	2455132	A1	5/2012
EP	2574371	B1	6/2014
JP	1110344	A	1/1999
JP	2000023932	A	1/2000
JP	2006523505	A	10/2006
JP	2006526472	A	11/2006
JP	2007501099	A	1/2007
JP	2007510447	A	4/2007
JP	2008536633	A	9/2008
WO	2004105871	A1	12/2004
WO	2006113698	A	10/2006
WO	2009111764	A2	9/2009
WO	2009111766	A3	9/2009
WO	2009111764	A3	11/2009
WO	2009111766	A2	11/2009

(56)

**References Cited**

FOREIGN PATENT DOCUMENTS

WO 2009137726 A2 11/2009  
WO 2009137726 A3 1/2010

OTHER PUBLICATIONS

"Methods and Devices for Identifying and Correcting Overdetection of Cardiac Events", U.S. Appl. No. 61/051,332, filed May 7, 2008, 62 pgs.

"QT Interval", Wikipedia, [Online]. Retrieved from the Internet: <URL: [http://en.wikipedia.org/wiki/QT\\_interval](http://en.wikipedia.org/wiki/QT_interval)>, (Accessed May 11, 2011), 5 pgs.

Gunderson, et al., "An algorithm to Predict Implantable Cardioverter-Defibrillator Lead Failure", JACC, vol. 44, No. 9, (Nov. 2004), 1898-902.

Olson, Walter, et al., "Onset and Stability for Ventricular Tachyarrhythmia Detection in an Implantable Pacer-Cardioverter-Defibrillator", IEEE, (1987), 167-170.


Schuder, John C., "The Role of an Engineering Oriented Medical Research Group in Developing Improved Methods & Devices for Achieving Ventricular Defibrillation: The University of Missouri Experience", PACE vol. 16, Part 1, (Jan. 1993), 95-124.

Schwake, "Komplikationen mit Sonden bei 340 Patienten mit einem implantierbaren Kardioverter/Defibrillator", Z Kardiol 88, (1999), 559-565.

Swerdlow, C. D, et al., "Advanced ICD Troubleshooting: Part I", accessed and printed Jul. 7, 2009, indicates publication Jan. 9, 2006 (publication date not confirmed), [Online]. Retrieved from the Internet: <[http://www.medscape.com/viewarticle/520588\\_print](http://www.medscape.com/viewarticle/520588_print)>, (Accessed Jul. 7, 2009), 1322-46.

Throne, Robert D, et al., "A Comparison of Four New Time-Domain Techniques for Discriminating Monomorphic Ventricular Tachycardia from Sinus Rhythm Using Ventricular Waveform Morphology", IEEE Transactions on Biomedical Engineering, vol. 38, No. 6, (Jun. 1991), 561-570.

\* cited by examiner



*FIG. 1*





FIG. 2



*FIG. 3*




FIG. 4






FIG. 5



**FIG. 6A**



**FIG. 6B**





FIG. 7A



**FIG. 7B**





FIG. 8



**FIG. 9**






FIG. 10




**FIG. 11**

*First Wide Complex Rule Set*



**FIG. 12A**

*Second Wide Complex Rule Set*



**FIG. 12B**






FIG. 12D

True False Marking				
N-2	N-1		N-2	N-1
362 → [T]	[?]	Neither Rule Set Satisfied →	[T]	[T]
364 → [T]	[?]	Met Rules, Template Formed & $CWA(n-2) \leq CWA(n-1)$ →	[F]	[T]
366 → [T]	[?]	Met Rules, Any Other Score Combination or no template →	[T]	[F]
368 → [F]	[?]	Only result for n-2 = F →	[F]	[T]

**FIG. 13A**

Rate in Range, Pattern Found			
N-3	N-2	N-1	
[T]	[F]	[T]	Assign N-2 WC Overdetect Marker
Otherwise			No WC OD Marker Assigned
Rate in Range, No Pattern			
N-3	N-2	N-1	
[T]	[F]	[T]	Assign N-2 WC Suspect Event Marker
Otherwise			No WC Suspect Marker Assigned

**FIG. 13B**




FIG. 14




FIG. 15






FIG. 16



Overdetecting T-Waves



Overdetecting Wide Complexes

*FIG. 17*




FIG. 18






FIG. 20




FIG. 21




FIG. 22




FIG. 23

**1**  
**METHODS AND DEVICES FOR**  
**ACCURATELY CLASSIFYING CARDIAC**  
**ACTIVITY**

RELATED APPLICATIONS

The present application is a divisional of U.S. patent application Ser. No. 14/096,285, filed Dec. 4, 2013, and published as US Patent Application Publication Number 2014-0094868, now issued as U.S. Pat. No. 8,929,977, which is a divisional of U.S. patent application Ser. No. 13/436,398, filed Mar. 30, 2012 and published as US Patent Application Publication Number 2012-0197147, now issued as U.S. Pat. No. 8,626,280, which is a divisional of U.S. patent application Ser. No. 12/399,914, filed Mar. 6, 2009 and published as US Patent Application Publication Number 2009-0259271, now issued as U.S. Pat. No. 8,160,686, which claims the benefit of and priority to U.S. Provisional Patent Application No. 61/051,332, filed May 7, 2008 and titled METHODS AND DEVICES FOR IDENTIFYING AND CORRECTING OVERDETECTION OF CARDIAC EVENTS, the disclosures of each of which are incorporated herein by reference; U.S. patent application Ser. No. 12/399,914, now issued as U.S. Pat. No. 8,160,686, also claims the benefit of and priority to U.S. Provisional Patent Application No. 61/034,938, filed Mar. 7, 2008 and titled ACCURATE CARDIAC EVENT DETECTION IN AN IMPLANTABLE CARDIAC STIMULUS DEVICE, the disclosure of which is incorporated herein by reference.

The present application is related to U.S. patent application Ser. No. 12/399,901, filed Mar. 6, 2009, published as US Patent Application Publication Number 2009-0228057 now issued as U.S. Pat. No. 8,565,878, and titled ACCURATE CARDIAC EVENT DETECTION IN AN IMPLANTABLE CARDIAC STIMULUS DEVICE, which claims the benefit of and priority to U.S. Provisional Patent Application No. 61/034,938, filed Mar. 7, 2008, and the disclosure of which is also incorporated herein by reference. The present application is also related to U.S. patent application Ser. No. 12/637,438, filed Dec. 14, 2009 and published as US Patent Application Publication Number 2010-0094369, now issued as U.S. Pat. No. 8,265,749, which is a continuation of U.S. patent application Ser. No. 12/399,914, now issued as U.S. Pat. No. 8,160,686, claiming the benefit of and priority to U.S. 61/051,332 filed May 7, 2008 and U.S. 61/034,938 filed Mar. 7, 2008.

FIELD

The present invention relates generally to implantable medical device systems that sense and analyze cardiac signals. More particularly, the present invention relates to implantable medical devices that capture cardiac signals within an implantee's body in order to classify cardiac activity as likely benign or malignant.

BACKGROUND

Implantable cardiac devices typically sense cardiac electrical signals in an implantee and classify the implantee's cardiac rhythm as normal/benign or malignant. Illustrative malignant rhythms may include ventricular fibrillation and/or ventricular tachyarrhythmia. The accuracy with which an implantable medical device analyzes captured signals determines how well it makes therapy and other decisions.

**2**

New and/or alternative methods and devices for cardiac signal analysis are desired.

SUMMARY

Various illustrative embodiments of the present invention are directed toward improved accuracy in cardiac signal analysis by implantable medical devices. Some illustrative embodiments identify overdetection of cardiac events. Some illustrative embodiments also correct at least some captured data and use the corrected data to make operational decisions. The invention may be embodied in methods and/or devices.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a block diagram for an illustrative method of identifying overdetection and taking corrective action;

FIG. 2 is a block diagram further illustrating an example of identifying overdetection and making therapy decisions;

FIG. 3 shows an illustrative implantable medical device;

FIG. 4 is an illustration of a detection profile that may be used while detecting cardiac events in an implantable medical device;

FIG. 5 is a graphical illustration of double detection where both R and T waves are detected in each cardiac cycle;

FIGS. 6A-6B show an illustrative method of morphological analysis of the detections in FIG. 5, relative to a stored R-wave template;

FIGS. 7A-7B provide a detailed example of illustrative identification of overdetections using morphology analysis;

FIG. 8 shows an illustrative example of analysis to mark similar and dissimilar events in FIGS. 7A-7B;

FIG. 9 shows an illustrative oversensed cardiac signal having alternating long-short-long intervals;

FIG. 10 illustrates analysis of an alternating interval overdetection identification method;

FIG. 11 shows an illustrative oversensed wide QRS complex;

FIGS. 12A-12D show illustrative application of wide-complex overdetection identification rules;

FIGS. 13A-13B illustrate handling of outcomes from the rule set analysis of FIGS. 12A-12D;

FIG. 14 is a process flow diagram for an illustrative wide complex overdetection identification method;

FIG. 15 provides a graphical illustration of data analysis from detection-to-detection for illustrative True-False marking;

FIG. 16 shows an illustrative example for integration of a waveform appraisal method with morphology, alternating interval and wide complex overdetection methods;

FIG. 17 illustrates how modifications to the detection profile may fail to avoid overdetection in some circumstances;

FIGS. 18-21 provide graphical illustrations of handling of suspect and overdetection markers in a stream of captured events;

FIG. 22 is a process flow diagram for an illustrative charge confirmation method; and

FIG. 23 shows an illustrative method of analysis.

DETAILED DESCRIPTION

The following detailed description should be read with reference to the drawings. The drawings, which are not necessarily to scale, depict illustrative embodiments and are not intended to limit the scope of the invention.

Some of the following examples and explanations include references to issued patents and pending patent applications.

These references are for illustrative purposes and are not intended to limit the present invention to the particular methods or structures from those referenced patents and patent applications.

Unless implicitly required or explicitly stated, the methods below do not require any particular order of steps. It should be understood that when the following examples refer to a “current event,” in some embodiments, this means the most recently detected cardiac event is being analyzed. However, this need not be the case, and some embodiments perform analysis that is delayed by one or more detections and or a fixed period of time.

The illustrative examples below use rectified captured signals for purposes of event detection, for example, as shown in FIGS. 5, 7A (at 148), 9, 11, 12C-12D, 17 and 18. Some illustrative examples perform analysis of shape characteristics (morphology) of the captured signals using an unrectified signal, as shown, for example, by FIGS. 6A-6B, 7A, 11 and 12A-12D. Choices shown regarding use of rectified/unrectified signals are merely illustrative, and may be changed if desired.

The nomenclature used herein indicates that a signal is sensed by an implantable cardiac device system, events are detected in the sensed signal, and cardiac activity is classified by use of the detected events (detections). Rhythm classification includes the identification of malignant rhythms, such as ventricular fibrillation or certain tachyarrhythmias, for example. Implantable therapy systems make therapy/stimulus decisions in reliance upon the classification of the cardiac rhythm.

In an illustrative example, a detected event is detected by comparing received signals to a detection threshold, which is defined by a detection profile. FIGS. 4 and 17, below, provide illustrative examples of detection profiles. Some embodiments of the present invention incorporate detection profiles and associated analysis as discussed in U.S. Provisional Patent Application No. 61/034,938, entitled ACCURATE CARDIAC EVENT DETECTION IN AN IMPLANTABLE CARDIAC STIMULUS DEVICE, filed on Mar. 7, 2008. Any suitable detection profile may be used.

Detected events are separated by intervals, for example, as shown in FIG. 18 at 602. Several intervals can be used to generate an average interval across a selected number of intervals. Some examples shown below use four intervals to calculate an average interval. Some other number of intervals may be used, as desired. The detected heart rate can then be calculated using the average interval.

A cardiac electrogram includes several portions (often referenced as “waves”) that, according to well known convention, are labeled with letters including P, Q, R, S, and T, each of which corresponds to particular physiological events. It is typical to design detection algorithms to sense the R-wave, though any portion, if repeatedly detected, can be used to generate a beat rate. If morphology (shape) analysis is used in addition to heart rate, the system may capture and/or analyze the portion of the cycle that includes the Q, R and S waves, referred to as the QRS complex. Other portions of the patient’s cardiac cycle, such as the P-wave and T-wave, are often treated as artifacts that are not sought for the purpose of estimating heart rate, though this need not be the case.

Typically, for purposes of ascertaining rate each cardiac cycle is counted only once. Overdetection (such as a double or triple detection) may occur if the device declares more than one detected event within a single cardiac cycle. FIGS. 5, 7A, 9, 11, 12C-12D and 17 each show, in one form or another, overdetection. Examples include the detection of both an R-wave and a trailing T-wave (see FIGS. 5, 7A, 9 and 17) as

well as multiple detections of a wide QRS complex (see FIGS. 11, 12C-12D and 17). These examples are not intended to be exhaustive, and those skilled in the art understand that detection methods in implanted devices can be challenged by any number of variations of “normal” cardiac activity. For example, a P-wave may be detected and followed by detection of a trailing part of the QRS or a T-wave from the same cardiac cycle. Overdetection may also occur if noise causes an event to be declared when no cardiac event has taken place, for example, due to external therapy or noise, pacing artifact, skeletal muscle noise, electro-therapy, etc.

Overdetection can lead to overcounting of cardiac cycles. For example, if one cardiac cycle takes place and a detection algorithm declares multiple detected events, overdetection has occurred. If the heart rate is then calculated by counting each of these detections, overcounting occurs. Calculated heart rates may be used alone or in combination with other factors to classify cardiac rhythms as malignant or benign. Overcounting in reliance on overdetection events can result in erroneously high rate calculation. Miscalculation of heart rate can lead to incorrect rhythm classification and therapy decisions. Some embodiments are directed to identifying overdetection and/or correcting affiliated data.

FIG. 1 is a process flow diagram for an illustrative method of identifying overdetection and taking corrective action. The illustrative method begins with event detection 10, where the received cardiac signal is captured and compared to a detection threshold until the received signal crosses the detection threshold, resulting in declaration of a detected event. FIGS. 4-5 provide illustration of detection step 10. An additional detection profile example is shown in FIG. 17 as well.

Next, the method performs an overdetection identification step 12. This may include one or more of several analysis methods including, as illustratively shown, morphology analysis 14, interval analysis 16 and wide QRS analysis 18. FIGS. 6A-6B, 7A-7B and 8 show illustrative morphology analysis 14 as part of overdetection identification 12. FIGS. 9-10 show illustrative interval analysis 16 as part of overdetection identification 12. FIGS. 11, 12A-12D, 13A-13B, and 14-15 show illustrative wide QRS analysis 18 as part of overdetection identification 12. FIG. 16 shows an example in which calculated beat rate is used to select from several overdetection identification methods 14, 16, 18.

Following overdetection identification 12, if one or more overdetections are identified, the method corrects data, as shown at 20. FIGS. 18-21 show illustrative data correction methods that can be performed in step 20. If no data correction is needed at step 20, the method may simply go to the next step.

Finally, the method includes a therapy decision, as shown at 22. A therapy decision 22 may classify a cardiac rhythm of the implantee. The therapy decision 22 may incorporate additional methods such as charge confirmation shown in FIG. 22. The method then iterates to event detection 10, as indicated by line 24.

The therapy decision 22 may include one or more of several forms of analysis. In one illustrative example, individual detected events are marked as shockable or non-shockable and an X-out-of-Y counter is maintained to determine whether the overall cardiac rhythm merits therapy. The marking of individual events as shockable or non-shockable may take several forms, including rate-based and/or morphology based determinations, or combinations thereof. Some illustrative factors and combinations of factors that may be considered are discussed in U.S. Pat. No. 6,754,528, entitled APPARATUS AND METHOD OF ARRHYTHMIA DETECTION IN A SUBCUTANEOUS IMPLANTABLE

CARDIOVERTER/DEFIBRILLATOR, and U.S. Pat. No. 7,330,757 entitled METHOD FOR DISCRIMINATING BETWEEN VENTRICULAR AND SUPRAVENTRICULAR ARRHYTHMIAS.

Therapy decision **22** may also take into account the persistence of a malignant condition. Some illustrative examples are shown in US Patent Application Publication Number 2006/0167503, now issued as U.S. Pat. No. 8,160,697, titled METHOD FOR ADAPTING CHARGE INITIATION FOR AN IMPLANTABLE CARDIOVERTER-DEFIBRILLATOR. Other methods may be used as a part of the therapy decision **22**. A detailed example using multiple rate zones for identifying shockable events in the therapy decision **22** is further discussed below.

The method of FIG. 1 includes over detection identification **12** and data correction **20**. These steps are designed to improve classification outcomes. The examples below provide details for implementing these steps in some illustrative embodiments.

FIG. 2 is a process flow diagram further illustrating an example of identifying over detection and making therapy decisions. The method **30** provides an example which incorporates each of several different over detection identification steps, as well as additional analysis of captured data for waveform appraisal. The illustrative method begins with the declaration of a new detected event, as shown at **32** (again reference is made to FIGS. 4-5 and/or **17** to show detection threshold usage in step **32**).

The detected event undergoes waveform appraisal as indicated at **34**. Waveform appraisal **34** analyzes data captured in association with the detected event to ensure the detection is cardiac in origin. Waveform appraisal can mark detected events having significant noise as suspect events. For example, noise may be identified by counting the number of zero crossings of the signal, or of the first or second derivative of the signal, during a predetermined time period. U.S. Pat. No. 7,248,921, titled METHOD AND DEVICES FOR PERFORMING CARDIAC WAVEFORM APPRAISAL provides additional detailed examples of waveform appraisal **34**.

If the detected event fails waveform appraisal **34**, it is marked as a suspect event and the method returns to step **32** and awaits a next detection threshold crossing. Once a detected event is captured that passes waveform appraisal **34**, the method **30** goes into steps for analyzing detections and identifying over detection. As shown at **36**, the illustrative method **30** determines whether a morphology template exists. A morphology template is a data set useful for morphological comparison with recently detected event(s). Morphology templates may be formed by implanted device systems or associated programmers, or may be selected or identified by medical personnel. U.S. Pat. No. 7,376,458, entitled METHOD FOR DEFINING SIGNAL TEMPLATES IN IMPLANTABLE CARDIAC DEVICES discusses some examples of template formation and/or testing. In some examples, template formation is performed by identifying a representative QRS complex that is reflective of an average or typical morphology of a cardiac cycle for an implantee.

In an illustrative example of automatic template formation, a detected event is identified and data for the detected event is stored by a device as a preliminary template. In the illustrative example, the preliminary template can be validated by comparing the stored data to data captured for a number of adjacent-in-time detected events. If the set of adjacent-in-time detected events demonstrates high correlation to one another, the preliminary template is validated and a morphology template is defined using the preliminary template. If the preliminary template cannot be validated, it is discarded. Template

formation may fail if the captured signal persistently varies, since high variability may prevent validation of a preliminary template. The query at step **36** determines whether a template is available for use in morphology over detection identification **38**.

In some systems, a morphology template will always exist. For example, some embodiments allow a physician to select a representative beat during implantation or during a telemetry session as a morphology template, or a representative template may be selected from a library of known templates. If so, step **36** may be omitted.

At step **38**, the morphology of one or more detected events is analyzed to determine whether one or more detected events is likely the result of over detection. Steps as shown below with reference to FIGS. 6A-6B, 7A-7B and **8** may be performed as part of step **38**. This may include identifying alternating patterns of morphology indicating High-Low-High correlations to the morphology template.

Following step **38** (if a stored morphology template exists) or step **36** (if there is no stored morphology template), the method continues at **40**, where the measured heart rate of the implantee is considered. If the rate falls into an AI Range (short for Alternating Interval Range) the illustrative example proceeds with Alternating Interval Over detection Identification as shown at **42**. In Alternating Interval Over detection Identification **42**, the intervals between detected events are analyzed to determine whether over detection is occurring. The Alternating Interval Over detection Identification **42** method may include steps as shown below with reference to FIGS. 9-10.

Returning to step **40**, if the implantee heart rate falls into the WC Range (Wide QRS Complex range), then Wide Complex Over detection Identification methods are called, as indicated at **44**. Wide Complex Over detection Identification **44** is designed to identify over detection of wide QRS complexes, and may include the methods discussed below with reference to FIGS. 11, 12A-12D, 13A-13B and 14-15.

The AI Range and WC Range may be separate from one another, or there may be overlap of these ranges such that each of steps **42** and **44** are performed. Further discussion of the integration of these methods is set out with reference to FIG. 16, below. In yet another embodiment, each of steps **42**, **44** are performed regardless of the calculated heart rate.

In FIG. 2, following the applicable over detection identification steps **38**, **42** and/or **44**, data correction may be invoked, as shown at **46**. Data correction **46** is invoked when one or more of the over detection identification steps **38**, **42** and/or **44** identifies over detection. If no over detection is identified, data correction **46** may be bypassed.

In some examples, data correction includes recalculation of intervals between detected events by removing one or more identified over detections from analysis. For example, if an over detection is identified, then step **46** can manipulate stored data to correct for the over detection and reduce the calculated heart rate. FIGS. 18-21 further illustrate this concept in a particular series of examples.

The examples of FIGS. 18-21 buffer rate calculations from ongoing detections by waiting until an interval between two detections is "certified" before using the interval for rate calculation. In some examples, an interval is considered certified if it passes waveform appraisal **34** and the several over detection identification steps **38**, **42**, **44** without being marked as noise or as an over detected event.

Following data correction **46**, the method makes a therapy decision **48**. If no therapy is needed, the method returns to block **32**. If therapy is indicated at step **48**, then charging and therapy delivery steps can be performed, as shown at **50**.

Typically, implanted therapy devices use charging circuitry that takes a period of time to prepare the device for therapy delivery. The method may iterate several times after a charge is initiated before therapy can be delivered. The specifics of steps 48 and 50 may vary. Once therapy is indicated at 48, a system may ensure that therapy continues to be indicated until it is delivered. US Patent Application Publication Number 2006/0167503, now issued as U.S. Pat. No. 8,160,697, titled METHOD FOR ADAPTING CHARGE INITIATION FOR AN IMPLANTABLE CARDIOVERTER-DEFIBRILLATOR provides some illustrative examples of these concepts.

FIG. 3 shows an illustrative implantable medical device and implant location. More particularly, an illustrative subcutaneous-only system is shown in FIG. 3. The subcutaneous system is shown relative to a heart 60, and includes a canister 62 coupled to a lead 66. The canister 62 preferably houses operational circuitry for performing analysis of cardiac activity and for providing a therapy output. The operational circuitry may include batteries, input/output circuitry, power capacitors, a controller, memory, telemetry components, etc., as known in the art.

Electrodes are disposed at locations throughout the system including, for example, an electrode 64 on the canister 62, and electrodes 68, 70, 72 on lead 66. The electrodes 64, 68, 70, 72 may take any suitable form and can be made of any suitable material. For example, the canister electrode 64 may be an isolated button electrode or it may be a region or surface of the canister 62, and the electrodes 68, 70, 72 on lead 66 may be coil electrodes, ring electrodes, or other structures known in the art.

The electrodes 64, 68, 70, 72 define a plurality of sensing vectors such as V1, V2, V3 and, optionally, V4. If desired, one or more vectors V1, V2, V3, and V4 may be chosen as a default sensing vector, for example, as discussed in US Patent Application Publication Number 2007-0276445 titled SYSTEMS AND METHODS FOR SENSING VECTOR SELECTION IN AN IMPLANTABLE MEDICAL DEVICE. Other uses of multiple vectors are shown, for example, in U.S. Pat. No. 7,392,085 titled MULTIPLE ELECTRODE VECTORS FOR IMPLANTABLE CARDIAC TREATMENT DEVICES. Another embodiment considers posture in vector analysis, for example, as discussed in US Patent Application Publication Number 2008-0188901, now issued as U.S. Pat. No. 8,200,341, titled SENSING VECTOR SELECTION IN A CARDIAC STIMULUS DEVICE WITH POSTURAL ASSESSMENT. Multiple sensing vectors may be analyzed, sequentially or in combination, as desired.

Therapy may be applied using any chosen pair of electrodes. An illustrative example uses the can electrode 64 and the coil electrode 72 to apply therapy. Other electrode combinations may be used. Therapy may include mono-, bi- or other multi-phasic defibrillation and/or various pacing operations.

The present invention is not limited to any particular hardware, implant location or configuration. Instead, it is intended as an improvement upon any implantable cardiac system. Some illustrative examples can associate with an external programmer 74 configured to communicate with the implanted device for various purposes, including, for example and without limitation, one or more of the following: device testing; upload new/revised software; modify sensing, detection or therapy settings; determine the status of device operation, battery life, or lead integrity; and/or download data relating to the implantee's condition, prior data capture, or treatment. Any suitable communication method may be used, such as various protocols and hardware widely known in the art.

FIG. 3 omits several anatomical landmarks. The illustrative system shown may be implanted beneath the skin outside of the ribcage of the implantee. The location illustratively shown would place the canister 62 at approximately the left axilla of the implantee, level with the cardiac apex, with the lead 66 extending medially toward the xiphoid and then toward the head of the implantee along the left side of the sternum. One illustrative example uses a method/system as shown in commonly assigned US Patent Application Publication Number 2006-0122676 entitled APPARATUS AND METHOD FOR SUBCUTANEOUS ELECTRODE INSERTION, now U.S. Pat. No. 7,655,014. Other illustrative subcutaneous systems and locations are shown in commonly assigned U.S. Pat. Nos. 6,647,292, 6,721,597 and 7,149,575.

The present invention may also be embodied in systems having various implant configurations including, for example, other subcutaneous-only, vascular-only, and/or transvenous implantation configurations/locations. The canister 62 may be placed in anterior, lateral, and/or posterior positions including, without limitation, axillary, pectoral, and sub-pectoral positions, as well as placements on either the left or right side of the implantee's torso and/or in the abdomen. Entirely intravascular implantation of the system has also been proposed. The lead 66 may be placed in any of a number of suitable configurations including anterior-posterior combinations, anterior-only combinations, transvenous placement, or other vascular placements.

FIGS. 4-5 illustrate a detection profile and how its use, in given circumstances, may lead to overdetection. Referring to FIG. 4, a detection profile is shown at 80 as including a refractory period which is followed by an exponential decay. For illustrative purposes, the height of the refractory period is shown as the "Estimated Peak." The Estimated Peak is an implantable systems' estimate of the peak amplitude of captured cardiac signals. The use of Estimated Peak allows the detection profile to adapt to the amplitude of captured signals.

The decay slope of detection profile 80 uses the Estimated Peak (or, in some embodiments, a percentage of the Estimated Peak) as its starting point. The decay approaches the sensing floor over time. The sensing floor may be the ultimate floor or highest sensitivity of the system, or it may be set to a predetermined level. Multiple decays may be used, as shown in U.S. Provisional Patent Application No. 61/034,938. The decay may be exponential or may take some other shape such as a straight-line decay, stepped function, etc.

FIG. 5 shows application of the detection profile 80 from FIG. 4 to a captured signal, which is shown at 104. Refractory periods are shown in cross-hatching at 100, 106, 112, and 118. Exponential decays 102, 108, 114 follow each refractory period 100, 106, 112, 118. Where the detection profile meets the captured signal 104, a detected event is declared and a refractory period starts. Thus, when exponential decay 102 meets the captured signal 104, a detected event is declared and a refractory period 106 starts. In the example shown, overdetection occurs when the T-waves are detected, as occurs in association with refractory periods 106, 118 in addition to the R-waves associated with refractory periods 100, 112.

In the illustrative example of FIG. 5, the Estimated Peak is calculated as the average of two previous peaks. As can be seen at 120, the Estimated Peak (represented as the height of the refractory periods 100, 106, 112, 118) drops following the overdetection associated with refractory period 106, as the newly calculated Estimated peak is an average of R-wave and T-wave amplitudes. This may increase the likelihood of fur-

ther overdetection by lowering the Estimated Peak to a level that is closer to more signal peaks that represent potential sources of overdetection.

#### Morphology Overdetection Identification

Some embodiments of the present invention provide example methods to identify and correct overdetection. FIGS. 6A-6B, 7A-7B, and 8 present morphology-based approaches to identifying overdetection using correlation. For illustrative purposes, these methods are applied to the overdetection shown in FIG. 5.

Some illustrative embodiments of morphology overdetection identification identify alternating morphology patterns. For example, during overdetection, some events may correlate highly to a stored template while other events may correlate poorly (indicating overdetections), in an alternating pattern. When a sequence of comparisons yields High-Low-High correlations, the pattern may be attributed to overdetection. As shown below, the Low correlated detected events can then be marked as overdetections. An alternating sequence is one type of pattern, but other patterns may be sought instead. In another example, triple detection may be identified by the use of High-Low-Low triplets, and in yet another example, rather than a stored, static morphology template, a series of detections may be compared one to another, making each new detection a separate template. Yet another example uses a dynamic template that changes over time, for example, by integrating new detections into the template, or by averaging a plurality of previously detected events.

Referring now to FIG. 6A, correlation waveform analysis is shown. A portion of signal within the refractory period 100 in FIG. 5 is shown at 130 in defined sample window 132. FIGS. 6A-6B show the unrectified signal, while FIG. 5 shows the rectified signal. The sample window 132 defines a number of samples 134, which are shown as a continuous line for simplicity, as an understanding of "sampling" an analog signal into the digital domain is considered to be within the knowledge of those skilled in the art.

The sample window also defines the alignment of the samples 134 around a fiducial point (typically the maximum amplitude point) in the captured signal. Some illustrative methods for defining a sample window are discussed in U.S. Pat. No. 7,477,935 entitled METHOD AND APPARATUS FOR BEAT ALIGNMENT AND COMPARISON.

While some embodiments may use the refractory period to define the sample window 132, other embodiments tailor the sample window 132 using features of the template 136. In an illustrative embodiment, the template 136 can be formed by analyzing one or more detected events to identify QRS begin and end points, as well as their position relative to a fiducial point (such as the peak during refractory). These features can be used to define the stored template so it approximates the QRS complex. Other template types may be used, including, for example, data transforms and set reduction techniques. Some templates may also rely on multi-channel sensing.

The samples within the sample window 132 are compared to the stored template, which is graphically shown at 136. The specific mathematical analysis of a template comparison may vary. Morphology analysis may include, for example and without limitation, Correlation Waveform Analysis (CWA), reduced data set analysis including peak-feature-location identification and comparison, wavelet transformation, Fourier transformation, signal decomposition such as source separation, or other data analysis methods such as compression methods. For simplicity, in the following examples, reference is made to comparison in the form of correlation/CWA, with the understanding that these other analysis methods may be substituted in other illustrative embodi-

ments. CWA may take use a simplified calculation of the sum of absolute values of differences between a template and a signal under analysis, or CWA may use an approach in which the squares of differences between signal samples and template samples are calculated and used to find correlation. Simplified methods may be used to reduce computational expense.

With respect to the comparison in FIG. 6A, it can be noted that, as stated above, the signal at 130 comes from the refractory period at 100 in FIG. 5, which corresponds to the R-wave of a cardiac cycle. As a result, there is good correlation of the captured R-Wave to the morphology template.

FIG. 6B shows the signal 140 derived from samples adjacent the peak in the refractory period 106 (FIG. 5) that occurs in association with overdetection of a T-wave. As may be expected, the signal 140, as windowed at 142, displays poor correlation to the stored template 136. Thus, the accurate detection in FIG. 6A shows good correlation to the stored template, while the overdetection in FIG. 6B displays poor correlation to the stored template. FIGS. 7A-7B and 8 illustrate how these features of the overdetection in FIG. 5 may be used to identify overdetection.

Referring to FIG. 7A, a series of detections and associated refractory periods are displayed at 148, with the signal rectified. Unrectified signal is shown at 150 including detected events 152, 154, 156. For illustration, the events are numbered as shown at 148: event 156 is the N-1 event, event 154 is the N-2 event, and event 152 is the N-3 event. The event that is the most recent is shown at the far right of the event detection graphic 148. The detections 150 correspond to an R-wave 152, a trailing T-wave at 154, and another R-wave at 156. Sample windows 160, 162, 164 are defined for each detection 152, 154, 156. In the example, the fiducial point of each sample window is shown as a vertical line. The fiducial point is offset to the left of the sample windows 160, 162, 164; an offset fiducial point may be used but need not be the case.

Next, the signal samples within each sample window 160, 162, 164 are compared to a template 172, as shown at 170. The comparison outcomes are shown as percentage correlations, indicated at 174. As shown, the score for R-wave 152 is high (95%), indicating strong correlation to the template 170. This makes R-wave 152 "Similar" to the template, as indicated. Likewise, the score for R-wave 156 is high (90%), again indicating strong correlation to the template 170, thus, the "Similar" marking. However, the overdetected T-wave 154 does not correlate well to the template 170, and has a low correlation score (5%) and is marked "Dissimilar". The numbers provided in FIG. 7A at 174 are provided only for illustration and are not the result of actual computations.

Following calculation of scores at 174, the method next characterizes each score, as indicated at 182. An illustrative characterization method is shown in FIG. 8. Referring to FIG. 8, CWA is referenced, with scores provided on a scale from 0-100%. Three zones of comparison are shown at 184, 186, and 188. Scores falling within the first zone 184 are considered dissimilar from the stored template, while scores falling within the third zone 188 are considered similar to the stored template. The second zone 186 is treated as a hysteresis band in which events are marked the same as the prior event, for example, an event falling within the second zone 186 that follows an event falling in the third zone 188 would be marked "similar". In an illustrative example, the boundary between the first and second zones 184, 186 is set to about 25% correlation, while the boundary between the second and third zones is set to about 52% correlation. Other boundaries and/or forms of this analysis to mark similar and dissimilar events relative to a template may be used.

Referring back to FIG. 7A, the comparison scores **174** are characterized as shown at **182**. The second detection **154** is a T-wave and, due to a low comparison score, is marked “Dissimilar”, while the other two detections are marked as “Similar.” The “Similar” and “Dissimilar” markings are used for applying a comparison overdetection rule which is shown in FIG. 7B. The rules rely in part on the pattern shown at **190**, in which the events N-1, N-2, N-3 form a similar-dissimilar-similar pattern. There are two parts to the comparison overdetection rule:

A) As shown at **192**, an alternating pattern **190** is sought; and

B) As shown at **194**, the N-3 detection must score “High” and above the Hysteresis zone **186** in FIG. 8.

As can be appreciated from the manner in which events are marked, rule **194** effectively ensures that none of the three detections (N-1, N-2, N-3) has a correlation score that falls into the hysteresis zone **186**.

As indicated at **196**, if both rules are met, then the method marks one of the events (N-2) as a Morphology Overdetection. In the illustrative example, the analysis contemplates events N-3, N-2 and N-1. The timing of analysis (using events N-1, N-2 and N-3 but not event N) is merely illustrative, and the present invention is not limited to any particular architecture with respect to the timing of analysis of individual events.

The use of the overdetection marker is further discussed below with reference to FIGS. **18-21**. Generally speaking, the method in FIGS. **18-21** does not differentiate Morphology Overdetection from other detections, however, if desired, the treatment of overdetection(s) may vary depending upon the identifying method. In another embodiment, data relating to which type of Overdetection Analysis has identified overdetection(s) may be retained to help analyze device operation, for example, to allow refinement of the detection profile and/or the Overdetection Analysis.

In addition to the morphology analysis, interval timing may be considered. In one embodiment, the Morphology Analysis Overdetection is omitted if the intervals between the three detections are greater than a threshold, such as 500-1000 milliseconds. For example, it may be found that detections more than 800 milliseconds apart are unlikely to result from overdetection, or that an implantable system is unlikely to make any incorrect therapy decisions based on overdetection resulting in 800 millisecond intervals (equal to 75 beats-per-minute).

#### Alternating Interval Overdetection Identification

As indicated by FIGS. **1-2**, another illustrative method for identifying overdetections uses event intervals to identify alternating interval patterns. It is believed that overdetection may be identified by analyzing the intervals between detected events. If analysis of a set of detected events indicates an alternating pattern of long-short intervals between events, overdetection may be occurring.

FIG. **9** provides an illustration of an alternating long-short-long interval pattern. In particular, a captured signal is shown at **200**. A detection profile similar to that of FIG. **4** is applied to the captured signal **200**. The result is consistent overdetection, with an R-wave detection shown in association with a refractory period at **204**, and a T-wave detection shown in association with a refractory period at **206**. This pattern repeats with detections associated with refractory periods at **208** and **210**.

The intervals from detection to detection are shown and characterized at **212**, including short intervals **214** and long intervals **216**. In a numeric example, if the refractory periods are about 100 ms, then the short intervals may be in the range

of 200 ms, while the long intervals are in the range of about 450 ms. This would result in a detected heart rate of about 184 beats-per-minute (bpm) with an actual cardiac rate of only 92 bpm, with the difference being attributed to persistent overdetection. A different duration for the refractory period may be used.

The long-short-long pattern provides another basis for identifying overdetection. The pattern may become more difficult to discern at higher rates, since the difference between long intervals **216** and short intervals **214** becomes less apparent. If desired, and as shown in FIG. **16**, the alternating interval pattern analysis may be omitted when detected heart rates become relatively high.

FIG. **10** illustrates an alternating interval pattern. At **220**, a mapping of interval durations is shown, with a center line shown at **222** as the average interval. Any suitable number of intervals may be used to calculate the average. A voidband having high and low boundaries is shown, with the short interval boundary shown at **224** and a long interval boundary shown at **226**. The voidband is defined by a voidband constant in the example shown. Thus, for example, if the four interval average at a given point in time is 400 milliseconds (150 bpm), and a voidband constant of about 23 milliseconds is used (other voidband constants may be used), then the boundaries **224**, **226** would be 377 milliseconds and 423 milliseconds, (142 to 159 beats bpm) respectively. A different voidband definition may be used instead, for example, simply +/-10 bpm, or an offset such as +10 milliseconds, -20 milliseconds.

In the illustrative example, in order to identify an alternating interval pattern, several rules are applied. First, the four interval average **222** must fall within a predetermined range, as indicated at **230**. Some embodiments omit rule **230**. Second, a specific pattern must be found, as indicated at **232**. In the illustrative example, pairs of consecutive intervals are considered, and there must be at least six crossings of the voidband by a line drawn between each interval within the previous 8 intervals. Crossings of the voidband in the illustrative example of FIG. **10** are shown and numbered at **234**. For example, interval I.sub.n-5 is longer than the boundary **226**, and interval In-4 is shorter than the duration defined by boundary **224**. Thus, the pair I.sub.n-5, I.sub.n-4 crosses the voidband, increasing the count of interval pairs that satisfy the specific pattern **232**. Other parameters may be used to identify the alternating intervals, if desired.

Another rule is shown at **236** and calls for a Long-Short-Long pattern in the three most recent intervals. Referring to FIG. **9**, it can be seen that, when a Long-Short-Long pattern forms due to overdetection of T-waves, the Short interval likely corresponds to the time from the R-wave detection to the T-wave detection. The rule **236** calls for identifying a set of Long-Short-Long intervals in the intervals for N-1 to N-3.

As shown in FIG. **10** at **238**, if each rule **230**, **232**, **236** is met, then detection N-2 is marked as an alternating interval overdetection. The incorporation of overdetection marking into a rate calculation method is further illustrated by FIGS. **18-21**, below. FIGS. **18-21** illustrate selective correction of data for rate calculation; however, such data correction could interfere with the Alternating Interval Overdetection Identification method by combining intervals, removing the short intervals and preventing the noted voidband crossings. Within the alternating interval analysis, the identification of an overdetection does not change the handling of detected events. Therefore, in an illustrative example, Alternating Interval Overdetection Identification methods make use of raw, uncorrected intervals (based on detections that pass waveform

appraisal) to establish the Average Interval and to identify excursions below and above the voidband, rather than using corrected intervals.

Analysis as shown in FIG. 10 is one example of an Alternating Interval analysis. Other Alternating Interval analysis may look for other time or interval based patterns in a queue of intervals between detected events. Examples include triple detection (long-short-short triplets), combinations (sets where three intervals are captured, with the second and third interval being approximately as long as the first interval, indicating a correct detection followed by a double detection pair), or any other suitable timing-based pattern analysis.

#### Wide Complex Overdetection Identification

Some embodiments of the present invention are directed toward identifying overdetection of wide QRS complexes. FIGS. 11, 12A-12D, 13A-13B, and 14 illustrate Wide Complex Overdetection Identification. The Wide Complex Overdetection Identification methods observe whether detections occur within short intervals and with predetermined morphology characteristics. If the proximity and morphology characteristics are identified, the Wide Complex Overdetection Identification method determines that overdetection has occurred.

Referring now to FIG. 11, the unrectified signal is shown as signal 290. The signal 290 demonstrates a wide QRS complex. The rectified version of the signal 290 is shown at 300. As can be seen at 302, 304, the wide QRS is detected twice. This pattern repeats itself again at 306, 308.

FIGS. 12A and 12B show two rule combinations that can be used, either alone or as alternatives to one another, for identifying wide complex double detections. In FIG. 12A, at 320, detections N-1 and N-2 are shown. For purposes of applying the rule set, positive and negative peaks of each detection are marked as "p+" and "p-", respectively. The positive peak, p+, is marked at the point of maximum (or most positive) signal amplitude, and the negative peak, p-, is marked at the point of minimum (or most negative) signal amplitude during each refractory period.

FIG. 12A shows a first wide complex rule set. A first rule is shown at 322 and is labeled the Detection Interval Rule. The first rule 322 calls for the interval between the detections (shown as t.sub.1 324) to be less than a predetermined value, noted as Rule.sub.--1\_Duration. The second rule 326 is labeled the Peak Proximity Rule and calls for a time t.sub.2 328 that is the duration between the latter peak (here, p-) of the N-2 detection and the earlier peak (here, p+) of the N-1 detection to be less than another predetermined value, noted as Rule.sub.--2\_Duration (it should be noted that time is not shown to scale).

In an illustrative example, Rule.sub.--1\_Duration is set to about 195 milliseconds. In another illustrative example, Rule.sub.--1\_Duration is set to the sum of the duration of the refractory period plus about 40 milliseconds. In an illustrative example, Rule.sub.--2\_Duration is set to about 20 milliseconds. Other values may be used for Rule.sub.--1\_Duration and Rule.sub.--2\_Duration. Some examples set Rule.sub.--1\_Duration within a range of 150-240 milliseconds, or, in other examples, the refractory duration plus 20-60 milliseconds. Some examples set the Rule.sub.--2\_Duration in the range of 10-40 milliseconds. Other formulations may be used as well.

FIG. 12B shows a second wide complex rule set. In FIG. 12B, at 330, a set of detections N-1 and N-2 are shown, with positive and negative peaks marked with p+ and p- indicators. A first rule is shown at 332 as a Detection Interval Rule in which the interval t1 334 between the detections is compared to Rule.sub.--1\_Duration. The second rule is shown at 336 and is referred to as a Polarity Rule. The Polarity Rule

determines whether the N-1 and N-2 detections are of opposing "polarity." For the purposes of the Polarity Rule, a detection is considered as having positive polarity if the p+ peak occurs before the p- peak; otherwise, the detection is negative. If the polarities of the two detections N-1 and N-2 are not the same, as shown, then the second rule 336 is met.

The signals shown in FIGS. 12A-12B are simplified to highlight the use of p+ and p- markers for identifying peak proximity and polarity. FIGS. 12C and 12D provide examples simulating more realistic signals in which wide QRS complexes are overdetection.

FIG. 12C illustrates application of a Wide Complex rule set to an overdetection signal having a wide QRS complex. The rectified version of the signal is shown in the upper portion of FIG. 12C to illustrate detections 340 and 342 occurring as the wide complex is overdetection. The unrectified signal is shown at 344. For a one-sided signal as shown, the negative peak p- can be defined as the lowest amplitude sample. The first detection 340 has p- occurring before p+. By definition, this gives the first detection 340 negative polarity.

For the second detection, the p+ occurs first, giving the second detection positive polarity. Because the first detection has negative polarity and the second detection has positive polarity, the polarity rule is met. As noted, the detection interval rule is met. As a result, both the first and second rules noted in FIG. 12B are satisfied by the detected event pattern shown in FIG. 12C.

FIG. 12D illustrates application of another Wide Complex rule set to another signal. Again two detections 350, 352 are shown in rectified form for detection purposes. In FIG. 12D, the alternating polarity rule fails because the first event 350 and second event 352 both have positive polarity, with the positive peak of each occurring first. Meanwhile, the detection interval rule is met. In the example, the peak proximity rule is met because p- for the first detection 350 is near the end of the refractory period, while p+ for the second detection 352 is near the start of the refractory period.

Rule sets are met in each of FIGS. 12C-12D. FIG. 13A shows how satisfaction of a rule set may be handled. FIG. 13B shows how events can be marked for purposes of rate calculation in FIGS. 18-21 using the rule set results and other conditions.

As shown in FIG. 13A, the Wide Complex Overdetection Identification method uses "True" and "False" markers for individual detected events. These markers indicate the confidence the system has in the individual detections. A "False" marking indicates a lack of confidence in a given detection, meaning that the analysis of the Wide Complex Overdetection Identification method has found that the False detection is likely an overdetection. A "True" marking indicates that the wide complex analysis has not identified a given detection as a likely overdetection. If large numbers of detections are marked False, overdetection is suspected. FIG. 22 provides an example of a charge confirmation method that may be used to verify therapy decisions before preparations for therapy delivery are made if large numbers of detections are marked False.

The True-False marking of FIG. 13A may be performed regardless of heart rate. In an illustrative example, the additional marking shown in FIG. 13B of individual events as Wide Complex Overdetections and/or Wide Complex Suspect is performed only while the detected rate is in a predetermined range (FIG. 16). This heart rate range limit on Wide Complex Overdetection marking and/or Wide Complex Suspect marking may be omitted in some embodiments.

Referring to FIG. 13A, the illustrative example shows how events may be marked given initial circumstances and rule

outcomes. For example, as shown at **362**, when event N-2 is True and no rule set (FIGS. **12A-12B**) is satisfied, then N-2 remains True and N-1 is newly marked as True. Another circumstance is shown at **364**, which begins with N-2 marked as True. In this circumstance, a rule has been met, a morphology template is available to the system, and the correlation of event N-1 to the morphology template is better (higher CWA score in the illustrative example) than the correlation of event N-2 to the morphology template. In such a circumstance **364**, event N-2 has its marker changed from True to False, while event N-1 is marked True. As illustrated by the circumstance at **364**, the marking of an event as True is sometimes only a preliminary determination which may be changed later in the analysis.

Next, as shown at **366**, in any other circumstance in which event N-2 starts True and a rule set is met, the result will be a marker of True for event N-2 and a marker of False for event N-1. Finally, as shown at **368**, if the initial circumstance is that N-2 has been marked False, then event N-1 is marked True without consideration of the outcome of the application of the rule sets of FIGS. **12A-12B**.

Referring to FIG. **13B**, illustrative handling of True-False markers is shown. The handling relies, in part, upon the status of the system as shown at **380** and **390**. A "Pattern Found" or "No Pattern" state results from identification of a detection pattern that indicates wide complex overdetection. Illustrative examples of patterns that can be used to identify "Pattern Found" and "No Pattern" states are shown below.

As shown at **380**, a first system state is one in which the calculated heart rate is in a predetermined range and a pattern has been found. When in this state, the method assigns wide complex overdetection markers to selected events. In the illustrative example, when detected events N-3, N-2 and N-1 form a True-False-True sequence, then a wide complex overdetection marker is assigned to N-2. Otherwise, as shown at **384**, no wide complex overdetection marker is assigned. The use of the overdetection marker is further explained with reference to FIGS. **18-21**.

As shown at **390**, a second system state occurs in which the rate is in range but the system is not in a pattern found state. As shown at **392**, when detected events N-3, N-2 and N-1 form a True-False-True sequence, event N-2 is assigned a suspect event marker. The use of the suspect event marker, again, is explained further with reference to FIGS. **18-21**. In any other combination, no WC suspect marker is assigned, as shown at **394**.

As noted at **380**, **390**, "Pattern Found" and "No Pattern" states are defined, therefore some illustrative pattern searching examples are shown next. Generally the approach is to identify particular features of the overall rhythm, encompassing several detected events, which indicate that a pattern of Wide Complex overdetection appears likely. When such particular features are identified, a "Pattern Found" state can be invoked, allowing events to be marked as overdetections.

A first example of a pattern that may be used to define the "Pattern Found" and "No Pattern" states has been shown above in FIG. **10** as an alternating interval pattern. Different heart rate ranges may be used for Wide Complex Overdetection Analysis and Alternating Interval analysis, as indicated in FIG. **16**, below. Thus, in the illustrative example, when the rate is in the Wide Complex range and the other rules (rules **232**, **236**) for an alternating pattern from FIG. **10** are met, the "Pattern Found" state is entered.

Other patterns may also be used to establish a "Pattern Found" state. One example uses alternating Wide Complex Suspect (WC Suspect) event markers. An alternating pattern could be: [WC Suspect]-[Not Suspect]-[WC Suspect]-[Not

Suspect]. Such a four event pattern can be sufficient to enter the Pattern Found state. In one illustrative example, only suspect markers generated by the Wide Complex Overdetection method are used to identify the alternating suspect event marking. In another example, a larger set of events is used to establish the pattern, and/or any source of suspect event markers may be relied upon to establish the pattern.

FIG. **14** graphically illustrates transitions between system states. The example in FIG. **14** includes two in-range states and an out of range state. In each state, the system performs True-False marking as set out in FIG. **13A**. The True-False marking may be used in later steps such as charge confirmation shown in FIG. **22**.

The illustration **400** provides for an Out of Range state **402**, in which wide-complex suspect and overdetection marking is off (WC Off). The Out of Range state **402** is effective when the detected heart rate falls outside of a predetermined range. When the heart rate enters the range, the system leaves the Out of Range State and enters an In Range, No Pattern State **404**.

Once in the In-Range, No Pattern State **404**, the system begins looking for T-F-T sequences and, if any are found, suspect event marking as shown at **390-392-394** in FIG. **13B** takes place. The system also looks for patterns that indicate overdetection is occurring. This may include observing a pattern of alternating long-short intervals and/or a pattern of WC Suspect event markers. In one example, a pattern as shown in FIG. **10** is sought. Once both the rate range and a pattern are found, the system then transitions to an In-Range, Pattern Found state **406**.

Once in the In-Range, Pattern Found state **406**, if a T-F-T pattern is found, the system assigns a Wide Complex Overdetection marker as explained at **380-382-384** in FIG. **13B**. A transition from the In-Range, Pattern Found state **406** to the In-Range, No Pattern state **404** may occur if a timeout occurs without any Wide Complex Overdetection markers being assigned. In one illustrative example, if 64 consecutive detected events pass without any wide complex overdetection markers being assigned, the pattern is considered lost and the system transitions from state **406** to state **404**. Use of N=64 is merely illustrative, and other thresholds may be used.

Within the illustration **400**, from either In-Range state **404**, **406**, if the calculated rate falls outside of the rate range, the system returns to the Out of Range state **402**. In an alternative embodiment, the system may wait to begin suspect event or overdetection marking until a pattern has been found in addition to meeting the rate range. In yet another embodiment, rather than entering the In Range, No Pattern state **404** when the rate enters the predetermined range, the method may assume a pattern exists and enter the In-Range Pattern Found state **406** immediately upon meeting the rate range condition.

While in the Out Of Range state **402**, an illustrative method does not perform either WC Suspect or WC Overdetection marking as shown in FIG. **13B**. If desired, True/False marking may be omitted while in the Out of Range state **402**. In one example, however, True/False marking is performed and may be used, upon transition into the rate range, to immediately enter the In-Range, Pattern Found state **406**. In another example, True/False marking is performed at all times, and a buffer of True/False markers and event polarity indications is kept in order to provide information for use in Charge Confirmation methods shown in FIG. **22**. Event width and correlation scores may be carried forward as well.

Thus, FIG. **14** provides an illustration of system operation by integrating the True-False marking and suspect and/or overdetection markers of FIGS. **13A-13B**, which in turn apply the rules of FIGS. **12A-12D**.

The above rules indicate that, following a False event marker, the next event is marked True (Rule 368 in FIG. 13A). However, the marking of an N-1 event as "True" is a preliminary indication. During a next iteration of the method, an event that was marked True when in the N-1 analysis slot may be marked false when it is in the N-2 analysis slot, as may occur as shown by FIG. 15.

FIG. 15 shows analysis of four events, a, b, c, and d, which are consecutively occurring detected events that each have passed waveform appraisal. As shown at 450, at time t1 events a and b are treated as events N-2 and N-1, respectively, for the rule analysis of FIG. 12A-12B. As shown by FIG. 13A, at 366, when the rules are met and the earlier event, N-2, does not have lesser correlation to the stored template than the latter event, N-1, the N-1 event (event b) is marked False, while the N-2 event (event a) is marked True.

The method then iterates to 452, where, at time t2, events b and c are treated as N-2 and N-1, respectively, and the rules would again be applied. Here, because event b is already marked as False, event c is automatically marked as True based on the rule shown in FIG. 13A at 368. If a Wide Complex rate range is met, the T-F-T pattern will result in the N-2 event (event b) being marked as either a Wide Complex Overdetection or as Wide Complex Suspect, depending on whether a Pattern Found state is in effect. The method next iterates to 454.

As shown at 454, events c and d are treated as N-2 and N-1, respectively, and the rules of FIG. 12A-12B are applied. As indicated, one of the rule sets of FIGS. 12A-12B is again met. In the illustrative embodiment, the correlation to the stored morphology template of the latter event, N-1, is greater than the correlation of the earlier event, N-2. As per rule 366 in FIG. 13A, the N-2 event is marked False and the N-1 event is marked True. The result of this analysis is the marking of consecutive events b and c as False. Note that at this point, an F-F-T pattern has developed. No Wide Complex Overdetection or Wide Complex Suspect event marker is applied to the N-2 event (event c), since this pattern is not one of the marker patterns shown in FIG. 13B. The consecutive False markers do, however, reduce confidence in event detection accuracy. FIG. 22, below, provides further illustration of marking and analysis for charge confirmation that can add persistence factors to therapy decisions when too many events are marked False. In yet another embodiment, if desired, a pairing of F-F may be analyzed to determine whether the two detections indicate a triple-detection pattern has occurred. For example, consecutive False markers may result in a calling of a morphology analysis to determine whether an immediately preceding or following event matches a stored or dynamic template. Alternatively, if a T-F-F-T sequence is identified, the two detections marked as True may be compared one to another; high correlation may indicate triple detection has caused the intervening False events.

#### Integration, Data Correction and Charge Confirmation

FIG. 16 graphically illustrates an integration of several overdetection analysis methods. In the illustrative example 470, waveform appraisal 472 may be enabled at any detected event rate, as is Morphology Overdetection Analysis 474, if a template can be established for use in the analysis.

As shown at 476, Wide Complex Overdetection Identification Analysis is enabled in a relatively higher rate zone, with Alternating Interval Overdetection Identification Analysis enabled in a lower rate zone at 478. In some embodiments, an upper limit is placed on the Wide Complex Analysis 476, for example, in the range of 405 bpm calculated heart rate,

and the border between the Wide Complex Analysis 476 and Alternating Interval Analysis 478 is set in the range of about 160 bpm.

These variables may change or may be omitted. The upper and/or lower rate limits on Wide Complex Analysis 476 may be omitted, for example, as well as the upper limit on Alternating Interval Analysis 478. Also, rather than a strict "border," these analysis zones may overlap. Transitions may also take into account various hysteresis factors such as, but not limited to, crossing the "border" by an amount greater than some value (i.e. 20 ms or 20 bpm beyond the border) and/or meeting the requirement for a selected number of consecutive detected events.

FIG. 17 illustrates the use of a refined detection profile. The purpose of FIG. 17 is to show that, for any given profile, it is likely possible to identify an implantee in whom the profile may result in overdetection. The illustrative profile is similar to one of those shown in U.S. Provisional Patent Application No. 61/034,938, entitled ACCURATE CARDIAC EVENT DETECTION IN AN IMPLANTABLE CARDIAC STIMULUS DEVICE, filed on Mar. 7, 2008. As shown above the label "Overdetecting T-Waves" cardiac cycles shown at 510, 512 are double counted as both the R-waves and the trailing T-waves lead to detections. Further, as shown above the label "Overdetecting Wide Complexes," the profile also double detects the QRS complexes shown at 520, 522. Refining the detection profile may not avoid all overdetection.

FIGS. 18-21 provide illustrations of the handling of Overdetection and Suspect event markers from the above illustrative examples. FIG. 18 provides an example of what happens during "normal" detection, when no events are marked as suspect or overdetections. A buffer of detections and associated intervals is shown at 600. The definition of detection and interval is indicated at 602: a detection threshold crossing is a detection, and an interval is the period of time between consecutive detections.

As shown at 600, detections and intervals occur in an ongoing series, with a most recent detection shown at 604, separated by a most recent interval 606 from a second most recent detection 608. For illustrative purposes, the examples in FIGS. 18-21 operate using a delay of at least one event; a real time system that analyzes event 602 as soon as it is defined could be used instead.

As shown at 610, an analysis window is defined to perform analysis on three detected events and associated intervals. As the analysis 610 is completed, detected events are marked as certified detected events 612. In addition, an interval is marked as a certified interval if no suspect event or overdetection markers are applied to events defining the interval. The newest certified interval is introduced into a first-in, first-out (FIFO) buffer of certified intervals 614, as indicated by line 616.

In the illustrative example, four certified intervals 614 are used in the FIFO buffer to calculate a 4RR Average 618, which is used to find a calculated heart rate 620 for the system. In the illustrative example, until intervals are certified, they are not used in rate calculations. The analysis 610 will "certify" intervals for use in rate calculation unless the interval is marked suspect or is combined as a result of a detection being marked as an overdetection. The analysis 610 may include any of the above analyses such as waveform appraisal, morphology overdetection analysis, alternating interval overdetection analysis, and/or wide complex overdetection analysis.

FIG. 19 shows analysis when a suspect event marker is applied. A suspect event marker is shown in the above examples as a possible outcome of Waveform Appraisal analysis or Wide Complex Overdetection Identification

analysis. Within the series of detections and intervals **640**, the analysis window is shown at **642**. An event at **644** is marked as a suspect event.

In operation, the suspect event **644** is known to be unreliable, but it is not known whether the suspect event **644** is, for example, an R-wave masked by spurious noise, a double detection, or a detection caused by external noise. Since the source of event **644** is unclear, as indicated by its marking as suspect, each interval defined by the event **644**, including both intervals **646** and **648**, is determined to be unreliable for rate calculation. The method does not pass intervals **646**, **648** to the buffer of certified intervals **650** which is used to generate the 4RR average **652** and hence the rate **654**. Instead, prior intervals that have already been certified are retained in the buffer **650** until a new interval is certified. For example, if neither of the detections on either side of interval **656** are marked as suspect or as overdetections, then interval **656** will pass to the buffer **650** once analysis **642** has moved on, as indicated by **658**.

FIG. **20** shows treatment of overdetection markers. In the example shown, persistent overdetection is marked within the series of detections and intervals **700**. The analysis window is shown at **702**, and overdetection markers are shown at **704**. In the illustrative example, data is corrected when an overdetection marker is applied. More specifically, intervals around an event having an overdetection marker are combined, and the event itself is discarded.

For example, an overdetection marker is applied to the detection at **706**. The intervals **708**, **710** on either side of detection **706** are combined into a single interval **712**. Detection **706** may also be discarded, for example, removing it from estimated peak calculation(s). This combined interval **712** is brought into the certified interval buffer **720**. Likewise, a combined interval at **714** enters the buffer **720**. As the analysis continues, the combined interval shown at **716** will also be added to the buffer **720** and used to generate the 4RR Average **722** and rate **724**.

FIG. **20** provides a contrast to FIG. **19**. When a detection is marked suspect, as in FIG. **19**, it is not known whether an associated cardiac cycle has been counted yet. An overdetection **706**, when identified, likely corresponds to a cardiac cycle that has already been counted by another detection. Therefore, data correction by combining intervals **708**, **710** into combined interval **712** is determined to be appropriate.

It should be noted that for either of FIG. **19** or FIG. **20**, in addition to modifying the rate calculation, applying a suspect event or overdetection marker may also change the calculation of an estimated peak. As noted, overdetections or suspect events may sometimes lower the estimated peak and increase the likelihood of further overdetection. When a suspect event or overdetection marker is applied, some embodiments exclude one or more detected events from calculation of the estimated peak. In one illustrative example, if two previous peaks would usually be averaged to calculate estimated peak, if an overdetection or suspect event marker is applied, the larger peak of the two peaks may be used as the estimated peak.

FIG. **21** combines the above analysis of FIGS. **19-20** by showing a circumstance in which both suspect event and overdetection markers are applied. In the data **750**, a suspect event marker has been applied at **752**. This results in intervals shown at **754** being marked as suspect and treated as unreliable and unusable.

Also in FIG. **21**, the detection at **756** is marked as an overdetection. This detection **756** is then discarded and the associated intervals **758**, **760** are combined into a single interval **762**. The combined interval **762** is used in the buffer of

certified intervals **764**, which is used to calculate the 4RR Average **766** and heart rate **768**.

FIG. **22** provides an example of charge confirmation analysis. The method of FIG. **22** is largely directed toward analyzing whether therapy is proper at a time when the cardiac rhythm is likely malignant. The analysis of FIG. **22** is largely an effort to avoid improper therapy delivery to an implantee when overdetection is occurring. The method in FIG. **22** may be performed as part of a therapy decision, for example, as shown at **22** in FIG. **1** or **48** in FIG. **2**. The analysis shown in FIG. **22** includes a Start Block which would begin with an internal variable, denoted "Tolerance" in the Figure, is initialized to zero, and the Start Block would be called once other factors (such as the X/Y and persistence conditions noted above) are already met.

FIG. **22** makes use of two further data sets. First, individual events are tagged as 0, 1 or 2 using the True-False and polarity designations from FIGS. **12A-12D** and **13A**, as follows:

If marked True, the event receives tag 0.

If marked False and having positive polarity, the event receives tag 1.

If marked False and having negative polarity, the event receives tag 2.

Several counters are then generated from a buffer of the 16 most recent detected events that have passed waveform appraisal (this would include events marked as overdetections and/or suspect by methods other than waveform appraisal), as follows:

Total\_WC\_Beats: Number of Wide Complex Suspect or Wide Complex Overdetection marked detections in the buffer

Max\_Cons.sub.--01: Maximum number of consecutive 0-1 tag combinations

Max\_Cons.sub.--02: Maximum number of consecutive 0-2 tag combinations

These calculated variables are then used as shown in FIG. **22**.

Beginning at a start block **800**, the method determines if Total\_WC\_Beats is less than six, as shown at **802**. If not, the method checks whether Total\_WC\_Beats is greater than or equal to eight, as shown at **804**. If so, the method determines whether Max\_Cons.sub.--01 is greater than or equal to three, as shown at **806**. If not, the method determines whether Max\_Cons.sub.--02 is greater than or equal to three, as shown at **808**. If not, the variable "Tolerance," which is an integer variable created for use as a persistence factor in the flow diagram of FIG. **22**, is compared to five. If Tolerance is greater than or equal to five, as shown at **810**, the charge confirmation method is satisfied, and the method returns an indication to start charging, as shown at **812**, for the purpose of charging high power capacitors for use in delivering therapy.

Going back to step **810**, if Tolerance is not equal to or greater than five, the method goes to block **814**, where Tolerance is incremented and the method returns an indication that charging should not be started, as indicated at **816**. Setting the Tolerance limit as five is merely illustrative, and larger or smaller settings may be used.

Continuing back through the method to capture alternative outcomes, if either of blocks **806** or **808** returns a Yes result, then the method resets the Tolerance variable to zero, as shown at **818**, and the method returns an indication that charging should not be started, as shown at **816**. The consecutive pairings of 0-1 or 0-2 that trigger reset of the Tolerance variable from blocks **810** and/or **812** indicates repetitive double detections having similar morphology over time. Resetting the Tolerance variable is allowed in each of these circumstances at least because a requisite level of polymorphic behavior that would be associated with ventricular fibril-

lation and/or highly discordant arrhythmias (such as polymorphic ventricular tachycardia) is not occurring. Such judgments regarding the cardiac rhythms that will or will not be treated aggressively may vary in some embodiments or in response to physician preference.

In some embodiments, a triple detection identification method may be called in addition to the other overdetection identification methods shown herein. The use of True-False and 0-1-2 marking shown above may provide analytical tools for such triple detection identification. In one such embodiment, triple detection patterns are identified by observing whether a pattern of 0-1-2 or 0-2-1 repeats, such as {0-1-2-0-1-2-0 . . . }, and data correction to remove each of the 1 and 2 detections can be performed. Such an embodiment may include analysis of the True (0) detections to determine whether narrow QRS features can be identified.

In block 802, the Yes result likely indicates a shockable rhythm such as ventricular fibrillation. Therefore, the method goes directly to block 816 and returns a result indicating that charging should begin. This bypass of the "Tolerance" analysis may be omitted in some embodiments. Finally, if block 804 returns a No result, then the checks at 806 and 808 are determined to be unnecessary, and the method skips to block 810 where the Tolerance variable is checked.

In an illustrative example, the charge confirmation method shown in FIG. 22 is used as a prerequisite to initiating charging of high-power capacitors in an implantable cardioverter-defibrillator or other implantable therapy delivery system. Once capacitor charging begins, in an illustrative example, the method of FIG. 22 is no longer invoked until a shock is delivered or the episode terminates.

FIG. 23 shows an example of analysis. Some analysis methods take an approach in which a series of buffers are filled during analysis toward a decision to deliver therapy to a patient. For example, cardiac rate may be measured and, once calculated as tachyarrhythmic, a counter begins to determine how many consecutive rate calculations occur having the tachyarrhythmic rate. Once the tachyarrhythmic rate counter is filled, a tachy condition is met and the device will perform additional morphology analysis to determine whether the patient is showing a monomorphic rhythm and/or whether the patient's individual detected events are not correlated to a stored template. In this example, morphology analysis occurs at the end of the analysis. By only using the morphology analysis at the end of the analysis, it is underemphasized. With morphology only at the end of the analytical method, incorrect therapy decisions may not be avoided.

In contrast, the method of FIG. 23 is shown at 900 using a different order. In particular, the method 900 follows event detection 902 with waveform appraisal 904, in which the detected event is analyzed by itself to determine whether it likely is caused by, or is masked by, noise. As suggested above, waveform appraisal 904 may take a form as shown in U.S. Pat. No. 7,248,921, titled METHOD AND DEVICES FOR PERFORMING CARDIAC WAVEFORM APPRAISAL. Next, morphology qualification takes place, as shown at 906. Morphology qualification 906 includes one or more of the double detection methods shown above, such as wide complex overdetection, morphology overdetection, and alternating interval overdetection.

Next, the rate is estimated, as shown at 908. The rate is characterized as falling into one of three zones: A VF zone, a VT zone, and a Low zone. The VF zone is a high zone, typically greater than 180 bpm, and sometimes higher than 240 bpm, for example. The Low zone is a non-malignant zone, for example, below 140 bpm, though possibly reaching to as high as 170 bpm for some patients, and even higher,

particularly with younger patients. The VT zone is defined between the Low zone and the VF zone. In this example, "VT" and "VF" are simply labels, not diagnoses. The rate estimate may make use of the methods shown above that correcting data in response to identified overdetection.

If the rate is Low, the detected event is marked as not shockable, as indicated at 910. If the rate is in the VT zone, an optional detection enhancement 912 may be called. In an illustrative example, detection enhancement 912 includes a tiered analysis in which the detected event under consideration is compared to a static template. If the detected event correlates well with the static template, the detected event is marked as not shockable 910. If the event does not correlate to the static template but does correlate well to a dynamic template formed of an average of four recently captured events and shows a narrow QRS complex (the combination suggests a monomorphic tachycardia having narrow complexes), the method will also proceed to step 910. Otherwise, if detection enhancement 912 fails, the detected event is marked as shockable, as shown at 914.

If the rate calculated at 908 is in the VF zone, detection enhancement 912 may be bypassed and the detected event is marked as shockable as shown at 914. In one embodiment, the implantable device is programmed to set the boundaries of the VT zone and VF zone and/or to omit the VT zone. In yet another embodiment, the VF zone may be omitted, and all rates above the Low zone would be directed through detection enhancement 912.

The markings of shockable and not shockable are maintained in an X/Y counter, which provides an initial counter for determining whether to proceed to therapy. If the X/Y counter fails (counters such as 12/16, 18/24, or 24/32, for example, may be used), then no therapy is applied and the method of analysis ends with no shock 918. The system then waits to call the method again when the next detection occurs. The X/Y counter 916 may also integrate a persistence factor, for example, calling for the X/Y counter condition to be met for a series of consecutive detected events.

The illustrative method 900 also calls a charge confirmation check, as shown at 920. The charge confirmation check 920 may be as shown above in FIG. 22. The charge confirmation check, if passed, leads to the decision to charge and shock 922. Charge and shock 922 may be called with analysis continuing to ensure that the patient's malignant rhythm does not correct itself. If the patient's malignant rhythm returns to normal before a shock is delivered, the method may terminate the charge and shock sequence 922. If the charge confirmation check 920 does not pass, the method again ends at 918 and waits for the next detected event.

The method shown in FIG. 23 is separable from the other methods shown above for identifying overdetections and/or for correcting data resulting from overdetection.

#### Additional Features

Some embodiments take the form of devices and methods that are directed toward cardiac activity monitoring. One example may be an implantable loop recorder. Referring to FIG. 1, for monitoring embodiments, rather than a therapy decision 22, a decision to store certain data for later upload may be made instead. For example, some implantable monitors are configured to retain data only when a decision is made by the implant that abnormal and/or potentially malignant activity is occurring. In some further embodiments, data may be stored when captured data requires correction, in order that the sensing and detection characteristics of the system and/or implant location may be analyzed to determine its suitability for long-term use. A monitoring system may also output a

warning if a malignant condition is identified, for example by annunciation to the implantee or by communication with an external alert system.

The X out of Y counter referred to above may be integrated with a persistence factor as in US Patent Application Publication Number 2006/0167503, now issued as U.S. Pat. No. 8,160,697, titled METHOD FOR ADAPTING CHARGE INITIATION FOR AN IMPLANTABLE CARDIOVERTER-DEFIBRILLATOR. A persistence factor requires the X out of Y counter requirement be met for a predetermined number of consecutive iterations. In the illustrative example, the charge confirmation method of FIG. 22 is integrated as an additional requirement that follows the persistence factor. That is, in the illustrative example, charge confirmation would be invoked only after the persistence requirement is satisfied by meeting the X out of Y counter requirement for a predetermined number of consecutive iterations. If/when a non-sustained arrhythmic condition is identified, the persistence factor and/or X/Y condition may be modified as explained in the 2006/0167503 publication.

The above illustrative examples may be embodied in many suitable forms. Some embodiments will be method embodiments incorporating one or more of the above features/sub-methods in various combinations. Some embodiments will be devices adapted to perform one or more of the methods discussed above and/or a system including implantable devices and associated external programming devices. Some embodiments will take the form of tangible media, such as magnetic, electric, or optical storage media, incorporating controller readable instruction sets. Some embodiments will take the form of or comprise controllers/microcontrollers associated with stored instruction sets for directing operations of various components in a device in accordance with one or more methods.

The design details of operational circuitry contained within a canister, such as canister 62 in FIG. 3, may vary widely. Briefly, an illustrative example may make use of a microcontroller-driven system which includes an input switch matrix for selecting one or more signal vectors as a sensing vector. The switch matrix is coupled to filtering circuitry and at least one input amplifier. The amplified, filtered signal is typically fed to analog-to-digital conversion circuitry. Additional filtering of the incoming signal may be performed in the digital domain including, for example, 50/60 Hz notch filters. The incoming signal may then be analyzed using the microcontroller and any associated suitable registers and logic circuits. Some embodiments include, for example, dedicated hardware for peak or event detection and measurement, or for morphology analysis such as correlation waveform analysis or wavelet transform analysis.

In several illustrative examples, upon identification of a rhythm that indicates therapy, a charging operation is undertaken to charge one or more capacitors to suitable levels for therapy. A charging sub-circuit may take any suitable form. One example uses a flyback transformer circuit, a structure well known in the art. Any process and/or circuit that enables relatively low voltage batteries to charge capacitors to relatively high voltages may be used. Some systems also perform annunciation and/or communication in response to detected malignancy, for example, to alert the implantee or a medical facility that therapy is imminent or intervention is needed.

The device may further include output circuitry comprising, for example, an output H-bridge or modification thereof for controlling output polarity and pulse duration from the high-power capacitor. Control circuitry associated with the

H-bridge may be included, for example, to monitor or control current levels for constant current output signals or for performing diagnostic functions.

The circuitry may be housed in a hermetically sealed canister made of any suitable material.

The above description details several over-detection identification methods and associated data correction methods. Each of these methods may be used individually in some embodiments. For example, the wide-complex over-detection identification methods shown below may be used as a stand-alone method for identifying and, if desired, correcting over-detection. In some embodiments, multiple methods are used in a synchronized manner, for example, each of a morphology over-detection, alternating interval, and wide-complex over-detection methods may be used together and may analyze individual detected events or groups of detected events continuously. In yet other embodiments, a combination of these methods is used in response to given conditions.

In addition to selective activation of the separate over-detection analysis methods, there are several ways to integrate the results of over-detection analysis in addition to those shown by FIGS. 18-21. The following summaries provide alternatives and variants upon the illustrative examples shown above. In one illustrative example, the outcomes are integrated as follows:

1. Waveform Appraisal suspect events can be used in Over-detection Analysis. Any event marked as an Over-detection by any method is discarded with associated interval correction, regardless of any Suspect marker;
2. Any event marked Suspect by any method and not marked Over-detection by any method is Suspect; and
3. Any event not marked Over-detection or Suspect is considered certified once it is no longer eligible to be marked Over-detection or Suspect.

This example allows detected events that fail waveform appraisal to be used in later identification of over-detection.

Some examples do not allow detected events that fail waveform appraisal to be used in any subsequent analysis. Thus, in another illustrative example, the outcomes are integrated as follows:

1. Any Waveform Appraisal Marking of a Suspect event prevents marking of that event by any other method, and that event and associated intervals are marked WA Suspect;
2. Any event marked Over-detection and not WA Suspect is discarded with associated interval correction, regardless of any Suspect marker;
3. Any event marked Suspect by any method other than Waveform Appraisal is Suspect unless it was marked Over-detection by any method; and
4. Any event not marked Over-detection or Suspect is considered certified once it is no longer eligible to be marked Over-detection or Suspect.

In some embodiments, marking of a detected event as suspect in waveform appraisal disables classification of adjacent events by over-detection methods. This prevents a likely noise detection from causing an actual detection to be discarded. Certain counters may be preserved to avoid impact by the WA Suspect event as well, for example, when identifying a pattern for Alternating Interval Over-detection identification (or to enable the Pattern Found state of the Wide Complex Over-detection methods), one may exclude WA suspect events and one or more adjacent events, if desired.

While voltage and power levels may vary, in one example, an implantable subcutaneous cardioverter-defibrillator includes charging circuitry and capacitors sized to receive and hold energy at 1350 volts, and uses output circuitry/

controller that provide an output that yields a delivered charge of 80 Joules in a biphasic waveform with about 50% tilt. Other voltage, energy and tilt levels (higher and/or lower), and other waveforms may be used, and the load varies in response to electrode position and physiology. The configuration of output waveform need not be static, and any suitable methods/configurations for providing the output may be used (including, without limitation, pre-shock waveforms, monophasic or multiphasic waveforms, adaptation or progression of therapy energy or voltage level, changes in duration or polarity, fixed current or fixed voltage, etc.) Some embodiments use tiered therapies including anti-tachycardia-pacing as well as cardioversion and/or defibrillation stimuli. The above generally assumes two output electrodes (an anode and a cathode), however, it is understood that other systems including, for example, arrays, and/or three or more electrode stimulus systems may be used in which a pair or more electrodes are used in common.

Analysis may take several forms in terms of the inputs taken. For example, a multiple sensing electrode system may be configured to select a default sensing vector and use the default vector throughout analysis. Other systems may prioritize vectors for use in tiered analysis in which one vector is analyzed after another. Yet other systems may analyze multiple vectors simultaneously.

For purposes of conversion into the digital domain, any suitable sampling frequency may be used. Some examples use 256 Hertz; other frequencies may be used as desired. Further, the illustrative examples shown with respect to particular values can be varied, including, without limitation, changes to the refractory periods, event and peak proximity periods, rate ranges, "shockable" event rates, the number of intervals used to estimate rate, and any other values provided. Analysis using "suspect" or "certified" events and intervals, waveform appraisal, and other features may vary, and some of these features may be omitted in some embodiments. The completeness of the examples shown is not an indication that all parts are necessary to any given embodiment.

Those skilled in the art will recognize that the present invention may be manifested in a variety of forms other than the specific embodiments described and contemplated herein. Accordingly, departures in form and detail may be made without departing from the scope and spirit of the present invention.

What is claimed is:

1. An implantable cardiac stimulus device (ICSD) comprising the following:  
 a canister housing operational circuitry; and  
 a lead electrode assembly including a plurality of electrodes disposed thereon;  
 wherein with the lead electrode assembly is configured to couple to the canister to electrically couple the operational circuitry to the electrodes on the lead electrode assembly;  
 the operational circuitry being configured to perform a method of cardiac signal analysis comprising:  
 the operational circuitry detecting a series of events;  
 the operational circuitry comparing the detected events to a morphology template to establish a series of correlation scores indicative of the extent of correlation between the shape of detected events and the morphology template;  
 the operational circuitry analyzing the series of correlation scores to observe a high-low-high pattern of:  
 a first-most recent event having a high correlation score;  
 a second-most recent event having a low correlation score; and

a third-most recent event having a high correlation score;

when the high-low-high pattern is identified, the operational circuitry determining that the second-most recent event is an overdetection;

upon finding an overdetection, the operational circuitry combining an interval preceding the overdetection and an interval following the overdetection into a combined interval;

the operational circuitry using the combined interval in estimating cardiac rate; and

the operational circuitry using the estimated cardiac rate to make a therapy decision.

2. The ICSD of claim 1 wherein operational circuitry is further configured such that the step of analyzing the series of correlation scores to observe a high-low-high pattern includes:

the operational circuitry defining three zones including a Low Zone in which any correlation score is considered low, a high zone in which any correlation score is considered high, and a hysteresis zone between the low zone and the high zone in which any correlation score is considered high or low depending upon whether an immediately previous correlation score was characterized as high or low; and

the high-low-high pattern is only identified if the third-most recent event has a correlation score in the high zone.

3. An implantable cardiac stimulus device (ICSD) comprising a canister housing operational circuitry configured for coupling to and use with a lead including a plurality of electrodes disposed thereon, with the lead configured to couple to the canister to electrically couple the operational circuitry to the electrodes on the lead, the operational circuitry being configured to perform a method of cardiac signal analysis comprising:

the operational circuitry detecting a series of events;

the operational circuitry comparing the detected events to a morphology template to establish a series of correlation scores indicative of the extent of correlation between the shape of detected events and the morphology template;  
 the operational circuitry analyzing the series of correlation scores to observe a high-low-high pattern of:

a first-most recent event having a high correlation score;  
 a second-most recent event having a low correlation score; and

a third-most recent event having a high correlation score;

when the high-low-high pattern is identified, the operational circuitry determining that the second-most recent event is an overdetection;

upon finding an overdetection, the operational circuitry combining an interval preceding the overdetection and an interval following the overdetection into a combined interval;

the operational circuitry using the combined interval in estimating cardiac rate; and

the operational circuitry using the estimated cardiac rate to make a therapy decision.

4. The ICSD of claim 3 wherein operational circuitry is further configured such that the step of analyzing the series of correlation scores to observe a high-low-high pattern includes:

the operational circuitry defining three zones including a Low Zone in which any correlation score is considered low, a high zone in which any correlation score is considered high, and a hysteresis zone between the low zone

27

and the high zone in which any correlation score is considered high or low depending upon whether an immediately previous correlation score was characterized as high or low; and

the high-low-high pattern is only identified if the third-most recent event has a correlation score in the high zone.

5 **5.** A method of operation in an implantable cardiac stimulus device (ICSD), the ICSD comprising a canister housing operational circuitry configured for coupling to and use with a lead including a plurality of electrodes disposed thereon, with the lead configured to couple to the canister to electrically couple the operational circuitry to the electrodes on the lead, the a method comprising analyzing a cardiac signal by:  
 10 detecting a series of events;  
 comparing the detected events to a morphology template to establish a series of correlation scores indicative of the extent of correlation between the shape of detected events and the morphology template;  
 15 analyzing the series of correlation scores to observe a high-low-high pattern of:  
 20 a first-most recent event having a high correlation score;  
 a second-most recent event having a low correlation score; and  
 a third-most recent event having a high correlation score;

28

when the high-low-high pattern is identified, determining that the second-most recent event is an overdetection; upon finding an overdetection, combining an interval preceding the overdetection and an interval following the overdetection into a combined interval;

estimating cardiac rate using the combined interval; and using the estimated cardiac rate to make a therapy decision.

**6.** The method of claim **5** wherein each of the detecting, comparing, analyzing, determining, combining, estimating and using steps are performed by the operational circuitry of the ICSD.

**7.** The method of claim **5** wherein the step of analyzing the series of correlation scores to observe a high-low-high pattern includes:

15 defining three zones including a Low Zone in which any correlation score is considered low, a high zone in which any correlation score is considered high, and a hysteresis zone between the low zone and the high zone in which any correlation score is considered high or low depending upon whether an immediately previous correlation score was characterized as high or low; and  
 20 wherein the high-low-high pattern is only identified if the third-most recent event has a correlation score in the high zone.

\* \* \* \* \*

专利名称(译)	用于精确分类心脏活动的方法和装置		
公开(公告)号	<a href="#">US9162074</a>	公开(公告)日	2015-10-20
申请号	US14/551444	申请日	2014-11-24
[标]申请(专利权)人(译)	卡梅伦保健公司		
申请(专利权)人(译)	CAMERON HEALTH, INC.		
当前申请(专利权)人(译)	CAMERON HEALTH, INC.		
[标]发明人	ALLAVATAM VENUGOPAL PALREDDY SUREKHA SANGHERA RICK WARREN JAY A		
发明人	ALLAVATAM, VENUGOPAL PALREDDY, SUREKHA SANGHERA, RICK WARREN, JAY A.		
IPC分类号	A61B5/0452 A61N1/39 A61N1/37 A61B5/04 A61B5/00		
CPC分类号	A61N1/3987 A61B5/04014 A61B5/0452 A61N1/3704 A61N1/3956 A61B5/726 A61B5/024 A61B5/6847		
优先权	61/051332 2008-05-07 US 61/034938 2008-03-07 US		
其他公开文献	US20150088214A1		
外部链接	<a href="#">Espacenet</a> <a href="#">USPTO</a>		

摘要(译)

用于植入式心脏监测和治疗设备（例如植入式心律转复除颤器）中的信号分析的方法，系统和设备。在说明性示例中，分析包括检测到事件的捕获数据以识别心脏事件的可能过度检测。在一些说明性示例中，当识别出过度检测时，可以修改数据以校正过度检测，减少过度检测的影响，或忽略过度检测的数据。还讨论了在用于节律分类和心脏信号分析的整体架构中组织形态学和速率分析的新方法。

