



US009375162B2

(12) **United States Patent**
Callahan et al.

(10) **Patent No.:** **US 9,375,162 B2**
(45) **Date of Patent:** **Jun. 28, 2016**

(54) **ECG LEADWIRE SYSTEM WITH NOISE SUPPRESSION AND RELATED METHODS**

USPC 607/1-2, 9, 27, 36-38, 115;
600/508-509

(71) Applicant: **Covidien LP**, Mansfield, MA (US)

See application file for complete search history.

(72) Inventors: **Mark J. Callahan**, Medway, MA (US);
Glenn Gilbert, Plymouth, MA (US);
Scott R. Coggins, Littleton, MA (US);
Linda D'Elia, Westfield, MA (US)

(56) **References Cited**

U.S. PATENT DOCUMENTS

4,832,608 A 5/1989 Kroll
4,885,559 A 12/1989 Nakano

(Continued)

FOREIGN PATENT DOCUMENTS

EP 2 314 215 4/2011

OTHER PUBLICATIONS

European Office Action dated May 9, 2014; for European Pat. App. No. 12778168.0; 2 pages.

(Continued)

(21) Appl. No.: **14/135,239**

(22) Filed: **Dec. 19, 2013**

(65) **Prior Publication Data**

US 2014/0221856 A1 Aug. 7, 2014

Related U.S. Application Data

(62) Division of application No. 13/249,450, filed on Sep. 30, 2011, now Pat. No. 8,634,901.

Primary Examiner — Deborah Malamud

(51) **Int. Cl.**

A61B 5/0428 (2006.01)

A61B 5/0402 (2006.01)

(Continued)

(57) **ABSTRACT**

A noise-suppressing electrocardiograph (ECG) adapter having a first end, a second end, and a noise-suppression element is presented, together with an ECG noise-suppressing system and related methods. In an embodiment, the noise-suppressing ECG adapter includes a housing having at least one first connector disposed at a first end of the housing adapted to electrically couple with an ECG lead set, and at least one second connector adapted for coupling to an input of an ECG device. The adapter includes a noise suppression element. The noise suppression element includes a ferromagnetic element having an opening defined therein. In an embodiment the noise suppression element is internal to the adapter. In another embodiment, the noise suppression element is tethered externally to the adapter and configured to clamp around at least a portion of an ECG leadwire.


(52) **U.S. Cl.**

CPC **A61B 5/04286** (2013.01); **A61B 5/0402** (2013.01); **A61B 5/04017** (2013.01); **A61B 5/7217** (2013.01); **H01F 17/06** (2013.01);
(Continued)

(58) **Field of Classification Search**

CPC A61B 5/0402; A61B 5/04017; A61B 5/7203; A61B 5/7217; A61B 2562/222; A61N 1/3718; A61N 2001/086; A61N 1/16; A61N 1/375; A61N 1/3925; A61N 1/08; H01R 2201/12; A61F 2210/009; Y10T 428/24992; Y10T 428/25; Y10T 428/27; Y10T 428/2982

16 Claims, 7 Drawing Sheets



(51)	Int. Cl.		5,546,950 A	8/1996	Schoeckert et al.
	H01R 13/719	(2011.01)	5,558,526 A	9/1996	Nagamine
	H01R 31/06	(2006.01)	5,558,534 A	9/1996	Sarkady et al.
	H05K 9/00	(2006.01)	5,558,535 A	9/1996	Saka et al.
	H01F 17/06	(2006.01)	5,564,939 A	10/1996	Maitani et al.
	A61B 5/04	(2006.01)	5,584,719 A	12/1996	Tsuji et al.
	A61B 5/00	(2006.01)	5,599,199 A	2/1997	Wright
	H03H 1/00	(2006.01)	5,603,632 A	2/1997	Johannes et al.
			5,611,708 A	3/1997	Mizunuma et al.
(52)	U.S. Cl.		5,613,870 A	3/1997	Traver, Jr.
	CPC	H01R13/719 (2013.01); H01R 31/065	5,615,674 A	4/1997	Maurer
		(2013.01); H05K 9/0066 (2013.01); A61B	5,622,168 A	4/1997	Keusch et al.
		2562/182 (2013.01); A61B 2562/227 (2013.01);	5,624,271 A	4/1997	Childs et al.
		H01F 2017/065 (2013.01); H01R 2201/12	5,626,135 A	5/1997	Sanfilippo
		(2013.01); H03H 2001/005 (2013.01)	5,632,274 A	5/1997	Quedens et al.
			5,632,643 A	5/1997	Shepherd et al.
			5,651,689 A	7/1997	Plyler et al.
			5,653,606 A	8/1997	Chrysostomou
(56)	References Cited		5,674,088 A	10/1997	Roche et al.
	U.S. PATENT DOCUMENTS		5,676,694 A	10/1997	Boser et al.
			5,679,022 A	10/1997	Cappa et al.
			5,679,029 A	10/1997	Saunier et al.
			5,695,355 A	12/1997	Hasenfratz et al.
	5,080,604 A	1/1992 Rider et al.	5,702,265 A	12/1997	Yamaguchi
	5,083,238 A	1/1992 Bousman	5,711,684 A	1/1998	Inoue et al.
	5,083,933 A	1/1992 Colleran et al.	5,718,596 A	2/1998	Inaba et al.
	5,091,707 A	2/1992 Wollmerschauser et al.	5,724,984 A	3/1998	Arnold et al.
	5,104,253 A	4/1992 Zielinski et al.	5,725,525 A	3/1998	Kordis
	5,104,334 A	4/1992 Honma et al.	5,741,155 A	4/1998	Herman
	5,131,854 A	7/1992 Jose et al.	5,749,746 A	5/1998	Tan et al.
	5,137,466 A	8/1992 Endo et al.	5,769,650 A	6/1998	Aoyama et al.
	5,154,646 A	10/1992 Shoup	5,772,591 A	6/1998	Cram
	5,158,469 A	10/1992 Martin	5,775,953 A	7/1998	Yamanashi et al.
	5,160,276 A	11/1992 Marsh et al.	5,782,647 A	7/1998	Okura et al.
	5,173,059 A	12/1992 Sato et al.	5,782,892 A	7/1998	Castle et al.
	5,176,343 A	1/1993 Cheney, II et al.	5,788,527 A	8/1998	Sanders et al.
	5,178,556 A	1/1993 Chen	5,797,854 A	8/1998	Hedgecock
	5,180,312 A	1/1993 Martin	5,806,152 A	9/1998	Saitou et al.
	5,190,467 A	3/1993 Ohta	5,813,404 A	9/1998	Devlin et al.
	5,192,226 A	3/1993 Wang	5,813,979 A	9/1998	Wolfer
	5,197,901 A	3/1993 Hashiguchi	5,827,086 A	10/1998	Fukuda
	5,199,897 A	4/1993 Hashiguchi	5,830,000 A	11/1998	Shifflett et al.
	5,201,669 A	4/1993 Lin	5,836,783 A	11/1998	Morisawa et al.
	5,203,715 A	4/1993 Yamamoto	5,843,141 A	12/1998	Bischoff et al.
	5,203,719 A	4/1993 Kozono	5,848,456 A	12/1998	Sjoqvist
	5,232,383 A	8/1993 Barnick	5,873,747 A	2/1999	Tsuji
	5,234,356 A	8/1993 Macjima et al.	5,876,232 A	3/1999	Matsushita et al.
	5,234,357 A	8/1993 Yamaguchi	5,895,284 A	4/1999	Kocher et al.
	5,243,510 A	9/1993 Chaney, II	5,904,579 A	5/1999	McLean et al.
	5,276,443 A	1/1994 Gates et al.	5,931,689 A	8/1999	Patel
	5,278,759 A	1/1994 Berra et al.	5,931,861 A	8/1999	Werner et al.
	5,293,013 A	3/1994 Takahashi	5,934,926 A	8/1999	Gabrisko, Jr. et al.
	5,320,621 A	6/1994 Gordon et al.	5,937,950 A	8/1999	Adams et al.
	5,326,272 A	7/1994 Harhen et al.	5,938,470 A	8/1999	Kashiyama
	5,331,549 A	7/1994 Crawford, Jr.	5,941,725 A	8/1999	Brennan et al.
	5,332,330 A	7/1994 Kaneko	5,951,316 A	9/1999	Kawano et al.
	5,334,955 A	8/1994 Strnad	5,964,624 A	10/1999	Pernelle
	5,338,219 A	8/1994 Hiramoto et al.	5,968,087 A	10/1999	Hess et al.
	5,341,806 A	8/1994 Gadsby et al.	5,971,790 A	10/1999	Rohde
	5,341,812 A	8/1994 Allaire et al.	5,971,799 A	10/1999	Swade
	5,362,249 A	11/1994 Carter	5,980,332 A	11/1999	Tsuji et al.
	5,370,116 A	12/1994 Rollman et al.	5,984,717 A	11/1999	Lee
	5,370,550 A	12/1994 Alwine et al.	5,997,334 A	12/1999	Goto
	5,376,016 A	12/1994 Inaba et al.	6,027,359 A	2/2000	Aoki et al.
	5,378,168 A	1/1995 Sumida	6,032,063 A	2/2000	Hoar et al.
	5,380,223 A	1/1995 Marsh et al.	6,032,064 A	2/2000	Devlin et al.
	5,382,176 A	1/1995 Norden	6,038,479 A	3/2000	Werner et al.
	5,383,794 A	1/1995 Davis et al.	6,038,481 A	3/2000	Werner et al.
	5,387,116 A	2/1995 Wang	6,050,838 A	4/2000	Norizuki et al.
	5,387,127 A	2/1995 Wang	6,062,892 A	5/2000	Meng et al.
	5,399,045 A	3/1995 Yoneda et al.	6,062,902 A	5/2000	Buckles et al.
	5,415,164 A	5/1995 Faupel et al.	6,074,234 A	6/2000	Hasegawa
	5,429,526 A	7/1995 Ann	6,098,127 A	8/2000	Kwang
	5,454,739 A	10/1995 Strand	6,109,948 A	8/2000	Kuo
	5,462,448 A	10/1995 Kida et al.	6,115,623 A	9/2000	McFee
	5,486,117 A	1/1996 Chang	6,116,940 A	9/2000	Bertens
	5,507,665 A	4/1996 Oda	6,116,941 A	9/2000	Kuo
	5,507,668 A	4/1996 Lambrinos et al.	6,129,666 A	10/2000	DeLuca et al.
	5,509,822 A	4/1996 Negus et al.	6,132,233 A	10/2000	Fukuda
	5,511,546 A	4/1996 Hon			

(56)

References Cited

U.S. PATENT DOCUMENTS

6,139,350	A	10/2000	Mathesius	6,648,666	B1	11/2003	Wu
6,139,360	A	10/2000	Hayashi	6,654,626	B2	11/2003	Devlin et al.
6,152,778	A	11/2000	Dalton	6,655,979	B1	12/2003	Lee
6,155,864	A	12/2000	Yoshiura	6,659,790	B1	12/2003	Wu
6,165,017	A	12/2000	Kuo	6,663,412	B2	12/2003	Aramoto et al.
6,168,453	B1	1/2001	Kuo	6,663,419	B2	12/2003	Vaden
6,171,139	B1	1/2001	Sato et al.	6,663,420	B1	12/2003	Xiao
6,190,385	B1	2/2001	Tom et al.	6,663,570	B2	12/2003	Mott et al.
6,203,354	B1	3/2001	Kuwahara et al.	6,669,510	B2	12/2003	Yamawaki et al.
6,223,088	B1	4/2001	Scharnberg et al.	6,688,894	B2	2/2004	Knox, Jr. et al.
6,234,827	B1	5/2001	Nishio et al.	6,688,907	B2	2/2004	Yamaoka et al.
6,236,874	B1	5/2001	Devlin et al.	6,702,602	B2	3/2004	Wu
6,246,902	B1	6/2001	Naylor et al.	6,702,603	B2	3/2004	Wu
6,247,963	B1	6/2001	Rattner	6,702,616	B1	3/2004	Chang et al.
6,250,955	B1	6/2001	Archuleta	6,709,284	B1	3/2004	Avlonitis
6,254,425	B1	7/2001	Shchervinsky et al.	6,716,165	B1	4/2004	Flanders et al.
6,257,914	B1	7/2001	Comerci et al.	6,722,912	B2	4/2004	Wu
6,257,925	B1	7/2001	Jones	6,736,650	B1	5/2004	Chen et al.
6,280,209	B1	8/2001	Bassler et al.	6,743,052	B1	6/2004	Lin et al.
6,280,227	B1	8/2001	Terada et al.	6,743,053	B2	6/2004	Wu
6,280,243	B1	8/2001	Liu et al.	6,751,493	B2	6/2004	Wenger
6,283,789	B1	9/2001	Tsai	6,755,689	B2	6/2004	Zhang et al.
6,290,530	B1	9/2001	Chang	6,773,293	B1	8/2004	Lee
6,298,255	B1	10/2001	Cordero et al.	6,780,065	B2	8/2004	Schwarz
6,324,432	B1	11/2001	Rigaux et al.	6,786,755	B2	9/2004	Dambach et al.
6,340,306	B1	1/2002	Daoud	6,786,764	B2	9/2004	Sivertsen
6,356,779	B1	3/2002	Katzenmaier et al.	6,832,928	B2	12/2004	Suzuki
6,358,083	B1	3/2002	Kraft	6,837,734	B2	1/2005	Ushio et al.
6,364,685	B1	4/2002	Manning	6,848,926	B2	2/2005	Ling et al.
6,383,010	B1	5/2002	Mayo et al.	6,851,969	B2	2/2005	Archuletta
6,383,011	B2	5/2002	Chen	6,860,750	B1	3/2005	Wu
6,383,036	B1	5/2002	Steinhauser et al.	6,866,535	B2	3/2005	Uchida
6,386,917	B1	5/2002	Sakaguchi	6,881,098	B2	4/2005	Jeansonne et al.
6,393,317	B1	5/2002	Fukuda et al.	6,891,379	B2	5/2005	Kelly et al.
6,394,953	B1	5/2002	Devlin et al.	6,913,482	B1	7/2005	Wu
6,398,575	B1	6/2002	Bresson	6,939,158	B2	9/2005	Moffett et al.
6,398,577	B1	6/2002	Simmel et al.	6,939,345	B2	9/2005	KenKnight et al.
6,411,834	B1	6/2002	Nagai	6,945,796	B2	9/2005	Bassler et al.
6,413,112	B2	7/2002	Semmeling et al.	6,945,807	B1	9/2005	Wu
6,415,169	B1	7/2002	Kornrumpf et al.	6,948,973	B1	9/2005	Hsu et al.
6,419,636	B1	7/2002	Young et al.	6,984,143	B2	1/2006	Roose
6,434,410	B1	8/2002	Cordero et al.	6,997,733	B2	2/2006	Peng
D462,662	S	9/2002	Lindekugel	7,004,787	B2	2/2006	Milan
6,447,170	B1	9/2002	Takahashi et al.	7,008,255	B1	3/2006	Wang
6,454,577	B1	9/2002	Yi	7,025,618	B2	4/2006	Fukuda
6,454,590	B1	9/2002	Goodrich et al.	7,025,628	B2	4/2006	LaMeres et al.
6,454,605	B1	9/2002	Bassler et al.	7,029,286	B2	4/2006	Hall et al.
6,461,179	B1	10/2002	Sullivan et al.	7,033,207	B2	4/2006	Nimura
6,487,430	B1	11/2002	Henderson et al.	7,041,918	B1	5/2006	Wu
6,494,744	B1	12/2002	Lee	7,056,134	B2	6/2006	Martin et al.
6,514,099	B2	2/2003	Endo	7,056,141	B2	6/2006	Moffett et al.
6,517,372	B1	2/2003	Jones	7,081,008	B2	7/2006	Tan
6,531,657	B1	3/2003	Jones, Jr. et al.	7,085,598	B2	8/2006	Sato et al.
6,533,600	B1	3/2003	Kashiyama et al.	7,104,801	B1	9/2006	Brodnick et al.
6,540,549	B2	4/2003	Rupert	7,110,804	B2	9/2006	Baumer et al.
6,551,117	B2	4/2003	Poplawski et al.	7,117,590	B2	10/2006	Koenig et al.
6,558,189	B2	5/2003	Groebe et al.	7,118,411	B2	10/2006	Huang et al.
6,561,834	B2	5/2003	Chen	7,127,279	B2	10/2006	Finneran et al.
6,565,388	B1	5/2003	Van Woensel et al.	7,128,600	B2	10/2006	Osypka
6,567,680	B2	5/2003	Swetlik et al.	7,134,908	B2	11/2006	Wu
6,575,759	B1	6/2003	Ollivier	7,137,839	B2	11/2006	Dilliner et al.
6,575,794	B1	6/2003	Nakamura	7,144,268	B2	12/2006	Koenig et al.
6,582,252	B1	6/2003	Lin	7,160,136	B2	1/2007	Zhang et al.
6,589,066	B1	7/2003	Wu	7,177,673	B2	2/2007	Matsumura et al.
6,592,391	B1	7/2003	Wu	7,179,111	B2	2/2007	Van Der Mee et al.
6,592,404	B2	7/2003	Endo	7,179,113	B2	2/2007	Koenig et al.
6,604,963	B2	8/2003	Lin	7,182,630	B1	2/2007	Su
6,607,397	B1	8/2003	Zhang et al.	7,189,097	B2	3/2007	Benham
6,609,018	B2	8/2003	Cory et al.	7,198,502	B2	4/2007	Koenig et al.
6,609,833	B1	8/2003	Miyachi et al.	7,201,599	B2	4/2007	Holub
6,612,860	B2	9/2003	Droesbeke	7,207,825	B2	4/2007	LeGallic et al.
6,619,976	B2	9/2003	Huetter et al.	7,236,825	B2	6/2007	Wang
6,619,989	B1	9/2003	Yi	7,252,542	B2	8/2007	Chen
6,636,754	B1	10/2003	Baura et al.	7,252,556	B2	8/2007	Anbo et al.
6,648,665	B1	11/2003	Wu	7,252,565	B2	8/2007	Hunter
				7,258,566	B2	8/2007	Koenig et al.
				7,264,510	B2	9/2007	Koenig et al.
				7,270,568	B2	9/2007	Osypka
				7,272,427	B2	9/2007	Ristolainen

(56)

References Cited

U.S. PATENT DOCUMENTS

7,275,951 B2 10/2007 Shigeta et al.
 7,281,937 B2 10/2007 Reed et al.
 7,287,998 B2 10/2007 Masai
 7,303,430 B2 12/2007 Butcher
 7,318,740 B1 1/2008 Henry et al.
 7,322,849 B2 1/2008 Sutton
 7,329,139 B2 2/2008 Benham
 7,336,985 B2 2/2008 Wallace et al.
 7,347,710 B2 3/2008 Ohtaka et al.
 7,347,826 B1 3/2008 Karicherla et al.
 7,361,058 B1 4/2008 Lien et al.
 7,371,102 B2 5/2008 Sakamoto et al.
 7,373,196 B2 5/2008 Ryu et al.
 7,374,448 B1 5/2008 Jepsen et al.
 7,381,082 B2 6/2008 Lai
 7,390,224 B2 6/2008 Sodermann et al.
 7,396,246 B2 7/2008 Okada et al.
 7,399,195 B2 7/2008 Kim et al.
 7,401,946 B2 7/2008 Laukhuf
 7,402,071 B2 7/2008 Ohtaka et al.
 7,413,461 B2 8/2008 Dawiedczyk et al.
 7,413,485 B2 8/2008 Lappoehn
 7,416,440 B2 8/2008 Homyk et al.
 7,422,437 B1 9/2008 Lin et al.
 7,422,452 B2 9/2008 Achtner et al.
 7,462,074 B1 12/2008 Devlin et al.
 7,473,141 B2 1/2009 Liao
 7,488,187 B2 2/2009 Wolf
 7,494,383 B2 2/2009 Cohen et al.
 7,497,731 B2 3/2009 Rosenfeldt et al.
 7,497,738 B2 3/2009 Kuo
 7,497,740 B2 3/2009 Mei et al.
 7,503,807 B2 3/2009 Martin et al.
 7,544,089 B2 6/2009 Liu et al.
 7,553,184 B2 6/2009 Butcher

7,556,535 B2 7/2009 Liao
 7,581,992 B1 9/2009 Liu et al.
 7,585,182 B2 9/2009 Asante et al.
 7,591,673 B2 9/2009 Chan et al.
 7,591,674 B2 9/2009 Sutton et al.
 7,604,511 B1 10/2009 Johnson
 7,618,262 B2 11/2009 Fogg et al.
 7,618,377 B2 11/2009 McAtamney et al.
 7,632,130 B2 12/2009 Sami
 7,666,028 B2 2/2010 Meleck
 7,682,198 B1 3/2010 Plattner
 RE41,206 E 4/2010 Gwiazdowski et al.
 7,703,987 B2 4/2010 Kramer et al.
 7,713,073 B2 5/2010 Lin
 7,717,739 B2 5/2010 Hawkins et al.
 7,731,519 B1 6/2010 Swenson, Jr.
 7,731,520 B1 6/2010 Daily et al.
 7,740,510 B2 6/2010 Muz
 7,749,013 B2 7/2010 Sato et al.
 7,753,613 B2 7/2010 Tsuji
 7,828,583 B2 11/2010 Ohsumi et al.
 7,844,316 B1 11/2010 Botero
 8,591,427 B2* 11/2013 Zuckerman et al. 600/508
 8,634,901 B2 1/2014 Callahan et al.
 2008/0306380 A1 12/2008 Parchk et al.
 2009/0099423 A1 4/2009 Al-Ali et al.
 2010/0168547 A1 7/2010 Kendricks

OTHER PUBLICATIONS

PCT International Preliminary Report on Patentability dated Apr. 10, 2014; for PCT Pat. App. No. PCT/US2012/057760; 13 pages.
 PCT Search Report dated Mar. 7, 2013; for PCT Pat. App. No. PCT/US2012/057760.
 Canadian Office Action dated Aug. 20, 2015; for Canadian Pat. App. No. 2,850,336, 4 pages.

* cited by examiner




FIG. 1




FIG. 2A




FIG. 2B




FIG. 3B




FIG. 3A




FIG. 4




FIG. 5A




FIG. 5B




FIG. 6

ECG LEADWIRE SYSTEM WITH NOISE SUPPRESSION AND RELATED METHODS

RELATED APPLICATIONS

This is a DIVISIONAL application under 35 U.S.C. §121 of U.S. patent application Ser. No. 13/249,450 (filed Sep. 20, 2011), which is incorporated here by reference in its entirety.

TECHNICAL FIELD

The present disclosure relates to medical equipment. In particular, the present disclosure relates to an electrocardiograph (ECG) leadwire system having improved noise reduction characteristics that includes an ECG lead set, an adapter system, an extension cable, a noise reduction element, and methods for coupling the ECG lead sets with the adapter.

BACKGROUND

ECG lead systems are used to obtain biopotential signals containing information indicative of the electrical activity associated with the heart and pulmonary system. To obtain biopotential signals, ECG electrodes are applied to the skin of a patient in various locations and coupled to an ECG device, e.g., an "ECG monitor" or "ECG telemetry." Placement of the electrodes is dependent on the information sought by the clinician.

The placement of the ECG electrodes on the patient has been established by medical protocols. The most common protocols require the placement of the electrodes in a three-lead, a five-lead, or a twelve-lead configuration. A three-lead configuration requires the placement of three electrodes; one electrode adjacent each clavicle bone (RA, LA) on the upper chest and a third electrode adjacent the patient's lower left abdomen (LL). A five-lead configuration requires the placement of the three electrodes in the three-lead configuration with the addition of a fourth electrode adjacent the sternum (Va) and a fifth electrode on the patient's lower right abdomen (RL). A twelve-lead configuration requires the placement of ten electrodes on the patient's body. Four electrodes, which represent the patient's limbs, include the left arm electrode (LA lead), the right arm electrode (RA lead), the left leg electrode (LL lead), and the right leg electrode (RL lead). Six chest electrodes (V1-V6 leads) are placed on the patient's chest at various locations near the heart. Three standard limb leads are constructed from measurements between the right arm and left arm (Lead I), the right arm and the left leg (Lead II) and the left arm to left leg (Lead III). Other conventional lead configurations include a 14 leads system that incorporated additional leads located on a back surface.

An ECG lead set typically includes an array of three, five, or twelve leads as determined by the intended clinical protocol. Each individual lead wire includes, at a patient end thereof (e.g., distal end), an ECG lead wire connector configured to operably couple the lead wire to an electrode pad affixed to the body of a patient. At the opposite (e.g., proximal) end, the individual lead wires are gathered into a common coupler that is configured to operably couple the array of lead wires to an ECG device. Leads sets are typically provided with a generous length of lead wire sufficient to reach from the patient to the ECG device. In some instances, however, the lead wire may fall short, in which case a lead wire extension cable having appropriate distal and proximal couplers may be employed. In some instances, the lead wire coupler of an ECG lead set and/or ECG lead extension may be incompatible with an available ECG device, in which case an

ECG adapter may be employed that facilitates operable coupling of the otherwise-incompatible physical and/or electrical characteristics of the disparate couplers.

Radio frequency interference (RFI), sometime referred to as electromagnetic interference (EMI), is a disturbance that affects an electrical circuit due to either electromagnetic induction or electromagnetic radiation emitted from an external source. The disturbance may interrupt, obstruct, or otherwise degrade or limit the effective performance of a circuit. Biopotential signals are generally very low-level signals, and a typical ECG device has a very high input impedance. As a result, biopotential signals may be susceptible to RFI, particularly from devices that may be in use concurrently in a clinical environment, e.g., an electrosurgical instrument, or a microwave ablation unit. RFI may be exacerbated when an ECG lead wire extension cable is used.

SUMMARY

The present disclosure is directed to a noise-suppressing ECG adapter. In some embodiments the disclosed adapter includes a housing having a first end and a second end, and at least one first connector disposed at the first end of the housing. The at least one first connector is adapted for operably coupling to a proximal end of an ECG lead set. The disclosed adapter includes at least one second connector disposed at the second end of the housing that is adapted for coupling to an input of an ECG device. A noise suppression element is disposed within the housing, and includes one of a ferromagnetic element and an electromagnet having an opening defined therein. A least one conductor operably couples the first connector and the second connector, and passes through the opening defined in the ferromagnetic element. The noise suppression element of the adapter may include a low pass filter, a high pass filter, a notch filter, or a nyquist filter. In some embodiments, a connector includes a six-pin configuration. In some embodiments, the six-pin configuration comprises five signal pins and one ground pin. In some embodiments, a connector includes one signal pin and one ground pin.

In some embodiments, the ferromagnetic element includes a shape selected from the group consisting of a toroid and an open cylinder. The ferromagnetic element may be formed from material selected from the group consisting of ferrite and laminated iron. At least one conductor may pass through the opening of the ferromagnetic element in a plurality of windings.

Also disclosed is a noise-suppressing ECG system. In some embodiments, the disclosed system includes a noise-suppressing ECG adapter, comprising a housing having a first end and a second end, at least one first connector disposed at the first end of the housing, the at least one first connector adapted for operably coupling to proximal end of ECG lead set. The adapter includes at least one second connector disposed at the second end of the housing adapted for coupling to an input of an ECG device. The adapter includes a noise suppression element disposed within the housing, the noise suppression element including a ferromagnetic element having an opening defined therein, and at least one conductor operably coupling the first connector and the second connector and passing through the opening of the ferromagnetic element. The system includes an ECG device adapted to operably couple to the at least one second connector of the noise-suppressing ECG adapter.

In some embodiments, the disclosed noise-suppressing ECG system includes an ECG lead set including a plurality of lead wires at a distal end thereof that are configured to oper-

ably couple to a plurality of ECG pads, and at least one ECG connector disposed at a proximal end of ECG leadwire set. The noise-suppressing ECG system, in some embodiments, includes a noise suppression element that includes a low pass filter, a high pass filter, a notch filter and a nyquist filter.

In some embodiments, the disclosed noise-suppressing ECG system includes an ECG adapter having a connector having a six-pin configuration. The six-pin configuration may include five signal pins and one ground pin. Other embodiments may include a connector that contains 12 pins with 2 separate grounds pins. Still other examples may utilize shielded leadwires that use two pins for each contact, one for signal and one for shield.

In some embodiments, the disclosed noise-suppressing ECG system includes an ECG adapter having a connector that includes one signal pin and one ground pin.

In some embodiments, the disclosed noise-suppressing ECG system includes an ECG adapter having a ferromagnetic element that includes a shape selected from the group consisting of a toroid and an open cylinder.

In some embodiments, the disclosed noise-suppressing ECG system includes an ECG adapter wherein the at least one conductor passes through the opening of the ferromagnetic element in a plurality of windings. In another embodiment, electromagnets could be actuated as part of the interface to the ECG monitor so that the magnetic field used to attenuate the electromagnetic interference would only be present when the ECG system was in use.

In some embodiments, the disclosed noise-suppressing ECG system includes an ECG adapter wherein the ferromagnetic element is formed from material selected from the group consisting of ferrite and laminated iron.

Also disclosed is a method of suppressing noise in an ECG system. In some embodiments, the disclosed method includes providing an ECG adapter including an ECG leadwire connector, an ECG device connector, and a noise suppression element. The method includes operably coupling the ECG device connector to an ECG device, and operably coupling an ECG leadwire set to the ECG leadwire connector.

In some embodiments, the disclosed method of suppressing noise in an ECG system includes positioning the noise suppression element around at least a portion of the ECG leadwire set. In some embodiments, the disclosed method of suppressing noise in an ECG system includes a positioning step that further includes closing two semicylindrical halves of a ferromagnetic collar around at least a portion of the ECG leadwire set.

Other advantages, novel features, and objects of the present disclosure will become apparent from the following detailed description of the present disclosure when considered in conjunction with the accompanying drawings, which are schematic and are not intended to be drawn to scale. For purposes of clarity, not every component is labeled in every figure, nor is every component of each embodiment of the present disclosure shown where illustration is not necessary to allow those of ordinary skill in the art to understand the present disclosure.

BRIEF DESCRIPTION OF THE DRAWINGS

Various embodiments of the subject instrument are described herein with reference to the drawings wherein:

FIG. 1 is a schematic view of an embodiment of a noise suppressing adapter in accordance with the present disclosure;

FIG. 2A is a schematic view of an embodiment of a noise suppressing collar annexed to an adapter;

FIG. 2B is a schematic view of an embodiment of the noise suppressing collar of FIG. 2A operatively coupled to a set of leadwires in accordance with the present disclosure;

FIG. 3A is a schematic view of another embodiment of a noise suppressing collar in accordance with the present disclosure;

FIG. 3B is a schematic view of a variation of the FIG. 3A embodiment of a noise suppressing collar in accordance with the present disclosure;

FIG. 4 is a schematic view of the FIG. 3A embodiment of a noise suppressing collar operatively coupled to a set of leadwires in accordance with the present disclosure;

FIG. 5A is a view of still another embodiment of a noise suppressing adapter in accordance with the present disclosure;

FIG. 5B is a circuit diagram of the FIG. 5A embodiment; and

FIG. 6 is a view of yet another embodiment of a noise suppressing adapter in accordance with the present disclosure.

DETAILED DESCRIPTION

Particular embodiments of the present disclosure are described hereinbelow with reference to the accompanying drawings; however, it is to be understood that the disclosed embodiments are merely examples of the disclosure, which may be embodied in various forms. The terminology used herein is for the purpose of describing particular embodiments only, and is not intended to be limiting. Well-known and/or repetitive functions and constructions are not described in detail to avoid obscuring the present disclosure in unnecessary or redundant detail. Therefore, specific structural and functional details disclosed herein are not to be interpreted as limiting, but merely as a basis for the claims and as a representative basis for teaching one skilled in the art to variously employ the present disclosure in virtually any appropriately detailed structure. As used herein, and as is traditional, the term “distal” refers to the portion which is furthest from the user/clinician and the term “proximal” refers to the portion that is closest to the user/clinician. In addition, terms such as “above,” “below,” “forward,” “rearward,” etc. refer to the orientation of the figures or the direction of components and are simply used for convenience of description. It is to be understood that embodiments in accordance with the present disclosure may be practiced in any orientation without limitation. In this description, as well as in the drawings, like-referenced numbers represent elements which may perform the same, similar, or equivalent functions. References to connector gender presented herein are for illustrative purposes only, and embodiments are envisioned wherein the various components described can be any of mate, female, hermaphroditic, or sexless gender. Likewise, references to connector types are illustrative in nature, and other connector types, shapes and configurations are contemplated within the scope of the present disclosure.

With reference to FIG. 1, an ECG monitoring system 10 having a noise suppressing ECG adapter 20 is shown. According to one embodiment of the present disclosure, the system 10 enables an end user to use a single ECG leadwire set 30 in association with one or more disparate ECG devices 11, e.g., an ECG monitoring device and/or an ECG telemetry device, as desired. ECG adapter 20 includes an adapter housing 21 having a first end 22 and a second end 24. In the embodiment shown in FIG. 1, first end 22 includes a pin configuration having a six-pin arrangement that is adapted to operably couple with a corresponding, mating six-pin connector 34

disposed at a proximal end of ECG leadwire set **130** having one or more ECG electrode connectors **32** adapted to operatively couple to an ECG electrode pad affixed to a patient. ECG adapter second end **24** includes a pin configuration adapted to mate with a corresponding connector provided by ECG device **11**.

Noise suppression element may be formed from any material having suitable electromagnetic, coercivity, and permeability properties, including without limitation, ferrite, laminated iron, and the like. In one embodiment, the noise suppression element is one of a ferromagnetic element and an electromagnet. An electromagnet noise suppression element may draw power from a monitor to which it is connected. An electromagnetic noise suppression element may be actuated as part of an interface to an ECG monitor so that the magnetic field used to attenuate the electromagnetic interference would only be present when the ECG system was in use.

The noise suppression element may include a filter such as a low pass filter, a high pass filter, a notch filter, and a nyquist filter. The passive low pass filter exhibits high impedance at high frequencies typically associated with RFI, which, in turn, attenuates or suppresses RFI within the one or more leadwires **134** and/or high-impedance input circuit of the ECG device.

The pin configurations of first end **22** and/or second end **24** may vary depending on the desired application, the intended ECG device(s) **110** to be used, and the specific lead set or lead sets to be used. For example, and without limitation, pin configuration of first end **22** may include only a single pin used in an unshielded configuration of a single electrode lead set. In another non-limiting example, the pin configuration of second end **24** of ECG connector **20** may include a five-pin male socket connector. In this example, each plug includes a pair of contacts, wherein one plug corresponds to one ECG lead and the corresponding plug corresponds to a ground or shield lead, such as specified by ANSI/AAMI EC53 for shielded leadwire to trunk cable interconnections. The second end **24** of ECG connector **20** may be referred to as monitor plugs. The second end or monitor plugs **24** are configured for coupling to the lead set input connector of ECG device **11**.

ECG adapter **20** includes a tether boss **23** that enables one or more tethers, e.g., an additional noise suppressor tether (not shown) and/or a placard tether (not shown), to be affixed thereto. As shown, tether boss **23** includes a u-shaped protuberance having an opening defined therein that extends from an exterior surface of ECG connector **20**, however, other tether boss arrangements are contemplated, such as, and without limitation, to a recess with a transverse pin arrangement. A placard annexed to connector **20** may include an inscription conveying operating instructions, e.g., "STOP-Do Not Discard-Reusable" and the like.

Turning to FIGS. 2A and 2B, ECG adapter **120** includes a noise suppressor collar **150** that is annexed thereto by noise suppressor tether **155**. In one embodiment, adapter **120** does not comprise a noise suppression component within its housing. In one embodiment, the noise suppression element is one of a ferromagnetic element and an electromagnet. An electromagnet noise suppression element may draw power from a monitor to which it is connected. An electromagnetic noise suppression element may be actuated as part of an interface to an ECG monitor so that the magnetic field used to attenuate the electromagnetic interference would only be present when the ECG system was in use.

In another embodiment, adapter **120** may be a noise suppression adapter comprising a noise suppression component within its housing. The noise suppression element in the adapter may, but need not, be of a similar type to that used in

the noise suppression collar. For example, the noise suppression element in the adapter may be one of a ferromagnetic element and an electromagnet, while the noise suppression collar may be the other of the ferromagnetic element and the electromagnet. Alternatively, the noise suppression adapter and the noise suppression collar may comprise both a ferromagnetic element or both comprise an electromagnet.

In one embodiment, the noise suppression adapter may comprise a first filter and the noise suppression collar may comprise a second filter, which may, but need not, be the same type of filter as the first filter. For example, the noise suppression adapter may comprise one of a low pass filter, a high pass filter, a notch filter, and a nyquist filter, while the noise suppression collar may comprise a different one of a low pass filter, a high pass filter, a notch filter, and a nyquist filter.

Noise suppressor collar may **150** include a tether boss **153** that is adapted to enable noise suppressor tether **155** to be affixed to collar **150**. Noise suppressor collar **150** is selectively configurable between an open configuration as illustrated in FIG. 2A, and a closed configuration as illustrated in FIG. 2B. When configured in a closed configuration, noise suppressor collar **150** has a generally open cylindrical or tubular (e.g., pipe-like or elongate toroid) shape having an inner diameter "D" that is dimensioned to enable one or more ECG leadwires **134** to pass therethrough. In this embodiment, it is believed that noise suppressor collar **150** forms a common mode choke that suppresses RFI induced by stray electromagnetic fields propagating upon the one or more ECG leadwires **134**.

Noise suppressor collar **150** may be formed from any material having suitable electromagnetic, coercivity, and permeability properties, including without limitation, ferrite, laminated iron, and the like. The noise suppressor collar may include a filter, such as, a low pass filter, a high pass filter, a notch filter, and a nyquist filter. It is believed that this composition, e.g., ferrite, in cooperation with the open cylindrical or tubular shape of noise suppressor collar **150**, forms a passive low-pass filter. The passive low pass filter exhibits high impedance at high frequencies typically associated with RFI, which, in turn, attenuates or suppresses RFI within the one or more leadwires **134** and/or high-impedance input circuit of the ECG device.

In an exemplary embodiment, noise suppressor collar **150** is formed from two generally semi-cylindrical halves consisting of a collar bottom portion **152** and a collar top portion **154** that are joined along a common edge by a hinge **158**. In various embodiments, hinge **158** may include a living hinge, a piano hinge, or any suitable hinge arrangement. Collar top portion **154** includes a clasp **156** that is configured to engage a corresponding clasp saddle (not explicitly shown) provided by collar bottom portion **152** to join collar bottom portion **152** and collar top portion **154** in the closed configuration shown in FIG. 2. Noise suppressor collar **150** may additionally or optionally include a jacket **157**, **159** covering at least a part of a surface of collar bottom portion **152** and a collar top portion **154**. Jacket **157**, **159** may be formed from any suitable material, such as a polymeric material including without limitation high density polyethylene, polyurethane, and acrylonitrile butadiene styrene. In an embodiment, jacket **157**, **159**, and hinge **158** may be integrally formed, e.g., from polypropylene. In this embodiment hinge **158** may be in the form of a living hinge.

During use, a clinician may couple connector **134** of ECG leadwire set **130** with first end **122** of ECG adapter **120**. A clinician may separate the two portions **152**, **154** of noise suppressor collar **150**, e.g., move collar bottom portion **152** and collar top portion **154** to the open configuration as illus-

trated in FIG. 1. One or more leadwires 134 are positioned between the inner portions of collar bottom portion 152 and collar top portion 154, and the collar bottom portion 152 and collar top portion 154 are moved to the closed configuration as illustrated in FIG. 2. The second end 124 of ECG adapter 120 is mated to an ECG device 110. One or more ECG pads are affixed to a patient, and the one or more ECG electrode connectors 132 are affixed to the one or more ECG pads in accordance with the appropriate protocol (e.g., a three-lead, a five-lead, or a twelve-lead configuration). The ECG device may be activated to commence ECG monitoring, ECG telemetry, and the like.

Turning to FIGS. 3A and 4, another embodiment of an ECG adapter 220 in accordance with the present disclosure includes a first end 222 that is operatively coupled to a second end 224 by one or more ECG conductors 226. First end 222 of ECG adapter 220 includes a first connector 223 that is adapted to operably couple with a corresponding, mating six-pin connector 234 disposed at a proximal end of ECG leadwire set 230 having one or more ECG electrode connectors 232 adapted to operably couple to an ECG electrode pad affixed to a patient. ECG adapter 220 second end 224 includes a second connector 225 adapted to mate with a corresponding connector provided by ECG device 210.

ECG adapter 220 includes a noise suppressor collar 228 having a generally open cylindrical or tubular shape (e.g., pipe-like or elongate toroid) that is disposed about at least a portion of the one or more ECG conductors 226. Noise suppressor collar 228 includes an inner diameter that is dimensioned to enable one or more ECG leadwires 226 to pass therethrough. Noise suppressor collar 228 may be formed from any material having suitable electromagnetic, coercivity, and permeability properties as previously described herein, such as, for example, ferrite, laminated iron, and the like. In embodiments, noise suppressor collar 228 may be fixed to the one or more ECG leadwires 226 by any suitable manner of attachment, including without limitation, by an adhesive, by encapsulation, by encasing in heat shrink tubing, and the like. In some embodiments, such as that illustrated in FIG. 3B, an ECG adapter 220' includes a noise suppressor collar 228' that is integrally formed with ECG leadwires 226', a first end 222', and/or a second end 224', wherein ECG adapter 220' is encapsulated in a heat shrink tubing.

During use, as seen in FIG. 4, a clinician may couple connector 234 of ECG leadwire set 230 to first end 222 of ECG adapter 220, and second end 224 of ECG adapter 220 is mated to an ECG device 210. One or more ECG pads are affixed to a patient, and the one or more ECG electrode connectors 232 are affixed to the one or more ECG pads in accordance with the appropriate protocol (e.g., a three-lead, a five-lead, or a twelve-lead configuration). The ECG device may be activated to commence ECG monitoring, ECG telemetry, and the like.

Turning now to FIGS. 5A and 5B, still another embodiment of an ECG noise suppression adapter 300 is presented in accordance with the present disclosure. ECG noise suppression adapter 300 includes a housing 320 having a first end 322 and a second end 324. First end 322 includes one or more input terminals 321a-f that are adapted to operably couple with one or more corresponding, mating pins disposed at a proximal end of ECG leadwire set (not explicitly shown) to receive ECG signals therefrom. Second end 324 of housing 320 of ECG noise suppression adapter 300 includes one or more second connectors 325a-e adapted to mate with one or more corresponding connectors provided by an ECG device. In the present embodiment, the one or more second connectors 325a-e includes a pair of contacts, wherein one plug

corresponds to one ECG lead and the corresponding plug corresponds to a ground or shield lead, such as specified by ANSI/AAMI EC53 for shielded leadwire to trunk cable interconnections, as described above.

ECG noise suppression adapter 300 includes a toroidal inductor core 328. Toroidal inductor core 328 may be formed from any material having suitable electromagnetic, coercivity, and permeability properties as previously described herein, such as, without limitation, ferrite and/or laminated iron. One or more ECG conductors 326 are coupled, at a distal end thereof, to one or more input terminals 321a-f. In the present example, six ECG conductors 326 are shown which correspond to input terminals 321a-e (e.g., ECG signals 1 through 5, respectively) and to input terminal 321f that is coupled to a ground (e.g., shield) conductor. The conductors 326 pass around the toroidal inductor core 328 in a plurality of windings to form a low pass choke, or filter, that exhibits high impedance at high frequencies typically associated with RFI as previously described. Conductors 326 may be wound around toroidal inductor core 328 at least one turn, and in some embodiments, may be wound at least five turns, at least ten turns, and/or at least twenty-five turns. In some embodiments, conductors 326 may be grouped and wound collectively, e.g., as a unified cable bundle wound together around toroidal inductor core 328.

In some embodiments, conductors 326 may be individually wound around toroidal inductor core 328. At a proximal end, conductors 326 are operably coupled to corresponding second (output) connectors 325a-e. As shown in FIG. 5B, input pins 321a-e are operably coupled to a signal portion of output connectors 325a-e, respectively, and input pin 321f is operably coupled in common to a ground portion of output connectors 325a-e. It is to be understood that the arrangement and correspondence of inputs and outputs may differ in various and alternative embodiments, particularly where disparate ECG leadwire assemblies are to be coupled to ECG devices that provide differing or non-standard ECG input connectors, as will be appreciated by the skilled artisan.

Housing 320 may be formed from any suitable electrically non-conductive material, including without limitation polymeric material such as polyurethane, polypropylene, polyethylene, acrylonitrile butadiene styrene, polystyrene, polyvinyl chloride, polyacetal, polymethyl methacrylate and acetals. In embodiments, housing 320 may be fabricated by injection molding and/or overmolding around the components of ECG noise suppression adapter 300, e.g., input pins 321a-f and output connectors 325a-e, that mechanically supports and electrically insulates the electrically conductive element(s) therewithin, e.g., toroidal inductor core 328, and/or conductors 326.

Turning now to FIG. 6, yet another embodiment of an ECG noise suppression adapter 400 is presented. ECG noise suppression adapter 400 includes a housing 420 having a first end 422 and a second end 424. ECG noise suppression adapter 400 includes a noise suppression core 428 that has a generally open cylindrical shape and is formed from any material having suitable electromagnetic, coercivity, and permeability properties as previously described herein, such as, without limitation, ferrite and/or laminated iron. One or more ECG conductors 426 are coupled, at a distal end thereof, to one or more input terminals 421, and at a proximal end thereof, to one or more output connectors 425. In the present example, six ECG conductors 426 are shown wherein input terminals 421a-e corresponding to ECG signals 1 through 5, respectively, are operatively coupled by conductors 426a-e to output connectors 425a-e, respectively. Input terminal 421f is coupled to a ground (e.g., shield) conductor 426f, which, in

turn, is coupled to common ground terminals of output connectors **425a-e**. Conductors **426a-f** pass through noise suppression core **428** to form a low pass choke, or filter, that exhibits high impedance at high frequencies typically associated with RFI as previously described.

One or more input terminals **421** are adapted to operably couple with one or more corresponding, mating pins disposed at a proximal end of ECG leadwire set (not explicitly shown) to receive ECG signals therefrom. Second end **424** includes one or more second connectors **425** adapted to mate with one or more corresponding connectors provided by an ECG device. At a proximal end, conductors **426a-f** are operably coupled to corresponding second (output) connectors **425a-e**. It is to be understood that the arrangement and correspondence of inputs and outputs may differ in various and alternative embodiments, particularly where disparate ECG leadwire assemblies are to be coupled to ECG devices that provide differing or non-standard ECG input connectors, as will be appreciated by the skilled artisan.

Housing **420** may be formed from any suitable electrically non-conductive material, including without limitation polymeric material such as polyurethane, polypropylene, polyethylene, or acrylonitrile butadiene styrene. In embodiments, housing **420** may be fabricated by injection molding and/or overmolding around the components of ECG noise suppression adapter **400**, e.g., input pins **421a-f** and output connectors **425a-e**, to mechanically support and electrically insulate the electrically conductive element(s) therewithin, e.g., noise suppression core **428**, and/or conductors **426**.

While several embodiments of the disclosure have been shown in the drawings and/or discussed herein, it is not intended that the disclosure be limited thereto, as it is intended that the disclosure be as broad in scope as the art will allow and that the specification be read likewise. Therefore, the above description should not be construed as limiting, but merely as exemplifications of particular embodiments. Those skilled in the art will envision other modifications within the scope and spirit of the claims appended hereto.

What is claimed is:

1. A noise-suppressing ECG adapter, comprising:
 - a housing having a first end and a second end;
 - at least one first connector disposed at the first end of the housing, the at least one first connector adapted for operably coupling to a proximal end of an ECG lead set;
 - at least one second connector disposed at the second end of the housing, the at least one second connector adapted for coupling to an input of an ECG device;
 - a noise suppression element disposed within the housing, the noise suppression element including one of a ferromagnetic element and an electromagnet having an opening defined therein; and
 - at least one conductor operably coupling the first connector and the second connector and passing through the opening of the one of the ferromagnetic element and the electromagnet,
 - wherein the noise suppression element includes the ferromagnetic element formed from material selected from the group consisting of ferrite and laminated iron.
2. The noise-suppressing ECG adapter according to claim 1, wherein the noise suppression element includes one of a low pass filter, a high pass filter, a notch filter, or a nyquist filter.
3. The noise-suppressing ECG adapter according to claim 1, wherein the at least one first connector includes a six-pin configuration.

4. The noise-suppressing ECG adapter according to claim 3, wherein the six-pin configuration comprises five signal pins and one ground pin.

5. The noise-suppressing ECG adapter according to claim 1, wherein the at least one second connector includes one signal pin and one ground pin.

6. The noise-suppressing ECG adapter according to claim 1, wherein the one of the ferromagnetic element and the electromagnet includes a shape selected from the group consisting of a toroid and an open cylinder.

7. The noise-suppressing ECG adapter according to claim 1, wherein the at least one conductor passes through the opening of the ferromagnetic element in a plurality of windings.

8. A noise-suppressing ECG system, comprising:

- a noise-suppressing ECG adapter, comprising:
 - a housing having a first end and a second end;
 - at least one first connector disposed at the first end of the housing, the at least one first connector adapted for operably coupling to proximal end of an ECG lead set;
 - at least one second connector disposed at the second end of the housing, the at least one second connector adapted for coupling to an input of an ECG device;
 - a noise suppression element disposed within the housing, the noise suppression element including one of a ferromagnetic element and an electromagnet having an opening defined therein; and
 - at least one conductor operably coupling the first connector and the second connector and passing through the opening of the one of the ferromagnetic element and the electromagnet; and
 - an ECG device adapted to operably couple to the at least one second connector of the noise-suppressing ECG adapter,
 - wherein the noise suppression element includes the ferromagnetic element formed from material selected from the group consisting of ferrite and laminated iron.

9. The noise-suppressing ECG system according to claim 8, further comprising the ECG lead set including a plurality of lead wires at a distal end of the ECG lead set configured to operably couple to a plurality of ECG pads, and an ECG connector disposed at a proximal end of the ECG lead set.

10. The noise-suppressing ECG system according to claim 8, wherein the noise suppression element includes one of a low pass filter, a high pass filter, a notch filter and a nyquist filter.

11. The noise-suppressing ECG system according to claim 8, wherein the at least one first connector includes a six-pin configuration.

12. The noise-suppressing ECG system according to claim 11 wherein the six-pin configuration comprises five signal pins and one ground pin.

13. The noise-suppressing ECG system according to claim 8, wherein the at least one second connector includes one signal pin and one ground pin.

14. The noise-suppressing ECG system according to claim 8, wherein the one of the ferromagnetic element and the electromagnet includes a shape selected from the group consisting of a toroid and an open cylinder.

15. The noise-suppressing ECG system according to claim 14, wherein the at least one conductor passes through the opening of the ferromagnetic element in a plurality of windings.

16. A removable radio frequency interference (RFI) noise-suppressing ECG adapter, comprising:

a housing having a first end and a second end;
 at least one first connector disposed at the first end of the
 housing, the at least one first connector adapted for
 operably coupling to a connector of an ECG lead set that
 is adapted to connect to an ECG monitoring device; 5
 at least one second connector disposed at the second end of
 the housing, the at least one second connector adapted
 for coupling to an external input connector of the ECG
 monitoring device that is adapted to connect to the con-
 nector of the ECG lead set; 10
 an RFI noise suppression element disposed within the
 housing, the noise suppression element including one of
 a ferromagnetic element and an electromagnet having an
 opening defined therein; and
 at least one conductor operably coupling at least one pin of 15
 the first connector and at least one pin of the second
 connector and passing through the opening of the one of
 the ferromagnetic element and the electromagnet;
 wherein the ECG adapter is a removable adapter config-
 ured to be installed external to the ECG monitoring 20
 device and between the ECG monitoring device and the
 ECG lead set to suppress RFI noise,
 wherein the RFI noise suppression element includes the
 ferromagnetic element formed from material selected
 from the group consisting of ferrite and laminated iron. 25

* * * * *

专利名称(译)	具有噪声抑制和相关方法的ECG导联线系统		
公开(公告)号	US9375162	公开(公告)日	2016-06-28
申请号	US14/135239	申请日	2013-12-19
[标]申请(专利权)人(译)	柯惠有限合伙公司		
申请(专利权)人(译)	COVIDIEN LP		
当前申请(专利权)人(译)	COVIDIEN LP		
[标]发明人	CALLAHAN MARK J GILBERT GLENN COGGINS SCOTT R DELIA LINDA		
发明人	CALLAHAN, MARK J. GILBERT, GLENN COGGINS, SCOTT R. D'ELIA, LINDA		
IPC分类号	A61B5/0428 H01R31/06 H05K9/00 H01F17/06 H01R13/719 A61B5/0402 A61B5/04 A61B5/00 H03H1/00		
CPC分类号	A61B5/04286 A61B5/0402 A61B5/04017 A61B5/7217 H01F17/06 H01R13/719 H01R31/065 H05K9/0066 A61B2562/182 A61B2562/227 H01F2017/065 H01R2201/12 H03H2001/005		
其他公开文献	US20140221856A1		
外部链接	Espacenet USPTO		

摘要(译)

提出了具有第一端，第二端和噪声抑制元件的噪声抑制心电图（ECG）适配器，以及ECG噪声抑制系统和相关方法。在一个实施例中，所述噪声抑制ECG适配器包括壳体，所述壳体具有至少一个第一连接器，所述第一连接器设置在所述壳体的第一端，适于与ECG引线组电连接；以及至少一个第二连接器，适于连接到输入端。心电图设备。适配器包括噪声抑制元件。噪声抑制元件包括铁磁元件，铁磁元件具有限定在其中的开口。在一个实施例中，噪声抑制元件在适配器内部。在另一个实施例中，噪声抑制元件在适配器外部系留并且被配置为夹紧ECG导联线的至少一部分。

