



US010531861B2

(12) **United States Patent**
Abe

(10) **Patent No.:** **US 10,531,861 B2**
(45) **Date of Patent:** **Jan. 14, 2020**

(54) **ULTRASONIC DIAGNOSIS APPARATUS**

- (71) Applicant: **Toshiba Medical Systems Corporation**, Otawara-shi (JP)
- (72) Inventor: **Yasuhiko Abe**, Otawara (JP)
- (73) Assignee: **Canon Medical Systems Corporation**, Otawara-shi (JP)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 687 days.

(21) Appl. No.: **14/663,108**

(22) Filed: **Mar. 19, 2015**

(65) **Prior Publication Data**
US 2015/0223781 A1 Aug. 13, 2015

Related U.S. Application Data
(63) Continuation of application No. PCT/JP2013/077177, filed on Oct. 4, 2013.

(30) **Foreign Application Priority Data**
Oct. 4, 2012 (JP) 2012-222590

(51) **Int. Cl.**
A61B 8/08 (2006.01)
A61B 8/12 (2006.01)
A61B 8/06 (2006.01)

(52) **U.S. Cl.**
CPC *A61B 8/488* (2013.01); *A61B 8/065* (2013.01); *A61B 8/0883* (2013.01); *A61B 8/12* (2013.01)

(58) **Field of Classification Search**
CPC A61B 8/488
See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

- 5,148,808 A * 9/1992 Satake A61B 8/06 600/441
- 5,249,577 A * 10/1993 Shinomura A61B 8/06 600/441

(Continued)

FOREIGN PATENT DOCUMENTS

- CN 20980680 Y 11/2007
- CN 101094611 A 12/2007

(Continued)

OTHER PUBLICATIONS

Office Action dated Mar. 24, 2016 in Chinese Patent Application No. 201380052105.5 (with English translation of category of cited documents).


(Continued)

Primary Examiner — Rochelle D Turchen
(74) *Attorney, Agent, or Firm* — Oblon, McClelland, Maier & Neustadt, L.L.P.

(57) **ABSTRACT**

An ultrasound diagnosis apparatus includes an ultrasound transceiver and a controller. The ultrasound transceiver includes a changer that changes transmission direction of ultrasound waves. The ultrasound transceiver transmits ultrasound waves in a direction set while being inserted in a subject to acquire biological information of an observation site of the subject. The controller obtains a direction toward the observation site based on the biological information, and controls the changer to adjust the transmission direction of ultrasound waves to the direction thus obtained.

18 Claims, 28 Drawing Sheets



(56)

References Cited

U.S. PATENT DOCUMENTS

6,645,147	B1 *	11/2003	Jackson	A61B 8/06 600/458
8,923,949	B2	12/2014	Amit	
2007/0016050	A1 *	1/2007	Moehring	A61B 8/06 600/454
2007/0016072	A1 *	1/2007	Grunwald	A61B 5/06 600/468
2008/0081993	A1	4/2008	Waki	
2008/0097217	A1 *	4/2008	Itoh	A61B 5/6848 600/459
2009/0048489	A1	2/2009	Igarashi et al.	
2009/0069684	A1 *	3/2009	Shibata	A61B 8/0833 600/443
2009/0149759	A1	6/2009	Baba et al.	
2010/0249597	A1 *	9/2010	Shi	A61B 8/06 600/454
2010/0312109	A1	12/2010	Satoh	

2013/0308850	A1 *	11/2013	Oikawa	G01S 7/52085 382/131
2013/0331702	A1 *	12/2013	Yan	A61B 5/022 600/454

FOREIGN PATENT DOCUMENTS

CN	101268953	A	9/2008
CN	10144998	A	6/2009
JP	05-161649	A	6/1993
JP	2002-306485	A	10/2002
JP	2006-150053	A	6/2006
JP	2010-279506	A	12/2010
JP	2012-081362	A	4/2012

OTHER PUBLICATIONS

International Search Report dated Nov. 12, 2013 for PCT/JP2013/077177 filed Oct. 4, 2013 with English Translation.

* cited by examiner

FIG. 1




FIG. 2A




FIG. 2B




FIG. 2C




FIG. 2D




FIG. 3A




FIG. 3B




FIG. 3C




FIG. 3D




FIG. 4




FIG. 5




FIG. 6




FIG. 7A




FIG. 7B




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12A




FIG. 12B




FIG. 13




FIG. 14




FIG. 15




FIG. 16




FIG. 17




FIG. 18




FIG. 19




FIG. 20A





FIG. 20B



ULTRASONIC DIAGNOSIS APPARATUS

CROSS-REFERENCE TO RELATED APPLICATION

This application is based upon and claims the benefit of priority from Japanese Patent Application No. 2012-222590, filed Oct. 4, 2012; the entire contents of which are incorporated herein by reference.

FIELD

Embodiments described herein relate generally to an ultrasound diagnosis apparatus.

BACKGROUND

A medical image diagnosis apparatus is a device that creates, for examination and diagnosis, medical images (B-mode image, blood flow image, etc.) from information on tissues in a subject without surgical removal of the tissues. Examples of such medical image diagnosis apparatus include X-ray diagnosis apparatuses, X-ray CT (Computed Tomography) apparatuses, MRI (Magnetic Resonance Imaging) apparatuses, and ultrasound diagnosis apparatuses.

In one example, after the image of a subject is captured, the medical image is stored in a medical image system (e.g., PACS; Picture Archiving and Communication Systems) in a healthcare institution. After that, a radiologist or the like retrieves the medical image from the medical image archive system to interpret it. In another example, after the image of a subject is captured, the medical image is displayed immediately (in real time) for inspection by a doctor or the like. In this manner, medical images may be used so that a doctor or the like can promptly know about conditions inside the subject's body. In still another example, medical images may be used to monitor conditions inside the subject's body during a specific period for a follow-up. An ultrasound diagnosis apparatus may be used in this monitoring. In this case, the ultrasound diagnosis apparatus is used in consideration of such a point as that it does not cause radiation exposure to the subject.

In one example of examination and diagnosis, when conditions inside the subject's body are monitored for a certain period, it may be difficult to keep the subject in a gantry (an X-ray CT apparatus, an MRI apparatus, etc.) depending on the length of the period. The same is applied to X-ray diagnosis apparatuses that require the subject to be kept between an X-ray irradiator and a detector. In contrast, the ultrasound diagnosis apparatus does not need a gantry or the like. The ultrasound diagnosis apparatus transmits/receives ultrasound waves to/from an observation site with an ultrasound probe or the like, thereby obtaining information on body tissues to be imaged. In addition, the ultrasound diagnosis apparatus does not make noise due to vibration of a gradient magnetic field coil unlike MRI apparatuses.

However, if the ultrasound probe transmits/receives ultrasound waves to/from the observation site from outside the body, there may be the influence of tissues (bones, lungs, etc.) present in the way to the desired observation site from the outside. To solve the problem, the ultrasound diagnosis apparatus is provided with a transesophageal echocardiography (TEE) probe. The ultrasound diagnosis apparatus having the TEE probe transmits/receives ultrasound waves to/from the observation site from the esophagus or the upper digestive tract. This enables the ultrasound diagnosis apparatus having the TEE probe to obtain the ultrasound image

of a desired observation site without the influence of the tissues (bones, lungs, etc.) as mentioned above.

As a structure example, the TEE probe includes a guiding hollow tube part, an end part, and a curved part. The guiding hollow tube part has a predetermined length. The end part has an ultrasound transducer. The curved part connects the guiding hollow tube part with the end part. The portion from the guiding hollow tube part to the end part is inserted in the body cavity, for example, in the upper gastrointestinal tract, such as the esophagus and the stomach. Therefore, the guiding hollow tube part is formed to be flexible. The end of the guiding hollow tube part opposite to the end part is connected to a gripper. The gripper is held by the operator. The gripper is provided with an operation unit. The operation unit is used to manipulate the curved part and the end part. A wire is strung from the gripper through the guiding hollow tube part to the end part. The wire is used to bend the curved part.

By the operation on a scanner provided to the gripper, the wire is driven. In response to the driving of the wire, the curved part is bent. When the curved part is bent, the end part is pointed in a predetermined direction. While the end part is pointed in the predetermined direction, the TEE probe transmits/receives ultrasound waves to/from a desired observation site by the ultrasound transducer of the end part. With this, the ultrasound diagnosis apparatus having the TEE probe can obtain an image that indicates, for example, conditions of the heart from a predetermined location in the esophagus.

In the body cavity, due to the influence of pulsating and breathing, there may be a change in the relative positions of the end part of the TEE probe and the desired observation site. When the observation site is monitored for a predetermined period as described above, it can be a burden for the operator of the ultrasound diagnosis apparatus to keep monitoring the shift of the end part all the time and adjust the position if necessary, resulting in a reduction in the efficiency of the examination.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic perspective view of an ultrasound diagnosis apparatus;

FIG. 2A is a schematic side view of an end part;

FIG. 2B provides schematic cross sections taken along lines A-A' and B-B' in FIG. 2A, illustrating the positional relationship of parts therein;

FIG. 2C is a schematic cross section of an ultrasound transducer illustrated in FIG. 2A, to which offset is applied;

FIG. 2D is a schematic perspective view of a flexible printed circuit board;

FIG. 3A is a schematic perspective view of the ultrasound transducer;

FIG. 3B is a schematic perspective view of the ultrasound transducer;

FIG. 3C is a schematic perspective view of the ultrasound transducer;

FIG. 3D is a schematic perspective view of the ultrasound transducer;

FIG. 4 is a schematic block diagram illustrating an example of the functional structure of an end part of an ultrasound diagnosis apparatus according to a first embodiment;

FIG. 5 is a schematic block diagram illustrating an example of the functional structure of a main body of the ultrasound diagnosis apparatus of the first embodiment;

FIG. 6 is a schematic diagram of an example of a B-mode image generated by a generating unit of the first embodiment;

FIG. 7A is a schematic diagram of an example of a Doppler spectrum image generated by the generating unit of the first embodiment;

FIG. 7B is a schematic diagram of an example of ECG (electrocardiogram) waveform and the Doppler spectrum image generated by the generating unit of the first embodiment;

FIG. 8 is a schematic diagram illustrating a positional relationship for obtaining the B-mode image illustrated in FIG. 6;

FIG. 9 is a flowchart schematically illustrating the operation of the ultrasound diagnosis apparatus of the first embodiment;

FIG. 10 is a flowchart schematically illustrating the operation of the ultrasound diagnosis apparatus of the first embodiment;

FIG. 11 is a flowchart schematically illustrating the operation of the ultrasound diagnosis apparatus of the first embodiment;

FIG. 12A is a schematic perspective view of an ultrasound transducer according to a modification of the first embodiment;

FIG. 12B is a schematic cross section taken along line C-C' in FIG. 12A;

FIG. 13 is a flowchart schematically illustrating the operation of an ultrasound diagnosis apparatus according to a second embodiment;

FIG. 14 is a flowchart schematically illustrating the operation of the ultrasound diagnosis apparatus of the second embodiment;

FIG. 15 is a flowchart schematically illustrating the operation of the ultrasound diagnosis apparatus of the second embodiment;

FIG. 16 is a flowchart schematically illustrating the operation of an ultrasound diagnosis apparatus according to a fourth embodiment;

FIG. 17 is a flowchart schematically illustrating the operation of an ultrasound diagnosis apparatus according to a fifth embodiment;

FIG. 18 is a flowchart schematically illustrating the operation of the ultrasound diagnosis apparatus of the fifth embodiment;

FIG. 19 is a schematic diagram illustrating a contour and operation points set on a B-mode image;

FIG. 20A is a schematic diagram illustrating a specific example of heart chamber volume measurement performed by a main control unit; and

FIG. 20B is a schematic diagram illustrating a specific example of heart chamber volume measurement performed by the main control unit.

DETAILED DESCRIPTION

In general, according to one embodiment, an ultrasound diagnosis apparatus includes an ultrasound transceiver and a controller. The ultrasound transceiver includes a changer that changes transmission direction of ultrasound waves. The ultrasound transceiver transmits ultrasound waves in a direction set while being inserted in a subject to acquire biological information of an observation site of the subject. The controller obtains a direction toward the observation site based on the biological information, and controls the changer to adjust the transmission direction of ultrasound waves to the direction thus obtained.

Referring to FIGS. 1 to 20B, a description is given of an ultrasound diagnosis apparatus according to first to seventh embodiments.

[First Embodiment]

The overview of the overall structure of the ultrasound diagnosis apparatus 100 according to the first embodiment is described first with reference to FIG. 1. FIG. 1 is an external view of the ultrasound diagnosis apparatus 100 for explaining the overview of its structure.

As illustrated in FIG. 1, the ultrasound diagnosis apparatus 100 of the embodiment includes a main body 101 and an end part 10. The end part 10 and the main body 101 are connected through a cable 11. In the example of FIG. 1, a connector 11a is provided to the end of the cable 11. The main body 101 is provided with connection parts 101a. The connection parts 101a are formed to be connectable to the connector 11a. The main body 101 includes an operation unit 102 and a display unit 103. The operation unit 102 is used to operate the ultrasound diagnosis apparatus 100. The display unit 103 displays an image generated by the ultrasound diagnosis apparatus 100 and other images. Incidentally, the illustration of the ultrasound diagnosis apparatus 100 in FIG. 1 is by way of example only. The structure of the main body 101, the arrangement and the structure of the cable 11, the operation unit 102 and the display unit 103, and the like are not limited to those in FIG. 1, and susceptible to various modifications as appropriate. For example, instead of being configured as illustrated in FIG. 1, the main body 101 may be configured as a portable ultrasound diagnosis apparatus.

<Structure of End Part>

In the following, the structure of the end part 10 is described with reference to FIGS. 2A, 2B, and 3A. FIG. 2A is a schematic side view of the end part 10. FIG. 2B provides schematic cross sections taken along lines A-A' and B-B' in FIG. 2A, and illustrates the positional relationship of parts therein. In FIG. 2B, the cable 11, a direction controller 16, and a drive unit 18 are not illustrated. FIG. 3A is a schematic perspective view of an ultrasound transducer 12, which is a one-dimensional (1D) transducer array where ultrasound oscillators 12a are provided all over the outer peripheral surface of a support.

(Overview of End Part)

In the examples of FIGS. 1 and 2A, the end part 10 in a capsule form is used as a device for transmitting/receiving ultrasound waves. As illustrated in FIG. 2B, the end part 10 includes a container 10a. The container 10a is formed in an ellipsoid. The container 10a includes therein the ultrasound transducer 12, a transmit-receive controller 14, and an interface (I/F) 15 (see FIG. 4). The direction controller 16 and the drive unit 18 may be provided inside the container 10a. FIG. 2B does not illustrate the direction controller 16 and the drive unit 18 of this case.

As illustrated in FIG. 2B, in the ellipsoidally formed end part 10, for example, the cable 11 is connected to one longitudinal end of the container 10a. A power supply line and a signal line in the cable 11 run through the inside of the container 10a. These lines are connected to the transmit-receive controller 14, the direction controller 16, and the drive unit 18. When the container 10a is configured to be placed on tissue in the subject's body, the cable 11 can be configured to prevent the end part 10 from moving in the subject's body. For example, a part of the cable 11 may be fixed to a fixing part (not illustrated) that is fixed to a part of the tissue in the subject's body. Examples of the fixing part include a mouthpiece worn by the subject. By providing a mouthpiece with the fixing part, the extent to which the

cable **11** is inserted into the subject's body can be kept within a predetermined range. Thus, the end part **10** can be stayed in the subject's body.

For another example, the container **10a** of the end part **10** may be configured to expand so that it is appressed to the body tissue of the subject such as the esophagus. By appressing the container **10a** to the body tissue, the end part **10** can be stayed at the body tissue. Although not illustrated, in such a configuration, the container **10a** is formed to have a double-bag structure. The ultrasound transducer **12** is placed in the inner bag of the container **10a**. The outer bag of the container **10a** is connected to the cable **11**. The cable **11** is communicated with the outer bag, so that fluid, i.e., liquid such as sterile water, gas such as air, and the like, can be injected from a pipe **11c** (see FIG. 2B) in the cable **11**. The container **10a** expands with the injection of fluid, and contracts when the fluid is discharged. While the ultrasound transducer **12** is provided in the container **10a** of the end part **10**, whether other elements, such as the transmit-receive controller **14**, the direction controller **16**, and the drive unit **18**, are provided to the end part **10** is determined as appropriate depending on the structure of the ultrasound transducer **12** (element array, etc.).

(Structure of Entire Ultrasonic Transducer and Each Component)

The ultrasound transducer **12** used in the end part **10** illustrated in FIG. 2B includes the rectangular ultrasound oscillators **12a**, which are arranged in a circular array, i.e., 1D array (see FIG. 3A). In the ultrasound transducer **12**, the ultrasound oscillators **12a** are arranged all over the outer peripheral surface of the support (not illustrated). Hereinafter, the structure, where a back member, a back electrode, a piezoelectric element, a front electrode, and an acoustic matching layer are arranged on the support in layers, is referred to as the "ultrasound oscillators" **12a**. In addition, a group of the support, the ultrasound oscillators **12a**, and an acoustic lens **12c** is referred to as the "ultrasound transducer" **12**. The support (not illustrated) supports the ultrasound oscillators **12a**. The support is, for example, formed in a cylinder, the inside of which is hollow along the central axis. The support may have a columnar form. If all the ultrasound oscillators **12a** are required to be tilted to change the transmission direction of ultrasound waves (ultrasound beam angle, etc.), the support is connected to the drive unit **18**. The ultrasound oscillators **12a** are configured with the back member, the back electrode, the piezoelectric element, the front electrode, and the acoustic matching layer arranged radially in layers from the outer peripheral surface of the support toward the outside.

The piezoelectric element (not illustrated) is provided with the back electrode on a surface on the side of the back member (on the side of the support), and the front electrode on a surface on the opposite side (the side of the acoustic lens). The piezoelectric element converts a voltage applied to the front electrode and the back electrode into ultrasound waves. The ultrasound waves are transmitted to the subject. Having received reflected waves from the subject, the piezoelectric element converts the waves into voltage (echo signal). The piezoelectric element is generally made of such material as PZT (piezoelectric zirconate titanate/e.g., lead zirconate titanate/Pb(Zr, Ti)O₃). As the piezoelectric element, PVDF (polyvinylidene difluoride/polyvinylidene fluoride/(CH₂CF₂)_n) may be used. The use of a PVDF film as a piezoelectric element facilitates making the end part **10** because of its flexibility. Further, if a PVDF film is used as the piezoelectric element, the ultrasound oscillators **12a** can be thinner in the layer direction, and thus the end part **10** can

be downsized. Moreover, PVDF films possess good resistance to shock. As for other examples of the piezoelectric element, barium titanate (BaTiO₃), PZNT (Pb(Zn_{1/3}Nb_{2/3})O₃-PbTiO₃) single crystal, PMNT (Pb(Mg_{1/3}Nb_{2/3})O₃-PbTiO₃) single crystal, and the like may be used. The piezoelectric element may be of a single layer, or it may be multilayered.

Part of all the piezoelectric elements may be connected to a temperature sensing circuit (not illustrated). The piezoelectric element connected to the temperature sensing circuit is used as a pyroelectric element. The temperature sensing circuit detects the temperature around the ultrasound oscillators **12a** based on a pyroelectric voltage value or a pyroelectric current value received from the pyroelectric element. The temperature sensing circuit may be located in the end part **10**, or in the main body **101**. Since the end part **10** is placed in the subject's body, it is effective in monitoring an observation site to enable the operator to know the temperature around the ultrasound oscillators **12a**.

The acoustic matching layer is arranged adjacent to the front electrode on the acoustic lens **12c** side in the front electrode of the piezoelectric element. Thus, the acoustic matching layer is located between the piezoelectric element and the acoustic lens **12c**. The acoustic matching layer matches acoustic impedance between the piezoelectric element and the subject. There may be two or more acoustic matching layers arranged in the layer direction. In this case, materials that vary in acoustic impedance in stages are used for the acoustic matching layers. This structure achieves acoustic matching by changing acoustic impedance in stages between the piezoelectric element and the acoustic lens **12c**.

The back member is arranged adjacent to the back electrode on the side of the support in the back electrode of the piezoelectric element. The back member absorbs ultrasound waves emitted to the opposite direction to their irradiation direction (backward) during ultrasound transmission, thereby suppressing the excessive oscillation of the piezoelectric element. The back member suppresses the reflection of ultrasound waves from the back surface of the piezoelectric element when the piezoelectric element is oscillating. Therefore, with the back member, it is possible to avoid adverse effect on transmitting/receiving of ultrasound waves. As the back member, based on the features including acoustic attenuation, acoustic impedance, and the like, any materials such as an epoxy resin containing PZT powder, tungsten powder, etc., rubber filled with polyvinyl chloride and/or ferrite powder, or porous ceramic impregnated with resin such as epoxy, and the like may be used.

<Acoustic Lens>

The acoustic lens **12c** (see FIG. 2B) converges transmitted/received ultrasound waves and forms them into a beam shape. The acoustic lens **12c** is made of such material as silicone having an acoustic impedance similar to the living body. If the ultrasound oscillators **12a** are in a 2D array, and the ultrasound transducer **12** is capable of converging ultrasound waves into a beam by electronic scanning, the ultrasound transducer **12** may not include the acoustic lens **12c**.

When the end part **10** is inserted in the esophagus of the subject and the transmission direction of ultrasound waves is pointed to the heart, a wedge-shaped offset **12f** may be added between the acoustic lens **12c** and the ultrasound oscillators **12a** as illustrated in FIG. 2C. By the addition of the offset **12f**, the acoustic lens **12c** is tilted to the support of the ultrasound oscillators **12a**. With this structure, directions of ultrasound waves from the piezoelectric elements are converged into a different direction. Depending on the tilt angle of the offset **12f**, it becomes unnecessary to perform drive

control for transmitting ultrasound waves from the ultrasound oscillators **12a** of the end part **10** placed in the esophagus to the heart. Alternatively, depending on the tilt angle, the drive control can be simplified.

In the structure illustrated in FIG. 3A, the direction controller **16** and the drive unit **18** (described later) tilt the ultrasound transducer **12** in response to an instruction signal on the transmission direction of ultrasound waves from the main body **101**. By this tilting operation, the transmission direction of ultrasound waves is adjusted. If the offset **12f** is provided, the tilting operation may not be necessary.

(Other Examples of Ultrasonic Transducer)

Referring to FIGS. 3B to 3D, other examples of the structure of the ultrasound transducer **12** are described. FIGS. 3B to 3D each illustrate a schematic perspective view of the ultrasound transducer **12**. FIG. 3C illustrates the 1D array ultrasound transducer **12**, while FIGS. 3B and 3D illustrate the 2D array ultrasound transducer **12**. Besides, FIG. 3B illustrates the ultrasound transducer **12**, in which the ultrasound oscillators **12a** are provided all over the outer peripheral surface of the support. FIGS. 3C and 3D illustrate the ultrasound transducer **12**, in which the ultrasound oscillators **12a** are provided to a part of the outer peripheral surface of the support.

In the example of FIG. 3B, the ultrasound oscillators **12a** are arranged in a 2D array all over the outer peripheral surface of the support. In this structure, the transmit-receive controller (described later) is capable of switching the ultrasound oscillators to be driven as well as deflecting and converging ultrasound waves (ultrasound beams) by electronic scanning. In the structure of the ultrasound transducer **12** illustrated in FIG. 3B, the transmit-receive controller **14** can deflect and converge ultrasound waves, by electronic scanning, not only in a direction in which the ultrasound oscillators are arrayed (azimuth direction), but also in the elevation direction substantially perpendicular to the direction. Accordingly, in this structure, there may be no need to rotate and tilt the ultrasound transducer **12**. In this case, the structure does not include the direction controller **16** and the drive unit **18**. The acoustic lens **12c** may also not be included.

In the example of FIG. 3C, the ultrasound oscillators **12a** are arranged in a 1D array in a part in the circumferential direction of the outer peripheral surface of the support. That is, for example, when the support is of a cylindrical form, the ultrasound oscillators **12a** are arrayed in an area within a predetermined angle range (e.g., 60°) from the central axis in the circumferential direction of the outer peripheral surface. In this structure, upon receipt of an instruction signal from the main body **101**, the direction controller **16** and the drive unit **18** (described later) perform rotating or tilting of the ultrasound transducer **12**, or both.

In the example of FIG. 3D, the ultrasound oscillators **12a** are arranged in a 2D array in a part in the circumferential direction of the outer peripheral surface of the support. In this structure, upon receipt of an instruction signal from the main body **101**, the direction controller **16** and the drive unit **18** (described later) rotate the ultrasound transducer **12**. The state that the ultrasound oscillators **12a** are arrayed in a part means that, for example, when the support is of a cylindrical form, the ultrasound oscillators **12a** are arrayed in the azimuth and elevation directions in an area within a predetermined angle range (e.g., 60°) from the central axis in the circumferential direction of the outer peripheral surface.

(Modification of End Part)

If the used as the piezoelectric element is among those having low acoustic impedance such as PVDF, the back

member may be configured to reflect ultrasound waves radiated thereto instead of absorbing them. For example, a material that doubles as the back member and the support of the ultrasound oscillators **12a** may be used. The use of a shape-memory alloy as the material enables the end part **10** having the following structure. The modification of the end part **10** is described below with reference to FIG. 2D.

The container **10a** is configured such that the entire end part **10** is contracted when inserted into the subject's body. As illustrated in FIG. 2D, layers from the acoustic matching layer to the piezoelectric element are arranged on a flexible printed circuit (FPC) board **12d**. On the FPC board **12d** may be arranged an integrated circuit (IC) **12e** having the function of the transmit-receive controller **14** and the like. The IC **12e** has the function of the transmit-receive controller **14** and the like. The transmit-receive controller **14** is electrically connected to the electrode of the piezoelectric element via a pattern formed on the FPC board **12d** and the like. The FPC board **12d** is formed on the back member made of a shape-memory alloy.

The container **10a** is configured such that, having been inserted in the subject's body, for example, when placed in the esophagus, the entire end part **10** is expanded by the injection of fluid such as air, water, and the like through the cable **11** (see FIG. 2B). When the container **10a** is expanded, a predetermined space is formed therein. The shape-memory alloy as the back member is configured to recover, for example, cylindrical or columnar form as illustrated in FIG. 3A, when being expanded. By the discharge (suction, etc.) of fluid injected in the container **10a**, the entire end part **10** is contracted.

The ultrasound transducer **12** is supported by the FPC board **12d** and the back member made of a shape-memory alloy. Accordingly, in response to the contraction of the container **10a**, the entire ultrasound transducer **12** is also contracted. With this structure, the end part **10** becomes smaller when being contracted. Thus, the operator can arbitrarily expand/contract the end part **10**, and thereby can easily insert and remove the end part **10** into/from the subject's body.

(Transmit-Receive Controller)

Referring next to FIG. 4, a description is given of the transmit-receive controller **14** of the end part **10**. FIG. 4 is a schematic block diagram illustrating an example of the functional structure of the end part **10** of the ultrasound diagnosis apparatus **100** of the first embodiment. As illustrated in FIG. 4, the transmit-receive controller **14** includes a transmitter **141**, a receiver **142**, and a switching unit **143**. They are each described below.

(Transmitter)

The transmitter **141** of the end part **10** includes a transmit controller **141a**, a transmission waveform generator **141b**, and a transmitter amplifier **141c**. The transmitter **141** receives an instruction signal on the transmission of ultrasound waves from the main body **101** (a transmitter unit **105** or the like, see FIG. 5) through the I/F **15**. The transmitter **141** further includes a clock generation circuit and a transmitter delay circuit (not illustrated). The transmit controller **141a** controls the clock generation circuit, the transmitter delay circuit, and the like. The clock generation circuit generates clock signals for determining the transmission frequency and the transmission timing of ultrasound waves. For example, the clock generation circuit feeds the transmitter delay circuit with a reference clock signal. The transmitter delay circuit sends the transmission waveform generator **141b** a drive signal having a predetermined delay

time. The predetermined delay time is determined based on the transmission focal point of ultrasound waves.

The transmission waveform generator **141b** includes, for example, a pulser circuit (not illustrated). The pulser circuit includes therein as many pulsers as individual channels corresponding to the ultrasound oscillators **12a**, and generates transmission drive pulses. The pulser circuit repeatedly generates a rate pulse at a predetermined pulse repetition frequency (PRF). The rate pulses are distributed into the number of the channels, and sent to the transmitter delay circuit.

The transmitter delay circuit of the transmit controller **141a** provides the rate pulse with a transmission delay time related to the transmission direction and the transmission focus. Transmission drive pulses are generated at timing based on the rate pulses each being delayed. The transmission drive pulses are amplified by the transmitter amplifier **141c**, and sent to the switching unit **143**. As described above, the transmitter delay circuit provides the rate pulse with a transmission delay time to focus ultrasound waves for transmission (to converge ultrasound waves into a beam). With this, the transmission directivity of the ultrasound waves is determined. In addition, the transmitter delay circuit changes the transmission delay time to be given to each rate pulse, thereby controlling the transmission direction of ultrasound waves from the ultrasound wave radiation surfaces of the ultrasound oscillators **12a**.

(Switching Unit)

The switching unit **143** controls switching between the transmitter **141** and the receiver **142**. The switching unit **143** has a switch relating to transmitting/receiving of ultrasound waves. If scan mode on the main body **101** side is set to continuous wave Doppler (CWD) mode, as described below, the switching unit **143** connects some elements of the ultrasound oscillators **12a** to the transmitter **141** for transmission, and connects some others to the receiver **142** for reception.

If the scan mode on the main body **101** side is set to perform B (brightness) mode and pulsed wave Doppler (PWD) mode in parallel, the switching unit **143** alternately repeats control to sequentially switch elements to be driven according to the B mode and control to switch to elements that transmit ultrasound waves toward a set sample volume (sampling gate). In the B mode, a group of elements to be driven is shifted in the element array direction to control the transmission direction of ultrasound waves or the like.

Besides, the switching unit **143** switches sub-arrays each including a group of elements in m rows x n columns (a group of oscillators) in the 2D array ultrasound transducer **12**. A transmission drive pulse from the transmitter amplifier **141c** is applied to each element of the sub-array connected to the switch of the switching unit **143**, and the piezoelectric element is driven.

(Receiver)

The receiver **142** of the end part **10** receives echo signals corresponding to ultrasound waves reflected from the subject. The receiver **142** amplifies the echo signals received by the ultrasound transducer **12**, and also adds delay thereto. By the delay addition of the receiver **142**, the analog echo signals are converted to digital data having been subjected to phasing (i.e., subjected to beam forming). Specific examples are as follows.

The receiver **142** includes a receiver amplifier **142a**, an A/D converter **142b**, and a beamformer **142c**. The receiver **142** may further include a sub-array beamformer (not illustrated). The receiver amplifier **142a** amplifies echo signals received from the ultrasound transducer **12** with respect to

each receiver channel. The A/D converter **142b** converts the amplified echo signals to digital signals. Having been converted into digital signals, the echo signals are each stored in a digital memory (not illustrated). The digital memory is provided for each channel (or each element). Each echo signal is stored in the corresponding digital memory. The echo signal is also stored in an address corresponding to the time it is received. The A/D converter **142b** is capable of thinning out data that has been filtered according to the bandwidth of the echo signal. If the receiver **142** has the sub-array beamformer (not illustrated), the sub-array beamformer can add echo signals from adjacent elements in the ultrasound oscillators **12a**.

The beamformer **142c** provides the echo signals each converted into a digital signal with a delay time required to determine the reception directivity. The reception delay time is calculated for each element. The beamformer **142c** adds up the echo signals having the delay time. The beamformer **142c** reads each of the echo signals from the digital memory as appropriate based on the required delay time calculated, and adds up them. The beamformer **142c** repeats this addition while changing a reception focus position along the transmission beam. The beamformer **142c** emphasizes a reflection component from a direction corresponding to the reception directivity. The received beam signal processed by the receiver **142** is sent to a signal processor (a B-mode signal processing unit **107**, a Doppler signal processing unit **108**) via the I/F **15**, a receiver unit **106**, or the like.

(Direction Controller, Drive Unit)

In response to an instruction signal on the transmission direction of ultrasound waves from the main body **101**, the direction controller **16** controls the drive unit **18**. For example, the direction controller **16** drives the drive unit **18** to change the angle or orientation of the radiation surface of the ultrasound waves according to ROI (Region of Interest) set on the main body **101** side. The drive unit **18** is comprised of, for example, a micro-actuator such as an ultrasound motor. The drive unit **18** is driven under the control of the direction controller **16**. The drive unit **18** is connected to the ultrasound transducer **12**. With this structure, when the drive unit **18** is driven, the ultrasound transducer **12** is rotated or tilted. Thus, by driving the drive unit **18**, the transmission direction of ultrasound waves can be changed in the ultrasound transducer **12**.

<Structure of Main Body>

Next, the control and the operation of each part of the main body **101** are described with reference to FIG. 5. The ultrasound diagnosis apparatus **100** illustrated in FIG. 5 is, for example, used to obtain such images as those indicating the form of biological tissues such as the heart (see FIG. 6) and those indicating the state of blood flow (see FIG. 7A). As illustrated in FIG. 5, in the ultrasound diagnosis apparatus **100**, the main body **101** is connected to the end part **10** and a biological information measuring unit **120**. The end part **10** corresponds to an example of "ultrasound transmitter/receiver". FIG. 5 is a schematic block diagram illustrating an example of the functional structure of the main body **101** of the ultrasound diagnosis apparatus of the first embodiment.

The main body **101** includes therein units for performing input/output operations, calculations, controls, and the like of the ultrasound diagnosis apparatus **100** (see FIG. 5). In FIG. 5, the main body **101** includes, as the functional units, the operation unit **102**, the display unit **103**, a main control unit **104**, the transmitter unit **105**, the receiver unit **106**, the B-mode signal processing unit **107**, the Doppler signal processing unit **108**, a generating unit **109**, a direction

setting unit **110**, and a search unit **111**. Incidentally, the biological information measuring unit **120** may be included in the configuration of the ultrasound diagnosis apparatus **100**. The main body **101** may include a power supply connected to the end part **10** via the cable **11**.

(Operation Unit)

In response to operation by the operator, the operation unit **102** feeds signals and information corresponding to the operation to each unit. Examples of the operation unit **102** are not limited to a keyboard and a pointing device such as a mouse, but may include any other user interfaces. For example, the function of the operation unit **102** for inputting signals and information may be implemented as a software keyboard (softkey) on the touch panel integrated with the display unit **103**. The operation unit **102** may have a function of receiving input of signals and information via media and networks. Note that, in the following, the ultrasound image includes not only anatomical images such as B-mode images but also waveform images based on the motion information of tissues and blood flow and color display images of brightness and color based on the motion information of tissues and blood flow.

If, for example, the operator operates a FREEZE button or an end button on the operation unit **102**, transmitting/receiving of ultrasound waves is paused or terminated, respectively. The operator can select scan mode of ultrasound waves by operating the operation unit **102**. Using the operation unit **102**, the operator can select scan mode relating to transmitting/receiving of ultrasound waves and determine the initial setting. The operator can also specify sample volume (sampling gate) in Doppler mode through the operation unit **102**. Further, the operator can determine the settings for monitoring biological information such as cardiac ejection fraction through the operation unit **102**.

(Display Unit)

The display unit **103** displays ultrasound images as well as operation screens, setting screens, and the like. Examples of the display unit **103** include any display devices such as a cathode ray tube (CRT), a liquid crystal display (LCD), a plasma display panel, an organic electroluminescent display (OLED), a field emission display (FED), and the like.

(Main Control Unit)

The main control unit **104** includes CPU (Central Processing Unit), ROM (Read Only Memory), RAM (Random Access Memory), and the like. The CPU loads a control program into the RAM as appropriate, and thereby the main control unit **104** functions as a controller that controls each part of the main body **101**. That is, the main control unit **104** controls each part in the main body **101** as follows.

(Transmitter Unit)

The transmitter unit **105** of the main body **101** transmits a signal related to the driving of the ultrasound transducer **12** to the transmit-receive controller **14** of the end part **10** according to selected scan mode. For example, the main control unit **104** receives a selection operation of scan mode (scan sequence) through the operation unit **102**. In response to this operation, the main control unit **104** controls the transmitter unit **105** depending on the selected scan mode. According to the selected scan mode, transmission frequency, transmission driving voltage, and the like are changed. As the scan mode, such modes as follows can be selected: B-mode, power Doppler mode (PDI; Power Doppler Imaging), pulsed Doppler mode, continuous wave Doppler mode, color Doppler mode (CDI; Color Doppler Imaging/CFM; Color Flow Mapping), tissue Doppler mode (TDI;

Tissue Doppler Imaging), M (motion) mode, and the like. In addition, any combination of them is also selectable for the scan mode.

In the pulsed Doppler mode, the direction of transmission beams and transmission focal point (range related to the depth direction and the position of an observation area) are set based on the sample volume (sampling gate). The sample volume is, for example, set via the direction setting unit **110** by the operator specifying any range on a displayed B-mode image using the operation unit **102**. In the continuous wave Doppler mode, a region of space occupied by transmission beams is the observation area.

When the search unit **111** performs a search process, according to the elapse of predetermined time, in any of the above Doppler modes, the transmitter unit **105** sends the transmitter **141** of the end part **10** a control signal for obtaining information on the motion of a tissue and blood flow in an observation site inside the subject's body. In this process, the transmission direction of ultrasound waves in the Doppler mode is changed according to a predetermined trigger. The details are described in the explanation of the search unit **111**.

(Receiver Unit)

From the end part **10**, the receiver unit **106** of the main body **101** receives a digital echo signal (received beam signal) having been subjected to predetermined processing by the receiver **142**. The echo signal is sent to the signal processor (the B-mode signal processing unit **107**, the Doppler signal processing unit **108**).

(Signal Processor; B-Mode Signal Processing Unit)

The signal processor includes the B-mode signal processing unit **107** and the Doppler signal processing unit **108**. Having received the received beam signal from the receiver unit **106**, the B-mode signal processing unit **107** creates a visual image of amplitude information of the signal. Specifically, the B-mode signal processing unit **107** performs band-pass filtering on the received beam signal, then detects the envelope of the received beam signal after the band-pass filtering, and compresses detected data by logarithmic transformation. Thus, the B-mode signal processing unit **107** generates RAW data of a B-mode image.

(Signal Processor; Doppler Signal Processing Unit)

As Doppler processing, the Doppler signal processing unit **108** detects Doppler shift frequency component by quadrature detection of the received beam signals, and performs fast Fourier transform (FFT). The Doppler signal processing unit **108** extracts a Doppler shift by the frequency analysis of the received beam signal (Doppler signal). The Doppler signal processing unit **108** extracts, based on the Doppler shift, contrast medium echo component as well as blood flow and tissues caused by Doppler effect, and generates RAW data of a Doppler image extracting mobile object information such as average velocity, variance, and power with respect to a plurality of points.

The Doppler signal processing unit **108** may be configured to perform color Doppler processing. The blood flow information is visualized by the color Doppler processing. The blood flow and tissue motion information includes velocity, distribution, and power. For example, the Doppler signal processing unit **108** processes the received beam signal, thereby generating RAW data of a color flow mapping (CFM) image in the region of interest. In particular, the Doppler signal processing unit **108** performs quadrature detection of the received beam signal from the receiver unit **106**. The Doppler signal processing unit **108** then performs frequency analysis on the echo signal after the quadrature detection by autocorrelation method. By the frequency

analysis, the Doppler signal processing unit **108** calculates the variance and the average velocity of blood flow at each point of the sample. The Doppler signal processing unit **108** generates the RAW data of the color flow mapping image representing the calculated variance and the average flow velocity by color. The Doppler signal processing unit **108** also calculates the power of blood flow based on the received beam signal subjected to the quadrature detection. The Doppler signal processing unit **108** generates the RAW data of the color flow mapping image representing the calculated power by color.

The signal processing units send the RAW data (ultrasound raster data) subjected to the signal processing to the generating unit **109**. Incidentally, the B-mode signal processing unit **107** and the Doppler signal processing unit **108** of the embodiment can process both two-dimensional echo data and three-dimensional echo data.
(Generating Unit)

With reference to FIGS. **6**, **7A**, **7B**, and **8**, the operation of the generating unit **109** is described. FIG. **6** is a schematic diagram of an example of a B-mode image generated by the generating unit **109** of the first embodiment. FIG. **7A** is a schematic diagram of an example of a Doppler spectrum image generated by the generating unit **109**. FIG. **7B** is a schematic diagram of an example of the Doppler spectrum image illustrated in FIG. **7A** displayed in parallel with ECG (electrocardiogram) waveform *W* fed by the biological information measuring unit **120**. FIG. **8** is a schematic diagram of screen data illustrating a positional relationship for obtaining the cross section of the B-mode image illustrated in FIG. **6**.

The generating unit **109** generates ultrasound image data based on the RAW data after the signal processing output from the signal processor (the B-mode signal processing unit **107**, the Doppler signal processing unit **108**). The generating unit **109** includes, for example, DSC (Digital Scan Converter). The generating unit **109** converts the RAW data subjected to the signal processing represented by a signal sequence of a scan line into image data represented by a Cartesian coordinate system (scan conversion). For example, by applying the scan conversion to the RAW data subjected to the signal processing by the B-mode signal processing unit **107**, the generating unit **109** generates B-mode image data representing signal strength by brightness for each form of the tissues of the subject (see FIG. **6**). As illustrated in FIG. **8**, FIG. **6** is a four-chamber cross-sectional view, approached from the esophagus. FIG. **6** illustrates left atrium LA, mitral valve M, and a broken line L1 indicating the transmission direction of ultrasound waves. FIG. **6** also illustrates ECG waveform *W*.

Besides, the generating unit **109** performs coordinate transformation on the RAW data having undergone the color Doppler processing or the Doppler processing, and generates data of the Doppler image and data of the color flow mapping image that can be displayed on the display unit **103**. For example, based on the result of the frequency analysis of the Doppler signal (echo signal) using FFT (Fast Fourier Transform) by the Doppler signal processing unit **108**, the generating unit **109** generates a Doppler spectrum image where the velocity information of the mobile object (velocity information of blood flow, tissues, etc.) is drawn along the time series (see FIG. **7A**).

In FIG. **7A**, the vertical axis indicates frequency *f* (velocity *v*), while the horizontal axis indicates time *t*, and thus the spectrum is represented (FFT display). Additionally, in the waveform display, the line width represents the magnitude of the velocity, and the brightness represents the strength of

the Doppler spectrum (corresponding to the power of the Doppler signal). In FIG. **7A**, the tone is displayed in reverse to enhance the viewability of the image (the same is applied to FIG. **7B**).

After ultrasound waves are transmitted/received with time through the end part **10**, Doppler spectrum images are sequentially generated by the generating unit **109** through the above processing. The display unit **103** sequentially displays the generated images, and thus the state that the frequency *f* (the velocity *v* of the object) changes from moment to moment is displayed as a pattern.

The generating unit **109** can obtain ECG waveform from the biological information measuring unit **120** connected to the main body **101** via the main control unit **104** and the receiver unit **106**. As illustrated in FIG. **7B**, based on the ECG waveform *W*, the generating unit **109** generates an image capable of representing the Doppler spectrum image and the ECG waveform *W* synchronously in parallel.

Also, for example, from the RAW data of the color flow mapping image, the generating unit **109** generates color flow mapping images as an average velocity image indicating mobile object information (blood flow information, tissue motion information, etc.) a variance image, a power image, and a combination of these. The generating unit **109** may generate a composite image by combining any images from the B-mode image, the color flow mapping image, and the Doppler image. For example, the generating unit **109** generates a color flow mapping image by superimposing a color display image based on the motion information of tissues and blood flow on the B-mode image (or MPR (Multi-Planar Reconstruction) image) as well as generating a Doppler spectrum image by pulsed Doppler mode. Further, the generating unit **109** can generate an image capable of representing the color flow mapping image and the Doppler spectrum image in parallel with the ECG waveform based on the ECG waveform obtained from the biological information measuring unit **120**.

When a volume data processing unit (not illustrated) is provided to the signal processor of the main body **101**, the generating unit **109** may also display a volume rendering image and an MPR image. In this case, based on the echo signal received by the ultrasound transducer **12**, the signal processor generates volume data representing the three-dimensional shape of tissues in the subject's body. Further, for example, the signal processor performs volume rendering on the volume data, thereby generating RAW data. Having obtained the RAW data after the volume rendering from the signal processor, the generating unit **109** generates a volume rendering image. The generating unit **109** can also generate an MPR image from the volume data.
(Direction Setting Unit)

The direction setting unit **110** sets the transmission direction of ultrasound waves by the ultrasound transducer **12** in the end part **10**. The transmission direction is set based on operator's operation on the operation unit **102** or transmission direction data received from the search unit **111** (described later). The direction setting unit **110** sends the transmit-receive controller **14** or the direction controller **16** of the end part **10** determined transmission direction data. The direction setting unit **110** includes a storage unit (not illustrated) to store sample volume and the transmission direction data.

With respect to the setting of the transmission direction of ultrasound waves, the direction setting unit **110** receives such operations as selecting scan mode, setting sample volume, rotating/tilting the ultrasound transducer **12**, and the like. The direction setting unit **110** also sets elements (or

channels) to apply a drive signal in the ultrasound transducer 12 of the end part 10 depending on scan mode (continuous wave Doppler mode, etc.). As for the process of setting the transmission direction in response to the transmission direction data from the search unit 111, a description is given in the explanation of the search unit 111.

The information set for the transmission direction of ultrasound waves according to scan mode selection and sample volume setting (elements to be driven, angle/direction with respect to the ultrasound wave radiation surface, etc.) is sent to the transmit-receive controller 14 of the end part 10 via the transmitter unit 105. The information set for the transmission direction of ultrasound waves according to the rotation/tilting of the ultrasound transducer 12 (the amount of rotation, the tilt angle of the ultrasound transducer 12, etc.) is sent to the direction controller 16 of the end part 10. Incidentally, the direction setting unit 110 corresponds to an example of a "changer". Besides, in combination with the direction controller 16 and the drive unit 18 of the end part 10, the direction setting unit 110 corresponds to an example of a "changer". In combination with the transmitter unit 105 and the transmit-receive controller 14 of the end part 10, the direction setting unit 110 corresponds to an example of a "changer". With the structure described above, these examples of the "changer" can change the transmission direction of ultrasound waves.

(Search Unit)

While the ultrasound diagnosis apparatus 100 is transmitting/receiving ultrasound waves to obtain an ultrasound image, for adjusting the transmission direction of the ultrasound waves and the position of an area to be examined, the search unit 111 searches for the transmission direction of the ultrasound waves. The search is based on a Doppler signal obtained by transmitting/receiving ultrasound waves in the Doppler mode. Specifically, the search is performed by determining whether the transmission direction of ultrasound waves in the Doppler signal (or sample volume) adjusts to the desired observation object that produces a blood flow. When the adjustment is performed by the search unit 111 as a precondition, if any scan mode is selected by the operator, the main control unit 104 controls the end part 10 to acquire the Doppler signal in parallel with the acquisition of the ultrasound image. Note that the Doppler signal indicates an echo signal obtained in the Doppler mode, or the RAW data of the Doppler image having subjected to the signal processing by the signal processor. For convenience of the description, the Doppler signal may be similarly described below. In addition, the Doppler mode indicates any one of scan modes for obtaining blood flow information, including pulsed Doppler mode, continuous wave Doppler mode, color Doppler mode, power Doppler mode, and the like. For convenience of the description, the Doppler mode may be similarly described below.

For example, while the B-mode is selected and a B-mode image is generated, the main control unit 104 prompts the operator to set sample volume to be superimposed on the B-mode image displayed. When sample volume is set by the operator, according to a control signal received from the transmitter unit 105, the end part 10 alternately repeats B-mode scanning and the acquisition of Doppler signals in the pulsed Doppler mode. Based on the Doppler signals acquired, the search unit 111 performs the search process for the adjustment of the transmission direction of ultrasound waves and the position of an area to be examined. For example, the search unit 111 can be used to search for the transmission direction of ultrasound waves in the ultrasound transducer 12 upon monitoring cardiac ejection fraction.

Comparing pieces of signal strength information indicating the strength of Doppler signals obtained over time, the search unit 111 of the first embodiment determines the transmission direction of ultrasound waves with the highest signal strength. The transmission direction thus obtained corresponds to the direction of ultrasound beams being transmitted/received toward the observation site. Described below is an example of the search process performed by the search unit 111.

<<Start of Transmission of Ultrasonic Waves>>

After the end part 10 is inserted in the subject's body and scan mode is selected by the operator for preparation, the transmission of ultrasound waves is started. The receiver unit 106 of the main body 101 acquires echo signals based on the scan mode over time. The signal processor, the generating unit 109, and the like generate ultrasound images corresponding to the scan mode based on the echo signals. The display unit 103 displays the ultrasound images as appropriate. If the Doppler mode is selected as scan mode, only echo signals based on the selected scan mode are obtained. In this case, switching of the scan mode is not performed.

<<Start of Search>>

In the B mode, the B-mode signal processing unit 107 sends RAW data based on the echo signals to the generating unit 109. The Doppler signal processing unit 108 sends Doppler signals to the search unit 111. The transmitter unit 105 of the main body 101 starts transmitting ultrasound waves in the Doppler mode for the search process of the search unit 111. Triggered by the elapse of a predetermined time (any time that is set) from the start of the transmission, the transmitter unit 105 makes the end part 10 transmit ultrasound waves in the Doppler mode. At this time, the direction setting unit 110 sets the transmission direction so that the end part 10 transmits ultrasound waves not only in the direction in which ultrasound waves are transmitted first, but it transmits ultrasound waves while changing the transmission direction. The time interval at which the search process is performed can be set arbitrarily.

<<Ultrasonic Transmission Based on ECG Waveform>>

In the search process, ultrasound waves can be transmitted while the transmission direction is changed at any time interval set by the operator. For example, based on ECG waveform received from the biological information measuring unit 120, the main control unit 104 obtains predetermined cardiac time phase (diastole phase, etc.). The main control unit 104 may send the transmitter unit 105 a control signal related to the transmission timing of ultrasound waves with respect to each cardiac time phase thus obtained. The predetermined cardiac time phase refers to diastole or systole, early systole, mid-systole, late systole, early diastole, mid-diastole, late diastole or the like. Note that, in the search process, the main control unit 104 is not necessarily configured to transmit a control signal related to the transmission timing of ultrasound waves in the predetermined cardiac time phase. For another example, the main control unit 104 may be configured to obtain the predetermined cardiac time phase from ECG waveform received from the biological information measuring unit 120, and determine the signal strength (described later) of a Doppler signal in the time corresponding to the predetermined cardiac time phase among Doppler signals acquired successively.

Also when the search unit 111 performs the search process, the initial setting of the Doppler mode is required. For example, the main control unit 104 notifies the operator of the start of selected scan mode, or prompts the operator to set sample volume before or after it. As the notification, for

example, a predetermined character string may be displayed on the display unit 103, or voice guidance may be output. After a predetermined time has elapsed, first, the direction setting unit 110 makes the end part 10 transmit ultrasound waves via the transmitter unit 105 in the transmission direction corresponding to the initial setting. Then, the direction setting unit 110 makes the end part 10 transmit ultrasound waves via the transmitter unit 105 towards around the transmission direction of the initial setting, for example, in directions adjacent to the transmission direction of the initial setting.

<<Acquisition of Signal Strength Information>>

In the Doppler mode, the receiver unit 106 sequentially obtains Doppler signals transmitted in different directions. The Doppler signals are those obtained by the Doppler signal processing unit 108, and derived from blood flow (if the observation object is blood flow: blood flow PWD or CWD), or derived from tissues (if the observation object is tissues: tissue Doppler imaging-PWD). In the following, unless otherwise noted, the observation object is described as blood flow. In this case, it is assumed that a signal derived from blood flow, from which components derived from tissues that represent noise are removed, is extracted as a Doppler signal. The Doppler signal processing unit 108 sends a Doppler signal to the search unit 111. Together with information on the transmission direction of ultrasound waves, the search unit 111 stores Doppler signals obtained sequentially from the signal processor in a storage unit (not illustrated). From each of the stored Doppler signals transmitted in different directions, the search unit 111 acquires signal strength information that indicates the strength of the signal. The signal strength information is, for example, blood flow sensitivity information in the pulsed Doppler mode. In this case, the blood flow sensitivity information may be the amplitude value or the brightness value of a waveform depicted in a Doppler spectrum image. Each time the search unit 111 obtains a Doppler signal, the search unit 111 may acquire signal strength information from the Doppler signal. In this case, the search unit 111 stores, in the storage unit (not illustrated), signal strength information obtained sequentially and information on the transmission direction of ultrasound waves.

<<Comparison of Signal Strength>>

Besides, the search unit 111 compares Doppler signals in different directions corresponding to, for example, predetermined cardiac time phase, and obtains a Doppler signal having a higher signal strength. By the comparison of signal strength, a Doppler signal indicating the highest signal strength is stored together with information on the corresponding transmission direction of ultrasound waves. The search unit 111 may acquire the signal strength upon acquisition of each Doppler signal. The search unit 111 may also be configured to obtain the highest signal strength from Doppler signals at each time point, after the completion of the search process described below.

<<End of Search>>

The transmission of ultrasound waves and the process of acquiring Doppler signals corresponding thereto continue, under the control of the direction setting unit 110, until a predetermined condition is satisfied. Examples of the predetermined condition include completion of predetermined times of transmission, completion of transmission in a predetermined range (a predetermined angle range from the sound source), elapse of a predetermined time, and the like. One predetermined condition corresponds to one cycle. Upon receipt of a Doppler signal obtained last in a cycle, the search unit 111 obtains signal strength information deter-

mining that it is the end of the cycle. Then, the search unit 111 compares Doppler signals with a Doppler signal having the highest signal strength in an earlier cycle. With this comparison, the search unit 111 completes one cycle of the search process, and determines information on the transmission direction of ultrasound waves corresponding to a Doppler signal having the highest signal strength. The search unit 111 transmits the information on the transmission direction of ultrasound waves thus determined to the direction setting unit 110.

<<Update of Direction Setting>>

The direction setting unit 110 compares the information on the transmission direction of ultrasound waves received from the search unit 111 to the transmission direction of ultrasound waves before the search process. If there is a difference between them, based on the information on the transmission direction of ultrasound waves received from the search unit 111, the direction setting unit 110 updates the setting of the transmission direction of ultrasound waves. In addition, based on the updated setting, the direction setting unit 110 changes the transmission direction of ultrasound waves to a new direction through the transmitter 141 of the end part 10, or the direction controller 16 and the drive unit 18. The direction setting unit 110 and the search unit 111 of this embodiment correspond to an example of a "controller".

The above is an example of the search process by the search unit 111. As another example, when the continuous wave Doppler mode is initially selected by the operator, the signal strength of a Doppler signal may be obtained in response to the start of the transmission of ultrasound waves without waiting for the elapse of a predetermined time as described above. In this case, changes in signal strength in the same transmission direction may be continuously obtained based on Doppler signals acquired sequentially. However, in the continuous wave Doppler mode, ultrasound waves are continuously transmitted and received. Therefore, it is preferable to search the transmission direction of ultrasound waves as well as changing the transmission direction also at predetermined time intervals, in the same manner as the search of the transmission direction based on the signal strength as described above.

Due to the breathing, beats, body movement, throat reflection, emetic response, and the like of the subject, the transmission direction of ultrasound waves sometimes shifts from the object observed by the ultrasound diagnosis apparatus. In particular, if the observation object shifts not in the depth direction in the transmission direction of ultrasound waves, but in a direction deviating from the direction (orthogonal direction, etc.), it is difficult to continue the monitoring by the ultrasound diagnosis apparatus. Thus, each time a shift occurs, it is required to adjust the rotation and tilt of the ultrasound transducer 12 of the end part 10, the focus and transmission direction of ultrasound beams, and the like. Alternatively, each time a shift occurs, it is required to adjust the sample volume location (depth).

PWD mode has a range resolution. For example, during monitoring in the PWD mode, as well as the adjustment of the transmission direction of ultrasound beams, the sample volume location (depth) is adjusted with respect to the distance direction in the sound ray (scan line) of the ultrasound beams.

On the other hand, CWD mode has no range resolution. For example, during monitoring in the CWD mode, adjustment is performed for obtaining a location (depth) where the signal strength of a Doppler signal is the highest while the focus position (depth) of ultrasound beams is being changed.

However, it may be a heavy burden for the operator to keep monitoring shifts and also adjust them. If the operator bears these tasks, it may cause a decrease in the efficiency of monitoring inside the subject's body by the ultrasound diagnosis apparatus. In the case of long-term monitoring, if the operator bears the tasks, since it is difficult for the operator to keep monitoring whether the transmission direction of ultrasound waves is appropriate, it may interfere with the implementation of the monitoring. In this respect, the ultrasound diagnosis apparatus **100** includes the search unit **111** as described above to periodically adjust the transmission direction of ultrasound waves, thus solving the problems. That is, the ultrasound diagnosis apparatus **100** including the search unit **111** can improve the operation efficiency without imposing burdensome tasks on the operator in monitoring inside the subject's body. Moreover, the ultrasound diagnosis apparatus **100** including the search unit **111** can effectively cope with long-term monitoring.

(Biological Information Measuring Unit)

In FIG. 5, the biological information measuring unit **120** is connected to the main body **101**. The biological information measuring unit **120** generates information indicating the conditions of the subject such as a biological signal, and sends the generated information to the main body **101**. Examples of the biological information measuring unit **120** include bioelectric equipment (electrocardiograph, electroencephalograph, electromyography, etc.), respiratory equipment (respiratory flow meters, electronic spirometers, respiratory resistance meters, etc.), and medical monitoring equipment (singular monitor (bedside monitor), multiple monitors (central monitor), etc.), and the like. The medical monitoring equipment is configured to monitor vital signs such as ECG, blood pressure, respiratory rate, body temperature, pulse rate, blood oxygen saturation, exhaled gas partial pressure, and the like.

For example, if the biological information measuring unit **120** is an electrocardiograph, the main control unit **104** receives ECG waveform from the biological information measuring unit **120** via the receiver unit **106** and the like. Although FIG. 5 illustrates the biological information measuring unit **120** that is located outside the main body **101**, some part thereof may be arranged in the main body **101** so that the measurement is performed in the main body **101**.

<Operation>

In the following, a description is given of a control flow to perform the search process at predetermined time intervals as well as displaying a B-mode image, a Doppler spectrum image, and ECG waveform in parallel according to the embodiment with reference to FIGS. 9 to 11. FIGS. 9 to 11 are flowcharts schematically illustrating the operation of the ultrasound diagnosis apparatus **100** of the first embodiment.

(Step S01)

The operator selects a scan mode and determines the initial setting (transmission direction, transmission focal point, receive focal point, sample volume setting, etc.) using the operation unit **102**. Through the transmitter unit **105** of the main body **101** and the I/F **15** of the end part **10**, the main control unit **104** sends the transmit-receive controller **14** of the end part **10** a control signal related to the drive control of the ultrasound transducer **12** according to the scan mode. At this time, the main control unit **104** may be configured to obtain ECG waveform from the biological information measuring unit **120** via the receiver unit **106** or the like. In addition, the display unit **103** may display the ECG waveform.

(Step S02)

In one example, the transmit-receive controller **14** generates a transmission drive pulse at the timing based on the rate pulse that is delayed by the transmission waveform generator **141b**. The transmission drive pulse is amplified by the transmitter amplifier **141c**, and sent to the switching unit **143**. With this, predetermined ones of the ultrasound oscillators **12a** are driven. Thus, the ultrasound transducer **12** emits predetermined ultrasound waves. In this way, the transmission of ultrasound waves is started. When the scan mode is the B mode, the receiver unit **106** sends an echo signal received from the end part **10** to the B-mode signal processing unit **107**. The B-mode signal processing unit **107** performs signal processing thereon, thus generating RAW data. The generating unit **109** generates a B-mode image based on the RAW data. The display unit **103** displays the B-mode image as appropriate.

(Step S03)

The main control unit **104** determines whether a predetermined time has elapsed from the start of the transmission of ultrasound waves based on the selected scan mode. If, in step S03, determining that the predetermined time (e.g., any time period set by the operator) has not elapsed (Step S03; No), the main control unit **104** repeats this determination.

(Step S04)

In step S03, having determined that the predetermined time has elapsed (step S03; Yes), the main control unit **104** makes the end part **10** start transmitting/receiving ultrasound waves via the transmitter unit **105** for the search process. If a B-mode image BI is displayed on the display unit **103** (see FIG. 6), the main control unit **104** may prompt the operator to specify the position of sample volume to obtain a Doppler signal. The operator specifies any region of the B-mode image as sample volume using the operation unit **102**. As for the direction of the sample volume, in FIG. 6, the transmission direction is indicated by a broken line L1 extending from the left atrium LA through the mitral valve M to the left chamber and passing by the center of the left heart. The depth of the sample volume (sampling gate) in the case of PW Doppler is, for example, set as a position on the broken line L1 that does not intersect the mitral valve in the left ventricular cavity. The specified depth and direction of the sample volume are sent to the direction setting unit **110**, and the direction setting unit **110** returns information on the transmission direction of ultrasound waves from the sound source via the transmitter unit **105**. The position of the sample volume may be specified prior to step S04.

(Step S05)

The main control unit **104** determines whether the Doppler mode is selected as scan mode in step S01. If it is determined that the scan mode is the Doppler mode (step S05; Yes), the process proceeds to step S07.

(Step S06)

In step S05, if it is determined that the scan mode is not the Doppler mode (step S05; No), the main control unit **104** switches the scan mode to the Doppler mode to start the search process.

(Step S07)

For the search process, the main control unit **104** makes the end part **10** start transmitting ultrasound waves in the Doppler mode via the transmitter unit **105**. If a scan mode other than the Doppler mode (B-mode, etc.) is selected in step S01, after the Doppler mode transmission, the scan mode is switched alternately between the Doppler mode and the scan mode selected in step S01.

(Step S08)

The receiver unit **106** receives an echo signal based on the Doppler mode from the end part **10**. The Doppler signal processing unit **108** performs the signal processing on the echo signal to obtain a Doppler signal and sends the Doppler signal to the search unit **111**. The search unit **111** generates signal strength information based on the Doppler signal in the time corresponding to predetermined cardiac time phase. The signal strength information generated by the search unit **111** is stored in the storage unit (not illustrated) with the information on the transmission direction of ultrasound waves.

(Step S09)

Based on the ECG waveform fed from the biological information measuring unit **120**, the main control unit **104** measures the timing of the next transmission of ultrasound waves in the search process. The main control unit **104** repeats this (step S09; No) until the timing of the next transmission of ultrasound waves.

(Step S10)

In step S09, having determined that it is the timing of the next transmission of ultrasound waves based on the ECG waveform (step S09; Yes), the main control unit **104** controls the direction setting unit **110** so that the end part **10** transmits ultrasound waves after changing the transmission direction of ultrasound waves from the direction initially set to a direction around it. If the scan mode in the initial setting is not the Doppler mode, the main control unit **104** changes the transmission direction of ultrasound waves at the end part **10** after switching the scan mode to the Doppler mode.

(Step S11)

Having received an echo signal related to ultrasound waves transmitted by changing the transmission direction, the receiver unit **106** sends the signal to the Doppler signal processing unit **108**. The search unit **111** generates signal strength information based on the Doppler signal received from the Doppler signal processing unit **108**, and stores it in the storage unit (not illustrated) with the information on the transmission direction of ultrasound waves. The main control unit **104** obtains the predetermined cardiac time phase based on the ECG waveform fed from the biological information measuring unit **120**. The main control unit **104** also obtains signal strength in the time corresponding to the predetermined cardiac time phase from among Doppler signals acquired successively.

(Step S12)

The main control unit **104** determines whether the termination condition of the search process, such as completion of predetermined times of the search process, completion of transmission in a predetermined range (a predetermined angle range from the sound source), elapse of a predetermined time, and the like, is satisfied. In step S12, having determined that the termination condition of the search process is not satisfied (step S12; No), the main control unit **104** repeats steps S09 to S12.

(Step S13)

In step S12, if the main control unit **104** determines that the termination condition of the search process is satisfied (Step S12; Yes), the search unit **111** retrieves pieces of the signal strength information from the storage unit (not illustrated) and compares them. The search unit **111** may be configured to compare signal strength information with prior one each time signal strength information is obtained through the repetition of steps S09 to S11. In this case, since the provisional highest signal strength has already been

determined, the search unit **111** compares signal strength obtained most recently with the provisional highest signal strength at the previous time.

(Step S14)

According to the result of the comparison in step S13, the search unit **111** determines the transmission direction of ultrasound waves with the highest signal strength.

(Step S15)

The search unit **111** sends the direction setting unit **110** information on the transmission direction of ultrasound waves thus determined.

(Step S16)

Comparing the transmission direction set in advance with the information on the transmission direction received in step S15, the direction setting unit **110** determines whether there is a difference between them.

(Step S17)

In step S16, having determined that there is a difference between the transmission direction set in advance and the information on the transmission direction received in step S15 (step S16; Yes), the direction setting unit **110** updates the setting of the transmission direction of ultrasound waves based on the information on the transmission direction of ultrasound waves received in step S15.

(Step S18)

The direction setting unit **110** determines whether the ultrasound transducer **12** is required to be rotated or tilted by the direction controller **16** and the drive unit **18** based on the updated setting.

(Step S19)

In step S18, having determined that the ultrasound transducer **12** is required to be rotated or tilted (step S18; Yes), the direction setting unit **110** rotates or tilts the ultrasound transducer **12** with the direction controller **16** and the drive unit **18**. However, when the 2D array ultrasound transducer **12** is used, there may be a case where this determination is not necessary.

(Step S20)

The direction setting unit **110** changes the transmission direction of ultrasound waves to a new direction and transmits ultrasound waves through the transmitter **141** of the end part **10**. In step S18, having determined that the ultrasound transducer **12** is not required to be rotated or tilted (step S18; No), the direction setting unit **110** performs step S20 without performing step S19.

In step S16, having determined that there is no difference between the transmission direction set in advance and the information on the transmission direction received in step S15 (step S16; No), the direction setting unit **110** ends the process without performing steps S17 to S20.

The ultrasound diagnosis apparatus **100** of this embodiment transmits ultrasound waves at predetermined intervals in the transmission direction set in advance and directions around it, and acquires a plurality of Doppler signals corresponding to different transmission directions. The search unit **111** compares pieces of information on the signal strength of the Doppler signals corresponding to the different transmission directions, thereby determining the transmission direction of ultrasound waves with the highest signal strength. The direction setting unit **110** changes the transmission direction of ultrasound waves at the end part **10** to the transmission direction. Thus, even if the end part **10** shifts in the subject's body due to the breathing, beats, body movement, throat reflection, emetic response, and the like of the subject, and the transmission direction of ultrasound waves shifts from the object to be observed, the ultrasound diagnosis apparatus **100** can change the transmission direc-

tion of ultrasound waves to follow the shift, thereby enabling the continuation of monitoring inside the subject' body without imposing burdensome tasks on the operator. Moreover, even in long-term monitoring, the ultrasound diagnosis apparatus **100** can avoid a decrease in the operation efficiency.

The ultrasound diagnosis apparatus **100** of this embodiment includes the end part **10**. The end part **10** includes, for example, the ultrasound transducer **12** in the container **10a** in a capsule form. The end part **10** is inserted in the subject's body. On the other hand, if a common transesophageal echocardiography (TEE) probe is inserted in the esophagus, the guide tube portion from the grip to the end part stays in the esophagus. For example, when ultrasound waves are transmitted and received between a predetermined position in the esophagus and the heart, the guide tube portion is placed in the esophagus while at least ultrasound waves are being transmitted and received. That is, while an observation site such as the heart or the like is being monitored, the guide tube portion to the end part stays in the esophagus of the subject all the time.

The guide tube portion and the end part of the TEE probe are provided therein with not only a signal line for exchanging signals with the ultrasound transducer and a power supply line or the like for supplying power, but also a wire for bending the end part. This means that the subject is obliged to bear with patience the guide tube portion or the like that includes therein a wire and the like being placed in the esophagus. If the monitoring continues for a long time, it may impose a burden on the subject depending on his/her condition. As a result, the TEE probe may not be used for the continuous monitoring of the observation site. If ultrasound waves are transmitted and received at the outside of the body to avoid this problem, it is required to consider the influence of tissues (bones, lungs, etc.) present in the way to the observation site from the outside. As in the embodiment, if the end part **10** is in a capsule form, and only minimal lines such as a signal line and a power supply line are passed through the cable **11**, it is possible to reduce the burden on the subject compared to the case of using the TEE probe. Further, with the use of the cylindrical support having a hollow penetrating along the central axis, even if the end part **10** is placed at a fixed position for a long time, the esophagus can maintain its functions.

<Modification 1>

In the following, a modification 1 of the first embodiment is described with reference to FIGS. **12A** and **12B**. FIG. **12A** is a schematic perspective view of the ultrasound transducer **12** according to the modification 1 of the first embodiment. FIG. **12B** is a schematic cross section taken along line C-C' in FIG. **12A**. As illustrated in FIGS. **12A** and **12B**, the ultrasound transducer **12** of the modification 1 is provided with a support **12k** for the ultrasound oscillators **12a**, the diameter of which increases gradually from one end face toward the other in the axial direction so that the shape is flared at the bottom.

In this structure, the ultrasound oscillators **12a** are arranged to be tilted with respect to the longitudinal axis of the container **10a** (the axis in the direction in which the end part **10** is inserted). Thus, the ultrasound transducer **12** need not be tilted by the actuator or the like differently from the above embodiment. For example, even if the heart is located in such a position where it looks up at the ultrasound wave radiation surface of the ultrasound transducer **12** of the end part **10** inserted around the middle of the esophagus, the heart can be included in ROI.

This eliminates the need of drive control by the drive unit **18**, thereby enabling space-saving in the container **10a**.

Further, if the transmission direction of ultrasound waves shifts from the observation object, the ultrasound diagnosis apparatus of the modification 1 can change the transmission direction of ultrasound waves to follow the shift of the end part **10**, thereby enabling the continuation of monitoring inside the subject' body without imposing burdensome tasks on the operator.

<Modification 2>

Next, a modification 2 of the first embodiment is described. In this modification, the transmitter unit **105** and the receiver unit **106** of the main body **101** implement the most functions of the transmitter **141** and the receiver **142** of the end part **10** of the first embodiment. With this, the internal structure of the container **10a** may be simplified. Described below is an example of the functions of the transmitter unit **105** and the receiver unit **106**.

(Transmitter Unit—Modification 2)

The transmitter unit **105** of the main body **101** includes a clock generation circuit, a transmitter delay circuit, and a pulser circuit (not illustrated). The main control unit **104** controls the clock generation circuit, the transmitter delay circuit, the pulser circuit, and the like. The clock generation circuit generates clock signals for determining the transmission frequency and the transmission timing of ultrasound waves. For example, the clock generation circuit feeds the transmitter delay circuit with a reference clock signal. The transmitter delay circuit sends the pulser circuit a drive signal having a predetermined delay time. The predetermined delay time is determined based on the transmission focal point of ultrasound waves. The pulser circuit includes therein as many pulsers as individual channels corresponding to the ultrasound oscillators **12a**, and generates transmission drive pulses.

The pulser circuit repeatedly generates a rate pulse to form transmission ultrasound waves at a predetermined repetition frequency (PRF). The transmitter delay circuit provides the rate pulse with a transmission delay time related to the transmission direction and the transmission focus. Transmission drive pulses are generated at timing based on the rate pulses each being delayed. The transmission drive pulses are sent to the end part **10** through the cable **11**, and fed to the ultrasound oscillators **12a** of the ultrasound transducer **12** via the transmit-receive controller **14**. The transmission drive pulses excite the piezoelectric elements. As described above, the transmitter delay circuit provides the rate pulse with a transmission delay time to focus ultrasound waves for transmission, thereby converging the ultrasound waves into a beam. With this, the transmission directivity of the ultrasound waves is determined. In addition, the transmitter delay circuit changes the transmission delay time to be given to each rate pulse, thereby controlling the transmission direction of ultrasound waves from the ultrasound wave radiation surface.

(Receiver Unit—Modification 2)

The receiver unit **106** of the main body **101** is controlled by the main control unit **104**. The receiver unit **106** of the main body **101** receives echo signals corresponding to ultrasound waves reflected from the subject. Having received the echo signals received by the end part **10**, the receiver unit **106** performs delay addition processing on them. Thus, the receiver unit **106** converts the analog echo signals to digital data having been subjected to phasing (i.e., subjected to beam forming). Specific examples are as follows.

The receiver unit **106** includes, for example, a preamplifier circuit, an A/D converter, a receiver delay circuit, and an adder (all not illustrated). The preamplifier circuit amplifies echo signals received from the ultrasound transducer **12** with respect to each receiver channel. The A/D converter converts the amplified echo signals to digital signals. Having been converted into digital signals, the echo signals are each stored in a digital memory (not illustrated). The digital memory is provided for each channel (or each element). Each echo signal is stored in the corresponding digital memory. The echo signal is also stored in an address corresponding to the time it is received.

The receiver delay circuit provides echo signals converted to digital signals with a delay time required to determine the reception directivity. The reception delay time is calculated for each element. The adder adds up the echo signals having the delay time. The adder reads each of the echo signals from the digital memory as appropriate based on the required delay time calculated, and adds up them. The adder repeats this addition while changing a reception focus position along the transmission beam. The adder emphasizes a reflection component from a direction corresponding to the reception directivity. The received beam signal processed by the receiver unit **106** is sent to the signal processor (the B-mode signal processing unit **107**, the Doppler signal processing unit **108**).

[Second Embodiment]

In the following, the ultrasound diagnosis apparatus **100** according to the second embodiment is described. In the second embodiment, the operation of the search unit **111** is different from that of the first embodiment. The ultrasound diagnosis apparatus **100** of the second embodiment is similar to that of the first embodiment in other respects. The differences are mainly described below.

In the first embodiment, the search unit **111** is configured to determine the optimal transmission direction of ultrasound waves based on the signal strength of Doppler signals. On the other hand, in the ultrasound diagnosis apparatus **100** of the second embodiment, the search unit **111** performs the search process based on a waveform indicating blood flow information generated by the generating unit **109**. (Overview of Search Unit)

For example, the search unit **111** of the second embodiment may compare a waveform based on Doppler signals previously stored with a waveform based on Doppler signals obtained sequentially in the search process (e.g., FIG. 7A). Preferably, the waveforms of the Doppler signals are compared in each predetermined period (e.g., in one cardiac cycle) that is synchronized with cardiac time phase. As a result of the comparison, the search unit **111** may be configured to determine the transmission direction of ultrasound waves by obtaining a direction with the highest similarity to the waveform based on the Doppler signal stored in advance. In the first embodiment described above, an example is described in which the transmission direction is determined based on the signal strength of Doppler signals. Here, in the case of pulsed Doppler, if sample volume touches the myocardial tissue or the valve, received beam signals are saturated, which may cause a significant increase in the signal strength of Doppler signals as compared to the signals obtained from the blood stream. In case of this, preferably, the search unit **111** provides an upper limit to expected values of the signal strength of Doppler signals, and searches for a direction where the highest signal strength is obtained within the range of the expected values. Further, as described below, by searching for a direction with the highest similarity of Doppler waveforms in a predetermined

period, the search unit **111** can estimate a transmission direction with high accuracy while reducing the effect of saturation. Hereinafter, the waveform based on Doppler signals previously stored (reference waveform) may be sometimes referred to as "second waveform". Besides, the waveform based on Doppler signals obtained sequentially in the search process may be sometimes referred to as "first waveform". The second waveform corresponds to an example of "second waveform pattern". The first waveform corresponds to an example of "first waveform pattern".

<<Generation of Reference Waveform Data>>

The second waveform data related to the second waveform is stored in the storage unit (not illustrated). The second waveform is compared with the first waveform in the search process. The second waveform data is acquired until a predetermined time has elapsed from the start of transmitting/receiving of ultrasound waves based on, for example, acquisition conditions determined in advance in selected scan mode. In this case, if the scan mode selected by the operator is the B mode, the main control unit **104** controls the end part **10**, through the transmitter unit **105**, to alternately switch between the control of electronic scanning of the ultrasound transducer **12** according to the B-mode and the control of ultrasound wave transmitting/receiving according to the Doppler mode. The control switching is repeated until a predetermined time has elapsed. At this time, the transmission direction of ultrasound waves in the Doppler mode is a direction set in advance as the initial setting. The initial setting is determined by the operator at the start timing of the transmission of ultrasound waves, or before or after it. In the generation of the second waveform, unlike the search process, ultrasound waves are transmitted in a set direction without a change in the transmit direction.

The main control unit **104** also controls the transmit-receive controller **14** of the end part **10** to acquire Doppler signals in predetermined cardiac time phase (diastole phase, etc.) for generating the second waveform data. For this control, the main control unit **104** obtains ECG waveform from the biological information measuring unit **120**. The generating unit **109** generates an image (Doppler spectrum image, etc.) indicating waveform in the Doppler mode based on the Doppler signals.

The search unit **111** extracts a waveform corresponding to the predetermined cardiac time phase in the ECG waveform from the image indicating waveform in the Doppler mode. The search unit **111** generates the second waveform based on the waveform, and stores it in the storage unit. Data indicating a waveform obtained in advance may be stored as the second waveform data without the above process of generating the second waveform data. For example, it may also be possible to use waveform data indicating a typical waveform according to the condition of the subject. For another example, the search unit **111** may extract a specific waveform from waveforms based on Doppler signals acquired from the same subject in the past by referring to the current condition of the subject, and use the specific waveform as the second waveform.

<<Start of Search>>

The transmitter unit **105** of the main body **101** starts transmitting ultrasound waves in the Doppler mode to obtain the first waveform used in the search process of the search unit **111**. Triggered by the elapse of a predetermined time from when the second waveform is acquired, the transmitter unit **105** makes the end part **10** transmit ultrasound waves in the Doppler mode. The time interval at which the search process is performed can be set arbitrarily.

<<Ultrasonic Transmission Based on ECG Waveform>>

In the search process, the time interval, at which ultrasound waves are transmitted while the transmission direction is changed, is set correspondingly to cardiac time phase in the second waveform. For example, the main control unit **104** receives ECG waveform from the biological information measuring unit **120**. Next, the main control unit **104** obtains cardiac time phase corresponding to cardiac time phase (diastole phase, etc.) in the second waveform from the ECG waveform. The main control unit **104** then sends a control signal on the transmission timing of ultrasound waves to the transmitter unit **105** based on the cardiac time phase. The main control unit **104** may not necessarily be configured to send a control signal on the transmission timing of ultrasound waves in predetermined cardiac time phase. For another example, the main control unit **104** may be configured to obtain predetermined cardiac time phase from the ECG waveform fed by the biological information measuring unit **120**, and generate the first waveform (described later) corresponding to the predetermined cardiac time phase among Doppler signals acquired sequentially.

<<Generation of Waveform Image>>

The Doppler signal processing unit **108** performs the same signal processing as in the first embodiment on echo signals received from the receiver unit **106**, thereby sending RAW data of the Doppler mode to the generating unit **109**. The generating unit **109** sequentially generates Doppler spectrum images based on the RAW data.

<<Generation of First Waveform>>

At this time, the main control unit **104** obtains cardiac time phase corresponding to that of the second waveform from the ECG waveform fed by the biological information measuring unit **120**, and send it to the search unit **111**. The search unit **111** extracts a waveform in the cardiac time phase corresponding to that in the second waveform from the Doppler spectrum image generated by the generating unit **109**. The search unit **111** sequentially generates such waveform for each of transmission directions as the first waveform.

<<Calculation of Similarity of Waveforms>>

The search unit **111** determines the similarity between the second waveform stored and each of the first waveforms generated sequentially in the search process. The similarity can be obtained by, for example, cross-correlation operation. Based on the cross-correlation coefficient value between the first waveform and the second waveform, the search unit **111** determines the similarity of the two waveforms. The similarity thus obtained is stored in the storage unit (not illustrated) with information on the transmission direction of ultrasound waves.

<<Comparison of Similarity>>

Comparing the first waveforms in different directions, the search unit **111** determines one which is more similar to the second waveform. The first waveform with the highest similarity in the comparison is stored with information on the corresponding transmission direction of ultrasound waves. The first waveform with the highest similarity corresponds to an example of a "similar waveform pattern".

In the following, a description is given of a control flow to perform the search process at predetermined time intervals as well as displaying a Doppler spectrum image and ECG waveform in parallel according to the embodiment with reference to FIGS. 13 to 15. FIGS. 13 to 15 are flowcharts schematically illustrating the operation of the ultrasound diagnosis apparatus **100** of the second embodiment.

Incidentally, with the parallel display of a Doppler spectrum image and ECG waveform, monitoring is conducted on, for example, the peak value of the left ventricular inflow in systole as illustrated in FIG. 7B. At this time, the ECG waveform is acquired, and thus cardiac time phase for Doppler waveform can be identified (diastole, systole, etc.). When, as illustrated in FIG. 7B, the left ventricular inflow that occurs during diastole is monitored, the polarity of a waveform indicating the direction of blood flow is detected as negative (lower side in FIG. 7B). On the other hand, as illustrated in FIG. 7B, if the polar component of a reverse waveform (forward direction (upper side in FIG. 7B)) is detected in systole, it means that there exists mitral regurgitation (MR in FIG. 7B). However, if the presence of mitral regurgitation MR is determined only by the polarity of a waveform, this determination may result in error. This is because when the end part **10** shifts with respect to the left ventricular inflow (object to be observed), the transmission direction of ultrasound waves shifts. Thus, Doppler signals for the aortic ejection blood flow having the same positive polarity (upper side in FIG. 7B) are received in systole, and the waveform of the Doppler signals may be detected erroneously as mitral regurgitation MR. To avoid such erroneous detection, it is important that the search unit **111** performs the search process in consideration of cardiac time phase in monitoring.

(Step S31)

The operator selects a scan mode and determines the initial setting (transmission direction, transmission focal point, receive focal point, sample volume setting, etc.) using the operation unit **102**. Through the transmitter unit **105** of the main body **101** and the I/F **15** of the end part **10**, the main control unit **104** sends the transmit-receive controller **14** of the end part **10** a control signal related to the drive control of the ultrasound transducer **12** according to the scan mode. The main control unit **104** may be configured to obtain ECG waveform at this time from the biological information measuring unit **120** via the receiver unit **106** or the like. In addition, the display unit **103** may display the ECG waveform (e.g., FIG. 7).

(Step S32)

The ultrasound oscillators **12a** are driven by the transmit-receive controller **14**, thereby emitting predetermined ultrasound waves. In this way, the transmission of ultrasound waves is started. When the scan mode is the Doppler mode, the receiver unit **106** sends an echo signal received from the end part **10** to the Doppler signal processing unit **108**. The Doppler signal processing unit **108** performs signal processing thereon, thus generating RAW data. The generating unit **109** generates a Doppler spectrum image based on the RAW data. The display unit **103** displays the Doppler spectrum image as appropriate.

(Step S33)

The main control unit **104** determines whether the Doppler mode is selected as scan mode in step S31. If it is determined that the scan mode is the Doppler mode (step S33; Yes), the process proceeds to step S35.

(Step S34)

In step S05, if it is determined that the scan mode is not the Doppler mode (step S33; No), the main control unit **104** switches the scan mode to the Doppler mode to start the search process.

(Step S35)

For the search process, the main control unit **104** makes the end part **10** start transmitting ultrasound waves in the Doppler mode via the transmitter unit **105**. Via the receiver unit **106**, an echo signal is sent from the end part **10** to the

main body **101**. The Doppler signal processing unit **108** performs the signal processing on the echo signal. Having received RAW data from the Doppler signal processing unit **108**, the generating unit generates a Doppler spectrum image. The search unit **111** extracts a waveform corresponding to predetermined cardiac time phase in ECG waveform from the Doppler spectrum image. The search unit **111** generates the second waveform based on the waveform, and stores it in the storage unit.
(Step S36)

The main control unit **104** determines whether a predetermined time has elapsed from the start of the transmission of ultrasound waves based on the selected scan mode, or from when the second waveform is generated. If, in step S36, determining that the predetermined time has not elapsed (step S36; No), the main control unit **104** repeats this determination.
(Step S37)

In step S37, having determined that the predetermined time has elapsed (step S36; Yes), the main control unit **104** makes the end part **10** start transmitting/receiving ultrasound waves for the search process via the transmitter unit **105**. If the scan mode selected in step S31 is not the Doppler mode, the main control unit **104** switches the scan mode to the Doppler mode to start the search process.
(Step S38)

The receiver unit **106** receives an echo signal based on the Doppler mode from the end part **10**. The Doppler signal processing unit **108** performs the signal processing on the echo signal to obtain a Doppler signal and sends the Doppler signal to the generating unit **109**. The generating unit **109** generates a Doppler spectrum image.
(Step S39)

The search unit **111** extracts a waveform in cardiac time phase corresponding to that in the second waveform from the Doppler spectrum image generated by the generating unit **109**. The search unit **111** generates the first waveform based on the waveform. The search unit **111** stores the first waveform in the storage unit (not illustrated) with information on the transmission direction of ultrasound waves.
(Step S40)

Based on ECG waveform fed from the biological information measuring unit **120**, the main control unit **104** measures the timing of the next transmission of ultrasound waves in the search process. The main control unit **104** repeats this (step S40 No) until the timing of the next transmission of ultrasound waves.
(Step S41)

In step S40, having determined that it is the timing of the next transmission of ultrasound waves based on the ECG waveform (step S40; Yes), the main control unit **104** controls the direction setting unit **110** so that the end part **10** transmits ultrasound waves after changing the transmission direction of ultrasound waves from the direction initially set to a direction around it. If the scan mode in the initial setting is not the Doppler mode, the main control unit **104** changes the transmission direction of ultrasound waves at the end part **10** after switching the scan mode to the Doppler mode.
(Step S42)

Having received an echo signal related to ultrasound waves transmitted by changing the transmission direction, the receiver unit **106** sends the signal to the Doppler signal processing unit **108**. The generating unit **109** generates a Doppler spectrum image based on the Doppler signal processed by the Doppler signal processing unit **108**. The search unit **111** extracts a waveform in cardiac time phase corresponding to that in the second waveform from the Doppler

spectrum image generated by the generating unit **109**. The search unit **111** generates the first waveform based on the waveform. The search unit **111** stores the first waveform in the storage unit (not illustrated) with information on the corresponding transmission direction of ultrasound waves.
(Step S43)

The main control unit **104** determines whether the termination condition of the search process, such as completion of predetermined times of transmission, completion of transmission in a predetermined range (a predetermined angle range from the sound source), elapse of a predetermined time, and the like, is satisfied. In step S43, having determined that the termination condition of the search process is not satisfied (step S43; No), the main control unit **104** repeats steps S40 to S43.
(Step S44)

In step S43, if the main control unit **104** determines that the termination condition of the search process is satisfied (Step S43; Yes), the search unit **111** retrieves the first waveforms from the storage unit (not illustrated) and compares them with the second waveform, thereby determining the similarity between the second waveform and each of the first waveforms (by the cross-correlation operation, etc.). In addition, the search unit **111** determines one with the highest similarity to the second waveform among the first waveforms.

The search unit **111** may be configured to compare the first waveform with the second waveform to determine the similarity between them each time the first waveform is generated through the repetition of steps S40 to S42. In this, the search unit **111** may also be configured to provisionally determine the first waveform with the highest similarity among similarities having been obtained in the past.

In this case, the search unit **111** compares the first waveform obtained most recently to that with the provisional highest similarity obtained at the previous time.
(Step S45)

According to the result of the comparison in step S44, the search unit **111** determines the transmission direction of ultrasound waves corresponding to the first waveform with the highest similarity.
(Step S46 to Step S50)

The following steps, i.e., sending information on the transmission direction (step S46), determining about a difference between the transmission directions (step S47), updating the setting of the transmission direction (step S48), determining necessity for rotating or tilting the ultrasound transducer **12** (step S49), rotating or tilting the ultrasound transducer **12** (step S50), and transmitting ultrasound waves in a new direction (step S51), are performed in the same manner as described in the first embodiment, and the details are not repeated here.

The ultrasound diagnosis apparatus **100** of this embodiment transmits ultrasound waves at predetermined intervals in the transmission direction set in advance and directions around it, and acquires a plurality of Doppler signals corresponding to different transmission directions. The search unit **111** compares each of a plurality of first waveforms corresponding to the different transmission directions with the second waveform (reference waveform) stored in advance, thereby determining the similarity to the second waveform. The search unit **111** determines the first waveform with the highest similarity among similarities thus obtained. The search unit **111** sends the transmission direction of ultrasound waves corresponding to the first waveform to the direction setting unit **110**. The direction setting unit **110** changes the transmission direction of ultrasound

waves to the transmission direction. Thus, even if the end part **10** shifts in the subject's body due to the breathing, beats, body movement, throat reflection, emetic response, and the like of the subject, and the transmission direction of ultrasound waves shifts from the object to be observed, the ultrasound diagnosis apparatus **100** can change the transmission direction of ultrasound waves to follow the shift, thereby enabling the continuation of monitoring inside the subject's body without imposing burdensome tasks on the operator. Moreover, even in long-term monitoring, the ultrasound diagnosis apparatus **100** can avoid a decrease in the operation efficiency.

As in the first embodiment, the ultrasound diagnosis apparatus **100** of the second embodiment may have the end part **10** in a capsule form. Moreover, the end part **10** may have a structure in which only minimal lines such as a signal line and a power supply line are passed through the cable **11**. This makes it possible to reduce the burden on the subject compared to the case of using the TEE probe.

[Third Embodiment]

In the following, the ultrasound diagnosis apparatus **100** according to the third embodiment is described. In the second embodiment, the first waveform, which is generated periodically, is compared with the second waveform as a reference to determine the transmission direction of ultrasound waves with the highest similarity. On the other hand, the search unit **111** of the third embodiment performs the search process of the first embodiment as well as that of the second embodiment in parallel. The ultrasound diagnosis apparatus **100** of the third embodiment is similar to that of the second embodiment in other respects. The differences are mainly described below.

To generate the first waveform, the Doppler signal processing unit **108** of the second embodiment generates RAW data of a Doppler spectrum image based on an echo signal in the Doppler mode. In the third embodiment, the Doppler signal processing unit **108** sends the RAW data or the echo signal to the search unit **111**. The search unit **111** obtains signal strength in parallel with calculating the similarity of the first waveform. Further, in the third embodiment, the similarity is weighted, and also the signal strength is weighted correspondingly to the weighting of the similarity. Accordingly, the search unit **111** can make an evaluation in association with the level of similarity and the magnitude of signal strength. The search unit **111** makes an evaluation for each transmission direction based on the weight of similarity and that of signal strength. Based on this evaluation, the search unit **111** determines the optimal transmission direction of ultrasound waves, and sends it to the direction setting unit **110**.

The ultrasound diagnosis apparatus **100** of the embodiment is configured to search the transmission direction of ultrasound waves based on both the similarity and the signal strength. This improves the accuracy of searching for the transmission direction of ultrasound waves.

[Fourth Embodiment]

In the following, the ultrasound diagnosis apparatus **100** according to the fourth embodiment is described. The ultrasound diagnosis apparatus **100** of the fourth embodiment is different from that of the first and the third embodiment in the start timing of the search process by the search unit **111**. The ultrasound diagnosis apparatus **100** of the fourth embodiment is similar to that of the first embodiment in other respects. The differences are mainly described below.

In the first embodiment, the search unit **111** performs the search process at predetermined time intervals. On the other hand, the search unit **111** of the ultrasound diagnosis appa-

ratus **100** of the fourth embodiment continuously or intermittently obtains signal strength in predetermined transmission direction of ultrasound waves. Hereinafter, the operation of the search unit **111** that continuously or intermittently obtains signal strength in predetermined transmission direction of ultrasound waves is sometimes described as "monitoring signal strength" or simply as "monitoring". Besides, the search unit **111** starts the search process when signal strength obtained by monitoring drops below a threshold stored in advance.

<Operation>

Next, a description is given of a control flow to perform the search process by monitoring signal strength according to the embodiment with reference to FIG. **16**. FIG. **16** is a flowchart schematically illustrating the operation of the ultrasound diagnosis apparatus **100** of the fourth embodiment. The steps, in which the operator determines the initial setting including scan mode, and ultrasound waves are transmitted in the selected scan mode, are the same as in the first embodiment, and not described here.

(Step S61)

The main control unit **104** determines whether the Doppler mode is selected as scan mode in the initial setting.

(Step S62)

In step S61, if it is determined that the scan mode is not the Doppler mode (step S61; No), the main control unit **104** switches the scan mode to the Doppler mode to start the monitoring.

(Step S63)

When the scan mode is switched to the Doppler mode in step S62 or if it is determined that the Doppler mode is selected as scan mode in the initial setting at step S61 (step S61; Yes), the monitoring is initiated. The main control unit **104** makes the end part **10** start transmitting ultrasound waves in the Doppler mode via the transmitter unit **105** for the monitoring. If a scan mode other than the Doppler mode (B-mode, etc.) is selected in the initial setting, after the Doppler mode transmission, the scan mode is switched alternately between the Doppler mode and the scan mode selected in the initial setting.

(Step S64)

The receiver unit **106** receives an echo signal based on the Doppler mode from the end part **10**. The Doppler signal processing unit **108** performs the signal processing on the echo signal and sends a Doppler signal obtained thereby to the search unit **111**. The search unit **111** generates signal strength information based on the Doppler signal in the time corresponding to predetermined cardiac time phase.

(Step S65)

The signal strength information generated as above is compared to a threshold stored in advance. If the signal strength information indicates strength above the threshold (step S65; Yes), steps S63 to S65 are repeated.

(Step S66)

If the search unit **111** determines in step S65 that the signal strength is below the threshold (step S65; No), the main control unit **104** makes the end part **10** start transmitting/receiving ultrasound waves via the transmitter unit **105** for the search process.

The steps of the search process for determining the transmission direction of ultrasound waves and updating the setting of the transmission direction are performed in the same manner as described in the first and the third embodiments. After that, the main control unit **104** repeats steps S63 to S65.

The ultrasound diagnosis apparatus **100** of this embodiment monitors signal strength in a particular direction upon

start of transmitting/receiving ultrasound waves in selected scan mode. If the signal strength drops below a threshold, the search unit **111** starts the search process. In the search process, the search unit **111** compares pieces of information on the signal strength of a plurality of Doppler signals corresponding to different transmission directions, thereby determining the transmission direction of ultrasound waves with the highest signal strength. The direction setting unit **110** changes the transmission direction of ultrasound waves at the end part **10** to the transmission direction. Thus, even if the end part **10** shifts in the subject's body due to the breathing, beats, body movement, throat reflection, emetic response, and the like of the subject, and the transmission direction of ultrasound waves shifts from the object to be observed, the ultrasound diagnosis apparatus **100** can change the transmission direction of ultrasound waves to follow the shift, thereby enabling the continuation of monitoring inside the subject' body without imposing burdensome tasks on the operator. Moreover, even in long-term monitoring, the ultrasound diagnosis apparatus **100** can avoid a decrease in the operation efficiency.

As in the first embodiment, the ultrasound diagnosis apparatus **100** of the fourth embodiment may have the end part **10** in a capsule form. Moreover, the end part **10** may have a structure in which only minimal lines such as a signal line and a power supply line are passed through the cable **11**. This makes it possible to reduce the burden on the subject compared to the case of using the TEE probe.

Further, in the fourth embodiment, the search unit **111** performs the search process as needed. With this, the ultrasound diagnosis apparatus **100** can correct the transmission direction of ultrasound waves at appropriate timing. In this manner, the ultrasound diagnosis apparatus **100** is further capable of preventing a shift between the observation object and the transmission direction of ultrasound waves. Furthermore, the ultrasound diagnosis apparatus **100** can reduce unnecessary transmission/reception of ultrasound waves. [Fifth Embodiment]

In the following, the ultrasound diagnosis apparatus **100** according to the fifth embodiment is described. The ultrasound diagnosis apparatus **100** of the fifth embodiment is different from that of the second and the third embodiment in the start timing of the search process by the search unit **111**. The ultrasound diagnosis apparatus **100** of the fifth embodiment is similar to that of the second embodiment in other respects. The differences are mainly described below.

In the second embodiment, the search unit **111** performs the search process at predetermined time intervals. On the other hand, the search unit **111** of the ultrasound diagnosis apparatus **100** of the fifth embodiment continuously or intermittently generates a waveform based on a Doppler signal in predetermined transmission direction of ultrasound waves (hereinafter, sometimes referred to as "third waveform"). The third waveform corresponds to an example of "third waveform pattern". The search unit **111** obtains the similarity of the third waveform to the second waveform stored in advance. Hereinafter, the operation of the search unit **111** that continuously or intermittently obtains similarity in predetermined transmission direction of ultrasound waves is sometimes described as "monitoring similarity" or simply as "monitoring". Besides, the search unit **111** starts the search process when similarity obtained by monitoring drops below a threshold stored in advance.

<Operation>

Next, a description is given of a control flow to perform the search process by monitoring similarity according to the embodiment with reference to FIG. 17. FIG. 17 is a flow-

chart schematically illustrating the operation of the ultrasound diagnosis apparatus **100** of the fifth embodiment. The steps, in which the operator determines the initial setting including scan mode, and ultrasound waves are transmitted in the selected scan mode, are the same as in the second embodiment, and not described here.

(Step S71)

The main control unit **104** determines whether the Doppler mode is selected as scan mode in the initial setting.

(Step S72)

In step S71, if it is determined that the scan mode is not the Doppler mode (step S71; No), the main control unit **104** switches the scan mode to the Doppler mode to start the monitoring.

(Step S73)

When the scan mode is switched to the Doppler mode in step S72 or if it is determined that the Doppler mode is selected as scan mode as the initial setting in step S71 (step S71; Yes), the monitoring is initiated. The main control unit **104** makes the end part **10** start transmitting ultrasound waves in the Doppler mode via the transmitter unit **105** for the monitoring. If a scan mode other than the Doppler mode (B-mode, etc.) is selected in the initial setting, after the Doppler mode transmission, the scan mode is switched alternately between the Doppler mode and the scan mode selected in the initial setting.

(Step S74)

The receiver unit **106** receives an echo signal based on the Doppler mode from the end part **10**. The Doppler signal processing unit **108** performs the signal processing on the echo signal and sends RAW data obtained thereby to the generating unit **109**. The generating unit **109** generates a Doppler spectrum image based on the RAW data. The search unit **111** generates the third waveform from the Doppler spectrum image generated by the generating unit **109** in the monitoring.

(Step S75)

The search unit **111** calculates the similarity of the third waveform to the second waveform stored in advance.

(Step S76)

The similarity obtained as above is compared to a threshold stored in advance. If the third waveform indicates similarity above the threshold (step S76; Yes), steps S73 to S76 are repeated.

(Step S77)

If the search unit **111** determines in step S76 that the similarity is below the threshold (step S76; No), the main control unit **104** makes the end part **10** start transmitting/receiving ultrasound waves via the transmitter unit **105** for the search process.

The steps of the search process for determining the transmission direction of ultrasound waves and updating the setting of the transmission direction are performed in the same manner as described in the second and the third embodiment. After that, the main control unit **104** repeats steps S73 to S77.

The ultrasound diagnosis apparatus **100** of this embodiment monitors similarity between the third waveform and the second waveform in a particular direction upon start of transmitting/receiving ultrasound waves in selected scan mode. If the similarity drops below a threshold, the search unit **111** starts the search process. In the search process, the search unit **111** obtains similarity between each of a plurality of first waveforms corresponding to different transmission directions and the second waveform, thereby determining the transmission direction of ultrasound waves corresponding to the first waveform with the highest similarity among

obtained similarities. The direction setting unit **110** changes the transmission direction of ultrasound waves at the end part **10** to the transmission direction. Thus, even if the end part **10** shifts in the subject's body due to the breathing, beats, body movement, throat reflection, emetic response, and the like of the subject, and the transmission direction of ultrasound waves shifts from the object to be observed, the ultrasound diagnosis apparatus **100** can change the transmission direction of ultrasound waves to follow the shift, thereby enabling the continuation of monitoring inside the subject's body without imposing burdensome tasks on the operator. Moreover, even in long-term monitoring, the ultrasound diagnosis apparatus **100** can avoid a decrease in the operation efficiency.

As in the first embodiment, the ultrasound diagnosis apparatus **100** of the fifth embodiment may have the end part **10** in a capsule form. Moreover, the end part **10** may have a structure in which only minimal lines such as a signal line and a power supply line are passed through the cable **11**. This makes it possible to reduce the burden on the subject compared to the case of using the TEE probe.

Further, in the fifth embodiment, the search unit **111** performs the search process as needed. With this, the ultrasound diagnosis apparatus **100** can correct the transmission direction of ultrasound waves at appropriate timing. In this manner, the ultrasound diagnosis apparatus **100** is further capable of preventing a shift between the observation object and the transmission direction of ultrasound waves. Furthermore, the ultrasound diagnosis apparatus **100** can reduce unnecessary transmission/reception of ultrasound waves. [Sixth Embodiment]

In the following, the ultrasound diagnosis apparatus **100** according to the sixth embodiment is described. In the fifth embodiment, similarity is monitored between the third waveform and the second waveform in a particular direction. When the similarity drops below a threshold, the search process starts. On the other hand, the search unit **111** of the fifth embodiment performs the monitoring of the fourth embodiment as well as that of the fifth embodiment in parallel. The ultrasound diagnosis apparatus **100** of the sixth embodiment is similar to that of the fifth embodiment in other respects. The differences are mainly described below.

In the fifth embodiment, the search unit **111** monitors similarity between the third waveform and the second waveform in a predetermined direction upon start of transmitting/receiving ultrasound waves in selected scan mode. On the other hand, in the sixth embodiment, the search unit **111** monitors signal strength of a Doppler signal in the predetermined direction in parallel with monitoring similarity between the third waveform and the second waveform. The "predetermined direction" as used herein is the same direction as the transmission direction of ultrasound waves in the third waveforms. The search unit **111** of the sixth embodiment starts the search process when each or both of similarity and signal strength drop below their thresholds, respectively. The search process may be the same as that of any one of the first to the third embodiments.

The ultrasound diagnosis apparatus **100** of the embodiment is configured to determine the timing of starting the search process by monitoring similarity and signal strength. With this, the ultrasound diagnosis apparatus **100** can correct the transmission direction of ultrasound waves at appropriate timing. In this manner, the ultrasound diagnosis apparatus **100** is further capable of preventing a shift between the observation object and the transmission direction of ultra-

sound waves. Furthermore, the ultrasound diagnosis apparatus **100** can reduce unnecessary transmission/reception of ultrasound waves.

[Seventh Embodiment]

In the following, the seventh embodiment is described. The search unit **111** of the first to the sixth embodiments is configured to search for the optimal transmission direction of ultrasound wave through any one of the search processes as described above. The seventh embodiment is the same in this respect. However, the search unit of the seventh embodiment further performs, when there is found no suitable transmission direction of ultrasound waves, error notification, termination of ultrasound monitoring (transmitting/receiving ultrasound waves), and the like. The ultrasound diagnosis apparatus **100** of the embodiment is similar to that of the first to sixth embodiments in other aspects. The differences are mainly described below. (Search Process—Signal Strength)

The search unit **111** of the seventh embodiment stores a threshold for signal strength. In the search process, having determined the highest signal strength, the search unit **111** compares the signal strength with the threshold. If the signal strength is below the threshold, the search unit **111** determines that there is found no suitable transmission direction of ultrasound waves. Then, the search unit **111** notifies, via a notification unit (not illustrated), the operator of recognizable error information. For example, the notification unit displays an error message on the display unit **103**. For another example, the notification unit outputs predetermined sound from an audio output unit (not illustrated). In this case, the search unit **111** does not send information on the transmission direction of ultrasound waves to the direction setting unit **110**.

As another operation of the search unit **111**, if the signal strength is below the threshold, the search unit **111** determines that there is found no suitable transmission direction of ultrasound waves. Then, the search unit **111** informs the main control unit **104** of this. Upon receipt of the information, the main control unit **104** stops the transmission of ultrasound waves by the end part **10**. As an example of the situation where the search unit **111** cannot find the suitable transmission direction of ultrasound waves may be cited a case where the shift of the end part **10** is large. In this case, the observation object is likely to be not included in ROI even if the direction setting unit **110** rotates/tilts the ultrasound transducer **12** and changes the transmission direction of ultrasound waves by electronic scanning. (Search Process—Similarity)

The search unit **111** of the seventh embodiment stores a threshold for similarity. In the search process, having determined the transmission direction of ultrasound waves with the highest similarity, the search unit **111** compares the similarity with the threshold. If the similarity is below the threshold, the search unit **111** determines that there is found no suitable transmission direction of ultrasound waves. Then, the search unit **111** notifies, via the notification unit (not illustrated), the operator of recognizable error information. The notification unit operates in the same manner as described above. Also, the main control unit **104** stops the transmission of ultrasound waves by the end part **10** in the same manner as described above.

As in the third embodiment, when both signal strength and similarity are used in the search process, the search unit **111** performs a combination of the above processes.

In this embodiment, the search unit **111** is configured to perform, when there is found no optimal transmission direction of ultrasound waves, error notification, termination of

ultrasound transmission, and the like. For example, if the observation object is not included in ROI even by rotating/tilting the ultrasound transducer **12** and changing the transmission direction of ultrasound waves in electronic scanning, the operator needs to recognize the situation. In addition, the end part **10** is required to be removed in such a situation. In this respect, according to the embodiment, when the end part **10** has shifted largely with respect to the subject, the operator can handle the situation appropriately. [Usage Example]

Described below is an example of how to use the ultrasound diagnosis apparatus **100** according to the first to the seventh embodiments. An example is described in which the ultrasound diagnosis apparatus **100** is used to monitor cardiac ejection fraction.

(Display B-Mode Image)

For monitoring cardiac ejection fraction, the ultrasound diagnosis apparatus **100** displays a B-mode image of the heart on the display unit **103**. This is conducted, for example, as follows. First, the operator determines the initial setting, in which the B-mode is selected as scan mode, using the operation unit **102**. According to the initial setting, the transmitter unit **105** sends the end part **10** a drive control signal of the ultrasound transducer **12** in the B-mode. The ultrasound transducer **12** is driven by the transmitter **141** of the end part **10**, and ultrasound waves are transmitted to the subject.

Through the receiver **142** or the like, the end part **10** sends echo signals to the main body **101**. Through the receiver unit **106** or the like, the main body **101** sends the echo signals to the B-mode signal processing unit **107**. The B-mode signal processing unit **107** performs the signal processing on the echo signals, thereby generating RAW data related to the echo signals in the B-mode. Having received the RAW data from the B-mode signal processing unit **107**, the generating unit **109** generates B-mode image data. The generating unit **109** displays a B-mode image on the display unit **103** based on the B-mode image data. Then, the end part **10** is inserted into the subject's body by the operator. Referring to the B-mode image, the operator inserts the end part **10** into the subject's body.

(Set Contour)

The operator inserts the end part **10** in the subject's body to a predetermined position in the esophagus. Then, the operator adjusts the position of the ultrasound transducer **12** (rotate, tilt, etc.) or adjusts the ultrasound beam angle, so that the heart is included in ROI. With this, the display unit **103** displays a B-mode image representing a cross section of the heart. In the B-mode image of the heart, the main control unit **104** sets a contour at the boundary between the myocardium and the heart chamber (hereinafter, referred to as "myocardium/heart chamber boundary"). For example, the main control unit **104** extracts a contour corresponding to the boundary position in the cardiac cavity by manual setting of the operator, or by using an automatic method such as ACT (Automated-Contour-Tracking). This contour is used when the heart chamber volume is obtained for calculating the cardiac ejection fraction through, for example, modified Simpson's method, Area-Length method, or the like.

A specific example of the contour setting is described with reference to FIG. **19**. FIG. **19** is a schematic diagram illustrating a contour and operation points set on an apical two-chamber view. As illustrated in FIG. **19**, the operator sets, through the operation unit **102**, a closed curve **B1** at a predetermined position in the heart chamber indicated on the B-mode image. As illustrated in FIG. **19**, the main control unit **104** sets a plurality of operation points **R1**, **R2**,

R3, . . . , **RN** on the closed curve at predetermined intervals. The main control unit **104** moves the operation points radially toward the myocardium. For example, the main control unit **104** moves the operation points **R1**, **R2**, **R3**, . . . , **RN** on the closed curve **B1** along their normal directions **C1**, **C2**, **C3**, . . . , **CN**, respectively.

While moving the operation points **RN**, **R1**, **R2**, **R3**, . . . , **RN** radially, the main control unit **104** continuously obtains a pixel value in the B-mode image data corresponding to the position of each of the operation points **R1**, **R2**, **R3**, . . . , **RN**. Then, the main control unit **104** detects a boundary position between the myocardium and the heart chamber where the pixel value changes suddenly. Besides, the main control unit **104** generates contour data by connecting a plurality of boundary positions detected as above. In this generation of the contour data, regarding image data, the main control unit **104** sequentially retrieves pixel values corresponding to the positions of the operation points **R1**, **R2**, **R3**, . . . , **RN** that radially move in the heart chamber, thereby obtaining the amount of change in pixel value. The main control unit **104** detects the boundary between the heart chamber in which reflection of ultrasound waves is small and the myocardium with relatively large reflection (myocardium/heart chamber boundary) based on the change amount.

(Sampling Gate Set)

The operator sets sampling gate to be superimposed on a B-mode image indicating the heart using the operation unit **102**. FIG. **6** illustrates the transmission direction of the ultrasound waves in the pulsed Doppler (beam angle from the sound source) without the illustration of the sampling gate. For example, the operator sets the sampling gate to be superimposed on a broken line **L1** in FIG. **6**. The broken line **L1** runs from left atrium **LA** through mitral valve **M** to the left chamber in the B-mode image, and passes by the center of the left heart system. For example, the sampling gate is set in an area of the left ventricular cavity around the mitral valve **M**. This is the direction in which the strength of blood flow is likely to be detected as being large.

(Heart Chamber Volume Measurement)

FIGS. **20A** and **20B** illustrate a specific example of the heart chamber volume measurement performed by the main control unit **104**. Having received a selection operation through the operation unit **102**, the main control unit **104** selects **M** pieces of image data **P1** to **PM** corresponding to desired time period **T0** from time-series B-mode image data stored in the storage unit (not illustrated), and stores them in the storage unit separately. The main control unit **104** also detects the valve annulus from the contour data generated for each of the image data **P1** to **PM**, and sets the longitudinal axis **FL** of the heart based on the position of the valve annulus. In addition, the main control unit **104** draws normals to the longitudinal axis **FL** to pass division points **h_j** (**j**=1 to **J**) to divide the longitudinal axis **FL** into **J** parts at interval Δh . The main control unit **104** calculates length **X_j** (**j**=1 to **J**) between two intersections **f1_j** and **f2_j** where the normal intersects contour data **E** (see FIG. **20A**).

The main control unit **104** measures the heart chamber volume in each time phase using a method of approximating the volume by the sum of small cylinders with the length **X1** to **X_j** determined in the above manner as the diameter and the interval Δh set in advance as the height, i.e., so-called disk summation method (see FIG. **20B**). The heart chamber volume measured for each time phase is stored in a memory circuit (not illustrated) of the main control unit **104** with the time phase as incidental information.

(Cardiac Ejection Fraction Measurement)

Further, the main control unit **104** acquires heart chamber volume V_{xs} at end-systole and heart chamber volume V_{xd} at end-diastole from the heart chamber volume data stored in the memory circuit thereof. Thus, the main control unit **104** calculates the cardiac ejection fraction Z_x based on the following formula (1):

$$Z_x = (V_{xd} - V_{xs}) / V_{xd} \times 100(\%) \quad (1)$$

The measurement of the cardiac ejection fraction as described above is continuously performed until terminated by the operator or set monitoring period has elapsed.

(Monitoring Process)

The main control unit **104** starts the search process at the start timing described in any one of the first to the sixth embodiment. For example, in the ultrasound diagnosis apparatus **100**, the search unit **111** sequentially obtains the third waveform in the above direction of FIG. 6. The search unit **111** monitors the similarity between the third waveform and the second waveform. For example, if the end part **10** has shifted relatively with respect to an observation site inside the subject's body due to peristaltic motion, the similarity between the third waveform and the second waveform drops below the threshold in the monitoring of the search unit **111**. Thereby, the search process of the ultrasound diagnosis apparatus **100** is started.

(Search Process)

In the search process, based on a control signal received from the transmitter unit **105**, the end part **10** transmits ultrasound waves in the transmission direction of ultrasound waves passing through the sampling gate and in peripheral directions adjacent to the transmission direction at a predetermined angle. The search unit **111** obtains similarity between each of a plurality of first waveforms corresponding to different transmission directions and the second waveform, thereby determining the transmission direction of ultrasound waves corresponding to the first waveform with the highest similarity among obtained similarities. The search unit **111** determines whether the highest similarity drops below the threshold. If the suitable transmission direction of ultrasound waves is found, the direction setting unit **110** changes the beam angle of ultrasound waves based on information on the transmission direction. At this time, through the direction controller **16** of the end part **10**, the direction setting unit **110** drives the drive unit **18**, thereby rotating/tilting the ultrasound transducer **12**. Besides, the search unit **111** may compare the similarities of waveforms while the depth of the sampling gate is varied to obtain the depth with the highest similarity, and change the sampling gate to the depth thus obtained.

(Error Handling)

If there is found no suitable transmission direction of ultrasound waves, for example, the search unit **111** displays an error message such as "Transmission Direction Error" on the display unit **103**, and also outputs sound indicating error from the audio output unit. If there is found no suitable transmission direction of ultrasound waves, the search unit **111** may send an error signal to the main control unit **104**. Upon receipt of the error signal, the main control unit **104** terminates the monitoring by ultrasound waves. Having been notified of the error, the operator can recognize that the end part **10** had shifted, and adjust the position of the end part **10** manually by the cable **11**. Further, the operator can operate the ultrasound wave radiation surface so that the heart is included in ROI by driving the drive unit **18** using the operation unit **102** to rotate/tilt the ultrasound transducer **12**.

As well as cardiac ejection fraction, the ultrasound diagnosis apparatus **100** can monitor heart chamber volume (including left ventricular volume, left atrial volume, etc.), mitral regurgitation, and left ventricular inflow in the vicinity of the mitral valve. Also, in view of such a situation that the operator notices an obvious position shift while viewing an ultrasound image, the ultrasound diagnosis apparatus **100** may be configured so that the search process can be performed immediately through the operation unit **102**.

With the ultrasound diagnosis apparatus **100** according to the first to seventh embodiments described above, even if the end part **10** shifts in the subject's body due to the breathing, beats, body movement, throat reflection, emetic response, and the like of the subject, and the transmission direction of ultrasound waves shifts from the object to be observed, it is possible to change the transmission direction of ultrasound waves to follow the shift, thereby enabling the continuation of monitoring inside the subject's body without imposing burdensome tasks on the operator. Moreover, even in long-term monitoring, the ultrasound diagnosis apparatus **100** can avoid a decrease in the operation efficiency.

The first to the seventh embodiments can be used in any combination as appropriate. In the embodiments, not only the end part **10** in a capsule form, but a TEE probe may also be used in the configuration.

While certain embodiments have been described, these embodiments have been presented by way of example only, and are not intended to limit the scope of the inventions. Indeed, the novel embodiments described herein may be embodied in a variety of other forms; furthermore, various omissions, substitutions and changes in the form of the embodiments described herein may be made without departing from the spirit of the inventions. The accompanying claims and their equivalents are intended to cover such forms or modifications as would fall within the scope and spirit of the inventions.

What is claimed is:

1. An ultrasound diagnosis apparatus, comprising:

an ultrasound transceiver configured to

change a transmission direction of ultrasound waves, and

transmit the ultrasound waves continuously or repeatedly at predetermined intervals, the ultrasound waves being transmitted in a direction set while the ultrasound transceiver is inserted and placed in an esophagus of a subject to acquire biological information including a Doppler signal indicating blood flow information of an observation site of the subject, the observation site being heart of the subject; and

a controller configured to

obtain a direction toward the observation site based on a signal strength of the Doppler signal or a measured waveform pattern of the Doppler signal, and

control, based on the obtained direction, the ultrasound transceiver being inserted and placed in the esophagus to adjust the transmission direction of ultrasound waves to be the obtained direction.

2. The ultrasound diagnosis apparatus according to claim 1, further comprising a display unit configured to display the condition of the observation site based on the biological information.

3. The ultrasound diagnosis apparatus according to claim 1, wherein

the controller is configured to control the ultrasound transceiver to sequentially change the transmission direction of ultrasound waves, and obtain a transmis-

sion direction in which signal strength of the Doppler signal is highest as the direction toward the observation site.

4. The ultrasound diagnosis apparatus according to claim 3, wherein the controller is configured to obtain the transmission direction in which the signal strength of the Doppler signal is highest as the direction toward the observation site at predetermined time intervals.

5. The ultrasound diagnosis apparatus according to claim 3, wherein the controller is configured to obtain the transmission direction in which the signal strength of the Doppler signal is highest as the direction toward the observation site when the signal strength of the Doppler signal obtained by the ultrasound transceiver is below a threshold stored in advance.

6. The ultrasound diagnosis apparatus according to claim 1, further comprising processing circuitry configured to generate first waveform patterns based on Doppler signals indicating blood flow information of the subject obtained by the ultrasound transceiver as the biological information, wherein

the controller is configured to control the ultrasound transceiver to change the transmission direction of ultrasound waves, and, from the first waveform patterns each generated for a transmission direction, obtain a similar waveform pattern which is most similar to a second waveform pattern stored in advance, and obtain the transmission direction for which the similar waveform pattern is generated as the direction toward the observation site.

7. The ultrasound diagnosis apparatus according to claim 6, wherein the controller is configured to obtain the similar waveform pattern at predetermined time intervals.

8. The ultrasound diagnosis apparatus according to claim 6, wherein

the processing circuitry is configured to generate a third waveform pattern based on a Doppler signal in a predetermined transmission direction, and

the controller is configured to obtain similarity between the third waveform pattern and the second waveform pattern, and start a process to obtain the similar waveform pattern when the similarity is below a threshold stored in advance.

9. The ultrasound diagnosis apparatus according to claim 3, wherein

the direction in which the ultrasound transceiver transmits ultrasound waves is set to direction of left ventricle of the subject, and

the ultrasound transceiver is configured to obtain a Doppler signal from the left ventricle as the biological information.

10. The ultrasound diagnosis apparatus according to claim 2, wherein the controller is configured to sequentially receive an electrocardiogram waveform of the subject and obtain predetermined cardiac time phase, and control the ultrasound transceiver to transmit ultrasound waves to obtain the Doppler signal based on the cardiac time phase.

11. The ultrasound diagnosis apparatus according to claim 10, wherein the predetermined cardiac time phase is diastole.

12. The ultrasound diagnosis apparatus according to claim 3, wherein

the ultrasound transceiver is configured to be included in a capsule container, and

the capsule container further includes an interface configured to transmit and receive signals between the

capsule container and a main body, and a power supply line configured to supply power to the ultrasound transceiver.

13. The ultrasound diagnosis apparatus according to claim 6, wherein the second waveform pattern is generated based on the biological information acquired under a predetermined acquisition condition determined in advance, and stored.

14. The ultrasound diagnosis apparatus according to claim 2, wherein

the biological information includes a Doppler signal indicating blood flow information of the subject, and the controller is configured to obtain a position of the observation site based on the Doppler signal sequentially obtained.

15. The ultrasound diagnosis apparatus according to claim 1, wherein the biological information includes at least one of heart chamber volume, cardiac ejection fraction, and blood flow information of the observation site.

16. The ultrasound diagnosis apparatus according to claim 12, wherein

the main body includes:
a power supply connected to the power supply line; and
a signal processor connected to the controller and the interface, and configured to perform signal processing on signals received from the ultrasound transceiver, and

the capsule container is configured to be connected to the main body by the interface.

17. The ultrasound diagnosis apparatus according to claim 6, wherein

the ultrasound transceiver is configured to be included in a capsule container, and

the capsule container further includes an interface configured to transmit and receive signals between the capsule container and a main body, and a power supply line configured to supply power to the ultrasound transceiver.

18. An ultrasound diagnosis apparatus, comprising:

an ultrasound transceiver configured to update a transmission direction of ultrasound waves to follow an observation site inside of a subject, thereby correcting the transmission direction to compensate for a shift of a position of the ultrasound transceiver shifts relative to a position of the observation site, the ultrasound transceiver performing the update of the transmission direction by

transmitting the ultrasound waves in the transmission direction of the observation site, the ultrasound waves being transmitted continuously or repeatedly at predetermined intervals, and

changing the transmission direction of the ultrasound waves while the ultrasound transceiver is inserted and placed in an esophagus of the subject to acquire biological information including a Doppler signal indicating blood flow information of the observation site inside of the subject, the observation site being heart of the subject; and

a controller configured to determine, based on either (i) a signal strength of the Doppler signal or (ii) a waveform pattern of the Doppler signal, a direction from ultrasound transceiver to the observation site, and

control the ultrasound transceiver that is inserted and placed in the esophagus to update the transmission direction to the determined direction from ultrasound transceiver to the observation site.

专利名称(译)	超声波诊断仪		
公开(公告)号	US10531861	公开(公告)日	2020-01-14
申请号	US14/663108	申请日	2015-03-19
[标]申请(专利权)人(译)	株式会社东芝 东芝医疗系统株式会社		
申请(专利权)人(译)	株式会社东芝 东芝医疗系统公司		
[标]发明人	ABE YASUHIKO		
发明人	ABE, YASUHIKO		
IPC分类号	A61B8/08 A61B8/06 A61B8/12		
CPC分类号	A61B8/12 A61B8/0883 A61B8/065 A61B8/488 A61B8/06 A61B8/08 A61B8/145 A61B8/4444 A61B8/4483 A61B8/4494 A61B8/466 A61B8/483 A61B8/5292 A61B8/54 A61B8/543		
优先权	2012222590 2012-10-04 JP		
其他公开文献	US20150223781A1		
外部链接	Espacenet		

摘要(译)

超声诊断设备包括超声收发器和控制器。超声波收发器包括改变超声波的发射方向的变换器。超声波收发器在被插入到对象中的同时沿设定的方向发送超声波，以获取对象的观察部位的生物信息。控制器基于生物学信息获得朝向观察部位的方向，并控制变换器将超声波的发送方向调整为所获得的方向。

