



US01020662B2

(12) **United States Patent**
Smith et al.

(10) **Patent No.:** **US 10,206,662 B2**
(45) **Date of Patent:** **Feb. 19, 2019**

(54) **CALIBRATION OF ULTRASOUND PROBES**

(71) Applicant: **MAUI IMAGING, INC.**, Sunnyvale,
CA (US)

(72) Inventors: **David M. Smith**, Lodi, CA (US);
Sharon L. Adam, San Jose, CA (US);
Donald F. Specht, Los Altos, CA (US);
Kenneth D. Brewer, Santa Clara, CA
(US); **John P. Lunsford**, San Carlos,
CA (US); **David J. Specht**, San Jose,
CA (US)

(73) Assignee: **MAUI IMAGING, INC.**, Sunnyvale,
CA (US)

(*) Notice: Subject to any disclaimer, the term of this
patent is extended or adjusted under 35
U.S.C. 154(b) by 229 days.

(21) Appl. No.: **15/044,932**

(22) Filed: **Feb. 16, 2016**

(65) **Prior Publication Data**

US 2016/0157833 A1 Jun. 9, 2016

Related U.S. Application Data

(63) Continuation of application No. 13/279,110, filed on
Oct. 21, 2011, now Pat. No. 9,282,945, which is a
(Continued)

(51) **Int. Cl.**

A61B 8/00 (2006.01)

G01S 7/52 (2006.01)

G01S 15/89 (2006.01)

(52) **U.S. Cl.**

CPC **A61B 8/587** (2013.01); **A61B 8/00**
(2013.01); **A61B 8/4218** (2013.01);
(Continued)

(58) **Field of Classification Search**

CPC **A61B 8/587**; **A61B 8/00**; **A61B 8/4218**;
A61B 8/4254; **A61B 8/4444**;

(Continued)

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,174,286 A 3/1965 Erickson
3,895,381 A 7/1975 Kock

(Continued)

FOREIGN PATENT DOCUMENTS

CN 1781460 6/2006
CN 101116622 A 2/2008

(Continued)

OTHER PUBLICATIONS

Call et al.; U.S. Appl. No. 15/495,591 entitled "Systems and
methods for improving ultrasound image quality by applying weight-
ing factors," filed Apr. 24, 2017.

(Continued)


Primary Examiner — Daniel Pihulic

(74) *Attorney, Agent, or Firm* — Shay Glenn LLP

(57) **ABSTRACT**

A method of calibrating an ultrasound probe includes
mounting an ultrasound probe onto a calibration system,
transmitting an ultrasound test signal from an element of the
probe through a test medium of the calibration system, and
receiving the test signal on a matrix of hydrophones such
that an element's position relative to other elements and
other arrays within the same probe can be computed. Fur-
ther, the system described herein is configured to detect the
acoustic performance of elements of a probe and report the
results to an end user or service provider.

13 Claims, 43 Drawing Sheets



Related U.S. Application Data

- continuation-in-part of application No. 12/760,327,
filed on Apr. 14, 2010, now Pat. No. 8,473,239.
- (60) Provisional application No. 61/169,200, filed on Apr.
14, 2009.
- (52) **U.S. Cl.**
CPC **A61B 8/4254** (2013.01); **A61B 8/4444**
(2013.01); **A61B 8/4477** (2013.01); **A61B**
8/4483 (2013.01); **G01S 7/5205** (2013.01);
G01S 15/8913 (2013.01); **G01S 15/8915**
(2013.01)
- (58) **Field of Classification Search**
CPC . A61B 8/4477; A61B 8/4483; G01S 15/8913;
G01S 15/8915; G01S 7/5205
See application file for complete search history.

(56) References Cited

U.S. PATENT DOCUMENTS

- | | | | | | |
|---------------|---------|-------------------------------|--------------|---------|-------------------------|
| 3,974,692 A | 8/1976 | Hassler | 5,409,010 A | 4/1995 | Beach et al. |
| 4,055,988 A | 11/1977 | Dutton | 5,442,462 A | 8/1995 | Guissin |
| 4,072,922 A | 2/1978 | Taner et al. | 5,454,372 A | 10/1995 | Banjanin et al. |
| 4,097,835 A | 6/1978 | Green | 5,503,152 A | 4/1996 | Oakley et al. |
| 4,105,018 A | 8/1978 | Greenleaf et al. | 5,515,853 A | 5/1996 | Smith et al. |
| 4,180,792 A | 12/1979 | Lederman et al. | 5,515,856 A | 5/1996 | Olstad et al. |
| 4,205,394 A * | 5/1980 | Pickens G01V 13/00 | 5,522,393 A | 6/1996 | Phillips et al. |
| | | 367/13 | 5,526,815 A | 6/1996 | Granz et al. |
| 4,229,798 A * | 10/1980 | Rosie G01F 23/2962 | 5,544,659 A | 8/1996 | Banjanin |
| | | 340/621 | 5,558,092 A | 9/1996 | Unger et al. |
| 4,259,733 A | 3/1981 | Taner et al. | 5,564,423 A | 10/1996 | Mele et al. |
| 4,265,126 A | 5/1981 | Papadofrangakis et al. | 5,568,812 A | 10/1996 | Murashita et al. |
| 4,271,842 A | 6/1981 | Specht et al. | 5,570,691 A | 11/1996 | Wright et al. |
| 4,325,257 A | 4/1982 | Kino et al. | 5,581,517 A | 12/1996 | Gee et al. |
| 4,327,738 A | 5/1982 | Green et al. | 5,625,149 A | 4/1997 | Gururaja et al. |
| 4,333,474 A | 6/1982 | Nigam | 5,628,320 A | 5/1997 | Teo |
| 4,339,952 A | 7/1982 | Foster | 5,673,697 A | 10/1997 | Bryan et al. |
| 4,452,084 A | 6/1984 | Taenzler | 5,675,550 A | 10/1997 | Ekhaus |
| 4,501,279 A | 2/1985 | Seo | 5,720,291 A | 2/1998 | Schwartz |
| 4,511,998 A | 4/1985 | Kanda et al. | 5,720,708 A | 2/1998 | Lu et al. |
| 4,539,847 A | 9/1985 | Paap | 5,744,898 A | 4/1998 | Smith et al. |
| 4,566,459 A | 1/1986 | Umemura et al. | 5,769,079 A | 6/1998 | Hossack |
| 4,567,768 A | 2/1986 | Satoh et al. | 5,784,334 A | 7/1998 | Sena et al. |
| 4,604,697 A | 8/1986 | Luthra et al. | 5,785,654 A | 7/1998 | Iinuma et al. |
| 4,662,222 A | 5/1987 | Johnson | 5,795,297 A | 8/1998 | Daigle |
| 4,669,482 A | 6/1987 | Ophir | 5,797,845 A | 8/1998 | Barabash et al. |
| 4,682,497 A | 7/1987 | Sasaki | 5,798,459 A | 8/1998 | Ohba et al. |
| 4,781,199 A | 11/1988 | Hirama et al. | 5,820,561 A | 10/1998 | Olstad et al. |
| 4,817,434 A | 4/1989 | Anderson | 5,838,564 A | 11/1998 | Bahorich et al. |
| 4,831,601 A | 5/1989 | Breimesser et al. | 5,850,622 A | 12/1998 | Vassiliou et al. |
| 4,893,284 A | 1/1990 | Magrane | 5,862,100 A | 1/1999 | VerWest |
| 4,893,628 A | 1/1990 | Angelsen | 5,870,691 A | 2/1999 | Partyka et al. |
| 5,050,588 A | 9/1991 | Grey et al. | 5,876,342 A | 3/1999 | Chen et al. |
| 5,062,295 A * | 11/1991 | Shakkottai G01F 23/2962 | 5,891,038 A | 4/1999 | Syed-Bolorforosh et al. |
| | | 340/621 | 5,892,732 A | 4/1999 | Gersztenkorn |
| 5,141,738 A | 8/1992 | Rasor et al. | 5,916,169 A | 6/1999 | Hanafy et al. |
| 5,161,536 A | 11/1992 | Vilkomerson et al. | 5,919,139 A | 7/1999 | Lin |
| 5,197,475 A | 3/1993 | Antich et al. | 5,920,285 A | 7/1999 | Benjamin |
| 5,226,019 A | 7/1993 | Bahorich | 5,930,730 A | 7/1999 | Marfurt et al. |
| 5,230,339 A | 7/1993 | Charlebois | 5,940,778 A | 8/1999 | Marfurt et al. |
| 5,269,309 A | 12/1993 | Fort et al. | 5,951,479 A | 9/1999 | Holm et al. |
| 5,278,757 A | 1/1994 | Hector et al. | 5,964,707 A | 10/1999 | Fenster et al. |
| 5,293,871 A | 3/1994 | Reinstein et al. | 5,969,661 A | 10/1999 | Benjamin |
| 5,299,576 A | 4/1994 | Shiba | 5,999,836 A | 12/1999 | Nelson et al. |
| 5,301,674 A | 4/1994 | Erikson et al. | 6,007,499 A | 12/1999 | Martin et al. |
| 5,305,756 A | 4/1994 | Entrekin et al. | 6,013,032 A | 1/2000 | Savord |
| 5,339,282 A | 8/1994 | Kuhn et al. | 6,014,473 A | 1/2000 | Hossack et al. |
| 5,340,510 A | 8/1994 | Bowen | 6,048,315 A | 4/2000 | Chiao et al. |
| 5,345,426 A | 9/1994 | Lipschutz | 6,049,509 A | 4/2000 | Sonneland et al. |
| 5,349,960 A | 9/1994 | Gondo | 6,050,943 A | 4/2000 | Slayton et al. |
| 5,355,888 A | 10/1994 | Kendall | 6,056,693 A | 5/2000 | Haider |
| 5,381,794 A | 1/1995 | Tei et al. | 6,058,074 A | 5/2000 | Swan et al. |
| 5,398,216 A | 3/1995 | Hall et al. | 6,077,224 A | 6/2000 | Lang et al. |
| | | | 6,092,026 A | 7/2000 | Bahorich et al. |
| | | | 6,122,538 A | 9/2000 | Sliwa, Jr. et al. |
| | | | 6,123,670 A | 9/2000 | Mo |
| | | | 6,129,672 A | 10/2000 | Seward et al. |
| | | | 6,135,960 A | 10/2000 | Holmberg |
| | | | 6,138,075 A | 10/2000 | Yost |
| | | | 6,148,095 A | 11/2000 | Prause et al. |
| | | | 6,162,175 A | 12/2000 | Marian, Jr. et al. |
| | | | 6,166,384 A | 12/2000 | Dentinger et al. |
| | | | 6,166,853 A | 12/2000 | Sapia et al. |
| | | | 6,193,665 B1 | 2/2001 | Hall et al. |
| | | | 6,196,739 B1 | 3/2001 | Silverbrook |
| | | | 6,200,266 B1 | 3/2001 | Shokrollahi et al. |
| | | | 6,210,335 B1 | 4/2001 | Miller |
| | | | 6,213,958 B1 | 4/2001 | Winder |
| | | | 6,221,019 B1 | 4/2001 | Kantorovich |
| | | | 6,231,511 B1 | 5/2001 | Bae |
| | | | 6,238,342 B1 | 5/2001 | Feleppa et al. |
| | | | 6,246,901 B1 | 6/2001 | Benaron |
| | | | 6,251,073 B1 | 6/2001 | Imran et al. |
| | | | 6,264,609 B1 | 7/2001 | Herrington et al. |
| | | | 6,266,551 B1 | 7/2001 | Osadchey et al. |
| | | | 6,278,949 B1 | 8/2001 | Alam |
| | | | 6,289,230 B1 | 9/2001 | Chaiken et al. |
| | | | 6,299,580 B1 | 10/2001 | Asafusa |
| | | | 6,304,684 B1 | 10/2001 | Niczyporuk et al. |

(56)

References Cited

U.S. PATENT DOCUMENTS

6,309,356 B1	10/2001	Ustuner et al.	7,474,778 B2	1/2009	Shinomura et al.	
6,324,453 B1	11/2001	Breed et al.	7,481,577 B2	1/2009	Ramamurthy et al.	
6,345,539 B1	2/2002	Rawes et al.	7,491,171 B2	2/2009	Barthe et al.	
6,361,500 B1	3/2002	Masters	7,497,828 B1	3/2009	Wilk et al.	
6,363,033 B1	3/2002	Cole et al.	7,497,830 B2	3/2009	Li	
6,370,480 B1	4/2002	Gupta et al.	7,510,529 B2	3/2009	Chou et al.	
6,374,185 B1	4/2002	Taner et al.	7,514,851 B2	4/2009	Wilser et al.	
6,394,955 B1	5/2002	Perlitz	7,549,962 B2	6/2009	Dreschel et al.	
6,423,002 B1	7/2002	Hossack	7,574,026 B2	8/2009	Rasche et al.	
6,436,046 B1	8/2002	Napolitano et al.	7,625,343 B2	12/2009	Cao et al.	
6,449,821 B1	9/2002	Sudol et al.	7,637,869 B2	12/2009	Sudol	
6,450,965 B2	9/2002	Williams et al.	7,668,583 B2	2/2010	Fegert et al.	
6,468,216 B1	10/2002	Powers et al.	7,674,228 B2	3/2010	Williams et al.	
6,471,650 B2	10/2002	Powers et al.	7,682,311 B2	3/2010	Simopoulos et al.	
6,475,150 B2	11/2002	Haddad	7,699,776 B2	4/2010	Walker et al.	
6,480,790 B1	11/2002	Calvert et al.	7,722,541 B2	5/2010	Cai	
6,487,502 B1	11/2002	Taner	7,744,532 B2	6/2010	Ustuner et al.	
6,499,536 B1	12/2002	Ellingsen	7,750,311 B2	7/2010	Daghighian	
6,508,768 B1	1/2003	Hall et al.	7,785,260 B2	8/2010	Umemura et al.	
6,508,770 B1	1/2003	Cai	7,787,680 B2	8/2010	Ahn et al.	
6,517,484 B1	2/2003	Wilk et al.	7,806,828 B2	10/2010	Stringer	
6,526,163 B1	2/2003	Halmann et al.	7,819,810 B2	10/2010	Stringer et al.	
6,543,272 B1	4/2003	Vitek	7,822,250 B2	10/2010	Yao et al.	
6,547,732 B2	4/2003	Jago	7,824,337 B2	11/2010	Abe et al.	
6,551,246 B1	4/2003	Ustuner et al.	7,833,163 B2	11/2010	Cai	
6,565,510 B1	5/2003	Haider	7,837,624 B1	11/2010	Hossack et al.	
6,585,647 B1	7/2003	Winder	7,846,097 B2	12/2010	Jones et al.	
6,604,404 B2 *	8/2003	Paltieli A61B 8/587	7,850,613 B2	12/2010	Stribling	
		73/1.82	7,862,508 B2	1/2011	Davies et al.	
			7,867,167 B2 *	1/2011	Boctor A61B 8/00	600/437
6,604,421 B1	8/2003	Li	7,876,945 B2	1/2011	Lötjönen	
6,614,560 B1	9/2003	Silverbrook	7,887,486 B2	2/2011	Ustuner et al.	
6,620,101 B2	9/2003	Azzam et al.	7,901,358 B2	3/2011	Mehl et al.	
6,652,461 B1	11/2003	Levkovitz	7,914,451 B2	3/2011	Davies	
6,668,654 B2	12/2003	Dubois et al.	7,919,906 B2	4/2011	Cerofolini	
6,672,165 B2	1/2004	Rather et al.	7,926,350 B2	4/2011	Kröning et al.	
6,681,185 B1	1/2004	Young et al.	7,927,280 B2	4/2011	Davidson	
6,690,816 B2	2/2004	Aylward et al.	7,972,271 B2	7/2011	Johnson et al.	
6,692,450 B1	2/2004	Coleman	7,984,637 B2	7/2011	Ao et al.	
6,695,778 B2	2/2004	Golland et al.	7,984,651 B2	7/2011	Randall et al.	
6,702,745 B1	3/2004	Smythe	8,002,705 B1	8/2011	Napolitano et al.	
6,719,693 B2	4/2004	Richard	8,007,439 B2	8/2011	Specht	
6,728,567 B2	4/2004	Rather et al.	8,057,392 B2	11/2011	Hossack et al.	
6,752,762 B1	6/2004	DeJong et al.	8,057,393 B2	11/2011	Yao et al.	
6,755,787 B2	6/2004	Hossack et al.	8,079,263 B2	12/2011	Randall et al.	
6,780,152 B2	8/2004	Ustuner et al.	8,079,956 B2	12/2011	Azuma et al.	
6,790,182 B2	9/2004	Eck et al.	8,088,067 B2	1/2012	Vortman et al.	
6,835,178 B1 *	12/2004	Wilson A61B 8/0875	8,088,068 B2	1/2012	Yao et al.	
		600/449	8,088,071 B2	1/2012	Hwang et al.	
6,837,853 B2	1/2005	Marian	8,105,239 B2	1/2012	Specht	
6,843,770 B2	1/2005	Sumanaweera	8,135,190 B2	3/2012	Bae et al.	
6,847,737 B1	1/2005	Kouri et al.	8,157,737 B2	4/2012	Zhang et al.	
6,854,332 B2	2/2005	Alleyne	8,182,427 B2	5/2012	Wu et al.	
6,865,140 B2	3/2005	Thomenius et al.	8,202,219 B2	6/2012	Luo et al.	
6,932,767 B2	8/2005	Landry et al.	8,277,383 B2	10/2012	Specht	
7,033,320 B2	4/2006	Von Behren et al.	8,279,705 B2	10/2012	Choi et al.	
7,087,023 B2	8/2006	Daft et al.	8,412,307 B2	4/2013	Willis et al.	
7,104,956 B1	9/2006	Christopher	8,419,642 B2	4/2013	Sandrin et al.	
7,217,243 B2	5/2007	Takeuchi	8,473,239 B2	6/2013	Specht et al.	
7,221,867 B2	5/2007	Silverbrook	8,478,382 B2	7/2013	Burnside et al.	
7,231,072 B2	6/2007	Yamano et al.	8,532,951 B2	9/2013	Roy et al.	
7,269,299 B2	9/2007	Schroeder	8,582,848 B2	11/2013	Funka-Lea et al.	
7,283,652 B2	10/2007	Mendonca et al.	8,602,993 B2	12/2013	Specht et al.	
7,285,094 B2	10/2007	Nohara et al.	8,627,724 B2	1/2014	Papadopoulos et al.	
7,293,462 B2	11/2007	Lee et al.	8,634,615 B2	1/2014	Brabec	
7,313,053 B2	12/2007	Wodnicki	8,672,846 B2	3/2014	Napolitano et al.	
7,366,704 B2	4/2008	Reading et al.	8,684,936 B2	4/2014	Specht	
7,402,136 B2	7/2008	Hossack et al.	9,072,495 B2	7/2015	Specht	
7,410,469 B1	8/2008	Talish et al.	9,146,313 B2	9/2015	Specht et al.	
7,415,880 B2	8/2008	Renzel	9,192,355 B2	11/2015	Specht et al.	
7,443,765 B2	10/2008	Thomenius et al.	9,220,478 B2	12/2015	Smith et al.	
7,444,875 B1	11/2008	Wu et al.	9,247,926 B2	2/2016	Smith et al.	
7,447,535 B2	11/2008	Lavi	9,265,484 B2	2/2016	Brewer et al.	
7,448,998 B2	11/2008	Robinson	9,282,945 B2 *	3/2016	Smith A61B 8/00	
7,466,848 B2	12/2008	Metaxas et al.	9,339,256 B2	5/2016	Specht et al.	
7,469,096 B2	12/2008	Silverbrook	2002/0035864 A1 *	3/2002	Paltieli A61B 8/587	73/1.01
			2002/0087071 A1	7/2002	Schmitz et al.	

(56)

References Cited

U.S. PATENT DOCUMENTS

2002/0111568 A1	8/2002	Bukshpan	2008/0114253 A1	5/2008	Randall et al.
2002/0138003 A1	9/2002	Bukshpan	2008/0114255 A1	5/2008	Schwartz et al.
2002/0161299 A1	10/2002	Prater et al.	2008/0125659 A1	5/2008	Wilser et al.
2003/0013962 A1	1/2003	Bjaerum et al.	2008/0181479 A1	7/2008	Yang et al.
2003/0028111 A1	2/2003	Vaezy et al.	2008/0183075 A1	7/2008	Govari et al.
2003/0040669 A1	2/2003	Grass et al.	2008/0188747 A1	8/2008	Randall et al.
2003/0228053 A1	12/2003	Li et al.	2008/0188750 A1	8/2008	Randall et al.
2004/0054283 A1	3/2004	Corey et al.	2008/0194957 A1	8/2008	Hector et al.
2004/0068184 A1	4/2004	Trahey et al.	2008/0194958 A1	8/2008	Lee et al.
2004/0100163 A1	5/2004	Baumgartner et al.	2008/0194959 A1	8/2008	Wang et al.
2004/0111028 A1	6/2004	Abe et al.	2008/0208061 A1	8/2008	Halmann
2004/0122313 A1	6/2004	Moore et al.	2008/0242996 A1	10/2008	Hall et al.
2004/0122322 A1	6/2004	Moore et al.	2008/0249408 A1	10/2008	Palmeri et al.
2004/0127793 A1	7/2004	Mendlein et al.	2008/0255452 A1	10/2008	Entrekin
2004/0138565 A1	7/2004	Trucco	2008/0269604 A1 *	10/2008	Boctor A61B 8/00 600/437
2004/0144176 A1	7/2004	Yoden	2008/0269613 A1	10/2008	Summers et al.
2004/0236217 A1	11/2004	Cerwin et al.	2008/0275344 A1	11/2008	Glide-Hurst et al.
2004/0236223 A1	11/2004	Barnes et al.	2008/0285819 A1	11/2008	Konofagou et al.
2005/0004449 A1	1/2005	Mitschke et al.	2008/0287787 A1	11/2008	Sauer et al.
2005/0053305 A1	3/2005	Li et al.	2008/0294045 A1	11/2008	Ellington et al.
2005/0054910 A1	3/2005	Tremblay et al.	2008/0294050 A1	11/2008	Shinomura et al.
2005/0090743 A1	4/2005	Kawashima et al.	2008/0294052 A1	11/2008	Wilser et al.
2005/0090745 A1	4/2005	Steen	2008/0306382 A1	12/2008	Guracar et al.
2005/0111846 A1	5/2005	Steinbacher et al.	2008/0306386 A1	12/2008	Baba et al.
2005/0113689 A1	5/2005	Gritzky	2008/0319317 A1	12/2008	Kamiyama et al.
2005/0113694 A1	5/2005	Haugen et al.	2009/0010459 A1	1/2009	Garbini et al.
2005/0124883 A1	6/2005	Hunt	2009/0012393 A1	1/2009	Choi
2005/0131300 A1	6/2005	Bakircioglu et al.	2009/0016163 A1	1/2009	Freeman et al.
2005/0147297 A1	7/2005	McLaughlin et al.	2009/0018445 A1	1/2009	Schers et al.
2005/0165312 A1	7/2005	Knowles et al.	2009/0024039 A1	1/2009	Wang et al.
2005/0203404 A1	9/2005	Freiburger	2009/0036780 A1	2/2009	Abraham
2005/0215883 A1	9/2005	Hundley et al.	2009/0043206 A1	2/2009	Towfiq et al.
2005/0240125 A1	10/2005	Makin et al.	2009/0048519 A1	2/2009	Hossack et al.
2005/0252295 A1	11/2005	Fink et al.	2009/0069681 A1	3/2009	Lundberg et al.
2005/0281447 A1	12/2005	Moreau-Gobard et al.	2009/0069686 A1	3/2009	Daft et al.
2005/0288588 A1	12/2005	Weber et al.	2009/0069692 A1	3/2009	Cooley et al.
2006/0062447 A1	3/2006	Rinck et al.	2009/0099483 A1	4/2009	Rybyanets
2006/0074313 A1	4/2006	Slayton et al.	2009/0112095 A1	4/2009	Daigle
2006/0074315 A1	4/2006	Liang et al.	2009/0131797 A1	5/2009	Jeong et al.
2006/0074320 A1	4/2006	Yoo et al.	2009/0143680 A1	6/2009	Yao et al.
2006/0079759 A1	4/2006	Vaillant et al.	2009/0148012 A1	6/2009	Altmann et al.
2006/0079778 A1	4/2006	Mo et al.	2009/0150094 A1	6/2009	Van Velsor et al.
2006/0079782 A1	4/2006	Beach et al.	2009/0182233 A1	7/2009	Wodnicki
2006/0094962 A1	5/2006	Clark	2009/0182237 A1	7/2009	Angelsen et al.
2006/0111634 A1	5/2006	Wu	2009/0198134 A1	8/2009	Hashimoto et al.
2006/0122506 A1	6/2006	Davies et al.	2009/0203997 A1	8/2009	Ustuner
2006/0173327 A1	8/2006	Kim	2009/0208080 A1	8/2009	Grau et al.
2006/0262961 A1	11/2006	Holsing et al.	2009/0259128 A1	10/2009	Stribling
2006/0270934 A1	11/2006	Savord et al.	2009/0264760 A1	10/2009	Lazebnik et al.
2007/0016022 A1	1/2007	Blalock et al.	2009/0306510 A1	12/2009	Hashiba et al.
2007/0016044 A1	1/2007	Blalock et al.	2009/0326379 A1	12/2009	Daigle et al.
2007/0036414 A1	2/2007	Georgescu et al.	2010/0010354 A1	1/2010	Skerl et al.
2007/0055155 A1	3/2007	Owen et al.	2010/0016725 A1	1/2010	Thiele
2007/0078345 A1	4/2007	Mo et al.	2010/0063397 A1	3/2010	Wagner
2007/0088213 A1	4/2007	Poland	2010/0063399 A1	3/2010	Halker et al.
2007/0138157 A1	6/2007	Dane et al.	2010/0069751 A1	3/2010	Hazard et al.
2007/0161898 A1	7/2007	Hao et al.	2010/0069756 A1	3/2010	Ogasawara et al.
2007/0161904 A1	7/2007	Urbano	2010/0106431 A1	4/2010	Baba et al.
2007/0167752 A1	7/2007	Proulx et al.	2010/0109481 A1	5/2010	Buccafusca
2007/0167824 A1	7/2007	Lee et al.	2010/0121193 A1	5/2010	Fukukita et al.
2007/0232914 A1	10/2007	Chen et al.	2010/0121196 A1	5/2010	Hwang et al.
2007/0238985 A1	10/2007	Smith et al.	2010/0130855 A1	5/2010	Lundberg et al.
2007/0242567 A1	10/2007	Daft et al.	2010/0168566 A1	7/2010	Bercoff et al.
2008/0110261 A1	5/2008	Randall et al.	2010/0168578 A1	7/2010	Garson, Jr. et al.
2008/0110263 A1	5/2008	Klessel et al.	2010/0174194 A1	7/2010	Chiang et al.
2008/0112265 A1	5/2008	Urbano et al.	2010/0191110 A1	7/2010	Insana et al.
2008/0114241 A1	5/2008	Randall et al.	2010/0217124 A1	8/2010	Cooley
2008/0114245 A1	5/2008	Randall et al.	2010/0228126 A1	9/2010	Emery et al.
2008/0114246 A1	5/2008	Randall et al.	2010/0240994 A1	9/2010	Zheng
2008/0114247 A1	5/2008	Urbano et al.	2010/0249570 A1	9/2010	Carson et al.
2008/0114248 A1	5/2008	Urbano et al.	2010/0249596 A1	9/2010	Magee
2008/0114249 A1	5/2008	Randall et al.	2010/0256488 A1	10/2010	Kim et al.
2008/0114250 A1	5/2008	Urbano et al.	2010/0262013 A1	10/2010	Smith et al.
2008/0114251 A1	5/2008	Weymer et al.	2010/0266176 A1	10/2010	Masumoto et al.
2008/0114252 A1	5/2008	Randall et al.	2010/0286525 A1	11/2010	Osumi
			2010/0286527 A1	11/2010	Cannon et al.
			2010/0310143 A1	12/2010	Rao et al.
			2010/0324418 A1	12/2010	El-Aklouk et al.

(56)

References Cited

U.S. PATENT DOCUMENTS

2010/0324423 A1 12/2010 El-Aklouk et al.
 2010/0329521 A1 12/2010 Beymer et al.
 2011/0005322 A1 1/2011 Ustuner
 2011/0016977 A1 1/2011 Guracar
 2011/0021920 A1 1/2011 Shafir et al.
 2011/0021923 A1 1/2011 Daft et al.
 2011/0033098 A1 2/2011 Richter et al.
 2011/0044133 A1 2/2011 Tokita
 2011/0066030 A1 3/2011 Yao
 2011/0098565 A1 4/2011 Masuzawa
 2011/0112400 A1 5/2011 Emery et al.
 2011/0112404 A1 5/2011 Gourevitch
 2011/0125017 A1 5/2011 Ramamurthy et al.
 2011/0270088 A1 11/2011 Shiina
 2011/0301470 A1 12/2011 Sato et al.
 2011/0306886 A1 12/2011 Daft et al.
 2011/0319764 A1 12/2011 Okada et al.
 2012/0035482 A1 2/2012 Kim et al.
 2012/0036934 A1 2/2012 Kröning et al.
 2012/0057428 A1* 3/2012 Specht A61B 8/00
 367/13
 2012/0085173 A1 4/2012 Papadopoulos et al.
 2012/0095347 A1 4/2012 Adam et al.
 2012/0101378 A1 4/2012 Lee
 2012/0114210 A1 5/2012 Kim et al.
 2012/0116226 A1 5/2012 Specht
 2012/0121150 A1 5/2012 Murashita
 2012/0137778 A1 6/2012 Kitazawa et al.
 2012/0141002 A1 6/2012 Urbano et al.
 2012/0165670 A1 6/2012 Shi et al.
 2012/0179044 A1 7/2012 Chiang et al.
 2012/0226201 A1 9/2012 Clark et al.
 2012/0235998 A1 9/2012 Smith-Casem et al.
 2012/0243763 A1 9/2012 Wen et al.
 2012/0253194 A1 10/2012 Tamura
 2012/0265075 A1 10/2012 Pedrizzetti et al.
 2012/0277585 A1 11/2012 Koenig et al.
 2013/0070062 A1 3/2013 Fouras et al.
 2013/0076207 A1 3/2013 Krohn et al.
 2013/0079639 A1 3/2013 Hctor et al.
 2013/0083628 A1 4/2013 Qiao et al.
 2013/0088122 A1 4/2013 Krohn et al.
 2013/0116561 A1 5/2013 Rothberg et al.
 2013/0131516 A1 5/2013 Katsuyama
 2013/0144165 A1 6/2013 Ebbini et al.
 2013/0144166 A1 6/2013 Specht et al.
 2013/0253325 A1 9/2013 Call et al.
 2013/0258805 A1 10/2013 Hansen et al.
 2013/0261463 A1 10/2013 Chiang et al.
 2014/0043933 A1 2/2014 Belevich et al.
 2014/0058266 A1 2/2014 Call et al.
 2014/0073921 A1 3/2014 Specht et al.
 2014/0086014 A1 3/2014 Kobayashi
 2014/0243673 A1 8/2014 Anand et al.
 2014/0269209 A1 9/2014 Smith et al.
 2015/0045668 A1 2/2015 Smith et al.
 2015/0080727 A1 3/2015 Specht et al.
 2015/0297184 A1 10/2015 Specht
 2015/0374345 A1 12/2015 Specht et al.
 2016/0095579 A1 4/2016 Smith et al.
 2016/0157833 A1* 6/2016 Smith A61B 8/00
 367/13
 2017/0074982 A1 3/2017 Smith et al.
 2017/0079621 A1 3/2017 Specht et al.

FOREIGN PATENT DOCUMENTS

CN 101190134 A 6/2008
 CN 101453955 A 6/2009
 CN 101843501 A 9/2010
 CN 102018533 A 4/2011
 CN 102123668 7/2011
 EP 1949856 A1 7/2008
 EP 2058796 A2 5/2009

EP 2101191 A2 9/2009
 EP 2182352 A2 5/2010
 EP 2187813 A1 5/2010
 EP 2198785 A1 6/2010
 EP 1757955 B1 11/2010
 EP 2325672 A1 5/2011
 EP 2356941 A1 8/2011
 EP 1979739 10/2011
 EP 2385391 A2 11/2011
 EP 2294400 2/2012
 EP 2453256 A2 5/2012
 EP 1840594 B1 6/2012
 EP 2514368 A1 10/2012
 EP 1850743 B1 12/2012
 EP 1594404 B1 9/2013
 EP 2026280 B1 10/2013
 FR 2851662 A1 8/2004
 JP S49-11189 A 1/1974
 JP S54-44375 A 4/1979
 JP S55-103839 A 8/1980
 JP 57-31848 A 2/1982
 JP 58-223059 A 12/1983
 JP 59-101143 A 6/1984
 JP S59-174151 A 10/1984
 JP S60-13109 U 1/1985
 JP S60-68836 A 4/1985
 JP 2-501431 A 5/1990
 JP 03015455 A 1/1991
 JP 03126443 A 5/1991
 JP 04017842 A 1/1992
 JP 4-67856 3/1992
 JP 05-042138 A 2/1993
 JP 6-125908 A 5/1994
 JP 7-051266 A 2/1995
 JP 07204201 A 8/1995
 JP 08154930 A 6/1996
 JP 08-252253 10/1996
 JP 9-103429 A 4/1997
 JP 9-201361 A 8/1997
 JP 2777197 B 5/1998
 JP 10-216128 A 8/1998
 JP 11-089833 A 4/1999
 JP 11-239578 A 9/1999
 JP 2001-507794 A 6/2001
 JP 2001-245884 A 9/2001
 JP 2002-209894 A 7/2002
 JP 2002-253548 A 9/2002
 JP 2002-253549 A 9/2002
 JP 2004-167092 A 6/2004
 JP 2004-215987 8/2004
 JP 2004-337457 12/2004
 JP 2004-351214 12/2004
 JP 2005152187 A 6/2005
 JP 2005-523792 8/2005
 JP 2005-526539 9/2005
 JP 2006051356 A 2/2006
 JP 2006-61203 A 3/2006
 JP 2006-122657 A 5/2006
 JP 2006130313 A 5/2006
 JP 2007-325937 A 12/2007
 JP 2008-122209 5/2008
 JP 2008-513763 A 5/2008
 JP 2008132342 A 6/2008
 JP 2008522642 A 7/2008
 JP 2008-259541 A 10/2008
 JP 2008279274 A 11/2008
 JP 2009240667 A 10/2009
 JP 20105375 1/2010
 JP 2010124842 A 6/2010
 JP 2010526626 A 8/2010
 KR 100715132 B1 4/2007
 KR 1020090103408 A 10/2009
 WO WO92/18054 A1 10/1992
 WO WO98/00719 A2 1/1998
 WO WO01/64109 A1 9/2001
 WO WO02/084594 A2 10/2002
 WO WO2005/009245 A1 2/2005
 WO WO2006/114735 A1 11/2006
 WO WO2007/127147 A2 11/2007

(56)

References Cited

FOREIGN PATENT DOCUMENTS

WO	WO2009/060182	A2	5/2009
WO	WO2010/095094	A1	8/2010
WO	WO2010/139519	A1	12/2010
WO	WO2011/004661	A1	1/2011
WO	WO2011/057252	A1	5/2011
WO	WO2011/064688	A1	6/2011
WO	WO2011/100697	A1	8/2011
WO	WO2011/123529	A1	10/2011
WO	WO2012/028896	A1	3/2012
WO	WO2012/049124	A2	4/2012
WO	WO2012/049612	A2	4/2012
WO	WO2012/078639	A1	6/2012
WO	WO2012/091280	A1	7/2012
WO	WO2012/112540	A2	8/2012
WO	WO2012/131340	A2	10/2012
WO	WO2012/160541	A2	11/2012
WO	WO2013/059358	A2	4/2013

OTHER PUBLICATIONS

Arigovindan et al.; Full motion and flow field recovery from echo doppler data; *IEEE Transactions on Medical Imaging*; 26(1); pp. 31-45; Jan. 2007.

Capineri et al.; A doppler system for dynamic vector velocity maps; *Ultrasound in Medicine & Biology*; 28(2); pp. 237-248; Feb. 28, 2002.

Dunmire et al.; A brief history of vector doppler; *Medical Imaging 2001*; International Society for Optics and Photonics; pp. 200-214; May 30, 2001.

Saad et al.; Computer vision approach for ultrasound doppler angle estimation; *Journal of Digital Imaging*; 22(6); pp. 681-688; Dec. 1, 2009.

Zang et al.; A high-frequency high frame rate duplex ultrasound linear array imaging system for small animal imaging; *IEEE transactions on ultrasound, ferroelectrics, and frequency control*; 57(7); pp. 1548-1567; Jul. 2010.

Abeysekera et al.; Alignment and calibration of dual ultrasound transducers using a wedge phantom; *Ultrasound in Medicine and Biology*; 37(2); pp. 271-279; Feb. 2011.

Carson et al.; Measurement of photoacoustic transducer position by robotic source placement and nonlinear parameter estimation; *Bio-medical Optics (BiOS)*; International Society for Optics and Photonics (9th Conf. on Biomedical Thermoacoustics, Optoacoustics, and Acousto-optics; vol. 6856; 9 pages; Feb. 28, 2008.

Chen et al.; Maximum-likelihood source localization and unknown sensor location estimation for wideband signals in the near-field; *IEEE Transactions on Signal Processing*; 50(8); pp. 1843-1854; Aug. 2002.

Chen et al.; Source localization and tracking of a wideband source using a randomly distributed beamforming sensor array; *International Journal of High Performance Computing Applications*; 16(3); pp. 259-272; Fall 2002.

Cristianini et al.; *An Introduction to Support Vector Machines*; Cambridge University Press; pp. 93-111; Mar. 2000.

Du et al.; User parameter free approaches to multistatic adaptive ultrasound imaging; 5th IEEE International Symposium; pp. 1287-1290, May 2008.

Feigenbaum, Harvey, M.D.; *Echocardiography*; Lippincott Williams & Wilkins; Philadelphia; 5th Ed.; pp. 482, 484; Feb. 1994.

Fernandez et al.; High resolution ultrasound beamforming using synthetic and adaptive imaging techniques; *Proceedings IEEE International Symposium on Biomedical Imaging*; Washington, D.C.; pp. 433-436; Jul. 7-10, 2002.

Gazor et al.; Wideband multi-source beamforming with array location calibration and direction finding; *Conference on Acoustics, Speech and Signal Processing ICASSP-95*; Detroit, MI; vol. 3 IEEE; pp. 1904-1907; May 9-12, 1995.

Haykin, Simon; *Neural Networks: A Comprehensive Foundation* (2nd Ed.); Prentice Hall; pp. 156-187; Jul. 16, 1998.

Heikkila et al.; A four-step camera calibration procedure with implicit image correction; *Proceedings IEEE Computer Society Conference on Computer Vision and Pattern Recognition*; San Juan; pp. 1106-1112; Jun. 17-19, 1997.

Hendee et al.; *Medical Imaging Physics*; Wiley-Liss, Inc. 4th Edition; Chap. 19-22; pp. 303-353; (year of pub. sufficiently earlier than effective US filing date and any foreign priority date) © 2002.

Hsu et al.; Real-time freehand 3D ultrasound calibration; CUED/F-INFENG/TR 565; Department of Engineering, University of Cambridge, United Kingdom; 14 pages; Sep. 2006.

Jeffs; *Beamforming: a brief introduction*; Brigham Young University; 14 pages; retrieved from the internet (<http://ens.ewi.tudelft.nl/Education/courses/et4235/Beamforming.pdf>); Oct. 2004.

Khamene et al.; A novel phantom-less spatial and temporal ultrasound calibration method; *Medical Image Computing and Computer-Assisted Intervention—MICCAI (Proceedings 8th Int. Conf.)*; Springer Berlin Heidelberg; Palm Springs, CA; pp. 65-72; Oct. 26-29, 2005.

Kramb et al.; Considerations for using phased array ultrasonics in a fully automated inspection system. *Review of Quantitative Non-destructive Evaluation*, vol. 23, ed. D. O. Thompson and D. E. Chimenti, pp. 817-825, (year of publication is sufficiently earlier than the effective U.S. filing date and any foreign priority date) 2004.

Ledesma-Carbayo et al.; Spatio-temporal nonrigid registration for ultrasound cardiac motion estimation; *IEEE Trans. on Medical Imaging*; vol. 24; No. 9; Sep. 2005.

Leotta et al.; Quantitative three-dimensional echocardiography by rapid imaging . . . ; *J American Society of Echocardiography*; vol. 10; No. 8; pp. 830-839; Oct. 1997.

Li et al.; An efficient speckle tracking algorithm for ultrasonic imaging; 24; pp. 215-228; Oct. 1, 2002.

Morrison et al.; A probabilistic neural network based image segmentation network for magnetic resonance images; *Proc. Conf. Neural Networks*; Baltimore, MD; vol. 3; pp. 60-65; Jun. 1992.

Nadkarni et al.; Cardiac motion synchronization for 3D cardiac ultrasound imaging; Ph.D. Dissertation, University of Western Ontario; Jun. 2002.

Opretzka et al.; A high-frequency ultrasound imaging system combining limited-angle spatial compounding and model-based synthetic aperture focusing; *IEEE Transactions on Ultrasonics, Ferroelectrics and Frequency Control*, IEEE, US; 58(7); pp. 1355-1365; Jul. 2, 2011.

Press et al.; Cubic spline interpolation; §3.3 in "Numerical Recipes in FORTRAN: The Art of Scientific Computing", 2nd Ed.; Cambridge, England; Cambridge University Press; pp. 107-110; Sep. 1992.

Sakas et al.; Preprocessing and volume rendering of 3D ultrasonic data; *IEEE Computer Graphics and Applications*; pp. 47-54, Jul. 1995.

Sapia et al.; Deconvolution of ultrasonic waveforms using an adaptive wiener filter; *Review of Progress in Quantitative Nondestructive Evaluation*; vol. 13A; Plenum Press; pp. 855-862; (year of publication is sufficiently earlier than the effective U.S. filing date and any foreign priority date) 1994.

Sapia et al.; Ultrasound image deconvolution using adaptive inverse filtering; 12 IEEE Symposium on Computer-Based Medical Systems, CBMS, pp. 248-253; Jun. 1999.

Sapia, Mark Angelo; Multi-dimensional deconvolution of optical microscope and ultrasound imaging using adaptive least-mean-square (LMS) inverse filtering; Ph.D. Dissertation; University of Connecticut; Jan. 2000.

Slavine et al.; Construction, calibration and evaluation of a tissue phantom with reproducible optical properties for investigations in light emission tomography; *Engineering in Medicine and Biology Workshop*; Dallas, TX; IEEE pp. 122-125; Nov. 11-12, 2007.

Smith et al.; High-speed ultrasound volumetric imaging system. 1. Transducer design and beam steering; *IEEE Trans. Ultrason., Ferroelect., Freq. Contr.*; vol. 38; pp. 100-108; Mar. 1991.


Specht et al.; Deconvolution techniques for digital longitudinal tomography; *SPIE*; vol. 454; presented at Application of Optical Instrumentation in Medicine XII; pp. 319-325; Jun. 1984.

(56)

References Cited**OTHER PUBLICATIONS**

- Specht et al.; Experience with adaptive PNN and adaptive GRNN; Proc. IEEE International Joint Conf. on Neural Networks; vol. 2; pp. 1203-1208; Orlando, FL; Jun. 1994.
- Specht, D.F.; A general regression neural network; IEEE Trans. on Neural Networks; vol. 2.; No. 6; Nov. 1991.
- Specht, D.F.; Blind deconvolution of motion blur using LMS inverse filtering; Lockheed Independent Research (unpublished); Jun. 23, 1975.
- Specht, D.F.; Enhancements to probabilistic neural networks; Proc. IEEE International Joint Conf. on Neural Networks; Baltimore, MD; Jun. 1992.
- Specht, D.F.; GRNN with double clustering; Proc. IEEE International Joint Conf. Neural Networks; Vancouver, Canada; Jul. 16-21, 2006.
- Specht, D.F.; Probabilistic neural networks; Pergamon Press; Neural Networks; vol. 3; pp. 109-118; Feb. 1990.
- UCLA Academic Technology; SPSS learning module: How can I analyze a subset of my data; 6 pages; retrieved from the internet (http://www.ats.ucla.edu/stat/spss/modules/subset_analyze.htm) Nov. 26, 2001.
- Urban et al; Implementation of vibro-acoustography on a clinical ultrasound system; IEEE Transactions on Ultrasonics, Ferroelectrics, and Frequency Control; 58(6); pp. 1169-1181 (Author Manuscript, 25 pgs.); Jun. 2011.
- Urban et al; Implementation of vibro-acoustography on a clinical ultrasound system; IEEE Ultrasonics Symposium (IUS); pp. 326-329; Oct. 14, 2010.
- Von Ramm et al.; High-speed ultrasound volumetric imaging-System. 2. Parallel processing and image display; IEEE Trans. Ultrason., Ferroelect., Freq. Contr.; vol. 38; pp. 109-115; Mar. 1991.
- Wang et al.; Photoacoustic tomography of biological tissues with high cross-section resolution: reconstruction and experiment; Medical Physics; 29(12); pp. 2799-2805; Dec. 2002.
- Wells, P.N.T.; Biomedical ultrasonics; Academic Press; London, New York, San Francisco; pp. 124-125; Mar. 1977.
- Widrow et al.; Adaptive signal processing; Prentice-Hall; Englewood Cliffs, NJ; pp. 99-116; Mar. 1985.
- Wikipedia; Point cloud; 2 pages; retrieved Nov. 24, 2014 from the internet (https://en.wikipedia.org/w/index.php?title=Point_cloud&oldid=472583138).
- Wikipedia; Curve fitting; 5 pages; retrieved from the Internet (http://en.wikipedia.org/wiki/Curve_fitting) Dec. 19, 2010.
- Wikipedia; Speed of sound; 17 pages; retrieved from the internet (http://en.wikipedia.org/wiki/Speed_of_sound) Feb. 15, 2011.
- Yang et al.; Time-of-arrival calibration for improving the microwave breast cancer imaging; 2011 IEEE Topical Conf. on Biomedical Wireless Technologies, Networks, and sensing Systems (BioWireless); Phoenix, AZ; pp. 67-70; Jan. 16-19, 2011.
- Brewer et al.; U.S. Appl. No. 15/005,866 entitled "M-mode ultrasound imaging of arbitrary paths," filed Jan. 25, 2016.
- Belevich et al.; U.S. Appl. No. 15/400,826 entitled "Calibration of multiple aperture ultrasound probes," filed Jan. 6, 2017.
- Davies et al.; U.S. Appl. No. 15/418,534 entitled "Ultrasound imaging with sparse array probes," filed Jan. 27, 2017.
- Call et al.; U.S. Appl. No. 15/500,933 entitled "Network-based ultrasound imaging system," filed Feb. 1, 2017.
- Specht; U.S. Appl. No. 15/240,884 entitled "Method and apparatus to produce ultrasonic images using multiple apertures," filed Aug. 18, 2016.
- Specht et al.; U.S. Appl. No. 15/155,908 entitled "Determining material stiffness using multiple aperture ultrasound," filed May 16, 2016.

* cited by examiner










Fig. 3








Fig. 6




Fig. 6A




Fig. 6B




Fig. 6C




Fig. 7A




Fig. 7B




Fig. 7C

Fig. 8A




Fig. 8B




Fig. 8C




Fig. 9A




Fig. 9B




Fig. 9C








Fig. 9D







Phantom End View

Fig. 12




Fig. 13A




Fig. 13B




Fig. 13C




Fig. 14A




Fig. 14B





Fig. 14C









Fig. 17

**Fig. 18A**





**Fig. 18B**

Fig. 19A**Fig. 19B**



Assembled test fixture in tank.

Fig. 21A





Fig. 21B



First reference is LC or RC

Final reference is center of center probe (cc)


**Fig. 21C**


Fig. 22

Fig. 23B




Fig. 23C




Fig. 23D




Fig. 24





Fig. 25





Fig. 27A






Fig. 27B














Fig. 29B











Fig. 33A




Fig. 33B








Fig. 34A**Fig. 34B**

CALIBRATION OF ULTRASOUND PROBES**CROSS REFERENCE TO RELATED APPLICATIONS**

This is a continuation of U.S. patent application Ser. No. 13/279,110, filed Oct. 21, 2011, which is a continuation-in-part of U.S. patent application Ser. No. 12/760,327, filed Apr. 14, 2010, now U.S. Pat. No. 8,473,239, which claims the benefit of U.S. Provisional Patent Application No. 61/169,200, filed Apr. 14, 2009, titled "Alignment and Fixturing of the Universal Multiple Aperture Medical Ultrasound Transducer". All of the above referenced patents and applications are incorporated herein by reference in their entireties.

This application is relevant to Applicant's co-owned patent applications including U.S. patent application Ser. No. 12/760,375, filed Apr. 14, 2010, titled "Universal Multiple Aperture Medical Ultrasound Probe", published Oct. 14, 2010 as U.S. Patent Publication No. 2010-0262013, and U.S. Provisional Patent Application No. 61/392,896, filed Oct. 13, 2010, titled "Multiple Aperture Medical Ultrasound Transducers." All of the above referenced patents and applications are incorporated herein by reference in their entireties.

INCORPORATION BY REFERENCE

Unless otherwise specified herein, all patents, publications and patent applications mentioned in this specification are herein incorporated by reference to the same extent as if each individual publication or patent application was specifically and individually indicated to be incorporated by reference.

FIELD

The present invention relates generally to imaging techniques, and more particularly to ultrasound imaging, and still more particularly to systems and methods for calibration and quality assurance measurement of ultrasound probes, particularly probes having multiple apertures.

BACKGROUND

In conventional ultrasonic imaging, a focused beam of ultrasound energy is transmitted into body tissues to be examined and the returned echoes are detected and plotted to form an image. While ultrasound has been used extensively for diagnostic purposes, conventional ultrasound has been greatly limited by depth of scanning, speckle noise, poor lateral resolution, obscured tissues and other such problems.

Significant improvements have been made in the field of ultrasound imaging with the creation of multiple aperture imaging, examples of which are shown and described in Applicant's U.S. Pat. No. 8,007,439 issued Aug. 30, 2011 and titled "Method and Apparatus to Produce Ultrasonic Images Using Multiple Apertures"; U.S. Pat. No. 9,146,313 issued Sep. 29, 2015, titled "Point Source Transmission and Speed-Of-Sound Correction Using Multiple-Aperture Ultrasound Imaging"; and U.S. patent application Ser. No. 12/760,375, filed Apr. 14, 2010, titled "Universal Multiple Aperture Medical Ultrasound Probe," all three of which are incorporated herein by reference. Multiple aperture imaging methods and systems allow for ultrasound signals to be both transmitted and received from separate apertures.

One problem with multiple aperture imaging is that it can be difficult to know the exact position of the elements of a large apparatus with multiple and separate physical points of contact ("footprints") on the patient. It is desirable for each element position to be known to within $\frac{1}{10}$ wavelength (for example, 0.03 mm at 3 MHz). In contrast, with conventional ultrasound probes, regardless of array vertical displacement or integration (e.g., 1.5D or 2D), there has never been a need to solve alignment and position issues between multiple arrays or multiple individual elements. The calibration methods and apparatuses described herein teach how to solve these problems for Universal Multiple Aperture ultrasound probes.

SUMMARY

In general, in one aspect, a method of calibrating an ultrasound probe includes mounting an ultrasound probe onto a calibration system, transmitting an ultrasound test signal from an element of the probe through a test medium of the calibration system, receiving the test signal at a first hydrophone of the calibration system at a first time; receiving the test signal at a second hydrophone of the calibration system at a second time, receiving the test signal at a third hydrophone of the calibration system at a third time, and determining an acoustic position of the element based upon differences in the first time, the second time, and the third time.

This and other embodiments may include one or more of the following features.

The elements can be part of an array having a plurality of elements, and the method can further include repeating the transmitting, receiving, and determining steps for at least one additional element in the array. The transmitting, receiving, and determining steps can be performed for every element in the array. The transmitting, receiving, and determining steps can be performed for less than all of the elements in the array, and the method can further include interpolating acoustic positions of all remaining elements. The probe can include a plurality of distinct arrays, and the transmitting, receiving, and determining steps can be performed for at least two elements in each array. The plurality of arrays can be separated by physical space. At least one array can be non-planar with respect to another array.

The first, second, and third hydrophones can be part of a first line of hydrophones and fourth, fifth, and sixth hydrophones can be part of a second line that is parallel to the first line, and the method can further include receiving the test signal on all six hydrophones and determining an x, y, and z position of the element based on differences of arrival times at each hydrophone. Further, there can be a third line of two or more hydrophones that is transverse to the first and second lines, and the method can further include computing the angle of transmission of the element based upon the position of maximum levels of energy received on any of the hydrophones.

The method can further include storing the determined position of the element in a memory chip on the probe. The method can further include overwriting position data stored in a memory chip with the determined position.

The method can further include establishing a tank coordinate system relative to the first, second, or third hydrophone. The method can further include determining a position of every element of the probe relative to the tank coordinate system. The method can further include establishing a probe coordinate system relative to an element of the probe. The method can further include rotating or

translating all of the determined positions to the probe coordinate system. The position can be determined relative to a Cartesian coordinate system.

The method can further include storing the determined position in memory and retrieving the stored position during imaging or image processing.

The method can further include transmitting an ultrasound test signal from a fourth hydrophone to the first, second, or third hydrophone to verify the operation of the first, second, or third hydrophone.

In general, in one aspect, a method of determining functionality of an ultrasound probe can include mounting an ultrasound probe onto a calibration system, transmitting an ultrasound signal between a hydrophone of the calibration system and an element of the probe, the transmitting occurring through test medium of the calibration system; and determining an acoustic performance of the element.

This and other embodiments can include one or more of the following features.

The test signal can be transmitted from the hydrophone and received by the element. The test signal can be transmitted from the element and received by the hydrophone.

The element can be part of an array having a plurality of elements, and the method can further include repeating the transmitting, receiving, and determining steps for at least one additional element in the array. The probe can include a plurality of distinct arrays, and the transmitting, receiving, and determining steps can be performed for at least one element of each array.

The test signal can be transmitted by the first, second, or third hydrophone and received by a fourth hydrophone to verify signal performance.

The determined acoustic performance can be stored and transmitted electronically to report probe performance to service providers and end users.

In general, in one aspect, a system for calibrating an ultrasound probe includes a tank substantially filled with a test medium, a dock attached to the tank, and a plurality of hydrophones. The dock is configured to hold an ultrasound probe. The plurality of hydrophones are arranged in a matrix along a wall of the tank opposite the dock.

This and other embodiments can include one or more of the following features.

The system can further include a controller configured to send an ultrasound signal from an element of the probe through the test medium to first, second, and third hydrophones of the plurality of hydrophones, and the controller can be further configured to determine an acoustic position of the element based upon differences in times that the signal is received at the first, second, and third hydrophones.

The system can further include the probe, and the probe can include at least two arrays separated by a physical space, and the dock can be configured so as to hold at least one of the arrays at a non-orthogonal angle with respect to the hydrophone matrix. The probe can include a calibration memory chip configured to store data obtained by the calibration system.

The dock can be configured to conform to the ultrasound probe shape. The dock can be configured such that, when the probe is positioned in the dock, the probe is directly adjacent to the test medium. The material of the dock can have substantially the same speed of sound as the test medium.

The matrix can include a first row of hydrophones, a second row of hydrophones parallel to the first row of hydrophones, and a third row of hydrophones transverse to the first and second rows.

The system can further include a calibrator hydrophone located on a wall of the tank separate from the wall along which the plurality of hydrophone receivers are arranged.

BRIEF DESCRIPTION OF THE FIGURES

FIG. 1 illustrates a two-aperture system.

FIG. 2 illustrates a three-aperture system.

FIG. 3 is a schematic diagram showing a possible fixture for positioning an omni-directional probe relative to the main probe.

FIG. 4 is a schematic diagram showing a non-instrumented linkage for two probes.

FIG. 5 is a block diagram of the transmit and receive functions where a three array Multiple Aperture Ultrasound Transducer and the associated MAUI electronics are used in conjunction with a host ultrasound machine. In this embodiment, the center probe is used for transmit only and mimics the normal operation of the host transmit probe.

FIG. 5A is a block diagram of the transmit and receive functions where a two array Multiple Aperture Ultrasound Transducer and the associated MAUI electronics are used as an add-on to a host ultrasound machine, primarily for cardiac applications, with an add-on instrument. In this case, one probe is used for transmit only and mimics the normal operation of the host transmit probe, while the other probe operates only as a receiver.

FIG. 6 is a block diagram of the transmit and receive functions where a Multiple Aperture Ultrasound Transducer is used in conjunction with only a Multiple Aperture Ultrasonic Imaging (MAUI) device. The stand-alone MAUI electronics control all elements on all apertures. Any element may be used as a transmitter or omni-receiver, or grouped into transmit and receive full apertures or even sub-arrays. In this figure the insonification emanates from the central aperture, aperture 2 of 3 apertures.

FIG. 6A depicts the insonification emanating from other than center aperture, in this figure Aperture 3 of 3.

FIG. 6B is an illustration of two apertures being used a Multiple Aperture Ultrasound Transducer is used in conjunction with only a Multiple Aperture Ultrasonic Imaging (MAUI) device. In this figure the insonification emanates from aperture 2 of 2.

FIG. 6C is an illustration of two apertures being used a Multiple Aperture Ultrasound Transducer is used in conjunction with only a Multiple Aperture Ultrasonic Imaging (MAUI) device. In this figure the insonification emanates from aperture 1 of 2.

FIG. 7A is a top view of the precision array carrier with six adjustment screws and an array installed.

FIG. 7B is a side view showing the longitudinal axis adjustment of an array in the precision array carrier being supported by the array-centering gasket.

FIG. 7C is an end view showing the transverse axis adjustment of the array in the precision array carrier being supported by the array-centering gasket.

FIG. 8A is a top view of the precision array carrier.

FIG. 8B is a side (longitudinal) view of the precision array carrier.

FIG. 8C is an end (lateral) view of the precision array carrier.

FIG. 9A is a top view of the precision array carrier with a centering gasket in place.

FIG. 9B is a side view (longitudinal) of the precision array carrier with a centering gasket in place.

FIG. 9C is an end view (lateral) of the precision array carrier with a centering gasket in place.

FIG. 9D is a bottom view of the precision array carrier with a centering gasket in place.

FIG. 10A is a top view of the array in the precision array carrier during a counter-clockwise rotational axis adjustment.

FIG. 10B is a top view of the array in the precision array carrier during a clockwise rotational axis adjustment.

FIG. 11 shows an end view of a precision array carrier **2150** installed on a tissue equivalent phantom **2182** and ready to transmit and receive during alignment.

FIG. 12 shows a side view of the phantom **2182** with the ends of the targets **2167** visible.

FIG. 13A is a top view of a carrier assembly with arrays installed (to become a precision carrier array assembly) and aligned within a precision transducer receptacle and stabilized with an acoustic damping material.

FIG. 13B is a side view of a precision array carrier with arrays installed (to become a precision carrier array assembly) and aligned within a precision transducer receptacle and stabilized with an acoustic damping material.

FIG. 13C is an end view of a precision carrier array with arrays installed (to become a precision carrier array assembly) and aligned within a precision transducer receptacle and stabilized with an acoustic damping material.

FIG. 14A is a top view of a precision carrier array with arrays installed and aligned within a precision transducer head receptacle, the acoustic damping material has set and alignment screws have been removed.

FIG. 14B is a side view of a precision carrier array assembly with arrays installed and aligned within a precision transducer head receptacle, the acoustic damping material has set and alignment screws have been removed.

FIG. 14C is an end view of a precision carrier array with arrays installed and aligned within a precision transducer head receptacle, the acoustic damping material has set and alignment screws have been removed.

FIG. 15 shows a precision transducer receptacle or nose piece and three precision carrier array assemblies seated atop the transducer guides.

FIG. 16 shows the precision transducer receptacle or nose piece and three precision carrier array assemblies as in FIG. 22, and an ultrasound transducer array seated in each transducer guide of the nose piece.

FIG. 17 is a drawing using three independent probes and their installed arrays or transducers. This illustration represents the positional nomenclature and array element numbering conventions.

FIG. 18A shows the Precision Stage Assembly and sections that control movement in three different axes.

FIG. 18B shows the controls for the Precision Stage Assembly.

FIG. 19A depicts an enclosure containing Right and Left Axial Hydrophones and a Transverse Hydrophone.

FIG. 19B depicts the dual Axial Hydrophones from the side and illustrates the angular orientation of the Transverse Hydrophone.

FIG. 20 is a representation of probes attached to the precision stage assemblies on top of a fluid filled tank, and well above the hydrophone assembly.

FIG. 21A is a graphic of basic geometry used to begin the conversion of distance difference into total distance.

FIG. 21B is a graphic of the detailed geometry used to begin the conversion of distance difference into total distance allowing for the precision location of array element using three hydrophones.

FIG. 21C is a graphic of geometry used to compute the z position of an element.

FIG. 22 illustrates a nose piece containing three separate arrays after it is installed into a Multiple Aperture Transducer. This figure includes the transducer specific calibration chip, the transmit synchronization module and probe position displacement sensor.

FIG. 23A is a representation of the graphical user interface or GUI developed to allow for the precise location of elements of multiple arrays under test.

FIG. 23B depicts an array of elements under test with the ultrasound beam in the center of the transverse hydrophone, centered between the left and right hydrophones with the results displayed on the graphical user interface.

FIG. 23C is a representation of an array under test where its beam is on center but with the array to the right of center with the results displayed on the graphical user interface.

FIG. 23D is a representation of an array under test that is physically on the center axis, but has its beam to the left of center with the results displayed on the graphical user interface.

FIG. 24 is a representation of the automatic precision stage assembly and its major components.

FIG. 25 is a representation using three arrays and three precision alignment stage assemblies showing their physical placement during testing.

FIG. 26A is an illustration of an Onboard Calibration and Quality Assurance fixture mounted to the side of the MAUI standalone system. This illustration depicts a MAUI Radiology probe being evaluated.

FIG. 26B illustrates the Onboard Calibration and Quality Assurance fixture evaluating a MAUI Cardiac probe.

FIG. 27A is a perspective view illustrating an embodiment of a calibration system attached to a multiple aperture ultrasound imaging (MAUI) control panel.

FIG. 27B illustrates an embodiment of a calibration system built into a MAUI electronics control panel.

FIG. 28 represents a side section view of a calibration system.

FIG. 29A illustrates a multiple aperture probe containing three separate arrays. This figure includes a transducer specific calibration chip mounted within the probe handle.

FIG. 29B illustrates an embodiment of a curvilinear multiple aperture ultrasound imaging probe.

FIG. 30A is a bottom view of a 1D or 1.5D ultrasound transducer array.

FIG. 30B is a perspective view of a single 1D or 1.5D ultrasound transducer element with a longitudinal geometric centerline shown.

FIG. 30C is a bottom view of a 2D matrix ultrasound transducer array.

FIG. 30D is a bottom view of a CMUT ultrasound transducer array.

FIG. 31 illustrates an embodiment of a calibration system with an adjustable clasp retaining one embodiment of a MAUI probe in a docking site which may contain a coupling gel.

FIG. 32A shows the top view of an embodiment of a calibration system containing a removable docking site which contains multiple docking forms for various shapes and types of probes.

FIG. 32B shows a side view illustrating an embodiment of a calibration system containing a removable docking site having three different docking forms for receiving ultrasound probes.

FIG. 33A shows a side section view of an embodiment of a calibration system with a removable docking site with a single docking form for receiving an ultrasound probe.

FIG. 33B is a section view illustrating three embodiments of docking forms for curvilinear, linear and trans-esophageal ultrasound probes.

FIG. 34A is a plan view illustration of one embodiment of a hydrophone matrix which may be located at a bottom of a calibration system.

FIG. 34B a side view of the hydrophone matrix of FIG. 34A.

DETAILED DESCRIPTION

The following disclosure provides embodiments of calibration systems and related operation methods for calibrating ultrasound imaging probes, and particularly multiple aperture ultrasound imaging (MAUI) probes. Embodiments herein also provide systems and methods for operating such a calibration system for various purposes relating to quality assurance of the probes.

In some embodiments, a calibrating system may be configured to identify the location of each and every individual element in an ultrasound probe to a high degree of accuracy and precision. In probes having multiple arrays of transducer elements, a calibration system may be configured to identify the location and/or orientation of individual arrays. In other embodiments, a calibration system may be configured to identify the location of only selected elements of one or more arrays. In some embodiments, the location of elements and/or arrays may be determined in a three dimensional space such as a given X, Y, and Z coordinate system. In other embodiments, the location of elements and/or arrays may be determined in only two dimensions, such as an X, Y coordinate system which may correspond to an imaging plane of the probe.

As used herein, references to the “exact” or “precise” position of transducer elements (and similar terms) may imply a relatively tight tolerance. For example, in some embodiments ultrasound probe calibration systems and methods may provide information describing the acoustic position of each transducer element in an array to within a distance of a fraction of a wavelength of ultrasound being used. In some embodiments, the acoustic position of transducer elements may be determined to within $\frac{1}{10}$ of a wavelength. In other embodiments, the acoustic position of transducer elements may be determined to within a tolerance of less than $\frac{1}{10}$ of a wavelength. In some embodiments, such as for calibrating a standard (i.e., single aperture) ultrasound probe, much looser tolerances may also be used, provided that such tolerances meet the needs of a particular system.

The simplest multi-aperture system consists of two apertures, as shown in FIG. 1. One aperture could be used entirely for transmit elements 110 and the other for receive elements 120. Transmit elements can be interspersed with receive elements, or some elements could be used both for transmit and receive. In this example, the probes have two different lines of sight to the tissue to be imaged 130. That is, they maintain two separate physical apertures on the surface of the skin 140. Multiple Aperture Ultrasonic Transducers are not limited to use from the surface of the skin, they can be used anywhere in or on the body to include intracavity and intravenous probes. In transmit/receive probe 110, the positions of the individual elements T_{x1} through T_{xn} can be measure in three different axes. This illustration shows the probe perpendicular to the x axis 150, so each element would have a different position x and the same position y on the y axis 160. However, the y axis positions of elements in probe 120 would be different since

it is angled down. The z axis 170 comes in or out of the page and is very significant in determine whether an element is in or out of the scan plane.

Referring to FIG. 1, suppose that a Transmit Probe containing ultrasound transmitting elements $T1, T2, \dots Tn$ 110 and a Receive Probe 120 containing ultrasound receive elements $R1, R2, \dots Rm$ are placed on the surface of a body to be examined (such as a human or animal). Both probes can be sensitive to the same plane of scan, and the mechanical position of each element of each probe is known precisely relative to a common reference such as one of the probes. In one embodiment, an ultrasound image can be produced by insonifying the entire region to be imaged (e.g., a plane through the heart, organ, tumor, or other portion of the body) with a transmitting element (e.g., transmit element T_{x1}), and then “walking” down the elements on the Transmit probe (e.g., T_{x2}, T_{xn}) and insonifying the region to be imaged with each of the transmit elements. Individually, the images taken from each transmit element may not be sufficient to provide a high resolution image, but the combination of all the images can provide a high resolution image of the region to be imaged. Then, for a scanning point represented by coordinates (i,j), it is a simple matter to calculate the total distance “a” from a particular transmit element T_{xn} to an element of tissue 130 plus the distance “b” from the tissue 130 to a particular receive element. With this information, one could begin rendering a map of scatter positions and amplitudes by tracing the echo amplitude to all of the points for the given locus.

Another multi-aperture system is shown FIG. 2 and consists of transducer elements in three apertures. In one concept, elements in the center aperture 210 can be used for transmitting and then elements in the left 220 and right 230 apertures can be used for receiving. Another possibility is that elements in all three apertures can be used for both transmitting and receiving, although the compensation for speed of sound variation would be more complicated under these conditions. Positioning elements or arrays around the tissue 240 to be imaged provides much more data than simply having a single probe 210 over the top of the tissue.

The Multiple Aperture Ultrasonic Imaging methods described herein are dependent on a probe apparatus that allows the position of every element to be known and reports those positions to any new apparatus the probe becomes attached. FIGS. 3 and 4 demonstrate how a single omni-probe 310 or 410 can be attached to a main transducer (phased array or otherwise) so as to collect data, or conversely, to act as a transmitter where the main probe then becomes a receiver. In both of these embodiments the omni-probe is already aligned within the scan plan. Therefore, only the x and y positions 350 need be calculated and transmitted to the processor. It is also possible to construct a probe with the omni-probe out of the scan plane for better transverse focus.

An aspect of the omni-probe apparatus includes returning echoes from a separate relatively non-directional receive transducer 310 and 410 located away from the insonifying probe transmit transducer 320 and 420, and the non-directional receive transducer can be placed in a different acoustic window from the insonifying probe. The omni-directional probe can be designed to be sensitive to a wide field of view for this purpose.

The echoes detected at the omni-probe may be digitized and stored separately. If the echoes detected at the omni-probe (310 in FIG. 3 and 410 in FIG. 4) are stored separately for every pulse from the insonifying transducer, it is surprising to note that the entire two-dimensional image can be

formed from the information received by the one omni. Additional copies of the image can be formed by additional omni-directional probes collecting data from the same set of insonifying pulses.

In FIG. 5, the entire probe, when assembled together, is used as an add-on device. It is connected to both an add-on instrument or MAUI Electronics 580 and to any host ultrasound system 540. The center array 510 can be used for transmit only. The outrigger arrays 520 and 530 can be used for receive only and are illustrated here on top of the skin line 550. Reflected energy off of scatterer 570 can therefore only be received by the outrigger arrays 520 and 530. The angulation of the outboard arrays 520 and 530 are illustrated as angles α_1 560 or α_2 565. These angles can be varied to achieve optimum beamforming for different depths or fields of view. α_1 and α_2 are often the same for outboard arrays, however, there is no requirement to do so. The MAUI Electronics can analyze the angles and accommodate asymmetrical configurations. FIG. 5A demonstrates the right transducer 510 being used to transmit, and the other transducer 520 is being used to receive.

FIG. 6 is much like FIG. 5, except the Multiple Aperture Ultrasound Imaging System (MAUI Electronics) 640 used with the probe is a stand-alone system with its own on-board transmitter (i.e., no host ultrasound system is used). This system may use any element on any transducer 610, 620, or 630 for transmit or receive. The angulation of the outboard arrays 610 and 630 is illustrated as angle α 660. This angle can be varied to achieve optimum beamforming for different depths or fields of view. The angle is often the same for outboard arrays; however, there is no requirement to do so. The MAUI Electronics will analyze the angle and accommodate asymmetrical configurations.

In this illustration, transmitted energy is coming from an element or small group of elements in Aperture 2 620 and reflected off of scatterer 670 to all other elements in all the apertures. Therefore, the total width 690 of the received energy is extends from the outermost element of Aperture 1 610 to the outmost element of Aperture 2 630. FIG. 6A shows the right array 610 transmitting, and all three arrays 610, 620 and 630 receiving. FIG. 6B shows elements on the left array 610 transmitting, and elements on the right array 620 receiving. Using one transducer for transmit only has advantages with regard to a lack of distortion due to variation in fat layer. In a standalone system, transmit and/or receive elements can be mixed in both or all three apertures.

FIG. 6b is much like FIG. 5A, except the Multiple Aperture Ultrasound Imaging System (MAUI Electronics) 640 used with the probe is a stand-alone system with its own on-board transmitter. This system may use any element on any array 610 or 620 for transmit or receive as is shown in FIG. 6C. As shown in either FIG. 6B or FIG. 6C, a transmitting array provides angle off from the target that adds to the collective aperture width 690 the same way two receive only transducers would contribute.

Some embodiments described herein include a precision carrier for the proper alignment of a universal multiple aperture ultrasound transducer. Referring to FIGS. 7A-7C, transducer array 2161 can be already "potted" in its own fixture 2161 with lens 2162 intact. Potting procedures are conventional methods to secure the transducer array to its lens and to the case. Flex circuitry, cabling, and attachment to the larger multiple aperture ultrasound transducer fixture can take place after the potting procedure is complete. A benefit of such embodiments is that they do not use the same transducers during the alignment. Different transducers with

different "pots" can be utilized in any location of the alignment fixture thanks to the flexibility of the alignment carrier.

FIGS. 8A-8C provide views of the basic structure and features of embodiments of a precision carrier 2150 for a multiple aperture ultrasound transducer array. FIG. 8A shows a top view of a precision array carrier 2150 with six positioning screws 2151. FIG. 8B shows a side view of a precision array carrier 2150 having two threaded screw holes 2180 on each side. When positioning screws 2151 are inserted into threaded screw holes (e.g., screw holes 2155 and 2156 in FIG. 7B), adjustments may be made to employ longitudinal corrections 2159 to the "seated" array. FIG. 8C shows a side view of a precision carrier 2150 with threaded screw holes 2180 located on each end. When positioning screws are inserted into these threaded screw holes, adjustments may be made to employ lateral corrections 2160 to the "seated" array (as illustrated in FIG. 7C).

FIGS. 9A-9D show a precision array carrier 2150 with an array-centering gasket 2152 installed. FIG. 9A is a top view of the precision carrier 2150, with an array-centering gasket 2152 placed at the bottom of the carrier where the lens 2162 located in the center. FIGS. 9B-9D show side, end, and bottom views of the carrier, respectively. The array centering gasket 2152 can be located on the carrier's L-shaped shoulder 2181, as illustrated in FIG. 9B. Further, as shown in FIG. 9B, the gasket 2152 can extend the entire length of the carrier over the L-shaped shoulder 2181. The gasket 2152 can extend around the corners of the L-shaped shoulder 2181 to cover the ends of the carrier as it illustrated in FIG. 9C. The gasket provides the array translational centering and a pivot point for positioning adjustments during operation without interfering with the integrity of the lens 2162. FIG. 9D provides a view of the lens 2162, the bottom of the precision carrier array centering gasket 2152, and finally the L-shaped shoulder 2181.

Referring back to FIGS. 7A-7C, which show top, end, and side views, respectively of a precision array carrier 2150 with an array 2161 inserted therein. The array 2161 is supported end-to-end by positioning screws 2155 and 2156. The array can be supported from each side by positioning screws 2153, 2154, 2157, 2158 and from the bottom by the array centering gasket 2152. FIG. 7B shows the array 2161 in the precision array carrier 2150 being supported by array centering gasket 2152 and ready for longitudinal adjustment. Alternately tightening and loosening positioning screws 2155 and 2156 allows the array 2161 to be adjusted through arc 2159 to correct longitudinal axis errors. FIG. 7C shows the array 2161 in the precision array carrier 2150 supported by the array centering gasket 2152 ready for transverse alignment. Alternately adjusting positioning screw pairs 2157, 2158 and 2153, 2154 allow the array 2161 to be corrected for transverse axis errors.

FIGS. 10A and 10B show a top views of a precision array carrier 2150 with the array 2161 inserted. Arrows depict, respectively, counter-clockwise and clockwise rotational adjusting by way of selective screw adjustments. FIG. 10A shows a tightening of position screws 2153 and 2158 while loosening position screws 2154 and 2157 shifting the array 2161 in a counter-clockwise arc 2165 to correct rotational axis errors. FIG. 10B shows a tightening position of screws 2154 and 2157 while loosening position screws 2153 and 2158 to shift the array 2161 in a clockwise arc 2166 to correct rotational axis errors.

FIG. 11 shows an end view of a precision array carrier 2150 installed on a tissue equivalent phantom or test block 2182 and ready to transmit and receive during alignment. A

'phantom' is a structure filled with tissue equivalent material that has a speed of sound characteristics similar to that of human tissue with known voids and reflectors placed at known locations within the phantom. This end view of the phantom shows one embodiment including three targets **2167** in profile view. These targets can be echogenic, very reflective, or anechoic, void of reflection. The top target can be at a pre-determined depth D from the surface of the phantom and the face of array carrier **2150**. The other targets can be spaced at distances D1 and D2 from the top target. In some embodiments, the pre-determined depth D can be 100 mm from the top target to the face of the array. The other targets can have D1 and D2 distances of 10 mm, for example. However, any range of depths for the targets **2167** can be used, depending on the desired application of the transducer arrays. The perpendicular targets **2167** serve to assist during the longitudinal adjustment of the array positioning. When correctly positioned, the three targets would be displayed as exactly perpendicular to the front of the array, and further, each target **2167** would be displayed equidistantly one a top the other.

FIG. 12 shows a side view of the phantom **2182** with the ends of the targets **2167** visible. Once transmitting and receiving, a lateral adjustment could be made to the array **2163** in the carrier **2150**. The correct alignment is for achieved when all targets are visible above and below the center target **2168**.

FIGS. 13A-13C show a precision array carrier **2150** with an array **2161** inserted and aligned, in top, side, and end views, respectively. At this stage an acoustic damping material **2162** can be poured into the gap between the array and the carrier to stabilize the position of arrays **2161**. FIG. 13B is a side view of the precision array carrier **2150** showing the gap between the array **2161** and the precision array carrier **2150** filled with acoustic damping material **2162**. FIG. 13C shows the gap between the array **2161** and the precision array carrier **2150** filled with acoustic damping material **2162**.

FIGS. 14A-14C show the precision array carrier **2150** with the array **2161** inserted and aligned in top, side, and end views, respectively. The acoustic damping material **2162** has cured and the six alignment screws have been removed. FIG. 14B is a side view of the precision array carrier **2150** with the array **2161** inserted, aligned, the acoustic damping material **2162** cured and the position alignment screws removed: At this point, the precision array carrier **2150** with its captured array becomes a precision carrier array assembly **2163**.

FIG. 15 shows a multi-aperture ultrasound probe assembly **2183** constructed with precision transducer receptacles surrounded by structural supports **2164**. The structural supports **2164** can be constructed out of many hard materials (e.g., metals or plastics) and usually are built into a larger structure such as the probe **2200** in FIG. 22. In FIG. 15, the three precision carrier array assemblies **2163** are inserted into the precision transducer receptacles **2166**.

FIG. 16 shows the multi-aperture probe assembly **2183** having precision transducer receptacles **2166** with the precision array assemblies **2163** each locked into the receptacles, thus completing the construction of the multi-aperture ultrasound probe **2184** having three transducer arrays.

FIG. 22 shows a completed probe **2200** with arrays **1701**, **1702**, and **1703** fitted in array receptacles and ready for submission to the calibration cycle.

Alternative apparatus and methods for constructing and aligning multi-aperture ultrasound probes will now be discussed. Variations in the ultrasound beam displacement or

rotation of both the insonifying and receiving probes about the x, y and z axes are preferably detected and corrected to achieve the best image quality. A MAUI alignment fixture for aligning a multi-aperture probe uses one or more precision angular alignment controls, precision stage assemblies that provide for the adjustment, in 6 degrees of freedom of the each array under test.

One factor in making multi-aperture imaging systems is the importance of precisely aligning the elements of the multiple arrays. It is well recognized that by increasing the effective aperture of a probe system by including more than one probe head and using the elements of all of the probes to render an image, the lateral resolution of the image can be greatly improved. In order to render an image, the relative positions of all of the elements are preferably known precisely. In some embodiments, if the probe system has position and rotation adjustments, a display is provided to position all of the elements to be in the same plane of scan and to transmit or receive in the same plane of scan.

FIG. 17 shows a probe system **1700** comprising three probes **1701**, **1702**, and **1703** working together as a multi-aperture transducer though not assembled in a single shell. This is not a standard embodiment of a multiple aperture transducer, but serves here to aid in describing arrays alignment. A multi-aperture transducer can comprise of any number of arrays **1710**, **1720**, **1730** (two or more), or even individual elements. For practical reasons, arrays in probes can easily be manufactured with a large number of elements and element spacing within a head can be well controlled. If one can precisely position the end elements of each probe, it is possible to imply the positions of the other elements. Therefore, a fixture will be described which finds the positions of the elements. This apparatus could determine the exact location of independent elements either inside or outside of an array; however, because arrays are typically constructed in a linear format, the embodiment discussed here only identifies the end elements.

In FIG. 17 these end elements are designated as element numbers **0** through **5**, where **0** and **1** are the end elements of array **1710**, **2** and **3** are the end elements of arrays **1720** and **4** and **5** are the end elements of array **1730**. Any of the intermediate elements could be located in the same way as will be described.

A precision alignment stage assembly is shown in FIG. 18A. The far left area of the assembly **1801** allows for the mechanical connection of a single probe, such as **1701** from FIG. 17. The precision alignment stage assembly has three separate mechanisms **1801**, **1802** and **1803** that control the position of the attached array in x, y and z axes. Several alignment stage assemblies can be used in concert so that multiple probe arrays can be manipulated independently. FIG. 18B allows the operator to manipulate an array in any axis by using controls **1805**, **1806**, **1807**, **1808**, and bearing **1809**. Precision screws **1804**, **1805**, **1806**, **1807**, and **1808** can be adjusted, and bearing **1809** can be rotated to affect one or more axes for the array during the alignment process.

FIG. 25 shows the arrays **1710**, **1720** and **1730** attached in line to precision alignment stages **2510**, **2520** and **2530**. With the arrays set in place, they can now transmit to common points of interest and compare their points of impact with the other arrays.

As used herein, calibration of an ultrasound probe may involve determining the acoustic position of each individual ultrasound element in a probe with a desired degree of precision relative to some known coordinate system. The

basic technique for aligning and calibrating a multiple aperture probe can be seen with reference to FIGS. 19A, 19 and 20.

FIG. 20 illustrates probes 1701, 1702 and 1703 from FIG. 17 now attached to alignment stage assemblies above a tank or test block 2012. The tank can be filled with any liquid, fluid, gel, solid, or other medium 2014 that is desirable for manufacture and safety considerations, as long as the speed of sound for the fluid is known. The tank can include a mounting location for the alignment stage assemblies. In some embodiments, as shown in FIG. 20, multiple alignment stage assemblies holding transducer elements can be mounted on the test block. From this position, it is possible to transmit ultrasonic pulses from the elements of any of the arrays to be received by ultrasonic sensor or hydrophones 2085 at the other end of the tank 2012.

As used herein, the term "hydrophone" is used in a generic sense and refers to any instrument capable of accurately receiving and transducing ultrasound waves into electronic signals. In some embodiments, hydrophones may also be used to transmit ultrasound signals. Thus, in some embodiments, hydrophones may comprise piezoelectric transducer arrays, or any other suitable technology. The term "hydrophone" is generally used herein to refer to ultrasound receiving and/or transmitting instruments attached to a calibration system, as distinct from the transducer elements and arrays of ultrasound imaging probes to be calibrated.

As shown in FIGS. 19A-19B, the hydrophone 2085 can be a multi-axis ultrasonic hydrophone 2085 configured to detect the X, Y and Z positions of each element of a single array or multiple arrays under test. The multi-axis hydrophone 2085 can include a transverse hydrophone 2086, and right and left hydrophones 2087 and 2088. The common targets for the probes 1701, 1702 and 1703 to shoot at are elements 2091, 2092 and 2093 on the right hydrophone 2087. On the left hydrophone 2088, elements 2094, 2095, and 2096 are the targets.

In use, the probe can be attached to a signal generator configured to excite any of the transducer elements to transmit ultrasonic pulses. An ultrasonic signal is transmitted which exhibits good autocorrelation properties (e.g., a long frequency sweep, or 'chirp' waveform, a short (wide-band) pulse, a spread spectrum waveform, etc) from at least one element in arrays 1710, 1720 and 1730. The transmitted ultrasound signal can travel through the test block and be received by the receiving hydrophone transducer elements 2091, 2092, 2093, 2094, 2095, 2096 and the transverse hydrophone 2086. It is important to note that detection of the ultrasonic signal or pulse as received by the hydrophone arrays cannot be detected accurately enough by cross correlation with the signal impressed on the probe element because the probe element itself distorts the signal.

Two innovative techniques are used to obtain the needed accuracy in finding the relative time delays and hence the relative distances. The first technique is to use cross correlation between the signal received at one element of the hydrophone (for example 2091) and the signal received at another element of the same hydrophone (for example 2093). The correlation peak will yield the time difference and thus the distance difference.

The second technique is to interpolate between samples of the received waveforms to obtain better time resolution than simply the sampling interval. Perhaps the best way to accomplish both of these tasks is to take the Fourier transform of both signals, fill in zeros for the high frequency components of a much larger transform. Call these larger

transforms FFT 1 and FFT 2. Then find the peak of the inverse transform of (FFT 1*(conjugate of FFT 2)).

A third technique may be used to convert differential distances to total distance. Consider the triangle bce in FIG. 21A where the point b represents one of the elements for which we need to compute a position, and c and e are known reference points in the bottom of the water tank. The distance d_4 represents a total distance between the test element at point b and the hydrophone element at point c (840 or 870). Similarly, the distance d_0 represents a total distance between the test element at point b and the hydrophone element at point e (820 or 850). It is desired to measure the lengths d_4 and d_0 by triangulation, but just knowing the difference between d_0 and d_4 is not enough. By adding a transverse hydrophone (see 2086 in FIG. 19A) in the bottom of the tank we have two triangles from which we can compute d_0 and d_4 . Let e, d, and c be the locations of the hydrophones 2094, 2095 and 2096 or 2091, 2092 and 2093 of FIG. 19A.

For the following analysis, the hydrophones 2094, 2095 and 2096 are preferably on the same line and on a parallel line to that formed by 2091, 2092 and 2093. The distance between 2094 and 2095 is designated d and the distance between 2095 and 2096 is designated d_3 . d_1 and d_3 are preferably known precisely as this becomes the reference "yardstick" for the other measurements. 2095 should be roughly centered between 2094 and 2096 LN, but d does not need to equal d_3 . The same is true for R0, RC, and RN.

Let d be the reference distance and define measured distances as:

$$d_2m = d_2 - d_2 = 0$$

$$d_0m = d_0 - d_2$$

$$d_4m = d_4 - d_2$$

From the law of cosines we have

$$d_4^2 = d_2^2 + d_3^2 - 2d_3d_2 \cos \alpha$$

$$d_0^2 = d_2^2 + d_1^2 - 2d_1d_2 \cos(\pi - \alpha) = d_2^2 + d_1^2 + 2d_1d_2 \cos \alpha$$

$$\cos \alpha = (d_4^2 - d_2^2 - d_3^2) / (-2d_3d_2) = (d_0^2 - d_2^2 - d_1^2) / (2d_1d_2)$$

$$d_4^2 - d_2^2 - d_3^2 = -(d_0^2 - d_2^2 - d_1^2)d_3/d_1$$

$$(d_4m + d_2)^2 - d_2^2 - d_3^2 + (d_0m + d_2)^2 d_3/d_1 - d_2^2 d_3/d_1 d_3 = 0$$

Combining and canceling terms this becomes

$$d_2^2 = (-d_4m^2 + d_3^2 - d_0m^2 d_3/d_1 + d_1d_3) / (2d_4m + 2d_0md_3/d_1)$$

Then $d_0 = d_0m + d_2$ and $d_4 = d_4m + d_2$.

Thus we have the full measurements from received differential times.

Two parallel "yardsticks" or right and left hydrophones are provided in the bottom of the tank in order to measure position along the z axis (i.e., the axis perpendicular to the scan plane), as illustrated in FIG. 23B. It will be the goal to position all of the probe elements from all three arrays 1701, 1702 and 1703 in a line midway between the two yardsticks using the various controls illustrated in FIG. 18B.

Referring now to FIG. 21B, consider the measurement of the position of any probe element such as M0 1206. First, consider using the right yardstick R 0-RC-RN 2091, 2092, 2093. By transmitting a chirp signal from element M0 1206 and receiving it on hydrophones at R0, RC, and RN 2091, 2092 and 2093, one can calculate the differential times for transmission along the paths d_0 , d_2 , and d_4 . Times can be converted to distances if the speed of ultrasound of the test

15

block medium is known. If the test block medium is water, the speed of sound is approximately

$$\text{sos} = 1.40238742 + 5.03821344 \cdot \text{TE} / 1000 - 5.80539349 \cdot \text{TE}^2 / 100000 + 3.32000870 \cdot \text{TE}^3 / 10000000 - 1.44537900 \cdot \text{TE}^4 / 1000000000 + 2.99402365 \cdot \text{TE}^5 / 1000000000000$$
 in mm per microsecond where TE is the temperature in degrees Celsius. Differential distances can be converted to total distances according to the derivation above.

Now from trigonometry, distance $a = (d_0^2 - d_4^2 + (d_1 + d_3)^2) / (2(d_1 + d_3))$

The position along the x' axis is $d_1 - a$.

Assuming that the element is midway between the two yardsticks, then the position along the y' axis is $\sqrt{(d_0^2 - a^2 - (x/2)^2)}$.

Initially considerable error may occur as a result of this assumption, but the measurement of z will allow for adjustment of the element or the entire probe assembly until this assumption is satisfied.

Again referring to FIG. 21B, the same computations for x' and y' can be made using the left hydrophone array **2094**, **2095** and **2095**. In some embodiments, the results of the measurements made with the right hydrophone array may be averaged with results of measurements made with the left hydrophone array.

Advantageously, by having two hydrophone arrays or "yardsticks," the z axis can be measured, i.e., the position of the elements in or out of the scan plane. Then the array alignment apparatus can display it (see FIG. 22A, **2300**), and thus allow either manual (FIG. 18B) or automatic (FIG. 24) correction and alignment. The z variable is related to the time of arrival difference of the pulse as received at RC **2092** and LC **2095**. The probe position should be adjusted until the time difference is close to zero. When this is done, all of the x and y measurements will be accurate and the relative positions of all of the elements will be known.

In some embodiments, the right and left hydrophone arrays may be used to measure an acoustic position of a test element along the z axis; i.e., the test element's position in or out of the scan plane. In some embodiments, following such a measurement the calibration system may display and/or automatically correct an alignment of the probe within the docking area of the calibration system. In other embodiments, the calibration system may direct an operator to manually adjust an alignment of the probe.

The z variable may be proportional to the distance d2 as computed from the hydrophones on track **845** minus the distance d2 as computed from the hydrophones on track **875** in FIG. 34A. In some embodiments, the probe position may be adjusted until this difference is close to zero.

In other embodiments in which the probe element cannot be mechanically centered between the two tracks, the z position can be computed. This is particularly true for 1.5D probes and 2D probes where it is not possible to position all elements simultaneously to a central position. In these cases, the acoustic position of elements along the z axis may be stored in the calibration table along with x and y coordinates as discussed above.

The value of z can be computed through a straightforward trigonometric calculation as illustrated in FIG. 21C.

Let m = the distance d2 as computed from the hydrophones on track **845** and let n = the distance d2 as computed from the hydrophones on track **875**.

16

Let w indicate half the known distance between the two tracks.

$$n^2 = (w - z)^2 + y^2$$

$$m^2 = (w + z)^2 + y^2$$

$$\text{then } n^2 = (w - z)^2 + m^2 - (w + z)^2$$

$$\text{and } z = (m^2 - n^2) / 4w.$$

In some embodiments, the transverse hydrophone array may be used to determine an angular displacement of a probe test element. In some embodiments, such information may be used to direct automatic or manual re-positioning of the probe. In alternative embodiments, such information may be incorporated into stored calibration data.

In some embodiments, a controller, such as a computer, can scan and find the maximum signal strength on the transverse hydrophone **2086** and record the angular displacement for the probe element.

To use the multiple aperture array alignment apparatus as a daily calibrator, multiple aperture ultrasound transducers may already be fully assembled, such as the embodiment illustrated in FIG. 22. Therefore, all of these measurements will preferably be referenced to axes on the probe assembly. In the multi-aperture transducer probe assembly **2200** shown in FIG. 22, it would be reasonable to rotate and translate all measurements to a new coordinate system (x,y) centered on the center array. The appropriate coordinate system would be dependent on the ultrasound imaging system for which the probe assembly would be used. The multi-aperture probe can have a resident calibration memory or cal chip **2201** that can be programmed with calibration data received from the automated precision stage assembly, described below.

The transmit synchronization module **2202** is not related to calibration, but may be used to identify the start of pulse when the probe is used as an add-on device with a host machine transmitting. The probe displacement sensor **2203** can be an accelerometer or gyroscope that senses the three dimensional movement of the probe. During calibration, the probe should be securely attached to the array alignment apparatus so that the probe is still. The calibration system may then compare information from the position sensor of the probe with information from the position sensor of the calibration tank **122** to determine whether the probe is properly aligned.

Referring now to FIG. 23A, a proprietary graphical user interface or GUI **2300**, allows the elemental array data to be visualized in real-time allowing for correction of the x, y and z variation errors. The two wide vertical lines **2001** and **2003** represent the z positions of the yardsticks R 0-RC-RN (**2091**, **2092**, and **2093** from FIG. 19A) and L 0-LC-LN (**2094**, **2095**, and **2096** from FIG. 19A). The thinner vertical line **2302** is the z=0 line and the desired position of each of the elements of a probe system. The vertical position is the x coordinate.

Each small square, such as **2305**, **2306**, **2307**, **2308**, **2309**, **2310** and **2011**, is the position of a probe element in the x-z plane. In this example there are six small squares indicating the positions of the end elements of three probe heads. However, the positions of more or fewer elements could be displayed in this way. The thin horizontal lines **2312**, **2313**, **2314**, **2315**, **2316**, **2317** and **2018** represent the directivity and angular spread of each element as detected on the multi-axis hydrophone. A useful angular spread measure is the number of hydrophone elements on the transverse hydrophone array which record signal strength greater or equal to half of the maximum strength.

FIG. 23B depicts a probe element positioned correctly with the z position **2305** at or near z=0 and its directivity positioned over the centerline. In contrast, FIG. 23C depicts a probe element with its z position **2305** offset toward the

right hydrophone. The resulting display shows the small square, **2305**, to the right of centerline, **2302**. Note that in this case, the element position is in error, but the element directivity remains over the centerline as indicated on the display by the horizontal line **2312** remaining centered over centerline, **2302**.

Finally, FIG. **23D** depicts a probe element correctly positioned with its **z 2305** position at or near $z=0$, **2302**. The directivity **2312**, however, is misaligned in this case with an offset toward the left hydrophone as indicated by the horizontal line shifted to the left of centerline, **2302**. In this case, the directivity needs to be corrected by adjusting the angulation to bring the directivity back over center. This could be accomplished, for example, by using controls **1805** and **1807** in FIG. **18B**. Thus with this display, element position and directivity can be monitored simultaneously and both brought into alignment.

Adjustments of the probe position and angulation with the precision alignment stage assembly or assemblies should continue until all of the small squares and all of the horizontal lines are aligned on the center vertical line as closely as practicable, ensuring in alignment in the z axis. As this is done, the x and y positions will be computed accurately and no separate iteration will be required for these.

In some manufacturing formats, arrays **2406** could be loaded into an automated precision stage assembly like the one in FIG. **24**. Here, arrays while still within their nose pieces can still be manipulated. In FIG. **24**, we see an automated precision stage assembly, **2406**, fitted with precision stepper motors, **2403**. Stepper motor controller, **2401**, drives the transducer, **2405**, under test in response to instructions from controller, **2402**. The controller, **2401**, evaluates data from the hydrophone assembly, **2404**, and calculates transducer corrections. Test programs residing in the controller, **2402**, provide transducer specific calibration data back to the transducer, **2405**, under test incorporation in its on board calibration chip, **2201**. This automatically acquired element and array position data would be MAUI probe specific and would be used to optimize probe and system performance.

Using the precision stage assemblies with the array alignment system is only part of the value of the system. FIGS. **20A** and **20B** illustrate array alignment systems **2610** attached to the control unit **2620** of an ultrasound machine **2600**. A cut away shows hydrophone assembly **2085** is located at the bottom of the fluid filled system **2610**. In FIG. **26A** a MAUI general radiology probe **2630** is affixed to the system for testing. In FIG. **26B**, a MAUI cardiac probe **2640** is affixed to the system for calibration. The portability of this system, therefore allows for calibration of probes in the field multiple times per day. Additionally the MAUI system would alert the operator if service or maintenance was required.

To calibrate a probe, MAUI electronic apparatus can send a test pattern to the arrays in the probe to transmit to the hydrophone assembly **2085**. When the positions of the probes and their directivities are reported as a result of the sequence, the positions of all of the elements can be downloaded to a file specific to that probe. Each file may be stored in the probe calibration chip **2201**. The calibration chip may report element positions in x , y and z axes to every MAUI electronic apparatus it connects to, and therefore can perform multiple aperture imaging without recalibrating before use with a different MAUI apparatus. The calibration chip memory can also be used to analyze probe performance and reliability.

In the special case in which all of the transmit and receive elements are aligned in the same plane or are manufactured so that there is no adjustment in z position, a simplified alignment fixture can be used. Instead of two parallel "yardsticks" of hydrophones, a single yardstick can be used. In this case the probe would be centered over the single yardstick using a plumb bob or a clamping device. The x and y measurements would then be made assuming $z=0$ and $zr=0$. This is possible since accuracy in the value of z is much less critical in beamforming than is accuracy in the values of x and y . Thus adjusting z by the relatively crude methods of sighting with a plumb bob or clamping to a machined edge of the probe can be acceptable in spite of the high accuracy demands for measurement of x and y . Obviously, the cost of this simplified fixture would be much reduced resulting in a fixture which could be used in the field rather just in the probe assembly factory.

Embodiments below provide further systems and methods for calibrating ultrasound imaging probes as well as systems and methods for testing quality assurance characteristics of ultrasound imaging probes. Although the following embodiments are shown and described with reference to multiple aperture ultrasound imaging (MAUI) probes, the skilled artisan will recognize that many features of the systems and methods described may also be applied to ultrasound probes of any configuration where it is desirable to determine the acoustic position or the health of one or more ultrasound transducer elements in an ultrasound probe.

As discussed above and with further reference to FIGS. **28**, **34A**, and **34B**, some embodiments of a calibration process may comprise three stages: First, a single test-element of the probe may transmit an ultrasound test signal into the calibration tank **122** through the filler material **210**. Second, the hydrophones **230** may receive the ultrasound test signal, and associated electronics and/or software may geometrically triangulate the origin of the test signal in order to determine an acoustic position of the test element to within a desired degree of accuracy. Third, the acoustic position of the test element may be transformed into a coordinate system with a known origin relative to the probe. Coordinates for the test element may be stored in a table of coordinates associated with the probe. These steps may then be repeated for each transducer element in each transducer array within a probe until the acoustic position of each element is determined and recorded in a table of coordinates.

Embodiments of the systems and methods herein may quantify both transmitted and received ultrasonic pulses and use the information obtained to identify the acoustic position of single transducer elements and/or full arrays of transducer elements. Further, embodiments of the systems and methods herein may also quantify the "health" of probe elements. The "health" of a probe element may refer to a number of factors including transmitting and receiving efficiency of probe elements, element sensitivity, and electronic functionality.

Probes with multiple aperture arrays may be properly aligned during production as discussed above. However, regularly recalibrating an ultrasound probe throughout the life of the probe as opposed to only during manufacturing can allow for high quality imaging over a long period of time without requiring the probe to be returned to a manufacturer or repair facility. To address these needs, a calibration system may be provided to accompany probes into the field. In some embodiments, a calibration system may be attached to or integrally formed with an ultrasound control panel. In some embodiments, a calibration system may include a tank in the shape of an open-topped box with a mounting portion in a top section of the box for holding a probe in a calibration

orientation and a plurality of receivers at a bottom of the box for receiving ultrasound signals transmitted from the probe.

By providing a calibration system as an attachment to an ultrasound imaging system, the calibration system becomes easily accessible to operators. In some embodiments, the calibration system may serve as a probe storage location for holding probes not in use. In some embodiments, a plurality of imaging probes of different configurations may be stored in the calibration system. Probes may then be selectively calibrated according to a calibration process, thus making a wide range of probe designs readily available for imaging. Moreover, adjustable multiple aperture probes may be re-configured into a different shape and then recalibrated for each patient.

Referring to FIG. 27A, a calibration system **120** may work in conjunction with a control panel **100**. The control panel **100** can contain and control electronic hardware and software configured to transmit, receive and process ultrasound signals using a multiple aperture ultrasound imaging (MAUI) probe. Such hardware and software is generically referred to herein as MAUI electronics. As shown in FIG. 27A, the calibration system **120** may be externally mounted to a control panel **100**. In such embodiments, the system **120** may be electronically connected to the MAUI electronics by a wired system which may include any desired wiring arrangement, such as wiring harnesses or removable plugs. Alternatively, referring to FIG. 27B, a calibration system **120** may be embedded into the control panel **100**. In further embodiments, a calibration system **120** may be provided as an entirely separate device, which may be electronically connected to the MAUI electronics by any suitable wired or wireless arrangement. In further embodiments, the electronics controlling a calibration system, including electronics controlling a probe during calibration may be entirely independent (physically and/or electronically) of the electronics used for controlling an ultrasound imaging process.

As shown in FIG. 28, in some embodiments the calibration system **120** may resemble a rectangular tank that may be relatively small in size without the bulky alignment features that can be required during manufacturing. In some embodiments, an opening at the top of the tank **122** may be sized to receive a probe **370**. The tank **122** may have an overall height approximately the length of a pencil box (e.g., between about 10 and 24 inches in some embodiments), although larger or smaller tanks may also be used. In some embodiments, a width and/or depth (e.g., in/out of the plane of FIG. 28) of the tank **122** may be sized to minimize undesired reflections from side walls of the tank. Additionally, a material and internal surface texture of the tank **122** may also be engineered to minimize noise from undesired reflected ultrasound waves.

In some embodiments, a matrix of ultrasonic sensors or hydrophones **230** may be attached to the bottom of the tank **122**. The matrix of hydrophones **230** can function similar to the multi-axis hydrophone **2085** described above. It is desirable for the calibration tank **122** to be configured such that an entire ultrasound path between the probe and all receivers is occupied by a material with a consistent and known speed of sound. Thus, similar to the tank **2012** described above, the tank **122** may be filled by a filler **210** made of a liquid, gel or solid material with a consistent and known speed of sound. The filler **210** may be any material that is desirable for manufacture and safety considerations. The speed of sound through the filler **210** should be known precisely in order to accurately calculate the distance traveled by any given ultrasound pulse during a calibration process. In one embodiment, the filler **210** is made of a relatively rigid

ballistics gel. The filler **210** can occupy substantially all of the tank **122**. In some embodiments, the filler occupies most of the tank **122** except for a top layer which may be reserved for a docking area **220** configured for receiving an ultrasound probe to be calibrated.

In some embodiments, the docking area **220** may be an empty void which may be filled with a liquid or gel which may conform to a shape of a probe to be calibrated such as the illustrated multiple aperture probe **370**. In other embodiments, the docking area **220** may include a molded piece of ballistics gel (or other suitable material) configured to conform to the shape of a probe to be calibrated. Preferably, the material used in the docking area **220** has substantially the same speed of sound as the filler material **210**. In other embodiments, the docking area and/or the entire filler may comprise a flexible bladder filled with a suitable liquid or gel material. In some embodiments, the probe and/or the docking area may be coated with an ultrasound coupling gel as will be clear to the skilled artisan.

For the best results, probes should be substantially immobile during all calibration and quality testing. To reduce error the calibration system **120** may be equipped with a mechanical docking device configured to hold the probe(s) in a substantially rigid and consistent position. Referring to FIG. 31, in some embodiments, an adjustable clasp **510** may be provided to capture and hold a probe **370** by a handle section or any other suitable portion of the probe. In other embodiments, a clasp or grasping element may be integrally formed with the docking area **220**. In some embodiments, the docking area **220** and/or a clasp **510** may include electronic contacts or other elements which may interact with corresponding features on a probe to ensure consistently proper positioning of the probe for calibration.

In other embodiments, accelerometers, gyroscopes or other position sensors within the probe may be used to inform an operator of proper or improper positioning of a probe within a docking area of a calibration system. In some embodiments, corresponding position sensors (e.g., gyroscopes, accelerometers or other sensors) may be provided in or on the calibration tank. A calibration system may then compare information from the position sensor of the probe with information from the position sensor of the calibration tank **120** to determine whether the probe is properly aligned for calibration.

FIGS. 32A-33B illustrate embodiments of docking devices **610** that may be used in a docking area of a calibration system. FIG. 32A shows an embodiment of a docking device **610** with a plurality of probe-specific molded receivers (**602-628**). In such an embodiment, each probe that might be used with a particular system may have a specific receiver within the calibration system. For example, the top center docking site **604** may be configured to receive a curvilinear MAUI probe **375** having a continuous concave curved array **378** of ultrasound transducer elements such as that shown in FIG. 29B.

FIG. 32B is a cross-sectional view of the calibration tank taken through line A1-A in the plan view of FIG. 32A. In some embodiments, each docking device molded receiver may be manufactured to best fit the specific needs of each probe; this can be especially useful for probes with a more tight curvature or uniquely designed probes.

Other embodiments, as shown for example in FIGS. 33A and 33B may feature interchangeable docking receivers custom made for each transducer. The docking receivers **710**, **720**, and **730** may be removably attached to a docking area **220** of the calibration system. Each receiver **710**, **720**, and **730** may be formed for a specific type of probe. In

further embodiments, one or more receivers may be configured to receive any of the probes shown and described in U.S. patent application Ser. No. 13/029,907 now published as US Patent Publication 2011/0201933, and incorporated herein by reference.

In some embodiments, the dock may be configured such that the ultrasound probe may be stored in the dock when not in use. The user or operator can then optionally calibrate the probe prior to removing the probe from the dock.

In some embodiments, one or more temperature sensors may be provided and configured to measure a temperature of the filler **210**. As discussed above, the temperature of the filler material **210** is used to calculate the acoustic position of transducer elements in a probe during calibration. Thus, in some embodiments, a plurality of temperature sensors (e.g., thermocouples, thermistors, optical thermal imaging systems, etc.) may be positioned throughout the tank to obtain enough measurements to determine an average temperature of the filler **210** at any given time. In other embodiments, a single temperature sensor may be sufficient.

In some embodiments, a hydrophone matrix **230** such as that shown in FIG. **34A** and FIG. **28B** may be used to detect the X, Y and Z positions of each element of a single array or multiple arrays in a probe under calibration. In some embodiments, the multi-axis hydrophone **230** can include a transverse hydrophone array **810**, a right hydrophone array **845** and a left hydrophone array **875**. In other embodiments, the hydrophone matrix may include only a single array of hydrophone elements. In other embodiments, a hydrophone matrix may comprise a two-dimensional array of many detector elements to enable further measurements. For example, the hydrophone matrix may comprise a 3x3 array, a 4x4 array, a 4x6 array or any other 'n'x'm' array of hydrophone elements.

In some embodiments, the hydrophone matrix **230** may act as a target when the probe is firing. In some embodiments, hydrophone elements selected to be detectors may depend on the size, shape and orientation of the probe to be calibrated. In some embodiments, such calibration process details may be stored in the calibration chip or another data store in communication with the calibration system electronics.

Ultrasound transducer elements or arrays of elements are typically cut from a common crystal wafer (e.g., of a piezoelectric crystal) to form 1D, 1.5D and 2D arrays. Alternatively, some ultrasound elements may be printed or machined into a micromachined lattice structure to form an array called a Capacitive Micromachined Ultrasonic Transducer (CMUT) array. FIG. **24A** illustrates a 1D piezoelectric transducer array in which each rectangular segment represents a single transducer element **400**. Such an array is referred to as one-dimensional because the array has only rows of longitudinal transducer elements without columns. FIG. **24B** illustrates a 2D piezoelectric transducer array in which each square segment represents a separate transducer element **400**. Such an array is referred to as 2-dimensional because the array of elements extends in two directions, having both rows and columns. FIG. **30C** illustrates a CMUT array in which each transducer element **400** has a more complex geometric shape. Furthermore, a CMUT array has a much more complex arrangement, where elements are not necessarily arranged in rows and columns.

In the case of conventional 1D and 1.5D phased array probes, the position of the elements is often roughly determined by the size of the cuts inside the crystal wafer upon initial manufacture. Referring to FIG. **30B**, in this process, the acoustic center of each element is assumed to be at the

center of the shaped crystalline structure **440**, usually a parabolic channel running down the mid portion **420** of the elements. This may or may not be the true acoustic center of the element due to slight variations in the structure of the PZT crystal or variability in the machining process. Nonetheless, transmit and receive beamformers typically assume that the acoustic center position of a transducer element is coincident with its geometric center. When the true acoustic center of an element is not exactly at the geometric center (e.g., along the longitudinal axis **420**), then both transmit waveform energy and echoes being received are not being optimized. They are subject to the errors of being out of alignment, which detrimentally affects image quality and depth. The same problem may also exist for 1.5D, 2D and CMUT arrays. Therefore, even traditional single-aperture phased array probes may benefit from regular calibration using the systems and methods described herein.

Once an ultrasound probe is firmly mounted in the docking area of the calibration system, a calibration process may be initiated. In some embodiments, a calibration process may be initiated by a user pressing a button (e.g., **140** in FIG. **27B**) on a calibrator or imaging system control panel.

In some embodiments, the calibration system may be configured to determine the acoustic position of transducer elements relative to a single array of which an individual test element is a part. For example, in the case of a multiple aperture probe such as that shown in FIG. **29A**, the acoustic position of each element on the center array **350** may be determined relative to a coordinate system **380** centered on that array. Similarly, the acoustic positions of elements in the left **340** and right **360** arrays may also be determined relative to separate coordinate systems centered on those respective arrays.

A further calibration process may then be employed to detect the position of one full array relative to another, thereby providing information describing the relative positions of the three coordinate systems. In such an embodiment, test signals may be transmitted from elements at opposite ends or corners of each array to be located relative to other arrays. This may allow for the measurement of the length, acoustic center and 3-dimensional orientation of each array relative to other arrays in a probe containing multiple arrays. For example, the position and orientation of a planar transducer array may be determined by identifying the three-dimensional location of a sufficient number of array elements to define the orientation of the array's planar surface. In some embodiments, three elements may be sufficient to define the plane of an array. In other embodiments, several or all elements may be located to define the orientation of the array's plane. In some embodiments, information describing the orientation of a planar array may be stored along with other calibration data. Such embodiments may be especially useful when calibrating adjustable probes which may contain two or more physically separate arrays which are free to move relative to one another.

In some embodiments, the calibration system can be configured to transmit a new test signal to the hydrophone matrix from every element of the probe such that the acoustic location of every element of the probe can be determined. In other embodiments, a test signal can be sent from only a few of the probe elements, such as two probe elements in an array, and the remaining locations can be determined through interpolation.

Many transmit pulse patterns may be used in the step of transmitting an ultrasound test signal from a test element. In some embodiments, an ultrasonic test signal may be transmitted which exhibits good autocorrelation properties. In

some embodiments, such a test signal may comprise a long frequency sweep, a ‘chirp’ waveform, a spread spectrum waveform, a ‘ping’, a pseudorandom sequence, or another suitable pattern. In some embodiments, a test signal may be selected to require minimal computational complexity.

As will be clear to the skilled artisan in view of the discussion herein, the only directly measurable ultrasound parameter in the calibration system is the time delay between transmission of a test signal from a probe test element and receipt of the test signal at each hydrophone element. Based on these time delays, known speed of sound through the filler material, and known physical geometry of the calibration system, the position of a test element may be calculated.

It is important to note that in many cases, a test element may distort the timing of a transmitted signal. Thus, in some embodiments, it may be desirable to perform time delay measurements without relying on a presumed “transmit time” as determined by a time of sending an electrical signal to a transducer element. In such embodiments, the total distance traveled by an ultrasound test signal may be determined by using only the speed of sound and the difference between the time at which the test signal is received at a first hydrophone element and a time-of-receipt of the test signal at a second hydrophone element.

Multiple techniques, such as those described above with reference to FIGS. 21A, 21B & 21C, may be used to obtain the needed accuracy in finding the relative time delays and hence the relative distances, including using cross correlation between the signal received at one hydrophone element (e.g., 820) and the signal received at another element of the same hydrophone array (e.g., 840), interpolating between samples of the received waveforms to obtain better time resolution than simply the sampling interval, and converting a differential distance measured by two hydrophone elements to a total distance traveled by an ultrasound test signal.

Referring to FIG. 28, a coordinate system 260 can be established relative to the hydrophone matrix. In FIG. 28, the X-axis is aligned with left and right directions in the tank, the Y-axis is aligned with the “up and down” directions in the tank, and the Z-axis is perpendicular to the scan-plane and the plane of FIG. 28. The position of a plurality of probe elements, such as every probe element, can then be determined relative to the coordinate system 260.

In some embodiments, position measurements may be translated from the coordinate system 260 with an origin relative to the hydrophones matrix to a coordinate system 380 with an origin located on the probe itself, as shown in FIG. 29. In the coordinate system 380 shown in FIG. 29, the X-axis lies along a center line of all three arrays, the Y-axis is perpendicular to the plane of the center array, and the Z-axis is perpendicular to the X & Y axes, extending in and out of the page of FIG. 29A. In some embodiments, a process of rotating and translating coordinates may be used to translate the coordinate systems. In some embodiments, an appropriate probe-relative coordinate system may be dependent on the ultrasound imaging system for which the probe assembly is to be used.

With a conventional array, a transmit pulse from a transmitting element to a reflector is easily calculated back to a given receive element. Assuming a constant speed of sound, the positions in a conventional matrix or linear array are mechanically assumed so that transmit and receive paths can be easily computed. In multiple aperture imaging it is important to determine the position of each element relative to the position of any other element(s) in a known space such

as a Cartesian X, Y, and Z coordinate system illustrated in FIG. 31 for example. In some embodiments, such a coordinate system may have one element designated as an origin and acoustic center positions of all other element(s) may be assigned coordinates relative to this initial position. From this the position of any element may then be known relative to any other.

As will be clear to the skilled artisan, the origin of a coordinate system may be centered at any element, or at any other point on or off of the probe. Additionally, the calibration system need not necessarily use a Cartesian coordinate system; any suitable coordinate system may be used, provided that such a coordinate system gives accurate information about the position of transducer elements.

The information obtained through calibration as well as the new coordinate system may then be compared to original element position information for the probe, as well as any previous calibration data. In some embodiments, this information may be tracked over time to better understand the properties of the probe elements and the probes as they are used. In some embodiments, this time-series calibration information may be stored and/or analyzed in an ultrasound imaging system, a remote server system, or any other suitable computing system.

During manufacturing, each MAUI transducer may be properly aligned and calibrated according to the type of crystal matrix used. The initial coordinate system and calibration may then be programmed into a memory chip 310, which can be set in the handle of the probe as shown in FIG. 29A. When the probe is recalibrated at some later time, the calibration system electronics may compare the new calibration results to the initial or last-known position of the elements. Difference data or new position data may then be updated in the calibration chip 310. Besides maintaining the calibration data, calibration chip 310 may also contain data for setting up a general layout of each probe, this information may be used to inform the calibration system of the number of elements to fire and in roughly what order or design during calibration.

In some embodiments, calibration data for a probe may be stored in a location other than the probe itself. It is generally desirable for calibration data to be associated specifically with the probe it describes, but such information may be stored in any practical physical location. For example, in some embodiments, a probe may have an ID chip which carries substantially only an identification number which may be used to retrieve a unique calibration record stored in a remote (e.g., internet-accessible) database, in an ultrasound imaging system, or any other location. In some embodiments, communications systems may also be provided to allow for logging of calibration data into an ultrasound imaging system data log, and/or sending to a service provider and/or providing an operator with an appropriate on screen notification.

Each probe may have a unique element coordinate table which may be permanently associated with the probe, and which may be updated in subsequent calibration processes. In some embodiments, the calibration data overwrites calibration data previously stored in the memory. Overwriting advantageously ensures that updated data is constantly available, even in systems with small amounts of available memory.

In some embodiments, probes may be recalibrated and data stored as many times as desired by an operator, technician, or manufacturer.

The stored coordinate table may be used by ultrasound imaging system electronics in order improve the quality of

ultrasound images generated using the calibrated probe. In one embodiment, the updated position data can be used during imaging, e.g., the stored data can be used as an input in an algorithm used to generate an image from a multiple aperture ultrasound imaging system. In another embodiment, the stored coordinate table can be used in post-image processing, i.e., the stored data can be used to decode stored image data or raw echo data.

Instruments of any kind used in the field on a daily basis will typically suffer from general wear and tear. To better understand the degradation of ultrasound transducers over time, as well as to obtain regular feedback pertaining to the general functionality of the probe, the calibration system may also be configured to perform general quality assurance functions. In some embodiments, the calibration system may test both the transmitting and receiving functions of the probe, report operational capabilities to the sonographer and send probe functionality data and repair requests to the service provider.

In some embodiments, the quality assurance test may be performed before each calibration so that the information obtained can be used to more accurately calibrate the probe. In some embodiments, after securing a probe in a docking area of the calibration system, a quality assurance test sequence may be manually or automatically initiated. For example, in some embodiments, the quality assurance test may be initiated via a button on the control panel. In some embodiments, a quality assurance test sequence may comprise three stages: The first stage will be referred to as hydrophone verification, the second stage will be referred to as an element transmit test and the third will be referred to as an element receive test.

In some embodiments, an additional self-test hydrophone **240** may be mounted to a side wall near the top of the tank **122** for use in quality assurance testing. The self-test hydrophone **240** and corresponding control electronics may be configured to check the position and function of the hydrophones of the main hydrophone matrix **230** in order to ensure proper calibration of the calibration system. In one embodiment the self-test hydrophone **240** may be located in the top of the tank **122** along the centerline of the hydrophone matrix **230**. In other embodiments, a self-test hydrophone **240** may be positioned at any other location within the tank suitable for performing the described functions. In a process similar to the process for calibrating ultrasound probe elements, the self-test hydrophone **240** may send and receive ultrasound pulses to the main calibration hydrophones **230** and then use this information to ensure the hydrophones **230** are functioning properly and accurately.

Each hydrophone of the main hydrophone matrix **230** may also transmit a self-test signal to be received by the self-calibrator hydrophone **240**. The process may be similar to those described elsewhere herein for the calibration and quality assurance testing of ultrasound probe elements. The proper functioning and exact location of the hydrophone elements is very important for the best possible calibration of the probes.

In some embodiments, the hydrophone verification stage may ensure that information obtained from the hydrophones is accurate. As shown in FIG. **28**, some embodiments of the calibration system may be equipped with one or more self-calibrator hydrophones **240** located in a top corner of the tank. A self-calibrator hydrophone **240** may be used to verify the transmitting and receiving capabilities of the hydrophones elements of the hydrophone arrays **810**, **845**, **875** in the hydrophone matrix **230**. In some embodiments, the self-calibrator may also be used to verify the acoustic

positions of the elements of the main hydrophone matrix **230**. The self-calibrator may transmit ultrasonic self-test signal pulse or pulses in a set pattern from a known location. The strength of received signals and the order in which they are received may be used to determine the acoustic position and receiving functionality of the hydrophone elements using methods similar to those described above.

In some embodiments, a quality assurance transmit test may be designed to test the transmit strength, efficiency and/or effectiveness of each transducer element of an ultrasound probe. A QA transmit test may begin by exciting a test transducer element with a precise electrical signal to cause the transducer to transmit ultrasonic pulses. The transmit test signal may have any shape and frequency as desired, preferably with good autocorrelation properties as discussed above with reference to calibration test embodiments.

The test signals may then be received by one or more hydrophone elements. The received frequency may then be transformed by the hydrophone transducer into specific amplitudes of electrical charge. From the resulting charges obtained by the hydrophones, the calibration system may determine whether a received signal has expected properties based on the electrical signal input to the test element. After testing all test elements, the calibration system may determine which test elements fall below an average transmitting capability and which fail to fire at all. This information may be obtained by comparing the amplitudes created by each test signal and then identifying which elements fall below the mean and by how much. In some embodiments, QA transmit test result data may be stored in a calibration chip within a probe or in any other suitable location. In some embodiments, an absolute value of a mean transmit strength may also be stored and analyzed over time to evaluate the long term health of a probe.

In some embodiments, a quality assurance receive test may evaluate the receiving capabilities of each probe element in a similar (but opposite) process. In some embodiments, a calibration hydrophone (**230** or **240**) may transmit a precise ultrasonic test signal pulse or pulses of a known frequency. Each probe element may then receive the test signal and transform it into an electrical charge with a specific amplitude. The electric charges or amplitudes of the receiving probe elements may then be compared relative to each other and to any previous receive test data. Much like the transmitting test elements that are receiving poorly or not converting the ultrasonic pulses at all may fall out of tolerance. The average of the element receiving pulse amplitudes compared over time may indicate the degradation of elements. As above, test data may be logged, stored, and analyzed over time.

In some embodiments an ultrasound system operator/technician may be provided with information about quality assurance calibration and test data resulting from the above processes. In some embodiments, a service provider and/or probe manufacturer may also be informed of calibration and/or test data, e.g., when elements are underperforming or no longer transmitting or receiving. This information can be used to decide when to schedule probe repairs or when a probe should be replaced. Compensation for elements which are no longer firing, or for the adjustment of transmit amplitude and receive gain of any particular element may then be done internally to the electronics of an ultrasound imaging system (e.g., MAUI electronics in the case of a multiple aperture ultrasound imaging system).

Although many of the embodiments of ultrasound probe calibration and quality assurance testing systems and methods are shown and described with reference to multiple

27

aperture ultrasound imaging probes, these systems and methods can also be applied to single aperture ultrasound imaging systems.

Terms such as “optimized,” “optimum,” “precise,” “exact” and similar terms used in relation to quantitative parameters are merely intended to indicate design parameters which may be controlled or varied in accordance with general engineering principles, and may involve a compromise based on the balancing of competing design factors. Use of these terms is not intended to imply or require that the parameters or components thereof are designed for the best possible or theoretical performance.

The above disclosure is sufficient to enable one of ordinary skill in the art to practice the invention, and provides the best mode of practicing the invention presently contemplated by the inventor. While there is provided herein a full and complete disclosure of the preferred embodiments of this invention, it is not desired to limit the invention to the exact construction, dimensional relationships, and operation shown and described. Various modifications, alternative constructions, changes and equivalents will readily occur to those skilled in the art and may be employed, as suitable, without departing from the true spirit and scope of the invention. Such changes might involve alternative materials, components, structural arrangements, sizes, shapes, forms, functions, operational features or the like.

What is claimed is:

1. An ultrasound probe calibration device, comprising:

a tank having a top portion, a bottom wall, at least one side wall between the top portion and the bottom wall, an internal volume filled with a gel or a solid filler material, and at least one target within the tank volume; and

the upper portion defining an ultrasound probe docking area having at least one ultrasound probe receiver and a mechanical docking device configured to hold an ultrasound probe in a substantially rigid, consistent, and immobile position,

wherein the at least one ultrasound probe receiver comprises electrical contacts arranged and configured to interact with corresponding electrical contacts on an ultrasound probe positioned in the at least one ultrasound probe receiver.

28

2. The device of claim 1, wherein the mechanical docking device comprises a clasp configured to secure a handle portion of the ultrasound probe in a fixed position.

3. The device of claim 1, wherein the probe receiver comprises a molded body that conforms to a shape of the ultrasound probe.

4. The device of claim 3, wherein a material of the ultrasound probe receiver is the same material as the filler material.

5. The device of claim 4, wherein the filler material and the ultrasound probe receiver material are both ballistics gel.

6. The device of claim 1, wherein the ultrasound probe receiver comprises a flexible fluid-filled bladder.

7. The device of claim 1, wherein the ultrasound probe docking area comprises a plurality of molded probe receivers conforming to shapes of differently-shaped ultrasound probes.

8. The device of claim 1, further comprising at least one temperature sensor in the tank.

9. An ultrasound probe calibration device, comprising:

a tank having a top portion, a bottom wall, at least one side wall between the top portion and the bottom wall, an internal volume filled with a gel or a solid filler material, and at least one target within the tank volume wherein the target comprises a hydrophone matrix on the bottom wall of the tank; and

the upper portion defining an ultrasound probe docking area having at least one ultrasound probe receiver and a mechanical docking device configured to hold an ultrasound probe in a substantially rigid, consistent, and immobile position.

10. The device of claim 9, wherein the hydrophone matrix comprises a multi-axis hydrophone including a transverse hydrophone array, a right hydrophone array, and a left hydrophone array.

11. The device of claim 9, wherein the hydrophone matrix comprises a two-dimensional array of hydrophone elements.

12. The device of claim 9, further comprising a self-test hydrophone on the at least one side wall of the tank and separate from the hydrophone matrix.

13. The device of claim 9, further comprising a self-test hydrophone located in the upper portion of the tank along a centerline of the hydrophone matrix.

* * * * *

专利名称(译)	超声探头的校准		
公开(公告)号	US10206662	公开(公告)日	2019-02-19
申请号	US15/044932	申请日	2016-02-16
[标]申请(专利权)人(译)	史密斯戴维M ADAM SHARON大号 SPECHT DONALD F BREWER KENNETH D 伦斯福德JOHN P SPECHT大卫·		
申请(专利权)人(译)	斯密，大卫M. ADAM，SHARON L. SPECHT唐纳德F. 布鲁尔，KENNETH D. 伦斯福德，约翰P. SPECHT，DAVID J.		
当前申请(专利权)人(译)	MAUI IMAGING，INC.		
[标]发明人	SMITH DAVID M ADAM SHARON L SPECHT DONALD F BREWER KENNETH D LUNSFORD JOHN P SPECHT DAVID J		
发明人	SMITH, DAVID M. ADAM, SHARON L. SPECHT, DONALD F. BREWER, KENNETH D. LUNSFORD, JOHN P. SPECHT, DAVID J.		
IPC分类号	A61B8/00 G01S15/89 G01S7/52		
CPC分类号	A61B8/587 A61B8/00 A61B8/4218 A61B8/4254 G01S15/8915 A61B8/4477 A61B8/4483 G01S7/5205 G01S15/8913 A61B8/4444		
优先权	61/169200 2009-04-14 US		
其他公开文献	US20160157833A1		
外部链接	Espacenet		

摘要(译)

校准超声探头的方法包括将超声探头安装到校准系统上，通过校准系统的测试介质从探头的元件发射超声测试信号，以及在水听器矩阵上接收测试信号，使得可以计算元素相对于同一探针内其他元素和其他数组的位置。此外，这里描述的系统被配置为检测探测器的元件的声学性能并将结果报告给最终用户或服务提供者。

