



US010459072B2

(12) **United States Patent**  
**Liu**

(10) **Patent No.:** **US 10,459,072 B2**  
(45) **Date of Patent:** **Oct. 29, 2019**

(54) **ULTRASOUND PROBE AND ULTRASOUND SYSTEM**

(2013.01); *G01N 29/348* (2013.01); *G01S 7/5202* (2013.01); *G01S 7/52022* (2013.01); *G01S 7/52042* (2013.01); *G01S 15/8913* (2013.01); *G01S 15/8915* (2013.01); *G01S 15/8952* (2013.01); *G01N 2291/104* (2013.01)

(71) Applicants: **QISDA OPTRONICS (SUZHOU) CO., LTD.**, Suzhou, Jiangsu Province (CN); **QISDA CORPORATION**, Taoyuan (TW)

(58) **Field of Classification Search**  
CPC ..... *G01S 7/52079*; *A61B 8/14*; *A61B 8/4281*; *A61B 8/4444*  
USPC ..... *73/628*  
See application file for complete search history.

(72) Inventor: **Jian-Hung Liu**, New Taipei (TW)

(73) Assignees: **Qisda (Suzhou) Co., Ltd.**, Suzhou (CN); **Qisda Corporation**, Taoyuan (TW)

(56) **References Cited**

U.S. PATENT DOCUMENTS

(\* ) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 299 days.

3,712,119 A 1/1973 Cross  
3,987,673 A 10/1976 Hansen  
(Continued)

(21) Appl. No.: **15/379,510**

FOREIGN PATENT DOCUMENTS

(22) Filed: **Dec. 15, 2016**

CN 104549978 A 4/2015  
JP 2009296055 A 12/2009  
TW 201512655 A 4/2015

(65) **Prior Publication Data**

US 2017/0343657 A1 Nov. 30, 2017

*Primary Examiner* — Tarun Sinha

(30) **Foreign Application Priority Data**

May 27, 2016 (CN) ..... 2016 1 0363265

(57) **ABSTRACT**

An ultrasound probe includes a casing, a first transmitting unit, a second transmitting unit and a receiving unit. The first transmitting unit is used for transmitting a first push beam and the first push beam has a first transmitting frequency. The second transmitting unit is used for transmitting a second push beam and the second push beam has a second transmitting frequency. The receiving unit has a receiving frequency and is used for selectively receiving a reflective wave of the first push beam and the second push beam, wherein the receiving frequency is covered with the first transmitting frequency and the second transmitting frequency. The receiving unit, the first transmitting unit and the second transmitting unit are disposed in the casing side by side.


(51) **Int. Cl.**

*G01S 7/52* (2006.01)  
*A61B 8/14* (2006.01)  
*A61B 8/00* (2006.01)  
*G01N 29/04* (2006.01)  
*G01S 15/89* (2006.01)  
*G01N 29/22* (2006.01)  
*G01N 29/34* (2006.01)

(52) **U.S. Cl.**

CPC ..... *G01S 7/52079* (2013.01); *A61B 8/14* (2013.01); *A61B 8/4281* (2013.01); *A61B 8/4444* (2013.01); *A61B 8/4483* (2013.01); *G01N 29/043* (2013.01); *G01N 29/221*

**14 Claims, 1 Drawing Sheet**




(56)

**References Cited**

U.S. PATENT DOCUMENTS

5,460,595 A 10/1995 Hall  
2002/0050169 A1\* 5/2002 Ritter ..... G01S 7/52046  
73/606  
2011/0184287 A1\* 7/2011 McAleavey ..... A61B 8/4483  
600/438  
2012/0232397 A1\* 9/2012 Ohshima ..... A61B 8/4472  
600/447  
2013/0123630 A1\* 5/2013 Freiburger ..... G01S 7/52042  
600/443  
2013/0241356 A1\* 9/2013 Kim ..... A61B 8/4444  
310/336  
2015/0289846 A1\* 10/2015 Park ..... A61B 8/5207  
600/447

\* cited by examiner



## ULTRASOUND PROBE AND ULTRASOUND SYSTEM

### CROSS REFERENCE TO RELATED APPLICATION

This application claims the benefit of China Application No. 201610363265.7, which was filed on May 27, 2016, and is incorporated herein by reference.

### BACKGROUND OF THE INVENTION

#### 1. Field of the Invention

The invention relates to an ultrasound probe and an ultrasound system and, more particularly, to an ultrasound probe and an ultrasound system capable of transmitting two push beams with different frequencies.

#### 2. Description of the Prior Art

Since ultrasound scanning equipments do not destroy material structure and cell, ultrasound scanning equipments are in widespread use for the field of material and clinical diagnosis. When an ultrasound probe is scanning, the ultrasound probe transmits a push beam with a specific intensity to a tissue, so as to vibrate the tissue. Then, the vibration spreads in all directions with a specific speed based on a characteristic of the tissue, wherein a reflective wave perpendicular to a direction of the push beam is called "shear wave". Since a wave speed of the shear wave changes with the hardness of the tissue, the hardening of the tissue can be obtained by measuring the wave speed of the shear wave. In general, a shear wave generated by a push beam with low frequency may spread with a long distance, but the resolution is bad. Therefore, the push beam with low frequency is suitable for scanning a tissue of liver, breast or the like. Furthermore, a shear wave generated by a push beam with high frequency may spread with a short distance, but the resolution is good. Therefore, the push beam with high frequency is suitable for scanning a tissue of a small area. In the prior art, the ultrasound probe can only transmit a push beam with one single frequency. When a doctor wants to perform the ultrasound scanning for tissues located at different distances, he/she has to change different ultrasound probes and it is very inconvenient in use.

### SUMMARY OF THE INVENTION

An objective of the invention is to provide an ultrasound probe and an ultrasound system capable of transmitting two push beams with different frequencies, so as to solve the aforesaid problems.

According to an embodiment of the invention, an ultrasound probe comprises a casing, a first transmitting unit, a second transmitting unit and a receiving unit. The first transmitting unit is used for transmitting a first push beam and the first push beam has a first transmitting frequency. The second transmitting unit is used for transmitting a second push beam and the second push beam has a second transmitting frequency. The receiving unit has a receiving frequency and the receiving unit is used for selectively receiving a reflective wave of the first push beam and the second push beam, wherein the receiving frequency is covered with the first transmitting frequency and the second

transmitting frequency. The receiving unit, the first transmitting unit and the second transmitting unit are disposed in the casing side by side.

According to another embodiment of the invention, an ultrasound system comprises an ultrasound probe, a receiver and a pulser. The ultrasound probe comprises a casing, a first transmitting unit, a second transmitting unit and a receiving unit. The first transmitting unit is used for transmitting a first push beam and the first push beam has a first transmitting frequency. The second transmitting unit is used for transmitting a second push beam and the second push beam has a second transmitting frequency. The receiving unit has a receiving frequency, wherein the receiving frequency is covered with the first transmitting frequency and the second transmitting frequency. The receiving unit, the first transmitting unit and the second transmitting unit are disposed in the casing side by side. The receiver is electrically connected to the receiving unit. The pulser is electrically connected to the first transmitting unit, the second transmitting unit and the receiver. The pulser is used for triggering the first transmitting unit and the second transmitting unit to selectively transmit the first push beam and the second push beam.

As mentioned in the above, the invention integrates the two transmitting units and the receiving unit into the ultrasound probe, wherein the two transmitting units can transmit two push beams with different frequencies. Accordingly, the ultrasound probe of the invention can selectively transmit a push beam with low frequency to scan a tissue of liver, breast or the like or transmit a push beam with high frequency to scan a tissue of a small area. In other words, the ultrasound probe of the invention can perform ultrasound scanning for tissues located at different distances. Therefore, the invention is very convenient in use.

These and other objectives of the present invention will no doubt become obvious to those of ordinary skill in the art after reading the following detailed description of the preferred embodiment that is illustrated in the FIGURE.

### BRIEF DESCRIPTION OF THE DRAWINGS

The FIGURE is a schematic diagram illustrating an ultrasound system according to an embodiment of the invention.

### DETAILED DESCRIPTION

Referring to the FIGURE, the FIGURE is a schematic diagram illustrating an ultrasound system **1** according to an embodiment of the invention. As shown in the FIGURE, the ultrasound system **1** comprises an ultrasound probe **10**, a receiver **12** and a pulser **14**. The ultrasound probe **10** comprises a casing **100**, a first transmitting unit **102**, a second transmitting unit **104** and a receiving unit **106**, wherein the receiving unit **106**, the first transmitting unit **102** and the second transmitting unit **104** are disposed in the casing **100** side by side. The receiver **12** is electrically connected to the receiving unit **106** and the pulser **14** is electrically connected to the first transmitting unit **102**, the second transmitting unit **104** and the receiver **12**. Furthermore, the ultrasound probe **10** further comprises a matching layer **108**, a backing layer **110** and a lens **112**, wherein the matching layer **108** is disposed on the receiving unit **106**, the first transmitting unit **102** and the second transmitting unit **104**, the backing layer **110** and the matching layer **108** are disposed at opposite sides of the receiving unit **106**, the first transmitting unit **102** and the second transmitting unit **104**,

and the lens **112** is disposed in the matching layer **108**. The receiving unit **106** may also be used as a common diagnostic probe for scanning tissue structure. In this embodiment, the receiving unit **106** is used for receiving a reflective wave when detecting a shear wave. It should be noted that the ultrasound system **1** and the ultrasound probe **10** may be further equipped with other necessary circuits and components according to practical applications and those will not be depicted herein.

In this embodiment, the first transmitting unit **102** and the second transmitting unit **104** are located at opposite sides of the receiving unit **106**. However, in another embodiment, the first transmitting unit **102** and the second transmitting unit **104** may be located at an identical side of the receiving unit **106** according to practical applications.

The receiving unit **106**, the first transmitting unit **102** and the second transmitting unit **104** may be made of a piezoelectric material, wherein the piezoelectric material may be lead zirconate titanate (PZT), polyvinylidene (PVDF), Lithium Niobate (LiNbO<sub>3</sub>), PMNPT or other piezoelectric materials. Furthermore, the receiving unit **106** may essentially consist of a plurality of channels **1060**, wherein the number of the channels **1060** may be 64, 128, 192, 256 or other values according to practical applications. It should be noted that a common coaxial cable has 134 cores. If the number of the channels **1060** of the receiving unit **106** is 128, the signal lines of the receiving unit **106**, the first transmitting unit **102** and the second transmitting unit **104** may be integrated into one single coaxial cable.

In this embodiment, the first transmitting unit **102** is used for transmitting a first push beam and the second transmitting unit **104** is used for transmitting a second push beam, wherein the first push beam has a first transmitting frequency and the second push beam has a second transmitting frequency. Furthermore, the receiving unit **106** has a receiving frequency, wherein the receiving frequency is covered with the first transmitting frequency and the second transmitting frequency.

In general, an oscillation frequency of the ultrasound probe is related to a thickness of the piezoelectric material. The thickness of the piezoelectric material is equal to  $\frac{1}{2}$  wavelength and the relationship between wavelength, sound speed of material and center frequency is represented by the following equation 1.

$$\text{wavelength} = \text{sound speed of material} / \text{center frequency.} \quad \text{Equation 1:}$$

$$\text{center frequency} = (FL + FH) / 2. \quad \text{Equation 2:}$$

Where:

A Fast Fourier Transform (FFT) is performed on the echo pulse and the  $-6$  dB levels of the rising edge (FL) and falling edge (FH) of the spectrum are summed then divided by two.

$$\text{Operating Bandwidth} = (FH - FL) / \text{center frequency} * 100. \quad \text{Equation 3:}$$

Where:

A Fast Fourier Transform (FFT) is performed on the echo pulse. The difference from the  $-20$  dB levels of the rising edge (FL) and falling edge (FH) of the spectrum are divided by the center frequency (FC) then multiplied by one hundred. It's usually more than 100% in the ultrasound transducer.

Accordingly, in the invention, a thickness **t3** of the receiving unit **106** may be between a thickness **t1** of the first transmitting unit **102** and a thickness **t2** of the second transmitting unit **104**, such that the receiving frequency of the receiving unit **106** may be between the first transmitting

frequency of the first transmitting unit **102** and the second transmitting frequency of the second transmitting unit **104**. For example, when the thickness **t3** of the receiving unit **106** is  $\frac{1}{2}$  times the thickness **t1** of the first transmitting unit **102** and the thickness **t2** of the second transmitting unit **104** is  $\frac{1}{4}$  times the thickness **t1** of the first transmitting unit **102**, the receiving frequency of the receiving unit **106** is two times the first transmitting frequency of the first transmitting unit **102** and the second transmitting frequency of the second transmitting unit **104** is four times the first transmitting frequency of the first transmitting unit **102**. At this time, the wavelength of the matching layer **108** may be  $\frac{1}{4}$ ,  $\frac{1}{8}$  and  $\frac{1}{16}$ . Accordingly, a thickness **t4** of the matching layer **108** of the invention may be uniform, wherein the thickness **t4** of the matching layer **108** is corresponding to the first transmitting frequency, two times the first transmitting frequency (i.e. the receiving frequency), and four times the first transmitting frequency (i.e. the second transmitting frequency), i.e. equal to  $\frac{1}{4}$  wavelength of the first transmitting frequency,  $\frac{1}{8}$  wavelength of the receiving frequency and  $\frac{1}{16}$  wavelength of the second transmitting frequency. In practical system design, the first transmitting frequency of the first transmitting unit **102** may be selected within a bandwidth range of 2-5 MHz with a center frequency of 3 MHz, the receiving frequency of the receiving unit **106** may receive a transmitting signal within bandwidth range of 3-9 MHz with a center frequency of 6 MHz, and the second transmitting frequency of the second transmitting unit **104** may be selected within a bandwidth range of 6-18 MHz with a center frequency of 12 MHz. However, the invention is not limited to the aforesaid embodiments.

It should be noted that if the relationship between the first transmitting frequency of the first transmitting unit **102**, the receiving frequency of the receiving unit **106** and the second transmitting frequency of the second transmitting unit **104** is not a multiple of 2, the thickness of the matching layer **108** may be various, so as to be corresponding to the first transmitting frequency of the first transmitting unit **102**, the receiving frequency of the receiving unit **106** and the second transmitting frequency of the second transmitting unit **104**.

When the ultrasound system **1** of the invention is used to perform ultrasound scanning, the pulser **14** is used for triggering the first transmitting unit **102** and the second transmitting unit **104** to selectively transmit the first push beam and the second push beam and the receiving unit **106** is used for selectively receiving a reflective wave (i.e. shear wave) of the first push beam and the second push beam.

For example, when a doctor wants to use the ultrasound system **1** of the invention to scan a tissue of liver, breast or the like, he/she can operate the pulser **14** to trigger the first transmitting unit **102** to transmit a first push beam with a first frequency (e.g. 3 MHz, low frequency) and then the receiving unit **106** receives a reflective wave of the first push beam.

At this time, the pulser **14** will trigger the receiver **12** to receive the reflective wave of the first push beam from the receiving unit **106**. Then, a backend control circuit (not shown) processes the reflective wave of the first push beam and generates an image. Similarly, when the doctor wants to use the ultrasound system **1** of the invention to scan a tissue of a small area, he/she can operate the pulser **14** to trigger the second transmitting unit **104** to transmit a second push beam with a second frequency (e.g. 12 MHz, high frequency) and then the receiving unit **106** receives a reflective wave of the second push beam. At this time, the pulser **14** will trigger the receiver **12** to receive the reflective wave of the second push beam from the receiving unit **106**. Then, the

backend control circuit (not shown) processes the reflective wave of the second push beam and generates an image.

As mentioned in the above, the invention integrates the two transmitting units and the receiving unit into the ultrasound probe, wherein the two transmitting units can transmit two push beams with different frequencies. Accordingly, the ultrasound probe of the invention can selectively transmit a push beam with low frequency to scan a tissue of liver, breast or the like or transmit a push beam with high frequency to scan a tissue of a small area. In other words, the ultrasound probe of the invention can perform ultrasound scanning for tissues located at different distances. Therefore, the invention is very convenient in use.

Those skilled in the art will readily observe that numerous modifications and alterations of the device and method may be made while retaining the teachings of the invention. Accordingly, the above disclosure should be construed as limited only by the metes and bounds of the appended claims.

What is claimed is:

1. An ultrasound probe comprising:

- a casing;
- a first transmitting unit for transmitting a first push beam, the first push beam having a first transmitting frequency;
- a second transmitting unit for transmitting a second push beam, the second push beam having a second transmitting frequency, the first transmitting frequency being different from the second transmitting frequency;
- a receiving unit having a receiving frequency, the receiving unit being used for selectively receiving a reflective wave of the first push beam and the second push beam, the receiving frequency being covered with the first transmitting frequency and the second transmitting frequency, the receiving unit, the first transmitting unit and the second transmitting unit being disposed in the casing side by side; and
- a matching layer disposed on the receiving unit, the first transmitting unit and the second transmitting unit; wherein the receiving frequency is two times the first transmitting frequency and the second transmitting frequency is four times the first transmitting frequency, such that a thickness of the receiving unit is  $\frac{1}{2}$  times a thickness of the first transmitting unit, a thickness of the second transmitting unit is  $\frac{1}{4}$  times the thickness of the first transmitting unit, and a thickness of the matching layer is uniform.

2. The ultrasound probe of claim 1, wherein the first transmitting unit and the second transmitting unit are located at opposite sides of the receiving unit.

3. The ultrasound probe of claim 1, wherein a thickness of the receiving unit is between a thickness of the first transmitting unit and a thickness of the second transmitting unit.

4. The ultrasound probe of claim 1, wherein the receiving unit, the first transmitting unit and the second transmitting unit are made of a piezoelectric material.

5. The ultrasound probe of claim 1, wherein the receiving unit essentially consists of a plurality of channels.

6. The ultrasound probe of claim 1, further comprising a backing layer, the backing layer and the matching layer

being disposed at opposite sides of the receiving unit, the first transmitting unit and the second transmitting unit.

7. The ultrasound probe of claim 1, further comprising a lens disposed on the matching layer.

8. An ultrasound system comprising:

- an ultrasound probe comprising:
  - a casing;
  - a first transmitting unit for transmitting a first push beam, the first push beam having a first transmitting frequency;
  - a second transmitting unit for transmitting a second push beam, the second push beam having a second transmitting frequency, the first transmitting frequency being different from the second transmitting frequency;
  - a receiving unit having a receiving frequency, the receiving frequency being covered with the first transmitting frequency and the second transmitting frequency, the receiving unit, the first transmitting unit and the second transmitting unit being disposed in the casing side by side; and
  - a matching layer disposed on the receiving unit, the first transmitting unit and the second transmitting unit; wherein the receiving frequency is two times the first transmitting frequency and the second transmitting frequency is four times the first transmitting frequency, such that a thickness of the receiving unit is  $\frac{1}{2}$  times a thickness of the first transmitting unit, a thickness of the second transmitting unit is  $\frac{1}{4}$  times the thickness of the first transmitting unit, and a thickness of the matching layer is uniform;
  - a receiver electrically connected to the receiving unit; and
  - a pulser electrically connected to the first transmitting unit, the second transmitting unit and the receiver, the pulser being used for triggering the first transmitting unit and the second transmitting unit to selectively transmit the first push beam and the second push beam.

9. The ultrasound system of claim 8, wherein the first transmitting unit and the second transmitting unit are located at opposite sides of the receiving unit.

10. The ultrasound system of claim 8, wherein a thickness of the receiving unit is between a thickness of the first transmitting unit and a thickness of the second transmitting unit.

11. The ultrasound system of claim 8, wherein the receiving unit, the first transmitting unit and the second transmitting unit are made of a piezoelectric material.

12. The ultrasound system of claim 8, wherein the receiving unit essentially consists of a plurality of channels.

13. The ultrasound system of claim 8, wherein the ultrasound probe further comprises a backing layer, and the backing layer and the matching layer are disposed at opposite sides of the receiving unit, the first transmitting unit and the second transmitting unit.

14. The ultrasound system of claim 8, wherein the ultrasound probe further comprises a lens disposed on the matching layer.

\* \* \* \* \*

专利名称(译)	超声探头和超声系统		
公开(公告)号	<a href="#">US10459072</a>	公开(公告)日	2019-10-29
申请号	US15/379510	申请日	2016-12-15
[标]申请(专利权)人(译)	佳世达苏州OPTRONICS 明基电通股份有限公司		
申请(专利权)人(译)	佳世达OPTRONICS ( 苏州 ) 有限公司. 佳世达科技股份有限公司		
当前申请(专利权)人(译)	佳世达科技 ( 苏州 ) 有限公司. 佳世达科技股份有限公司		
[标]发明人	LIU JIAN HUNG		
发明人	LIU, JIAN-HUNG		
IPC分类号	G01S7/52 G01N29/04 A61B8/00 A61B8/14 G01S15/89 G01N29/34 G01N29/22		
CPC分类号	G01S7/5202 A61B8/4483 G01N29/348 G01S7/52079 G01N29/043 G01S7/52022 A61B8/4444 A61B8/14 G01S7/52042 G01S15/8913 G01S15/8952 G01N29/221 G01S15/8915 A61B8/4281 G01N2291/104 A61B8/0825 A61B8/0833 A61B8/54		
优先权	201610363265.7 2016-05-27 CN		
其他公开文献	US20170343657A1		
外部链接	<a href="#">Espacenet</a>		

摘要(译)

超声探头包括壳体，第一发送单元，第二发送单元和接收单元。第一发射单元用于发射第一推杆，第一推杆具有第一发射频率。第二发射单元用于发射第二推力梁，第二推力梁具有第二发射频率。接收单元具有接收频率，并用于选择性地接收第一推力光束和第二推力光束的反射波，其中，接收频率被第一发射频率和第二发射频率覆盖。接收单元，第一发送单元和第二发送单元并排设置在壳体中。

