



US008278114B2

(12) **United States Patent**
Gambini et al.

(10) **Patent No.:** **US 8,278,114 B2**
(45) **Date of Patent:** ***Oct. 2, 2012**

(54) **METHOD FOR MEASURING
LUMINESCENCE AT A LUMINESCENCE
DETECTION WORKSTATION**

(75) Inventors: **Michael Gambini**, Bolton, MA (US); **Jeff Levi**, Trumbull, CT (US); **John Voyta**, Sudbury, MA (US); **John Atwood**, West Redding, CT (US); **Susan Atwood-Stone**, legal representative, Charlotte, VT (US); **Bruce De Simas**, Danville, CA (US); **Edward Lakatos**, Croton On Hudson, NY (US); **Israel Metal**, Flushing, NY (US); **George Sabak**, Monroe, CT (US); **Yongdong Wang**, Wilton, CT (US)

(73) Assignee: **Applied Biosystems, LLC**, Carlsbad, CA (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

This patent is subject to a terminal disclaimer.

(21) Appl. No.: **12/716,219**

(22) Filed: **Mar. 2, 2010**

(65) **Prior Publication Data**

US 2010/0248387 A1 Sep. 30, 2010

Related U.S. Application Data

(60) Division of application No. 11/251,873, filed on Oct. 18, 2005, now Pat. No. 7,670,848, which is a division of application No. 10/323,669, filed on Dec. 20, 2002, now abandoned, which is a continuation of application No. 09/621,961, filed on Jul. 21, 2000, now Pat. No. 6,518,068.

(60) Provisional application No. 60/144,891, filed on Jul. 21, 1999.

(51) **Int. Cl.**
G01N 21/76 (2006.01)
G01T 1/10 (2006.01)

(52) **U.S. Cl.** **436/172**; 250/361 C; 250/361 R; 250/363.1; 250/368; 356/222; 356/435; 422/52; 422/65; 422/67; 422/82.08; 436/50; 702/19; 702/25

(58) **Field of Classification Search** 250/332.361 C, 250/361 R, 362, 368, 486.1, 559.08, 363.1; 356/222, 435; 422/52, 63-65, 67, 73, 82.08-82.09; 435/287.2-287.3, 288.4; 436/43, 47, 50, 436/172

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,264,474 A * 8/1966 Heiss 250/429
(Continued)

FOREIGN PATENT DOCUMENTS

CA 2157755 * 3/1997
(Continued)

OTHER PUBLICATIONS

Oldenburg, K. R. et al, Journal of Biomolecular Screening 1998, 3, 55-62.*



(Continued)

Primary Examiner — Arlen Soderquist

(57) **ABSTRACT**

A luminescence detecting apparatus and method for analyzing luminescent samples is disclosed. A detecting apparatus may be configured so that light from luminescent samples pass through a collimator, a first lens, a filter, and a camera lens, whereupon an image is created by the optics on the charge-coupled device (CCD) camera. The detecting apparatus may further include central processing control of all operations, multiple wavelength filter wheel, and/or a robot for handling of samples and reagents.

38 Claims, 11 Drawing Sheets



U.S. PATENT DOCUMENTS

3,628,028	A *	12/1971	Thorsheim	250/576
4,004,150	A *	1/1977	Natelson	250/328
4,099,920	A *	7/1978	Heiss	422/52
4,126,783	A *	11/1978	Lanza et al.	250/336.2
4,307,294	A *	12/1981	Campbell	250/201.7
4,320,841	A *	3/1982	Gordon et al.	209/552
4,366,118	A *	12/1982	Bunce et al.	422/57
4,521,689	A *	6/1985	Pritzkow	250/385.1
4,597,096	A *	6/1986	Larsson	378/149
4,772,453	A *	9/1988	Lisenbee	422/52
4,949,079	A *	8/1990	Loebner	345/180
4,968,148	A *	11/1990	Chow et al.	356/427
5,234,665	A *	8/1993	Ohta et al.	422/73
5,315,375	A *	5/1994	Allen	356/417
5,329,353	A *	7/1994	Ichimura et al.	356/328
5,329,461	A *	7/1994	Allen et al.	702/26
5,611,994	A *	3/1997	Bailey et al.	422/52
5,656,493	A *	8/1997	Mullis et al.	
5,657,118	A *	8/1997	Lee	356/246
5,674,698	A *	10/1997	Zarling et al.	
5,751,444	A *	5/1998	Ward	358/471
5,766,875	A *	6/1998	Hafeman et al.	435/29
5,854,684	A *	12/1998	Stabile et al.	356/440
5,939,024	A *	8/1999	Robertson	422/534
5,961,926	A *	10/1999	Kolb et al.	422/534
6,057,163	A *	5/2000	McMillan	436/172
6,198,577	B1 *	3/2001	Kedar et al.	359/663
6,301,005	B1 *	10/2001	Epstein et al.	356/124
6,345,115	B1 *	2/2002	Ramm et al.	382/133
6,441,973	B1 *	8/2002	Ramm et al.	359/778
6,518,068	B1 *	2/2003	Gambini et al.	436/50
6,602,657	B1 *	8/2003	Bronstein et al.	
6,686,582	B1 *	2/2004	Volcker et al.	250/216
7,289,217	B2 *	10/2007	Boege et al.	356/417
7,295,316	B2 *	11/2007	Boege et al.	356/417
7,387,891	B2 *	6/2008	Boege et al.	
7,435,602	B2 *	10/2008	Gunstream et al.	436/172
7,670,848	B2 *	3/2010	Gambini et al.	436/172

FOREIGN PATENT DOCUMENTS

DE	19748211	5/1999
EP	25350	* 3/1981
EP	640828	* 3/1995

WO	90/02326	* 3/1990
WO	WO99/23474	5/1999
WO	WO99/60381	11/1999
WO	WO00/22417	4/2000

OTHER PUBLICATIONS

- Aldridge P. K. *Journal of Liquid Chromatography* vol. 13, 1990, 2829-2839.
- Duller, G. A. *Radiation Measurements*, vol. 27 1997, 91-99.
- Feofanov, A., A new confocal stigmatic spectrometer for micro-Raman and microfluorescence spectral imaging analysis: Design and applications, *Review of Scientific Instruments*, 1995, 66, 3146-3158.
- Fowler, A., A Multi-Modality Assay Platform for Ultra-High Throughput Screening, *Current Pharmaceutical Biotechnology*, vol. 1, 2000, 265-281.
- Groebe D. R. *SPIE* vol. 3603, 1999, 297-306.
- Hooper, C. E. *Journal of Bioluminescence and Chemiluminescence* vol. 5, 1990, 123-130.
- Hooper, C. E. *Journal of Bioluminescence and Chemiluminescence* vol. 9, 1994, 113-122.
- Jansen, E. H. *Journal of Bioluminescence and Chemiluminescence* vol. 3, 1989, 53-57.
- Karger, A., *SPIE* vol. 1206, 1990, 78-89.
- Leaback, D. H. *Journal of Bioluminescence and Chemiluminescence* vol. 4, 1989, 512-522.
- Maly, F. E., A Single-Proton Imaging System for the Simultaneous Quantitation of Luminescent Emissions from Multiple Samples, *Analytical Biochemistry* 168, 1988, 462-469.
- Maly F. E. *Journal of Immunological Methods* vol. 122, 1989, 91-96.
- Martin C. S. *Journal of Bioluminescence and Chemiluminescence* vol. 9, 1994, 145-153.
- Nicholas, J. C. *Journal of Bioluminescence and Chemiluminescence* vol. 9, 1994, 139-144.
- Porakishvili, N. *Journal of Immunological Methods* vol. 1, 2000, 265-281.
- Roda A. *Analytical Biochemistry* vol. 257, 1998, 53-62.
- Sadler D. A. *Journal of Analytical Atomic Spectrometry* vol. 10, 1995, 253-257.

* cited by examiner




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6

FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14




FIG. 15

METHOD FOR MEASURING LUMINESCENCE AT A LUMINESCENCE DETECTION WORKSTATION

This application is a divisional application of U.S. application Ser. No. 11/251,873 filed on Oct. 18, 2005, now U.S. Pat. No. 7,670,848, which is a divisional application of U.S. application Ser. No. 10/323,669 filed on Dec. 20, 2002, now abandoned, which is a continuation of U.S. application Ser. No. 09/621,961 filed on Jul. 21, 2000, now U.S. Pat. No. 6,518,068, which claims priority from provisional application 60/144,891 filed on Jul. 21, 1999, the entire contents of each of which applications are hereby incorporated by reference in their entirety as if fully set forth herein.

BACKGROUND OF THE INVENTION

1. Field of the Invention

This invention relates to the field of apparatus and methods for detecting and quantifying light emissions, and more particularly, to detecting and quantifying light emitted from luminescent-based assays. Still more particularly, this invention pertains to apparatus and methods for detecting and quantifying luminescence such as bioluminescence and/or chemiluminescence from luminescent assays as an indicator of the presence or amount of a target compound. Preferred embodiments of the invention include as an imaging device a charge coupled device (CCD) camera and a computer for analyzing data collected by the imaging device. Further preferred embodiments include the capacity for use in high throughput screening (HTS) applications, and provide for robot handling of assay plates.

2. Description of the Related Art

The analysis of the luminescence of a substance, and specifically the analysis of either bioluminescence (BL) or chemiluminescence (CL), is becoming an increasingly useful method of making quantitative determinations of a variety of luminescent analytes.

Recently, methods have been introduced that utilize luminescence detection for quantitatively analyzing analytes in an immunoassay protocol. Such luminescence immunoassays (LIA) offer the potential of combining the reaction specificity of immunospecific antibodies or hybridizing nucleic acid sequences and similar specific ligands with the high sensitivity available through light detection. Traditionally, radioactive reagents have been used for such purposes, and the specificity and sensitivity of LIA reagents is generally comparable to those employing traditional radiolabelling. However, LIA is the preferred analytical method for many applications, owing to the nontoxic nature of LIA reagents and the longer shelf lives of LIA reagents relative to radioactive reagents.

Among other luminescent reagents, chemiluminescent compounds such as 1,2-dioxetanes, developed by Tropix, Inc. and other stable chemiluminescent molecules, such as xanthan esters and the like, are in commercial use. These compounds are triggered to release light through decomposition triggered by an agent, frequently an enzyme such as alkaline phosphatase, which is present only in the presence, or specific absence, of the target compound. The detection of light emission is a qualitative indication, and the amount of light emitted can be quantified as an indicator of the amount of triggering agent, and therefore target compound, present. Other well known luminescent compounds can be used as well.

Luminescent release may sometimes be enhanced by the presence of an enhancement agent that amplifies or increases the amount of light released. This can be achieved by using agents which sequester the luminescent reagents in a

microenvironment which reduces suppression of light emission. Much biological work is done, perforce, in aqueous media. Water typically suppresses light emission. By providing compounds, such as water soluble polymeric onium salts (ammonium, phosphonium, sulfonium, etc.) small regions where water is excluded that may sequester the light emitting compound may be provided.

The majority of instrumentation used to monitor light emitting reactions (luminometers) use one or more photomultiplier tubes (PMTs) to detect the photons emitted. These are designed to detect light at the low light levels associated with luminescent reactions. The rate at which a PMT based microplate luminometer can measure signal from all wells of the plate is limited by the number of PMTs used. Most microplate luminometers have only one PMT so a 384 well plate requires four times longer than is required to read a 96-well plate.

The nature of biological research dictates that numerous samples be assayed concurrently, e.g., for reaction of a chemiluminescent substrate with an enzyme. This is particularly true in gene screening and drug discovery, where thousands of samples varying by concentration, composition, media, etc. must be tested. This requires that multiple samples be reacted simultaneously, and screened for luminescence. However, there is a need for high speed processing, as the chemiluminescence or bioluminescence may diminish with time. Simultaneously screening multiple samples results in improved data collection times, which subsequently permits faster data analysis, and contingent improved reliability of the analyzed data.

In order for each specific sample analyte's luminescence to be analyzed with the desired degree of accuracy, the light emission from each sample must be isolated from the samples being analyzed concurrently. In such circumstances, stray light from external light sources or adjacent samples, even when those light levels are low, can be problematic. Conventional assays, particularly those employing high throughput screening (HTS) use microplates, plastic trays provided with multiple wells, as separate reaction chambers to accommodate the many samples to be tested. Plates currently in use include 96- and 384-well plates. In response to the increasing demand for HTS speed and miniaturization, plates having 1,536 wells are being introduced. An especially difficult impediment to accurate luminescence analysis is the inadvertent detection of light in sample wells adjacent to wells with high signal intensity. This phenomenon of light measurement interference by adjacent samples is termed 'crosstalk' and can lead to assignment of erroneous values to samples in the adjacent wells if the signal in those wells is actually weak.

Some previously proposed luminometers include those described in U.S. Pat. Nos. 4,772,453; 4,366,118; and European Patent No. EP 0025350. U.S. Pat. No. 4,772,453 describes a luminometer having a fixed photodetector positioned above a platform carrying a plurality of sample cells. Each cell is positioned in turn under an aperture through which light from the sample is directed to the photodetector. U.S. Pat. No. 4,366,118 describes a luminometer in which light emitted from a linear array of samples is detected laterally instead of above the sample. Finally, EP 0025350 describes a luminometer in which light emitted through the bottom of a sample well is detected by a movable photodetector array positioned underneath the wells.

Further refinements of luminometers have been proposed in which a liquid injection system for initiating the luminescence reaction just prior to detection is employed, as disclosed in EP 0025350. Also, a temperature control mechanism has been proposed for use in a luminometer in U.S. Pat.

No. 4,099,920. Control of the temperature of luminescent samples may be important, for example, when it is desired to incubate the samples at an elevated temperature.

A variety of light detection systems for HTS applications are available in the market. These include the LEADseeker™ from Amersham/Pharmacia, the ViewLux™ offered by PerkinElmer and CLIPR™ from Molecular Devices. These devices are all expensive, large dimensioned (floorbased models), exhibit only limited compatibility with robotic devices for plate preparation and loading, have a limited dynamic range, and/or use optical detection methods which do not reduce, or account for, crosstalk. The optical systems used are typically complex telecentric glass lens systems, which may provide a distorted view of wells at the edges of the plates, and the systems are frequently expensive, costing in excess of \$200,000.00. Perhaps the most popular detection apparatus is the TopCount™, a PMT-based detection system from Packard. Although the TopCount™ device has a desirable dynamic range, it is not capable of reading 1,536 well plates, and it does not image the whole plate simultaneously.

Crosstalk from adjacent samples remains a significant obstacle to the development of improved luminescence analysis in imaging-based systems. This can be appreciated as a phenomenon of simple optics, where luminescent samples produce stray light which can interfere with the light from adjacent samples. Furthermore, the development of luminometers capable of detecting and analyzing samples with extremely low light levels are particularly vulnerable to crosstalk interference.

SUMMARY OF THE INVENTION

In order to meet the above-identified needs that are unsatisfied by the prior art, it is a principal object and purpose of the present invention to provide a luminescence detecting apparatus that will permit the analysis of luminescent samples. It is a further object of the present invention to provide a luminescence detecting apparatus capable of simultaneously analyzing a large number of luminescent samples. In a preferred embodiment of the present invention, a luminescence detecting apparatus is provided that simultaneously analyzes multiple samples held in wells, where the well plates contain as many as 1,536 wells. The present invention further includes robot handling of the multiple well trays during analysis.

It is yet another object of the present invention to provide a luminescence detecting apparatus capable of analyzing low light level luminescent samples, while minimizing crosstalk from adjacent samples, including and especially minimizing crosstalk from adjacent samples with higher light level output than the sample to be analyzed.

The apparatus of this invention employs a Fresnel lens arrangement, with a vertical collimator above the well plate, with dimensions to match the number of wells. Thus, a 1,536-well plate will employ a dark collimator above the plate with 1,536 cells in registry with the wells of the plate. Fixed above the collimator is a Fresnel lens, which refracts the light such that the view above the lens appears to be looking straight down into each well, regardless of its position on the plate, even at the edges.

Above the Fresnel lens is a CCD camera arranged so as to take the image of the entire plate at one time, viewing through a 35 mm wide angle lens, to give whole plate imaging on a rapid basis. Between the CCD and Fresnel/collimator is a filter, typically arrayed on a filter wheel, disposed at an angle to the lens. The filter is selected to permit the passage of the specific wavelength of the light emitted, and reflect or absorb all others. Several filters may be provided on the wheel, to

permit sequential detection of light emitted from multiple reagents emitting light at different wavelengths.

The samples are fed to the optical detection platform through a loading device designed to work well with robotic and automated preparation systems. The well-plate, with reaction mixture already provided, is placed on a shuttle by a human, or preferably, robot. Alignment of the plate on the shuttle may be relatively coarse, notwithstanding the requirement for tight tolerances to match the collimator grid array. As the shuttle leaves the loading position, a resilient means urges the plate into strict conformal alignment. The shuttle positions the plate under an overhead injection bar, which may accommodate up to sixteen wells in a column at one time. If not previously added, a triggering agent or luminescent reagent is added to the sample wells, and the plate indexes forward to load the next column of wells across the plate. The shuttle then advances through a door into the sample chamber, and the plate is aligned with the collimator and the Fresnel lens. Since many reactions proceed better, or only, at elevated temperatures, the sample chamber is insulated, and provided with heating means, for heating the air in or provided to the chamber. In order to maintain temperature in the chamber close to room temperature and to accurately control temperature, the chamber may also be provided with a heat exchanger.

The light emission from the entire multiple well plate is imaged at once, with subsequent imaging through a different filter if multiple wavelengths are employed. The signal obtained is processed to further reduce crosstalk reduced by the collimator and the presence and amount of luminescence is quickly detected and calculated by a personal computer using automated software. Data is then reported as intensity per well or further analyzed relative to specific assay standards.

BRIEF DESCRIPTION OF THE DRAWINGS

A more complete appreciation of the invention and many of the attendant advantages thereof will be readily obtained as the same becomes better understood by reference to the following detailed description when considered in connection with the accompanying drawings, wherein:

FIG. 1 is a cross section of a preferred embodiment of a luminescence detecting apparatus according to the present invention;

FIG. 2 is a detailed cross section of the optics of a luminescence detecting apparatus according to the present invention.

FIG. 3 is a cross-sectional view of the plate transport system of the invention.

FIG. 4 is a perspective illustration of the injector arm assembly of the invention.

FIG. 5 is an exploded view of the filter wheel assembly.

FIG. 6 is a cross-sectional view of the optical housing.

FIG. 6A is a plan view of a robotic mechanism of the invention.

FIG. 7 is a flow chart illustration of the processing method of the invention.

FIGS. 8-15 are illustrations of the results obtained using the invention in Examples 1-10, respectively.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Referring now to the drawings, wherein like reference numerals designate identical or corresponding parts throughout the several views, and more particularly to FIG. 1 thereof,

a preferred embodiment of the luminescence detecting apparatus of the present invention uses a shuttle or tray to carry a micro plate (plate) **10** comprising a plurality of sample wells **20** which may in the preferred embodiment number as many as 1,536 or more. Persons of ordinary skill in the relevant art will recognize that the number of sample wells **20** is limited only by the physical dimensions and optical characteristics of the luminometer elements, and not by the technology of the present invention. The sample wells **20** may be filled with analyte manually, or robotically prior to delivery to the inventive apparatus. Agents necessary for chemiluminescence may be filled automatically via the injector **30**, to which analyte is supplied through an array of supply tubes **40** or prior to placing the plate on the tray. Typically, the sample wells will contain chemiluminescent reagents. These reagents emit light at intensities proportional to the concentration of analyte in the sample. This light can be very low intensity and requires an instrument with sufficient sensitivity to achieve the desired detection limits.

The operation of injector **30** is controlled by central processor **50**, which in the preferred embodiment may control the operation of all elements of the luminometer of the present invention. Data collection, analysis and presentation may also be controlled by processor **50**. Further in a preferred embodiment of the present invention, the injector **30** may also be used to add buffer solutions to the analytes and also to add reagents that enable "glow" and/or "flash" luminescence imaging, that is sustained or brief, intense emission, respectively, all under control of central processor **50**.

After the analytes are placed in the sample wells **20**, plate **10** is placed in sample chamber **55**, which is located in optical chamber **60** at a fixed focal distance from and directly under the charge-coupled device (CCD) camera **70**, in order to permit the CCD camera to image the luminescent sample accurately. The sample chamber **55** is preferably capable of precise temperature control, as many luminescent reagents and specific luminescent reactions are temperature dependent. Temperature control is provided by central processor **50**, which can vary the temperature for each individual sample plate **10**, as central processor **50** controls the movement and injection of the sample wells **20** in each sample tray **10**. In a preferred embodiment of the luminometer of the present invention, central processor **50** also controls an industrial robot (not shown) which performs the activities involving analyte handling in the luminometer of the present invention.

With the plate **10** placed in the sample chamber **55**, the optics **80** deliver the image of the complete microplate **10** as a single image to the CCD camera **70**.

Although the operation of the luminometer of this invention is an integral, continuous practice, and all elements of the luminometer cooperate together to provide precise, accurate and reliable data, the invention may be more easily understood by reference to three separate, integrated systems, the optics system, the mechanical system and the processing system. Each is discussed in turn, with a discussion of examples of the operation as a whole to follow.

Optics System

Turning now to FIG. 2, the optics **80** are shown in further detail. Luminescent emission **100** from the analyte in plate well **20** located in the plate **10** travels first through dark collimator **110**, which permits only parallel and semi-parallel light rays to exit the sample wells **20** for eventual imaging by the CCD camera **70**. The effect of collimation assists with the prevention of stray light from the sample wells **20** and with the elimination of crosstalk between luminescent samples.

The collimator **110** may be sealably engaged, or in close proximity, to the sample tray **10**, to enhance the restriction of stray light from the samples. Each well **10** is in strict registration and alignment with a corresponding grid opening in collimator **110**. From the collimator **110**, the luminescent radiation passes through a Fresnel field lens **120**, which focuses the light toward filter **130**. In a preferred embodiment of the present invention, the collimator **110** and Fresnel field lens **120** are packaged in a cassette that can be changed by the user. Such an equipment change may be necessitated by varying optical characteristics of different analytes and different well distributions in plates.

The use of a Fresnel field lens is preferable to alternative optical devices for several reasons. Initially, improvements in design and materials have capitalized on the superior optical capabilities of the Fresnel lens, while virtually eliminating its once inherent limitations. Today, many Fresnel lenses are made of molded plastic, creating an almost flawless surface with very little scatter light. The elimination of scatter light is an important element of eliminating crosstalk between adjacent samples in the luminometer of the present invention. Furthermore, improved types of plastics commonly employed in the manufacturing of Fresnel lenses and other optical devices have optical qualities equivalent to ground glass lenses.

Using high tech processes such as computer-controlled diamond turning, complex aspheric surfaces can be cut into a long lasting mold for casting Fresnel lenses. In this manner, Fresnel lenses can be manufactured to produce the precise optical imaging effect that is most efficient for a charge coupled device camera, as in the present invention. Also, Fresnel lenses offer an advantage over conventional lenses in that they can be molded flat and very thin. Because of the shape of the Fresnel lens, it can easily be integrated directly into the housing of the luminometer, enhancing the light-tight properties necessary for accurate imaging of low light samples. Furthermore, Fresnel lenses are much less expensive than comparable conventional glass lenses.

As with any other lens, the total beam spread from a Fresnel lens depends on the size of the source in relation to the focal length of the lens. Smaller sources, such as luminescent assay samples, and longer focal lengths produce more compact beams. Since there are practical limitations to minimizing the geometry and dimensions of the optics **80** in the luminometer of the present invention, the use of Fresnel field lens **120** provides the greatest opportunity for fine-tuned optics. The emissions from plate **10** pass through lens **120**, and are refracted such that the image obtained at CCD **70** appears to look directly downward into all wells, even laterally displaced (edge) ones. This feature is typically called "telecentric."

Further in a preferred embodiment of the present invention, the filter **130** may be configured on a wheel, wherein different filter elements may occupy different portions of the wheel, depending on the luminescent characteristics of the sample being analyzed. Filter **130** is preferably inclined at an angle of 20°-30° relative to the CCD, so that stray reflected light is reflected outside the field of view. Specifically, the filter wheel **130** permits the selection of different wavelength ranges, which not only permit high quality imaging, but may be used to separate the emissions of different reagents emitting at different wavelengths. Again, the filter wheel **130** is controlled by central processor **50**, in coordination with central processor **50**'s control of the individual sample wells **20** in the sample plate **10**. In many assays, such as those addressed in U.S. Pat. No. 6,602,657, incorporated by reference herein, multiple luminescent reagents, which emit at

different wavelengths, are employed in a single well. Using multiple filters, each can be imaged in turn, and the true concentration can be calculated from the data set resulting using pre-stored calibration factors. Filter **130** is preferably provided with an infrared (IR) filter operating in conjunction with the selected bandpass, or as an independent element. Applicants have discovered that stray IR radiation, resulting from the plate phosphorescence, resulting in abnormally high backgrounds. An IR filter suppresses this.

From the filter wheel **130**, the sample-emitted light passes through camera lens **140**, which in the preferred embodiment is a large aperture, low distortion, camera lens. Camera lens **140** focuses the image of the sample on the CCD chip **70**. In the preferred embodiment of the present invention, CCD camera **70** is a cooled, low noise, high resolution device. The lens is preferably a 35 mm wide angle lens with a low light level (F 1.4) large aperture character. Magnification of 3-6, preferably about 5.5, is preferred. In preferred embodiments CCD camera **70** is provided with an anti-blooming CCD chip, to enhance dynamic range, which is about 10^5 in the claimed invention, referred to as the NorthStar™ luminometer. Blooming occurs when a single pixel is overloaded with light and its photoelectrons overflow the CCD device well capacity, obliterating surrounding pixels. Further in the preferred embodiment of the luminometer of the present invention, the selected CCD camera includes a liquid cooled thermoelectric (Peltier) device providing cooling of the CCD to approximately -35°C ., and the CCD has 1280×1024 pixels, each of which are $16\text{ }\mu\text{m}$ square, producing a total active area of $20.5\text{ mm} \times 16.4\text{ mm}$. The quantum efficiency averages 15% over the range from 450 nanometers to 800 nm. The output is digitized to 16 bit precision and pixels can be "binned" to reduce electronic noise.

By using the features disclosed herein, the luminometer of the present invention has a spatial resolution capable of providing high quality imaging of high density, sample trays. The noise performance and CCD temperature are designed to provide the desired detection limit.

Mechanics

The mechanical systems of the luminometer workstation of this invention are designed to achieve automated, high throughput precise delivery of microplates in registration with a collimator **110** so as to be read by the CCD Camera **70**. To this end, as shown in FIG. 3, a cross-section of the inventive luminometer shuttle **200** translates from a load position **202**, where plates **10** are loaded on to the shuttle, preferably by a robotic device such as robot arm, and the shuttle **200** then translates towards sample chamber **55**, to read position **203**. Shuttle **200** is caused to translate by a conventional stepper motor (not pictured). As shuttle **200** advances toward sample chamber **55**, it may stop underneath injector **30**. Injector **30** is more fully illustrated below in FIG. 4. Referring still to FIG. 3, injector **30** delivers fluid reagents drawn from reservoir **204**. Syringe pump **205** draws the fluid reagents from reservoir **204**, and pumps the fluid to the injector tubes **40**. Two way valve **206** controls the passage of the fluid drawn by syringe pump **205** from reservoir **204** and pumped by syringe pump **205** to the supply tubes **40**. In actual practice, there are as many injector tubes **40** as injection ports being used, and multiple syringe pumps **205** are also used. As will be shown below in FIG. 4, injector **30** has up to sixteen injection ports **302**. The plates used in conjunction with the luminometer when injection is used are typically prepared with up to sixteen wells in a column. As the shuttle **200** advances plate **10** underneath injector **30**, shuttle **200** stops so that the first column **208** of wells is directly aligned under injector **30**.

Precise amounts of analyte are delivered to the first set of wells, and shuttle **200** indexes forward one column, so as to inject reagent into the second column of wells **210**. This process is repeated until all wells are filled. Thereafter, shuttle **200** advances forward into sample chamber **55** through a hinged door. In the alternative, the door may be a guillotine door or similar type of closing mechanism. The wells of plate **10** are then read in sample chamber **55**. Upon completion of reading, shuttle **200** translates back to load position **202**.

Before shuttle **200** advances to the injection bar, it may be necessary to fully prime the tube with fluid, so as to provide for precise delivery into the plate. Trough **304** swings out from its storage position parallel to the direction of travel of shuttle **200**, shown by an arrow, to a position directly underlying the injector **30**, perpendicular to the direction of travel. Fluid in the injector and tubes **204** are delivered into trough **304**, and removed by suction. Trough **304** then returns to its rest position, parallel to, and away from, the direction of travel of the shuttle **200**, when the shuttle is moved toward the sample chamber **55**. On its return trip to load position **202**, locator **214** on shuttle **200** is engaged by cam **216**. Locator **214** is mounted on a resilient means, such that when engaged by cam **216**, the locator **214** recesses away from plate **10**. This permits removal of plate **10**, and delivery from a robotic arm or other source of a fresh plate **10**, without the requirement of precise location. As shuttle **200** moves away from load **202**, locator **214** is urged forward, firmly locating plate **10** in place. Plate **10** is held against shoulder **217** by the resilient urging of locator **214**.

It is important that each plate be precisely identified, so that results are correlated with the correct test samples. In most HTS laboratories, most microplates are labeled with a unique "bar code." The label is often placed on the surface perpendicular to the plane of the plate itself. To permit precise identification of each plate, a bar code reader **218** is mounted on the luminometer housing generally indicated at **299** and directly above the door **212**, for example on an arm or flange **220**. Bar code reader **218** is focused on a mirror **222** which in turn permits reading directly off the front or leading edge of plate **10** as it approaches on shuttle **200**. Thus, before each plate arrives in the sample chamber, its identity has been precisely recorded in processor **50**, and the results obtained can be correlated therewith. Persons of ordinary skill in the art will recognize that a variety of configurations of alignment and placement of both bar code reader **218** and mirror **222** will result in the desired identification.

As more clearly shown in FIG. 4, injector **30** may be precisely located by operation of actuator wheel **306**, provided with positions corresponding to the total number of wells on the plates being assayed. Similarly, the vertical position, to account for the different thicknesses of the plate, may be controlled by wheel **308**. Given the simple translation movement of shuttle **200**, and the precise locating and identification of each plate carried, rapid cycling of micro-plate test plates into and out of sample chamber **55** can be effected.

As described above in connection with the optics system of the invention, a filter is provided which includes or reflects passage of light other than light falling within the selected wavelength of the luminescent emitter in use. The filter assembly is illustrated in exploded format in FIG. 5. Filter frame **502** is supported by arm **504** which is connected to the hub of the filter wheel **506**. Multiple different filters may be provided on a single wheel. The filter itself, **508**, is securely mounted on the frame and held there by cover **510**, which is secured to frame **502** by grommets, screws or other holding devices **512**. As noted, filter wheel is positioned so as to hold filter **508** in frame **502** at an incline with respect to collimator

110, of about 22° nominally, so as to direct any reflections outside the field of view. Light passes through the filter opening 514, in alignment with camera lens 140 and CCD camera 70. As further noted above, filter 508 preferably includes an infrared block, either as a component of the filter itself, or as a component provided in addition to the filter for the measured light. An IR block is of value to prevent infrared emissions caused by extraneous radiation from altering the image received by the CCD camera.

Optical chamber 60 is more fully illustrated in FIG. 6. As shown, optical chamber 60 is bounded by optical housing 602 in which fits sample housing 604. When a plate 10 is loaded into optical chamber 60, the plate is secured in sample housing 604 which is positioned in registry with collimator 110, over which is provided Fresnel lens 120. While many luminescent assays can be provided at ambient temperatures, some require elevated temperatures. The luminometer of this device is provided with a sample chamber in which the sample housing 604 carries insulation 606 which, in a preferred embodiment is polyurethane foam, and heater element 608 to raise the temperature in the sample chamber 55 above ambient temperature, up to about 42° C.

There is a tendency, even at ambient conditions, for condensation to collect on the surface of the Fresnel lens 120, as a result of moisture coming from the filled wells of plate 10. The defogger 610 directs a stream of air heated just a few degrees, preferably about 2-3° degrees, above ambient conditions, or above the temperature of the chamber if the chamber is above ambient conditions, across the surface of the Fresnel lens 120, effectively preventing condensation. Mounted at the top of the interior of optical chamber 60 is filter motor 611 which drives filter wheel 612, on which may be mounted filters 614 of varying wavelength, for filtering undesirable wavelengths prior to imaging. Of course, a region is provided, indicated at 616, in the optical housing 602 of the optical chamber 60 for light to be directed onto the CCD camera after passing through the filter 614. The dimensions of optical chamber 60 are exaggerated in FIG. 6 to illustrate the relationship between the optical chamber 60 and the filter wheel 612, and defogger 610. In practice, the filter is located inside the optical chamber 60, and outside the sample housing 604 but alternate locations are possible while still achieving the desired function.

In FIG. 6A, a plan view of a novel robotic mechanism 616 is displayed in a preferred embodiment of the present invention, which provides capacity for use in high throughput screening (HTS) applications. Referring to FIG. 6A, the operation is as follows: robot plate stacks 620, 622, 624, 626, and 628 each can be filled with multiple sample plates 10, arranged in a vertical stack. In the preferred embodiment of FIG. 6A, robot plate stack 628 is designated as the discard stack. The remaining robot plate stacks 620, 622, 624, and 626 can be programmed in order of delivery by software controlled by processor 50 (not shown). In order to load or pick plates from any of these stacks, robot arm 630 moves vertically and rotationally to the desired robot plate stack, under control of the software programmed in processor 50.

When commanded by processor 50, transport 200 of the instrument will move the sample plate 10 from load position 202 to the Read position 203, and return it to load position 202 when imaging is complete. In the embodiment of the invention shown in FIG. 6A, the elapsed time between moving the sample plate 10 from load position 202 to the read position 203, and returning it to load position 202 is typically 30-120 seconds, including imaging time.

Staging positions 632 and 634 are located at 45 degree positions relative to the position of robot arm 630. In one

embodiment, while imaging is in process, the robot arm 630 can place a sample plate 10 at staging position 632, in preparation for placing the sample plate 10 in load position 202. When the imaging is complete, the robot can move the read plate from load position 202 to staging position 634, then load the plate from staging position 632 to load position 202, and while the sample plate 10 is being imaged, the robot can move the plate from staging position 634 to the discard stack 628, and place a new sample plate 10 at staging position 632. In practice, the staging positions are at approximately the same level as the load position, so movement is very quick. In the preferred embodiment, the robot arm 630 can do the time consuming moves to any of robot plate stacks 620, 622, 624, and 626 while imaging is going on, rather than in series with imaging.

With the staging positions 632 and 634, the cycle time for a single sample plate 10 is 2 moves from/to staging areas (3 seconds each), plus 2 transport moves IN/OUT to read position 203 (3 seconds each), plus the integration time (image exposure) time (typically 60 seconds), for a total cycle time of 72 seconds. Without using staging positions 632 and 634, the time would be 2 moves to stacks (30 seconds each), plus 2 transports (3 seconds each), plus the integration time (typically 60 seconds) for a total of 126 seconds. As described in the preferred embodiment of the robotic mechanism 616, the use of staging positions 632 and 634 decreases cycle time by 43%.

Processing

As set forth above, the mechanical and optical systems of the luminometer workstation of the invention are designed to provide precise, quantified luminescent values in an HTS environment, taking advantage of the use of a Fresnel lens/collimator assembly to permit single image viewing by the CCD camera, and subsequent analysis. The collimator, the lens and the camera together combine to reduce cross-talk experienced in prior art attempts. The signals obtained are further processed, as illustrated in FIG. 7, through software loaded onto processor 50, or other convenient method, to further refine the values obtained.

Prior to processing image data collected through the integrated mechanical and optical systems of the invention herein described, the integrated processing component of the invention must first control the mechanical alignment of those integrated mechanical and optical systems for reliable data collection. This process is conducted under control of the processor 50. To conduct an alignment test, the luminescence detection of the present invention measures the light emitted from four test sample wells, called hot wells, of a test plate. In a preferred embodiment, the hot wells are located near each corner of the sample tray used for the alignment testing. The adjacent well crosstalk from each of the four hot wells is analyzed, and the values are compared. When the collimator is aligned precisely over the sample well tray, the crosstalk values will be symmetrical for the four hot wells. The software of the present invention flags any errors detected, such as incorrect number of test sample wells, incorrect intensity, or incorrect location. After the detection of no errors or after the correction of detected and flagged errors, the software of the present invention performs a symmetry calculation to determine precise alignment of the sample well tray, collimator, Fresnel lens and CCD camera assembly. In a known embodiment of the invention, known software techniques are employed to perform the symmetry calculation process by performing the following steps:

1. Extract the hot well and vertical and horizontal adjacent well intensities;
2. Calculate the averages of the horizontal and vertical adjacent well intensities separately for each hot well;
3. Calculate the differences between the actual adjacent intensity vs. the average for each of the horizontal and vertical directions;
4. Normalize the differences by the hot well intensity to convert to a percentage intensity value;
5. Find the worst case absolute value of the differences and display that as the overall misalignment;
6. Calculate the average X-direction (horizontal) misalignment by averaging the four adjacent wells to the right (horizontal direction) of the hot wells;
7. Calculate the average Y-direction (vertical) misalignment by averaging the four adjacent wells to the top (vertical direction) of the hot wells;
8. Calculate the rotational misalignment by averaging the left side hot well vertical adjacent wells at the top of the hot wells, and subtracting that from the average of the right side hot well vertical adjacent wells, thereby indicating any tilt in adjacent well values.

In step A, three actual images for each filter/emitter are taken. A_1 is a precursor image, A_2 is the full integration time image, and A_3 is post-cursor image. The precursor and post-cursor images are taken to avoid the problem of pixel saturation and to extend the detection dynamic range. The precursor and post-cursor images refer to reduced integration time images, which should not contain multiple saturated pixels. If more than six pixels of the full integration time image are saturated, the pre- and post-cursor images are averaged together to form the actual data for that well area. In the absence of six pixel saturation, the full integration time image is used.

In order to clearly isolate and read each pixel, in step B, each image is subjected to edge detection and masking, a processing step whereby the edge of each well or corresponding light image is identified, or annotated, to set off and clearly separate each well region of interest, as disclosed in U.S. patent application Ser. No. 09/351,660, incorporated herein by reference. Again, edge detection and masking is performed for each of B_1 , B_2 and B_3 , referring to the precursor, full integration time image and post-cursor images, respectively. The images are then subjected to "outlier" correction, correcting or "shaving" outliers and anomalies. In this process, the pixels within the region of interest are examined to identify "outliers"—those that are in gross disagreement with their neighbors, in terms of light intensity detected, and if the intensity of a given pixel or small pixel area is significantly different than neighboring pixels or pixel areas, then the average of the surrounding pixels or areas is used to replace erroneous data. This can be due to random radiation, such as that caused by cosmic rays. In this process, this type of intensity is corrected.

Subsequently, in step C, each image C_1 , C_2 and C_3 is subjected to dark subtraction, subtracting the dark background, so as to obtain average pixel values within each mask-defined region of interest. The subtraction is done on a well-by-well basis from stored libraries which are updated periodically.

Specifically, the dark subtraction is conducted to correct for the fact that even in the absence of light, CCD cameras can output low level pixel or bin values. This value includes the electronic bias voltage, which is invariant of position and integration time, and the "dark current," which may vary by position, and is proportional to integration time and to the

temperature of the CCD. The CCD may also have faulty pixels that are always high level or saturated regardless of light input.

The processing software of the invention subtracts this background image or data from the real sample well image data in step C. As persons of ordinary skill in the relevant art will recognize, it is known to take a "dark" image immediately before or after a real image, imaging for the same integration time in both cases, and subtracting the "dark" image data from the real image data. In the preferred embodiment of the invention, "dark" image data is collected intermittently, preferably at specific time intervals. The initial "dark" image background data is collected at startup, and then typically at four hour intervals during image processing operations.

Because the background image has an integration time-invariant component and an integration time-variant component, data is collected for each sample well at minimum integration time and at maximum integration time, and a "slope/intercept" line is calculated between the two data points, using known data analysis techniques. This calculation permits data interpolation for any integration time between the minimum and maximum, and also permits data extrapolation for integration times below or beyond the minimum and maximum integration times.

In a preferred embodiment of the invention, a CCD camera is employed that has two separate "dark" current functions, caused by the CCD output amplifier. Operation of the amplifier generates heat and necessarily creates background "dark" image data. In the preferred embodiment, for integration times of less than 10 seconds, the amplifier operates continuously, whereas for integration times of more than 10 seconds, the amplifier remains off until immediately prior to the read operation. The "slope/intercept" line calculated for integration times of more than 10 seconds will then necessarily have a lower slope than a "slope/intercept" line calculated for integration times of less than 10 seconds. In step C, the processing software element allows separate collection and least squares regression for both the 0 to 10 second integration time region a processor 50, the "dark" background image data is stored separately for each individual AOI.

"Dark" current and bias can also vary over time. The processing software element corrects for this effect by comparing the integration time normalized (using the regression line technique described above) "dark reference" pixel values (outside the imaging field-described above), that were taken when the "dark" background images were taken, versus the "dark reference" pixel values taken while real sample well images are being taken. The difference between the values is then subtracted or added, as applicable, as a global number, to the "dark" background data. This corrects for bias drift and also for global CCD temperature drift.

As mentioned, all of the above "dark background" interpolation/subtraction of step C is done on a well by well basis.

At step D, if pixel saturation has occurred such that the average of the pre-cursor and post-cursor image must be used, the image data is multiplied by the reciprocal of the percentage represented by the pre-cursor images (e.g., 3%).

In step E, the well data is corrected for uniformity variations using a calibration file that is the reciprocal of the system response to a perfectly uniform input illumination.

In step F, the cross-talk correction is effected by processing the data as a whole and preparing a final image in much the same fashion as reconstruction of three dimensional images from a two dimensional data array is practiced.

Specifically in a preferred embodiment of step F, the impulse response function (IRF) is collected for all 96 wells

of the 96 well plate type. This is done by filling one particular well in a given plate with a high intensity luminescent source, imaging the plate, and analyzing all of the wells in the plate for their response to the one high intensity well. The IRF is collected for all of the wells individually by repeating the process for every different well location desired for the complete data set. For 384 plate types, 96 sampling areas are selected, and data for the wells in between the selected sampled areas are interpolated in two dimensions. In the preferred embodiment, the 96 sampling areas comprise every second row and every second column, starting at the outside and working toward the center. Because in the 384 well plates the number of rows and columns is even, the two center rows and the two center columns are interpolated. The reflections in a 384 well plate are also modeled, and used to predict and interpolate reflections for the missing input data. Further in the preferred embodiment, all wells are normalized to the well with the highest intensity.

Subsequently in step F, the two-dimensional array of well IRF values for each well are "unfolded" into a one-dimensional column array, and the two-dimensional arrays of IRF values for other wells are added as subsequent columns, as shown in Chart 1 following:

CHART 1

Unfolded Data Into Column 1			
IRF for A1	IRF for B1	IRF for C1	
A1	A1	A1	Etc
B1	B1	B1	
C1	C1	C1	
D1	D1	D1	
E1	E1	E1	
F1	F1	F1	
G1	G1	G1	
H1	H1	H1	
A2	A2	A2	
B2	B2	B2	
C2	C2	C2	
Etc	Etc	Etc	

The unfolded matrix, which has the form of an N×N matrix, where N=the number of wells to be corrected, comprises a full characterization of the instrument crosstalk, including reflection factors. This unfolded matrix is then inverted, using known matrix inversion techniques, and used as a correction to matrix multiply a one-dimensional matrix unfolded from real assay data. This arithmetic process may be shown as matrix algebra:

$$[\text{true source distribution}] \times [\text{system IRF}] = [\text{instrument output}] \text{ solving for } [\text{true source distribution}] \text{ produces}$$

$$[\text{true source distribution}] = \{1/[\text{system IRF}]\} \times [\text{instrument output}]$$

Subsequently, the calculated well intensities resulting from the above processing are calibrated to an absolute parameter of interest, such as the concentration of a known reporter enzyme. This calibration is conducted through a normalization process producing any of a variety of calibration curves, which will be familiar to those of ordinary skill in the relevant art.

In optional step G, the processed image information is subjected to any necessary post adjustment processing, for appropriate correlation with the materials tested. Specifically, in a preferred embodiment, the processing software of the present invention is capable of performing multi-component analysis. The basic problem is to calculate separately the

concentration of a single reagent in a single sample containing other different reagents. Typically, the reagents used with the invention are formulated so as to emit over different, but perhaps overlapping, spectrums. As earlier described with respect to the integrated optical element, the first step of separating the light from multiple reagents is accomplished by optical bandpass filters, which are designed to maximize the sensitivity of the target reagent emission, while minimizing the sensitivity to other non-target reagent emission. In the present embodiment of the invention, there is one optical filter for each target reagent emission spectrum.

Since optical filters are interference devices, their bandpass characteristics vary, dependent on the angle of incidence of the emission to be filtered. The angle of incidence will be unique for each well because each well's specific location is unique relative to the optical filter. Accordingly, all calculations and filter coefficients must be unique per sample well. The multi-component calibration is performed as follows:

Prior to the real multiplexed (multiple reagent) samples, standards containing only a single reagent in each well are imaged and analyzed. These standards will produce a set of coefficients to be used collectively as multi-component coefficients for each optical filter, for each well. For a given optical filter, the target reagent for that filter should produce the highest output. The other reagents may also have spectra in the filter's bandpass, and will produce smaller outputs, which are a measure of the overlap of those nontarget reagent spectra into the filter signal. For example, the filter's output for the target reagent might be 850, and the filter's output for the other 2 reagents might be 100 and 50, respectively. If the 3 reagents were added together in a single well, the total output would be 1000, and the proportions would be 850:100:50. These coefficients are measured for each well location and filter separately, which gives a complete set of coefficients for simultaneous equations. This will allow a solution for any combination of concentrations of reagent in one sample well. Further in the preferred embodiment, these coefficients will also be normalized by the total intensity read in the "total emission" filter, so that the calculation will result in the same intensity as the instrument would measure if only a single reagent was measured by the "total emission" filter. This calculation may be shown as follows for a simple case of blue and green reagents (abbreviated as R in the calculations), and blue and green and total emission filters (abbreviated as F in the calculations):

$$\text{Let } A = (\text{output of the instrument for blue } R \text{ thru the blue } F) / (\text{output of instrument for blue } R \text{ thru total emission } F);$$

$$\text{Let } B = (\text{output of the instrument for green } R \text{ thru the blue } F) / (\text{output of instrument for green } R \text{ thru total emission } F);$$

$$\text{Let } C = (\text{output of the instrument for blue } R \text{ thru the green } F) / (\text{output of instrument for blue } R \text{ thru total emission } F);$$

$$\text{Let } D = (\text{output of the instrument for green } R \text{ thru the green } F) / (\text{output of instrument for green } R \text{ thru total emission } F);$$

These coefficients are measured for each well prior to running a multi-color run.

15

Then for a multi-reagent/color run,

(output of the instrument for the blue F)= $A \times$ (true intensity of blue R)+ $B \times$ (intensity of green R);
and

(output of the instrument for the green F)= $C \times$ (true intensity of blue R)+ $D \times$ (intensity of green R)

These 2 simultaneous equations are then solved for the true intensity of the blue and green reagents by the processing software, under control of processor 50.

Further in step G, the raw output of the instrument for each filter is normalized for integration time before solving the equations.

The resulting intensities could then be calibrated as concentration by use of standards as described in the previous section.

Finally, in step H, the analyzed data is presented in a user-acceptable format, again controlled by processor 50.

The invention may be further understood by reference to examples of assays practiced in HTS format, demonstrating the dynamic range and flexibility of the NorthStar™ luminometer.

EXAMPLES

Example 1

Purified cAMP Quantitation

cAMP standards were serially diluted and added to a 96-well assay plate with alkaline phosphatase conjugated cAMP and anti-cAMP. Plates were processed with the cAMP-Screen™ protocol and imaged for 1 minute on the NorthStar™ 30 minutes after addition of CSPD®/Sapphire-II™. A sensitivity of 0.06 pM of purified cAMP is achieved with cAMP-Screen™ on the NorthStar™ workstation. The results are depicted in FIG. 8.

Example 2

cAMP Induction in Adrenergic β 2 Receptor-Expressing C2 Cells

Adrenergic β 2 Receptor-expressing C2 cells were plated in a 96-well plate (10,000 cells/well) and stimulated with isoproterenol for 10 minutes. cAMP production was quantitated in cell lysates using the cAMP-Screen™ assay. The assay plate was imaged for 1 minute on the NorthStar™, 30 minutes after addition of CSPD®/Sapphire-II™. Increasing cAMP levels were detected on the NorthStar™ from the stimulated adrenergic receptor. The results are depicted in FIG. 9.

Example 3

Luc-Screen™ Reporter Gene Assay in 96-384- and 1,536-Well Format

pCRE-Luc-Transfected cells were seeded in 96-, 384- and 1,536-well plates, incubated for 20 hours with forskolin, and assayed with the Luc-Screen™ system. pCRE-Luc contains the luciferase reporter gene under the control of a cAMP response element (CRE). Forskolin induces intracellular cAMP production through the irreversible activation of adenylyl cyclase. All plate formats demonstrate comparable forskolin-induced cAMP levels. The results are depicted in FIG. 10.

16

Example 4

Forskolin Induction of pCRE-Luc Transfected NIH-3T3 Cells

pCRE-Luc-Transfected cells were seeded in a 96-well plate. Four random wells were induced for 17 hours with 1 mM forskolin and the entire plate was assayed with the Luc-Screen™ system. The results are shown in FIG. 11.

Example 5

Dual-Light® Quantitation of Luciferase & β -Galactosidase Reporter Enzymes

NIH/3T3 cells were co-transfected with pCRE-Luc and p β gal-Control, and seeded into a 96-well microplate (2×10^4 cells/well). Cells were incubated with forskolin for 17 hours. Modified Dual-Light® Buffer A was added to cells and incubated for 10 minutes. Modified Dual Light® Buffer B was injected and luciferase-catalyzed light emission was measured immediately. Thirty minutes later, Accelerator-II was added, and then β -galactosidase-catalyzed light emission was quantitated on the NorthStar™ HTS workstation. Quantitation is shown graphically in FIG. 12.

Example 6

Normalized Fold Induction of Luciferase Reporter

Fold induction of luciferase activity was calculated following normalization to β -galactosidase activity. The Dual-Light® assay enables the use of a control reporter for normalization, or to monitor non-specific effects on gene expression. This is depicted in FIG. 13.

Example 7

Effect of BAPTA-AM on Antagonist Activity

CHO-Aeq-5HT2B cells were loaded with coelenterazine h+/-0.5 μ M BAPTA-AM for 4 hours. The antagonist methysergide was added to the charged cells for 30 minutes. 1 μ M agonist a-Me-5HT was injected, and the emitted light was integrated for 20 seconds on the NorthStar™ system. The reported IC50 for methysergide (0.6 nM) is unchanged in the presence of BAPTA-AM. The data obtained appears in FIG. 14.

Example 8

Effect of BAPTA-AM on Peptide Agonist Stimulated of the Orexin 2 Receptor

CHO-Aeq-OX2-A2 cells (Euroscreen) were loaded with coelenterazine h+/-0.6 μ M BAPTA-AM for 4 hours. The peptide agonist Orexin B was injected into the wells, and the emitted light was integrated for 20 seconds on the NorthStar™. Using this assay on the NorthStar™ system, the reported EC50 for Orexin B (0.75 nM) is unchanged in the presence of BAPTA-AM. This is shown in FIG. 15.

This invention has been described generically, by reference to specific embodiments and by example. Unless so indicated, no embodiment or example is intended to be limiting. Alternatives will occur to those of ordinary skill in the art without the exercise of inventive skill, and within the scope of the claims set forth below.

What is claimed is:

1. A method for analyzing a plurality of luminescent samples in a luminometer, comprising the steps of:
 placing said plurality of luminescent samples in a respective plurality of sample wells;
 placing said plurality of sample wells in a luminometer containing an imaging device;
 positioning a dark collimator comprising a two-dimensional array of openings between said plurality of sample wells and said imaging device;
 registering said dark collimator to each of said plurality of sample wells;
 positioning a first lens between said dark collimator and said imaging device; and
 positioning a second lens between said first lens and said imaging device.

2. The method of claim 1, additionally comprising the step of positioning a filter between said first lens and said second lens.

3. The method of claim 2, wherein said filter includes filter elements of varying wavelength.

4. The method of claim 1, wherein said dark collimator is positioned such that the only light from said luminescent samples received by said imaging device is light from said sample wells only parallel or semi-parallel light rays from said luminescent samples illuminate the imaging device.

5. The method of claim 1, further comprising producing quantified luminescent values by illuminating said imaging device with light from said luminescent samples, wherein said dark collimator is configured such that the only light from said plurality of said luminescent samples received by said imaging device is light from said luminescent samples that is parallel or semi-parallel to an optical axis of said dark collimator.

6. A luminometer for analyzing a plurality of luminescent samples, comprising:

an imaging device;

a plurality of wells, each said well for containing one of said plurality of luminescent samples;

a collimator comprising a two-dimensional array of corresponding openings positioned between said plurality of luminescent samples and said imaging device, said plurality of wells aligned to respective ones of said corresponding array of openings;

a lens positioned between said collimator and said imaging device; and

a camera lens positioned between said lens and said imaging device.

7. The luminometer of claim 6, further comprising a plurality of luminescent samples disposed within respective ones of said plurality of wells, wherein each of said plurality of luminescent samples is one of a bioluminescent material or a chemiluminescent material.

8. The luminometer of claim 6, further comprising a central processing unit for controlling the analysis of said plurality of luminescent samples.

9. The luminometer of claim 6, further comprising an injector for placing liquid reagents in said plurality of wells.

10. The luminometer of claim 9, wherein said injector places a reagent required for luminescence in said plurality of wells.

11. The luminometer of claim 6, further comprising a robot configured to transfer the plurality of wells.

12. The luminometer of claim 6, further comprising a chamber containing said imaging device, said plurality of sample wells, said collimator, said lens, and said camera lens, wherein said chamber is temperature controlled.

13. The luminometer of claim 6, further comprising a filter located between said lens and said imaging device.

14. The luminometer of claim 13, wherein said filter includes filter elements of varying wavelength.

15. The luminometer of claim 6, further comprising a defogger which prevents condensation on said lens.

16. The luminometer of claim 6, wherein said wells are disposed on a plate.

17. The luminometer of claim 16, further comprising a shuttle configured to support and transfer said plate.

18. The luminometer of claim 6, wherein said lens comprises a Fresnel lens.

19. The luminometer of claim 6, wherein said lens comprises an aspheric surface.

20. The luminometer of claim 6, wherein said lens comprises a molded plastic lens.

21. The luminometer of claim 6, wherein said camera lens comprises a single lens.

22. The luminometer of claim 6, wherein said camera lens is configured to focus an image of said plurality of luminescent samples on said imaging device.

23. The luminometer of claim 6, wherein said imaging device comprises a charge coupled device (CCD) chip.

24. The luminometer of claim 6, wherein said imaging device comprises charge coupled device (CCD) camera.

25. The luminometer of claim 6, wherein said collimator is in close proximity to said plurality of wells so as to enhance restriction of stray light from said wells.

26. The luminometer of claim 6, further comprising a heater disposed below said plurality of wells.

27. A luminometer for analyzing a plurality of luminescent samples, comprising:

an imaging device;

a sample housing comprising:

a sample holder configured to receive a plurality of wells containing one or more of a plurality of luminescent samples;

a collimator disposed above said sample holder, said collimator comprising a two-dimensional array of openings;

a first lens disposed between said collimator and said imaging device; and

a second lens disposed between said first lens and said imaging device.

28. The luminometer of claim 27, further comprising a chamber containing one or more of said sample holder, said collimator, said first lens, said second lens, or said imaging device.

29. The luminometer of claim 27, wherein said first lens comprises a lens.

30. The luminometer of claim 27, wherein said first lens comprises a Fresnel lens.

31. The luminometer of claim 27, further comprising a plurality of sample wells aligned to corresponding ones of said array of openings of said collimator.

32. The luminometer of claim 31, wherein said plurality of sample wells are disposed on a plate.

33. The luminometer of claim 27, wherein said collimator is disposed along an optical axis, said array of openings are each disposed along an axis parallel said optical axis, and the only light from said sample wells received by said imaging device is light from said sample wells that is parallel or semi-parallel to said optical axis.

19

34. The luminometer of claim **27**, wherein each well is in registration and alignment with a corresponding opening of the array of openings.

35. The luminometer of claim **27**, wherein said collimator is in close proximity to said plurality of wells so as to enhance restriction of stray light from a plurality of wells received by said sample holder.

36. The luminometer of claim **27**, wherein said sample housing comprises said first lens.

20

37. The luminometer of claim **27**, wherein said sample housing comprises a heater disposed below said sample holder.

38. The luminometer of claim **6**, wherein each well is in registration and alignment with a corresponding opening of the array of openings.

* * * * *

专利名称(译)	在发光检测工作站测量发光的方法		
公开(公告)号	US8278114	公开(公告)日	2012-10-02
申请号	US12/716219	申请日	2010-03-02
[标]申请(专利权)人(译)	生命技术公司		
申请(专利权)人(译)	Life Technologies公司		
当前申请(专利权)人(译)	应用生物系统有限责任公司		
[标]发明人	GAMBINI MICHAEL LEVI JEFF VOYTA JOHN ATWOOD JOHN ATWOOD STONE LEGAL REPRESENTATIVE SUSAN DE SIMAS BRUCE LAKATOS EDWARD METAL ISRAEL SABAK GEORGE WANG YONGDONG		
发明人	GAMBINI, MICHAEL LEVI, JEFF VOYTA, JOHN ATWOOD, JOHN ATWOOD-STONE, LEGAL REPRESENTATIVE, SUSAN DE SIMAS, BRUCE LAKATOS, EDWARD METAL, ISRAEL SABAK, GEORGE WANG, YONGDONG		
IPC分类号	G01N21/76 G01T1/10 G01N33/532 G01N21/15 G01N21/25 G01N21/27 G01N21/31 G01N21/64		
CPC分类号	G01N21/15 G01N21/274 G01N21/276 G01N21/31 G01N21/6452 G01N21/6456 G01N21/76 G01N21/763 G01N33/581 G01N21/6486 Y10T436/115831 G01N2021/6471 G01N2333/90241		
优先权	60/144891 1999-07-21 US		
其他公开文献	US20100248387A1		
外部链接	Espacenet USPTO		

摘要(译)

公开了一种用于分析发光样品的发光检测设备和方。检测装置可以配置成使得来自发光样本的光通过准直器，第一透镜，滤光器和相机镜头，由此通过电荷耦合器件（CCD）相机上的光学器件产生图像。检测设备还可以包括所有操作的中央处理控制，多波长滤光轮和/或用于处理样品和试剂的机器人。

